

BURN-IN TESTING APPARATUS AND METHOD

5

10

FIELD OF THE INVENTION

This invention relates to integrated circuit testing sockets and more particularly to the temperature control of integrated circuits in an integrated circuit testing and/or burn-in socket.

BACKGROUND OF THE INVENTION

15

Integrated circuit (IC) packages must be tested after their manufacture, normally at elevated temperatures, which is typically a burn-in process. During that process, it is often necessary to control the temperature of ICs, sensors, and other elements. Techniques for doing so have been widely practiced for many years. The system normally consists of a heater (or cooler), a temperature sensor, and a comparator which applies energy to a heater in proportion to the difference in voltage measured on the temperature sensor as compared to a reference voltage. The energy is applied in the proper direction to cause the difference voltage to be reduced. Temperature control modules and temperature sensors of many types are widely sold for these purposes. A typical application is the control of the temperature of ICs for a burn-in process because of the temperature sensitivity of the ICs.

20

25

30

To achieve more accurate testing results, it is desirable to control the temperature of each individual IC being tested. Within a testing oven without individual temperature control, the actual temperature of each IC can vary due to different rates of convection, heat dissipation, or radiation within the oven.

Individual temperature control can be achieved by sensing the temperature of each IC and varying the heat directed to each IC through the use of individual heaters.

Two such examples of sensing and heating individual ICs can be found in U.S. Pat. No. 5,164,661 to Jones and U.S. Pat. No. 5,911,897 to Hamilton. Both Jones and Hamilton disclose a testing socket with a sensor in direct contact with an IC that senses the temperature of the IC and a heater also in contact with the IC for affecting a change in the temperature of the IC. However, both Jones and Hamilton disclose separated sensors, heaters and controllers that require wiring to connect each sensor to a controller physically separated from the testing socket. Problems can arise during testing, caused by faulty sensors, wires, heaters or a failure of time-phasing between the controller and the sensor and heater. If any of these faults occur, the tester must check each individual component to discover the faulty component.

As shown in FIG. 10, in Hamilton, a temperature sensor 110 is positioned within an insulated sensor housing 112 such that the sensor 110 protrudes from the housing 112 to contact the integrated circuit being tested. The sensor housing 112 is located in an opening in the heat sink 114.

In both Hamilton and Jones, the temperature sensor directly contacts the integrated circuit when the socket is closed. The direct contact between the temperature sensor can cause damage to the integrated circuit because of the point loading of the relatively small temperature sensor on the integrated circuit when the socket is clamped closed. Damage to the temperature sensor can also be caused by the direct contact of the integrated circuit to the sensor.

Also, both Hamilton and Jones disclose testing sockets utilizing a threaded attachment of the heating and sensor elements to the testing socket.

Thus, it would be advantageous to have a testing socket with the sensor, heater (or cooler), and controller integrated into a single module and it would be advantageous for the testing socket to utilize a quickly releasable means to secure the module against the IC.

SUMMARY OF THE INVENTION

One aspect of the invention is a novel modular unit that may be used for burn-in, testing, and other process procedures of integrated circuit (IC) packages and the like. The modular unit has an arrangement of a heater (or cooler), an IC
5 temperature sensor, and a controller fully contained within the modular unit.

This arrangement can be achieved by embedding a microprocessor controller within a modularized heater/sensor/controller unit. The embedded microprocessor controller acts as the controller, responding to the temperature sensor and driving the heater (or cooler).

10 In another aspect of the invention, the microprocessor controller can utilize an analog-to-digital converter to convert data from the temperature sensor and compare the converted digital data to digital information that represents a selected temperature.

In a further aspect of the invention, the testing socket can include latches
15 on the socket for quickly releasing the heater/sensor/controller unit from the testing socket base.

Another aspect of the invention is a system for testing IC packages including testing sockets on testing boards within a testing chamber, wherein each testing socket has a heater, IC temperature sensor, and controller contained within
20 a modularized unit. The system can include a terminal in communication with the testing boards for inputting a selected temperature for each testing socket.

Another aspect of the invention is a testing board with a matrix of testing socket bases and a top attach plate with a corresponding matrix of self-contained heater/sensor/controller units that connect to corresponding testing
25 socket bases when the top attach plate is secured to the testing board. The units are independently spring-loaded on the top attach plate to allow for warping of the testing board.

Another aspect of the invention is a temperature sensing device located in a heater or cooler that has a temperature sensor positioned within a sensor housing

with the sensor housing contacting the IC package. The sensor and sensor housing are thermally insulated from heater or cooler by a thermal insulator surrounding the sensor housing. The sensor housing provides a short thermal path between the IC package and the sensor.

5 The foregoing and other objects, features, and advantages of the various embodiments of invention will become more readily apparent from the following detailed description of a preferred embodiment of the invention which proceeds with reference to the accompanying drawings.

10 BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is an exploded perspective view of a testing socket and modular sensor/heater/controller unit according to an embodiment of the invention.

FIG. 2 is a perspective view of the testing socket and modular sensor/heater/controller unit of FIG. 1 in a latched position.

15 FIG. 3 is an exploded perspective view of the testing socket of FIG. 1.

FIG. 4 is a perspective view of the modular sensor/heater/controller unit of the testing socket of FIG. 1 showing the heater, sensor and data communication connector.

20 FIG. 5 is a simplified layout elevation view of the testing socket of FIG. 1 including a block diagram of the sensor/heater/controller/communication circuit.

FIG. 6 is a circuit diagram of the sensor/heater/controller unit of the testing socket of FIG. 1.

FIG. 7 is block plan view of a system of multiple testing sockets on Burn-in-Boards in a Burn-in chamber according to another embodiment of the invention.

25 FIG. 8 is a perspective view of multiple testing sockets on a testing board showing multiple sensor/heater/controller units positioned on a single top attach plate according to another embodiment of the invention.

FIG. 9 is to plan view of the bottom side of the top attach plate of FIG. 8.

FIG. 10 is a side elevation view of a prior art integrated circuit testing socket.

FIG. 11 is a perspective view of an integrated circuit testing socket with a temperature sensing device and integrated circuit according to the invention.

5 FIG. 12 is a partial cross-sectional view of a portion of the integrated circuit testing socket of FIG. 10 showing the temperature sensing device positioned in a temperature control block.

FIG. 13 is an exploded perspective view of the temperature sensing arrangement of FIG. 10.

10

DETAILED DESCRIPTION

A. IC PACKAGE TEMPERATURE CONTROLLING DEVICE AND METHOD

15 FIGS. 1 and 2 show perspective views of a testing socket 20 and a modular sensor/heater/controller unit 22 according to an embodiment of the invention. The heater can also be a cooler but hereinafter for simplification will only be referred to as a heater. Springs 24 on latch 26 allow for easy and quick release of the heater unit 22 from the testing socket base 38. FIG. 2 shows the testing socket 20 and modular unit 22 in a closed position where board-side connector 30 located on the testing board 32 receives communication/power connector 34 located on the heater unit 22.

20

FIG. 3 shows an exploded perspective view of the testing socket 20, modular unit 22, and testing board 32. The testing socket 20 utilizes a generic open-top socket 36 that is secured to base 38 and base 38 has alignment pins 41 and two latches 26. The modular unit 22 has a guide plate 40 for aligning the modular unit 22 onto the base 38 and board-side connector 30. Microprocessor controller 42 (shown in FIG. 5) is embedded within the guide plate 40 near the communication/power connector 34 or mounted on a top attach plate 72 (see FIGS. 8-9) as described below. The communication/power connector 34 is located on a bottom surface of the guide plate 40. The heater 44 connects flushly with a bottom

25

surface of heat sink 46 and electrically communicates with the embedded microprocessor controller 42 for signal communication and electrically communicates with the communication/power connector 34 for power. The temperature sensor 48 (see FIG. 4) is positioned within heater 44 and also
5 communicates with the microprocessor controller 42 for signal communication and the communication/power connector 34 for power. The heat sink 46, that has the heater 44 and sensor 48 connected to its bottom surface, attaches to the guide plate 40 with a combination of barrel screws 50 and springs 52. The combination provides a controlled force of the heater 44 and sensor 48 against an IC package 54
10 in open-top socket 36 when the testing socket 20 and modular unit 22 are in a closed position.

FIG. 4 shows a bottom side of the modular sensor/heater/controller unit 22 of FIG. 1. The sensor 48 is located within a cavity in the heater 44 and is electrically connected to the embedded microprocessor controller 42 (not shown)
15 located within the controller casing 58 on guide plate 40. Communication/power connector 34 is located on the controller casing 58 and communicates with the microprocessor controller 42. The heater 44 is flushly connected with the bottom surface of heat sink 46 to provide effective heat transfer between the two through thermal conduction.

FIG. 5 shows a simplified layout elevation view of the testing socket 20 and
20 modular unit 22 of FIG. 1 located on a testing board 32. FIG. 5 includes a simple circuit diagram showing the microprocessor controller 42 in communication with the sensor 48 and the heater 44. The microprocessor controller 42 receives data via the communication/power plug 34 that connects to the board-side socket 30. The
25 heater 44, microprocessor 42, and sensor 48 receive power via the communication/power connector 34. The microprocessor controller 42 is embedded within the modular unit 22. By embedding the microprocessor controller 42 within the modular unit 22, the modular unit 22 acts as a single, modularized sensor/heater/controller unit. This allows for the advantage of testing this system as

a single unit as opposed to testing for faults in each of the components or in the communication links between the components. During testing, if a modular unit 22 fails, the whole unit is simply and quickly replaced with a functioning unit.

FIG. 6 shows a circuit diagram of the modular unit 22. The sensor 48 is shown as a thermistor being supplied with a constant current. The voltage of the thermistor 48 is converted into digital form by Analog-to-Digital (A/D) converter 60 within the microprocessor controller 42. The digital data from the A/D converter 60 is compared to a user-selected temperature expressed in digital form in processor 62. The user-selected temperature is inputted into the processor 62 via the communications portion 64 of the microprocessor controller 42. The communications portion 64 is in communication with the signal lines in the power/communication connector 34. The processor 62 then sends a digital signal to the Digital-to-Analog (D/A) converter 66 within the microprocessor controller 42. An analog signal from the D/A converter 66 is sent to an amplifier coupled to the heater 44 to control the amount of heat being dissipated by the heater 44. Heater 44 can also be a cooler with microprocessor 42 similarly driving the cooler.

FIG. 7 shows a simplified plan view of a system of testing boards 32 within a testing or burn-in chamber 68 according to another embodiment of the invention. A matrix of testing sockets 20 and modular units 22 are located on each testing board 32. The testing boards 32 are in communication with an outside power source and driver electronics 70. The power source and driver 70 communicates with the testing boards 32 preferably by means of an I2C data stream on a data bus which is included in a data/power bus 71. The power source and driver electronics 70 serves as a system controller which allows a user to determine a desired testing temperature for each IC package 54.

A typical testing chamber 68 is a burn-in chamber where air flow 67 from a fan or some other source is maintained across the testing boards 32. The air flow 67 is preferably maintained at a high enough rate to keep the IC packages below the selected temperature prior to application of heat from the individual heaters 44. The

heaters 44 can then more easily maintain an independently selected temperature of each IC package 54.

FIG. 8 shows a perspective view of another embodiment of the invention in which a plurality of modular heaters 44, temperature sensors 48 and heat sinks
5 46 are attached to a single top attach plate 72, preferably arranged in a regular matrix. Each modular unit 22 is individually spring-loaded on the top attach plate 72 to allow for any warping of the testing board 32. The top attach plate 72 is positioned over multiple open-top sockets 36 on a testing board 32.

The top attach plate 72 connects to the testing board 32 with fasteners 74
10 along the edges of the top attach plate 72 and testing board 32. Multiple fasteners 74 are used to secure the top attach plate so as to engage the temperature sensors 48 and heaters 44 with the IC packages 54 located in the open-top sockets 36.

FIG. 9 shows a plan view of the bottom side of the top attach plate 72. Here, the top attach plate 72 is arranged to incorporate the structure of what would
15 be an array of guide plates 40 (See FIG. 3) instead of having discrete guide plates 40. A plurality of heaters 44 and corresponding temperature sensors 48 are arranged in a regular matrix on a plurality of corresponding heat sinks 46. Electronic controllers 42 are electrically connected to the heaters 44 and temperature sensors 48. Power may be supplied to the electronic controllers 42,
20 heaters 44 and temperature sensors 48 through a signal/power bus 71 (see FIG. 7) that connects to the top attach plate 72 or the testing board 32.

This embodiment allows for easy and quick placement and removal of IC packages 54 into and out of the separate testing sockets 20. Rather than
individually securing each modular unit 22 to each open-top socket 36, the top
25 attach plate 72 allows for securing all of the modular units 22 with four corner fasteners 74.

B. IC PACKAGE TEMPERATURE SENSING DEVICE

FIG. 11 shows an integrated circuit temperature sensing device 48 according to an embodiment of the invention in an integrated circuit testing socket

123. Integrated circuits include individual dies and IC packages and the term integrated circuit (IC) used throughout this specification encompasses all forms of integrated circuits. The testing socket 123 can be a socket designed to receive an IC 54 for testing which includes, burning-in, testing and programming of the IC 54.

The IC testing socket 123 includes temperature control block 44 for directly controlling the temperature of the IC 54 during testing. The IC testing socket 123 generally comprises a base 38 connected to a testing board 32 and a lid 144. The preferred form of IC testing socket 123 is described above in further detail. However, particulars of construction of the IC testing socket 123 are not necessary to this embodiment of the present invention and so need not be described further herein. For example, this embodiment of the present invention can be incorporated into other IC testing sockets such as described in U.S Patent No. 5,911,897 to Hamilton and shown in FIG. 10.

The temperature control block 44 is positioned in the lid 144 so that when the IC testing socket 123 is in a closed position, the temperature control block 44 thermally contacts the IC 54. The temperature control block 44 then effects a change in the temperature of the IC 54 by conducting heat to or from the IC 54. Thus, the temperature control block 44 can be a heater or a cooler.

The IC temperature sensing device 48 is shown located within the temperature control block 44 positioned so as to thermally contact the IC 54 when the IC testing socket 123 is in a closed position.

FIG. 12 shows a partial cross-sectional view of the IC testing socket 123 of FIG. 11 showing the IC temperature sensing device 48 positioned within the temperature control block 44. FIG. 13 shows an exploded perspective view of the temperature sensing device 48.

Referring to FIGS. 12 and 13, the IC temperature sensing device 48 includes a temperature sensor 130, such as a thermistor, in electrical communication with devices capable of converting the temperature sensor signals

into useable form. One such device can be a microprocessor controller 42 that acts as a controller, responding to the temperature sensor 130 and driving the temperature control block 44.

5 The temperature sensor 130 is positioned within a cavity 132 of the thermally conductive sensor housing 134. The cavity 132 is shown here as being cylindrical, reflecting the overall shape of the temperature sensing device 48. The cavity 132 has a single opening at a first end of the sensor housing 134 to allow the temperature sensor to be in communication with devices like a microprocessor controller or off-board controller. When the IC testing socket 123 is in a closed position, the sensor housing 134 is in thermal contact with the IC 54. Because the sensor housing 134 is thermally conductive, the sensor housing 134 is able to provide a thermally conductive path between the IC 54 and the temperature sensor 130.

15 The cavity 132 is formed as a blind bore which includes an open first end and a conically shaped termination 136 at a second end of the sensor housing 134. The conically shaped termination 136 has a thickness which allows for a short thermal path for a fast transient response from the IC 54 to the temperature sensor 130. A suitable thickness for producing the short thermal path is 3 mm when the sensor housing 134 is formed of a metal comprising copper or aluminum.

20 A thermal insulator 138 surrounds the sensor housing 134 to thermally isolate the temperature sensor 130 from the temperature control block 44. The second end of the sensor housing 134 is exposed from the thermal insulator 138 to allow the sensor housing 134 to thermally contact the IC 54 when the IC testing socket 123 is in a closed position.

25 The sensor housing 134 provides both a thermally conductive path from the IC 54 to the temperature sensor 130 and protection from impact or problems related to point contact pressures that could occur if the IC 54 directly, physically contacted the temperature sensor 130. The sensor housing 134 protects the temperature sensor 130 by providing a protective layer of material that intervenes

between the IC 54 and the temperature sensor 130. The sensor housing 134 protects the IC 54 from point contact pressures that could be caused by directly contacting a temperature sensor 130 by providing a larger, substantially flatter contact surface area than the small temperature sensor 130 can provide.

5 For the most accurate results in sensing the temperature of an IC 54 during testing, the sensor housing 134 should be formed of a highly conductive metal. Most preferably, the sensor housing 134 is formed of a metal comprising aluminum or copper. Also, to increase accuracy, the thermal insulator 138 should adequately thermally isolate the temperature sensor 130 and sensor housing 134 from the
10 temperature control block 44 so that the temperature sensor 130 is predominantly sensing the temperature of the IC 54 and not the temperature control block 44. To achieve thermal isolation, the thermal insulator 138 is most preferably formed of a polythermide material. Ultem 1000®, manufactured by General Electric, is an example of a preferable polythermide material.

15

C. IC PACKAGE TEMPERATURE SENSING METHOD

A method for sensing the temperature of an IC 54 being tested includes placing the IC 54 in an IC testing socket 123. The temperature of the integrated circuit is changed by thermally contacting a heater or cooler 44 to the integrated
20 circuit. This is chiefly done in the burning-in process for ICs but the temperature of the IC 54 can also be controlled for programming and testing of the IC 54.

The temperature of the IC 54 is then sensed by means of a temperature sensor device 48 contained within the heater or cooler 44. The temperature sensor device 48 senses the temperature of the IC 54 by thermally connecting a
25 temperature sensor 130 to the IC 54 through a conductive material 134 and by thermally isolating the temperature sensor 130 from the heater or cooler 44 with a surrounding insulating material 138 so that the temperature sensor 130 predominantly senses the temperature of the IC 54 and not the heater or cooler 44.

The conductive material 134 spaces the temperature sensor 130 from the IC 54 such that a thermal path between the IC 54 and temperature sensor 130 is maintained to create a fast transient response in the temperature sensor 130.

5 The temperature sensor 130 is thermally isolated from the heater or cooler 44 by positioning the temperature sensor 130 within a thermally conductive sensor housing 134 that is surrounded by thermally insulating material 138 such that first and second ends of the sensor housing 134 are exposed. The sensor housing 134 and thermally insulating material 138 are then positioned within an appropriately sized and shaped opening in the heater or cooler 44 so that the thermally
10 conductive housing 134 can be in thermal contact with the IC 54.

Having described and illustrated the principles of the invention in a preferred embodiment thereof, it should be apparent that the invention can be modified in arrangement and detail without departing from such principles.

CLAIMS

What is claimed is:

1. An integrated circuit (IC) socket lid (22), comprising:
a temperature sensor (48) arranged to thermally contact an IC package
5 (54);
a heater or a cooler (44) arranged to directly contact the IC package (54);
and
an electronic controller (42) connected to the temperature sensor (48) and
to the heater or cooler (44),
10 wherein the electronic controller (42) is programmed to control the
temperature of the IC package (54) responsive to the temperature sensor (48).
2. The IC socket lid (22) of claim 1, further comprising:
a latch (26) adapted to quickly secure and release the lid (22) to and from
15 an IC socket base (38).
3. The IC socket lid (22) of claim 1, in which the electronic controller
(42) includes:
an analog-to-digital (A/D) converter (60) to convert signals from the
20 temperature sensor (48);
a processor (62) programmed to receive and transmit digital data; and
a digital-to-analog (D/A) converter (66) to convert digital data from the
processor (62),
wherein the processor (62) is programmed to compare the converted data
25 from the temperature signal with an operator inputted digital value and, responsive
to the comparison, transmit a signal from the processor (62) through the D/A
converter (66) to the heater or cooler (44) to affect the temperature of the IC
package (54).

4. The IC socket lid (22) of claim 1, further comprising an electrical connector (34) electrically coupled to the controller (42) and arranged to connect with a corresponding electrical connector (30) on a testing board (32).

5 5. The IC socket lid (22) of claim 1, in which:
the controller (42) is adapted to receive digital signals from the electrical connector (34);
the heater or cooler (44) is adapted to receive power from the electrical connector (34); and
10 the temperature sensor (48) is adapted to receive power from the electrical connector (34).

6. The IC socket lid (72) of claim 1, in which:
the temperature sensor (48) is a plurality of temperature sensors (48)
15 arranged to thermally contact a corresponding plurality of IC packages (54);
the heater or cooler (44) is a plurality of heaters or coolers (44) arranged to directly contact the corresponding plurality of IC packages (54); and
the electronic controller (42) is a plurality of electronic controllers (42).

20 7. The IC socket lid (72) of claim 6, further comprising a top attach plate (72) adapted to resiliently mount the plurality of temperature sensors (48) and heaters or coolers (44).

8. The IC socket lid (72) of claim 6, in which each electronic
25 controller (42) includes:
an analog-to-digital (A/D) (60) converter to convert signals from a temperature sensor (48);
a processor (62) programmed to receive and transmit digital data; and

a digital-to-analog (D/A) converter (66) to convert digital data from the processor (62),

wherein the processor (62) is programmed to compare the converted data from the temperature signal with an operator inputted digital value and, responsive to the comparison, transmit a signal from the processor (62) through the D/A converter (66) to a heater or cooler (44) to affect the temperature of an IC package (54).

9. An integrated circuit (IC) socket temperature controller (42), comprising:

an analog-to-digital (A/D) converter (60) to convert an analog signal from a temperature sensor (48);

a processor (62) programmed to receive and transmit digital data; and

a digital-to-analog (D/A) converter (66) to convert digital data from the processor (62),

wherein the processor (62) is programmed to compare the converted data from the temperature sensor (48) with an operator inputted digital value, and responsive to the comparison, transmit a signal from the processor (62) through the D/A converter (66) to one of a heater and cooler (44) to affect the temperature of an IC package (54).

10. The IC socket temperature controller (42) of claim 9, in which the controller (42) is located in an IC socket lid (22, 72).

11. The IC socket temperature controller (42) of claim 9, in which the controller (42) is adapted to receive digital data and power from a connector (34) on the IC socket lid (22).

12. A system for testing, burning-in and programming IC packages (54), comprising:

- a testing chamber (68);
- a testing board (32) placed within the testing chamber (68);
- 5 an IC socket base (20) mounted on the testing board (32);
- an IC package (54) received in the IC socket base (20); and
- an IC socket lid (22, 72), wherein the IC socket lid (22, 72) includes:
 - a temperature sensor (48) arranged to thermally contact the IC package (54);
 - 10 a heater or a cooler (44) arranged to directly contact the IC package (54); and
 - an electronic controller (42) connected to the temperature sensor (48) and the heater or cooler (44);
- wherein the electronic controller (42) is programmed to change the
- 15 temperature of the heater or cooler (44) responsive to the temperature sensor (48).

13. The system of claim 12, in which:
- the testing board (32) includes an electronic connector (30) and the IC socket lid (22) includes a corresponding electronic connector (34);
 - 20 the connector (30) on the testing board is positioned and adapted to connect to the connector (34) on the IC socket lid (22);
 - the connector (34) on the IC socket lid (22) is electrically coupled to the electronic controller (42); and
 - the testing board (32) is adapted to receive and transmit signals between a
 - 25 system controller (70) and the electronic controller (42), wherein the system controller (70) is located outside of the testing chamber (68).

14. The system of claim 12, in which:
the IC socket base (20) includes a plurality of IC socket bases (20)
mounted on the testing board (32); and
the temperature sensor (48) is a plurality of temperature sensors (48)
5 arranged to thermally contact a plurality of IC packages (54) in the plurality of IC
socket bases (20);
the heater or cooler (44) is a plurality of heaters or coolers (44) arranged to
directly contact the plurality of IC packages (54);
the electronic controller (42) is a plurality of electronic controllers (42);
10 and
the IC socket lid (72) includes a top attach plate (72) adapted to attach to
the testing board (32).

15. The system of claim 14, in which the plurality of IC socket bases
15 (20) and the plurality of temperature sensors (48) and heaters or coolers (44) are
arranged in a regular matrix.

16. The system of claim 14, in which the top attach plate (72) is
adapted to resiliently engage the temperature sensors (48) and heaters or coolers
20 (44) with the IC packages (54).

17. A method of controlling the temperature of an integrated circuit
(IC) package (54) during one of testing, burning-in and programming of the IC
package (54), comprising:
25 sensing a temperature of the IC package (54) with a temperature sensor
(48) in thermal contact with the IC package (54), the temperature sensor (48)
being located in an IC socket lid (22, 72);
processing data from the temperature sensor (48) in an electronic
controller (42) located in the IC socket lid (22, 72); and

controlling the temperature of the IC package (54) with a heater or cooler (44) located in the IC socket lid (22, 72) responsive to a signal from the electronic controller (42).

5 18. The method of claim 17, further comprising transmitting a digital value to the electronic controller (42) from a system controller (70), the digital value representing a desired IC package temperature.

 19. The method of claim 18, further comprising:
10 comparing the transmitted digital value representing the desired IC package temperature with the sensed temperature of the IC package (54) in the electronic controller(42); and

 transmitting a signal responsive to the comparison from the electronic controller (42) to the heater or cooler (44) to control the heater or cooler (44).

15

 20. A method of independently controlling the temperature of each of a plurality of IC packages (54) during one of testing, burning-in and programming the IC packages (54):

 sensing a temperature of each of the IC packages (54) with a separate
20 temperature sensor (48) in thermal contact with each IC package (54), the temperature sensors (48) mounted on a top attach plate (72);

 processing data from the temperature sensors (48) in a plurality of electronic controllers (42) located on the top attach plate (72); and

 controlling the temperature of each IC package (54) with a corresponding
25 heater or cooler (44) responsive to signals from the electronic controllers (42).

 21. The method of claim 20, further comprising transmitting a digital value to each of the electronic controllers (42) from a system controller (70), the digital value representing a desired temperature of an IC package (54).

22. The method of claim 21, further comprising:
comparing the transmitted digital value representing the desired IC
package temperature with the sensed temperature of an IC package (54) in the
5 electronic controllers (42); and
transmitting a signal responsive to each comparison from the electronic
controllers (42) to a heater or cooler (44) contacting the sensed IC package (54) to
control the heater or cooler (44).
- 10 23. The method of claim 21, in which transmitting a digital value to the
electronic controllers (42) from a system controller (70) includes transmitting an
independent digital value for each IC package (54) to the electronic controllers
(42) from the system controller (70).
- 15 24. In an integrated circuit testing socket (123) which includes a means
for heating or cooling (44) the integrated circuit (54), an integrated circuit
temperature sensing device (48) comprising:
a thermistor (130);
a sensor housing (134) positioned to thermally contact the integrated
20 circuit (54), wherein the thermistor (130) is positioned within the housing (134)
and the housing (134) is thermally conductive; and
a thermal insulator (138) surrounding the sensor housing (134) so that the
thermistor (130) is thermally isolated from the means for heating or cooling (44)
the integrated circuit (54).
- 25 25. The device (123) of claim 24, wherein the sensor housing (134) is
shaped to receive the thermistor (130) in a cylindrical cavity (132), wherein the
cavity (132) has a single opening at a first end of the housing (134) and the cavity
(132) extends toward a second end of the housing (134).

26. The device of claim 25, wherein the cylindrical cavity (132) includes a conically shaped termination (136) near the second end of the housing (134) to further receive the thermistor (130) into the cavity (132) near the second
5 end of the housing (134) so that a short thermal path exists from the exterior of the second end of the housing (134) to the thermistor (130).

27. The device of claim 25, in which the second end of the sensor housing (134) is exposed from the thermal insulator (138) to form a thermally
10 conductive path from an integrated circuit (54) to the thermistor (130).

28. The device of claim 24, wherein the sensor housing (134) is formed of a highly conductive metal.

15 29. The device of claim 24, wherein the sensor housing is formed of metal comprising aluminum or copper.

30. The device of claim 24, wherein the thermal insulator (138) is formed of a polythermide material.

20

31. An integrated circuit temperature controlling arrangement comprising:

a temperature control block (44) thermally contacting an integrated circuit (54), wherein the temperature control block (44) effects a change in integrated
25 circuit (54) temperature by conducting heat to or from the integrated circuit (54);
and

an integrated circuit temperature sensing device (48) positioned within the temperature control block (44), wherein a temperature sensor (130) is located within the temperature sensing device (48) such that the temperature sensor (130)

thermally contacts the integrated circuit (54) through a conductive material (134) and an insulating material (138) thermally isolates the temperature sensor (130) from the temperature control block (44).

5 32. The arrangement of claim 31, wherein the conductive material (134) is a highly conductive metal.

 33. The arrangement of claim 31, wherein the conductive material (134) comprises copper or aluminum and the insulating material (138) is formed
10 of a polythermide material.

 34. The arrangement of claim 31, wherein the conductive material (134) spaces the temperature sensor (130) from the integrated circuit (54) a predetermined distance to provide a thermal path for fast transient response to
15 temperature changes of the integrated circuit (54).

 35. The arrangement of claim 34, wherein the conductive material (134) spaces the temperature sensor (130) from the integrated circuit so that the temperature sensor (130) or integrated circuit (54) is physically protected from
20 damage otherwise resulting from contact between the temperature sensor (130) and the integrated circuit (54).

 36. The arrangement of claim 31, wherein the conductive material (134) is shaped so that a flat surface contacts the integrated circuit (54).
25

 37. An integrated circuit temperature sensing and control arrangement for use in testing integrated circuits (54), comprising:

 a temperature sensor (130) having a generally cylindrically tip located in a blind cylindrical bore (132) of a generally cylindrically-shaped housing (134);

the housing (134) being formed of a conductive material;
an annular sleeve of thermally insulating material (138) surrounding the housing (134); and

5 a temperature control block (44) arranged to actively conduct heat to or from an integrated circuit (54) when thermally contacting the integrated circuit (54),

the control block (44) having a cylindrical through-bore sized and shaped to receive the insulating material (138), housing (134) and temperature sensor (130) as a unit so that the housing (134) is thermally insulated from the
10 temperature control block (44) and the housing (134) thermally contacts the integrated circuit (54).

38. A method of sensing the temperature of an integrated circuit (54) during testing of the integrated circuit (54), comprising:

15 placing an integrated circuit (54) in a test socket (123);

changing the temperature of the integrated circuit (54) by thermally contacting a heater or cooler (44) to the integrated circuit (54); and

sensing the temperature of the integrated circuit (54) by means of a temperature sensor (130) contained within the heater or cooler (44), by thermally
20 connecting the temperature sensor (130) to the integrated circuit (54) through a conductive material (134) and by thermally isolating the temperature sensor (130) from the heater or cooler (44) so that the temperature sensor (130) predominantly senses the temperature of the integrated circuit (54).

25 39. The method of claim 38, wherein thermally connecting the temperature sensor (130) to the integrated circuit (54) through a conductive material (134) includes the conductive material (134) spacing the sensor (130) from the integrated circuit (54) a predetermined distance to provide a thermal path for fast transient response to temperature changes of the integrated circuit (54).

40. The method of claim 38, wherein testing of the integrated circuit (54) can include testing, burning-in, and programming the integrated circuit (54).

- 5 41. The method of claim 38 wherein thermally isolating the temperature sensor (130) from the heater or cooler (44) includes:
- positioning the temperature sensor (13) in a thermally conductive temperature sensor housing (134);
- forming an insulator (138) to surround the temperature sensor housing (134) leaving exposed a first and second end of the temperature sensor housing (134); and
- 10 positioning the temperature sensor housing (134) and surrounding insulator (138) in an opening in the heater or cooler (44) sized and shaped to receive the temperature sensor housing (134) and surrounding insulator (138).

15