

DESCRIPTION

USER DEVICE, BASE STATION DEVICE, AND CHANNEL STATE
INFORMATION COMMUNICATION METHOD

5

TECHNICAL FIELD

The present invention relates to a field
of mobile communications. More specifically, the
present invention relates to a user equipment
10 terminal, a base station apparatus, and a control
information communication method in a mobile
communication system.

BACKGROUND ART

15 In the field of mobile communications,
research and development on a next generation
communication system is rapidly progressing. In the
communication system considered as of now, from the
view point of broadening the coverage area while
20 reducing PAPR (Peak-to-Average Power Ratio), it is
proposed to use a single carrier scheme for uplink.
In this communication system, radio resources for
both uplink and downlink are properly assigned, as a
form of a shared channel which is shared by plural
25 users, according to communication conditions of
respective users and the like. More specifically, a
data signal of a user in uplink is transmitted on a
physical uplink shared channel (PUSCH). The terms
"channel" and "signal" may be used synonymously as
30 long as there is no fear of confusion. A data
signal of a user in downlink is transmitted on a
physical downlink shared channel (PDSCH).

Processing for determining assignment is
called scheduling. In order to properly perform
35 scheduling in uplink, each user equipment terminal
transmits a reference signal (also called a pilot
channel) to a base station and the base station

evaluates the uplink channel state based on reception quality of the reference signal. In addition, in order to perform scheduling in downlink, the base station transmits a reference signal to the user equipment terminal and the user equipment terminal reports to the base station information about the channel state (CQIs: Channel Quality Indicators) based on reception quality of the reference signal. Based on the CQIs reported from each user equipment terminal, the base station evaluates the downlink channel state to perform scheduling in downlink. The results of scheduling are transmitted to each user equipment terminal via a downlink control signal. This control signal is called a downlink L1/L2 control signal.

There are two types of uplink control signals: one is control information (called first control information, for the sake of convenience) that should be transmitted together with an uplink data signal and the other is control information (called second control information, for the sake of convenience) that is transmitted irrespective of the presence or absence of the uplink data signal. The first control information includes information necessary for demodulation of the data signal, such as a modulation scheme, a channel coding rate, and the like of the data signal. The second control information includes CQI information of a downlink channel, acknowledgement information (ACK/NACK) of a downlink data signal, information about a resource assignment request, and the like.

When a resource block (radio resource) is assigned for transmitting an uplink data signal, the first control information (and second control information as necessary) is transmitted in the resource block. On the other hand, when the uplink data signal is not transmitted, it is considered

that the second control information is transmitted using a dedicated resource (dedicated band). In the following, an example of using the band is described below.

5 Fig. 1 shows a configuration of an uplink channel. Fig. 1 shows resources (plural resource blocks) for transmitting the physical uplink shared channel (PUSCH) as the uplink data signal, and resources (corresponding to the dedicated band) for
10 a user to which resources for the PUSCH are not assigned to transmit the uplink control signal. The latter is called a physical uplink control channel (PUCCH). In the shown example, one or more of four resource blocks are assigned to users, a first
15 hopping control signal and a second hopping control signal are provided in a certain transmission time interval (subframe), and a third hopping control signal and a fourth hopping control signal are provided in the following subframe. Each hopping
20 control signal corresponds to the PUCCH. By performing hopping with respect to time and frequency in subframes, a greater diversity effect can be obtained. Each of the first through fourth hopping control signals may be occupied by one user
25 or may be multiplexed by plural users. This transmission scheme of uplink control signals is described in 3GPP, R1-071245.

DISCLOSURE OF INVENTION

30 [PROBLEM(S) TO BE SOLVED BY THE INVENTION]
 When the L1/L2 control channel (first through fourth hopping control signals) is multiplexed by plural users without uplink data transmission, it is considered that orthogonality
35 among the plural users is achieved using a CAZAC sequence. The CAZAC sequence has a characteristic in that a CAZAC code is orthogonal to a code with a

cyclic shift of the CAZAC code. Accordingly, when the same CAZAC sequence is used among users and different cyclic shifts are applied to the users, orthogonality among the users can be achieved. Fig. 2 shows a configuration of the L1/L2 control channel, where the cyclic shift amount of zero (0) is applied to a user #1 and the cyclic shift amount of Δ is applied to a user #2.

In this manner, the L1/L2 control channel for users without uplink data transmission undergoes block-modulation using the CAZAC code in order to multiplex data for plural users. Thus, the number of bits available for transmission per user is determined in advance. For example, it is assumed that ten symbols per user can be transmitted in the subframe configuration shown in Fig. 2. When a QPSK data modulation and the coding rate of 1/2 are used, a user equipment terminal can transmit ten bits of information for each subframe.

As described above, the L1/L2 control channel for users without uplink data transmission includes CQI information, acknowledgement information (ACK/NACK), information about a resource assignment request, and the like. Regarding the CQI information, the user equipment terminal may transmit fine-grained CQIs for respective bands to be scheduled according to an instruction from the base station apparatus. In addition, the user equipment terminal may transmit CQIs for respective streams in the case of MIMO (multiple input multiple output) transmission using plural antennas. In these circumstances, the CQI information may exceed the number of bits which can be transmitted in each subframe.

For example, by increasing the coding rate, for example (using the coding rate of 3/4, for example), it is possible to increase the number of

bits which can be transmitted in each subframe. In this case, however, a problem of degrading reception quality may arise. For example, in W-CDMA (wideband code division multiple access), CQI information is
5 repeatedly transmitted in the case where reception quality is degraded.

In view of this problem, it is a general object of the present invention to transmit channel state information (CQI information) without
10 degrading reception quality.

[MEANS FOR SOLVING THE PROBLEM(S)]

In one aspect of the present invention, there is provided a user equipment terminal for estimating a channel state and transmitting, as
15 control information transmitted irrespective of a presence or absence of an uplink data signal, channel state information representing the estimated channel state according to a single carrier scheme, including:

20 an encoding unit configured to encode the channel state information; and

a transmitting unit configured to transmit the channel state information over plural transmission time intervals.

25 In another aspect of the present invention, there is provided a base station apparatus for receiving, as control information transmitted irrespective of a presence or absence of an uplink data signal, channel state information representing
30 a channel state estimated by a user equipment terminal, including:

a receiving unit configured to receive the channel state information over plural transmission time intervals;

35 a decoding unit configured to decode the channel state information; and

a resource assigning unit configured to

assign resources based on the channel state information.

In another aspect of the present invention, there is provided a channel state information communication method for use in a mobile communication system using a single carrier scheme for uplink, including the steps of:

- by a user equipment terminal,
 - estimating a channel state;
 - encoding channel state information representing the estimated channel state;
 - transmitting, as control information transmitted irrespective of a presence or absence of an uplink data signal, the channel state information over plural transmission time intervals;
- by a base station apparatus,
 - receiving the channel state information over plural transmission time intervals;
 - decoding the channel state information;

and

- assigning resources based on the channel state information.

[ADVANTAGEOUS EFFECT OF THE INVENTION]

According to an embodiment of the present invention, it is possible to transmit channel state information without degrading reception quality.

BRIEF DESCRIPTION OF THE DRAWINGS

Fig. 1 shows a channel configuration used in a mobile communication system.

Fig. 2 shows a multiplexing scheme among users in an L1/L2 control channel for users without uplink data transmission.

Fig. 3 shows a coding unit of a CQI encoding method in accordance with a first embodiment of the present invention.

Fig. 4 shows a flowchart of the CQI

encoding method in accordance with the first
embodiment of the present invention.

Fig. 5 shows a block diagram of a user
equipment terminal in accordance with the first
5 embodiment of the present invention.

Fig. 6 shows a block diagram of a base
station apparatus in accordance with the first
embodiment of the present invention.

Fig. 7 shows a coding unit of a CQI
10 encoding method in accordance with a second
embodiment of the present invention.

Fig. 8 shows a block diagram of a user
equipment terminal in accordance with the second
embodiment of the present invention.

Fig. 9 shows a block diagram of a base
15 station apparatus in accordance with the second
embodiment of the present invention.

Fig. 10 shows a coding unit of a CQI
encoding method in accordance with a third
20 embodiment of the present invention.

Fig. 11 shows a block diagram of a user
equipment terminal in accordance with the third
embodiment of the present invention.

Fig. 12 shows a block diagram of a base
25 station apparatus in accordance with the third
embodiment of the present invention.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

[DESCRIPTION OF NOTATIONS]

30 10 user equipment terminal
101 CQI estimating unit
103, 103a, 103b channel encoding unit
105 modulation pattern generating unit
107 modulation unit
35 109 discrete Fourier transform unit (DFT)
111 subcarrier mapping unit
113 inverse fast Fourier transform unit

(IFFT)

115 cyclic prefix (CP) adding unit
117 multiplexing unit
119 RF transmitting circuit
5 121 power amplifier
123 duplexer
125 CAZAC code generating unit
127 cyclic shift unit
129 block-spreading unit
10 131 frequency setting unit
133 reference signal generating unit
135 broadcast channel or dedicated L3
signaling demodulation unit
137 CQI arranging unit
15 20 base station apparatus
201 duplexer
203 RF receiving circuit
205 reception timing estimating unit
207 fast Fourier transform unit (FFT)
20 209 channel estimating unit
211 subcarrier demapping unit
213 frequency-domain equalizing unit
215 inverse discrete Fourier transform
unit (IDFT)
25 217 demodulation unit
219, 219a, 219b decoding unit
221 scheduler
213 control unit
[BEST MODE OF CARRYING OUT THE INVENTION]
30 With reference to the accompanying
drawings, embodiments of the present invention are
described below.
<First embodiment: approach for encoding
CQI information at one time>
35 In a first embodiment of the present
invention, a description is given below with regard
to an approach in which a user equipment terminal

encodes CQI information at one time (as a whole) and transmits the CQI information over plural subframes.

For example, when a base station apparatus includes two antennas and twenty bits of CQI information is needed for each antenna, the channel configuration in Fig. 2 does not allow a user equipment terminal to transmit the CQI information in a single subframe. Since forty bits ($20 \text{ (bits)} * 2 \text{ (antennas)} = 40 \text{ (bits)}$) of information are needed as a whole, four subframes are needed to transmit the CQI information.

Fig. 3 shows a coding unit of a CQI encoding method in accordance with the first embodiment of the present invention. In Fig. 3, the user equipment terminal encodes forty bits of information at one time and transmits the information with four subframes. In other words, encoding is performed for each set of CQI information. This first embodiment can increase the coding gain and allow for high quality transmission. Since the base station apparatus cannot decode CQI information until the last subframe is received, longer delay may develop with an increase in CQI information.

Fig. 4 shows a flowchart of a CQI communication method in accordance with the first embodiment of the present invention.

The user equipment terminal receives a reference signal (S101), and then measures CQIs with the amount of information specified by the base station apparatus (S103). For example, the user equipment terminal measures an average CQI for the whole band, CQIs for respective bands (resource blocks) to be scheduled, CQIs for respective antennas, and the like. In the first embodiment, the measured CQI information is encoded at one time (S105), and then transmitted to the base station

apparatus (S107).

The base station apparatus receives the CQI information which is encoded at one time until the last subframe is received (S109). When the last
5 subframe is received, the base station apparatus decodes the CQI information (S111). The base station assigns resources based on the CQI information (S113), and then transmits resource assignment information to the user equipment
10 terminal (S115). When the user equipment terminal receives the resource assignment information (S117), the user equipment terminal and the base station apparatus start data transmission and reception.

<First embodiment: configuration of a user
15 equipment terminal>

Fig. 5 shows a block diagram of a user equipment terminal 10 in accordance with the first embodiment of the present invention. The user equipment terminal 10 includes a CQI estimating unit
20 101, a channel encoding unit 103, a modulation pattern generating unit 105, a modulation unit 107, a discrete Fourier transform unit (DFT) 109, a subcarrier mapping unit 111, an inverse fast Fourier transform unit (IFFT) 113, a cyclic prefix (CP)
25 adding unit 115, a multiplexing unit 117, a RF transmitting circuit 119, a power amplifier 121, a duplexer 123, a CAZAC code generating unit 125, a cyclic shift unit 127, a block-spreading unit 129, a frequency setting unit 131, a reference signal
30 generating unit 133, and a broadcast channel or dedicated L3 signaling demodulation unit 135.

The CQI estimating unit 101 receives a reference signal from the base station apparatus and estimates CQIs. The CQI estimating unit 101 may
35 estimate an average CQI for the whole band or CQIs for respective resource blocks according to the instruction from the base station apparatus.

Alternatively, the CQI estimating unit 101 may estimate CQIs for respective streams (paths for linking antennas).

5 The channel encoding unit 103 encodes the estimated CQI information at one time. For example, when the base station apparatus includes two antennas and twenty bits of CQI information is needed for each antenna, the channel encoding unit 103 encodes CQI information corresponding to four
10 subframes at one time.

The block-by-block modulation pattern generating unit 105 arranges CQI information and acknowledgement information (ACK/NACK) according to a modulation pattern for each block.

15 The block-by-block modulation unit 107 applies different cyclic shift amounts to the CAZAC code sequence assigned to user equipment terminals to derive information sequences to be transmitted in a single subframe (or transmission time interval
20 (TTI)). As described above, the information sequences are orthogonal among user equipment terminals.

The discrete Fourier transform unit (DFT) performs discrete Fourier transform to convert
25 information in the time domain into information in the frequency domain.

The subcarrier mapping unit 111 performs mapping in the frequency domain. Specifically, when the frequency division multiplexing (FDM) scheme is
30 used for multiplexing signals for plural user equipment terminals, the subcarrier mapping unit 111 performs mapping of signals according to bands which are set in the frequency setting unit 131. There are two types of FDM schemes: one is a localized FDM
35 scheme and the other is a distributed FDM scheme. In the localized FDM scheme, a continuous band is assigned for each user on the frequency axis. In

the distributed FDM scheme, a downlink signal is generated such that the signal includes discontinuous frequency components over a wide band (over the whole band for uplink control signal).

5 The inverse fast Fourier transform unit (IFFT) 113 performs inverse Fourier transform to convert the signal in the frequency domain back into a signal in the time domain.

 The cyclic prefix (CP) adding unit 115
10 adds a cyclic prefix to information to be transmitted. The cyclic prefix (CP) functions as a guard interval for compensating multipath propagation delay and for compensating differences of reception timings among plural users in the base
15 station apparatus.

 The multiplexing unit 117 multiplexes the reference signal into information to be transmitted to generate a transmission symbol. The reference signal is a signal having a pattern which is known
20 to both the transmission side and the reception side, and may be also referred to as a pilot signal, a pilot channel, a training signal, and the like.

 The RF transmission circuit 119 performs processing such as digital-to-analog conversion,
25 frequency conversion, band limitation, and the like for transmitting the transmission symbol with a radio frequency.

 The power amplifier 121 adjusts transmission power.

30 The duplexer 123 properly separates a transmission signal and a received signal such that simultaneous communications are achieved.

 The CAZAC code generating unit 125 generates a CAZAC code sequence according to a
35 sequence number of a CAZAC code sequence used by the user equipment terminal.

 The cyclic shift unit 127 derives another

code by cyclically rearranging the CAZAC code sequence according to the cyclic shift amount of the CAZAC code sequence used by the user equipment terminal. For example, the CAZAC code is described
5 in detail in D. C. Chu, "Polyphase codes with good periodic correlation properties", IEEE Trans. Inform. Theory, vol. IT-18, pp.531-532, July 1972; and 3GPP, R1-050822, Texas Instruments, "On allocation of uplink sub-channels in EUTRA SC-FDMA".

10 The block spreading unit 129 prepares a set of predetermined number of factors (block spreading codes) and multiplies each block shown in Fig. 2 by each factor.

 The frequency setting unit 131 specifies
15 which frequency should be used by each user equipment terminal, when the frequency division multiplexing (FDM) scheme is applied for an uplink control signal from plural user equipment terminals.

 The reference signal generating unit 133
20 prepares a reference signal to be included in the uplink control signal.

 The broadcast channel or dedicated L3 signaling demodulation unit 135 receives from the base station apparatus a CAZAC number, a cyclic
25 shift amount, a block spreading code, and a frequency used by the user equipment terminal on the broadcast channel or the dedicated L3 signaling, and then demodulates them.

 <First embodiment: configuration of a base
30 station apparatus>

 Fig. 6 shows a block diagram of a base station apparatus 20 in accordance with the first embodiment of the present invention. The base station apparatus 20 includes a duplexer 201, a RF
35 receiving circuit 203, a reception timing estimating unit 205, a fast Fourier transform unit (FFT) 207, a channel estimating unit 209, a subcarrier demapping

unit 211, a frequency-domain equalizing unit 213, an inverse discrete Fourier transform unit (IDFT) 215, a demodulation unit 217, a decoding unit 219, and a scheduler 211.

5 The duplexer 201 properly separates between a transmission signal and a received signal such that simultaneous communications are achieved.

 The RF receiving circuit 203 performs processing such as digital-to-analog conversion,
10 frequency conversion, band limitation, and the like for processing the received symbol in baseband.

 The reception timing estimating unit 205 identifies reception timings based on a
15 synchronization channel or a reference signal in the received signal.

 The fast Fourier transform unit (FFT) 207 performs Fourier transform to convert information in the time domain into information in the frequency domain.

20 The channel estimating unit 209 estimates an uplink channel state based on reception state of the uplink reference signal and outputs information for performing channel compensation.

 The subcarrier demapping unit 211 performs
25 demapping in the frequency domain. This process is performed corresponding to mapping in the frequency domain performed in each user equipment terminal.

 The frequency-domain equalizing unit 213 performs equalization of the received signal based
30 on the channel estimation value.

 The inverse discrete Fourier transform unit (IDFT) 215 performs inverse discrete Fourier transform to convert the signal in the frequency domain back into a signal in the time domain.

35 The demodulation unit 217 demodulates the received signal.

 The decoding unit 219 decodes the

demodulated received signal. In the first embodiment, the decoding unit 219 outputs CQI information for the downlink channel at one time.

5 The scheduler 211 determines downlink resource assignment based on the level of the channel state information (CQI) for the downlink channel and other criteria. In addition, the scheduler 211 determines uplink resource assignment based on the reception result of the reference
10 signal transmitted from each user equipment terminal and other criteria. The determined assignment information is output as scheduling information. The scheduling information specifies a frequency, a time, a transmission format (data modulation scheme and channel coding rate), and the like used for
15 transmitting signals.

The scheduler also determines a CAZAC number, a cyclic shift amount, a block spreading code, and a frequency to be assigned to each user
20 equipment terminal. The determined information is transmitted to each user equipment terminal on the broadcast channel or the dedicated L3 signaling.

<Second embodiment: approach for encoding CQI information for each subframe>

25 In a second embodiment of the present invention, a description is given below with regard to an approach in which a user equipment terminal divides CQI information into information items, each of which can be transmitted in a single subframe, and encodes one information item for each subframe,
30 when the CQI information exceeds the number of bits which can be transmitted in each subframe.

Fig. 7 shows a coding unit of a CQI encoding method in accordance with the second
35 embodiment of the present invention. In Fig. 7, when forty bits are needed for CQI information, the user equipment terminal divides forty bits of

information into information items, each of which can be transmitted in a single subframe, and encodes one information item for each subframe. The whole CQI information is transmitted with four subframes.

5 In other words, encoding is performed for each subframe. According to this second embodiment, the base station apparatus can decode the information item upon receiving one subframe, and thus delay can be reduced irrespective of an increase in CQI
10 information.

In order to further reduce delay, the user equipment terminal may arrange the CQI information in descending order of the channel state (from a better channel state to a poorer channel state),
15 encode the CQI information in descending order of the channel state, and transmit the CQI information in descending order of the channel state. This allows the base station apparatus to perform scheduling in descending order of the channel state.
20 Accordingly, when the base station apparatus completes resource assignment, the base station apparatus need not decode unnecessary CQI information.

A CQI communication method in accordance
25 with the second embodiment of the present invention is performed according to the flowchart shown in Fig. 4. According to the second embodiment, in step S105, the user equipment terminal performs encoding for each subframe. In step S107, the user equipment
30 terminal transmits to the base station apparatus the CQI information which is encoded for each subframe. In step S109, the base station apparatus receives the CQI information for each subframe. In step S111, the base station apparatus decodes the CQI
35 information for each subframe.

<Second embodiment: configuration of a user equipment terminal>

Fig. 8 shows a block diagram of a user equipment terminal 10 in accordance with the second embodiment of the present invention. The user equipment terminal 10 shown in Fig. 8 may include a CQI arranging unit 137 in addition to the components shown in Fig. 5.

According to the second embodiment, the channel encoding unit 103 divides the estimated CQI information into information items, each of which can be transmitted in a single subframe, and encodes one information item for each subframe.

When the user equipment terminal 10 includes the CQI arranging unit 137, the CQI arranging unit 137 arranges the CQI information in descending order of the channel state. In this case, the channel encoding unit 103 encodes the CQI information in descending order of the channel state. The CQI information is transmitted to the base station apparatus in descending order of the channel state.

<Second embodiment: configuration of a base station apparatus>

Fig. 9 shows a block diagram of a base station apparatus 20 in accordance with the second embodiment of the present invention. The base station apparatus 20 shown in Fig. 9 may include a control unit 223 in addition to the components shown in Fig. 6.

According to the second embodiment, the decoding unit 219 outputs downlink CQI information for each subframe.

When the user equipment terminal arranges the CQI information in descending order of the channel state, the decoding unit 219 decodes the CQI information in descending order of the channel state and supplies the CQI information to the scheduler 221. The scheduler 221 can assign resources in

descending order of the channel state. Accordingly, when the scheduler 221 completes resource assignment, CQI information in other bands associated with these resources is not necessary. For this reason, the
5 base station apparatus may include the control unit 223. When resource assignment is completed, the control unit 223 instructs the decoding unit 219 to stop decoding the CQI information in other bands associated with these resources. It should be noted
10 that the control unit 223 may be integrated into the scheduler 221.

<Third embodiment: approach for encoding CQI information for each stream>

A third embodiment of the present
15 invention relates to MIMO transmission where a user equipment terminal or a base station apparatus performs transmission using plural antennas. In the MIMO transmission, CQI information is needed for each stream (path for linking antennas), which
20 causes an increase in CQI information. The user equipment terminal divides CQI information into information items for respective streams and encodes the CQI information by one information item for each stream, when the CQI information exceeds the number
25 of bits which can be transmitted in each subframe.

Fig. 10 shows a coding unit of a CQI encoding method in accordance with the third embodiment of the present invention. In Fig. 10, when forty bits are needed for CQI information, the
30 user equipment terminal divides forty bits of information into information items for respective streams and encodes the CQI information by one information item for each stream. When the base station apparatus includes two antennas, the user
35 equipment terminal divides forty bits of information into information items with twenty bits and encodes the CQI information by each information item with

twenty bits. The whole CQI information is transmitted with four subframes. In other words, encoding is performed for each stream. According to this third embodiment, the base station apparatus
5 can decode CQI information for one stream upon receiving two subframes.

A CQI communication method in accordance with the third embodiment of the present invention is performed according to the flowchart shown in Fig.
10 4. According to the third embodiment, in step S105, the user equipment terminal performs encoding for each stream. In step S107, the user equipment terminal transmits to the base station apparatus the CQI information which is encoded for each stream.
15 In step S109, the base station apparatus receives the CQI information for each stream. In step S111, the base station apparatus decodes the CQI information for each stream.

<Third embodiment: configuration of a user
20 equipment terminal>

Fig. 11 shows a block diagram of a user equipment terminal 10 in accordance with the third embodiment of the present invention. The user equipment terminal 10 shown in Fig. 11 may include
25 plural channel encoding units 103a and 103b corresponding to the number of streams.

According to the third embodiment, each of the channel encoding units 103a and 103b encodes CQI information for each stream. The CQI information
30 for each stream is transmitted to the base station apparatus. Although the user equipment terminal 10 includes the channel encoding units 103a and 103b corresponding to the number of streams, one channel encoding unit may perform encoding for each stream.
35 In addition, the user equipment terminal may include plural modulation pattern generating units 105 and plural modulation units 107 corresponding to the

number of streams, in order to process modulation for each stream in parallel.

<Third embodiment: configuration of a base station apparatus>

5 Fig. 12 shows a block diagram of a base station apparatus 20 in accordance with the third embodiment of the present invention. The base station apparatus 20 may include plural decoding units 219a and 219b corresponding to the number of
10 streams.

 According to the third embodiment, each of the decoding units 219a and 219b outputs downlink CQI information for each stream. When each of the decoding units 219a and 219b decodes the CQI
15 information for each stream, each of the decoding units 219a and 219b instructs the scheduler 221 to assign resources for the corresponding stream. Although the base station apparatus 20 includes the decoding units 219a and 219b corresponding to the
20 number of streams, one decoding unit may perform decoding for each stream.

 The present invention is not limited to these embodiments. The present invention may be modified within the scope of the claims.

25 This international patent application is based on Japanese Priority Application No. 2007-161948 filed on June 19, 2007, the entire contents of which are incorporated herein by reference.

CLAIMS

5

1. A user equipment terminal for estimating a channel state and transmitting, as control information transmitted irrespective of a presence or absence of an uplink data signal,
10 channel state information representing the estimated channel state according to a single carrier scheme, comprising:

an encoding unit configured to encode the channel state information; and

15 a transmitting unit configured to transmit the channel state information over plural transmission time intervals.

20

2. The user equipment terminal as claimed in Claim 1, wherein:

25 the encoding unit encodes the channel state information at one time.

30 3. The user equipment terminal as claimed in Claim 1, wherein:

the encoding unit divides the channel state information into information items, each of which can be transmitted in a single transmission
35 time interval, and encodes the channel state information by each of the information items, each of which can be transmitted in the single

transmission time interval.

5

4. The user equipment terminal as claimed in Claim 3, further comprising:

an arranging unit configured to arrange the channel state information in descending order of the channel state, wherein

the encoding unit encodes the channel state information in descending order of the channel state, and

the transmitting unit transmits the channel state information in descending order of the channel state.

20

5. The user equipment terminal as claimed in Claim 1, wherein:

the encoding unit divides the channel state information into information items for respective streams and encodes the channel state information by each of the information items for the respective streams, when the user equipment terminal or the base station apparatus performs transmission using plural antennas.

30

6. A base station apparatus for receiving, as control information transmitted irrespective of a presence or absence of an uplink data signal, channel state information representing a channel

state estimated by a user equipment terminal,
comprising:

5 a receiving unit configured to receive the
channel state information over plural transmission
time intervals;

a decoding unit configured to decode the
channel state information; and

10 a resource assigning unit configured to
assign resources based on the channel state
information.

15 7. The base station apparatus as claimed
in Claim 6, wherein:

when the channel state information is
arranged in descending order of the channel state,
the channel state information is divided into
20 information items, each of which can be transmitted
in a single transmission interval, and the channel
state information is encoded by each of the
information items, each of which can be transmitted
in the single transmission time interval,

25 the decoding unit decodes the channel
state information for each single transmission
interval, and

the resource assigning unit assigns
resources in descending order of the channel state
30 and, upon completing resource assignment, instructs
the decoding unit to stop decoding the channel state
information associated with the resources.

35

8. The base station apparatus as claimed

in Claim 6, wherein:

when the user equipment terminal or the
base station apparatus performs transmission using
plural antennas, the channel state information is
5 divided into information items for respective
streams, and the channel state information is
encoded by each of the information items for the
respective streams, and

the decoding unit decodes the channel
10 state information for each stream and, upon
completing decoding the stream, instructs the
resource assigning unit to start resource assignment
associated with the stream.

15

9. A channel state information
communication method for use in a mobile
20 communication system using a single carrier scheme
for uplink, comprising the steps of:

by a user equipment terminal,
estimating a channel state;
encoding channel state information

25 representing the estimated channel state;
transmitting, as control information
transmitted irrespective of a presence or absence of
an uplink data signal, the channel state information
over plural transmission time intervals;

30 by a base station apparatus,
receiving the channel state information
over plural transmission time intervals;
decoding the channel state information;

and

35 assigning resources based on the channel
state information.