

TITLE OF THE INVENTION

ADAPTER DEVICE, IMAGING APPARATUS, AND ACCESSORY

BACKGROUND OF THE INVENTION

Field of the Invention

[0001] The present invention relates to an adapter device, an imaging apparatus, and an accessory.

Description of the Related Art

[0002] Conventionally, accessories such as interchangeable lenses and so forth (camera accessories) are known to be able, when mounted to an imaging apparatus such as a digital camera (hereinafter, referred to as a "camera") or the like, to receive a supply of power from the camera and to enable communication of commands, data, and so forth between the accessory and the camera. It is known that multiple contacts (terminals) capable of electric connection, by coming into contact, are provided on both the camera and a mounting portion of the accessory, in order to enable the supply of power and the communication. There is also known a mounting system for mounting (coupling) the accessory to the camera employing so-called bayonet coupling, where mounts of both the camera and accessory are rotated relative to each other, and bayonet/mount claws provided on each

apparatus engage with the claws provided on the other apparatus.

[0003] Combinations that corresponding to each other are decided beforehand for cameras and accessories employing a mounting system such as described above. For example, corresponding accessories (e.g., interchangeable lenses, etc.) differ depending on the length of the flange focal distance of the camera. In other words, there are accessories that are not compatible with the flange focal distance of a given camera.

[0004] In a case where an accessory that is not compatible with a camera is mounted, problems may occur. For example, in a case where an interchangeable lens that is not compatible with a camera having a certain flange focal distance is mounted thereto an optical image of a subject entering via the interchangeable lens cannot be focused on the image plane of the camera or the like. Accordingly, there is a need to restrict the connecting of cameras and accessories in combinations that are mutually incompatible. In particular, in a case where multiple accessories that are compatible with different cameras have mount diameters that are generally the same, it is difficult to judge from the external appearance of the cameras and accessories whether they are a compatible combination or not.

[0005] Japanese Patent Laid-Open No. 2005-70712 proposes

a technology where a protrusion of a lens, that has the same flange focal distance but a short back focus, abuts a wall portion provided to a camera body, thereby preventing erroneous mounting of this lens to a camera body that cannot operate correctly with mounted lenses with short back focus.

SUMMARY OF THE INVENTION

[0006] An adapter device according to the present invention is an adapter device including a first mount on one side and a second mount on another side, where the first mount is detachably mountable to a first imaging apparatus, and the second mount is detachably mountable to a first accessory. The first mount has a first mount recess, a first mount claw, a second mount recess, a second mount claw, a third mount recess, and a third mount claw, disposed following a circumferential direction of the first mount. The second mount has a fourth mount claw, a fourth mount recess, a fifth mount claw, a fifth mount recess, a sixth mount claw, and a sixth mount recess, disposed following the circumferential direction of the second mount. The first, second, and third mount claws are insertable into corresponding mount recesses provided on a second imaging apparatus which is different from the first imaging apparatus, to detachably mount the first mount on the first

imaging apparatus. The fourth, fifth, and sixth mount claws are insertable into mount recesses provided to a second accessory which is different from the first accessory, to detachably mount the second mount on the first accessory. Each of the mount claws mount and mount recesses extends radially over an angle range in the circumferential direction of the mounts, where a smallest angle range out of angle ranges of the first, second, and third mount recesses is equal to or smaller than a smallest angle range out of angle ranges of the fourth, fifth, and sixth mount claws.

[0007] Further features of the present invention will become apparent from the following description of exemplary embodiments with reference to the attached drawings. Each of the embodiments of the present invention described below can be implemented solely or as a combination of a plurality of the embodiments. Also, features from different embodiments can be combined where necessary or where the combination of elements or features from individual embodiments in a single embodiment is beneficial.

BRIEF DESCRIPTION OF THE DRAWINGS

[0008] Figs. 1A and 1B are block diagrams of a camera accessory and imaging apparatus according to an embodiment of the present invention.

[0009] Figs. 2A and 2B are external perspective views of a camera body and a first lens unit according to an embodiment of the present invention.

[0010] Figs. 3A and 3B are disassembled perspective views of the camera body and the first lens unit according to an embodiment of the present invention.

[0011] Figs. 4A through 4C are diagrams exemplarily describing a case of viewing a camera mount according to an embodiment of the present invention from the photographer side of the camera body (rear face side of the camera body).

[0012] Figs. 5A and 5B are diagrams exemplarily describing engagement of the camera body and first lens unit by camera claws at a normal position of the camera body according to an embodiment of the present invention.

[0013] Figs. 6A and 6B are diagrams exemplarily describing engagement of the camera body and first lens unit by camera claws at a vertical position of the camera body according to an embodiment of the present invention.

[0014] Figs. 7A and 7B are diagrams exemplarily describing a case of viewing a lens mount according to an embodiment of the present invention from the rear face side in a state where the first lens unit is mounted to the camera body (side where the camera body is mounted).

[0015] Figs. 8A and 8B are external perspective views viewing the camera mount according to an embodiment of the

present invention from the front face side (subject side).

[0016] Figs. 9A and 9B are external perspective views of the lens mount according to an embodiment of the present invention, as viewed from the side to which the camera mount is mounted (rear face side).

[0017] Figs. 10A and 10B are diagrams exemplarily describing a contact state between terminals on the camera body and first lens unit according to an embodiment of the present invention.

[0018] Figs. 11A and 11B are diagrams describing a first conversion adapter that is mountable to the camera body, and a second lens unit.

[0019] Figs. 12A and 12B are diagrams describing a second conversion adapter that is mountable to a camera body, and the first lens unit.

[0020] Figs. 13A through 13C is a diagram for exemplarily describing angle so disposing bayonet claws in a camera mount provided on one end of the first conversion adapter.

[0021] Figs. 14A and 14B are diagrams exemplarily describing angle so disposing bayonet claws in the lens mount provided on the other end of the first conversion adapter.

[0022] Figs. 15A and 15B are diagrams exemplarily describing a mounting method of a predetermined imaging apparatus and a predetermined lens unit having claws and

recesses that interfere with each other.

[0023] Figs. 16A and 16B are diagrams exemplarily describing the way in which claws interfere with each other when attempting to mount the lens mount side to the camera mount side according to an embodiment of the present invention.

[0024] Figs. 17A through 17D is a diagram exemplarily describing a case of attempting to insert incompatible claws into recesses at the lens mount side and camera mount side according to an embodiment of the present invention.

[0025] Figs. 18A and 18B are diagrams exemplarily describing angle so disposing bayonet claws in the camera mount provided on one end of the second conversion adapter.

[0026] Figs. 19A through 19C are diagrams exemplarily describing angle so disposing bayonet claws in a lens mount provided on the other end of the second conversion adapter.

[0027] Figs. 20A and 20B are diagrams exemplarily describing the way in which claws interfere with each other, when attempting to mount a reference claw at the lens mount side to a reference recess at the camera mount side according to an embodiment of the present invention.

[0028] Figs. 21A through 21D are diagrams exemplarily describing the way in which claws interfere with each other, when attempting to mount a claw other than the reference claw at the lens mount side to a reference recess at the

camera mount side according to an embodiment of the present invention.

[0029] Fig. 22 is a diagram exemplarily describing a state in which claws provided to the camera mount side and lens mount side according to an embodiment of the present invention are engaged.

[0030] Fig. 23 is a disassembled perspective view of a mount mechanism according to a modification of the present invention.

[0031] Figs. 24A through 24C are diagrams for exemplarily describing a non-coupled state of the mount mechanism according to the modification of the present invention.

[0032] Figs. 25A through 25C are diagrams for exemplarily describing a coupled state of the mount mechanism according to the modification of the present invention.

DESCRIPTION OF THE EMBODIMENTS

[0033] Figs. 1A and 1B are block diagrams of a camera accessory and imaging apparatus according to an embodiment of the present invention. Fig. 1A is a diagram exemplarily describing a camera system including a first lens unit (hereinafter referred to as first lens) 100, serving as an accessory according to the embodiment of the present invention, and a camera body 10 serving as a first imaging

apparatus to which the first lens 100 can be directly detachably attached. Also, Fig. 1B is a diagram describing the configuration of a mount portion 1 formed by the mounts in both the first lens 100 and the camera body 10. That is in Figs. 1A and 1B, the mounts provided on the first lens 100 and the mounts provided on the camera body 10 are collectively referred to as the mount portion 1. The mounts provided to the first lens 100 and camera body 10 will be described later.

[0034] As illustrated in Fig. 1A, the camera body 10 has a charge-accumulation type solid-state imaging device (hereinafter referred to simply as sensor) 11, such as a complementary metal-oxide semiconductor (CMOS) sensor or the like, that performs photoelectric conversion of an optical image of a subject guided by a photography lens group 101 provided on the inner side of the first lens 100, and outputs electric signals. The camera body 10 also has an A/D conversion unit 12 that converts analog electric signals output from the imaging sensor 11, and an image processing unit 13 that generates image signals by performing various types of image processing on the digital signals. The image signals (still image and moving image) generated at the image processing unit 13 can be displayed on a display unit 14, and recorded in a recording medium 15.

[0035] The camera body 10 also has memory 16. This

memory 16 serves as a buffer for performing processing on image signals, and also stores operation programs (computer programs) that a later-described camera control unit 18 uses.

[0036] The camera body 10 also has a camera operating input unit 17 including a power source switch for turning the power source on/off, a photography switch (release switch) for starting recording of image signals, and selection/settings switches for performing various types of menu settings, and so forth. The camera body 10 also has the camera control unit 18 including a microprocessor central processing unit (CPU) serving as a computer) that centrally controls the operations of the camera body 10 and first lens 100. The camera control unit 18 performs various types of settings based on signals input from the camera operating input unit 17, for example, and controls communication with a lens control unit 103 provided to the first lens 100 via the mount portion 1.

[0037] On the other hand, the first lens 100 has the photography lens group 101 that is an optical member having multiple lens groups such as a zoom lens, shift lens, focus lens, and so forth, and light amount adjustment members such as a diaphragm and so forth. The first lens 100 has actuators for moving or operating optical members such as the multiple lens groups and diaphragm and so forth, and also has a lens drive unit 102 that drives the actuators.

The first lens 100 also has the lens control unit 103 including a microprocessor (logical CPU (LCPU)) for lenses, that centrally controls operations of the first lens 100. The lens control unit 103 controls the lens drive unit 102 by communicating with the camera control unit 18 via the mount portion 1, for example.

Basic Configuration of Mount Portion 1

[0038] Next, the configuration of the mount portion 1 including a camera mount face A provided on the camera body 10 side, and an accessory mount face B provided on the first lens 100 side, will be described with reference to Fig. 1B. Note that the camera mount and accessory mount include a locking mechanism, a mount holding mechanism, and multiple electric terminals. The mounts will be described in detail later.

[0039] The mount portion 1 has multiple terminals that are capable of electrically connecting the camera body 10 and the first lens 100 to each other, as illustrated in Fig. 1B. The multiple terminals are, at the camera mount face A, exposed to the outside of the camera body 10 as multiple camera-side contact pins provided to a contact holding member 203. The multiple terminals also are, at the accessory mount face B, exposed to the outside of the camera accessory (e.g., first lens 100) as multiple accessory-side contact faces provided to a contact face holding member 303.

The contact pins and the contact faces of the camera body 10 side and the camera accessory (e.g., first lens 100) side are electrically connected among mutually corresponding contacts, in a state where the camera accessory is mounted to the camera body 10.

[0040] A camera power source unit 19 generates communication control power source (VDD) as power source to be supplied to a mounted camera accessory via a VDD terminal, and power source to be supplied to a first communication I/F unit 21a via a power source switching unit 20. The camera power source unit 19 also generates driving power source (VBAT) as power source to be supplied to the mounted camera accessory via a VBAT terminal.

[0041] The camera power source unit 19 generates a 3.3 V power source as a power source to be supplied to the camera control unit 18, first communication I/F unit 21a, and a second/third communication I/F unit 21b. The camera power source unit 19 also generates 3.0 V power source as a power source to be supplied to the first communication I/F unit 21a and second/third communication I/F unit 21b via the power source switching unit 20.

[0042] The power source switching unit 20 is connected to the camera power source unit 19. The power source switching unit 20 supplies only one or the other of the VDD and 3.0 V power source, generated at the camera power source unit 19,

to the first communication I/F unit 21a as power source Vs for communication interface. Switching of power source voltage is executed following instructions from the camera control unit 18.

[0043] Next, a lens power source 104 generates a 3.0 V power source, as a power source voltage for supply to the lens control unit 103 and a lens-side I/F unit 106, based on VDD supplied from the camera body 10 side. In a state where the first lens 100 is mounted to the camera body 10, driving power source (VBAT) is supplied to a drive circuit unit 105 at the first lens 100 side, via a VBAT terminal from the above-described camera power source unit 19.

[0044] Although the power source voltage for the lens control unit 103 and lens-side I/F unit 106 is the same (3.0 V) in the present embodiment, a configuration may be made where the voltage level that the lens control unit 103 exhibits is 3.3 V. In this case, there is the need to supply power source of a voltage level of 3.0 V and 3.3 V to the lens-side I/F unit 106, so the lens power source 104 generates power sources of 3.0 V and 3.3 V.

[0045] Hereafter, the functions of the terminals common to both the camera mount face A and accessory mount face B will be described. VDD terminals 203a and 303a are terminals that supply communication control power source (VDD) as communication power primarily used for

communication control, to the camera accessory (e.g., the first lens 100) from the camera body 10. Note that while the voltage of power source supplied to the first lens 100 is 5.0 V, the voltage of supplied power source will change depending on the type of accessory mounted to the camera body 10.

[0046] VBAT terminals 203b and 303b are terminals that supply driving voltage source (VBAT) that is driving power used for operating the mechanical driving units of the actuators used for driving the diaphragm and focus lens, from the camera side to the camera accessory side. In other words, the VBAT terminals 203b and 303b are terminals used to supply power source other than the above-described communication power. Note that the voltage of the power source serving as driving power supplied to the first lens 100 is 4.25 V. The VDD terminals 203a and 303a and VBAT terminals 203b and 303b described above are power source terminals for supplying power source from the camera body 10 to the camera accessory, for example.

[0047] DGND terminals 203m and 303m are grounding terminals (GND terminals) corresponding to the communication control power source VDD. Note that grounding in the present embodiment means to set the voltage level of the grounding terminals to generally the same level as the negative pole side of the power source such as a battery or

the like.

[0048] PGND terminals 203d and 303d are grounding terminals for connecting the camera body 10, and a mechanical drive system including motors (actuators) and the like provided to a camera accessory (e.g., the first lens 100), to ground level. That is to say, the PGND terminals 203d and 303d are grounding terminals (GND terminals) corresponding to the driving power source VBAT. The DGND terminals 203m and 303m and PGND terminals 203d and 303d described above are grounding terminals for grounding various types of power source systems in the camera body 10 and accessory to the ground level.

[0049] MIF terminals 203e and 303e are terminals for detecting that the camera accessory (e.g., the first lens 100) has been mounted to the camera body 10. In the present embodiment, the MIF terminals 203e and 303e detect that the first lens 100 has been mounted to the camera body 10.

[0050] The camera control unit 18 detects that the camera accessory has been mounted to or detached from the camera body 10, by detecting the voltage level that the MIF terminals 203e and 303e indicated. Based on this detection, the camera control unit 18 starts supply of power source to power source terminals after having detected mounting of the camera accessory, for example, and effects control to start communication between the camera body 10 and camera

accessory.

[0051] TYPE terminals 203c and 303c are terminals for distinguishing the type of camera accessory (e.g., the first lens 100) mounted to the camera body 10. The camera control unit 18 detects the value of voltage of signals indicated by the TYPE terminals 203c and 303c, and distinguishes the type of camera accessory mounted to the camera body 10 based on this value. Note that the first lens 100 is pull-down connected to the DGND terminal at a predetermined resistance value. This resistance value differs depending on the type of the camera accessory.

[0052] Next, description will be made regarding various types of communication terminals between the camera body 10 and the camera accessory. Note that the multiple communication terminals provided to the mount portion 1 are divided into multiple communication systems (groups), and each communication system is capable of performing communication independently. In the present embodiment, LCLK terminals 203h and 303h, DCL terminals 203f and 303f, and DLC terminals 203g and 303g, are a first communication system that performs first communication. DLC2 terminals 203i and 303i are a second communication system that performs second communication, which is independent from the first communication. Further, CS terminals 203k and 303k, and DCA terminals 203j and 303j are a third communication

system that performs third communication, which is independent from the first and second communication. In the present embodiment, the camera control unit 18 and lens control unit 103 can perform communication independently with the first through third, via the above-described multiple communication terminals.

[0053] LCLK terminals 203h and 303h are terminals of the first communication system, and are terminals for communication clock signals output from the camera body 10 to the camera accessory (e.g., the first lens 100), and terminals for the camera body 10 to monitor the busy state of the accessory. DCL terminals 203f and 303f are terminals of the first communication system, and are communication data terminals for performing bidirectional communication between the camera body 10 and the camera accessory (e.g., the first lens 100). DLC terminals 203g and 303g are terminals of the first communication system, and are terminals for communication data output from the camera accessory (e.g., the first lens 100) to the camera body 10.

[0054] The above-described LCLK terminals, DCL terminals, and DLC terminals, corresponding to the first communication system, can switch the signal output format between so-called CMOS output type and open type. In the present embodiment, the CMOS output type has switch output of voltage at both H (High) and L (Low). In comparison with

this, the open type has switch output at only the L side. Although open type in the present embodiment means the so-called open drain type, this may be the open collector type.

[0055] DLC2 terminals 203i and 303i are terminals of the second communication system, and are terminals for communication data output from the camera accessory (e.g., the first lens 100) to the camera body 10. DCA terminals 203j and 303j are terminals of the third communication system, and are terminals for communication data for performing bidirectional communication between the camera body 10 and the camera accessory (e.g., the first lens 100). CS terminals 203k and 303k are terminals of the third communication system, and are signals terminals for communication requests between the camera body 10 and camera accessory (e.g., the first lens 100). Note that in the present embodiment, in a case where the first lens 100 is mounted to the camera body 10, the communication voltage at the corresponding terminals in the first through third communication systems is 3.0 V.

Configuration of Camera Mount and Accessory Mount

[0056] The configuration of the camera mount 201 and the lens mount (accessory mount) 301 according to the present embodiment will be described with reference to Figs. 2A through 3B. Note that in the following description, the mount provided to the imaging apparatus side will be

referred to as camera mount, and the mount provided to the lens unit side will be referred to as lens mount. Further, of mounts on a later-described conversion adapter, the side that is mounted to the imaging apparatus will be referred to as lens mount, and the side mounted to the lens unit will be referred to as camera mount. Note that in the following description, a second conversion adapter 70 has a camera mount 1201 that is the same as the camera mount 201 of the camera body 10. And note that in the following description, a first conversion adapter 40 has a lens mount 1301 that is the same as the lens mount 301 of the first lens 100.

[0057] Figs. 2A and 2B are external perspective views of the camera body 10 and first lens 100 according to the embodiment of the present invention. Fig. 2A illustrates a state in which the first lens 100 is mounted to the camera body 10, and Fig. 2B illustrates a state in which the first lens 100 has been removed from the camera body 10.

[0058] As illustrated in Figs. 2A and 2B, the camera body 10 and first lens 100 have a ring-shaped camera mount 201 and ring-shaped lens mount 301, which each have contact faces which are parallel in a direction orthogonal to the optical axis and as such are arranged to cooperate with each other in use. Although the camera mount 201 and the lens mount 301 are ring shaped, this is not restrictive in the present embodiment. For example, a configuration may be

employed in the configuration where this is realized by each of the camera mount 201 and lens mount 301 having arc-shaped contact faces. In other words, a configuration may be employed where this is realized by the camera mount 201 and the lens mount 301 having a part of the contact face notched out. Note that the above-described optical axis is parallel to a center axis passing through the center of an aperture of the camera mount and lens mount. In the present embodiment, the center axis of the camera mount 201 and the center axis of the lens mount 301 are same as each optical axis of the camera mount 201 or lens mount 301. In the present embodiment, a configuration may be employed where this is realized by differing the center axis of the mount from the optical axis. By rotating the camera body 10 and first lens 100 relative to each other, in a state where the reference faces of each of the camera mount 201 and lens mount 301 are in contact with each other, from an unlocked position to a locked position, the first lens 100 is mounted to the camera body 10. This will be described in detail later.

[0059] Figs. 3A and 3B are disassembled perspective views of the camera body 10 and first lens 100 according to the embodiment of the present invention. Fig. 3A illustrates a disassembled perspective view of the camera body 10, and Fig. 3B illustrates a disassembled perspective view of the first

lens 100.

[0060] As illustrated in Fig. 3A, a first optical axis 3000 indicates a light flux passing through the center of the camera mount 201 of the camera body 10 as illustrated in Fig. 3A. Also, as illustrated in Fig. 3B, an optical axis 3001 is an axis for exemplarily describing a light flux representing an optical image of a subject that is guided by the first lens 100. When the first lens 100 is mounted to the camera body 10, the first optical axis 3000 and optical axis 3001 described above match, and optical fluxes corresponding to these optical axes enter the imaging sensor 11 and are imaged, thereby imaging a subject image.

[0061] A lock pin 202 is a first restricting member (lock member) for restricting (locking) the mounted state of the camera body 10 and camera accessory. Note that the lock pin 202 is capable of advancing and retreating in a direction parallel to the first optical axis 3000. Specifically, when the first lens 100 is mounted to the camera body 10, the lock pin 202 enters a lock groove 301z that is a second restricting member provided to the lens mount 301, and locks the state of the first lens 100 being mounted to the camera body 10. The locking of the first lens 100 mounted to the camera body 10 can be disengaged by the user operating a lock disengaging member (omitted from illustration) connected to the lock pin 202, thereby retracting the lock

pin 202 from the lock groove 301z. Note that even in a case of further rotating the first lens 100 and camera body 10 relative to each other in the mounting direction with the lock disengaging member operated, rotation beyond a lock abutting face 301y is restricted (see Fig. 7A).

[0062] The contact holding member 203 is a holding unit for holding later-described (see Figs. 8A and 8B) multiple contact pins (contact faces) 203a through 203k and 203m, provided on the camera body 10 side. Note that in the present embodiment, the contact pins and contact faces corresponding to the above-described terminals are denoted by the same part numerals as the terminals for the sake of description.

[0063] A camera body member 204 is a camera housing that holds the members of the camera body 10. Specifically, the above-described camera mount 201 and contact holding member 203 are fastened to the camera body member 204 by camera mount fastening screws 205a through 205d and contact holding member fastening screws that are omitted from illustration. Camera mount fastening screws 205a through 205d are positioned where none of multiple leaf springs 206a, 206b, and 206c are positioned in the camera mount 201. Furthermore, camera mount fastening screws 205a through 205d are exposed at the contact faces of the camera mount 201 which is contact with the contact face of the lens mount 301.

Although the camera body member 204 holds an unshown imaging unit to which the aforementioned imaging sensor 11 is mounted, and a shutter unit that is omitted from illustration, description will be omitted.

[0064] A lens mount biasing member 206 is a biasing unit at the imaging apparatus side to pull lens claws 301d and 301e, which are multiple bayonet claws provided to the later-described lens mount 301, toward the camera mount 201 side. Specifically, the lens mount biasing member 206 has multiple leaf springs 206a, 206b, and 206c, and the bayonet claws provided to the first lens 100 are biased in the optical axis direction by the leaf springs. Note that the lens mount biasing member 206 is held between the camera mount 201 and camera body member 204 in a space formed therebetween.

[0065] Next, a front lens 101a and rear lens 101b are optical members making up the photography lens group 101, as illustrated in Fig. 3B. While the photography lens group 101 has multiple lenses, only the front lens 101a disposed at the subject-side end and the rear lens 101b disposed at the camera body 10 side end are illustrated in the present embodiment to simplify description.

[0066] A lens barrel 302 is a holding member that holds the photography lens group 101. Note that the lens mount 301 is fastened to the lens barrel 302 by lens mount

fastening screws 304a through 304d. A contact face holding member 303 is a holding unit for holding multiple contact faces 303a through 303k and 303m provided to a later-described (see Figs. 9A and 9B) first lens 100 side. The contact face holding member 303 is fastened to the lens mount 301 by lens contact holding portion fastening screws 305a and 305b.

Configuration of Bayonet Claws at Camera Body 10 Side

[0067] Next, the multiple bayonet claws provided to the camera mount 201 at the camera body 10 side will be described with reference to Figs. 4A through 6B. Figs. 4A through 4C are diagrams exemplarily describing a case of viewing the camera mount 201 according to the embodiment of the present invention from the photographer side (rear face side of the camera body 10) of the camera body 10. Fig. 4A is a diagram illustrating angle ranges that camera mount claws (hereinafter referred to simply as camera claws) and camera mount recesses (hereinafter referred to simply as camera recesses) having the lock pin 202 as a reference occupy in the circumferential direction of the camera mount 201. The camera recesses of the camera mount 201 are notch portions between adjacent camera claws. Camera recesses of the camera mount 201 are formed further toward the outside in the radial direction from the center axis of the camera mount 201 than the camera claws of the camera mount 201.

Also, lens recesses of the lens mount 301 are formed further toward the inside in the radial direction from the center axis of the lens mount 301 than the lens claws of the lens mount 301. Fig. 4B is a diagram illustrating angle ranges that multiple camera claws 201a through 201c occupy in the circumferential direction of the camera mount 201. Fig. 4C is a cross-sectional diagram taken along cross-section IVC-IVC in Fig. 4B.

[0068] Note that in the following description, protrusions protruding from recesses in the inner radial direction at the camera mount side will be referred to as camera claws, and protrusions protruding from recesses in the outer diameter direction at the later-described lens mount (accessory mount) side will be referred to as lens mount claws. In the following description, the side of the camera mount 201 as viewed from the side of the photographer (rear face of the camera body 10) of the camera body 10 will be referred to as rear face side, and the opposite side will be referred to as front face side (or camera accessory side). It should be noted that in the following description, description will be made with a case of viewing the camera mount 201 from the rear face side as a reference, but in a case of viewing the camera mount 201 from the front face side, angles and directions stipulating angles (clockwise, etc.) will be reversed.

[0069] A first camera claw 201a, second camera claw 201b, and third camera claw 201c, are provided in order, to the camera mount 201 in the circumferential direction (inner radial direction), as illustrated in Figs. 4A and 4B. When viewing the camera mount 201 from the rear face side as illustrated in Figs. 4A and 4B, the camera claw that is provided at a position farthest from the lock pin 202 is the first camera claw 201a. The second camera claw 201b and third camera claw 201c are then consecutively provided in order from the first camera claw 201a in a clockwise direction.

[0070] Also, recesses which are a first camera recess 201d, second camera recess 201e, and third camera recess 201f are provided in order, to the camera mount 201 in the circumferential direction (inner radial direction). When viewing the camera mount 201 from the rear face side as illustrated in Figs. 4A and 4B, the recess that is provided at a position nearest to the lock pin 202 is the second camera recess 201e. The third camera recess 201f and first camera recess 201d are then consecutively provided in order from the second camera recess 201e in a clockwise direction.

[0071] As illustrated in Fig. 4C, a fitting member 201x that restricts movement of the camera accessory in a direction parallel to the optical axis when the camera accessory is mounted, is provided to the camera mount 201

side in the circumferential direction. In the present embodiment, the diameter of the fitting member 201x in a direction orthogonal to the optical axis at the camera mount 201 is the mount diameter.

[0072] To mount the first lens 100 to the camera body 10, first, the camera claws of the camera body 10 are inserted into the lens mount recesses of the first lens 100, and the lens mount claws at the first lens 100 side are inserted into the camera recesses at the camera body 10 side. This state is a mounting start state (first state). Note that in the following description, accessory mount recesses will be referred to simply as accessory recesses, and accessory mount claws will be reference to simply as accessory claws. For example, in the case of the lens mount 301, this is lens recesses and lens claws.

[0073] The camera mount 201 and lens mount 301 are then rotated relative to each other from the mounting start state, whereby the camera claws and lens claws engage in the radial direction orthogonal to the optical axis, and transition to a state where the lens claws are biased by the above-described lens mount biasing member 206. In this state, relative positional relation between the camera body 10 and the first lens 100 transitions to a locked state where the lock pin 202 has fit into the lock groove 301z as described above. This state is a mounting complete state (second

state). Note that in the mounting complete state, contact of corresponding terminals at the camera mount 201 and lens mount 301 is complete.

[0074] As described above, the camera claws and accessory claws are so-called bayonet claws, and as described above, have shapes so that the first lens 100 can be mounted (can be coupled) to the camera body 10 by the so-called bayonet coupling method by engaging of the camera claws and accessory claws.

[0075] Note that the end portions of the camera claws 201a, 201b, and 201c, in the circumferential direction, will be referred to as first end portion 201a1, second end portion 201a2, third end portion 201b1, fourth end portion 201b2, fifth end portion 201c1, and sixth end portion 201c2, for the same of description. The end portions are denoted with part numerals in order from the first camera claw 201a in the clockwise direction, when viewing the camera mount 201 from the rear face side, as described above.

[0076] As illustrated in Fig. 4A, the angles that the camera claws and camera recesses occupy in the circumferential direction of the camera mount 201 (angle ranges) are stipulated as follows in the present embodiment. For the first camera claw 201a, the angle $\theta_a = 48^\circ$, for the second camera claw 201b, the angle $\theta_b = 40^\circ$, and for the third camera claw 201c, the angle $\theta_c = 92^\circ$. Also, for the

first camera recess 201d, the angle is 57° , for the second camera recess 201e, the angle is 66° , and for the third camera recess 201f, the angle is 57° .

[0077] Also, when viewing the camera claws from the rear face side of the camera body 10, the angles in the clockwise direction where the camera claws are disposed in the circumferential direction of the camera mount 201 with the position of the lock pin 202 (referred to as reference position) as a reference are stipulated as follows. The first camera claw 201a is disposed between 169° to 217° with the reference position as a start point. The second camera claw 201b is disposed between 274° to 314° with the reference position as a start point. The third camera claw 201c is disposed between 20° to 112° with the reference position as a start point.

[0078] Now, when viewing the camera mount 201 from the optical axis direction in the present embodiment, of the multiple bayonet claws, the third camera claw 201c overlaps a first camera mount center line 3003 that extends in the vertical direction from the center axis parallel with the optical axis of the camera mount 201 in the radial direction of the camera mount 201. Note that the first camera mount center line 3003 is a line that, in a normal position of the camera body 10 where the lock pin 202 is situated at the left side when viewing the camera mount 201 from the front

face side, extends in the gravitational direction and the opposite direction from the gravitational direction, from the center (optical axis) of the camera mount 201. That is to say, the first camera mount center line 3003 is a vertical line that passes through the optical axis in a normal position of the camera. In other words, the first camera mount center line 3003 is a vertical line that passes through the center of the camera mount 201 and orthogonal to the center axis of the camera mount 201 when the camera body 10 is placed on a horizontal plane.

[0079] As opposed to this, a line that, in a vertical position of the camera body 10 where the lock pin 202 is situated at the top side when viewing the camera mount 201 from the front face side, extends in the gravitational direction and the opposite direction from the gravitational direction, from the center (optical axis) of the camera mount 201, is a second camera mount center line 3002. That is to say, the second camera mount center line 3002 is a horizontal line that passes through the optical axis when the camera body 10 is in the normal position. The second camera mount center line 3002 overlaps the lock pin 202 and first camera claw 201a in the radial direction of the lens mount 201. Note that the first camera mount center line 3003 and the second camera mount center line 3002 are generally orthogonal.

[0080] Figs. 5A and 5B are diagrams exemplarily describing engagement of the camera body 10 and first lens 100 by camera claws at a normal position of the camera body 10 according to the embodiment of the present invention. Fig. 5A is a diagram viewing a state where the first lens 100 is mounted to the camera body 10 from the front face side. Fig. 5B is a partial cross-sectional view of the camera body 10 and first lens 100 taken along cross-section VB-VB in Fig. 5A. Note that in Figs. 5A and 5B, the camera body 10 is positioned in the above-described normal position, and, in this state, a camera grip 204a provided to the camera body member 204 is situated to the left side when viewing the camera body 10 from the front face side.

[0081] Figs. 6A and 6B are diagrams exemplarily describing engagement of the camera body 10 and first lens 100 by bayonet claws at a vertical position of the camera body 10 according to the embodiment of the present invention. Fig. 6A is a diagram viewing a state where the first lens 100 is mounted to the camera body 10 from the front face side. Fig. 6B is a partial cross-sectional view of the camera body 10 and first lens 100 taken along cross-section VIB-VIB in Fig. 6A. Note that in Figs. 6A and 6B, the camera body 10 is positioned in the above-described vertical position, and the camera grip 204a in this state is situated to the top side when viewing the camera body 10 from the

front face side.

[0082] Generally, in a case of mounting an interchangeable lens to a camera, a gap occurs between the camera and interchangeable lens in a direction orthogonal to the optical axis, due to dimensional tolerance of the two, and looseness of the lens as to the camera increases due to this gap. Particularly, in a case of coupling a camera and interchangeable lens by bayonet coupling, the looseness of the lens is greater the farther away from positions where the bayonet claws engage each other in the circumferential direction of the lens. Also, the looseness in the gravitational direction (bowing) of the interchangeable lens as to the camera is greater due to the weight of the interchangeable lens itself. Accordingly, if a subject is imaged in a case where the looseness of the interchangeable lens as to the camera is great, an unnatural image may be obtained that is unintended by the user, due to the deviation of optical axis of the camera and optical axis of the lens.

[0083] Accordingly, in the present embodiment, the third camera claw 201c that has the widest angle of the camera-side bayonet claws overlaps the first camera mount center line 3003 in the radial direction of the camera mount, as illustrated in Fig. 5B. According to this configuration, when the first lens 100 is mounted to the camera body 10,

the first camera mount center line 3003 overlaps the position where the third camera claw 201c and a later-described third lens claw 301f are engaged. In this case, looseness (bowing) of the camera accessory such as the first lens 100 or the like mounted to the camera body 10 in the gravitational direction, can be suppressed in the normal position of which the frequency of usage is highest for operating the imaging apparatus, for example. Due to the above-described configuration, the gap $\Delta 1$ illustrated in Fig. 5B can be kept from becoming large, so looseness of the first lens 100 as to the camera body 10 in the direction indicated by the arrow in Fig. 5B can be suppressed.

[0084] Also, in the present embodiment, the first camera claw 201a overlaps the second camera mount center line 3002, as illustrated in Fig. 6B in the radial direction of the camera mount 201. According to this configuration, when the first lens 100 is mounted to the camera body 10, the second camera mount center line 3002 overlaps the position where the first camera claw 201a and a later-described first lens claw 301d are engaged. In this case, looseness (bowing) of the camera accessory such as the first lens 100 or the like mounted to the camera body 10 in the gravitational direction, can be suppressed in the vertical position of the imaging apparatus as well, for example. Due to the above-described configuration, the gap $\Delta 2$ illustrated in Fig. 6B can be kept

from becoming large, so looseness of the first lens 100 as to the camera body 10 in the direction indicated by the arrow in Fig. 6B can be suppressed.

[0085] Also, the angle of the third camera claw 201c in the circumferential direction of the camera mount 201, situated at the top side in a case where the camera body 10 is at the normal position, is greater than the sum of angles of the first claw 201a and second claw 201b situated at the lower side, as illustrated in Fig. 4B. More precisely, the total sum of angles in the circumferential direction of the camera claws provided to the camera mount 201 is greater at the upper side of the second camera mount center line as a reference as compared to the lower side. Specifically, the sum of angle θ_c and the angle θ_{a1} of the first camera claw 201a on the upper side of the second camera mount center line 3002 is larger than the sum of angle θ_b and the angle θ_{a2} of the first camera claw 201a on the lower side of the second camera mount center line 3002. That is to say, the layout of the camera claws and recesses is decided so as to satisfy the two following expressions.

$$\theta_c \geq \theta_a + \theta_b \quad \dots(1)$$

$$\theta_{a1} + \theta_c > \theta_{a2} + \theta_b \quad \dots(2)$$

[0086] According to this configuration, in the normal position of the camera body 10 regarding which the frequency of usage is highest, the strength of camera claws at the

upper side of the second camera mount center line 3002 (opposite side from the gravitational direction) that indicates the horizontal direction of the camera mount 201 can be made to be greater than the camera claws at the lower side (gravitational direction). Accordingly, in the normal position of the camera body 10 regarding which the frequency of usage is highest in a state where the first lens 100 is mounted, the camera body 10 according to the present embodiment can reduce looseness (bowing) of the first lens 100 as to the camera body 10 in the gravitational direction. Also, according to the camera body 10 of the present embodiment, in the normal position of the camera body 10 regarding which the frequency of usage is highest in a state where the first lens 100 is mounted, deformation of camera claws and lens claws due to the weight of the first lens 100 itself can be suppressed.

Configuration of Bayonet Claws at First Lens 100 Side

[0087] Next, multiple lens claws (accessory claws) provided to the lens mount 301 at the first lens 100 side will be described with reference to Figs. 7A and 7B. Figs. 7A and 7B are diagrams exemplarily describing a case of viewing the lens mount 301 according to the embodiment of the present invention from the rear face side in a state where the first lens 100 is mounted to the camera body 10 (side where the camera body 10 is attached). Fig. 7A

exemplarily describes angles of the claws and recesses in the circumferential direction at the lens mount 301 side, and Fig. 7B is a cross-sectional view taken along cross-section VIIB-VIIB in Fig. 7A. Note that in the following description, the camera body 10 is positioned in the normal position in the state illustrated in Figs. 7A and 7B.

[0088] A first lens claw 301d, second lens claw 301e, and third lens claw 301f, are provided in order, to the lens mount 301 in the circumferential direction (inner radial direction), as illustrated in Figs. 7A. When viewing the lens mount 301 from the rear face side as illustrated in Fig. 7A, the lens claw that is provided at a position farthest from the lock groove 301z is the first lens claw 301d. The second lens claw 301e and third lens claw 301f are then consecutively provided in order from the first lens claw 301d in a clockwise direction.

[0089] Also, recesses which are a first lens recess 301a, second lens recess 301b, and third lens recess 301c are provided in order, to the lens mount 301 in the circumferential direction (inner radial direction). When viewing the lens mount 301 from the rear face side as illustrated in Fig. 7A, the recess that is provided at a position nearest to the lock groove 301z is the third lens recess 301c. The first lens recess 301a and second lens recess 301b are then consecutively provided in order from

the third lens recess 301c in a clockwise direction.

[0090] As illustrated in Fig. 7B, a fitting member 301x that restricts movement in a direction parallel to the optical axis of the imaging apparatus when mounted on the imaging apparatus, is provided to the lens mount 301 side in the circumferential direction. In the present embodiment, the diameter of the fitting member 301x in a direction orthogonal to the optical axis at the lens mount 301 side is the mount diameter.

[0091] Note that the end portions of the lens claws 301d, 301e, and 301f, in the circumferential direction, will be referred to as first end portion 301d1, second end portion 301d2, third end portion 301e1, fourth end portion 301e2, fifth end portion 301f1, and sixth end portion 301f2. The end portions are denoted with part numerals in order from the first lens claw 301d in the clockwise direction, when viewing the lens mount 301 from the rear face side, as described above.

[0092] As illustrated in Fig. 7A, the angles that the lens claws and lens recesses occupy in the circumferential direction of the lens mount 301 (angle ranges) are stipulated as follows in the present embodiment. For the first lens claw 301d, the angle $\theta_d = 53^\circ$, for the second lens claw 301e, the angle $\theta_e = 62^\circ$, and for the third lens claw 301f, the angle $\theta_f = 53^\circ$. Also, for the first lens recess

301a, the angle is 52° , for the second lens recess 301b, the angle is 44° , and for the third lens recess 301c, the angle is 96° .

[0093] Also, when viewing the lens claws from the rear face side, the angles where the lens claws are disposed in the circumferential direction of the lens mount 301 with the position of the lock groove 301z (referred to as reference position) as a reference in the clockwise direction are stipulated as follows. The first lens claw 301d is disposed between 159° to 212° with the reference position as a start point. The second lens claw 301e is disposed between 256° to 318° with the reference position as a start point. The third lens claw 301f is disposed between 54° to 107° with the reference position as a start point.

[0094] Now, when viewing the lens mount 301 from the optical axis direction in the present embodiment, of the multiple bayonet claws, the second lens claw 301e overlaps a first lens mount center line 3005 that extends in the vertical direction of the lens mount 301, in the radial direction of the lens mount 301. Also, when viewing the lens mount 301 from the rear face side and front face side in the present embodiment, of the multiple bayonet claws, the third lens claw 301f overlaps the first lens mount center line 3005 in the radial direction of the lens mount 301.

[0095] Note that the first lens mount center line 3005 is a line that, in a normal position of the camera body 10 to which the first lens 100 has been mounted, extends in the gravitational direction and the opposite direction from the gravitational direction, from the center (optical axis) of the camera mount 301. In other words, the first lens mount center line 3005 is a vertical line that passes through a center of the lens mount 301 and is orthogonal to the center axis of the lens mount 301 when the camera body 10 to which the first lens 100 is attached is placed on a horizontal plane. As opposed to this, a line that, in a vertical position of the camera body 10 to which the first lens 100 has been mounted, extends in the gravitational direction and the opposite direction from the gravitational direction, from the center (optical axis) of the camera mount 301, is a second lens mount center line 3006. This second lens mount center line 3006 overlaps the lock groove 301z and first lens claw 301d in the radial direction of the lens mount 301. Note that the first lens mount center line 3005 and second lens mount center line 3006 are mutually orthogonal.

[0096] In the present embodiment, when the first lens 100 is mounted to the camera body 10, the second lens claw 301e and third lens claw 301f overlap the first lens mount center line 3005 in the radial direction of the lens mount 301, as illustrated in Fig. 7A. According to this configuration,

when the first lens 100 is mounted to the camera body 10, the first lens mount center line 3005 overlaps two positions of engaging positions between lens claws and camera claws. In this case for example, in the normal position of the imaging apparatus 10 regarding which the frequency of usage is highest, looseness (bowing) of the first lens 100 mounted to the camera body 10 in the gravitational direction can be reduced.

[0097] Also, in the present embodiment, when the first lens 100 is mounted to the camera body 10, the first lens claw 301d overlaps the second lens mount center line 3006 in the radial direction of the lens mount 301, as illustrated in Fig. 7A. According to this configuration, when the first lens 100 is mounted to the camera body 10 the second lens mount center line 3006 overlaps the position where the first lens claw 301d and the first camera claw 201a engage. In this case for example, in the vertical position of the imaging apparatus as well, looseness (bowing) of the first lens 100 mounted to the camera body 10 in the gravitational direction can be reduced.

[0098] Also, in a state where the first lens 100 is mounted to the camera body 10, the second camera mount center line 3002 and second lens mount center line 3006 overlap a lock region where the lock pin 202 and lock groove 301z are fit, as described above. According to this

configuration, in the vertical position of the camera body 10, the engaging position of the first camera claw 201a and first lens claw 301d and the above-described lock region overlap the mount center lines extending in the gravitational direction and the opposite direction thereof. According to this configuration, in the vertical position of the imaging apparatus, for example, looseness (bowing) of the first lens 100 mounted to the camera body 10 in the gravitational direction can be suppressed even more effectively.

Configuration of Contact Pins in Camera Body 10

[0099] The configuration of the contact pins provided to the camera body 10 side will be described with reference to Figs. 8A and 8B below. Figs. 8A and 8B are external perspective views viewing a camera mount 201 according to the embodiment of the present invention from the front face side (subject side). Fig. 8A is an external view of the camera mount 201 from the optical axis direction, and Fig. 8B is an external perspective view of the camera mount 201 from above.

[00100] The contact holding member 203, and contact pins 203a through 203k and 203m that are held by the contact holding member 203 are disposed following the circumferential direction of the camera mount 201 on the inner side of the camera mount 201, as illustrated in Fig.

8A. An array line on which the contact points are disposed is illustrated in Fig. 8A as an array line 3007.

[00101] The contact pins 203a through 203k and 203m are movable pins that can advance and retreat (protrude and retract) in a direction parallel to the optical axis 3000, and are biased from behind toward the first lens 100 side by leaf springs (omitted from illustration). As described above, the contact pins 203a through 203k and 203m have the functions of the above-described respective terminals, and the part numerals by which the contact pins are denoted are the same as those of the terminals, to facilitate description.

[00102] As illustrated in Fig. 8B, out of the contact pins 203a through 203k and 203m, the contact pins 203a, 203b, 203c, and 203d are higher in the direction parallel to the optical axis 3000 (toward the front face) as compared to the other contact pins. Although the above-described configuration is realized by differing the amount of protrusion from the contact holding member 203 in the optical axis direction in the present embodiment, a configuration may be employed where this is realized by differing the amount of protrusion of the contact pins from the contact holding member 203.

[00103] Generally, in a case of employing the bayonet coupling method and attaching/detaching an interchangeable

lens to/from a camera, the contact pins at the camera side and the contact face on the lens side slide over each other. For example, at the camera side, contact pins other than the contact pin situated at the edge in the rotational direction to complete mounting of the interchangeable lens slide over one or another contact face provided to the lens side. Accordingly, the more times the camera accessory is attached/detached to/from the camera, the more the contact pins and contact faces are worn.

[00104] The greater the number of terminals is, the more pronounced this problem is, and the number of times of sliding between contact pins and contact faces increases. Voltage drop increases due to the contact impedance of the terminals rising due to wearing of the contact pins and contact faces, and the interchangeable lens may malfunction, for example, due to the voltage dropping below the allowable voltage range for operation of the electric circuits.

[00105] Accordingly, in the present embodiment, the contact height of the camera-side contact pins and the interchangeable-lens-side contact faces are differed in a direction parallel to the optical axis 3000, between an upper tier and a lower tier. Specifically, the contact holding member 203 has a step in a direction parallel to the optical axis 3000, with the contact pins 203a through 203d being provided to the upper tier, and the contact pins 203e

through 203k and 203m being provided to the lower tier. The contact face holding member 303 also is stepped in a direction parallel to the optical axis 3001, with the contact pins 303a through 303d provided to the lower tier, and the contact pins 303e through 303k and 303m provided to the upper tier.

[00106] The upper tier of the contact holding member 203 at the camera mount 201 side is a tier protruding toward the front face side (subject side) of the first lens 100 when the first lens 100 is mounted to the camera body 10. The lower tier of the contact holding member 203 is a tier recessed toward the rear face side (imaging sensor 11 side) of the camera body 10. The upper tier of the contact face holding member 303 at the lens mount 301 side is a tier protruding toward the rear face side (imaging sensor 11 side) of the first lens 100 when the first lens 100 is mounted to the camera body 10. The lower tier of the contact face holding member 303 is a tier recessed to the front face side (subject side) of the camera body 10.

[00107] In a case where the lens mount 301 is mounted to the camera mount 201, the contact pins provided to the upper tier side of the contact holding member 203 and the contact faces provided to the lower tier side of the contact face holding member 303 are electrically in contact among corresponding terminals. Also, in a case where the lens

mount 301 is mounted to the camera mount 201, the contact pins provided to the lower tier side of the contact holding member 203 and the contact faces provided to the upper tier side of the contact face holding member 303 are electrically in contact among corresponding terminals. Accordingly, the steps at the camera mount 201 side and lens mount 301 side have a mutually engageable shape, so when mounting the lens mount 301 to the camera mount face A, the contact pins at the camera side and contact faces at the lens side that are provided to different steps do not come into contact.

[00108] According to this configuration, when relatively rotating the first lens 100 as to the camera body 10 from the mounting start state to the mounting completed state, the contact pins 203e through 203k and 203m do not come into contact with the contact faces 303a through 303d. Also, when relatively rotating the first lens 100 as to the camera body 10 from the mounting completed state to the mounting start state, the contact pins 203e through 203k and 203m do not come into contact with the contact faces 303a through 303d. That is to say, the number of times of sliding between contact pins and contact faces can be reduced at both the camera mount 201 side and lens mount 301 side.

[00109] Note that the contact pins at the camera body 10 side and the contact faces at the first lens 100 side are all in a non-contact state in the mounting start state of

the first lens 100 as to the camera body 10, so short-circuiting among terminals before completion of mounting of the first lens 100 can be prevented.

Configuration of Contact Faces in First Lens 100

[00110] The following is a description regarding the configuration of the contact faces provided to the first lens 100 side, with reference to Figs. 9A and 9B. Figs. 9A and 9B are external perspective views of the lens mount 301 according to the embodiment of the present invention, as viewed from the side to which the camera mount 201 is mounted (rear face side). Fig. 9A is an external view of the lens mount 301 from the optical axis direction, and Fig. 9B is an external perspective view of the lens mount 301 from above.

[00111] The contact face holding member 303, and contact faces 303a through 303k and 303m that are held by the contact face holding member 303 are disposed on the inner side of the lens mount 301, following the circumferential direction of the lens mount 301, as illustrated in Fig. 9A. An array line on which the contact points are disposed is illustrated in Fig. 9A as an array line 3008. As described above, the contact faces 303a through 303k and 303m have the functions of the above-described respective terminals, and the part numerals by which the contact faces are denoted are the same as those of the terminals, to facilitate

description.

[00112] As illustrated in Fig. 9B, out of the contact faces 303a through 303k and 303m, the contact faces 303a, 303b, 303c, and 303d are lower in the direction parallel to the optical axis 3001 as compared to the other contact faces. The above-described configuration is realized by differing the amount of protrusion of the contact face holding member 303 in the optical axis direction in the present embodiment.

[00113] According to the configuration described above, when relatively rotating the first lens 100 as to the camera body 10 from the mounting start state to the mounting completed state, the contact faces 303a through 303d do not come into contact with the contact pins 203e through 203k and 203m. Also, when relatively rotating the first lens 100 as to the camera body 10 from the mounting completed state to the mounting start state, the contact faces 303a through 303d do not come into contact with the contact pins 203e through 203k and 203m. That is to say, the number of times of sliding between contact pins and contact faces can be reduced at both the camera mount 201 side and lens mount 301 side.

[00114] Also, the contact face holding member 303 has a first guiding inclined face 303n and a second guiding inclined face 303p for drawing corresponding contact pins toward the rear face direction (imaging sensor 11 side) when

mounting the first lens 100 to the camera body 10, as illustrated in Fig. 9B. According to this configuration, the contact pressure of the contact pins provided to the camera body 10 side as to the contact face holding member 303 gradually changes, whereby deformation and wear of the contact pins provided to the camera body 10 can be reduced.

Operations of Attaching First Lens 100 to Camera Body 10

[00115] Next, the operations at the time of mounting the first lens 100 to the camera body 10 will be described with reference to Figs. 10A and 10B. Figs. 10A and 10B are diagrams exemplarily describing a contact state between terminals on the camera body 10 and first lens 100 according to the embodiment of the present invention. Fig. 10A is a diagram for describing the contact state of the terminals in the mounting start state where mounting of the first lens 100 to the camera body 10 has been started. Fig. 10B is a diagram for describing the contact state of the terminals in the mounting completed state where mounting of the first lens 100 to the camera body 10 has been completed. Note that in the state illustrated in Fig. 10A, the contact pins 203a and 203b at the camera mount 201 side in the optical axis direction overlap the contact faces 303m and 303k at the lens mount face B side. However, the height of the contact holding member 203 and the contact face holding member 303 in the direction parallel with the optical axis

is made to differ for each region, as described above, none of the contact pins and contact faces come into contact in the state illustrated in Fig. 10A.

[00116] The state illustrated in Fig. 10B is a state where the first lens 100 has been rotated by generally 60° as to the camera body 10 from the state illustrated in Fig. 10A toward the direction indicated by the arrow (see Fig. 10A). That is to say, in the present embodiment, the relative rotational angle of the camera body 10 and first lens 100 from the mounting start state to the mounting completed state is generally 60° . Note that in the state illustrated in Fig. 10B, the lock pin 202 is in the state of fitting the lock groove 301z (locked).

[00117] Rotating the first lens 100 by generally 60° as to the camera body 10 guides the first lens claw 301d into the rear face side (imaging sensor 11 side) of the first camera claw 201a and the two are engaged with each other in the optical axis direction. Also, in this state, the second lens claw 301e is guided into the rear face side (imaging sensor 11 side) of the second camera claw 201b, and these are engaged with each other in the optical axis direction. Also, in the is state, the third lens claw 301f is guided into the rear face side (imaging sensor 11 side) of the third camera claw 201c, and these are engaged with each other in the optical axis direction. Further, the positions

of the lens claws provided to the first lens 100 are positioned by being biased toward the rear face side by the lens mount biasing member 206 provided to the camera mount 201 side, thereby coupling the camera body 10 and the first lens 100.

[00118] Also, the contact pins at the camera body 10 side are pressed toward the rear face side (imaging sensor 11 side) by the first guiding inclined face 303n and second guiding inclined face 303p. The contact pins of the camera body 10 come into contact with corresponding places on the contact faces 303a through 303k and 303m at the lens mount 301 side in a state of being pressed, and come into contact with the respectively corresponding contact faces in the mounting completed state. Note that at this time, the contact pin 203m provided to the camera mount 201 side and the contact face 303e provided to the lens mount 301 start coming into contact first.

Basic Configuration of Conversion Adapter

[00119] Next, the basic configuration of a conversion adapter (adapter device) that is a camera accessory mountable to the camera mount 201 of the above-described camera body 10 will be described with reference to Figs. 11A through 12B. Figs. 11A and 11B are diagrams describing the first conversion adapter 40 that is mountable to the camera body 10, and a second lens unit 50. Fig. 11A illustrates an

external perspective view of the second lens unit 50 having been mounted to the camera body 10 via the first conversion adapter 40. Fig. 11B illustrates an external perspective view of a state where the camera body 10, first conversion adapter 40, and second lens unit 50 have each been detached. Note that the second lens unit (hereinafter referred to as second lens) 50 has a lens mount 501 that is short in flange focal distance, but has the same mount diameter as the camera mount 201, as to the camera body 10. That is to say, the second lens 50 has the same mount diameter as the above-described first lens 100, but unlike the first lens 100, is a camera accessory that is not compatible with direct mounting to the camera body 10.

[00120] Figs. 12A and 12B are diagrams for describing the second conversion adapter 70 the is mountable to a camera body 60 and the first lens 100. Fig. 12A illustrates an external perspective view of a state where the first lens 100 is mounted to the camera body 60 via the second conversion adapter 70, and Fig. 12B illustrates an external perspective view where the camera body 60, second conversion adapter 70, and first lens 100 have each been detached.

[00121] Now, in a case where a lens unit with a long flange focal distance is directly mounted to an imaging apparatus with a short flange focal distance, trouble will occur such as the focal point not being formed at an

accurate position or the like, and imaging a subject in this way will result in an unnatural image being obtained. For example, the above problem will occur if the second lens unit 50 that has a long flange focal distance is mounted to the above-described camera body 10.

[00122] In the same way, in a case where a lens unit with a short flange focal distance is directly mounted to an imaging apparatus with a long flange focal distance, trouble will occur such as the focal point not being formed at an accurate position or the like, and imaging a subject in this way will result in an unnatural image being obtained. For example, the above problem will occur if the first lens 100 that has a short flange focal distance is mounted to the camera body 60 serving as a second imaging apparatus that has a longer flange focal distance than the above-described camera body 10.

[00123] Particularly, the camera body 10 and camera body 60, and the first lens 100 and second lens 50, have the same mount diameter, it is difficult for a user to judge which imaging apparatuses and which lens units have flange focal distances that are compatible for direct mounting.

[00124] Accordingly, it is preferable that only lens units that are compatible can be directly mounted to a certain imaging apparatus, so that imaging apparatuses and lens units that have mutually incompatible flange focal distances

are not erroneously directly mounted.

[00125] Also, in a case of mounting an incompatible lens unit to an imaging apparatus, a conversion adapter needs to be interposed between the two to adjust the flange focal distance. However, in a case where one side of the conversion adapter is mounted to the imaging apparatus and a lens unit compatible with direct mounting to the imaging apparatus is mounted to the other side of the conversion adapter, the focal point may not be accurately formed, as described above. Accordingly, the one side and other side of the conversion adapter preferably have configurations to restrict imaging apparatuses and camera accessories that are directly mountable.

[00126] Specifically, in a case of mounting a lens unit having a long flange focal distance to an imaging apparatus having a short flange focal distance, a conversion adapter is preferable where one end side is only mountable to this imaging apparatus, and the other end side is only mountable to this lens unit. Also, in a case of mounting a lens unit having a short flange focal distance to an imaging apparatus having a long flange focal distance, a conversion adapter is preferable where one end side is only mountable to this imaging apparatus, and the other end side is only mountable to this lens unit.

[00127] The first conversion adapter 40 has the lens mount

1301 attached to an adapter barrel 40a by fastening screws (omitted from illustration), at one end side in the optical axis direction. This lens mount 1301 is an accessory mount that is detachable from the camera mount 201 provided to the camera body 10 described above.

[00128] A camera mount 1401 is attached to the adapter barrel 40a by fastening screws (omitted from illustration), at the other end side of the first conversion adapter 40 in the optical axis direction. This camera mount 1401 is a camera mount that is detachable from the lens mount 501 of the second lens 50. Note that the camera mount 1401 of the first conversion adapter 40 is attached so that the imaging plane of the imaging sensor 11 of the will be situated at a position corresponding to the flange focal distance of the second lens 50.

[00129] The second conversion adapter 70 has the lens mount 1501 attached to an adapter barrel 70a by fastening screws (omitted from illustration), at one end side in the optical axis direction. This lens mount 1501 is an accessory mount that is detachable from the camera mount 401 provided to the camera body 60.

[00130] The camera mount 1201 is attached to the adapter barrel 70a by fastening screws (omitted from illustration), at the other end side of the second conversion adapter 70 in the optical axis direction. This camera mount 1201 is a

camera mount that is detachable from the lens mount 301 of the first lens 100, as described above.

[00131] Note that a first optical member 701a and a second optical member 701b are provided to the second conversion adapter 70, between the adapter barrel 70a and the lens mount 1501 in the optical axis direction. The first optical member 701a and second optical member 701b enable the second conversion adapter 70 to extend length of the flange focal distance of the first lens 100 in accordance with the imaging plane of the imaging sensor disposed in the camera body 60. While the optical members have been illustrated as two lenses for the sake of convenience, this is not restrictive.

Configuration of First Conversion Adapter 40

[00132] Next, the angles (phases) at which bayonet claws are disposed on the circumferential direction of the camera mount and lens mount of the first conversion adapter 40 will be described with reference to Fig. 13A through Fig. 17D. Figs. 13A through 13C are diagrams for exemplarily describing displacement angles of bayonet claws in the camera mount 1401 provided on one end of the first conversion adapter 40. Fig. 13A is a diagram illustrating angle ranges that camera claws and camera recesses occupy in the circumferential direction of the camera mount 1401 with the lock pin 1401z as a reference, as viewed from the rear

face side (camera body 10 side). Fig. 13B is a diagram illustrating angle ranges that multiple camera claws 1401a through 1401c occupy in the circumferential direction of the camera mount 1401, as viewed from the rear face side (camera body 10 side). Fig. 13C is a cross-sectional diagram taken along cross-section XIII B-XIII B in Fig. 13B.

[00133] The first conversion adapter 40 is a mount adapter used for mounting the second lens unit 50 that has a long flange focal distance to the camera body 10 that has a short flange focal distance. Accordingly, it is preferable for the first conversion adapter 40 to be configured such that the camera body 60 that has a long flange focal distance cannot be directly mounted to the lens mount 1301, and the first lens 100 that has a short flange focal distance cannot be directly mounted to the camera mount 1401. According to this configuration, the positional relation of claws and recesses can be satisfied so that the lens mount 1301 provided to one end (first end) of the first conversion adapter 40 and the camera mount 1401 provided to the other end (second end) cannot each be directly mounted.

[00134] A first camera claw 1401a, second camera claw 1401b, and third camera claw 1401c, are provided in order, to the camera mount 1401 in the circumferential direction (inner radial direction). When viewing the camera mount 1401 from the rear face side as illustrated in Fig. 13A, the

camera claw that is provided at a position farthest from the lock pin 1401z is the first camera claw 1401a. The second camera claw 1401b and third camera claw 1401c are then consecutively provided in order from the first camera claw 1401a in a clockwise direction.

[00135] Also, recesses which are a first camera recess 1401d, second camera recess 1401e, and third camera recess 1401f are provided in order, to the camera mount 1401 in the circumferential direction (inner radial direction). When viewing the camera mount 1401 from the rear face side as illustrated in Fig. 13A, the recess that is provided at a position nearest to the lock pin 1401z is the second camera recess 1401e. The third camera recess 1401f and first camera recess 1401d are then consecutively provided in order from the second camera recess 1401e in a clockwise direction.

[00136] As illustrated in Fig. 13C, a fitting member 1401x that restricts movement of the camera accessory in a direction parallel to the optical axis when the camera accessory is mounted, is provided to the camera mount 1401 side. In the present embodiment, the diameter of the fitting member 1401x in a direction orthogonal to the optical axis at the camera mount 1401 side is the mount diameter.

[00137] The way of bayonet coupling of the first conversion adapter 40 and second lens 50 is the generally

the same as the way of bayonet coupling of the camera body 10 and first lens 100 described above, so description will be omitted.

[00138] Note that the end portions of the camera claws 1401a, 1401b, and 1401c, in the circumferential direction, will be referred to as first end portion 1401a1, second end portion 1401a2, third end portion 1401b1, fourth end portion 1401b2, fifth end portion 1401c1, and end portion 1401c2, for the sake of description. The end portions are denoted with part numerals in order from the first camera claw 1401a in the clockwise direction, when viewing the camera mount 1401 from the rear face side, as described above.

[00139] As illustrated in Fig. 13A, the angles that the camera claws and camera recesses occupy in the circumferential direction of the camera mount 1401 (angle ranges) in the first conversion adapter 40 according to the present embodiment are stipulated as follows. For the first camera claw 1401a, the angle $\theta_1 = 56^\circ$, for the second camera claw 1401b, the angle $\theta_2 = 62^\circ$, and for the third camera claw 1401c, the angle $\theta_3 = 62^\circ$. Also, for the first camera recess 1401d, the angle is 57° , for the second camera recess 1401e, the angle is 66° , and for the third camera recess 1401f, the angle is 57° . That is to say the camera mount 1401 has different angles for the camera claws with respect to the above-described camera mount 201 of the camera body 10, but

the angles of the camera recesses are the same.

[00140] Also, when viewing the camera claws from the rear face side of the first conversion adapter 40, the angles where the camera claws are disposed on the circumferential direction of the camera mount 1401 with the position of the lock pin 402 (referred to as reference position) as a reference are stipulated as follows. The first camera claw 1401a is disposed between 159° to 215° with the reference position as a start point. The second camera claw 1401b is disposed between 272° to 334° with the reference position as a start point. The third camera claw 1401c is disposed between 40° to 102° with the reference position as a start point.

[00141] Next, Figs. 14A and 14B are diagrams exemplarily describing angles of disposing the bayonet claws on the lens mount 1301 provided to the other end of the first conversion adapter 40. Fig. 14A is a diagram illustrating angle ranges that camera claws and camera recesses occupy in the circumferential direction of the camera mount 1401 with the lock groove 1301z as a reference, as viewed from the rear face side. Fig. 14B is a diagram illustrating angle ranges that multiple lens recesses 1301a through 1301c occupy in the circumferential direction of the camera mount 1301, as viewed from the rear face side.

[00142] The angles (angle ranges) that the lens recesses

occupy in the circumferential direction of the lens mount 1301 are, represented by $\theta 4$ as the angle of the first lens recess 1301a and $\theta 5$ as the angle of the second lens recess 1301b, as illustrated in Fig. 14B. Note that the angle so disposing the claws and recesses on the lens mount 1301 of the first conversion adapter 40 is the same as the lens mount 301 of the first lens 100 described above, and accordingly description will be omitted.

[00143] The angles of the claws and recesses in the circumferential direction, on the lens mount 1301 and camera mount 1401 provided to the first conversion adapter 40, will be compared. For example, at the lens mount 1301 side, the angle $\theta 5$ of the second lens recess 1301b having the smallest angle is 44° , whereas, at the camera mount 1401 side, the angle $\theta 1$ of first camera claw 1401a having the smallest angle is 56° . That is to say, the claw having the smallest angle at the camera mount 1401 side is larger than the recess having the smallest angle at the lens mount 1301 side ($\theta 5 < \theta 1$). In this case, of the recesses on the lens mount 1301 side and the claws on the camera mount 1401 side, at least one or more lens recess and camera claws will interfere with each other. Accordingly, even if an attempt is made to mount the lens unit to the camera body so that the optical axis at the camera mount 1401 side and lens mount 1301 side are generally parallel, the claws and

recesses interfere, so the lens unit cannot be mounted to the camera body.

[00144] However, if only one claw and recess are interfering, there may be cases where claws of the camera mount side can be inserted into recesses of the lens mount side. Figs. 15A and 15B are diagrams exemplarily describing a mounting method of a predetermined imaging apparatus 1000 and a predetermined lens unit 2000 having claws and recesses that interfere with each other. Fig. 15A is a diagram exemplarily describing a frontal view of partway through mounting a predetermined lens unit to a predetermined imaging apparatus that have claws and recesses that interfere with each other. Fig. 15B is a cross-sectional view taken along cross-section XVB-XVB in Fig. 15A.

[00145] For example, in a state where the optical axis of the lens mount side is obliquely inclined as to the optical axis of the camera mount side, one end of a camera claw is inserted into a lens recess, and from this state, the lens mount and camera mount are rotated relatively to each other, as illustrated in Figs. 15A and 15B. In this case, even if the camera claws and lens recesses originally interfere with each other, this interference with each other is resolved during the relative rotation of the lens mount and camera mount, and transition can be made to a state where the camera claw is inserted into this lens recess. In this case,

if there are no other camera claws and lens recesses interfering, the lens unit can be mounted to the camera body.

[00146] Accordingly, the claws and recesses on the lens mount 1301 side and camera mount 1401 side are disposed such that the angle of a predetermined lens recess adjacent to a reference lens claw is smaller than the angle of two camera claws adjacent to a reference camera recess. Specifically, in the present embodiment, the angles θ_4 and θ_5 of the first lens recess 1301a and second lens recess 1301b adjacent to the first lens claw 1301d are smaller than the angles θ_1 and θ_2 of the first camera claw 1401a and second camera claw 1401b adjacent to the first camera recess 1401d. That is to say, θ_4 (52°) is smaller than θ_1 (56°), and θ_5 (44°) is smaller than θ_2 (62°) ($\theta_4 < \theta_1$, $\theta_5 < \theta_2$). Accordingly, even if an attempt is made to insert the first lens claw 1301d into the first camera recess 1401d, the second lens claw 1301e interferes with the second camera claw 1401b in a sure manner, as well does the third lens claw 1301f with the first camera claw 1401a, as illustrated in Figs. 16A and 16B.

[00147] Figs. 16A and 16B are diagrams exemplarily describing the way in which claws interfere with each other when attempting to mount the lens mount 1301 side to the camera mount 1401 side according to the embodiment of the present invention. Fig. 16A illustrates the way in which the third lens claw 1301f and the first camera claw 1401a

interfere, and Fig. 16B illustrates the way in which the second lens claw 1301e and the second camera claw 1401b interfere.

[00148] As described above, incompatible lens units and imaging apparatuses, and the mount portions of conversion adapters are configured so that two claws of each other out of the claws that an incompatible lens unit and imaging apparatus have interfere with each other in the present embodiment. According to this configuration, the risk of an incompatible lens unit being erroneously mounted to an imaging apparatus, or an incompatible lens unit and imaging apparatus being erroneously mounted to mount units provided to both ends of a conversion adapter, can be reduced.

[00149] However, even in a case where the above conditions are satisfied, there may be cases where, when attempting to insert three claws into incompatible recesses, for example, two claws are inserted into recesses depending on the angles of the claws and recesses. Accordingly, the present embodiment further takes a configuration where the angles of at least two adjacent lens recesses are smaller than the angles of all camera claws. Specifically, in the present embodiment, the angles $\theta 4$ and $\theta 5$ of the first lens recess 1301a and second lens recess 1301b in the circumferential direction are smaller than the angles $\theta 1$ through $\theta 3$ of the first through third camera claws 1401a through 1401c in the

circumferential direction. That is to say, the relation between the claws and recesses at the lens mount 1301 side and the camera mount 1401 side according to the present embodiment satisfy $\theta_4 < \theta_1$, $\theta_4 < \theta_2$, $\theta_4 < \theta_3$, $\theta_5 < \theta_1$, $\theta_5 < \theta_2$, and $\theta_5 < \theta_3$.

[00150] Figs. 17A through 17D is a diagram exemplarily describing a case of attempting to insert incompatible claws into recesses at the lens mount 1301 side and camera mount 1401 side according to the embodiment of the present invention. Fig. 17A illustrates the way in which the third lens claw 1301f and third camera claw 1401c interfere in a case of attempting to insert the first lens claw 1301d into the third camera recess 1401f. Fig. 17B illustrates the way in which second lens claw 1301e and first camera claw 1401a interfere in a case of attempting to insert the first lens claw 1301d into the third camera recess 1401f. Fig. 17C illustrates the way in which the third lens claw 1301f and second camera claw 1401b interfere in a case of attempting to insert the first lens claw 1301d into the second camera recess 1401e. Fig. 17D illustrates the way in which the second lens claw 1301e and third camera claw 1401c interfere in a case of attempting to insert the first lens claw 1301d into the second camera recess 1401e.

[00151] As illustrated in Figs. 17A through 17D, the lens claws and camera claws interfere in at least two places in

the present embodiment, regardless of the relative rotational angle of the lens mount 1301 and camera mount 1401. According to this configuration, erroneous mounting of a lens unit and conversion adapter having the lens mount 301 or the lens mount 1301 to an imaging apparatus and conversion adapter having the camera mount 401 or the camera mount 1401 can be prevented even more effectively.

Configuration of Second Conversion Adapter 70

[00152] Next, the angles (phases) at which bayonet claws are disposed on the circumferential direction of the camera mount and lens mount of the second conversion adapter 70 will be described with reference to Figs. 18A through 21D.

[00153] The second conversion adapter 70 is a mount adapter used for mounting the first lens 100 that has a short flange focal distance to the camera body 60 that has a long flange focal distance. The lens mount 1501 is provided at one end (third end) side of the second conversion adapter 70, and the camera mount 1201 is provided at the other end (fourth end). Note that the camera mount 1201 of the second conversion adapter 70 has the same configuration as the camera mount 201 of the camera body 10 that is the first imaging apparatus described above. Also, the lens mount 1501 of the second conversion adapter 70 has the same configuration as the lens mount 501 of the second lens 50 described above.

[00154] Accordingly, it is preferable for the second conversion adapter 70 to be configured such that the camera body 10 that has a short flange focal distance cannot be directly mounted to the lens mount 1501, and the second lens 50 that has a long flange focal distance cannot be directly mounted to the camera mount 1201. This configuration can be realized by satisfying the positional relation of claws and recesses so that the lens mount 1501 provided to one end (third end) of the second conversion adapter 70 and the camera mount 1201 provided to the other end (fourth end) cannot each be directly mounted.

[00155] Figs. 18A and 18B are diagrams exemplarily describing angles of disposing bayonet claws in the camera mount 1201 provided on one end of the second conversion adapter 70. Fig. 18A is a diagram illustrating angle ranges that camera claws and camera recesses occupy in the circumferential direction of the camera mount 1201 with the lock pin 202 as a reference, as viewed from the rear face side. Fig. 18B is a diagram illustrating angle ranges that, regarding multiple camera claws 1201a through 1201c, the claws occupy in the circumferential direction of the camera mount 1201, as viewed from the rear face side. Note that the angles of disposing the claws and recesses on the camera mount 1201 of the second conversion adapter 70 are the same as the camera mount 1201 of the camera body 10 described

earlier, so description will be omitted.

[00156] As illustrated in Fig. 18B, the angle from the sixth end 1201c2 of the third camera claw 1201c to the third end 1201b1 of the second camera claw 1201b, in the circumferential direction of the camera mount 1201 including the first camera claw 1201a, is $\theta 6$ (162°). The angle from the second end 1201a2 of the first camera claw 1201a to the fifth end 1201c1 of the third camera claw 1201c, in the circumferential direction of the camera mount 1201 including the second camera claw 1201b, is $\theta 7$ (163°). The angle from the fourth end 1201b2 of the second camera claw 1201b to the first end 1201a1 of the first camera claw 1201a, in the circumferential direction of the camera mount 1201 including the third camera claw 1201c, is $\theta 8$ (215°).

[00157] Next, Figs. 19A through 19C are diagrams exemplarily describing angle so disposing bayonet claws in a lens mount 1501 provided on the other end of the second conversion adapter 70. Fig. 19A is a diagram illustrating angle ranges that lens claws and lens recesses occupy in the circumferential direction of the lens mount 1501 with the lock pin 1501z as a reference, as viewed from the rear face side. Fig. 19B is a diagram illustrating angle ranges where recesses are provided regarding the multiple lens recesses 1501a through 1501c in the circumferential direction of the lens mount 1501, as viewed from the rear face side. Fig.

19C is a cross-sectional diagram taken along cross-section XIXC-XIXC in Fig. 19B.

[00158] A first lens claw 1501d, second lens claw 1501e, and third lens claw 1501f, are provided in order, to the camera mount 1501 in the circumferential direction (inner radial direction). Note that in a case of viewing the lens mount 1501 from the rear face side as illustrated in Fig. 19A, the lens claw that is provided at a position farthest from the lock groove 1501z is the first lens claw 1501d. The second lens claw 1501e and third lens claw 1501f are then consecutively provided in order from the first lens claw 1501d in a clockwise direction.

[00159] Also, recesses which are a first lens recess 1501a, second lens recess 1501b, and third lens recess 1501c are provided in order, to the lens mount 1501 in the circumferential direction (inner radial direction). Note that in a case of viewing the lens mount 1501 from the rear face side as illustrated in Fig. 19A, the recess that is provided at a position nearest to the lock groove 1501z is the third lens recess 1501c. The first lens recess 1501a and second lens recess 1501b are then consecutively provided in order from the third lens recess 1501c in a clockwise direction.

[00160] Note that the end portions of the lens claws 1501d, 1501e, and 1501f, in the circumferential direction, will be

referred to as first end portion 1501d1, second end portion 1501d2, third end portion 1501e1, fourth end portion 1501e2, fifth end portion 1501f1, and sixth end portion 1501f2, for the sake of description. The end portions are denoted with part numerals in order from the first lens claw 1501d in the clockwise direction, when viewing the lens mount 1501 from the rear face side, as described above.

[00161] As illustrated in Fig. 19A, the angles that the lens claws and lens recesses occupy in the circumferential direction of the lens mount 1501 (angle ranges) are stipulated as follows. The angle of the first lens claw 1501d is 53° , the angle of the second lens claw 1501e is 62° , and the angle of the third lens claw 1501f is 53° . That is to say, the angles of the lens claws on the lens mount 1501 side are the same as the angles of the lens claws on the lens mount 1301 side described earlier.

[00162] On the other hand, the angles of the lens recesses at the lens mount 1501 side differ from the angles of the lens recesses at the lens mount 1301 side described above. Specifically, the angle of the first lens recess 1501a is 60° , the angle of the second lens recess 1501b is 66° , and the angle of the third lens recess 1501c is 66° .

[00163] Also, when viewing the lens claws from the rear face side of the camera body 10, the angles in the clockwise direction where the lens claws are disposed on the

circumferential direction of the lens mount 1501 with the position of the lock groove 1501z (referred to as reference position) as a reference are stipulated as follows. The first lens claw 1501d is disposed between 157° to 210° with the reference position as a start point. The second lens claw 1501e is disposed between 276° to 338° with the reference position as a start point. The third lens claw 1501f is disposed between 44° to 97° with the reference position as a start point.

[00164] As illustrated in Fig. 19C, a fitting member 1501x that restricts movement of the imaging apparatus in a direction parallel to the optical axis when mounted to the imaging apparatus is provided to the lens mount 1501 side. In the present embodiment, the diameter of the fitting member 1501x in a direction orthogonal to the optical axis at the camera mount 1501 side is the mount diameter. The mount diameters of the camera mounts and lens mounts described above are generally the same length.

[00165] As illustrated in Fig. 19B, the angle from the fifth end 1501f1 of the third lens claw 1501f to the second end 1501d2 of the second lens claw 1501d, in the circumferential direction of the lens mount 1501 including the first lens recess 1501a, is θ_9 (166°). The angle from the first end 1501d1 of the first lens claw 1501d to the fourth end 1501e2 of the second lens claw 1501e, in the

circumferential direction of the lens mount 1501 including the second lens recess 1501b, is θ_{10} (181°). The angle from the third end 1501e1 of the second lens claw 1501e to the sixth end 1501f2 of the third lens claw 1501f, in the circumferential direction of the lens mount 1501 including the third lens recess 1501c, is θ_{11} (181°).

[00166] The angles of the claws and recesses in the circumferential direction will be compared between the camera mount 1201 and lens mount 1501 provided to the second conversion adapter 70. For example, the angle (92°) of the third camera claw at the camera mount 1201 side is larger than the angles (66°) of the second and third lens recesses 1501b and 1501c that are the largest angle of the lens recesses at the lens mount 1501 side. That is to say, the angle of at least one camera claw at the camera mount 1201 side is larger than the angle of the lens recess having the largest angle at the lens mount 1501 side.

[00167] In this case, of the claws at the camera mount 1201 side and recesses at the lens mount 1501 side, at least one or more camera claw and lens recess interfere with each other. Accordingly, even if an attempt is made to mount the lens unit to the camera body so that the optical axis at the camera mount 1201 side and lens mount 1501 side are generally parallel to each other, the claws and recesses interfere, so the lens unit cannot be mounted to the camera

body.

[00168] However, if only one claw and recess are interfering, there may be cases where claws of the camera mount side can be inserted into recesses of the lens mount side, in the same way as the description of the first conversion adapter made above. For example, there are cases where, in a state where the optical axis of the lens mount side is obliquely inclined as to the optical axis of the camera mount side, one end of a camera claw is inserted into a lens recess, and the lens mount and camera mount are rotated relative to each other, and the lens unit can be mounted to the camera body.

[00169] Accordingly, in the present embodiment, the claws and recesses at the camera mount 1201 side and the lens mount 1501 side are disposed so as to satisfy $\theta 6 < \theta 9$ and $\theta 7 < \theta 10$ in the circumferential direction. Figs. 20A and 20B are diagrams exemplarily describing the way in which claws interfere with each other, when attempting to mount a reference claw at the lens mount 1501 side to a reference recess at the camera mount 1201 side according to the embodiment of the present invention. Fig. 20A illustrates the way in which the third lens claw 1501f and the third camera claw 1201c interfere, and Fig. 20B illustrates the way in which the second lens claw 1501e and the third camera claw 1201c interfere.

[00170] As illustrated in Figs. 20A and 20B, in a case where the reference first lens claw 1501d is attempted to be inserted into the reference camera recess 1201d, for example, the third camera claw 1201c interferes with the second and third lens claws 1501e and 1501f.

[00171] That is to say, as viewed from the rear face side, the total sum of the angles of one reference lens claw, another lens claw adjacent thereto in the clockwise direction, and a lens recess situated between these lens claws, is taken as a first angle. Also, as viewed from the rear face side, the total sum of the angles of one reference camera recess, another camera recess adjacent thereto in the clockwise direction, and a camera claw portion situated therebetween, is taken as a second angle. Also, as viewed from the rear face side, the total sum of the angles of one reference lens claw, another lens claw adjacent thereto in the counterclockwise direction, and a lens recess situated between these lens claws, is taken as a first angle. Also, as viewed from the rear face side, the total sum of the angles of one reference camera recess, another camera recess adjacent thereto in the counterclockwise direction, and a camera claw portion situated therebetween, is taken as a fourth angle. According to the present embodiment, it is sufficient to layout the claws and recesses at the camera mount 1201 side and lens mount 1501 side such that the first

angle described above is larger than the second angle, and the third angle is larger than the fourth angle.

[00172] According to this configuration, at least two lens claws and one camera claw interfere with each other. Thus, the risk of an incompatible lens unit being erroneously mounted to an imaging apparatus, or an incompatible lens unit and imaging apparatus being erroneously mounted to mount units provided to both ends of a conversion adapter, can be reduced.

[00173] However, even in a case where the above conditions are satisfied, there may be cases where, when attempting to insert three claws into incompatible recesses, for example, two claws are inserted into recesses depending on the angles of the claws and recesses. Accordingly, the claws and recesses at the camera mount 1201 side and lens mount 1501 side are disposed in the circumferential direction so as to satisfy $\theta_6 < \theta_9$, $\theta_6 < \theta_{10}$, $\theta_6 < \theta_{11}$, $\theta_7 < \theta_9$, $\theta_7 < \theta_{10}$, and $\theta_7 < \theta_{11}$. That is to say, as viewed from the rear face side, the total sum of the angles of two claws other than the reference claw described above, and a lens recess situated therebetween, is taken as a fifth angle. According to the present embodiment, it is sufficient to layout the claws and recesses at the camera mount 1201 side and lens mount 1501 side such that the second angle and fourth angle described above are smaller than any of the first angle, third angle,

and fifth angle.

[00174] Figs. 21A through 21D are diagrams exemplarily describing the way in which claws interfere with each other, when attempting to mount a claw other than the reference claw at the lens mount 1501 side to a reference recess at the camera mount 1201 side according to the embodiment of the present invention. Fig. 21A illustrates the way in which the first lens claw 1501d and the third camera claw 1201c interfere in a case of attempting to insert the second lens claw 1501e into the first camera recess 1201d. Fig. 21B illustrates the way in which the third lens claw 1501c and the third camera claw 1201c interfere in a case of attempting to insert the second lens claw 1501e into the first camera recess 1201d. Fig. 21C illustrates the way in which the second lens claw 1501e and the third camera claw 1201c interfere in a case of attempting to insert the third lens claw 1501f into the first camera recess 1201d. Fig. 21D illustrates the way in which the first lens claw 1501d and the third camera claw 1201c interfere in a case of attempting to insert the third lens claw 1501f into the first camera recess 1201d.

[00175] As illustrated in Figs. 21A through 21D, at least two lens claws and one camera claw interfere, regardless of the relative rotation angle of the lens mount 1501 and camera mount 1201 according to the present embodiment.

According to this configuration, erroneous mounting of a lens unit and conversion adapter having the lens mount 501 or the lens mount 1501 to an imaging apparatus and conversion adapter having the camera mount 201 or the camera mount 1201 can be prevented even more effectively.

[00176] Fig. 22 is a diagram exemplarily describing a state in which claws provided to the camera mount 1401 side and lens mount 1501 side according to the embodiment of the present invention are engaged. Note that Fig. 22 illustrates a state in which the camera mount 401 of the camera body 60 is engaging the lens mount 501 of the second lens 50. The first lens claw 1501d can be inserted into the first camera recess 1401d, as illustrated in Fig. 22. Also, the second lens claw 1501e can be inserted into the second camera recess 1401e. Further, the third lens claw 1501f can be inserted into the third camera recess 1401f. That is to say, the camera mount 1401 side and the lens mount 1501 side are a combination compatible with being directly mounted to each other. Note that the camera mount 1201 side and the lens mount 1301 side are a combination compatible to being directly mounted to each other, as illustrated in Fig. 10A.

[00177] As described above, the camera mount 401 (1401) corresponding to an imaging apparatus that has a long flange focal distance (e.g., the camera body 60), and the lens mount 501 (1501) corresponding to a lens unit that has a

long flange focal distance (e.g., the second lens 50) can be directly mounted to each other. However, the camera mount 201 (1201) corresponding to an imaging apparatus having a short flange focal distance (e.g., the camera body 10) and the lens mount 501 (1501) corresponding to a lens unit that has a long flange focal distance (e.g., the second lens 50) cannot be directly mounted to each other. Also, the camera mount 201 (1201) corresponding to an imaging apparatus that has a short flange focal distance (e.g., the camera body 10) and the lens mount 301 (1301) corresponding to a lens unit that has a short flange focal distance (e.g., the first lens 100) can be directly mounted to each other. However, the camera mount 401 (1401) corresponding to an imaging apparatus that has a long flange focal distance (e.g., the camera body 60) and the lens mount 301 (1301) corresponding to a lens unit that has a short flange focal distance (e.g., the first lens 100) cannot be directly mounted to each other.

[00178] Accordingly, an imaging apparatus and camera accessory employing the configuration of the above-described embodiment can prevent erroneous mounting of an imaging apparatus and camera accessory that have generally the same mount diameter but are not mutually compatible.

[00179] Although a preferable embodiment of the present invention has been described, the present invention is not restricted to this embodiment, and various modifications and

alterations can be made within the scope of the essence thereof. For example, a case of employing a digital camera has been described as an example of the imaging apparatus in the above-described embodiment, but imaging apparatuses other than digital cameras, such as digital video cameras, security cameras, and so forth, may be employed in the configuration.

[00180] Also, although a case of employing an interchangeable lens and an intermediate accessory such as a conversion adapter, as an example of the camera accessory carrying out the present invention has been described in the embodiment above, this is not restrictive. Any sort of camera accessory may be employed as long as it is a device that has an accessory mount capable of directly connecting (coupling) to a camera mount provided to the above-described imaging apparatuses.

[00181] Although a configuration has been described in the above embodiment where both of the camera mount and accessory mount corresponding to each other have a pair of electric terminals through which electric connection is established in a mutually mounted state, this is not restrictive. For example, a configuration may be made having electric terminals that do not correspond to each other. For example, a configuration may be made where a terminal that the camera body 10 does not have is provided

to a camera accessory mountable to the camera body 10.

[00182] Although a configuration has been described in the above embodiment where the electric terminals are disposed in order along a circumferential direction where the diameter from the center of the camera mount and accessory mount is generally the same, this is not restrictive. For example, a configuration may be made where the electric terminals are disposed along the circumferential direction at different diameters from the center of the camera mount and accessory mount. In this case, the dimensions of the mounts in the radial direction will increase, but friction between terminals can be suppressed.

[00183] Also, although a case has been described in the above embodiment where each mount has three claws in the circumferential direction, the number of claws is not restricted to three, as long as the conditions of the above-described embodiment are satisfied.

[00184] A configuration may be made where each of the three claws provided to the mounts in the above-described embodiment is further divided. That is to say, a configuration may be made where one claw is one claw group made up of multiple claws. A case where a groove is provided to one claw falls under this, for example. In this case, the ranges of angles of claw groups disposed in the circumferential direction of the mounts is the same as those

in the embodiment described above.

[00185] Also, although a case has been described in the above embodiment where the mount diameter of each mount is the inner diameter of a fitting portion provided to each mount, in a direction orthogonal to the optical axis, this is not restrictive. For example, at each mount, an inner diameter of which the radius is the distance from the center (optical axis) of each mount to multiple terminals may be used as the mount diameter, or an inner diameter of which the radius is the distance from the center (optical axis) of each mount to a claw or recess may be used as the mount diameter.

[00186] Although a configuration has been described in the above embodiment where a device having one of a camera mount and an accessory mount is actually rotated as to a device having the other mount, thereby bayonet-coupling the devices to each other, this is not restrictive. For example, a configuration may be employed where a camera mount and accessory mount are relatively rotated, and the camera mount and accessory mount are bayonet-coupled. Specifics of this will be described in detail below.

[00187] Fig. 23 is a disassembled perspective view of a mount mechanism 5000 according to a modification of the present invention. Figs. 24A through 24C are diagrams for exemplarily describing a non-coupled state of the mount

mechanism 5000 according to the modification of the present invention. Figs. 25A through 25C are diagrams for exemplarily describing a coupled state of the mount mechanism 5000 according to the modification of the present invention. In Figs. 23 through 25C, the lens mount that is capable of bayonet-coupling to a movable mount portion 5010 of the mount mechanism 5000 is also illustrated, for the same of description. Members that are the same as in the above-described embodiment are denoted by the same reference numerals, and description thereof will be omitted.

[00188] As illustrated in Fig. 23, the mount mechanism 5000 according to the present embodiment has, in order from the side to which the lens mount is attached, an operation portion 5030, a fixed mount portion 5020, the movable mount portion 5010, and the contact holding member 203, centered on the optical axis 3000. The operation portion 5030 is a ring-shaped operating unit capable of rotating on a center axis, and is fixed to the movable mount portion 5010 by screws, by arm portions 5040. Note that in the present modification, the operation portion 5030 and movable mount portion 5010 are fixed at two positions, using two arm portions 5040 disposed in an orthogonal direction as to the center axis. According to this configuration, by the operation portion 5030 being rotationally operated, the movable mount portion 5010 also rotates integrally with the

center axis as the center.

[00189] Provided on the movable mount portion 5010 are movable mount claws 5011a, 5011b, and 5011c, that are each capable of bayonet-coupling with bayonet claws 301a through 301c provided to the lens mount. Also provided to the movable mount portion 5010 is a screw portion 5012 that has been threaded around the center axis, and the screwed state as to a later-described screw portion 5022 of the fixed mount portion 5020 changes in accordance with the rotation of the movable mount portion 5010 around the center axis.

[00190] The fixed mount portion 5020 has a camera mount face 5021 that comes into contact with the mount face of the lens mount, and the screw portion 5022 with which the screw portion 5012 of the above-described movable mount portion 5010 is screwed. Unlike the above-described movable mount portion 5010, the fixed mount portion 5020 does not rotate on the center axis in accordance with rotation operations of the operation portion 5030.

[00191] Next, the bayonet coupling method of the mount mechanism 5000 according to the present modification will be described with reference to Figs. 24A through 25C. Note that the bayonet claws provided to the lens mount are in a state of being capable to engage the movable mount claws 5011a through 5011c of the movable mount portion 5010, in a state of being passed through an opening portion of the

operation portion 5030 and an opening portion of the fixed mount portion 5020. The state illustrated in Figs. 24A through 24C is a state where the operation portion 5030 is situated at an unlocked position. In this state, the lens mount face of the lens mount and the camera mount face 5021 of the fixed mount portion 5020 are in contact, but the claws of each of the lens mount and movable mount portion 5010 do not engage each other, and do not overlap, as viewed from the center axis direction. Figs. 24C is a cross-sectional diagram taken along cross-section XXIVC-XXIVC in Fig. 24B. Figs. 25A through 25C exemplify the mount mechanism 5000 in a state where the operation portion 5030 has been rotationally operated from this state.

[00192] The state illustrated in Figs. 25A through 25C is a state where the operation portion 5030 is situated in a locked position. In this state, the claws of each of the lens mount and movable mount portion 5010 overlap each other, and thereby are engaged in the center axis direction. In this state, the screwing state of the screw portion 5022 of the fixed mount portion 5020 and the screw portion 5012 of the movable mount portion 5010 changes in accordance with rotational operation of the operation portion 5030, and the movable mount portion 5010 moves toward the imaging device side in the center axis direction. Fig. 25C is a cross-sectional diagram taken along cross-section XXVC-XXVC in Fig.

25B. As illustrated in Figs. 24C and 25C, the movable mount portion 5010 moves away from the fixed mount portion 5020 in a center axis direction of the mount in accordance with a non-locked state of the mount mechanism 5000 changing to a locked state of the mount mechanism 5000. According to this configuration, each of the movable mount claws 5011a through 5011c in a state of being engaged with the bayonet claws at the lens mount side moves toward the imaging apparatus side.

[00193] As described above, the mount mechanism 5000 can move the movable mount portion in the center axis direction as to the fixed mount portion, by rotating the movable mount portion that has claws capable of engaging lens-mount-side claws on the center axis. According to this configuration, the mount mechanism 5000 according to the present embodiment can reduce occurrence of gaps (looseness) that occurs between the lens mount and camera-side mount in a coupled state.

[00194] Although a configuration has been described in the above modification where the mount mechanism 5000 is provided to the imaging apparatus side, this can be applied to a configuration where the mount mechanism 5000 is provided to a camera accessory side, such as an interchangeable lens or the like.

[00195] While the present invention has been described with reference to exemplary embodiments, it is to be

10177092KR01TW01IN01BR01RU01MY01PH01SG01TH01VN01

understood that the invention is not limited to the disclosed exemplary embodiments.

CLAIMS

1. An adapter device comprising a first mount on one side and a second mount on another side, where the first mount is detachably mountable to a first imaging apparatus, and the second mount is detachably mountable to a first accessory,

wherein the first mount has a first mount recess, a first mount claw, a second mount recess, a second mount claw, a third mount recess, and a third mount claw, disposed following a circumferential direction of the first mount,

wherein the second mount has a fourth mount claw, a fourth mount recess, a fifth mount claw, a fifth mount recess, a sixth mount claw, and a sixth mount recess, disposed following the circumferential direction of the second mount,

wherein the first, second, and third mount claws are insertable into corresponding mount recesses provided on a second imaging apparatus which is different from the first imaging apparatus, to detachably mount the first mount on the first imaging apparatus,

wherein the fourth, fifth, and sixth mount claws are insertable into mount recesses provided to a second accessory which is different from the first accessory, to detachably mount the second mount on the first accessory,

and wherein each of the mount claws mount and mount recesses extends radially over an angle range in the circumferential direction of the mounts, where a smallest angle range out of angle ranges of the first, second, and third mount recesses is equal to or smaller than a smallest angle range out of angle ranges of the fourth, fifth, and sixth mount claws.

2. The adapter device according to Claim 1,
wherein the first mount and the second mount each has a plurality of terminals that are arranged to enable electrical connection.

3. The adapter device according to Claim 1,
wherein the adapter device is configured with the first amount and the second mount having substantially the same mount diameter.

4. The adapter device according to Claim 1,
wherein, of the first, second, and third mount recesses disposed on the first mount, an angle range in the circumferential direction of two mutually adjacent mount recesses is equal to or smaller than an angle range in the circumferential direction of two mutually adjacent mount claws out of the fourth, fifth, and sixth mount claws.

5. The adapter device according to Claim 1,
wherein, of the first, second, and third mount recesses disposed on the first mount, an angle range in the circumferential direction of two mutually adjacent mount recesses is equal to or smaller than an angle range in the circumferential direction of all mount claws of the fourth, fifth, and sixth mount claws.

6. The adapter device according to Claim 1,
wherein the first mount is configured to couple to a third mount on which are disposed a plurality of mount recesses and mount claws corresponding to the first, second, and third mount recesses and the first, second and third mount claws, by a bayonet coupling method, whereby the adapter device can be detachably mounted to the first imaging apparatus having the third mount, and in a state where the adapter device is mounted to the first imaging apparatus, the first, second, and third mount claws engage the plurality of mount claws disposed on the third mount in a center axis direction of the first mount.

7. The adapter device according to Claim 6,
wherein the adapter device is arranged to transition between a first state wherein the first, second, and third

mount claws of the first mount are inserted into the corresponding mount recesses of the plurality of mount recesses of the third mount, and a second state wherein the first, second, and third mount claws are engaged with corresponding mount claws of the plurality of mount claws of the third mount in the center axis direction of the first mount, by relative rotation of the first mount and the third mount in the circumferential direction,

and wherein the second state is a state where the adapter device is mounted to the imaging apparatus.

8. The adapter device according to Claim 6, wherein the first mount has a restricting member arranged to restrict relative rotation of the first mount and the third mount in the circumferential direction, in a state where coupling of the first mount and the third mount by the bayonet coupling method has been completed,

wherein, in a case of viewing the first mount from the first imaging apparatus side, in a state where the first mount is mounted to the first imaging apparatus,

the first mount claw is disposed in a range of 159° to 212° from the restricting member in the circumferential direction,

the second mount claw is disposed in a range of 256° to 318° from the restricting member in the

circumferential direction, and

the third mount claw is disposed in a range of 54° to 107° from the restricting member in the circumferential direction.

9. The adapter device according to Claim 1,

wherein the second mount is arranged to couple to a fourth mount on which are disposed a plurality of mount recesses and mount claws corresponding to the fourth, fifth, and sixth mount recesses and the fourth, fifth, and sixth mount claws, by a bayonet coupling method, whereby the adapter device can be detachably mounted to the first accessory having the fourth mount, and in a state where the adapter device is mounted to the first accessory, the fourth, fifth, and sixth mount recesses engage the plurality of mount claws disposed on the fourth mount in a center axis direction of the second mount.

10. An adapter device comprising a first mount on one side and a second mount on another side, the first mount being configured to detachably attach to a first imaging apparatus, and the second mount being arranged to detachably attach to a first accessory,

wherein the first mount has a first mount recess, a first mount claw, a second mount recess, a second mount claw,

a third mount recess, and a third mount claw, disposed following a circumferential direction,

wherein the second mount has a fourth mount claw, a fourth mount recess, a fifth mount claw, a fifth mount recess, a sixth mount claw, and a sixth mount recess, disposed following the circumferential direction,

wherein the first, second, and third mount claws are insertable into corresponding mount recesses provided to a second imaging apparatus which is different from the first imaging apparatus,

wherein the fourth, fifth, and sixth mount claws are insertable to mount recesses provided to a second accessory which is different from the first accessory to detachably mount the second mount the first accessory,

and each of the mount claws mount and mount recessed extends radially over an angle range in the circumferential direction of the mounts, wherein a largest angle range out of angle ranges of the fourth, fifth, and sixth mount claws is smaller than a largest angle range out of angle ranges of the first, second, and third mount recesses.

11. The adapter device according to Claim 10,

wherein the first amount and the second mount have a plurality of terminals arranged to enable electrical connection.

12. The adapter device according to Claim 10,
wherein the adapter device has substantially the same
mount diameter for the first mount and the second mount.

13. The adapter device according to Claim 10,
wherein a total sum of angle ranges in the
circumferential direction of, out of the fourth, fifth, and
sixth mount claws and the fourth, fifth, and sixth mount
recesses, a mount recess serving as a reference, one mount
recess adjacent to this mount recess, and a mount claw
situated therebetween, when viewing the second mount from
the center axis direction of the second mount, is smaller
than a total sum of angle ranges in the circumferential
direction of, out of the first, second, and third mount
recesses and the first, second, and third mount claws, a
mount claw serving as a reference when viewing the first
mount from the center axis direction of the second mount,
one mount claw adjacent to this mount claw, and a mount
recess situated therebetween,

and wherein a total sum of angle ranges in the
circumferential direction, of the camera-side mount recess
serving as a reference, another mount recess adjacent to
this camera-side mount recess serving as a reference, and a
mount claw situated therebetween, when viewing the second

mount from the center axis direction of the second mount, is equal to or smaller than a total sum of angle ranges in the circumferential direction, of the accessory-side mount claw serving as a reference when viewing the second mount from the center axis direction of the second mount, another mount claw adjacent to this accessory-side mount claw serving as a reference, and a mount recess situated therebetween.

14. The adapter device according to Claim 10, wherein at least a total sum of angle ranges of the sixth mount recess and the fourth mount recess and the fourth mount claw situated therebetween in the circumferential direction, and a total sum of angle ranges of the fourth mount recess and the fifth mount recess and the fifth mount claw situated therebetween in the circumferential direction, when viewing the second mount from the center axis direction of the second mount, are smaller than a total sum of angle ranges of the third mount claw and the first mount claw and the first mount recess situated therebetween in the circumferential direction, a total sum of angle ranges of the first mount claw and the second mount claw and the second mount recess situated therebetween in the circumferential direction, and a total sum of angle ranges of the second mount claw and the third mount claw and the third mount recess situated therebetween

in the circumferential direction, when viewing the first mount from the center axis direction of the first mount.

15. The adapter device according to Claim 10,
wherein the second mount is configured to couple to a fourth mount on which are disposed a plurality of mount recesses and mount claws corresponding to the fourth, fifth, and sixth mount recesses and the fourth, fifth, and sixth mount claws, by a bayonet coupling method, whereby the adapter device can be detachably mounted to the accessory having the fourth mount, and in a state where the adapter device is mounted to the accessory, the fourth, fifth, and sixth mount claws engage the plurality of mount claws disposed on the fourth mount in the center axis direction.

16. The adapter device according to Claim 15,
wherein the adapter device is configured to transition between a first state wherein the fourth, fifth, and sixth mount claws of the second mount are inserted into corresponding mount recesses of the plurality of mount recesses of the fourth mount, and a second state wherein the fourth, fifth, and sixth mount claws are engaged with corresponding mount claws out of the plurality of mount claws of the fourth mount in the center axis direction of the second mount, by relative rotation of the second mount

and the fourth mount in the circumferential direction,
and wherein the second state is a state where the
adapter device is mounted to the accessory.

17. The adapter device according to Claim 15,
wherein the second mount has a restricting member
configured to restrict relative rotation of the second mount
and the fourth mount in the circumferential direction, in a
state where coupling of the second mount and the fourth
mount by the bayonet coupling method has been completed,
and wherein, in a case of viewing the second mount from
the side to which the fourth mount is provided,
the fourth mount claw is disposed in a range of
169° to 217° from the restricting member,
the fifth mount claw is disposed in a range of
274° to 314° from the restricting member, and
the sixth mount claw is disposed in a range of 20°
to 112° from the restricting member.

18. An imaging apparatus configured to be attachable
to an accessory having a first mount, the imaging apparatus
comprising:

a second mount having a plurality of mount claws
arranged to couple a plurality of mount claws provided to
the first mount by a bayonet coupling method,

wherein the plurality of mount claws on the second mount include a first mount claw, a second mount claw, and a third mount claw, each of the mount claws extending radially over an angle range in the circumferential direction of the mount, the angle range of the second mount claws and the third mount claw, in the circumferential direction is smaller than that of the first mount claw, disposed following a circumferential direction of the second mount,

wherein, in a case where a line extending from a center of the second mount in the gravitational direction and a direction opposite to the gravitational direction when viewing the imaging apparatus in a normal position from the center axis direction of the second mount is taken as a first mount center line, and a line orthogonal to the first mount center line is taken as a second mount center line,

the first mount claw overlaps the first mount center line, and at least one of the second mount claw and the third mount claw overlap the second mount center line, in the radial direction of the second mount, and

the angle range of the first mount claw is greater than the total sum of the angle range of the second mount claw and the angle range of the third mount claw.

19. The imaging apparatus according to Claim 18,
wherein, in a case of viewing the imaging apparatus in

a normal position from the center axis direction of the second mount, the total sum of angle ranges of the plurality of mount claws at a side including the opposite from the gravitational direction with the second mount center line as a reference in the circumferential direction of the second mount, is larger than the total sum of angle ranges of the plurality of mount claws at a side including the gravitational direction with the second mount center line as a reference.

20. The imaging apparatus according to Claim 18, further comprising:

a lock member configured to engage a lock groove provided to the accessory, in a state where the second mount and the first mount are bayonet-coupled,

wherein the lock member is provided on the opposite side across the first mount center line from at least one of the second mount claw and third mount claw that overlap the second mount center line.

21. The imaging apparatus according to Claim 18,

wherein the second mount includes a first mount recess between the first mount claw and the second mount claw, to which a fourth mount claw out of the plurality of claws provided to the first mount can be inserted, a second mount

recess between the second mount claw and the third mount claw, to which a fifth mount claw out of the plurality of claws provided to the first mount can be inserted, and a third mount recess between the third mount claw and the first mount claw, to which a sixth mount claw out of the plurality of claws provided to the first mount can be inserted,

and wherein the angle range of the first mount recess in the circumferential direction of the second mount is equal to or greater than the angle range of the second mount recess and third mount recess in the circumferential direction.

22. The imaging apparatus according to Claim 21, wherein the angle ranges of the second mount in the circumferential direction are 92° for the first mount claw, 48° for the second mount claw, and 40° for the third mount claw.

23. An accessory configured to be mounted to an imaging apparatus having a first mount, the accessory comprising:

a second mount having a plurality of mount claws and a plurality of mount recesses configured to couple a plurality of claws provided to the first mount by a bayonet coupling

method,

wherein the plurality of mount recesses, each of the mount recesses extending radially over an angle range in the circumferential direction of the mount, include a first mount recess, disposed following a circumferential direction of the second mount, and a second mount recess and a third mount recess that are that have an angle range in the circumferential direction that is smaller than that of the first mount recess,

wherein, in a case where a line extending from a center of the second mount in the gravitational direction and a direction opposite to the gravitational direction when viewing from the center axis direction of the second mount with the imaging apparatus to which the accessory is mounted in a normal position, is taken as a first mount center line,

the first mount center line does not overlap any of the plurality of mount recesses, and

the angle range that the first mount recess occupies on the second mount is equal to or greater than the total sum of the angle range that the second mount recess occupies and the angle range that the third mount recess occupies.

24. The accessory according to Claim 23,

wherein at least two claws of the first mount claw, the

second mount claw, and the third mount claw, overlap the first mount center line in the radial direction of the second mount.

25. The accessory according to Claim 23,
wherein the accessory is configured to transition between a first state wherein the plurality of mount claws are inserted between the plurality of claws, and a second state where coupling of the second mount to the first mount is completed by the plurality of claws and the plurality of mount claws being engaged with each other in the optical axis direction.

26. The accessory according to Claim 23,
wherein the first mount claw and the second mount claw overlap the first mount center line in the radial direction of the second mount.

27. The accessory according to Claim 26,
wherein a line orthogonal to the first mount center line when viewing the accessory from the center axis direction of the second mount, in a state where the accessory is mounted to the imaging apparatus, is taken as a second mount center line,
and wherein the third mount claw overlaps the second

mount center line in the radial direction of the second mount.

28. The accessory according to Claim 27,
wherein the accessory has a lock groove configured to engage a lock member provided to the imaging apparatus, in a state where the second mount and the first mount are bayonet-coupled,

and wherein the lock groove is provided on the opposite side across the first mount center line from the third mount claw that overlaps the second mount center line, in the radial direction of the second mount.

29. The accessory according to Claim 23,
wherein, on the second mount, a fourth mount claw out of the plurality of claws provided to the first mount can be inserted to the first mount recess, a fifth mount claw out of the plurality of claws provided to the first mount can be inserted to the second mount recess, and a sixth mount claw out of the plurality of claws provided to the first mount can be inserted to the third mount recess.