



G00002

-1-

TITLE OF THE INVENTION**SEMICONDUCTOR MEMORY CELL**

159159

BACKGROUND OF THE INVENTION AND RELATED ART STATEMENT

5 The present invention relates to a
semiconductor memory cell which comprises at least a
first transistor for readout, a second transistor for
switching and an MIS (Metal-Insulator-Semiconductor)
type diode for retaining information and which does not
10 require a so-called refresh operation for retaining
information. Otherwise, it relates to a semiconductor
memory cell which comprises at least a first transistor
for readout, a second transistor for switching, a
junction type transistor for current control and an MIS
15 type diode for retaining information and which does not
require a so-called refresh operation for retaining
information.

 As a high-density semiconductor memory cell,
conventionally, there is used a dynamic semiconductor
20 memory cell that is called a single-transistor
semiconductor memory cell including one transistor and
one capacitor as shown in Fig. 210A. In the above
semiconductor memory cell, an electric charge stored in
the capacitor is required to be large enough to generate
25 a sufficiently large voltage change on a bit line.
However, with a decrease in the planar dimensions of the
semiconductor memory cell, the capacitor formed in a
parallel planar shape decreases in size, which causes
the following new problem. When information stored as
30 an electric charge in the capacitor of the semiconductor
memory cell is read out, the read-out information is
buried in a noise. Or, since the stray capacitance of
the bit line in the semiconductor memory cell increases
from generation to generation, only a small voltage
35 change is generated on the bit line. As means for
solving the above problems, there has been proposed a
dynamic semiconductor memory cell having a trench

-2-

capacitor cell structure as shown in Fig. 210B or a stacked capacitor cell structure. Since, however, the fabrication-related technology has its own limits on the depth of the trench (or groove) or the height of the stack, the capacitance of the capacitor is also limited. For this reason, dynamic semiconductor memory cells having the above structures are said to encounter the above limits unless expensive new materials are introduced for the capacitor as far as the dimensions thereof beyond the deep sub-micron rule (low sub-micron rule) are concerned.

In the planar dimensions smaller than those of the deep sub-micron rule (low sub-micron rule), the transistor constituting the semiconductor memory cell also has problems of deterioration of the drain breakdown voltage and a punchthrough from a drain region to a source region. There is therefore a large risk that current leakage takes place even if the voltage applied to the semiconductor memory cell is still within a predetermined range. When a semiconductor memory cell is made smaller in size, therefore, it is difficult to normally operate the semiconductor memory cell having a conventional transistor structure.

For overcoming the above limit problems of the capacitor, the present Applicant has proposed a semiconductor memory cell comprising two transistors or two transistors physically merged into one unit, as is disclosed in Japanese Patent Application No. 246264/1993 (JP-A-7-99251) corresponding to U.S. Patent No. 5,428,238. The following explanation is made by referring to Japanese Patent Application No. 246264/1993 (JP-A-7-99251). The semiconductor memory cell shown in Figs. 15(A) and 15(B) of the above Japanese Patent Application comprises a first semi-conductive region SC₁ of a first conductivity type formed in a surface region of a semiconductor substrate or formed on an insulating substrate, a first conductive region SC₂ formed in a

-3-

surface region of the first semi-conductive region SC_1 so as to form a rectifier junction together with the first semi-conductive region SC_1 , a second semi-conductive region SC_3 of a second conductivity type

5 formed in a surface region of the first semi-conductive region SC_1 and spaced from the first conductive region SC_2 , a second conductive region SC_4 formed in a surface region of the second semi-conductive region SC_3 so as to form a rectifier junction together with the second semi-

10 conductive region SC_3 , and a conductive gate G formed on a barrier layer so as to bridge the first semi-conductive region SC_1 and the second conductive region SC_4 and so as to bridge the first conductive region SC_2 and the second semi-conductive region SC_3 , the

15 conductive gate G being connected to a first memory-cell-selecting line, the first conductive region SC_2 being connected to a write-in information setting line, and the second conductive region SC_4 being connected to a second memory-cell-selecting line.

20 The first semi-conductive region SC_1 (functioning as a channel forming region Ch_2), the first conductive region SC_2 and the second semi-conductive region SC_3 (functioning as source/drain regions) and the conductive gate G constitute a switching transistor TR_2 .

25 On the other hand, the second semi-conductive region SC_3 (functioning as a channel forming region Ch_1), the first semi-conductive region SC_1 and the second conductive region SC_4 (functioning as source/drain regions) and the conductive gate G constitute an information storing

30 transistor TR_1 .

When information is written in the above semiconductor memory cell, the switching transistor TR_2 is brought into an on-state. As a result, the information is stored in the channel forming region Ch_1

35 of the information storing transistor TR_1 as a potential or as an electric charge. When the information is read out, the threshold voltage of the information storing

-4-

transistor TR_1 seen from the conductive gate G varies, depending upon the potential or the electric charge stored in the channel forming region Ch_1 of the information storing transistor TR_1 . Therefore, when the
5 information is read out, the storage state of the information storing transistor TR_1 can be judged from the magnitude of a channel current (including a zero magnitude) by applying a properly selected potential to the conductive gate G. The information is read out by
10 detecting the operation state of the information storing transistor TR_1 .

That is, when information is read out, the information storing transistor TR_1 is brought into an on-state or an off-state, depending upon the information
15 stored therein. Since the second conductive region SC_4 is connected to the second line, a current which is large or small depending upon the stored information ("0" or "1") flows in the information storing transistor TR_1 . In this way, the information stored in the
20 semiconductor memory cell can be read out through the information storing transistor TR_1 .

Further, the present Applicant in Japanese Patent Application No. 251646/1997 (JP-A-10-154757) has proposed a semiconductor memory cell comprising three
25 transistors such as a transistor TR_1 for readout, a transistor TR_2 for switching and a junction type transistor TR_3 for current control.

In the above semiconductor memory cell, information is stored in the second semi-conductive
30 region SC_3 . However, the second semiconductor-conductive region SC_3 is a floating region, so that the information disappears due to a leak current after a certain period of time. For retaining the information, therefore, there is required an refresh operation every
35 constant period of time.

OBJECT AND SUMMARY OF THE INVENTION

-5-

It is therefore a first object of the present invention to provide a memory cell which requires no refresh operation for retaining information, permits reliable writing and readout of information, has transistor operation stabilized, has a large window (current difference) for reading out information in the memory cell, requires no large-capacitance capacitor unlike a conventional DRAM and permits a decrease in dimensions, or a semiconductor memory cell for a logic, and further to provide a semiconductor memory cell comprising at least two transistors and a diode for retaining information or comprising a memory cell in which these are merged into one unit.

It is a second object of the present invention to provide a memory cell which requires no refresh operation for retaining information, permits reliable writing and readout of information, has transistor operation stabilized, has a large window (current difference) for reading out information in the memory cell, requires no large-capacitance capacitor unlike a conventional DRAM and permits a decrease in dimensions, or a semiconductor memory cell for a logic, and further to provide a semiconductor memory cell comprising at least two transistors, a junction type transistor for current control and a diode for retaining information or a semiconductor memory cell in which these are merged into one unit.

According to a first aspect of the present invention for achieving the above first object, there is provided a semiconductor memory cell comprising;

(1) a first transistor for readout, having a first conductivity type, and having source/drain regions, a semi-conductive channel forming region which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively coupled with the channel forming region,

(2) a second transistor for switching, having a

-6-

second conductivity type, and having source/drain regions, a semi-conductive channel forming region which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively
5 coupled with the channel forming region, and

(3) an MIS type diode for retaining information, wherein:

one source/drain region of the first transistor corresponds to the channel forming region of the second
10 transistor,

one source/drain region of the second transistor corresponds to the channel forming region of the first transistor, and

one end of the MIS type diode is formed of an
15 extending portion of the channel forming region of the first transistor, the other end of the MIS type diode is formed of an electrode composed of an electrically conductive material, and the electrode is connected to a line having a predetermined potential.

20 In the present specification, that X "corresponds to" Y refers to a constitution in which X and Y are shared, or in which X has a common region with Y, or in which X and Y are connected to each other. For example, the above expression "one source/drain region
25 of the first transistor corresponds to the channel forming region of the second transistor" refers to a constitution in which one source/drain region of the first transistor and the channel forming region of the second transistor are shared, or in which one
30 source/drain region of the first transistor has a common region with the channel forming region of the second transistor, or a constitution in which one source/drain region of the first transistor is connected to the channel forming region of the second transistor. The
35 term "corresponds to" is used in this sense hereinafter in some cases.

The semi-conductor memory cell according to

-7-

the first aspect of the present invention preferably has the following constitution. A material is interposed between one end and the other end of the MIS diode, in which material the tunnel transition of carriers is

5 caused depending upon a potential difference between the potential in the channel forming region of the first transistor and the potential in the other end of the MIS type diode. And, binary information of first information or second information is stored in the

10 semiconductor memory cell, the first information to be stored in the semiconductor memory cell corresponds to a first potential in the channel forming region of the first transistor, and the second information to be stored in the semiconductor memory cell corresponds to a

15 second potential in the channel forming region of the first transistor. (i) When the potential in the channel forming region of the first transistor is the first potential, the tunnel transition of carriers is caused from the other end to one end of the MIS type diode. As

20 a result, carrier multiplication takes place, holes or electrons are stored in the channel forming region of the first transistor depending upon the conductivity type of one end of the MIS type diode, and the potential in the channel forming region of the first transistor is

25 held nearly at the first potential. (ii) When the potential in the channel forming region of the first transistor is the second potential, carriers having the polarity opposite to that of the above carriers transit from one end to the other end of the MIS type diode. As

30 a result, the potential in the channel forming region of the first transistor is held at the second potential.

The semiconductor memory cell according to the first aspect of the present invention may have the following constitution. The gate of the first

35 transistor and the gate of the second transistor are connected to a word line, the other source/drain region of the first transistor is connected to a bit line, the

-8-

other source/drain region of the second transistor is connected to a write-in information setting line, and the other end of the MIS type diode is connected to the line having a predetermined potential through a high-resistance element. Otherwise, there may be employed a constitution in which the gate of the first transistor and the gate of the second transistor are connected to a word line, one source/drain region of the first transistor is connected to a bit line, the other source/drain region of the second transistor is connected to a write-in information setting line, and the other end of the MIS type diode is connected to the line having a predetermined potential through a high-resistance element. It is preferred to provide the above high-resistance element under bias conditions where there is a risk of excess current flowing in the MIS type diode. Further, there may be also employed a constitution in which a diode is further provided, the gate of the first transistor and the gate of the second transistor are connected to a word line, one source/drain region of the first transistor is connected to a write-in information setting line through the diode, the other source/drain region of the first transistor is connected to a bit line, the other source/drain region of the second transistor is connected to the write-in information setting line, and the other end of the MIS type diode is connected to the line having a predetermined potential through a high-resistance element. Moreover, there may be also employed a constitution in which a diode is further provided, a write-in information setting line functions as a bit line, the gate of the first transistor and the gate of the second transistor are connected to a word line, one source/drain region of the first transistor is connected to the write-in information setting line through the diode, the other source/drain region of the second transistor is connected to the write-in information

-9-

setting line, and the other end of the MIS type diode is connected to the line having a predetermined potential through a high-resistance element. The deterioration of characteristics of a wide gap thin film to be described
5 later can be prevented by connecting the other end of the MIS type diode to the line (a third line to be described latter) through the high-resistance element.

In the semiconductor memory cell according to the first aspect of the present invention, the gate
10 of the first transistor and the gate of the second transistor may be formed separately from each other. For decreasing the size of the semiconductor memory cell, however, it is preferred to employ a constitution in which the first transistor and the second transistor
15 have a common gate.

Preferably, a wide gap thin film is formed between the extending portion of channel forming region of the first transistor constituting the MIS type diode and the electrode. That is, the wide gap thin film is
20 preferably composed of a material in which the tunnel transition of carriers is caused depending upon a potential difference between the potential in the channel forming region of the first transistor and the potential in the other end of the MIS type diode.

According to a second aspect of the present invention for achieving the above first object, there is provided a semiconductor memory cell comprising, as a drawing of its principle is shown in Fig. 1,

(1) a first transistor for readout, having a
30 second conductivity type, and having source/drain regions, a semi-conductive channel forming region which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively coupled with the channel forming region,

35 (2) a second transistor for switching, having a second conductivity type, and having source/drain regions, a semi-conductive channel forming region which

-10-

is in contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively coupled with the channel forming region, and

(3) an MIS type diode for retaining information,
5 the semiconductor memory cell having;

(a) a semi-conductive first region having a first conductivity type,

(b) a semi-conductive second region being in contact with the first region and having a second
10 conductivity type,

(c) a third region which is formed in a surface region of the first region to be spaced from the second region and is in contact with the first region so as to form a rectifier junction together with the first region,
15 and

(d) a fourth region which is formed in a surface region of the second region to be spaced from the first region and is in contact with the second region so as to form a rectifier junction together with the second
20 region,

wherein:

(A-1) one source/drain region of the first transistor is formed of a surface region of the first region which surface region is interposed between the
25 second region and the third region,

(A-2) the other source/drain region of the first transistor is formed of the fourth region,

(A-3) the channel forming region of the first transistor is formed of a surface region of the second region which surface region is interposed between the
30 surface region of the first region and the fourth region,

(A-4) the gate of the first transistor is formed on the channel forming region of the first transistor through an insulation layer,

(B-1) one source/drain region of the second transistor is formed of the surface region of the second region which surface region constitutes the channel
35

-11-

forming region of the first transistor,

(B-2) the other source/drain region of the second transistor is formed of the third region,

(B-3) the channel forming region of the second transistor is formed of the surface region of the first region which surface region constitutes one source/drain region of the first transistor,

(B-4) the gate of the second transistor is formed on the channel forming region of the second transistor through an insulation layer,

(C-1) one end of the MIS type diode is formed of part of the second region,

(C-2) an electrode constituting the other end of the MIS type diode is formed to be opposed to said part of the second region constituting one end of the MIS type diode, through a wide gap thin film,

(D) the gate of the first transistor and the gate of the second transistor are connected to a first line for memory cell selection,

(E) the third region is connected to a write-in information setting line,

(F) the fourth region is connected to a second line,

(G) the electrode constituting the other end of the MIS type diode is connected to a third line having a predetermined potential, and

(H) the first region is connected to a fourth line.

In drawings, the write-in information setting line is indicated by "WISL".

In the semiconductor memory cell according to the second aspect of the present invention, there may be employed a constitution in which the second line is used as a memory-cell-selecting line (so-called bit line) and a second predetermined potential is applied to the fourth line. Otherwise, there may be employed a constitution in which a second predetermined potential is applied to the second line and the fourth line is

-12-

used as a memory-cell-selecting line (so-called bit line).

According to a third aspect of the present invention for achieving the above first object, there is
5 provided a semiconductor memory cell comprising, as a drawing of its principle is shown in Fig. 4,

(1) a first transistor for readout, having a first conductivity type, and having source/drain regions, a semi-conductive channel forming region which is in
10 contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively coupled with the channel forming region,

(2) a second transistor for switching, having a second conductivity type, and having source/drain
15 regions, a semi-conductive channel forming region which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively coupled with the channel forming region, and

(3) an MIS type diode for retaining information,
20 the semiconductor memory cell having;

(a) a semi-conductive first region having a first conductivity type,

(b) a semi-conductive second region being in contact with the first region and having a second
25 conductivity type,

(c) a third region which is formed in a surface region of the first region to be spaced from the second region and is in contact with the first region so as to form a rectifier junction together with the first region,

30 (d) a semi-conductive fourth region which is formed in a surface region of the second region to be spaced from the first region and has the first conductivity type, and

(e) a semi-conductive MIS-type-diode constituting
35 region which is formed in a surface region of the fourth region and has the second conductivity type,

wherein:

-13-

(A-1) one source/drain region of the first transistor is formed of a surface region of the first region which surface region is interposed between the second region and the third region,

5 (A-2) the other source/drain region of the first transistor is formed of the fourth region,

(A-3) the channel forming region of the first transistor is formed of a surface region of the second region which surface region is interposed between the
10 surface region of the first region and the fourth region,

(A-4) the gate of the first transistor is formed on the channel forming region of the first transistor through an insulation layer,

(B-1) one source/drain region of the second
15 transistor is formed of the surface region of the second region which surface region constitutes the channel forming region of the first transistor,

(B-2) the other source/drain region of the second transistor is formed of the third region,

20 (B-3) the channel forming region of the second transistor is formed of the surface region of the first region which surface region constitutes one source/drain region of the first transistor,

(B-4) the gate of the second transistor is formed
25 on the channel forming region of the second transistor through an insulation layer,

(C-1) one end of the MIS type diode is formed of the MIS-type-diode-constituting region,

(C-2) an electrode constituting the other end of
30 the MIS type diode is formed to be opposed to the MIS-type-diode-constituting region constituting one end of the MIS type diode, through a wide gap thin film,

(D) the gate of the first transistor and the gate of the second transistor are connected to a first line
35 for memory cell selection,

(E) the second region is connected to the MIS-type-diode-constituting region,

-14-

(F) the third region is connected to a write-in information setting line,

(G) the fourth region is connected to a second line,

5 (H) the electrode constituting the other end of the MIS type diode is connected to a third line having a predetermined potential, and

(I) the first region is connected to a fourth line.

In the semiconductor memory cell according
10 to the third aspect of the present invention, there may be employed a constitution in which the second line is used as a memory-cell-selecting line (so-called bit line) and a second predetermined potential is applied to the fourth line. Otherwise, there may be employed a
15 constitution in which a second predetermined potential is applied to the second line and the fourth line is used as a memory-cell-selecting line (so-called bit line).

In the semiconductor memory cell according
20 to the second or third aspect of the present invention, preferably, the electrode constituting the other end of the MIS type diode is connected to the third line through a high-resistance element for preventing the deterioration of characteristics of the wide gap thin
25 film. Preferably, the electrode constituting the other end of the MIS type diode and the high-resistance element are integrally formed and are composed of a silicon thin layer (for example, polysilicon thin layer) in view of the simplification of a wiring structure.
30 Further, preferably, the silicon thin layer contains an impurity having the first conductivity type.

In the semiconductor memory cell according to the second or third aspect of the present invention, the gate of the first transistor and the gate of the
35 second transistor may be provided separately from each other. For decreasing the semiconductor memory cell in size, however, it is preferred to employ a constitution

-15-

in which the gate of the first transistor and the gate of the second transistor are formed so as to bridge the first region and the fourth region and so as to bridge the second region and third region through the
5 insulation layer, and are shared by the first transistor and the second transistor.

In the semiconductor memory cell according to the second or third aspect of the present invention, it is preferred to employ a constitution in which the
10 first region and the third region constitute a diode, and the first region is connected to the write-in information setting line through the third region in place of being connected to the fourth line, as a drawing of its principle is shown in Fig. 2 or 5, in
15 view of the simplification of a wiring structure. When it is required to avoid possibility where carriers implanted from the diode may latch up the semiconductor memory cell, it is preferred to employ a constitution in which a majority carrier-diode (which means a Schottky
20 diode or a hetero-junction diode in which majority carriers flow, and used in this sense hereinafter) comprising the diode-constituting region provided in a surface region of the first region and the first region is further provided, and the first region is connected
25 to the write-in information setting line through the diode-constituting region in place of being connected to the fourth line, as a drawing of its principle is shown in Fig. 3 or 6. In this constitution, there may be employed a structure in which the diode-constituting
30 region has a common region with part of the write-in information setting line (in other words, a structure in which the diode-constituting region and part of the write-in information setting line are formed as a common region).

35 In the semiconductor memory cell according to the second or third aspect of the present invention, preferably, the wide gap thin film is composed of a

-16-

material in which the tunnel transition of carriers is caused depending upon a potential difference between the potential in the channel forming region of the first transistor and the potential in the other end of the MIS type diode. And, it is preferred to employ the following constitution. Binary information of first information or second information is stored in the semiconductor memory cell, the first information to be stored in the semiconductor memory cell corresponds to a first potential in the channel forming region of the first transistor, and the second information to be stored in the semiconductor memory cell corresponds to a second potential in the channel forming region of the first transistor. (i) When the potential in the channel forming region of the first transistor is the first potential, the tunnel transition of carriers is caused from the other end to one end of the MIS type diode. As a result, carrier multiplication takes place, holes or electrons are stored in the channel forming region of the first transistor depending upon the conductivity type of one end of the MIS type diode, and the potential in the channel forming region of the first transistor is held nearly at the first potential. (ii) When the potential in the channel forming region of the first transistor is the second potential, carriers having the polarity opposite to that of the above carriers transit from one end to the other end of the MIS type diode. As a result, the potential in the channel forming region of the first transistor is held at the second potential.

In a preferred embodiment of the semiconductor memory cell according to the second or third aspect of the present invention, it is preferred to form a first high-concentration-impurity-containing layer having the first conductivity type below the second region, since the potential or charge to be stored in the channel forming region of the first transistor can be increased.

-17-

In the semiconductor memory cell according to the second or third aspect of the present invention, there may be employed a constitution in which the second region is formed in a surface region of the first region, or the first region is formed in a surface region of the second region. In the former case, it is preferred to form a second high-concentration-impurity-containing layer having the first conductivity type below the first region, since the wiring structure can be simplified. That is, the connection between the first region and the fourth line can be simplified by using the second high-concentration-impurity-containing layer having the first conductivity type as the fourth line.

In the semiconductor memory cell according to the second or third aspect of the present invention, the third region may be composed of a silicide, a metal or a metal compound, while the third region is preferably composed of semiconductor. In the memory cell according to the second aspect of the present invention, the fourth region may be composed of a silicide, a metal or a metal compound, while the fourth region is preferably composed of semiconductor. Further, in the memory cell according to the second or third aspect of the present invention, when a diode-constituting region is provided for forming the majority carrier-diode, the diode-constituting region may be composed of a semiconductor, while the diode-constituting region is preferably composed of a silicide, a metal or a metal compound, and in this case, the third region is preferably composed of semiconductor. The structure in which the third region is connected to the write-in information setting line includes a structure in which the third region has a common region with part of the write-in information setting line (in other words, a structure in which the diode-constituting region and part of the write-in information setting line are formed as a common region). Further, in the memory cell

-18-

according to the second aspect of the present invention, the structure in which the fourth region is connected to the second line includes a structure in which the fourth region has a common region with part of the second line
5 (in other words, a structure in which the fourth region and part of the second line are formed as a common region).

According to a fourth aspect of the present invention for achieving the above first object, there is
10 provided a semiconductor memory cell having a semiconductor layer having two main surfaces opposed to each other, the main surfaces being a first main surface and a second main surface,

the semiconductor memory cell comprising;
15 (1) a first transistor for readout, having a first conductivity type, and having source/drain regions, a semi-conductive channel forming region which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively coupled
20 with the channel forming region,

(2) a second transistor for switching, having a second conductivity type, and having source/drain regions, a semi-conductive channel forming region which is in contact with the source/drain regions and spaces
25 out the source/drain regions, and a gate capacitively coupled with the channel forming region, and

(3) an MIS type diode for retaining information,
the semiconductor memory cell further having;

30 (a) a semi-conductive first region which is formed in the semiconductor layer to extend over from the first main surface to the second main surface and has a first conductivity type,

(b) a semi-conductive second region which is
35 formed in the semiconductor layer to extend over from the first main surface to the second main surface, is in contact with the first region and has a second

-19-

conductivity type,

(c) a third region which is formed in a surface region including the second main surface of the first region to be spaced from the second region and is in
5 contact with the first region so as to form a rectifier junction together with the first region,

(d) a fourth region which is formed in a surface region including the first main surface of the second region to be spaced from the first region and is in
10 contact with the second region so as to form a rectifier junction together with the second region,

(e) the gate of the first transistor formed on a first insulation layer formed on the first main surface so as to bridge the first region and the fourth region,
15 and

(f) the gate of the second transistor formed on a second insulation layer formed on the second main surface so as to bridge the second region and the third region,

20 wherein:

(A-1) one source/drain region of the first transistor is formed of a surface region including the first main surface of the first region,

(A-2) the other source/drain region of the first
25 transistor is formed of the fourth region,

(A-3) the channel forming region of the first transistor is formed of a surface region including the first main surface of the second region which surface region is interposed between the surface region
30 including the first main surface of the first region and the fourth region,

(B-1) one source/drain region of the second transistor is formed of a surface region including the second main surface of the second region,

(B-2) the other source/drain region of the second
35 transistor is formed of the third region,

(B-3) the channel forming region of the second

-20-

transistor is formed of a surface region including the second main surface of the first region which surface region is interposed between the surface region including the second main surface of the second region and the third region,

(C-1) one end of the MIS type diode is formed of part of the second region,

(C-2) an electrode constituting the other end of the MIS type diode is formed to be opposed to said part of the second region constituting one end of the MIS type diode, through a wide gap thin film,

(D) the gate of the first transistor and the gate of the second transistor are connected to a first line for memory cell selection,

(E) the third region is connected to a write-in information setting line,

(F) the fourth region is connected to a second line,

(G) the electrode constituting the other end of the MIS type diode is connected to a third line having a predetermined potential, and

(H) the first region is connected to a fourth line.

In the semiconductor memory cell according to the fourth aspect of the present invention, there may be employed a constitution in which the second line is used as a memory-cell-selecting line (so-called bit line) and a second predetermined potential is applied to the fourth line. Otherwise, there may be also employed another constitution in which a second predetermined potential is applied to the second line and the fourth line is used as a memory-cell-selecting line (so-called bit line).

In the semiconductor memory cell according to the fourth aspect of the present invention, there may be employed a constitution in which the first region and the third region constitute a diode, and the first region is connected to the write-in information setting

-21-

line through the third region in place of being connected to the fourth line, whereby the wiring structure can be simplified. In this case, there may be employed a constitution in which the second line is used
5 as a memory-cell-selecting line (so-called bit line) or the write-in information setting line is co-used as a bit line and a second predetermined potential is applied to the second line.

In the semiconductor memory cell according
10 to the forth aspect of the present invention or a memory cell according to any one of the 25th to 29th aspect of the present invention to be described later, when a diode is provided, a wiring structure can be simplified. Further, in the memory cell according to the forth
15 aspect or any one of the 25th to 29th aspect of the present invention, it is not necessary that the gate of the first transistor formed on the first main surface side and the gate of the second transistor formed on the second main surface side should be connected every
20 memory cell. The gates of the first transistors of mutually adjacent semiconductor memory cells in the range of a predetermined number or a predetermined arrangement may be connected to each other, the gates of the second transistors of mutually adjacent
25 semiconductor memory cells in the range of a predetermined number or a predetermined arrangement may be connected to each other, and these are connected to the first line for memory cell selection.

In the semiconductor memory cell according
30 to the fourth aspect of the present invention, when the third region or the fourth region is formed as a conductive region, these regions may be composed of a silicide, a metal or a metal compound. When these regions are to be composed of a silicide, a metal or a
35 metal compound, and when there is to be employed a constitution in which these regions are connected to the lines, these regions may be composed of the same

-22-

material as the material of the lines (for example, a material such as titanium silicide or TiN for use as a barrier layer or a glue layer). That is, these regions and part of the lines may be formed as a structurally
5 common region.

According to a fifth aspect of the present invention for achieving the above second object, there is provided a semiconductor memory cell comprising, as a drawing of its principle is shown in Fig. 44, 45A, 45B,
10 46, 47A, 47B, 48, 49, 50A, 50B, 61, 62A, 62B, 65, 66A, 66B, 67, 68A or 68B,

(1) a first transistor for readout, having a first conductivity type, and having source/drain regions, a semi-conductive channel forming region which is in
15 contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively coupled with the channel forming region,

(2) a second transistor for switching, having a second conductivity type, and having source/drain
20 regions, a semi-conductive channel forming region which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively coupled with the channel forming region,

(3) a junction-field-effect transistor for current
25 control, having source/drain regions, a channel region and gate regions, and

(4) an MIS type diode for retaining information,
wherein:

one source/drain region of the first transistor
30 corresponds to the channel forming region of the second transistor and corresponds to one source/drain region of the junction-field-effect transistor,

one source/drain region of the second transistor corresponds to the channel forming region of the first
35 transistor and corresponds to one gate region of the junction-field-effect transistor, and

one end of the MIS type diode is formed of an

-23-

extending portion of the channel forming region of the first transistor, the other end of the MIS type diode is formed of an electrode composed of a conductive material, and the electrode is connected to a line having a
5 predetermined potential.

In the semiconductor memory cell according to the fifth aspect of the present invention, there may be employed a constitution in which the gate of the first transistor and the gate of the second transistor
10 are connected to a first line for memory cell selection (for example, word line), the other source/drain region of the first transistor is connected to a second line, the other end of the MIS type diode is connected to a third line corresponding to the above line having a
15 predetermined potential through a high-resistance element, the other gate region of the junction-field-effect transistor is connected to a fourth line, one source/drain region of the first transistor is connected to a fifth line through the junction-field-effect
20 transistor, and the other source/drain region of the second transistor is connected to a write-in information setting line. Under bias conditions where there is a risk of excessive current flowing in the MIS type diode, it is preferred to provide the above high-resistance
25 element. Further, when the other end of the MIS type diode is connected to the above third line having a predetermined potential through the high-resistance element, the property degradation of a wide gap thin film to be described later can be prevented. It is
30 preferred to employ a constitution in which the second line is used as a bit line and a second predetermined potential is applied to the fifth line or a constitution in which the fifth line is used as a bit line and a second predetermined potential is applied to the second
35 line.

There may be also employed another constitution in which one source/drain region of the

-24-

first transistor is connected to the write-in information setting line through the junction-field-effect transistor and a diode in place of being connected to the fifth line through the junction-field-effect transistor. In this case, it is preferred to employ a constitution in which the second line is used as a bit line or a constitution in which the write-in information setting line is co-used as a bit line and a second predetermined potential is applied to the second line. In explanations to be made hereinafter, when a diode, a pn junction diode to be described later or a majority carrier diode is provided, it is preferred to employ a constitution in which the second line is used as a bit line or a constitution in which the write-in information setting line is co-used as a bit line and a second predetermined potential is applied to the second line.

There may be also employed another constitution in which the other gate region of the junction-field-effect transistor is connected to the write-in information setting line in place of being connected to the fourth line. In this case, there may be employed a constitution in which one source/drain region of the first transistor is connected to the write-in information setting line through the junction-field-effect transistor and a diode in place of being connected to the fifth line through the junction-field-effect transistor.

There may be employed still another constitution in which one source/drain region of the first transistor is connected to the fourth line through the junction-field-effect transistor and a diode in place of being connected to the fifth line through the junction-field-effect transistor.

There may be also employed yet another constitution in which the other gate region of the junction-field-effect transistor is connected to one

-25-

gate region of the junction-field-effect transistor in place of being connected to the fourth line. In this case, one end of the MIS type diode and the other gate region of the junction-field-effect transistor may be
5 formed as a common region. In these cases, there may be employed a constitution in which one source/drain region of the first transistor is connected to the write-in information setting line through the junction-field-effect transistor and a diode in place of being
10 connected to the fifth line through the junction-field-effect transistor.

According to a sixth aspect of the present invention for achieving the above second object, there is provided a semiconductor memory cell comprising, as a
15 drawing of its principle is shown in Fig. 92, 93A, 93B, 94, 95A, 95B, 96, 97A, 97B, 104, 105A, 105B, 108, 109A, 109B, 110, 111A, 111B, 112, 113A, 113B, 126, 127A or 127B,

(1) a first transistor for readout, having a first
20 conductivity type, and having source/drain regions, a semi-conductive channel forming region which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively coupled with the channel forming region,

(2) a second transistor for switching, having a
25 second conductivity type, and having source/drain regions, a semi-conductive channel forming region which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively
30 coupled with the channel forming region,

(3) a junction-field-effect transistor for current control, having source/drain regions, a channel region and gate regions, and

(4) an MIS type diode for retaining information,
35 wherein:

one source/drain region of the first transistor corresponds to the channel forming region of the second

-26-

transistor,

the other source/drain region of the first transistor corresponds to one source/drain region of the junction-field-effect transistor,

5 one source/drain region of the second transistor corresponds to the channel forming region of the first transistor and corresponds to one gate region of the junction-field-effect transistor, and

10 one end of the MIS type diode is formed of an extending portion of the channel forming region of the first transistor, the other end of the MIS type diode is formed of an electrode composed of a conductive material, and the electrode is connected to a line having a predetermined potential.

15 In the semiconductor memory cell according to the sixth aspect of the present invention, there may be employed a constitution in which the gate of the first transistor and the gate of the second transistor are connected to a first line for memory cell selection
20 (for example, word line), the other source/drain region of the first transistor is connected to a second line through the junction-field-effect transistor, the other end of the MIS type diode is connected to a third line corresponding to the above line having a predetermined
25 potential through a high-resistance element, the other gate region of the junction-field-effect transistor is connected to a fourth line, one source/drain region of the first transistor is connected to a fifth line, and the other source/drain region of the second transistor
30 is connected to a write-in information setting line. It is preferred to employ a constitution in which the second line is used as a bit line and a second predetermined potential is applied to the fifth line, or a constitution in which the fifth line is used as a bit
35 line and a second predetermined potential is applied to the second line.

In the above case, there may be also

-27-

employed a constitution in which one source/drain region of the first transistor is connected to the write-in information setting line through a diode in place of being connected to the fifth line.

5 There may be employed another constitution in which the other gate region of the junction-field-effect transistor is connected to the write-in information setting line in place of being connected to the fourth line. In this case, there may be employed a
10 constitution in which one source/drain region of the first transistor is connected to the write-in information setting line through a diode in place of being connected to the fifth line.

 There may be also employed a constitution in
15 which the other gate region of the junction-field-effect transistor is connected to one gate region of the junction-field-effect transistor in place of being connected to the fourth line. In this case, one end of the MIS type diode and the other gate region of the
20 junction-field-effect transistor can be formed as a common region. In these cases, there may be employed a constitution in which one source/drain region of the first transistor is connected to the write-in information setting line through a diode in place of
25 being connected to the fifth line.

 According to a seventh aspect of the present invention for achieving the above second object, there is provided a semiconductor memory cell comprising, as a drawing of its principle is shown in Fig. 132, 133A or
30 133B,

(1) a first transistor for readout, having a first conductivity type, and having source/drain regions, a semi-conductive channel forming region which is in contact with the source/drain regions and spaces out the
35 source/drain regions, and a gate capacitively coupled with the channel forming region,

(2) a second transistor for switching, having a

-28-

second conductivity type, and having source/drain regions, a semi-conductive channel forming region which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively
5 coupled with the channel forming region,

(3) a third transistor for current control, having the second conductivity type, and having source/drain regions, a semi-conductive channel forming region which is in contact with the source/drain regions and spaces
10 out the source/drain regions, and a gate capacitively coupled with the channel forming region,

(4) a junction-field-effect transistor for current control, having source/drain regions, a channel region and gate regions, and

15 (5) an MIS type diode for retaining information,
wherein:

one source/drain region of the first transistor corresponds to the channel forming region of the second transistor,

20 the other source/drain region of the first transistor corresponds to one source/drain region of the junction-field-effect transistor,

one source/drain region of the second transistor corresponds to the channel forming region of the first
25 transistor, corresponds to one gate region of the junction-field-effect transistor and corresponds to one source/drain region of the third transistor,

the other source/drain region of the third transistor corresponds to the other gate region of the
30 junction-field-effect transistor, and

one end of the MIS type diode is formed of an extending portion of the channel forming region of the first transistor, the other end of the MIS type diode is formed of an electrode composed of a conductive material,
35 and the electrode is connected to a line having a predetermined potential.

In the semiconductor memory cell according

-29-

to the seventh aspect of the present invention, there may be employed a constitution in which the gate of the first transistor, the gate of the second transistor and the gate of the third transistor are connected to a
5 first line for memory cell selection (for example, word line), the other source/drain region of the first transistor is connected to a second line through the junction-field-effect transistor, the other end of the MIS type diode is connected to a third line
10 corresponding to the above line having a predetermined potential through a high-resistance element, one source/drain region of the first transistor is connected to a fourth line, and the other source/drain region of the second transistor is connected to a write-in
15 information setting line. It is preferred to employ a constitution in which the second line is used as a bit line and a second predetermined potential is applied to the fourth line, or a constitution in which the fourth line is used as a bit line and a second predetermined
20 potential is applied to the second line.

In the above case, there may be employed a constitution in which one source/drain region of the first transistor is connected to the write-in information setting line through a diode in place of
25 being connected to the fourth line.

According to an eighth aspect of the present invention for achieving the above second object, there is provided a semiconductor memory cell comprising, as a drawing of its principle is shown in Fig. 138, 139A or
30 139B,

(1) a first transistor for readout, having a first conductivity type, and having source/drain regions, a semi-conductive channel forming region which is in contact with the source/drain regions and spaces out the
35 source/drain regions, and a gate capacitively coupled with the channel forming region,

(2) a second transistor for switching, having a

-30-

second conductivity type, and having source/drain regions, a semi-conductive channel forming region which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively
5 coupled with the channel forming region,

(3) a third transistor for current control, having the second conductivity type, and having source/drain regions, a semi-conductive channel forming region which is in contact with the source/drain regions and spaces
10 out the source/drain regions, and a gate capacitively coupled with the channel forming region,

(4) a junction-field-effect transistor for current control, having source/drain regions, a channel region and gate regions, and

15 (5) an MIS type diode for retaining information,
wherein:

one source/drain region of the first transistor corresponds to the channel forming region of the second transistor,

20 the other source/drain region of the first transistor corresponds to one source/drain region of the junction-field-effect transistor,

one source/drain region of the second transistor corresponds to the channel forming region of the first
25 transistor, corresponds to one gate region of the junction-field-effect transistor and corresponds to one source/drain region of the third transistor,

the other source/drain region of the third transistor corresponds to the other gate region of the
30 junction-field-effect transistor, and

one end of the MIS type diode corresponds to the other source/drain region of the third transistor, the other end of the MIS type diode is formed of an electrode composed of a conductive material, and the
35 electrode is connected to a line having a predetermined potential.

In the semiconductor memory cell according

-31-

to the eighth aspect of the present invention, there may be employed a constitution in which the gate of the first transistor, the gate of the second transistor and the gate of the third transistor are connected to a first line for memory cell selection (for example, word line), the other source/drain region of the first transistor is connected to a second line through the junction-field-effect transistor, the other end of the MIS type diode is connected to a third line corresponding to the above line having a predetermined potential through a high-resistance element, one source/drain region of the first transistor is connected to a fourth line, and the other source/drain region of the second transistor is connected to a write-in information setting line. It is preferred to employ a constitution in which the second line is used as a bit line and a second predetermined potential is applied to the fourth line or a constitution in which the fourth line is used as a bit line and a second predetermined potential is applied to the second line.

In the above case, there may be employed a constitution in which one source/drain region of the first transistor is connected to the write-in information setting line through a diode in place of being connected to the fourth line.

According to a ninth aspect of the present invention for achieving the above second object, there is provided a semiconductor memory cell comprising, as a drawing of its principle is shown in Fig. 144, 145A, 145B, 146, 147A, 147B, 156, 157A or 157B,

(1) a first transistor for readout, having a first conductivity type, and having source/drain regions, a semi-conductive channel forming region which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively coupled with the channel forming region,

(2) a second transistor for switching, having a

-32-

second conductivity type, and having source/drain regions, a semi-conductive channel forming region which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively
5 coupled with the channel forming region,

(3) a first junction-field-effect transistor for current control, having source/drain regions, a channel region and gate regions,

(4) a second junction-field-effect transistor for
10 current control, having source/drain regions, a channel region and gate regions, and

(5) an MIS type diode for retaining information,
wherein:

one source/drain region of the first transistor
15 corresponds to the channel forming region of the second transistor and corresponds to one source/drain region of the first junction-field-effect transistor,

the other source/drain region of the first transistor corresponds to one source/drain region of the
20 second junction-field-effect transistor,

one source/drain region of the second transistor corresponds to the channel forming region of the first transistor, corresponds to one gate region of the first junction-field-effect transistor and corresponds to one
25 gate region of the second junction-field-effect transistor, and

one end of the MIS type diode is formed of an extending portion of the channel forming region of the first transistor, the other end of the MIS type diode is
30 formed of an electrode composed of a conductive material, and the electrode is connected to a line having a predetermined potential.

In the semiconductor memory cell according to the ninth aspect of the present invention, there may
35 be employed a constitution in which the gate of the first transistor and the gate of the second transistor are connected to a first line for memory cell selection

-33-

(for example, word line), the other source/drain region of the first transistor is connected to a second line through the second junction-field-effect transistor, the other end of the MIS type diode is connected to a third line corresponding to the above line having a predetermined potential through a high-resistance element, the other gate region of the second junction-field-effect transistor is connected to a fourth line, one source/drain region of the first transistor is connected to a fifth line through the first junction-field-effect transistor, the other gate region of the first junction-field-effect transistor is connected to a write-in information setting line, and the other source/drain region of the second transistor is connected to the write-in information setting line. There may be employed another constitution in which the other gate region of the second junction-field-effect transistor is connected to one gate region of the second junction-field-effect transistor in place of being connected to the fourth line. In this case, one end of the MIS type diode and the other gate region of the second junction-field-effect transistor can be formed as a common region. In these cases, it is preferred to employ a constitution in which the second line is used as a bit line and a second predetermined potential is applied to the fifth line or a constitution in which the fifth line is used as a bit line and a second predetermined potential is applied to the second line. In these cases, further, there may be employed a constitution in which one source/drain region of the first transistor is connected to the write-in information setting line through the first junction-field-effect transistor and a diode in place of being connected to the fifth line through the first junction-field-effect transistor.

According to a tenth aspect of the present invention for achieving the above second object, there

-34-

is provided a semiconductor memory cell comprising, as a drawing of its principle is shown in Figs. 162 to 164,

(1) a first transistor for readout, having a first conductivity type, and having source/drain regions, a
5 semi-conductive channel forming region which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively coupled with the channel forming region,

(2) a second transistor for switching, having a
10 second conductivity type, and having source/drain regions, a semi-conductive channel forming region which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively coupled with the channel forming region,

(3) a third transistor for current control, having
15 the second conductivity type, and having source/drain regions, a semi-conductive channel forming region which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively
20 coupled with the channel forming region,

(4) a first junction-field-effect transistor for current control, having source/drain regions, a channel region and gate regions,

(5) a second junction-field-effect transistor for
25 current control, having source/drain regions, a channel region and gate regions, and

(6) an MIS type diode for retaining information,
wherein:

one source/drain region of the first transistor
30 corresponds to the channel forming region of the second transistor and corresponds to one source/drain region of the first junction-field-effect transistor,

the other source/drain region of the first transistor corresponds to one source/drain region of the
35 second junction-field-effect transistor,

one source/drain region of the second transistor corresponds to the channel forming region of the first

-35-

transistor, corresponds to one gate region of the first junction-field-effect transistor, corresponds to one gate region of the second junction-field-effect transistor and corresponds to one source/drain region of
5 the third transistor,

the other source/drain region of the third transistor corresponds to the other gate region of the second junction-field-effect transistor, and

one end of the MIS type diode is formed of an
10 extending portion of the channel forming region of the first transistor, the other end of the MIS type diode is formed of an electrode composed of a conductive material, and the electrode is connected to a line having a predetermined potential.

15 In the semiconductor memory cell according to the tenth aspect of the present invention, there may be employed a constitution in which the gate of the first transistor, the gate of the second transistor and the gate of the third transistor are connected to a
20 first line for memory cell selection (for example, word line), the other source/drain region of the first transistor is connected to a second line through the second junction-field-effect transistor, the other end of the MIS type diode is connected to a third line
25 corresponding to the above line having a predetermined potential through a high-resistance element, one source/drain region of the first transistor is connected to a fourth line through the first junction-field-effect transistor, the other source/drain region of the second
30 transistor is connected to a write-in information setting line, and the other gate region of the first junction-field-effect transistor is connected to the write-in information setting line. It is preferred to employ a constitution in which the second line is used
35 as a bit line and a second predetermined potential is applied to the fourth line or a constitution in which the fourth line is used as a bit line and a second

-36-

predetermined potential is applied to the second line.

In the above case, there may be also employed a constitution in which one source/drain region of the first transistor is connected to the write-in
5 information setting line through the first junction-field-effect transistor and a diode in place of being connected to the fourth line through the first junction-field-effect transistor.

According to an eleventh aspect of the
10 present invention for achieving the above second object, there is provided a semiconductor memory cell comprising, as a drawing of its principle is shown in Figs. 169 to 171,

(1) a first transistor for readout, having a first
15 conductivity type, and having source/drain regions, a semi-conductive channel forming region which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively coupled with the channel forming region,

20 (2) a second transistor for switching, having a second conductivity type, and having source/drain regions, a semi-conductive channel forming region which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively
25 coupled with the channel forming region,

(3) a third transistor for current control, having the second conductivity type, and having source/drain regions, a semi-conductive channel forming region which is in contact with the source/drain regions and spaces
30 out the source/drain regions, and a gate capacitively coupled with the channel forming region,

(4) a first junction-field-effect transistor for current control, having source/drain regions, a channel region and gate regions,

35 (5) a second junction-field-effect transistor for current control, having source/drain regions, a channel region and gate regions, and

-37-

(6) an MIS type diode for retaining information,
wherein:

one source/drain region of the first transistor
corresponds to the channel forming region of the second
5 transistor and corresponds to one source/drain region of
the first junction-field-effect transistor,

the other source/drain region of the first
transistor corresponds to one source/drain region of the
second junction-field-effect transistor,

10 one source/drain region of the second transistor
corresponds to channel forming region of the first
transistor, corresponds to one gate region of the first
junction-field-effect transistor, corresponds to one
gate region of the second junction-field-effect
15 transistor and corresponds to one source/drain region of
the third transistor,

the other source/drain region of the third
transistor corresponds to the other gate region of the
second junction-field-effect transistor, and

20 one end of the MIS type diode corresponds to the
other source/drain region of the third transistor, the
other end of the MIS type diode is formed of an
electrode composed of a conductive material, and the
electrode is connected to a line having a predetermined
25 potential.

In the semiconductor memory cell according
to the eleventh aspect of the present invention, there
may be employed a constitution in which the gate of the
first transistor, the gate of the second transistor and
30 the gate of third transistor are connected to a first
line for memory cell selection (for example, word line),
the other source/drain region of the first transistor is
connected to a second line through the second junction-
field-effect transistor, the other end of the MIS type
35 diode is connected to a third line corresponding to the
above line having a predetermined potential through a
high-resistance element, one source/drain region of the

-38-

first transistor is connected to a fourth line through the first junction-field-effect transistor, the other source/drain region of the second transistor is connected to a write-in information setting line, and
5 the other gate region of the first junction-field-effect transistor is connected to the write-in information setting line. It is preferred to employ a constitution in which the second line is used as a bit line and a second predetermined potential is applied to the fourth
10 line or a constitution in which the fourth line is used as a bit line and a second predetermined potential is applied to the second line.

In the above case, there may be also employed a constitution in which one source/drain region
15 of the first transistor is connected to the write-in information setting line through the first junction-field-effect transistor and a diode in place of being connected to the fourth line through the first junction-field-effect transistor.

In the semiconductor memory cell according to any one of the fifth to seventh aspects and ninth and tenth aspects of the present invention, there is a material interposed between one end and the other end of the MIS type diode, in which material the tunnel
25 transition of carriers is caused depending upon a potential difference between the potential in the channel forming region of the first transistor and the potential in the other end of the MIS type diode. That is, the MIS type diode comprises the above material, the
30 extending portion of the channel forming region of the first transistor and the electrode. And, it is preferred to employ the following constitution. Binary information of first information or second information is stored in the semiconductor memory cell, the first
35 information to be stored in the semiconductor memory cell corresponds to a first potential in the channel forming region of the first transistor, and the second

-39-

information to be stored in the semiconductor memory cell corresponds to a second potential in the channel forming region of the first transistor. (i) When the potential in the channel forming region of the first transistor is the first potential, the tunnel transition of carriers is caused from the other end to one end of the MIS type diode. As a result, carrier multiplication takes place, holes or electrons are stored in the above extending portion of the channel forming region of the first transistor depending upon the conductivity type of one end of the MIS type diode, and the potential in the channel forming region of the first transistor is held nearly at the first potential. (ii) When the potential in the channel forming region of the first transistor is the second potential, carriers having the polarity opposite to that of the above carriers transit from one end to the other end of the MIS type diode. As a result, the potential in the channel forming region of the first transistor is held at the second potential.

In the semiconductor memory cell according to any one of the eighth aspect and eleventh aspects of the present invention, there is a material interposed between one end and the other end of the MIS type diode, in which material the tunnel transition of carriers is caused depending upon a potential difference between the potential in the other source/drain region of the third transistor and the potential in the other end of the MIS type diode. That is, the MIS type diode comprises the above material, the other source/drain region of the third transistor and the electrode. And, it is preferred to employ the following constitution. Binary information of first information or second information is stored in the semiconductor memory cell, the first information to be stored in the semiconductor memory cell corresponds to a first potential in the channel forming region of the first transistor, and the second information to be stored in the semiconductor memory

-40-

cell corresponds to a second potential in the channel forming region of the first transistor. (i) When the potential in the channel forming region of the first transistor is the first potential, the tunnel transition of carriers is caused from the other end to one end of the MIS type diode. As a result, carrier multiplication takes place, holes or electrons are stored in the other source/drain region of the third transistor depending upon the conductivity type of one end of the MIS type diode, and the potential in the channel forming region of the first transistor is held nearly at the first potential. (ii) When the potential in the channel forming region of the first transistor is the second potential, carriers having the polarity opposite to that of the above carriers transit from one end to the other end of the MIS type diode. As a result, the potential in the channel forming region of the first transistor is held at the second potential.

In the semiconductor memory cell according to any one of the fifth to eleventh aspects of the present invention, preferably, a wide gap thin film is formed between the extending portion of the channel forming region of the first transistor or the other source/drain region of the third transistor constituting the MIS type diode and the electrode. That is, preferably, the wide gap thin film is composed of a material in which the tunnel transition of carriers is caused depending upon a potential difference between the potential in the channel forming region of the first transistor or the other source/drain region of the third transistor and the potential in the other end of the MIS type diode.

In the semiconductor memory cell according to the fifth aspect, sixth aspect or ninth aspect of the present invention, the gate of the first transistor and the gate of the second transistor may be formed separately from each other. For decreasing the size of

-41-

the semiconductor memory cell, however, it is preferred to employ a constitution in which the first transistor and the second transistor have a common gate. In the semiconductor memory cell according to the seventh, eighth, tenth or eleventh aspect of the present invention, the gate of the first transistor, the gate of the second transistor and the gate of the third transistor may be formed separately from each other. For decreasing the size of the semiconductor memory cell, however, it is preferred to employ a constitution in which the first transistor, the second transistor and the third transistor have a common gate.

According to a twelfth aspect of the present invention for achieving the above second object, there is provided a semiconductor memory cell comprising;

(1) a first transistor for readout, having a first conductivity type, and having source/drain regions, a semi-conductive channel forming region which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively coupled with the channel forming region,

(2) a second transistor for switching, having a second conductivity type, and having source/drain regions, a semi-conductive channel forming region which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively coupled with the channel forming region,

(3) a junction-field-effect transistor for current control, having source/drain regions, a channel region and gate regions, and

(4) an MIS type diode for retaining information, the semiconductor memory cell having;

(a) a semi-conductive first region having a second conductivity type,

(b) a semi-conductive second region which is formed in a surface region of the first region and has a first conductivity type,

-42-

(c) a third region which is formed in a surface region of the second region and is in contact with the second region so as to form a rectifier junction together with the second region,

5 (d) a fourth region which is formed in a surface region of the first region to be spaced from the second region and is in contact with the first region so as to form a rectifier junction together with the first region, and

10 (e) a fifth region which is formed in a surface region of the second region to be spaced from the third region and is in contact with the second region so as to form a rectifier junction together with the second region,

15 wherein:

(A-1) one source/drain region of the first transistor is formed of a portion of a surface region of the second region,

20 (A-2) the other source/drain region of the first transistor is formed of the fourth region,

(A-3) the channel forming region of the first transistor is formed of a portion of a surface region of the first region which portion is interposed between said portion of the surface region of the second region and the fourth region,

25 (A-4) the gate of the first transistor is formed on the channel forming region of the first transistor through an insulation layer,

(B-1) one source/drain region of the second transistor is formed of other portion of the surface region of the first region,

(B-2) the other source/drain region of the second transistor is formed of the third region,

35 (B-3) the channel forming region of the second transistor is formed of other portion of the surface region of the second region which other portion is interposed between said other portion of the surface

-43-

region of the first region and the third region,

(B-4) the gate of the second transistor is formed on the channel forming region of the second transistor through an insulation layer,

5 (C-1) the gate regions of the junction-field-effect transistor are formed of the fifth region and part of the first region which part is opposed to the fifth region,

(C-2) the channel region of the junction-field-effect transistor is formed of part of the second region
10 which part is interposed between the fifth region and said part of the first region,

(C-3) one source/drain region of the junction-field-effect transistor is formed of said portion of the
15 surface region of the second region which portion extends from one end of the channel region of the junction-field-effect transistor and constitutes one source/drain region of the first transistor,

(C-4) the other source/drain region of the
20 junction-field-effect transistor is formed of a portion of the second region which portion extends from the other end of the channel region of the junction-field-effect transistor,

(D-1) one end of the MIS type diode is formed of
25 part of the first region,

(D-2) an electrode constituting the other end of the MIS type diode is formed to be opposed to said part of the first region constituting one end of the MIS type diode, through a wide gap thin film,

30 (E) the gate of the first transistor and the gate of the second transistor are connected to a first line for memory cell selection,

(F) the third region is connected to a write-in information setting line,

35 (G) the fourth region is connected to a second line,

(H) the electrode constituting the other end of

-44-

the MIS type diode is connected to a third line having a predetermined potential, and

(I) the fifth region is connected to a fourth line.

It is preferred to employ a constitution in
5 which the second region is connected to a fifth line,
the second line is used as a bit line and a second
predetermined potential is applied to the fifth line, or
a constitution in which the second region is connected
to a fifth line, the fifth line is used as a bit line
10 and a second predetermined potential is applied to the
second line.

In the semiconductor memory cell according
to the twelfth aspect of the present invention, there
may be employed a constitution in which the second
15 region and the third region constitute a diode and the
second region is connected to the write-in information
setting line through the third region. When it is
required to avoid possibility where carriers implanted
from the above diode may latch up the semiconductor
20 memory cell, it is preferred to employ a constitution in
which further provided is a diode-constituting-region
which is formed in a surface region of the second region
and is in contact with the second region so as to form a
rectifier junction together with the second region, a
25 majority carrier diode (Schottky diode or hetero-
junction diode in which majority carriers flow)
comprises the diode-constituting-region and the second
region, and the second region is connected to the write-
in information setting line through the diode-
30 constituting region. In this case, there may be
employed a structure in which the above diode-
constituting region has a common region with part of the
write-in information setting line (in other words, a
structure in which the diode-constituting region and
35 part of the write-in information setting line are formed
as a common region).

In the semiconductor memory cell according

-45-

to the twelfth aspect of the present invention, there may be also employed another constitution in which further provided is a diode-constituting region which is formed in a surface region of the second region and is in contact with the second region so as to form a rectifier junction together with the second region, a diode comprises the diode-constituting region and the second region, and the second region is connected to the fourth line through the diode-constituting region.

10 In the semiconductor memory cell according to the twelfth aspect of the present invention, there may be also employed still another constitution in which the fifth region is connected to the first region in place of being connected to the fourth region. There
15 may be also employed yet another constitution in which the fifth region is connected to the write-in information setting line in place of being connected to the fourth line. In these cases, there may be employed a constitution in which the second region and the third
20 region constitute a diode and the second region is connected to the write-in information setting line through the third region. When it is required to avoid possibility where carriers implanted from the above diode may latch up the semiconductor memory cell, it is
25 preferred to employ a constitution in which further provided is a diode-constituting region which is formed in a surface region of the second region and is in contact with the second region so as to form a rectifier junction together with the second region, a majority
30 carrier diode comprises the diode-constituting region and the second region, and the second region is connected to the write-in information setting line through the diode-constituting region.

A semiconductor memory cell according to a
35 thirteenth aspect of the present invention for achieving the above second object differs from the semiconductor memory cell according to the twelfth aspect of the

-46-

present invention in that one end of the MIS type diode is formed of a fifth region. That is, according to the thirteenth aspect of the present invention, there is provided a semiconductor memory cell comprising;

- 5 (1) a first transistor for readout, having a first conductivity type, and having source/drain regions, a semi-conductive channel forming region which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively coupled
10 with the channel forming region,
- (2) a second transistor for switching, having a second conductivity type, and having source/drain regions, a semi-conductive channel forming region which is in contact with the source/drain regions and spaces
15 out the source/drain regions, and a gate capacitively coupled with the channel forming region,
- (3) a junction-field-effect transistor for current control, having source/drain regions, a channel region and gate regions, and
- 20 (4) an MIS type diode for retaining information, the semiconductor memory cell having;
- (a) a semi-conductive first region having a second conductivity type,
- (b) a semi-conductive second region which is
25 formed in a surface region of the first region and has a first conductivity type,
- (c) a third region which is formed in a surface region of the second region and is in contact with the second region so as to form a rectifier junction
30 together with the second region,
- (d) a fourth region which is formed in a surface region of the first region to be spaced from the second region and is in contact with the first region so as to form a rectifier junction together with the first region,
35 and
- (e) a semi-conductive fifth region which is formed in a surface region of the second region to be spaced

-47-

from the third region and has the second conductivity type,

wherein:

(A-1) one source/drain region of the first
5 transistor is formed of a portion of a surface region of the second region,

(A-2) the other source/drain region of the first transistor is formed of the fourth region,

(A-3) the channel forming region of the first
10 transistor is formed of a portion of a surface region of the first region which portion is interposed between said portion of the surface region of the second region and the fourth region,

(A-4) the gate of the first transistor is formed
15 on the channel forming region of the first transistor through an insulation layer,

(B-1) one source/drain region of the second transistor is formed of other portion of the surface region of the first region,

(B-2) the other source/drain region of the second
20 transistor is formed of the third region,

(B-3) the channel forming region of the second transistor is formed of other portion of the surface region of the second region which other portion is
25 interposed between said other portion of the surface region of the first region and the third region,

(B-4) the gate of the second transistor is formed on the channel forming region of the second transistor through an insulation layer,

(C-1) the gate regions of the junction-field-effect transistor are formed of the fifth region and part of the first region which part is opposed to the fifth region,

(C-2) the channel region of the junction-field-effect transistor is formed of part of the second region
35 which part is interposed between the fifth region and said part of the first region,

-48-

(C-3) one source/drain region of the junction-field-effect transistor is formed of said portion of the surface region of the second region which portion extends from one end of the channel region of the junction-field-effect transistor and constitutes one source/drain region of the first transistor,

(C-4) the other source/drain region of the junction-field-effect transistor is formed of a portion of the second region which portion extends from the other end of the channel region of the junction-field-effect transistor,

(D-1) one end of the MIS type diode is formed of the fifth region,

(D-2) an electrode constituting the other end of the MIS type diode is formed to be opposed to the fifth region constituting one end of the MIS type diode, through a wide gap thin film,

(E) the gate of the first transistor and the gate of the second transistor are connected to a first line for memory cell selection,

(F) the third region is connected to a write-in information setting line,

(G) the fourth region is connected to a second line,

(H) the fifth region is connected to the first region, and

(I) the electrode constituting the other end of the MIS type diode is connected to a third line having a predetermined potential.

In the semiconductor memory cell according to the thirteenth aspect of the present invention, there may be employed a constitution in which the second region and the third region constitute a diode and the second region is connected to the write-in information setting line through the third region. When it is required to avoid possibility where carriers implanted from the above diode may latch up the semiconductor

-49-

memory cell, it is preferred to employ a constitution in which further provided is a diode-constituting region which is formed in a surface region of the second region and is in contact with the second region so as to form a rectifier junction together with the second region, a majority carrier diode comprises the diode-constituting region and the second region, and the second region is connected to the write-in information setting line through the diode-constituting region.

10 A semiconductor memory cell according to a fourteenth aspect of the present invention for achieving the above second object differs from the semiconductor memory cell according to the twelfth aspect of the present invention in that the fifth region is omitted and that the first transistor and the second transistor share a gate. That is, according to the fourteenth aspect of the present invention, there is provided a semiconductor memory cell comprising;

20 (1) a first transistor for readout, having a first conductivity type, and having source/drain regions, a semi-conductive channel forming region which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively coupled with the channel forming region,

25 (2) a second transistor for switching, having a second conductivity type, and having source/drain regions, a semi-conductive channel forming region which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively coupled with the channel forming region,

30 (3) a junction-field-effect transistor for current control, having source/drain regions, a channel region and gate regions, and

 (4) an MIS type diode for retaining information, the semiconductor memory cell having;

35 (a) a semi-conductive first region having a first conductivity type,

-50-

(b) a semi-conductive second region which is in contact with the first region and has a second conductivity type,

5 (c) a third region which is formed in a surface region of the first region and is in contact with the first region so as to form a rectifier junction together with the first region,

10 (d) a fourth region which is formed in a surface region of the second region and is in contact with the second region so as to form a rectifier junction together with the second region, and

15 (e) the gate which is formed, through an insulation layer, so as to bridge the first region and the fourth region and so as to bridge the second region and the third region, and is shared by the first transistor and the second transistor,

wherein:

20 (A-1) one source/drain region of the first transistor is formed of a surface region of the first region,

(A-2) the other source/drain region of the first transistor is formed of the fourth region,

25 (A-3) the channel forming region of the first transistor is formed of a surface region of the second region which surface region is interposed between the surface region of the first region and the fourth region,

30 (B-1) one source/drain region of the second transistor is formed of the surface region of the second region which surface region constitutes the channel forming region of the first transistor,

(B-2) the other source/drain region of the second transistor is formed of the third region,

35 (B-3) the channel forming region of the second transistor is formed of the surface region of the first region which surface region constitutes one source/drain region of the first transistor,

(C-1) the gate regions of the junction-field-

-51-

effect transistor are formed of the third region and part of the second region which part is opposed to the third region,

(C-2) the channel region of the junction-field-effect transistor is formed of part of the first region
5 which part is interposed between the third region and said part of the second region,

(C-3) one source/drain region of the junction-field-effect transistor is formed of the surface region
10 of the first region which surface region extends from one end of the channel region of the junction-field-effect transistor and constitutes one source/drain region of the first transistor,

(C-4) the other source/drain region of the
15 junction-field-effect transistor is formed of a portion of the first region which portion extends from the other end of the channel region of the junction-field-effect transistor,

(D-1) one end of the MIS type diode is formed of
20 part of the second region or an extending portion of the second region,

(D-2) an electrode constituting the other end of the MIS type diode is formed to be opposed to said part of the second region or said extending portion of the
25 second region which constitutes one end of the MIS type diode, through a wide gap thin film,

(E) the gate is connected to a first line for memory cell selection,

(F) the third region is connected to a write-in
30 information setting line,

(G) the fourth region is connected to a second line, and

(H) the electrode constituting the other end of the MIS type diode is connected to a third line having a
35 predetermined potential.

It is preferred to employ a constitution in which the first region is connected to a fifth line, the

-52-

second line is used as a bit line and a second predetermined potential is applied to the fifth line, or a constitution in which the first region is connected to a fifth line, the fifth line is used as a bit line and a
5 second predetermined potential is applied to the second line.

In the semiconductor memory cell according to the fourteenth aspect of the present invention, there may be employed a constitution in which the first region
10 and the third region constitute a diode and the first region is connected to the write-in information setting line through the third region. When it is required to avoid possibility where carriers implanted from the above diode may latch up the semiconductor memory cell,
15 it is preferred to employ a constitution in which further provided is a diode-constituting region which is formed in a surface region of the first region and is in contact with the first region so as to form a rectifier junction together with the first region, a majority
20 carrier diode comprises the diode-constituting region and the first region, and the first region is connected to the write-in information setting line through the diode-constituting region.

A semiconductor memory cell according to a
25 fifteenth aspect of the present invention for achieving the above second object and the semiconductor memory cell according to the twelfth aspect of the present invention differ from each other in the position of the junction-field-effect transistor for current control.
30 That is, according to the fifteenth aspect of the present invention, there is provided a semiconductor memory cell comprising;

(1) a first transistor for readout, having a first conductivity type, and having source/drain regions, a
35 semi-conductive channel forming region which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively coupled

-53-

with the channel forming region,

(2) a second transistor for switching, having a second conductivity type, and having source/drain regions, a semi-conductive channel forming region which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively coupled with the channel forming region,

(3) a junction-field-effect transistor for current control, having source/drain regions, a channel region and gate regions, and

(4) an MIS type diode for retaining information, the semiconductor memory cell having;

(a) a semi-conductive first region having a second conductivity type,

(b) a semi-conductive second region which is formed in a surface region of the first region and has a first conductivity type,

(c) a third region which is formed in a surface region of the second region and is in contact with the second region so as to form a rectifier junction together with the second region,

(d) a semi-conductive fourth region which is formed in a surface region of the first region to be spaced from the second region and has the first conductivity type, and

(e) a fifth region which is formed in a surface region of the fourth region and is in contact with the fourth region so as to form a rectifier junction together with the fourth region,

wherein:

(A-1) one source/drain region of the first transistor is formed of a portion of a surface region of the second region,

(A-2) the other source/drain region of the first transistor is formed of a surface region of the fourth region,

(A-3) the channel forming region of the first

-54-

transistor is formed of a portion of a surface region of the first region which portion is interposed between said portion of the surface region of the second region and the surface region of the fourth region,

5 (A-4) the gate of the first transistor is formed on the channel forming region of the first transistor through an insulation layer,

(B-1) one source/drain region of the second transistor is formed of other portion of the surface
10 region of the first region,

(B-2) the other source/drain region of the second transistor is formed of the third region,

(B-3) the channel forming region of the second transistor is formed of other portion of the surface
15 region of the second region which other portion is interposed between said other portion of the surface region of the first region and the third region,

(B-4) the gate of the second transistor is formed on the channel forming region of the second transistor
20 through an insulation layer,

(C-1) the gate regions of the junction-field-effect transistor are formed of the fifth region and part of the first region which part is opposed to the fifth region,

25 (C-2) the channel region of the junction-field-effect transistor is formed of part of the fourth region which part is interposed between the fifth region and said part of the first region,

(C-3) one source/drain region of the junction-field-effect transistor is formed of the surface region
30 of the fourth region which surface region extends from one end of the channel region of the junction-field-effect transistor and constitutes the other source/drain region of the first transistor,

35 (C-4) the other source/drain region of the junction-field-effect transistor is formed of a portion of the fourth region which portion extends from the

-55-

other end of the channel region of the junction-field-effect transistor,

(D-1) one end of the MIS type diode is formed of part of the first region,

5 (D-2) an electrode constituting the other end of the MIS type diode is formed to be opposed to said part of the first region which part constitutes one end of the MIS type diode, through a wide gap thin film,

(E) the gate of the first transistor and the gate
10 of the second transistor are connected to a first line for memory cell selection,

(F) the third region is connected to a write-in information setting line,

(G) said portion of the fourth region which
15 portion constitutes the other source/drain region of the junction-field-effect transistor is connected to a second line,

(H) the electrode constituting the other end of the MIS type diode is connected to a third line having a
20 predetermined potential, and

(I) the fifth region is connected to a fourth line.

It is preferred to employ a constitution in which the second region is connected to a fifth line, the second line is used as a bit line and a second
25 predetermined potential is applied to the fifth line, or a constitution in which the second region is connected to a fifth line, the fifth line is used as a bit line and a second predetermined potential is applied to the second line.

30 In the semiconductor memory cell according to the fifteenth aspect of the present invention, there may be employed a constitution in which the second region and the third region constitute a diode and the second region is connected to the write-in information
35 setting line through the third region. When it is required to avoid possibility where carriers implanted from the above diode may latch up the semiconductor

-56-

memory cell, it is preferred to employ a constitution in which further provided is a diode-constituting region which is formed in a surface region of the second region and is in contact with the second region so as to form a rectifier junction together with the second region, a majority carrier diode comprises the diode-constituting region and the second region, and the second region is connected to the write-in information setting line through the diode-constituting region.

10 In the semiconductor memory cell according to the fifteenth aspect of the present invention, there may be employed a constitution in which the fifth region is connected to the write-in information setting line in place of being connected to the fourth line or a
15 constitution in which the fifth region is connected to the first region in place of being connected to the fourth line. In these cases, there may be employed a constitution in which the second region and the third region constitute a diode and the second region is
20 connected to the write-in information setting line through the third line. When it is required to avoid possibility where carriers implanted from the above diode may latch up the semiconductor memory cell, it is preferred to employ a constitution in which further
25 provided is a diode-constituting region which is formed in a surface region of the second region and is in contact with the second region so as to form a rectifier junction together with the second region, a majority carrier diode comprises the diode-constituting region
30 and the second region, and the second region is connected to the write-in information setting line through the diode-constituting region.

 A semiconductor memory cell according to a sixteenth aspect of the present invention differs from
35 the semiconductor memory cell according to the fifteenth aspect of the present invention in that one end of the MIS type diode is formed of the fifth region. That is,

-57-

according to the sixteenth aspect of the present invention, there is provided a semiconductor memory cell comprising;

- 5 (1) a first transistor for readout, having a first conductivity type, and having source/drain regions, a semi-conductive channel forming region which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively coupled with the channel forming region,
- 10 (2) a second transistor for switching, having a second conductivity type, and having source/drain regions, a semi-conductive channel forming region which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively
15 coupled with the channel forming region,
- (3) a junction-field-effect transistor for current control, having source/drain regions, a channel region and gate regions, and
- (4) an MIS type diode for retaining information,
20 the semiconductor memory cell having;
 - (a) a semi-conductive first region having a second conductivity type,
 - (b) a semi-conductive second region which is formed in a surface region of the first region and has a
25 first conductivity type,
 - (c) a third region which is formed in a surface region of the second region and is in contact with the second region so as to form a rectifier junction together with the second region,
 - 30 (d) a semi-conductive fourth region which is formed in a surface region of the first region to be spaced from the second region and has the first conductivity type, and
 - (e) a semi-conductive fifth region which is formed
35 in a surface region of the fourth region and has the second conductivity type,

wherein:

-58-

(A-1) one source/drain region of the first transistor is formed of a portion of a surface region of the second region,

5 (A-2) the other source/drain region of the first transistor is formed of a surface region of the fourth region,

(A-3) the channel forming region of the first transistor is formed of a portion of a surface region of the first region which portion is interposed between
10 said portion of the surface region of the second region and the surface region of the fourth region,

(A-4) the gate of the first transistor is formed on the channel forming region of the first transistor through an insulation layer,

15 (B-1) one source/drain region of the second transistor is formed of other portion of the surface region of the first region,

(B-2) the other source/drain region of the second transistor is formed of the third region,

20 (B-3) the channel forming region of the second transistor is formed of other portion of the surface region of the second region which other portion is interposed between said other portion of the surface region of the first region and the third region,

25 (B-4) the gate of the second transistor is formed on the channel forming region of the second transistor through an insulation layer,

(C-1) the gate regions of the junction-field-effect transistor are formed of the fifth region and
30 part of the first region which part is opposed to the fifth region,

(C-2) the channel region of the junction-field-effect transistor is formed of part of the fourth region which part is interposed between the fifth region and
35 said part of the first region,

(C-3) one source/drain region of the junction-field-effect transistor is formed of the surface region

-59-

of the fourth region which surface region extends from one end of the channel region of the junction-field-effect transistor and constitutes the other source/drain region of the first transistor,

5 (C-4) the other source/drain region of the junction-field-effect transistor is formed of a portion of the fourth region which portion extends from the other end of the channel region of the junction-field-effect transistor,

10 (D-1) one end of the MIS type diode is formed of the fifth region,

(D-2) an electrode constituting the other end of the MIS type diode is formed to be opposed to the fifth region constituting one end of the MIS type diode,
15 through a wide gap thin film,

(E) the gate of the first transistor and the gate of the second transistor are connected to a first line for memory cell selection,

(F) the third region is connected to a write-in
20 information setting line,

(G) said portion of the fourth region which portion constitutes the other source/drain region of the junction-field-effect transistor is connected to a second line,

25 (H) the fifth region is connected to the first region, and

(I) the electrode constituting the other end of the MIS type diode is connected to a third line having a predetermined potential.

30 It is preferred to employ a constitution in which the second region is connected to a fifth line, the second line is used as a bit line and a second predetermined potential is applied to the fifth line, or a constitution in which the second region is connected
35 to a fifth line, the fifth line is used as a bit line and a second predetermined potential is applied to the second line.

-60-

In the semiconductor memory cell according to the sixteenth aspect of the present invention, there may be employed a constitution in which the second region and the third region constitute a diode and the second region is connected to the write-in information setting line through the third region. When it is required to avoid possibility where carriers implanted from the above diode may latch up the semiconductor memory cell, it is preferred to employ a constitution in which further provided is a diode-constituting region which is formed in a surface region of the second region and is in contact with the second region so as to form a rectifier junction together with the second region, a majority carrier diode comprises the diode-constituting region and the second region, and the second region is connected to the write-in information setting line through the diode-constituting region.

A semiconductor memory cell according to a seventeenth aspect of the present invention for achieving the above second object differs from the semiconductor memory cell according to the fifteenth aspect of the present invention in that the first transistor and the second transistor share a gate. That is, according to the seventeenth aspect of the present invention, there is provided a semiconductor memory cell comprising;

(1) a first transistor for readout, having a first conductivity type, and having source/drain regions, a semi-conductive channel forming region which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively coupled with the channel forming region,

(2) a second transistor for switching, having a second conductivity type, and having source/drain regions, a semi-conductive channel forming region which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively

-61-

coupled with the channel forming region,

(3) a junction-field-effect transistor for current control, having source/drain regions, a channel region and gate regions, and

5 (4) an MIS type diode for retaining information, the semiconductor memory cell having;

(a) a semi-conductive first region having a first conductivity type,

(b) a semi-conductive second region which is in
10 contact with the first region and has a second conductivity type,

(c) a third region which is formed in a surface region of the first region and is in contact with the first region so as to form a rectifier junction together
15 with the first region,

(d) a semi-conductive fourth region which is formed in a surface region of the second region and has the first conductivity type,

(e) a fifth region which is formed in a surface
20 region of the fourth region and is in contact with the fourth region so as to form a rectifier junction together with the fourth region, and

(f) the gate which is formed, through an insulation layer, so as to bridge the first region and
25 the fourth region and so as to bridge the second region and the third region, and is shared by the first transistor and the second transistor,

wherein:

(A-1) one source/drain region of the first
30 transistor is formed of a surface region of the first region,

(A-2) the other source/drain region of the first transistor is formed of a surface region of the fourth region,

35 (A-3) the channel forming region of the first transistor is formed of a surface region of the second region which surface region is interposed between the

-62-

surface region of the first region and the surface region of the fourth region,

(B-1) one source/drain region of the second transistor is formed of the surface region of the second region which surface region constitutes the channel forming region of the first transistor,

(B-2) the other source/drain region of the second transistor is formed of the third region,

(B-3) the channel forming region of the second transistor is formed of the surface region of the first region which surface region constitutes one source/drain region of the first transistor,

(C-1) the gate regions of the junction-field-effect transistor are formed of the fifth region and part of the second region which part is opposed to the fifth region,

(C-2) the channel region of the junction-field-effect transistor is formed of part of the fourth region which part is interposed between the fifth region and said part of the second region,

(C-3) one source/drain region of the junction-field-effect transistor is formed of the surface region of the fourth region which surface region extends from one end of the channel region of the junction-field-effect transistor and constitutes the other source/drain region of the first transistor,

(C-4) the other source/drain region of the junction-field-effect transistor is formed of a portion of the fourth region which portion extends from the other end of the channel region of the junction-field-effect transistor,

(D-1) one end of the MIS type diode is formed of part of the second region,

(D-2) an electrode constituting the other end of the MIS type diode is formed to be opposed to said part of the second region which part constitutes one end of the MIS type diode, through a wide gap thin film,

-63-

(E) the gate is connected to a first line for memory cell selection,

(F) the third region is connected to a write-in information setting line,

5 (G) said portion of the fourth region which portion constitutes the other source/drain region of the junction-field-effect transistor is connected to a second line,

(H) the electrode constituting the other end of
10 the MIS type diode is connected to a third line having a predetermined potential, and

(I) the fifth region is connected to a fourth line.

It is preferred to employ a constitution in which the first region is connected to a fifth line, the
15 second line is used as a bit line and a second predetermined potential is applied to the fifth line, or a constitution in which the first region is connected to a fifth line, the fifth line is used as a bit line and a second predetermined potential is applied to the second
20 line.

In the semiconductor memory cell according to the seventeenth aspect of the present invention, there may be employed a constitution in which the first region and the third region constitute a diode and the
25 first region is connected to the write-in information setting line through the third region. When it is required to avoid possibility where carriers implanted from the above diode may latch up the semiconductor memory cell, it is preferred to employ a constitution in
30 which further provided is a diode-constituting region which is formed in a surface region of the first region and is in contact with the first region so as to form a rectifier junction together with the first region, a majority carrier diode comprises the diode-constituting
35 region and the first region, and the first region is connected to the write-in information setting line through the diode-constituting region.

-64-

Further, there may be employed a constitution in which the fifth region is connected to the write-in information setting line in place of being connected to the fourth line or a constitution in which
5 the fifth region is connected to the second region in place of being connected to the fourth line. In these cases, there may be employed a constitution in which the first region and the third region constitute a diode and the first region is connected to the write-in
10 information setting line through the third region. When it is required to avoid possibility where carriers implanted from the above diode may latch up the semiconductor memory cell, it is preferred to employ a constitution in which further provided is a diode-
15 constituting region which is formed in a surface region of the first region and is in contact with the first region so as to form a rectifier junction together with the first region, a majority carrier diode comprises the diode-constituting region and the first region, and the
20 first region is connected to the write-in information setting line through the diode-constituting region.

A semiconductor memory cell according to an eighteenth aspect of the present invention for achieving the above second object differs from the semiconductor
25 memory cell according to the seventeenth aspect of the present invention in that one end of the MIS type diode is formed of the fifth region. That is, according to the eighteenth aspect of the present invention, there is provided a semiconductor memory cell comprising;

30 (1) a first transistor for readout, having a first conductivity type, and having source/drain regions, a semi-conductive channel forming region which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively coupled
35 with the channel forming region,

(2) a second transistor for switching, having a second conductivity type, and having source/drain

-65-

regions, a semi-conductive channel forming region which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively coupled with the channel forming region,

5 (3) a junction-field-effect transistor for current control, having source/drain regions, a channel region and gate regions, and

 (4) an MIS type diode for retaining information, the semiconductor memory cell having;

10 (a) a semi-conductive first region having a first conductivity type,

 (b) a semi-conductive second region which is in contact with the first region and has a second conductivity type,

15 (c) a third region which is formed in a surface region of the first region and is in contact with the first region so as to form a rectifier junction together with the first region,

 (d) a semi-conductive fourth region which is
20 formed in a surface region of the second region and has the first conductivity type,

 (e) a semi-conductive fifth region which is formed in a surface region of the fourth region and has the second conductivity type, and

25 (f) the gate which is formed, through an insulation layer, so as to bridge the first region and the fourth region and so as to bridge the second region and the third region, and is shared by the first transistor and the second transistor,

30 wherein:

 (A-1) one source/drain region of the first transistor is formed of a surface region of the first region,

 (A-2) the other source/drain region of the first
35 transistor is formed of a surface region of the fourth region,

 (A-3) the channel forming region of the first

-66-

transistor is formed of a surface region of the second region which surface region is interposed between the surface region of the first region and the surface region of the fourth region,

5 (B-1) one source/drain region of the second transistor is formed of the surface region of the second region which surface region constitutes the channel forming region of the first transistor,

(B-2) the other source/drain region of the second
10 transistor is formed of the third region,

(B-3) the channel forming region of the second transistor is formed of the surface region of the first region which surface region constitutes one source/drain region of the first transistor,

15 (C-1) the gate regions of the junction-field-effect transistor are formed of the fifth region and part of the second region which part is opposed to the fifth region,

(C-2) the channel region of the junction-field-effect transistor is formed of part of the fourth region
20 which part is interposed between the fifth region and said part of the second region,

(C-3) one source/drain region of the junction-field-effect transistor is formed of the surface region
25 of the fourth region which surface region extends from one end of the channel region of the junction-field-effect transistor and constitutes the other source/drain region of the first transistor,

(C-4) the other source/drain region of the
30 junction-field-effect transistor is formed of a portion of the fourth region which portion extends from the other end of the channel region of the junction-field-effect transistor,

(D-1) one end of the MIS type diode is formed of
35 the fifth region,

(D-2) an electrode constituting the other end of the MIS type diode is formed to be opposed to the fifth

-67-

region which constitutes one end of the MIS type diode, through a wide gap thin film,

(E) the gate is connected to a first line for memory cell selection,

5 (F) the third region is connected to a write-in information setting line,

(G) said portion of the fourth region which portion constitutes the other source/drain region of the junction-field-effect transistor is connected to a
10 second line,

(H) the fifth region is connected to the second region, and

(I) the electrode constituting the other end of the MIS type diode is connected to a third line having a
15 predetermined potential.

It is preferred to employ a constitution in which the first region is connected to a fifth line, the second line is used as a bit line and a second predetermined potential is applied to the fifth line, or
20 a constitution in which the first region is connected to a fifth line, the fifth line is used as a bit line and a second predetermined potential is applied to the second line.

In the semiconductor memory cell according
25 to the eighteenth aspect of the present invention, there may be employed a constitution in which the first region and the third region constitute a diode and the first region is connected to the write-in information setting line through the third region. When it is required to
30 avoid possibility where carriers implanted from the above diode may latch up the semiconductor memory cell, it is preferred to employ a constitution in which further provided is a diode-constituting region which is formed in a surface region of the first region and is in
35 contact with the first region so as to form a rectifier junction together with the first region, a majority carrier diode comprises the diode-constituting region

-68-

and the first region, and the first region is connected to the write-in information setting line through the diode-constituting region.

A semiconductor memory cell according to a
5 nineteenth aspect of the present invention for achieving the above second object differs from the semiconductor memory cell according to the seventeenth aspect of the present invention in that a third transistor for current control is provide. That is, according to the
10 nineteenth aspect of the present invention, there is provided a semiconductor memory cell comprising;

(1) a first transistor for readout, having a first conductivity type, and having source/drain regions, a semi-conductive channel forming region which is in
15 contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively coupled with the channel forming region,

(2) a second transistor for switching, having a second conductivity type, and having source/drain
20 regions, a semi-conductive channel forming region which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively coupled with the channel forming region,

(3) a third transistor for current control, having
25 the second conductivity type, and having source/drain regions, a semi-conductive channel forming region which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively coupled with the channel forming region,

30 (4) a junction-field-effect transistor for current control, having source/drain regions, a channel region and gate regions, and

(5) an MIS type diode for retaining information,
the semiconductor memory cell having;

35 (a) a semi-conductive first region having a first conductivity type,

(b) a semi-conductive second region which is in

-69-

contact with the first region and has a second conductivity type,

(c) a third region which is formed in a surface region of the first region and is in contact with the first region so as to form a rectifier junction together with the first region,

(d) a semi-conductive fourth region which is formed in a surface region of the second region and has the first conductivity type,

10 (e) a fifth region which is formed in a surface region of the fourth region and is in contact with the fourth region so as to form a rectifier junction together with the fourth region, and

(f) the gate which is formed, through an insulation layer, so as to bridge the first region and the fourth region, so as to bridge the second region and the third region and so as to bridge the second region and the fifth region, and is shared by the first transistor, the second transistor and the third transistor,

wherein:

(A-1) one source/drain region of the first transistor is formed of a surface region of the first region,

25 (A-2) the other source/drain region of the first transistor is formed of a surface region of the fourth region,

(A-3) the channel forming region of the first transistor is formed of a surface region of the second region which surface region is interposed between the surface region of the first region and the surface region of the fourth region,

(B-1) one source/drain region of the second transistor is formed of the surface region of the second region,

(B-2) the other source/drain region of the second transistor is formed of the third region,

-70-

(B-3) the channel forming region of the second transistor is formed of the surface region of the first region,

(C-1) one source/drain region of the third
5 transistor is formed of the surface region of the second region,

(C-2) the other source/drain region of the third transistor is formed of the fifth region,

(C-3) the channel forming region of the third
10 transistor is formed of the surface region of the fourth region,

(D-1) the gate regions of the junction-field-effect transistor are formed of the fifth region and part of the second region which part is opposed to the
15 fifth region,

(D-2) the channel region of the junction-field-effect transistor is formed of part of the fourth region which part is interposed between the fifth region and said part of the second region,

(D-3) one source/drain region of the junction-field-effect transistor is formed of the surface region of the fourth region which surface region extends from one end of the channel region of the junction-field-effect transistor and constitutes the other source/drain
20 region of the first transistor and the channel forming
25 region of the third transistor,

(D-4) the other source/drain region of the junction-field-effect transistor is formed of a portion of the fourth region which portion extends from the
30 other end of the channel region of the junction-field-effect transistor,

(E-1) one end of the MIS type diode is formed of part of the second region,

(E-2) an electrode constituting the other end of
35 the MIS type diode is formed to be opposed to said part of the second region which part constitutes one end of the MIS type diode, through a wide gap thin film,

-71-

(F) the gate is connected to a first line for memory cell selection,

(G) the third region is connected to a write-in information setting line,

5 (H) said portion of the fourth region which portion constitutes the other source/drain region of the junction-field-effect transistor is connected to a second line, and

(I) the electrode constituting the other end of
10 the MIS type diode is connected to a third line having a predetermined potential.

It is preferred to employ a constitution in which the first region is connected to a fourth line, the second line is used as a bit line and a second
15 predetermined potential is applied to the fourth line, or a constitution in which the first region is connected to a fourth line, the fourth line is used as a bit line and a second predetermined potential is applied to the second line.

20 In the semiconductor memory cell according to the nineteenth aspect of the present invention, there may be employed a constitution in which the first region and the third region constitute a diode and the first region is connected to the write-in information setting
25 line through the third region. When it is required to avoid possibility where carriers implanted from the above diode may latch up the semiconductor memory cell, it is preferred to employ a constitution in which further provided is a diode-constituting region which is
30 formed in a surface region of the first region and is in contact with the first region so as to form a rectifier junction together with the first region, a majority carrier diode comprises the diode-constituting region and the first region, and the first region is connected
35 to the write-in information setting line through the diode-constituting region.

A semiconductor memory cell according to a

-72-

twentieth aspect of the present invention for achieving the above second object differs from the semiconductor memory cell according to the nineteenth aspect of the present invention in that one end of the MIS type diode
5 is formed of the fifth region. That is, according to the twentieth aspect of the present invention, there is provided a semiconductor memory cell comprising;

(1) a first transistor for readout, having a first conductivity type, and having source/drain regions, a
10 semi-conductive channel forming region which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively coupled with the channel forming region,

(2) a second transistor for switching, having a
15 second conductivity type, and having source/drain regions, a semi-conductive channel forming region which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively coupled with the channel forming region,

(3) a third transistor for current control, having
20 the second conductivity type, and having source/drain regions, a semi-conductive channel forming region which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively
25 coupled with the channel forming region,

(4) a junction-field-effect transistor for current control, having source/drain regions, a channel region and gate regions, and

(5) an MIS type diode for retaining information,
30 the semiconductor memory cell having;

(a) a semi-conductive first region having a first conductivity type,

(b) a semi-conductive second region which is in contact with the first region and has a second
35 conductivity type,

(c) a third region which is formed in a surface region of the first region and is in contact with the

-73-

first region so as to form a rectifier junction together with the first region,

(d) a semi-conductive fourth region which is formed in a surface region of the second region and has
5 the first conductivity type,

(e) a semi-conductive fifth region which is formed in a surface region of the fourth region and has the second conductivity type, and

(f) the gate which is formed, through an
10 insulation layer, so as to bridge the first region and the fourth region, so as to bridge the second region and the third region and so as to bridge the second region and the fifth region, and is shared by the first transistor, the second transistor and the third
15 transistor,

wherein:

(A-1) one source/drain region of the first transistor is formed of a surface region of the first region,

20 (A-2) the other source/drain region of the first transistor is formed of a surface region of the fourth region,

(A-3) the channel forming region of the first transistor is formed of a surface region of the second
25 region which surface region is interposed between the surface region of the first region and the surface region of the fourth region,

(B-1) one source/drain region of the second transistor is formed of the surface region of the second
30 region,

(B-2) the other source/drain region of the second transistor is formed of the third region,

(B-3) the channel forming region of the second transistor is formed of the surface region of the first
35 region,

(C-1) one source/drain region of the third transistor is formed of the surface region of the second

-74-

region,

(C-2) the other source/drain region of the third transistor is formed of the fifth region,

(C-3) the channel forming region of the third
5 transistor is formed of the surface region of the fourth region,

(D-1) the gate regions of the junction-field-effect transistor are formed of the fifth region and part of the second region which part is opposed to the
10 fifth region,

(D-2) the channel region of the junction-field-effect transistor is formed of part of the fourth region which part is interposed between the fifth region and said part of the second region,

(D-3) one source/drain region of the junction-field-effect transistor is formed of the surface region of the fourth region which surface region extends from one end of the channel region of the junction-field-effect transistor and constitutes the other source/drain
15 region of the first transistor and the channel forming region of the third transistor,

(D-4) the other source/drain region of the junction-field-effect transistor is formed of a portion of the fourth region which portion extends from the
20 other end of the channel region of the junction-field-effect transistor,

(E-1) one end of the MIS type diode is formed of the fifth region,

(E-2) an electrode constituting the other end of
30 the MIS type diode is formed to be opposed to the fifth region which constitutes one end of the MIS type diode, through a wide gap thin film,

(F) the gate is connected to a first line for memory cell selection,

(G) the third region is connected to a write-in
35 information setting line,

(H) said portion of the fourth region which

-75-

portion constitutes the other source/drain region of the junction-field-effect transistor is connected to a second line, and

(I) the electrode constituting the other end of
5 the MIS type diode is connected to a third line having a predetermined potential.

It is preferred to employ a constitution in which the first region is connected to a fourth line, the second line is used as a bit line and a second
10 predetermined potential is applied to the fourth line, or a constitution in which the first region is connected to a fourth line, the fourth line is used as a bit line and a second predetermined potential is applied to the second line.

15 In the semiconductor memory cell according to the twentieth aspect of the present invention, it is preferred to employ a constitution in which a high-concentration-impurity-containing layer having the second conductivity type is formed in the surface region
20 of the fourth region which surface region constitutes the channel forming region of the third transistor.

In the semiconductor memory cell according to the twentieth aspect of the present invention, there may be employed a constitution in which the first region
25 and the third region constitute a diode and the first region is connected to the write-in information setting line through the third region. When it is required to avoid possibility where carriers implanted from the above diode may latch up the semiconductor memory cell,
30 it is preferred to employ a constitution in which further provided is a diode-constituting region which is formed in a surface region of the first region and is in contact with the first region so as to form a rectifier junction together with the first region, a majority
35 carrier diode comprises the diode-constituting region and the first region, and the first region is connected to the write-in information setting line through the

-76-

diode-constituting region.

A semiconductor memory cell according to a twenty-first aspect of the present invention for achieving the above second object differs from the
5 semiconductor memory cell according to the fourteenth aspect of the present invention in that a second junction-field-effect transistor is provided. That is, according to the twenty-first aspect of the present invention, there is provided a semiconductor memory cell
10 comprising;

(1) a first transistor for readout, having a first conductivity type, and having source/drain regions, a semi-conductive channel forming region which is in contact with the source/drain regions and spaces out the
15 source/drain regions, and a gate capacitively coupled with the channel forming region,

(2) a second transistor for switching, having a second conductivity type, and having source/drain regions, a semi-conductive channel forming region which
20 is in contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively coupled with the channel forming region,

(3) a first junction-field-effect transistor for current control, having source/drain regions, a channel
25 region and gate regions,

(4) a second junction-field-effect transistor for current control, having source/drain regions, a channel region and gate regions, and

(5) an MIS type diode for retaining information,
30 the semiconductor memory cell having;

(a) a semi-conductive first region having a first conductivity type,

(b) a semi-conductive second region which is in contact with the first region and has a second
35 conductivity type,

(c) a third region which is formed in a surface region of the first region and is in contact with the

-77-

first region so as to form a rectifier junction together with the first region,

(d) a semi-conductive fourth region which is formed in a surface region of the second region and has
5 the first conductivity type,

(e) a fifth region which is formed in a surface region of the fourth region and is in contact with the fourth region so as to form a rectifier junction together with the fourth region, and

10 (f) the gate which is formed, through an insulation layer, so as to bridge the first region and the fourth region and so as to bridge the second region and the third region, and is shared by the first transistor and the second transistor,

15 wherein:

(A-1) one source/drain region of the first transistor is formed of a surface region of the first region,

(A-2) the other source/drain region of the first
20 transistor is formed of a surface region of the fourth region,

(A-3) the channel forming region of the first transistor is formed of a surface region of the second region which surface region is interposed between the
25 surface region of the first region and the surface region of the fourth region,

(B-1) one source/drain region of the second transistor is formed of the surface region of the second region,

30 (B-2) the other source/drain region of the second transistor is formed of the third region,

(B-3) the channel forming region of the second transistor is formed of the surface region of the first region,

35 (C-1) the gate regions of the first junction-field-effect transistor are formed of the third region and part of the second region which part is opposed to

-78-

the third region,

(C-2) the channel region of the first junction-field-effect transistor is formed of part of the first region which part is interposed between the third region
5 and said part of the second region,

(C-3) one source/drain region of the first junction-field-effect transistor is formed of the surface region of the first region which surface region extends from one end of the channel region of the first
10 junction-field-effect transistor and constitutes one source/drain region of the first transistor,

(C-4) the other source/drain region of the first junction-field-effect transistor is formed of a portion of the first region which portion extends from the other
15 end of the channel region of the first junction-field-effect transistor,

(D-1) the gate regions of the second junction-field-effect transistor are formed of the fifth region and part of the second region which part is opposed to
20 the fifth region,

(D-2) the channel region of the second junction-field-effect transistor is formed of part of the fourth region which part is interposed between the fifth region and said part of the second region,

(D-3) one source/drain region of the second junction-field-effect transistor is formed of the surface region of the fourth region which surface region extends from one end of the channel region of the second junction-field-effect transistor and constitutes the
25 other source/drain region of the first transistor,

(D-4) the other source/drain region of the second junction-field-effect transistor is formed of a portion of the fourth region which portion extends from the other end of the channel region of the second junction-field-effect transistor,
30 field-effect transistor,

(E-1) one end of the MIS type diode is formed of part of the second region,

-79-

(E-2) an electrode constituting the other end of the MIS type diode is formed to be opposed to said part of the second region which part constitutes one end of the MIS type diode, through a wide gap thin film,

5 (F) the gate is connected to a first line for memory cell selection,

(G) the third region is connected to a write-in information setting line,

10 (H) said portion of the fourth region constituting the other source/drain region of the second junction-field-effect transistor is connected to a second line,

(I) the electrode constituting the other end of the MIS type diode is connected to a third line having a predetermined potential, and

15 (J) the fifth region is connected to a fourth line.

It is preferred to employ a constitution in which the first region is connected to a fifth line, the second line is used as a bit line and a second predetermined potential is applied to the fifth line, or
20 a constitution in which the first region is connected to a fifth line, the fifth line is used as a bit line and a second predetermined potential is applied to the second line.

In the semiconductor memory cell according
25 to the twenty-first aspect of the present invention, there may be employed a constitution in which the first region and the third region constitute a diode and the first region is connected to the write-in information setting line through the third region. Otherwise, it is
30 preferred to employ a constitution in which further provided is a diode-constituting region which is formed in a surface region of the first region and is in contact with the first region so as to form a rectifier junction together with the first region, a majority
35 carrier diode comprises the diode-constituting region and the first region, and the first region is connected to the write-in information setting line through the

-80-

diode-constituting region.

In the semiconductor memory cell according to the twenty first aspect of the present invention, there may be further employed a constitution in which
5 the fifth region constituting the other gate region of the second junction-field-effect transistor is connected to the second region constituting one gate region of the second junction-field-effect transistor in place of being connected to the fourth line or a constitution in
10 which the fifth region constituting the other gate region of the second junction-field-effect transistor is connected to the write-in information setting line in place of being connected to the fourth line. In these cases, there may be employed a constitution in which the
15 first region and the third region constitute a diode and the first region is connected to the write-in information setting line through the third region. Otherwise, it is preferred to employ a constitution in which further provided is a diode-constituting region
20 which is formed in a surface region of the first region and is in contact with the first region so as to form a rectifier junction together with the first region, a majority carrier diode comprises the diode-constituting region and the first region, and the first region is
25 connected to the write-in information setting line through the diode-constituting region.

A semiconductor memory cell according to a twenty-second aspect of the present invention for achieving the above second object differs from the
30 semiconductor memory cell according to the twenty-first aspect of the present invention in that one end of the MIS type diode is formed of the fifth region. That is, according to the twenty-second aspect of the present invention, there is provided a semiconductor memory cell
35 comprising;

(1) a first transistor for readout, having a first conductivity type, and having source/drain regions, a

-81-

semi-conductive channel forming region which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively coupled with the channel forming region,

5 (2) a second transistor for switching, having a second conductivity type, and having source/drain regions, a semi-conductive channel forming region which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively
10 coupled with the channel forming region,

(3) a first junction-field-effect transistor for current control, having source/drain regions, a channel region and gate regions,

(4) a second junction-field-effect transistor for
15 current control, having source/drain regions, a channel region and gate regions, and

(5) an MIS type diode for retaining information, the semiconductor memory cell having;

(a) a semi-conductive first region having a first
20 conductivity type,

(b) a semi-conductive second region which is in contact with the first region and has a second conductivity type,

(c) a third region which is formed in a surface
25 region of the first region and is in contact with the first region so as to form a rectifier junction together with the first region,

(d) a semi-conductive fourth region which is formed in a surface region of the second region and has
30 the first conductivity type,

(e) a semi-conductive fifth region which is formed in a surface region of the fourth region and has the second conductivity type, and

(f) the gate which is formed, through an
35 insulation layer, so as to bridge the first region and the fourth region and so as to bridge the second region and the third region, and is shared by the first

-82-

transistor and the second transistor,
wherein:

(A-1) one source/drain region of the first transistor is formed of a surface region of the first
5 region,

(A-2) the other source/drain region of the first transistor is formed of a surface region of the fourth region,

(A-3) the channel forming region of the first
10 transistor is formed of a surface region of the second region which surface region is interposed between the surface region of the first region and the surface region of the fourth region,

(B-1) one source/drain region of the second
15 transistor is formed of the surface region of the second region,

(B-2) the other source/drain region of the second transistor is formed of the third region,

(B-3) the channel forming region of the second
20 transistor is formed of the surface region of the first region,

(C-1) the gate regions of the first junction-field-effect transistor are formed of the third region and part of the second region which part is opposed to
25 the third region,

(C-2) the channel region of the first junction-field-effect transistor is formed of part of the first region which part is interposed between the third region and said part of the second region,

(C-3) one source/drain region of the first
30 junction-field-effect transistor is formed of the surface region of the first region which surface region extends from one end of the channel region of the first junction-field-effect transistor and constitutes one
35 source/drain region of the first transistor,

(C-4) the other source/drain region of the first junction-field-effect transistor is formed of a portion

-83-

of the first region which portion extends from the other end of the channel region of the first junction-field-effect transistor,

(D-1) the gate regions of the second junction-field-effect transistor are formed of the fifth region and part of the second region which part is opposed to the fifth region,

(D-2) the channel region of the second junction-field-effect transistor is formed of part of the fourth region which part is interposed between the fifth region and said part of the second region,

(D-3) one source/drain region of the second junction-field-effect transistor is formed of the surface region of the fourth region which surface region extends from one end of the channel region of the second junction-field-effect transistor and constitutes the other source/drain region of the first transistor,

(D-4) the other source/drain region of the second junction-field-effect transistor is formed of a portion of the fourth region which portion extends from the other end of the channel region of the second junction-field-effect transistor,

(E-1) one end of the MIS type diode is formed of the fifth region,

(E-2) an electrode constituting the other end of the MIS type diode is formed to be opposed to the fifth region which constitutes one end of the MIS type diode, through a wide gap thin film,

(F) the gate is connected to a first line for memory cell selection,

(G) the third region is connected to a write-in information setting line,

(H) said portion of the fourth region constituting the other source/drain region of the second junction-field-effect transistor is connected to a second line,

(I) the fifth region is connected to the second region, and

-84-

(J) the electrode constituting the other end of the MIS type diode is connected to a third line having a predetermined potential.

It is preferred to employ a constitution in which the first region is connected to a fifth line, the second line is used as a bit line and a second predetermined potential is applied to the fifth line, or a constitution in which the first region is connected to a fifth line, the fifth line is used as a bit line and a second predetermined potential is applied to the second line.

In the semiconductor memory cell according to the twenty-second aspect of the present invention, there may be employed a constitution in which the first region and the third region constitute a diode and the first region is connected to the write-in information setting line through the third region. Otherwise, it is preferred to employ a constitution in which further provided is a diode-constituting region which is formed in a surface region of the first region and is in contact with the first region so as to form a rectifier junction together with the first region, a majority carrier diode comprises the diode-constituting region and the first region, and the first region is connected to the write-in information setting line through the diode-constituting region.

A semiconductor memory cell according to a twenty-third aspect of the present invention for achieving the above second object differs from the semiconductor memory cell according to the twenty-first aspect of the present invention in that a third transistor is provided. That is, according to the twenty-third aspect of the present invention, there is provided a semiconductor memory cell comprising;

(1) a first transistor for readout, having a first conductivity type, and having source/drain regions, a semi-conductive channel forming region which is in

-85-

contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively coupled with the channel forming region,

5 (2) a second transistor for switching, having a second conductivity type, and having source/drain regions, a semi-conductive channel forming region which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively coupled with the channel forming region,

10 (3) a third transistor for current control, having the second conductivity type, and having source/drain regions, a semi-conductive channel forming region which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively coupled with the channel forming region,

(4) a first junction-field-effect transistor for current control, having source/drain regions, a channel region and gate regions,

20 (5) a second junction-field-effect transistor for current control, having source/drain regions, a channel region and gate regions, and

(6) an MIS type diode for retaining information, the semiconductor memory cell having;

(a) a semi-conductive first region having a first conductivity type,

(b) a semi-conductive second region which is in contact with the first region and has a second conductivity type,

30 (c) a third region which is formed in a surface region of the first region and is in contact with the first region so as to form a rectifier junction together with the first region,

(d) a semi-conductive fourth region which is formed in a surface region of the second region and has the first conductivity type,

(e) a fifth region which is formed in a surface region of the fourth region and is in contact with the

-86-

fourth region so as to form a rectifier junction together with the fourth region, and

(f) the gate which is formed, through an insulation layer, so as to bridge the first region and the fourth region, so as to bridge the second region and the third region and so as to bridge the second region and the fifth region, and is shared by the first transistor, the second transistor and the third transistor,

10 wherein:

(A-1) one source/drain region of the first transistor is formed of a surface region of the first region,

(A-2) the other source/drain region of the first transistor is formed of a surface region of the fourth region,

(A-3) the channel forming region of the first transistor is formed of a surface region of the second region which surface region is interposed between the surface region of the first region and the surface region of the fourth region,

(B-1) one source/drain region of the second transistor is formed of the surface region of the second region,

(B-2) the other source/drain region of the second transistor is formed of the third region,

(B-3) the channel forming region of the second transistor is formed of the surface region of the first region,

(C-1) one source/drain region of the third transistor is formed of the surface region of the second region,

(C-2) the other source/drain region of the third transistor is formed of the fifth region,

(C-3) the channel forming region of the third transistor is formed of the surface region of the fourth region,

-87-

(D-1) the gate regions of the first junction-field-effect transistor are formed of the third region and part of the second region which part is opposed to the third region,

5 (D-2) the channel region of the first junction-field-effect transistor is formed of part of the first region which part is interposed between the third region and said part of the second region,

(D-3) one source/drain region of the first
10 junction-field-effect transistor is formed of the surface region of the first region which surface region extends from one end of the channel region of the first junction-field-effect transistor and constitutes one source/drain region of the first transistor,

15 (D-4) the other source/drain region of the first junction-field-effect transistor is formed of a portion of the first region which portion extends from the other end of the channel region of the first junction-field-effect transistor,

20 (E-1) the gate regions of the second junction-field-effect transistor are formed of the fifth region and part of the second region which part is opposed to the fifth region,

(E-2) the channel region of the second junction-field-effect transistor is formed of part of the fourth
25 region which part is interposed between the fifth region and said part of the second region,

(E-3) one source/drain region of the second junction-field-effect transistor is formed of the
30 surface region of the fourth region which surface region extends from one end of the channel region of the second junction-field-effect transistor and constitutes the other source/drain region of the first transistor and the channel forming region of the third transistor,

35 (E-4) the other source/drain region of the second junction-field-effect transistor is formed of a portion of the fourth region which portion extends from the

-88-

other end of the channel region of the second junction-field-effect transistor,

(F-1) one end of the MIS type diode is formed of part of the second region,

5 (F-2) an electrode constituting the other end of the MIS type diode is formed to be opposed to said part of the second region which part constitutes one end of the MIS type diode, through a wide gap thin film,

(G) the gate is connected to a first line for
10 memory cell selection,

(H) the third region is connected to a write-in information setting line,

(I) said portion of the fourth region constituting the other source/drain region of the second junction-field-effect transistor is connected to a second line,
15 and

(J) the electrode constituting the other end of the MIS type diode is connected to a third line having a predetermined potential.

20 It is preferred to employ a constitution in which the first region is connected to a fourth line, the second line is used as a bit line and a second predetermined potential is applied to the fourth line, or a constitution in which the first region is connected
25 to a fourth line, the fourth line is used as a bit line and a second predetermined potential is applied to the second line.

In the semiconductor memory cell according to the twenty-third aspect of the present invention,
30 there may be employed a constitution in which the first region and the third region constitute a diode and the first region is connected to the write-in information setting line through the third region. Otherwise, it is preferred to employ a constitution in which further
35 provided is a diode-constituting region which is formed in a surface region of the first region and is in contact with the first region so as to form a rectifier

-89-

junction together with the first region, a majority carrier diode comprises the diode-constituting region and the first region, and the first region is connected to the write-in information setting line through the
5 diode-constituting region.

A semiconductor memory cell according to a twenty-fourth aspect of the present invention for achieving the above second object differs from the semiconductor memory cell according to the twenty-third
10 aspect of the present invention in that one end of the MIS type diode is formed of the fifth region. That is, according to the twenty-fourth aspect of the present invention, there is provided a semiconductor memory cell comprising;

15 (1) a first transistor for readout, having a first conductivity type, and having source/drain regions, a semi-conductive channel forming region which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively coupled
20 with the channel forming region,

(2) a second transistor for switching, having a second conductivity type, and having source/drain regions, a semi-conductive channel forming region which is in contact with the source/drain regions and spaces
25 out the source/drain regions, and a gate capacitively coupled with the channel forming region,

(3) a third transistor for current control, having the second conductivity type, and having source/drain regions, a semi-conductive channel forming region which
30 is in contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively coupled with the channel forming region,

(4) a first junction-field-effect transistor for current control, having source/drain regions, a channel
35 region and gate regions,

(5) a second junction-field-effect transistor for current control, having source/drain regions, a channel

-90-

region and gate regions, and

(6) an MIS type diode for retaining information,
the semiconductor memory cell having;

(a) a semi-conductive first region having a first
5 conductivity type,

(b) a semi-conductive second region which is in
contact with the first region and has a second
conductivity type,

(c) a third region which is formed in a surface
10 region of the first region and is in contact with the
first region so as to form a rectifier junction together
with the first region,

(d) a semi-conductive fourth region which is
formed in a surface region of the second region and has
15 the first conductivity type,

(e) a semi-conductive fifth region which is formed
in a surface region of the fourth region and has the
second conductivity type, and

(f) the gate which is formed, through an
20 insulation layer, so as to bridge the first region and
the fourth region, so as to bridge the second region and
the third region and so as to bridge the second region
and the fifth region, and is shared by the first
transistor, the second transistor and the third
25 transistor,

wherein:

(A-1) one source/drain region of the first
transistor is formed of a surface region of the first
region,

30 (A-2) the other source/drain region of the first
transistor is formed of a surface region of the fourth
region,

(A-3) the channel forming region of the first
transistor is formed of a surface region of the second
35 region which surface region is interposed between the
surface region of the first region and the surface
region of the fourth region,

-91-

(B-1) one source/drain region of the second transistor is formed of the surface region of the second region,

(B-2) the other source/drain region of the second transistor is formed of the third region,

(B-3) the channel forming region of the second transistor is formed of the surface region of the first region,

(C-1) one source/drain region of the third transistor is formed of the surface region of the second region,

(C-2) the other source/drain region of the third transistor is formed of the fifth region,

(C-3) the channel forming region of the third transistor is formed of the surface region of the fourth region,

(D-1) the gate regions of the first junction-field-effect transistor are formed of the third region and part of the second region which part is opposed to the third region,

(D-2) the channel region of the first junction-field-effect transistor is formed of part of the first region which part is interposed between the third region and said part of the second region,

(D-3) one source/drain region of the first junction-field-effect transistor is formed of the surface region of the first region which surface region extends from one end of the channel region of the first junction-field-effect transistor and constitutes one source/drain region of the first transistor,

(D-4) the other source/drain region of the first junction-field-effect transistor is formed of a portion of the first region which portion extends from the other end of the channel region of the first junction-field-effect transistor,

(E-1) the gate regions of the second junction-field-effect transistor are formed of the fifth region

-92-

and part of the second region which part is opposed to the fifth region,

(E-2) the channel region of the second junction-field-effect transistor is formed of part of the fourth region which part is interposed between the fifth region and said part of the second region,

(E-3) one source/drain region of the second junction-field-effect transistor is formed of the surface region of the fourth region which surface region extends from one end of the channel region of the second junction-field-effect transistor and constitutes the other source/drain region of the first transistor and the channel forming region of the third transistor,

(E-4) the other source/drain region of the second junction-field-effect transistor is formed of a portion of the fourth region which portion extends from the other end of the channel region of the second junction-field-effect transistor,

(F-1) one end of the MIS type diode is formed of the fifth region,

(F-2) an electrode constituting the other end of the MIS type diode is formed to be opposed to the fifth region which constitutes one end of the MIS type diode, through a wide gap thin film,

(G) the gate is connected to a first line for memory cell selection,

(H) the third region is connected to a write-in information setting line,

(I) said portion of the fourth region constituting the other source/drain region of the second junction-field-effect transistor is connected to a second line,

(J) the fifth region is connected to the second region, and

(K) the electrode constituting the other end of the MIS type diode is connected to a third line having a predetermined potential.

It is preferred to employ a constitution in

-93-

which the first region is connected to a fourth line,
the second line is used as a bit line and a second
predetermined potential is applied to the fourth line,
or a constitution in which the first region is connected
5 to a fourth line, the fourth line is used as a bit line
and a second predetermined potential is applied to the
second line.

In the semiconductor memory cell according
to the twenty-fourth aspect of the present invention, it
10 is preferred to employ a constitution in which a high-
concentration-impurity-containing layer having the
second conductivity type is formed in the surface region
of the fourth region which surface region constitutes
the channel forming region of the third transistor.

15 In the semiconductor memory cell according
to the twenty-fourth aspect of the present invention,
there may be employed a constitution in which the first
region and the third region constitute a diode and the
first region is connected to the write-in information
20 setting line through the third region. Otherwise, it is
preferred to employ a constitution in which further
provided is a diode-constituting region which is formed
in a surface region of the first region and is in
contact with the first region so as to form a rectifier
25 junction together with the first region, a majority
carrier diode comprises the diode-constituting region
and the first region, and the first region is connected
to the write-in information setting line through the
diode-constituting region.

30 In the semiconductor memory cell according
to any one of the twelfth to twenty-fourth aspects of
the present invention and a twenty fifth to a twenty-
ninth aspects of the present invention to be described
later, preferably, the electrode constituting the other
35 end of the MIS type diode is connected to the third line,
having a predetermined potential and corresponding to
the above line, through a high-resistance element for

-94-

preventing the deterioration of characteristics of the wide gap thin film. Preferably, the electrode constituting the other end of the MIS type diode and the high-resistance element are integrally formed and are composed of a silicon thin layer (for example, polysilicon thin layer) in view of the simplification of a wiring structure. Further, preferably, the silicon thin layer contains an impurity having the first conductivity type.

10 In the semiconductor memory cell according to any one of the twelfth to twenty-fourth aspects of the present invention and the twenty fifth to the twenty-ninth aspects of the present invention to be described later, the wide gap thin film is preferably
15 composed of a material in which the tunnel transition of carriers is caused depending upon a potential difference between the potential in the region constituting one end of the MIS type diode and the potential in the other end of the MIS type diode. In this case, it is preferred to
20 employ the following constitution. Binary information of first information or second information is stored in the semiconductor memory cell, the first information to be stored in the semiconductor memory cell corresponds to a first potential in the channel forming region of
25 the first transistor, and the second information to be stored in the semiconductor memory cell corresponds to a second potential in the channel forming region of the first transistor. (i) When the potential in the channel forming region of the first transistor is the first
30 potential, the tunnel transition of carriers is caused from the other end to one end of the MIS type diode. As a result, carrier multiplication takes place, holes or electrons are stored in the region (or part of the region) constituting one end of the MIS type diode
35 depending upon the conductivity type of one end of the MIS type diode, and the potential in the channel forming region of the first transistor is held nearly at the

-95-

first potential. (ii) When the potential in the channel forming region of the first transistor is the second potential, carriers having the polarity opposite to that of the above carriers transit from one end to the other end of the MIS type diode. As a result, the potential in the channel forming region of the first transistor is held at the second potential.

In a preferred embodiment of the semiconductor memory cell according to any one of the twelfth to twenty-fourth aspects of the present invention, it is preferred to form a first high-concentration-impurity-containing layer having the first conductivity type below the region constituting the channel forming region of the first transistor, since the potential or charge to be stored in the channel forming region of the first transistor can be increased. In the semiconductor memory cell according to any one of the twelfth to twenty-fourth aspects of the present invention, there may be employed a constitution in which a second high-concentration-impurity-containing layer having the first conductivity type, which functions as a line connected to one source/drain region of the first transistor, is formed below the region constituting one source/drain region the first transistor depending upon the arrangement of the regions, since the wiring structure can be simplified.

In the semiconductor memory cell according to any one of the twelfth to twenty-fourth aspects of the present invention, the semi-conductive or conductive region may be composed of a silicide, a metal or a metal compound, while the region is preferably composed of semiconductor. When a diode-constituting region is provided for forming the majority carrier-diode, the diode-constituting region may be composed of a semiconductor, while the diode-constituting region may be composed of a silicide, a metal or a metal compound and in this case, the region, in the surface region of

-96-

which the diode-constituting region is formed, is preferably composed of semiconductor. The structure in which the third region is connected to the write-in information setting line includes a structure in which
5 the third region has a common region with part of the write-in information setting line (in other words, a structure in which the third line and part of the write-in information setting line are formed as a common region). Further, the structure in which the fourth
10 region is connected to the second line includes a structure in which the fourth region has a common region with part of the second line (in other words, a structure in which the fourth region and part of the second line are formed as a common region).

15 According to a twenty-fifth aspect of the present invention for achieving the above second object, as a drawing of its principle is shown in Fig. 179A, there is provided a semiconductor memory cell having a semiconductor layer having two main surfaces opposed to
20 each other, the main surfaces being a first main surface and a second main surface,

the semiconductor memory cell comprising;

(1) a first transistor for readout, having a first conductivity type, and having source/drain regions, a
25 semi-conductive channel forming region which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively coupled with the channel forming region,

(2) a second transistor for switching, having a
30 second conductivity type, and having source/drain regions, a semi-conductive channel forming region which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively coupled with the channel forming region,

35 (3) a junction-field-effect transistor for current control, having source/drain regions, a channel region and gate regions, and

-97-

(4) an MIS type diode for retaining information,
the semiconductor memory cell further
having;

5 (a) a semi-conductive first region which is formed
in the semiconductor layer to extend over from the first
main surface to the second main surface and has a first
conductivity type,

10 (b) a semi-conductive second region which is
formed in the semiconductor layer to extend over from
the first main surface to the second main surface, is in
contact with the first region and has a second
conductivity type,

15 (c) a third region which is formed in a surface
region including the second main surface of the first
region to be spaced from the second region and is in
contact with the first region so as to form a rectifier
junction together with the first region,

20 (d) a fourth region which is formed in a surface
region including the first main surface of the second
region to be spaced from the first region and is in
contact with the second region so as to form a rectifier
junction together with the second region,

25 (e) a fifth region which is formed in a surface
region including the first main surface of the first
region to be spaced from the second region and is in
contact with the first region so as to form a rectifier
junction together with the first region,

30 (f) the gate of the first transistor formed on a
first insulation layer formed on the first main surface
so as to bridge the first region and the fourth region,
and

(g) the gate of the second transistor formed on a
second insulation layer formed on the second main
surface so as to bridge the second region and the third
35 region,

wherein:

(A-1) one source/drain region of the first

-98-

transistor is formed of a surface region including the first main surface of the first region,

(A-2) the other source/drain region of the first transistor is formed of the fourth region,

5 (A-3) the channel forming region of the first transistor is formed of a surface region including the first main surface of the second region which surface region is interposed between the surface region including the first main surface of the first region and
10 the fourth region,

(B-1) one source/drain region of the second transistor is formed of a surface region including the second main surface of the second region,

(B-2) the other source/drain region of the second
15 transistor is formed of the third region,

(B-3) the channel forming region of the second transistor is formed of a surface region including the second main surface of the first region which surface region is interposed between the surface region
20 including the second main surface of the second region and the third region,

(C-1) the gate regions of the junction-field-effect transistor are formed of the fifth region and the third region which is opposed to the fifth region,

25 (C-2) the channel region of the junction-field-effect transistor is formed of part of the first region which part is interposed between the fifth region and the third region,

(C-3) one source/drain region of the junction-field-effect transistor is formed of a portion of the
30 first region which portion extends from one end of the channel region of the junction-field-effect transistor and constitutes one source/drain region of the first transistor and the channel forming region of the second
35 transistor,

(C-4) the other source/drain region of the junction-field-effect transistor is formed of a portion

-99-

of the first region which portion extends from the other end of the channel region of the junction-field-effect transistor,

(D-1) one end of the MIS type diode is formed of
5 part of the second region,

(D-2) an electrode constituting the other end of the MIS type diode is formed to be opposed to said part of the second region constituting one end of the MIS type diode, through a wide gap thin film,

10 (E) the gate of the first transistor and the gate of the second transistor are connected to a first line for memory cell selection,

(F) the third region is connected to a write-in information setting line,

15 (G) the fourth region is connected to a second line,

(H) the electrode constituting the other end of the MIS type diode is connected to a third line having a predetermined potential,

20 (I) the fifth region is connected to a fourth line, and

(J) said portion of the first region which portion constitutes the other source/drain region of the junction-field-effect transistor is connected to a fifth
25 line.

There may be employed a constitution in which the second line is used as a bit line and a second predetermined potential is applied to the fifth line.

Otherwise, there may be also employed another
30 constitution in which a second predetermined potential is applied to the second line and the fifth line is used as a bit line.

There may be employed a constitution in which, as a drawing of its principle is shown in Fig.
35 179B, the fifth line is connected to the write-in information setting line or the third region in place of being connected to the fourth line, since the wiring

-100-

structure can be simplified. In this case, there may be employed a constitution in which the second line is used as a bit line or a constitution in which the write-in information setting line is co-used as a bit line and a
5 second predetermined potential is applied to the second line.

In the semiconductor memory cell according to the twenty-fifth aspect of the present invention, the structure in which the third region is connected to the
10 write-in information setting line includes a structure in which the third region has a common region with part of the write-in information setting line. Further, the structure in which the fourth region is connected to the second line includes a structure in which the fourth
15 region has a common region with part of the second line. The structure in which the fifth region is connected to the fourth line includes a structure in which the fifth region has a common region with part of the fourth line. Further, the structure in which the fifth region is
20 connected to the write-in information setting line includes a structure in which the fifth region has a common region with part of the write-in information setting line.

According to a twenty-sixth aspect of the present invention for achieving the above second object, as a drawing of its principle is shown in Fig. 108,
there is provided a semiconductor memory cell having a semiconductor layer having two main surfaces opposed to each other, the main surfaces being a first main surface
30 and a second main surface,

the semiconductor memory cell comprising;

(1) a first transistor for readout, having a first conductivity type, and having source/drain regions, a semi-conductive channel forming region which is in
35 contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively coupled with the channel forming region,

-101-

(2) a second transistor for switching, having a second conductivity type, and having source/drain regions, a semi-conductive channel forming region which is in contact with the source/drain regions and spaces
5 out the source/drain regions, and a gate capacitively coupled with the channel forming region,

(3) a junction-field-effect transistor for current control, having source/drain regions, a channel region and gate regions, and

10 (4) an MIS type diode for retaining information, the semiconductor memory cell further having;

(a) a semi-conductive first region which is formed in the semiconductor layer to extend over from the first
15 main surface to the second main surface and has a first conductivity type,

(b) a semi-conductive second region which is formed in the semiconductor layer to extend over from the first main surface to the second main surface, is in
20 contact with the first region and has a second conductivity type,

(c) a third region which is formed in a surface region including the second main surface of the first region to be spaced from the second region and is in
25 contact with the first region so as to form a rectifier junction together with the first region,

(d) a fourth region which is formed in a surface region including the first main surface of the second region to be spaced from the first region and is in
30 contact with the second region so as to form a rectifier junction together with the second region,

(e) a fifth region which is formed in a surface region of the fourth region and is in contact with the fourth region so as to form a rectifier junction
35 together with the fourth region,

(f) the gate of the first transistor formed on a first insulation layer formed on the first main surface

-102-

so as to bridge the first region and the fourth region,
and

(g) the gate of the second transistor formed on a
second insulation layer formed on the second main
5 surface so as to bridge the second region and the third
region,

wherein:

(A-1) one source/drain region of the first
transistor is formed of a surface region including the
10 first main surface of the first region,

(A-2) the other source/drain region of the first
transistor is formed of the fourth region,

(A-3) the channel forming region of the first
transistor is formed of a surface region including the
15 first main surface of the second region which surface
region is interposed between the surface region
including the first main surface of the first region and
the fourth region,

(B-1) one source/drain region of the second
20 transistor is formed of a surface region including the
second main surface of the second region,

(B-2) the other source/drain region of the second
transistor is formed of the third region,

(B-3) the channel forming region of the second
25 transistor is formed of a surface region including the
second main surface of the first region which surface
region is interposed between the surface region
including the second main surface of the second region
and the third region,

(C-1) the gate regions of the junction-field-
30 effect transistor are formed of the fifth region and
part of the second region which part is opposed to the
fifth region,

(C-2) the channel region of the junction-field-
35 effect transistor is formed of part of the fourth region
which part is interposed between the fifth region and
said part of the second region,

-103-

(C-3) one source/drain region of the junction-field-effect transistor is formed of a portion of the fourth region which portion extends from one end of the channel region of the junction-field-effect transistor
5 and constitutes the other source/drain region of the first transistor,

(C-4) the other source/drain region of the junction-field-effect transistor is formed of a portion of the fourth region which portion extends from the
10 other end of the channel region of the junction-field-effect transistor,

(D-1) one end of the MIS type diode is formed of part of the second region,

(D-2) an electrode constituting the other end of
15 the MIS type diode is formed to be opposed to said part of the second region constituting one end of the MIS type diode, through a wide gap thin film,

(E) the gate of the first transistor and the gate of the second transistor are connected to a first line
20 for memory cell selection,

(F) said portion of the fourth region constituting the other source/drain region of the junction-field-effect transistor is connected to a second line,

(G) the electrode constituting the other end of
25 the MIS type diode is connected to a third line having a predetermined potential,

(H) the third region is connected to a write-in information setting line,

(I) the fifth region is connected to a fourth line,
30 and

(J) the first region is connected to a fifth line.

There may be employed a constitution in which the second line is used as a bit line and a second predetermined potential is applied to the fifth line.
35 Otherwise, there may be also employed another constitution in which a second predetermined potential is applied to the second line and the fifth line is used

-104-

as a bit line.

There may be employed a constitution in which, as a drawing of its principle is shown in Fig. 112, the fifth line is connected to the second region in place of being connected to the fourth line, since the wiring structure can be simplified. In this case, there may be employed a constitution in which the second line is used as a bit line or a constitution in which the write-in information setting line is co-used as a bit line and a second predetermined potential is applied to the second line.

In the semiconductor memory cell according to the twenty-sixth aspect of the present invention, the structure in which the third region is connected to the write-in information setting line includes a structure in which the third region has a common region with part of the write-in information setting line. Further, the structure in which the fifth region is connected to the fourth line includes a structure in which the fifth region has a common region with part of the fourth line.

A semiconductor memory cell according to a twenty-seventh aspect of the present invention for achieving the above second object differs from the semiconductor memory cell according to the twenty-sixth aspect of the present invention in that a sixth region is further formed and a second junction-field-effect transistor is provided, as a drawing of its principle is shown in Fig. 191.

That is, according to the twenty-seventh aspect of the present invention, there is provided a semiconductor memory cell having a semiconductor layer having two main surfaces opposed to each other, the main surfaces being a first main surface and a second main surface,

the semiconductor memory cell comprising;
(1) a first transistor for readout, having a first conductivity type, and having source/drain regions, a

-105-

semi-conductive channel forming region which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively coupled with the channel forming region,

5 (2) a second transistor for switching, having a second conductivity type, and having source/drain regions, a semi-conductive channel forming region which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively
10 coupled with the channel forming region,

 (3) a first junction-field-effect transistor for current control, having source/drain regions, a channel region and gate regions,

 (4) a second junction-field-effect transistor for
15 current control, having source/drain regions, a channel region and gate regions, and

 (5) an MIS type diode for retaining information, the semiconductor memory cell further
having;

20 (a) a semi-conductive first region which is formed in the semiconductor layer to extend over from the first main surface to the second main surface and has a first conductivity type,

 (b) a semi-conductive second region which is
25 formed in the semiconductor layer to extend over from the first main surface to the second main surface, is in contact with the first region and has a second conductivity type,

 (c) a third region which is formed in a surface
30 region including the second main surface of the first region to be spaced from the second region and is in contact with the first region so as to form a rectifier junction together with the first region,

 (d) a fourth region which is formed in a surface
35 region including the first main surface of the second region to be spaced from the first region and is in contact with the second region so as to form a rectifier

-106-

junction together with the second region,

(e) a fifth region which is formed in a surface region including the first main surface of the first region to be spaced from the second region and is in
5 contact with the first region so as to form a rectifier junction together with the first region,

(f) a sixth region which is formed in a surface region of the fourth region and is in contact with the fourth region so as to form a rectifier junction
10 together with the fourth region,

(g) the gate of the first transistor formed on a first insulation layer formed on the first main surface so as to bridge the first region and the fourth region, and

15 (h) the gate of the second transistor formed on a second insulation layer formed on the second main surface so as to bridge the second region and the third region,

wherein:

20 (A-1) one source/drain region of the first transistor is formed of a surface region including the first main surface of the first region,

(A-2) the other source/drain region of the first transistor is formed of the fourth region,

25 (A-3) the channel forming region of the first transistor is formed of a surface region including the first main surface of the second region which surface region is interposed between the surface region including the first main surface of the first region and
30 the fourth region,

(B-1) one source/drain region of the second transistor is formed of a surface region including the second main surface of the second region,

(B-2) the other source/drain region of the second
35 transistor is formed of the third region,

(B-3) the channel forming region of the second transistor is formed of a surface region including the

-107-

second main surface of the first region which surface region is interposed between the surface region including the second main surface of the second region and the third region,

5 (C-1) the gate regions of the first junction-field-effect transistor are formed of the fifth region and the third region which is opposed to the fifth region,

10 (C-2) the channel region of the first junction-field-effect transistor is formed of part of the first region which part is interposed between the fifth region and the third region,

(C-3) one source/drain region of the first junction-field-effect transistor is formed of a portion
15 of the first region which portion extends from one end of the channel region of the first junction-field-effect transistor and constitutes one source/drain region of the first transistor and the channel forming region of the second transistor,

20 (C-4) the other source/drain region of the first junction-field-effect transistor is formed of a portion of the first region which portion extends from the other end of the channel region of the first junction-field-effect transistor,

25 (D-1) the gate regions of the second junction-field-effect transistor are formed of the sixth region and part of the second region which part is opposed to the sixth region,

(D-2) the channel region of the second junction-field-effect transistor is formed of part of the fourth
30 region which part is interposed between the sixth region and said part of the second region,

(D-3) one source/drain region of the second junction-field-effect transistor is formed of a portion
35 of the fourth region which portion extends from one end of the channel region of the second junction-field-effect transistor and constitutes the other source/drain

-108-

region of the first transistor,

(D-4) the other source/drain region of the second junction-field-effect transistor is formed of a portion of the fourth region which portion extends from the
5 other end of the channel region of the second junction-field-effect transistor,

(E-1) one end of the MIS type diode is formed of part of the second region,

(E-2) an electrode constituting the other end of
10 the MIS type diode is formed to be opposed to said part of the second region constituting one end of the MIS type diode, through a wide gap thin film,

(F) the gate of the first transistor and the gate of the second transistor are connected to a first line
15 for memory cell selection,

(G) the third region is connected to a write-in information setting line,

(H) said portion of the fourth region constituting the other source/drain region of the second junction-field-effect transistor is connected to a second line,
20

(I) the electrode constituting the other end of the MIS type diode is connected to a third line having a predetermined potential,

(J) the fifth region and the sixth region are
25 connected to a fourth line, and

(K) said portion of the first region constituting the other source/drain region of the first junction-field-effect transistor is connected to a fifth line.

There may be employed a constitution in
30 which the second line is used as a bit line and a second predetermined potential is applied to the fifth line. Otherwise, there may be also employed another constitution in which a second predetermined potential is applied to the second line and the fifth line is used
35 as a bit line.

In the semiconductor memory cell according to the twenty-seventh aspect of the present invention,

-109-

the fifth region may be connected to the third region (the write-in information setting line) in place of being connected to the fourth line. The sixth region may be connected to the second region in place of being connected to the fourth line. In this case, there may be employed a constitution in which the second line is used as a bit line or a constitution in which the write-in information setting line is co-used as a bit line and a second predetermined potential is applied to the second line.

In the semiconductor memory cell according to the twenty-seventh aspect of the present invention, the structure in which the third region is connected to the write-in information setting line includes a structure in which the third region has a common region with part of the write-in information setting line. Further, the structure in which the fifth region and the sixth region are connected to the fourth line includes a structure in which the fifth region and the sixth region have common regions with part of the fourth line. Further, the structure in which the fifth region is connected to the write-in information setting line includes a structure in which the fifth region has a common region with part of the write-in information setting line.

In a semiconductor memory cell according to a twenty-eighth aspect of the present invention for achieving the above second object, a third transistor for current control, having a second conductivity, is added into a semiconductor memory cell having a structure similar to that of the semiconductor memory cell according to the twenty-sixth aspect of the present invention, as a drawing of its principle is shown in Fig. 138.

That is, according to the twenty-eighth aspect of the present invention, there is provided a semiconductor memory cell having a semiconductor layer

-110-

having two main surfaces opposed to each other, the main surfaces being a first main surface and a second main surface,

the semiconductor memory cell comprising;

5 (1) a first transistor for readout, having a first conductivity type, and having source/drain regions, a semi-conductive channel forming region which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively coupled
10 with the channel forming region,

(2) a second transistor for switching, having a second conductivity type, and having source/drain regions, a semi-conductive channel forming region which is in contact with the source/drain regions and spaces
15 out the source/drain regions, and a gate capacitively coupled with the channel forming region,

(3) a third transistor for current control, having the second conductivity type, and having source/drain regions, a semi-conductive channel forming region which
20 is in contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively coupled with the channel forming region,

(4) a junction-field-effect transistor for current control, having source/drain regions, a channel region
25 and gate regions, and

(5) an MIS type diode for retaining information,
the semiconductor memory cell further
having;

(a) a semi-conductive first region which is formed
30 in the semiconductor layer to extend over from the first main surface to the second main surface and has a first conductivity type,

(b) a semi-conductive second region which is formed in the semiconductor layer to extend over from
35 the first main surface to the second main surface, is in contact with the first region and has a second conductivity type,

-111-

(c) a third region which is formed in a surface region including the second main surface of the first region to be spaced from the second region and is in contact with the first region so as to form a rectifier junction together with the first region,

(d) a fourth region which is formed in a surface region including the first main surface of the second region to be spaced from the first region and is in contact with the second region so as to form a rectifier junction together with the second region,

(e) a fifth region which is formed in a surface region of the fourth region and is in contact with the fourth region so as to form a rectifier junction together with the fourth region,

(f) the gate formed on a first insulation layer formed on the first main surface so as to bridge the first region and the fourth region and so as to bridge the second region and the fifth region, and is shared by the first transistor and the third transistor, and

(g) the gate of the second transistor formed on a second insulation layer formed on the second main surface so as to bridge the second region and the third region,

wherein:

(A-1) one source/drain region of the first transistor is formed of a surface region including the first main surface of the first region,

(A-2) the other source/drain region of the first transistor is formed of the fourth region,

(A-3) the channel forming region of the first transistor is formed of a surface region including the first main surface of the second region which surface region is interposed between the surface region including the first main surface of the first region and the fourth region,

(B-1) one source/drain region of the second transistor is formed of a surface region including the

-112-

second main surface of the second region,

(B-2) the other source/drain region of the second transistor is formed of the third region,

(B-3) the channel forming region of the second
5 transistor is formed of a surface region including the second main surface of the first region which surface region is interposed between the surface region including the second main surface of the second region and the third region,

10 (C-1) one source/drain region of the third transistor constitutes the channel forming region of the first transistor,

(C-2) the other source/drain region of the third transistor is formed of the fifth region,

15 (C-3) the channel forming region of the third transistor constitutes the other source/drain region of the first transistor,

(D-1) the gate regions of the junction-field-effect transistor are formed of the fifth region and
20 part of the second region which part is opposed to the fifth region,

(D-2) the channel region of the junction-field-effect transistor is formed of part of the fourth region which part is interposed between the fifth region and
25 said part of the second region,

(D-3) one source/drain region of the junction-field-effect transistor is formed of a portion of the fourth region which portion extends from one end of the channel region of the junction-field-effect transistor
30 and constitutes the other source/drain region of the first transistor,

(D-4) the other source/drain region of the junction-field-effect transistor is formed of a portion of the fourth region which portion extends from the
35 other end of the channel region of the junction-field-effect transistor,

(E-1) one end of the MIS type diode is formed of

-113-

part of the second region,

(E-2) an electrode constituting the other end of the MIS type diode is formed to be opposed to said part of the second region constituting one end of the MIS
5 type diode, through a wide gap thin film,

(F) the gate shared by of the first transistor and the third transistor and the gate of the second transistor are connected to a first line for memory cell selection,

10 (G) the third region is connected to a write-in information setting line,

(H) said portion of the fourth region constituting the other source/drain region of the junction-field-effect transistor is connected to a second line,

15 (I) the electrode constituting the other end of the MIS type diode is connected to a third line having a predetermined potential, and

(J) the first region is connected to a fourth line.

There may be employed a constitution in
20 which the second line is used as a bit line and a second predetermined potential is applied to the fourth line. Otherwise, there may be also employed another constitution in which a second predetermined potential is applied to the second line and the fourth line is
25 used as a bit line.

In the semiconductor memory cell according to the twenty-eighth aspect of the present invention, the structure in which the third region is connected to the write-in information setting line includes a
30 structure in which the third region has a common region with part of the write-in information setting line.

A semiconductor memory cell according to a twenty-ninth aspect of the present invention for achieving the above second object, as a drawing of its
35 principle is shown in Fig. 202, has such a structure that the structure of the semiconductor memory cell according to the twenty-seventh aspect of the present

-114-

invention is combined with the structure of the semiconductor memory cell according to the twenty-eighth aspect of the present invention. That is, the semiconductor memory cell according to the twenty-ninth aspect of the present invention has a structure that a sixth region is further formed, a second junction-field-effect transistor having a first conductivity type is added and a third transistor for current control, having a second conductivity type, is added into the structure of the semiconductor memory cell according to the twenty-sixth aspect of the present invention.

That is, according to the twenty-ninth aspect of the present invention, there is provided a semiconductor memory cell having a semiconductor layer having two main surfaces opposed to each other, the main surfaces being a first main surface and a second main surface,

the semiconductor memory cell comprising;

(1) a first transistor for readout, having a first conductivity type, and having source/drain regions, a semi-conductive channel forming region which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively coupled with the channel forming region,

(2) a second transistor for switching, having a second conductivity type, and having source/drain regions, a semi-conductive channel forming region which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively coupled with the channel forming region,

(3) a third transistor for current control, having the second conductivity type, and having source/drain regions, a semi-conductive channel forming region which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate capacitively coupled with the channel forming region,

(4) a first junction-field-effect transistor for

-115-

current control, having source/drain regions, a channel region and gate regions,

(5) a second junction-field-effect transistor for current control, having source/drain regions, a channel
5 region and gate regions, and

(6) an MIS type diode for retaining information,
the semiconductor memory cell further
having;

(a) a semi-conductive first region which is formed
10 in the semiconductor layer to extend over from the first main surface to the second main surface and has a first conductivity type,

(b) a semi-conductive second region which is formed in the semiconductor layer to extend over from
15 the first main surface to the second main surface, is in contact with the first region and has a second conductivity type,

(c) a third region which is formed in a surface region including the second main surface of the first
20 region to be spaced from the second region and is in contact with the first region so as to form a rectifier junction together with the first region,

(d) a fourth region which is formed in a surface region including the first main surface of the second
25 region to be spaced from the first region and is in contact with the second region so as to form a rectifier junction together with the second region,

(e) a fifth region which is formed in a surface region including the first main surface of the first
30 region to be spaced from the second region and is in contact with the first region so as to form a rectifier junction together with the first region,

(f) a sixth region which is formed in a surface region of the fourth region and is in contact with the
35 fourth region so as to form a rectifier junction together with the fourth region,

(g) the gate formed on a first insulation layer

-116-

formed on the first main surface so as to bridge the first region and the fourth region and so as to bridge the second region and the fifth region, and is shared by the first transistor and the third transistor, and

- 5 (h) the gate of the second transistor formed on a second insulation layer formed on the second main surface so as to bridge the second region and the third region,

wherein:

- 10 (A-1) one source/drain region of the first transistor is formed of a surface region including the first main surface of the first region,

(A-2) the other source/drain region of the first transistor is formed of the fourth region,

- 15 (A-3) the channel forming region of the first transistor is formed of a surface region including the first main surface of the second region which surface region is interposed between the surface region including the first main surface of the first region and
20 the fourth region,

(B-1) one source/drain region of the second transistor is formed of a surface region including the second main surface of the second region,

- (B-2) the other source/drain region of the second
25 transistor is formed of the third region,

- (B-3) the channel forming region of the second transistor is formed of a surface region including the second main surface of the first region which surface region is interposed between the surface region
30 including the second main surface of the second region and the third region,

(C-1) one source/drain region of the third transistor constitutes the channel forming region of the first transistor,

- 35 (C-2) the other source/drain region of the third transistor is formed of the sixth region,

(C-3) the channel forming region of the third

-117-

transistor constitutes the other source/drain region of the first transistor,

(D-1) the gate regions of the first junction-field-effect transistor are formed of the fifth region
5 and the third region which is opposed to the fifth region,

(D-2) the channel region of the first junction-field-effect transistor is formed of part of the first region which part is interposed between the fifth region
10 and the third region,

(D-3) one source/drain region of the first junction-field-effect transistor is formed of a portion of the first region which portion extends from one end of the channel region of the first junction-field-effect
15 transistor and constitutes one source/drain region of the first transistor and the channel forming region of the second transistor,

(D-4) the other source/drain region of the first junction-field-effect transistor is formed of a portion
20 of the first region which portion extends from the other end of the channel region of the first junction-field-effect transistor,

(E-1) the gate regions of the second junction-field-effect transistor are formed of the sixth region
25 and part of the second region which part is opposed to the sixth region,

(E-2) the channel region of the second junction-field-effect transistor is formed of part of the fourth region which part is interposed between the sixth region
30 and said part of the second region,

(E-3) one source/drain region of the second junction-field-effect transistor is formed of a portion of the fourth region which portion extends from one end of the channel region of the second junction-field-effect transistor and constitutes the other source/drain
35 region of the first transistor,

(E-4) the other source/drain region of the second

-118-

junction-field-effect transistor is formed of a portion of the fourth region which portion extends from the other end of the channel region of the second junction-field-effect transistor,

5 (F-1) one end of the MIS type diode is formed of part of the second region,

(F-2) an electrode constituting the other end of the MIS type diode is formed to be opposed to said part of the second region constituting one end of the MIS
10 type diode, through a wide gap thin film,

(G) the gate shared by of the first transistor and the third transistor and the gate of the second transistor are connected to a first line for memory cell selection,

15 (H) the third region is connected to a write-in information setting line,

(I) said portion of the fourth region constituting the other source/drain region of the second junction-field-effect transistor is connected to a second line,

20 (J) the electrode constituting the other end of the MIS type diode is connected to a third line having a predetermined potential, and

(K) the fifth region is connected to a fourth line.

There may be employed a constitution in
25 which the first region is connected to a fifth line, the second line is used as a bit line and a second predetermined potential is applied to the fifth line. Otherwise, there may be also employed another constitution in which the first region is connected to a
30 fifth line, a second predetermined potential is applied to the second line and the fifth line is used as a bit line.

There may be employed a constitution in which, as a drawing of its principle is shown in Fig.
35 205, the fifth region is connected to the third region in place of being connected to the fourth line. In this case, there may be employed a constitution in which the

-119-

first region is connected to a fifth line, the second line is used as a bit line and a second predetermined potential is applied to the fifth line, or a constitution in which the first region is connected to a fifth line, a second predetermined potential is applied to the second line and the fifth line is used as a bit line.

In the semiconductor memory cell according to the twenty-ninth aspect of the present invention, the structure in which the third region is connected to the write-in information setting line includes a structure in which the third region has a common region with part of the write-in information setting line. Further, the structure in which the fifth region is connected to the fourth line includes a structure in which the fifth region has common regions with part of the fourth line. Further, the structure in which the fifth region is connected to the write-in information setting line includes a structure in which the fifth region has a common region with part of the write-in information setting line.

In the semiconductor memory cell according to the twenty-fifth aspect of the present invention, each of the third region, fourth region and the fifth region may be composed of a silicide, a metal or a metal compound, while each of these regions is preferably composed of semiconductor. In the semiconductor memory cell according to the twenty sixth or twenty-eighth aspect of the present invention, the fourth region is preferably composed of semiconductor, and, while the third region or the fifth region may be composed of a silicide, a metal or a metal compound, each of these regions is preferably composed of semiconductor. In the semiconductor memory cell according to the twenty seventh or twenty-ninth aspect of the present invention, the fourth region is preferably composed of semiconductor, and, while each of the third region, the

-120-

fifth region and the sixth region may be composed of a silicide, a metal or a metal compound, each of these regions is preferably composed of semiconductor. When these regions are to be composed of a silicide, a metal or a metal compound, and when there is to be employed a constitution in which these regions are connected to the lines, these regions may be composed of the same material as the material of the lines (for example, a material such as titanium silicide or TiN for use as a barrier layer or a glue layer). That is, these regions and part of the lines may be formed as a structurally common region.

In the semiconductor memory cell of the present invention, that the potential in the channel forming region of the first transistor is held "nearly" at the first potential means that there is a case when the potential in the channel forming region of the first transistor is not held at a potential equal to the first potential in the strict sense. That is, in some case, holes or electrons are stored in the channel forming region of the first transistor or the other source/drain region of the third transistor so that the absolute value of the potential held in the channel forming region of the first transistor is higher than the absolute value of the first potential by 0.1 to 0.2 volt. The absolute value of the second potential is smaller than the absolute value of the above predetermined potential by a potential drop in the MIS type diode (including a potential drop in the high-resistance element when the high-resistance element is connected).

The wide gap thin film is composed of a material having energy barrier against the valence band upper end and conduction band lower end of the semiconductive region constituting the extending portion of the first transistor or the other source/drain region of the third transistor which constitutes the MIS type diode. That is, the wide gap thin film is composed of a

-121-

material having a wide gap as compared with the energy gap of the above semi-conductive region. The wide gap thin film is not necessarily required to be an insulating thin film so long as the above requirement is satisfied. When the above semi-conductive region is formed of silicon (Si), the wide gap thin film can be composed of a semi-conductive material having an energy gap of at least 2.2 eV. That is, the material constituting the wide gap thin film may be a material having an energy gap approximately twice or more the energy gap of the semi-conductive region (Si in the above case) constituting the extending portion of the channel forming region of the first transistor or the other source/drain region of the third transistor. The wide gap thin film may have a multi-layered structure or may have a composition which varies in the thickness direction. The wide gap thin film includes an SiO₂ or SiON film having a thickness of 5 nm or less and an SiN film having a thickness of 9 nm or less.

The junction-field-effect transistor (JFET), the first junction-field-effect transistor or the second junction-field-effect transistor in the semiconductor memory cell of the present invention can be formed by

(X) optimizing the distance between the facing gate regions of the junction-field-effect transistor, that is, the thickness of the channel region, and

(Y) optimizing impurity concentrations of the facing gate regions and the channel region of the junction-field-effect transistor.

It should be noted that if neither the distance between the gate regions (the thickness of the channel region), nor the impurity concentrations of the gate regions and the channel region are optimized, the depletion layer will not be widened, making it impossible to bring the junction-field-effect transistor into an on-state or an off-state. These optimizations need to be carried out by computer simulation or

-122-

experiments.

The semiconductor memory cell according to any one of the first to third aspects and the fifth to twenty-fourth aspects of the present invention can be
5 formed in a surface region of a semiconductor substrate, formed on an insulating interlayer on a semiconductor substrate, formed in a well formed in a semiconductor substrate, or formed on an electric insulator or an insulating interlayer, and is preferably formed in a
10 well, or formed on an insulator or an insulating interlayer, or has an SOI structure or a TFT structure, for preventing alpha-particle or neutron induced soft error. The insulator or insulating interlayer is formed not only on a semiconductor substrate but also on a
15 glass or quartz substrate. The semiconductor memory cell according to any one of the first aspect (depending upon the structure), the fourth aspect and the twenty fifth to twenty-ninth aspects of the present invention should have a SOI structure.

20 The channel forming region or the channel region can be formed from a material such as silicon, silicon-germanium (Si-Ge) or GaAs by using a known process. Each gate of the first transistor, the second transistor and the third transistor can be formed of a
25 material such as a metal; GaAs doped with an impurity at a high concentration; silicon, amorphous silicon, polysilicon doped with an impurity; a silicide; or a polyside, by using a known process. An insulating interlayer to cover the first transistor, the second
30 transistor and the third transistor can be formed of a material such as SiO_2 , Si_3N_4 , Al_2O_3 or GaAlAs by using a known process. Each region can be formed of silicon, amorphous silicon or polysilicon doped with an impurity, a silicide, a two-layer structure having a silicide
35 layer and a semi-conductive layer, silicon-germanium (Si-Ge) or GaAs doped with an impurity at a high concentration by using a known process, depending upon

-123-

characteristics required. The semi-conductive layer can be formed of a material such as silicon, silicon-germanium or GaAs.

In the semiconductor memory cell of the present invention, each gate of the first transistor and the second transistor is connected to the first line for memory cell selection (for example, word line). It is therefore sufficient to provide one first line for memory cell selection, so that the chip area can be decreased. When the first transistor for readout and the second transistor for switching are merged into one unit, the semiconductor memory cell of the present invention is also beneficial in terms of reduction in the cell area and leakage current.

The semiconductor memory cell, according to any one of the fourth aspect and the twenty fifth to twenty-ninth aspects of the present invention, is also beneficial in terms of reduction in the cell area, since the gate of the first transistor and the gate of the second transistor are faced to each other through the semiconductor layer.

In the semiconductor memory cell of the present invention, one source/drain region of the second transistor (the first or second region) corresponds to the channel forming region of the first transistor. Further, the other source/drain region of the second transistor (the third region) is connected to the write-in information setting line. And, when the on- and off-states of the first transistor and the second transistor can be controlled by properly selecting a potential in the first line for memory cell selection (for example, word line). That is, when the potential in the first line for memory cell selection is set at a potential as high enough to bring the second transistor into an on-state at a write-in time, the second transistor is brought into an on-state, and whereby an electric charge is charged or accumulated in a capacitor formed between

-124-

the first region and the second region in the second transistor depending upon the potential in the write-in information setting line. As a result, the information is stored in the channel forming region (the first or
5 second region) of the first transistor as a potential difference between the first region and the second region or as an electric charge. When the information is read out, the potential or the electric charge (the information) stored or accumulated in the channel
10 forming region of the first transistor is converted to a potential difference between the channel forming region (the first or second region) and the other source/drain region (the fourth region) in the first transistor, or is converted to an electric charge, and, the threshold
15 voltage of the first transistor seen from the gate of the first transistor varies depending upon the electric charge (information). When the information is read out, therefore, the on/off operation of the first transistor can be controlled by applying a properly selected
20 potential to the gate of the first transistor. That is, the information can be read out by detecting the operation state of the first transistor.

Further, the semiconductor memory cell of the present invention has the MIS type diode. The MIS
25 type diode will be explained with reference to a case where one end of the MIS type diode is formed of an extending portion of the channel forming region of the first transistor. When a proper bias is applied between two ends of the MIS type diode, which proper bias is to
30 cause a potential difference between the potential in the electrode constituting the other end of the MIS type diode and the potential of the band end in the surface of the extending portion (semi-conductive region) of the channel forming region of the first transistor
35 constituting one end of the MIS type diode to be equal to, or higher than, the band gap of a material forming the above semi-conductive region, carrier multiplication

-125-

takes place due to carriers which are tunnel-transited from the electrode and implanted in the surface of the extending portion of the channel forming region of the first transistor, thereby to cause a high-current state.

5 For details, see, for example, Y. Hayashi, "Switching phenomena in thin-insulator metal-insulator-semiconductor diodes", Appl. Phys. Lett. 37(4), 15 August 1980. In other words, high-energy carriers are implanted from the other end to one end of the MIS type

10 diode depending upon the potential or charge (information) of the channel forming region (first region or second region) of the first transistor, and carrier multiplication takes place. And, the channel forming region is supplied with carriers having the same

15 conductivity type (polarity) as that of the channel forming region on the basis of the above carrier multiplication, and as a result, the first potential which is an information potential stored in the channel forming region (first region or second region) of the

20 first transistor remains as a potential close to the first potential which is the original information potential in the channel forming region (first region or second region) of the first transistor, without approaching to the predetermined potential. When the

25 information potential (second potential) in the extending portion of the channel forming region of the first transistor has a level close to the level of the potential in the electrode of the MIS type diode, majority carriers in the extending portion of the

30 channel forming region of the first transistor are transited to the electrode on the basis of the tunnel transition, the potential in the extending portion of the channel forming region of the first transistor approaches to the potential in the electrode and is held

35 at the second potential. Therefore, the semiconductor memory cell of the present invention does not require so-called refreshing operation unlike the case of a DRAM.

-126-

Moreover, the memory cell according to any one of the fifth to twenty-ninth aspects of the present invention is provided with the junction-field-effect transistor in addition to the first transistor having the first conductivity type and the second transistor having the second conductivity type. Since the on/off operation of the junction-field-effect transistor is controlled when the information is read out, a large margin can be assured for the current which flows in the source/drain regions of the first transistor. As a result, the number of semiconductor memory cells that can be connected to, for example, the second line is hardly limited. Further, when the third transistor for current control is provided, the on/off operations of the third transistor is controlled when the information is read out. As a result, a remarkably large margin can be consistently assured for the current which flows in the source/drain regions of the first transistor. Therefore, the number of semiconductor memory cells connectable to, for example, the second line becomes further less liable to be limited.

Further, when the diode is provided, it is not required to form a line to be connected to one source/drain region of the first transistor. When the third region is composed of semiconductor having a conductivity type opposite to that of the second or first region, the diode is a pn junction diode. Such a pn junction diode can be formed by properly setting impurity concentrations in the regions constituting the pn junction diode. If a potential to be applied to the regions constituting the pn junction diode or the design of the impurity concentrations of the regions constituting the pn junction diode is not proper, there is possibility that carriers implanted from the diode may latch up the semiconductor memory cell. That is, if a voltage applied to the write-in information setting line is not a low degree of voltage (0.4 volt or lower

-127-

in a case of a pn junction) at which no large forward current flows in the junction portion of the third region and the first or second region at a write-in time, there is possibility that latch-up takes place. The
5 above problem can be overcome, for example, by a method described above in which the diode-constituting region is formed in a surface region of the first or second region, a material such as a silicide, a metal or a metal compound is used to constitute the diode-
10 constituting region, and the junction between the diode-constituting region and the first or second region is formed as a junction in which majority carrier mainly constitutes a forward current like in a Schottky junction. That is, the diode-constituting region is
15 composed of a silicide layer, a metal layer formed of Mo, Al or the like, or a metal compound layer, and thus, a majority carrier-diode such as a Schottky junction type which is conducted with majority carrier is formed. The diode-constituting region may be composed of a material
20 in common with that constituting the write-in information setting line, such as titanium silicide or TiN used as a barrier layer or a glue layer. That is, the semiconductor memory cell preferably has a configuration in which the diode-constituting region is
25 formed in the surface region of the first or second region and has a common region with part of the write-in information setting line, that is, the diode-constituting region and part of the write-in information setting line are fabricated in common. The
30 configuration in which the diode-constituting region has a common region with part of the write-in information setting line includes a configuration in which the diode-constituting region is composed of a compound formed by reacting a material for a wiring with silicon
35 (Si) in a silicon semiconductor substrate. Otherwise, the material constituting the diode-constituting region can be composed of a materials which make an ISO-type

-128-

hetero-junction. The term of "ISO-type hetero-junction" means a hetero-junction which is formed between two dissimilar semiconductors having the same conductivity type (see S.M. Sze, "Physics of Semiconductor Devices", 2nd edition, pp. 122, John Wiley & Sons). The ISO-type hetero-junction is formed when the diode-constituting region is composed of semiconductor which is different in the material from the first or second region but has the same conductivity as that of the first or second region.

BRIEF DESCRIPTION OF THE DRAWINGS

Fig. 1 shows the principle of a semiconductor memory cell according to the second aspect of the present invention.

Fig. 2 shows the principle of a variant of the semiconductor memory cell according to the second aspect of the present invention.

Fig. 3 shows the principle of the semiconductor memory cell according to another variant of the second aspect of the present invention.

Fig. 4 shows the principle of a semiconductor memory cell according to the third aspect of the present invention.

Fig. 5 shows the principle of a variant of the semiconductor memory cell according to the third aspect of the present invention.

Fig. 6 shows the principle of another variant of the semiconductor memory cell according to the third aspect of the present invention.

Fig. 7A shows a schematic partial cross-sectional view of a semiconductor memory cell of Example 1 and Fig. 7B shows a schematic layout of regions of the semiconductor memory cell of Example 1.

Fig. 8A shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 1, and Fig. 8B shows a schematic layout

-129-

of regions thereof.

Figs. 9A and 9B show schematic partial cross-sectional views of variants of the semiconductor memory cell of Example 1.

5 Fig. 10 shows a schematic partial cross-sectional view of another variant of the semiconductor memory cell of Example 1.

Fig. 11A show a schematic partial cross-sectional view of another variant of the semiconductor memory cell of Example 1, and Fig. 11B shows a schematic layout of regions thereof.

Fig. 12A shows a schematic partial cross-sectional view of another variant of the semiconductor memory cell of Example 1, and Fig. 12B shows a schematic layout of regions thereof.

Fig. 13A shows a schematic partial cross-sectional view of another variant of the semiconductor memory cell of Example 1, and Fig. 13B shows a schematic layout of regions thereof.

20 Fig. 14 shows another schematic partial cross-sectional view of the variant of the semiconductor memory cell of Example 1, shown in Figs. 13A and 13B.

Fig. 15 shows a schematic partial cross-sectional view of another variant of the semiconductor memory cell according to the first aspect of the present invention.

Fig. 16 shows a schematic partial cross-sectional view of another variant of the semiconductor memory cell according to the first aspect of the present invention.

Figs. 17A and 17B show schematic partial cross-sectional views of a semiconductor substrate, etc., for explaining the method of manufacturing the semiconductor memory cell of Example 1.

35 Figs. 18A and 18B, following Fig. 17B, show schematic partial cross-sectional views of a semiconductor substrate, etc., for explaining the method

-130-

of manufacturing the semiconductor memory cell of Example 1.

Figs. 19A and 19B, following Fig. 18B, show schematic partial cross-sectional views of a semiconductor substrate, etc., for explaining the method of manufacturing the semiconductor memory cell of Example 1.

Fig. 20A shows a schematic partial cross-sectional view of a semiconductor memory cell of Example 2, and Fig. 20B shows a schematic layout of regions thereof and another schematic partial cross-sectional view of the regions thereof taken along some plane perpendicular to the cross section shown in Fig. 20A.

Fig. 21 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 2.

Fig. 22A shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 2, and Fig. 22B shows a schematic layout of regions of thereof and another schematic partial cross-sectional view of the regions thereof taken along some plane perpendicular to the cross section shown in Fig. 22A.

Fig. 23 shows a schematic partial cross-sectional view of another variant of the semiconductor memory cell of Example 2.

Figs. 24A and 24B show schematic partial cross-sectional views of variants of the semiconductor memory cell of Example 2.

Figs. 25A and 25B show schematic partial cross-sectional views of variants of the semiconductor memory cell of Example 2.

Figs. 26A and 26B show schematic partial cross-sectional views of variants of the semiconductor memory cell of Example 2.

Fig. 27 shows a schematic partial cross-sectional view of another variant of the semiconductor

-131-

memory cell of Example 2.

Fig. 28 shows a schematic partial cross-sectional view of another variant of the semiconductor memory cell of Example 2.

5 Fig. 29 shows a schematic partial cross-sectional view of another variant of the semiconductor memory cell of Example 2.

Fig. 30 shows a schematic partial cross-sectional view of another variant of the semiconductor
10 memory cell of Example 2.

Figs. 31A and 31B show schematic partial cross-sectional views of the semiconductor memory cells of Example 3.

Figs. 32A and 32B show schematic partial
15 cross-sectional views of variants of the semiconductor memory cell of Example 3.

Figs. 33A and 33B show schematic partial cross-sectional views of a semiconductor substrate, etc., for explaining the method of manufacturing the
20 semiconductor memory cell of Example 3.

Figs. 34A and 34B, following Fig. 33B, show schematic partial cross-sectional views of a semiconductor substrate, etc., for explaining the method of manufacturing the semiconductor memory cell of
25 Example 3.

Figs. 35A and 35B, following Fig. 34B, show schematic partial cross-sectional views of a semiconductor substrate, etc., for explaining the method of manufacturing the semiconductor memory cell of
30 Example 3.

Figs. 36A and 36B, following Fig. 35B, show schematic partial cross-sectional views of a semiconductor substrate, etc., for explaining the method of manufacturing the semiconductor memory cell of
35 Example 3.

Fig. 37, following Fig. 36B, shows a schematic partial cross-sectional view of a

-132-

semiconductor substrate, etc., for explaining the method of manufacturing the semiconductor memory cell of Example 3.

5 Figs. 38A and 38B show schematic partial cross-sectional views of the semiconductor memory cells of Example 4.

Figs. 39A and 39B show schematic partial cross-sectional views of variants of the semiconductor memory cell of Example 4.

10 Fig. 40 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 4.

Figs. 41A and 41B show schematic partial cross-sectional views of variants of the semiconductor memory cell of Example 4.

Figs. 42A and 42B show schematic partial cross-sectional views of variants of the semiconductor memory cell of Example 4.

20 Figs. 43A and 43B show schematic views of embodiments in which the semiconductor memory cells of Example 4 are applied to a side gate type semiconductor memory cell.

Fig. 44 shows the principle of a semiconductor memory cell according to the fifth aspect of the present invention.

Figs. 45A and 45B show the principles of variants of the semiconductor memory cell according to the fifth aspect of the present invention.

30 Fig. 46 shows the principle of a variant of the semiconductor memory cell according to the fifth aspect of the present invention.

Figs. 47A and 47B show the principles of variants of the semiconductor memory cell according to the fifth aspect of the present invention.

35 Fig. 48 shows the principle of a variant of the semiconductor memory cell according to the fifth aspect of the present invention.

-133-

Fig. 49 shows the principle of a variant of the semiconductor memory cell according to the fifth aspect of the present invention.

5 Figs. 50A and 50B show the principles of variants of the semiconductor memory cell according to the fifth aspect of the present invention.

Fig. 51 shows a schematic partial cross-sectional view of the semiconductor memory cell of Example 5.

10 Fig. 52 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 5.

Fig. 53 shows a schematic partial cross-sectional view of a variant of the semiconductor memory
15 cell of Example 5.

Fig. 54 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 5.

20 Fig. 55 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 5.

Fig. 56 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 5.

25 Fig. 57 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 5.

Fig. 58 shows a schematic partial cross-sectional view of a variant of the semiconductor memory
30 cell of Example 5.

Fig. 59 shows another schematic partial cross-sectional view of the variant shown in Fig. 58, prepared by cutting the variant with a different plane.

35 Fig. 60 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 5.

Fig. 61 shows the principle of a variant of

-134-

the semiconductor memory cell according to the fifth aspect of the present invention.

Figs. 62A and 52B show the principles of variants of the semiconductor memory cell according to the fifth aspect of the present invention.

Fig. 63 shows a schematic partial cross-sectional view of a semiconductor memory cell of Example 6.

Fig. 64 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 6.

Fig. 65 shows the principle of a variant of the semiconductor memory cell according to the fifth aspect of the present invention.

Figs. 66A and 66B show the principle of variants of the semiconductor memory cell according to the fifth aspect of the present invention.

Fig. 67 shows the principle of a variant of the semiconductor memory cell according to the fifth aspect of the present invention.

Figs. 68A and 68B show the principle of variants of the semiconductor memory cell according to the fifth aspect of the present invention.

Fig. 69A shows a schematic partial cross-sectional view of a semiconductor memory cell of Example 7, and Fig. 69B shows a schematic plan view of layout of regions thereof.

Fig. 70 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 7.

Fig. 71 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 7.

Fig. 72A shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 7, and Fig. 72B shows a schematic plan view of layout of regions thereof.

-135-

Figs. 73A and 73B show schematic partial cross-sectional views of variants of the semiconductor memory cell of Example 7.

5 Fig. 74 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 7.

10 Fig. 75A shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 7, and Fig. 75B shows a schematic plan view of layout of regions thereof.

Fig. 76 shows another schematic partial cross-sectional view of the variant shown in Figs. 75A and 75B, prepared by cutting the variant with a different plane.

15 Fig. 77A shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 7, Fig. 77B shows a schematic plan view of layout of regions thereof, and Fig. 77C shows another schematic partial cross-sectional view of the regions
20 thereof taken along some plane perpendicular to the cross section shown in Fig. 77A.

Fig. 78 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 7.

25 Fig. 79 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 7.

30 Fig. 80 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 7.

Fig. 81 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 7.

35 Fig. 82 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 7.

Figs. 83A and 83B show schematic partial

-136-

cross-sectional views of variants of the semiconductor memory cell of Example 7.

Figs. 84A and 84B show schematic partial cross-sectional views of variants of the semiconductor memory cell of Example 7.

Figs. 85A and 85B show schematic partial cross-sectional views of variants of the semiconductor memory cell of Example 7.

Fig. 86 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 7.

Fig. 87 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 7.

Fig. 88 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 7.

Fig. 89 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 7.

Fig. 90 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 7.

Fig. 91 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 7.

Fig. 92 shows the principle of the semiconductor memory cell according to the sixth aspect of the present invention.

Figs. 93A and 93B show the principles of variants of the semiconductor memory cell according to the sixth aspect of the present invention.

Fig. 94 shows the principle of a variant of the semiconductor memory cell according to the sixth aspect of the present invention.

Figs. 95A and 95B show the principles of variants of the semiconductor memory cell according to

-137-

the sixth aspect of the present invention.

Fig. 96 shows the principle of a variant of the semiconductor memory cell according to the sixth aspect of the present invention.

5 Figs. 97A and 97B show the principles of variants of the semiconductor memory cell according to the sixth aspect of the present invention.

Fig. 98 shows a schematic partial cross-sectional view of a semiconductor memory cell of Example
10 8.

Fig. 99 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 8.

Fig. 100 shows a schematic partial cross-sectional view of a variant of the semiconductor memory
15 cell of Example 8.

Fig. 101 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 8.

20 Fig. 102 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 8.

Fig. 103 shows a schematic partial cross-sectional view of a variant of the semiconductor memory
25 cell of Example 8.

Fig. 104 shows the principle of a variant of the semiconductor memory cell according to the sixth aspect of the present invention.

30 Figs. 105A and 105B show the principles of variants of the semiconductor memory cell according to the sixth aspect of the present invention.

Fig. 106 shows a schematic partial cross-sectional view of a semiconductor memory cell of Example
9.

35 Fig. 107 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 9.

-138-

Fig. 108 shows the principle of a variant of the semiconductor memory cell according to the sixth aspect of the present invention.

5 Figs. 109A and 109B show the principles of variants of the semiconductor memory cell according to the sixth aspect of the present invention.

Fig. 110 shows the principle of a variant of the semiconductor memory cell according to the sixth aspect of the present invention.

10 Figs. 111A and 111B show the principles of variants of the semiconductor memory cell according to the sixth aspect of the present invention.

Fig. 112 shows the principle of a variant of the semiconductor memory cell according to the sixth aspect of the present invention.

Figs. 113A and 113B show the principles of variants of the semiconductor memory cell according to the sixth aspect of the present invention.

20 Fig. 114 shows a schematic partial cross-sectional view of a semiconductor memory cell of Example 10.

Fig. 115 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 10.

25 Fig. 116 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 10.

Fig. 117 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 10.

Fig. 118 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 10.

35 Fig. 119 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 10.

Fig. 120 shows a schematic partial cross-

-139-

sectional view of a variant of the semiconductor memory cell of Example 10.

Fig. 121 shows a schematic partial cross-sectional view of a variant of the semiconductor memory
5 cell of Example 10.

Fig. 122 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 10.

Fig. 123 shows a schematic partial cross-sectional view of a variant of the semiconductor memory
10 cell of Example 10.

Fig. 124 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 10.

Fig. 125 shows a schematic partial cross-sectional view of a variant of the semiconductor memory
15 cell of Example 10.

Fig. 126 shows the principle of a variant of the semiconductor memory cell according to the sixth
20 aspect of the present invention.

Figs. 127A and 127B show the principles of variants of the semiconductor memory cell according to the sixth aspect of the present invention.

Fig. 128 shows a schematic partial cross-sectional view of a semiconductor memory cell of Example
25 11.

Fig. 129 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 11.

Fig. 130 shows a schematic partial cross-sectional view of a variant of the semiconductor memory
30 cell of Example 11.

Fig. 131 shows a schematic partial cross-sectional view of a variant of the semiconductor memory
35 cell of Example 11.

Fig. 132 shows the principle of the semiconductor memory cell according to the seventh

-140-

aspect of the present invention.

Figs. 133A and 133B show the principles of variants of the semiconductor memory cell according to the seventh aspect of the present invention.

5 Fig. 134 shows a schematic partial cross-sectional view of a semiconductor memory cell of Example 12.

10 Fig. 135 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 12.

Fig. 136 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 12.

15 Fig. 137 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 12.

Fig. 138 shows the principle of the semiconductor memory cell according to the eighth aspect of the present invention.

20 Figs. 139A and 139B show the principles of variants of the semiconductor memory cell according to the eighth aspect of the present invention.

25 Fig. 140 shows a schematic partial cross-sectional view of a semiconductor memory cell of Example 13.

Fig. 141 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 13.

30 Fig. 142 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 13.

Fig. 143 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 13.

35 Fig. 144 shows the principle of the semiconductor memory cell according to the ninth aspect of the present invention.

-141-

Figs. 145A and 145B show the principles of variants of the semiconductor memory cell according to the ninth aspect of the present invention.

Fig. 146 shows the principle of a variant of the semiconductor memory cell according to the ninth aspect of the present invention.

Figs. 147A and 147B show the principles of variants of the semiconductor memory cell according to the ninth aspect of the present invention.

Fig. 148 shows a schematic partial cross-sectional view of a semiconductor memory cell of Example 14.

Fig. 149 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 14.

Fig. 150 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 14.

Fig. 151 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 14.

Fig. 152 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 14.

Fig. 153 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 14.

Fig. 154 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 14.

Fig. 155 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 14.

Fig. 156 shows the principle of a variant of the semiconductor memory cell according to the ninth aspect of the present invention.

Figs. 157A and 157B show the principles of

-142-

variants of the semiconductor memory cell according to the ninth aspect of the present invention.

Fig. 158 shows a schematic partial cross-sectional view of a semiconductor memory cell of Example 5 15.

Fig. 159 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 15.

Fig. 160 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 15. 10

Fig. 161 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 15.

Fig. 162 shows the principle of the semiconductor memory cell according to the tenth aspect of the present invention. 15

Fig. 163 shows the principle of a variant of the semiconductor memory cell according to the tenth aspect of the present invention. 20

Fig. 164 shows the principle of a variant of the semiconductor memory cell according to the tenth aspect of the present invention.

Fig. 165 shows a schematic partial cross-sectional view of a semiconductor memory cell of Example 16. 25

Fig. 166 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 16.

Fig. 167 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 16. 30

Fig. 168 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 16. 35

Fig. 169 shows the principle of the semiconductor memory cell according to the eleventh

-143-

aspect of the present invention.

Fig. 170 shows the principle of a variant of the semiconductor memory cell according to the eleventh aspect of the present invention.

5 Fig. 171 shows the principle of a variant of the semiconductor memory cell according to the eleventh aspect of the present invention.

Fig. 172 shows a schematic partial cross-sectional view of a semiconductor memory cell of Example 10 17.

Fig. 173 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 17.

Fig. 174 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 17. 15

Fig. 175 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 17.

20 Figs. 176A and 176B show schematic partial cross-sectional views of a semiconductor substrate, etc., for explaining the method of manufacturing the semiconductor memory cell of Example 7 shown in Fig. 69.

Figs. 177A and 177B, following Fig. 176B, 25 show schematic partial cross-sectional views of a semiconductor substrate, etc., for explaining the method of manufacturing the semiconductor memory cell of Example 7 shown in Fig. 69.

Figs. 178A and 178B, following Fig. 177B, 30 show schematic partial cross-sectional views of a semiconductor substrate, etc., for explaining the method of manufacturing the semiconductor memory cell of Example 7 shown in Fig. 69.

Figs. 179A and 179B show the principles of 35 the semiconductor memory cells according to the twenty-fifth aspect of the present invention.

Figs. 180A and 180B show schematic partial

-144-

cross-sectional views of the semiconductor memory cells of Example 18.

Figs. 181A and 181B show schematic partial cross-sectional views of variants of the semiconductor memory cell of Example 18.

Figs. 182A and 182B show schematic partial cross-sectional views of variants of the semiconductor memory cell of Example 18.

Figs. 183A and 183B show schematic partial cross-sectional views of variants of the semiconductor memory cell of Example 18.

Figs. 184A and 184B show schematic partial cross-sectional views of variants of the semiconductor memory cell of Example 18.

Figs. 185A and 185B show schematic partial cross-sectional views of variants of the semiconductor memory cell of Example 18.

Figs. 186A and 186B show schematic partial cross-sectional views of the semiconductor memory cells of Example 19.

Figs. 187A and 187B show schematic partial cross-sectional views of variants of the semiconductor memory cell of Example 19.

Figs. 188A and 188B show schematic partial cross-sectional views of variants of the semiconductor memory cell of Example 19.

Fig. 189A shows a schematic layout of a gate and regions in the semiconductor memory cell of Example 19, and Fig. 189B shows a schematic layout of a gate and regions in a variant of the semiconductor memory cell of Example 19.

Figs. 190A and 190B show schematic partial cross-sectional views of variants of the semiconductor memory cell of Example 19.

Fig. 191 shows the principle of the semiconductor memory cell according to the twenty-seventh aspect of the present invention.

-145-

Figs. 192A and 192B show schematic partial cross-sectional views of the semiconductor memory cells of Example 20.

5 Figs. 193A and 193B show schematic partial cross-sectional views of variants of the semiconductor memory cell of Example 20.

Fig. 194 shows the principle of a variant of the semiconductor memory cell according to the twenty-seventh aspect of the present invention.

10 Figs. 195A and 195B show schematic partial cross-sectional views of variants of the semiconductor memory cell of Example 20.

Figs. 196A and 196B show schematic partial cross-sectional views of variants of the semiconductor memory cell of Example 20.

Figs. 197A and 197B show schematic partial cross-sectional views of variants of the semiconductor memory cell of Example 20.

20 Figs. 198A and 198B show schematic partial cross-sectional views of variants of the semiconductor memory cell of Example 20.

Fig. 199A shows a schematic partial cross-sectional view of a semiconductor memory cell of Example 21, and Fig. 199B shows a schematic layout of gates and regions thereof.

Fig. 200 shows a schematic partial cross-sectional view of a variant of the semiconductor memory cell of Example 21.

30 Figs. 201A and 201B show schematic partial cross-sectional views of variants of the semiconductor memory cell of Example 21.

Fig. 202 shows the principle of the semiconductor memory cell according to the twenty-ninth aspect of the present invention.

35 Figs. 203A and 203B show schematic partial cross-sectional views of the semiconductor memory cells of Example 22.

-146-

Figs. 204A and 204B show schematic partial cross-sectional views of variants of the semiconductor memory cell of Example 22.

Fig. 205 shows the principle of a variant of the semiconductor memory cell according to the twenty-ninth aspect of the present invention.

Figs. 206A and 206B show schematic partial cross-sectional views of variants of the semiconductor memory cell of Example 22.

Figs. 207A and 207B show schematic partial cross-sectional views of variants of the semiconductor memory cell of Example 22.

Figs. 208A and 208B show schematic partial cross-sectional views of variants of the semiconductor memory cell of Example 22.

Figs. 209A and 209B show schematic partial cross-sectional views of variants of the semiconductor memory cell of Example 22.

Fig. 210A shows the concept of a conventional single-transistor memory cell, and Fig. 210B shows a cross-sectional view of a conventional memory cell having a trench capacitor cell structure.

DESCRIPTION OF THE PREFERRED EMBODIMENTS

The present invention will be explained more specifically with reference to Examples hereinafter. Schematic partial cross-sectional views of semiconductor memory cells referred to in Examples are those which are prepared by cutting the semiconductor memory cells with a plane perpendicular to the extending direction of gates.

Example 1

Example 1 is concerned with the semiconductor memory cell according to the first and second aspects of the present invention. Fig. 1 shows the principle of a semiconductor memory cell of Example 1, Fig. 7A shows a schematic partial cross-sectional

-147-

view thereof, and Fig. 7B shows a schematic layout of regions thereof. In these and other Figures, "SCS" shows a semiconductor substrate, "n-SCS" shows an n-type semiconductor substrate, "p-SCS" shows a p-type semiconductor substrate, "SPS" shows a supporting substrate, "IL", "IL₁" and "IL₂" show insulating interlayers, "IL₀" shows an insulation material layer, and "IR₂" shows a device separation region.

The above semiconductor memory cell comprises;

- (1) a first transistor TR₁ for readout, having a first conductivity type (for example, n-channel type) and having source/drain regions, a semi-conductive channel forming region CH₁ which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate G₁ capacitively coupled with the channel forming region CH₁,
- (2) a second transistor TR₂ for switching, having a second conductivity type (for example, p-channel type) and having source/drain regions, a semi-conductive channel forming region CH₂ which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate G₂ capacitively coupled with the channel forming region CH₂, and
- (3) an MIS type diode DT for retaining information.

In Example 1, the first transistor TR₁ and the second transistor TR₂ constitute one merged transistor. That is, the area of the semiconductor memory cell of Example 1 is generally smaller than the area of two transistors.

And, the semiconductor memory cell of Example 1 has;

- (a) a semi-conductive first region SC₁ having a first conductivity type (for example, n-type),
- (b) a semi-conductive second region SC₂ which is in contact with the first region SC₁ and has a second conductivity type (for example, p⁺-type),

-148-

(c) a third region SC_3 which is formed in a surface region of the first region SC_1 to be spaced from the second region SC_2 and is in contact with the first region SC_1 so as to form a rectifier junction together with the first region SC_1 , the third region SC_3 being a region which is semi-conductive and has the second conductivity type (for example, p^{++} -type) or which is conductive and is composed of a silicide, a metal or a metal compound, and

10 (d) a fourth region SC_4 which is formed in a surface region of the second region SC_2 to be spaced from the first region SC_1 and is in contact with the second region SC_2 so as to form a rectifier junction together with the second region SC_2 , the fourth region
15 SC_4 being a region which is semi-conductive and has the first conductivity type (for example, n^{++} -type) or which is conductive and is composed of a silicide, a metal or a metal compound.

Concerning the first transistor TR_1 ,

20 (A-1) one source/drain region is formed of a surface region of the first region SC_1 which surface region is interposed between the second region SC_2 and the third region SC_3 ,

(A-2) the other source/drain region is formed of
25 the fourth region SC_4 ,

(A-3) the channel forming region CH_1 is formed of a surface region of the second region SC_2 which surface region is interposed between the surface region of the first region SC_1 and the fourth region SC_4 , and

30 (A-4) the gate G_1 is formed on the channel forming region CH_1 of the first transistor TR_1 through an insulation layer.

Concerning the second transistor TR_2 ,

(B-1) one source/drain region is formed of the
35 surface region of the second region SC_2 which surface region constitutes the channel forming region CH_1 of the first transistor TR_1 ,

-149-

(B-2) the other source/drain region is formed of the third region SC_3 ,

(B-3) the channel forming region CH_2 is formed of the surface region of the first region SC_1 which surface
5 region constitutes one source/drain region of the first transistor TR_1 , and

(B-4) the gate G_2 is formed on the channel forming region CH_2 of the second transistor TR_2 through an insulation layer.

10 Further, the gate G_1 of the first transistor TR_1 and the gate G_2 of the second transistor TR_2 are formed on the insulation layer so as to bridge the first region SC_1 and the fourth region SC_4 and so as to bridge the second region SC_2 and the third region SC_3 . The
15 above gate G_1 gate G_2 are shared by the first transistor TR_1 and the second transistor TR_2 , and the shared gate is referred to as "gate G".

Concerning the MIS type diode DT,

(C-1) one end thereof is formed of part SC_{2A} of the
20 second region SC_2 which part is an extending portion of the channel forming region CH_1 of the first transistor TR_1 , and

(C-2) an electrode constituting the other end thereof is formed so as to be opposed to said part SC_{2A}
25 of the second region SC_2 constituting one end of the MIS type diode DT through a wide gap thin film WG, and is composed of a conductive material.

The wide gap thin film WG can be composed of a material in which the tunnel transition of carriers is
30 caused depending upon a potential difference between the potential in the channel forming region CH_1 of the first transistor TR_1 and the potential in the other end (electrode EL) of the MIS type diode DT. Specifically, it can be composed, for example, of an SiO_2 or SiON film
35 having a thickness of 5 nm or smaller, or an SiN film having a thickness of 9 nm or smaller. In Examples to be described later, the wide gap thin films WG can be

-150-

constituted as described above.

The electrode EL constituting the other end of the MIS type diode is connected to a third line through a high-resistance element R having a resistance of approximately 10^9 to $10^{12} \Omega$. Specifically, the electrode EL constituting the other end of the MIS type diode DT and the high-resistance element are integrally formed and are composed of a polysilicon thin layer containing an impurity having the first conductivity type. In Examples to be described later, the electrodes EL and the high-resistance elements R can be constituted as described above.

In the semiconductor memory cell of Example 1, further, the gate G_1 of the first transistor TR_1 and the gate G_2 of the second transistor TR_2 are connected to a first line (word line) for memory cell selection. Further, the third region SC_3 is connected to a write-in information setting line WISL, the fourth region SC_4 is connected to a second line (for example, bit line for memory cell selection), the electrode EL constituting the other end of the MIS type diode DT is connected to the third line having a predetermined potential, and the first region SC_1 is connected to a fourth line having a predetermined second potential.

In another embodiment, the gate G_1 of the first transistor TR_1 and the gate G_2 of the second transistor TR_2 are connected to the first line (word line), the other source/drain region of the first transistor TR_1 is connected to the second line (for example, bit line), the other source/drain region of the second transistor TR_2 is connected to the write-in information setting line WISL, and the other end of the MIS type diode DT is connected to the line (third line) having a predetermined potential through the high-resistance element R.

In the semiconductor memory cell of Example 1, the second region SC_2 is formed in a surface region

-151-

of the first region SC_1 . Further, a second high-concentration-impurity-containing layer SC_{11} having the first conductivity type (for example, n^{++} -type) is formed below the first region SC_1 , and the second high-concentration-impurity-containing layer SC_{11} works as the fourth line. Furthermore, a first high-concentration-impurity-containing layer SC_{10} having the first conductivity type (for example, n^{++} -type) is formed below the second region SC_2 . The semiconductor memory cell is formed in a well structure having a first conductivity type (for example, n -type).

In the semiconductor memory cell of Example 1 shown in Figs. 7A and 7B, there may be employed a constitution in which a second predetermined potential is applied to the second line to which the fourth region SC_4 is connected, and the fourth line to which the first region SC_1 is used as a line (bit line) for memory cell selection.

In the semiconductor memory cell of Example 1, the third region SC_3 is formed of a semiconductor, and the impurity concentrations of the first region SC_1 and the third region SC_3 are properly controlled to constitute a pn junction diode D formed of the first region SC_1 and the third region SC_3 . In this case, as shown in the drawing of the principle of Fig. 2, there can be employed a constitution in which the fourth line is omitted and the first region SC_1 is connected to the write-in information setting line WISL through the third region SC_3 , so that the wiring structure can be simplified. The pn junction diode can be formed by bringing the impurity concentrations of the first region SC_1 and the third region SC_3 into proper values. This can be similarly applied in Examples to be described later. In the semiconductor memory cell of the above constitution, the gate G_1 of the first transistor TR_1 and the gate G_2 of the second transistor TR_2 are connected to the first line (word line), one

-152-

source/drain region of the first transistor TR_1 is connected to the write-in information setting line WISL through the pn junction diode D, the other source/drain region of the first transistor TR_1 is connected to the second line (which works, for example, as a bit line), the other source/drain region of the second transistor TR_2 is connected to the write-in information setting line WISL and the other end of the MIS type diode DT is connected to the line (third line) having a predetermined potential through the high-resistance element R.

Further, there may be employed a constitution in which a pn junction diode D is formed with the first region SC_1 and the third region SC_3 , a second predetermined potential is applied to the second line to which the fourth region SC_4 is connected, and the first region SC_1 is connected to the write-in information setting line WISL (which works as a bit line as well) through the third region SC_3 .

Fig. 3 shows the principle of a semiconductor memory cell which is a variant of the semiconductor memory cell of Example 1. Further, Fig. 8A shows a schematic partial cross-sectional view of the variant, and Fig. 8B shows a schematic layout of regions of the variant. In the semiconductor memory cell as the variant, a diode-constituting region SC_D is formed, for example, of titanium silicide or TiN and is provided in a surface region of the first region SC_1 . And, the first region SC_1 and the diode-constituting region SC_D constitute a majority carrier diode DS. In the above constitution, the fourth line can be omitted, and the first region SC_1 can be connected to the write-in information setting line WISL through the diode-constituting region SC_D , so that the structure of wiring can be simplified. In the semiconductor memory cell of the above constitution, the gate G_1 of the first transistor TR_1 and the gate G_2 of the second transistor

-153-

TR₂ are connected to the first line (word line), one source/drain region of the first transistor TR₁ is connected to the write-in information setting line WISL through the majority carrier diode DS, the other
5 source/drain region of the first transistor TR₁ is connected to the second line (bit line), the other source/drain region of the second transistor TR₂ is connected to the write-in information setting line WISL, and the other end of the MIS type diode DT is connected
10 to the line (third line) having a predetermined potential through the high-resistance element R. There may employed a constitution in which a second predetermined potential is applied to the second line and the write-in information setting line WISL is used
15 as a bit line as well.

Figs. 9 to 12 show other variants of the semiconductor memory cell of Example 1.

In the variants shown in Figs. 9A and 9B, a semiconductor memory cell structured as shown in Figs.
20 7A and 7B is formed in a semiconductor layer SC₀ surrounded by an insulation material layer IL₀ on a supporting substrate SPS. The semiconductor memory cell shown in Fig. 9A and the semiconductor memory cell shown in Fig. 9B differ from each other in degrees in which
25 third regions SC₃ extend downwardly. When the semiconductor memory cell structured as shown in Fig. 9B is employed, an electrode from a side portion of the third region SC₃ to the write-in information setting line WISL can be taken out. In any other points, the
30 semiconductor memory cells shown in Figs. 9A and 9B are substantially structurally the same as the semiconductor memory cell shown in Figs. 7A and 7B. In the variant shown in Fig. 10, a semiconductor memory cell structured as shown in Figs. 8A and 8B is formed in a semiconductor
35 layer SC₀ surrounded by an insulation material layer IL₀ on a supporting substrate SPS. In any other points, the semiconductor memory cell shown in Fig. 10 is

-154-

substantially structurally the same as the semiconductor memory cell shown in Figs. 8A and 8B.

The semiconductor memory cells shown in Figs. 9A, 9B and 10 can be manufactured by a so-called
5 substrate bonding method in which a convex portion is formed in a semiconductor substrate, an insulator (insulation material layer) is formed on the entire surface, then, the insulator (insulation material layer) and a supporting substrate are bonded to each other, and
10 the semiconductor substrate is ground and polished from its reverse surface side. Otherwise, an insulator (insulating interlayer) can be formed according to an SIMOX method in which, for example, a silicon semiconductor substrate is ion-implanted with oxygen and
15 then heat-treated, and a semiconductor memory cell is formed in a silicon layer remaining thereon. That is, these semiconductor memory cells have a so-called SOI structure. There may be employed another method in which, for example, an amorphous silicon layer or a
20 polysilicon layer is formed on an insulator (insulation material layer) by a CVD method, then, a silicon layer is formed from the amorphous or polysilicon layer by a known single crystallization method such as a zone melting crystallization method using laser beam or
25 electron beam or a lateral solid phase crystal growth method in which a crystal is grown through an opening formed in the insulator (insulation material layer), and the semiconductor memory cell is formed in the silicon layer. Otherwise, there may be employed still another
30 method in which, for example, a polysilicon layer or an amorphous silicon layer is formed on an insulator (insulation material layer) formed on a supporting substrate and the semiconductor memory cell is formed in the polysilicon layer or the amorphous silicon layer.
35 That is, these semiconductor memory cells have a so-called TFT structure. In Examples to be described later, SOI structures and TFT structures can be similarly

-155-

manufactured as described above.

A semiconductor memory cell shown in Figs. 11A and 11B is a variant of the semiconductor memory cell shown in Figs. 7A and 7B. A semiconductor memory cell shown in Figs. 12A and 12B is a variant of the semiconductor memory cell shown in Figs. 8A and 8B. In the semiconductor memory cells shown in Figs. 11A and 11B and Figs. 12A and 12B (for their principles, see Figs. 1 and 3, respectively), the first region SC_1 is formed in a surface region of the second region SC_2 . In any other points, the semiconductor memory cells shown in Figs. 11A and 11B and Figs. 12A and 12B are substantially structurally the same as the semiconductor memory cells shown in Figs. 7A and 7B and Figs. 8A and 8B.

In the variants of the semiconductor memory cell of Example 1, shown in Figs. 9A and 9B and Figs. 11A and 11B, there may be employed a constitution in which the second line to which the fourth region SC_4 is connected is used as a bit line for memory cell selection and a second predetermined potential is applied to the fourth line to which the first region SC_1 is connected, or a constitution in which a second predetermined potential is applied to the second line and the fourth line is used as a bit line for memory cell selection. In the variants of the semiconductor memory cell of Example 1, shown in Figs. 10 and Figs. 12A and 12B, there may be employed a constitution in which the second line to which the fourth region SC_4 is connected is used as a bit line for memory cell selection, or a constitution in which a second predetermined potential is applied to the second line and the write-in information setting line WISL is used as a bit line as well.

For example, the semiconductor memory cell of Example 1 shown in Figs. 7A and 7B may be structurally modified as shown in Figs. 13A, 13B and 14.

-156-

Fig. 13A shows a schematic partial cross-sectional view of a semiconductor memory cell, Fig. 13B is a schematic layout of regions thereof, and Fig. 14 shows a schematic partial cross-sectional view thereof taken along an
5 arrow in Fig. 13B. In the semiconductor memory cell, a portion of the second region SC_2 extends up to a surface of the semiconductor substrate beside the fourth region SC_4 . The extending portion SC_{2B} of the second region SC_2 corresponds to one end of the MIS type diode DT. An
10 electrode EL constituting the other end of the MIS type diode DT is formed on the extending portion SC_{2B} of the second region SC_2 through a wide gap thin film WG. Further, a high-resistance element R integrally extends from the electrode EL. The electrode EL and the high-
15 resistance element R are formed of a polysilicon thin film containing an impurity having the first conductivity type (for example, n-type). The second line (bit line) is formed on a second insulating interlayer IL_2 , and extends in the direction perpendicular to the
20 paper surface of Fig. 14. The structure of the second region SC_2 shown in Figs. 13A, 13B and 14 can be applied to the various variants explained in Example 1.

The semiconductor memory cell according to the first aspect of the present invention, explained
25 with reference to Figs. 7A and 7B and Figs. 8A and 8B, can be modified to semiconductor memory cells whose schematic partial cross-sectional views are shown in Figs. 15 and 16. In the semiconductor memory cells shown in Figs. 15 and 16, the gate G_1 of the first
30 transistor TR_1 and the gate G_2 of the second transistor TR_2 are separately formed. Except for the above point, the semiconductor memory cells shown in Figs. 15 and 16 are substantially structurally the same as those of the semiconductor memory cells shown Figs. 7A and 7B and
35 Figs. 8A and 8B.

The process for manufacturing the semiconductor memory cell of Example 1 shown in Figs. 7A

-157-

and 7B will be explained with reference to Figs. 17A, 17B, 18A, 18B, 19A and 19B hereinafter. The semiconductor memory cell of Example 2 to be described later can be also manufactured substantially by the same process.

[Step-100]

First, a device separation region (not shown), a well of the first conductivity type (for example, n-type well), the first region SC_1 of an n-type semiconductor, a second high-concentration-impurity-containing layer SC_{11} having the first conductivity type (for example, n^{++} -type) (not shown) and a gate insulation layer 12 corresponding to the insulation layer are formed in a p-type silicon semiconductor substrate 10 according to known methods. Then, the gate G ($G_1 + G_2$) is formed. For example, the gate G is composed of a polysilicon containing an impurity or polyside structure or a polymetal structure. In this manner, a structure shown in Fig. 17A can be obtained.

The n-type first region SC_1 had an impurity concentration of $1.0 \times 10^{17}/\text{cm}^3$, and the gate G ($G_1 + G_2$) had a length of $0.28 \mu\text{m}$.

[Step-110]

An ion-implanting mask 20 is formed from a resist material, then, ion-implantation with an impurity of the second conductivity type (for example, p-type) is carried out, and the semi-conductive third region SC_3 having the second conductivity type is formed in a surface region of the first region SC_1 (see Fig. 17B).

The ion-implantation is carried out under conditions shown in the following Table 1.

-158-

Table 1

Ion species	BF ₂
Acceleration energy	20 keV
Dosage	1 x 10 ¹³ /cm ²
Ion incidence angle	7 degrees

[Step-120]

5 Then, the ion-implanting mask 20 is removed,
an ion-implanting mask 21 is formed from a resist
material, and then, ion-implantation with an impurity
having the second conductivity type (for example, p-
type) is carried out by an oblique ion-implanting method,
10 to form the semi-conductive second region SC₂ having the
second conductivity type (for example, p⁺-type) which is
in contact with the first region SC₁ (specifically,
which is formed in a surface region of the first region
SC₁) and which is spaced from the third region SC₃. When
15 the ion-implantation is carried out by an oblique ion-
implanting method, the second region SC₂ is formed to
reach below the gate G (G₁ + G₂) (see Fig. 18A). The
ion-implantation was carried out twice under conditions
shown in the following Table 2, and the ion incidence
20 angle during one ion-implantation differed from that
during the other ion-implantation. Particularly, when
the ion incidence angle during the first ion-
implantation is set at 60 degrees, the impurity
concentration of the semi-conductive second region SC₂
25 below the gate G (G₁ + G₂) can be highly accurately
controlled.

-159-

Table 2

First ion-implantation

Ion species	Boron
Acceleration energy	10 keV
Dosage	$3.4 \times 10^{13}/\text{cm}^2$
Ion incidence angle	60 degrees

Second ion-implantation

Ion species	Boron
Acceleration energy	30 keV
Dosage	$2.1 \times 10^{13}/\text{cm}^2$
Ion incidence angle	10 degrees

5

[Step-130]

Then, ion-implantation with an impurity having the first conductivity type (for example, n-type) is carried out, to form the fourth region SC₄ which is formed in a surface region of the second region SC₂ and which is in contact so as to form a rectifier junction together with the second region SC₂ (see Fig. 18B). The ion-implantation is carried out under conditions shown in the following Table 3.

15

Table 3

Ion species	Arsenic
Acceleration energy	25 keV
Dosage	$1 \times 10^{13}/\text{cm}^2$
Ion incidence angle	7 degrees

[Step-140]

Then, the ion-implanting mask 21 is removed, an SiO₂ layer is formed on the entire surface by a CVD method, and the SiO₂ layer is etched back to form a side-wall 30 on the side wall of the gate G (G₁ + G₂).

[Step-150]

Then, an ion-implanting mask 22 is formed

25

-160-

from a resist material, and then ion-implantation with an impurity having the first conductivity type (for example, n-type) is carried out so that the impurity concentration of the fourth region SC₄ is increased up to approximately 10^{18} to 10^{20} cm⁻³, to decrease the resistance of the fourth region SC₄ (see Fig. 19A). The ion-implantation is carried out under conditions shown in the following Table 4.

10 Table 4

Ion species	Arsenic
Acceleration energy	30 keV
Dosage	$5 \times 10^{15}/\text{cm}^2$
Ion incidence angle	7 degrees

[Step-160]

Then, the ion-implanting mask 22 is removed, and an ion-implanting mask 23 is formed from a resist material. Then, ion-implantation with an impurity having the second conductivity type (for example, p-type) is carried out so that the impurity concentration of the third region SC₃ is increased up to approximately 10^{18} to 10^{20} cm⁻³, to decrease the resistance of the third region SC₃ (see Fig. 19B). The ion-implantation is carried out under conditions shown in the following Table 5.

25 Table 5

Ion species	BF ₂
Acceleration energy	30 keV
Dosage	$3 \times 10^{15}/\text{cm}^2$
Ion incidence angle	7 degrees

Under the above ion-implantation conditions, the second region SC₂ and the third region SC₃ had the

-161-

following impurity concentrations.

Table 6

Second region SC ₂	$1.5 \times 10^{18}/\text{cm}^3$
Third region SC ₃	$2.1 \times 10^{19}/\text{cm}^3$

5

[Step-170]

Then, an insulating interlayer is formed on the entire surface, and then, the insulating interlayer is patterned using a patterned resist material as a mask, to expose part of the second region SC₂. A silicon oxide layer (SiO₂ layer) as a wide gap thin film WG is formed on the surface of the exposed second region SC₂. Then, a polysilicon thin layer containing an impurity having the first conductivity type (for example, n-type) is formed on the entire surface, and then the polysilicon thin layer is patterned to form the electrode EL which constitutes the other end of a MIS type diode connected to the wide gap thin film WG and also to form the high-resistance element R extending from the electrode EL.

20

[Step-180]

Then, the write-in information setting line WISL, the second line (for example, bit line), the fourth line, etc., are formed according to known methods.

25

The steps of manufacturing the semiconductor memory cell shall not be limited to the above process. For example, [Step-110] may be omitted. [Step-120], [Step-130] and [Step-150] may be carried out in any order. The formation of the gate and the formation of the device separation region may be carried out after [Step-170]. The above-described ion-implantation conditions are given for explanation purposes and may be modified as required.

30

For forming a majority carrier diode DS of a Schottky junction type, for example, a diode-

35

-162-

constituting region SC_D composed, for example, of a titanium silicide layer is formed in a surface region of the first region SC_1 . The above titanium silicide layer can be formed, for example, by the following method.

- 5 That is, an insulating interlayer is formed on the entire surface, and the insulating interlayer in a region of the silicon semiconductor substrate 10 is removed, the region being a region where the titanium silicide layer is to be formed. Then, a titanium layer
- 10 is formed on the insulating interlayer including the exposed surface of the silicon semiconductor substrate 10 by a sputtering method. Then, the titanium layer and the silicon semiconductor substrate are allowed to react by a first annealing treatment, to form the titanium
- 15 silicide layer on the surface of the silicon semiconductor substrate. Then, an unreacted titanium layer on the insulating interlayer is removed, for example, with an ammonium hydrogen peroxide aqueous solution (mixture of NH_4OH , H_2O_2 and H_2O), and then a
- 20 second annealing treatment is carried out, whereby a stabilized titanium silicide layer can be formed. The material for forming the majority carrier diode DS is not limited to titanium silicide, and it can be selected from materials such as cobalt silicide and tungsten
- 25 silicide. In Examples to be described later, the diode-constituting regions SC_D can be similarly formed as described above.

The method for forming the majority carrier diode DS or the method for forming conductive regions on

30 surface regions of various regions are not limited to the above-described methods. For example, when the write-in information setting line WISL is formed, for example, a barrier layer or a glue layer of titanium silicide or TiN is formed. The barrier layer or the

35 glue layer is also formed on the surface of the first region SC_1 , whereby the diode-constituting region SC_D which is a common region with part of the write-in

-163-

information setting line WISL (more specifically, part of the barrier layer or the glue layer) can be formed in a surface of the first region SC_1 . Conductive regions can be similarly formed in surface regions of various regions as described above. In Examples to be described later, majority carrier diodes DS or conductive regions can be similarly formed on surface regions of various regions as described above.

The variants of the semiconductor memory cell of Example 1 can be also manufactured substantially by the above method. Further, a semiconductor memory cell of Example 2 to be described later can be also manufactured substantially by the above method except for the formation of MIS-type-diode constituting regions SC_{DT} . When a MIS-type-diode constituting region SC_{DT} (to be described later) having the second conductivity type (for example, p^+ -type) is formed in the form of a buried plug, it can be formed in [Step-170] by a method in which the insulating interlayer is formed, then, a MIS-type-diode constituting region SC_{DT} is formed by ion implantation using a patterned resist material as a mask, and then the MIS type diode DT is formed.

Example 2

Example 2 is concerned with the semiconductor memory cell according to the first and third aspects of the present invention. Fig. 4 shows the principle of the semiconductor memory cell of Example 2, Fig. 20A shows a partial cross-sectional view thereof, and Fig. 20B shows a schematic layout of regions thereof and a cross-sectional view taken by cutting regions including a MIS-type-diode constituting region SC_{DT} with a vertical plane.

The semiconductor memory cell comprises;

(1) a first transistor TR_1 for readout, having a first conductivity type (for example, n-channel type) and having source/drain regions, a semi-conductive channel forming region CH_1 which is in contact with the

-164-

source/drain regions and spaces out the source/drain regions, and a gate G_1 capacitively coupled with the channel forming region CH_1 ,

(2) a second transistor TR_2 for switching, having
5 a second conductivity type (for example, p-channel type) and having source/drain regions, a semi-conductive channel forming region CH_2 which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate G_2 capacitively coupled with the
10 channel forming region CH_2 , and

(3) an MIS type diode DT for retaining information.

In Example 2, similarly, the first transistor TR_1 and the second transistor TR_2 constitute one merged transistor. That is, the area of the
15 semiconductor memory cell of Example 2 is generally smaller than the area of two transistors.

The semiconductor memory cell of Example 2 has;

(a) a semi-conductive first region SC_1 having a
20 first conductivity type (for example, n-type),

(b) a semi-conductive second region SC_2 being in contact with the first region SC_1 and having a second conductivity type (for example, p^+ -type),

(c) a third region SC_3 which is formed in a
25 surface region of the first region SC_1 to be spaced from the second region SC_2 and is in contact with the first region SC_1 so as to form a rectifier junction together with the first region SC_1 , the third region SC_3 being a region which is semi-conductive and has the second
30 conductivity type (for example, p^{++} -type) or which is conductive and is formed of a silicide, a metal or a metal compound,

(d) a semi-conductive fourth region SC_4 which is formed in a surface region of the second region SC_2 to
35 be spaced from the first region SC_1 and has the first conductivity type (for example, n^{++} -type), and

(e) a semi-conductive MIS-type-diode constituting

-165-

region SC_{DT} which is formed in a surface region of the fourth region SC_4 and has the second conductivity type (for example, p^+ -type).

Concerning the first transistor TR_1 ,

5 (A-1) one source/drain region is formed of a surface region of the first region SC_1 which surface region is interposed between the second region SC_2 and the third region SC_3 ,

(A-2) the other source/drain region is formed of
10 the fourth region SC_4 ,

(A-3) the channel forming region CH_1 is formed of a surface region of the second region SC_2 which surface region is interposed between the surface region of the first region SC_1 and the fourth region SC_4 , and

15 (A-4) the gate G_1 is formed on the channel forming region CH_1 of the first transistor TR_1 through an insulation layer.

Concerning the second transistor TR_2 ,

(B-1) one source/drain region is formed of the
20 surface region of the second region SC_2 which surface region constitutes the channel forming region CH_1 of the first transistor TR_1 ,

(B-2) the other source/drain region is formed of the third region SC_3 ,

25 (B-3) the channel forming region CH_2 is formed of the surface region of the first region SC_1 which surface region constitutes one source/drain region of the first transistor TR_1 , and

(B-4) the gate G_2 is formed on the channel forming
30 region CH_2 of the second transistor TR_2 through an insulation layer.

The gate G_1 of the first transistor TR_1 and the gate G_2 of the second transistor TR_2 are formed on the insulation layer so as to bridge the first region
35 SC_1 and the fourth region SC_4 and so as to bridge the second region SC_2 and the third region SC_3 , and are shared by the first transistor TR_1 and the second

-166-

transistor TR_2 .

Further, concerning the MIS type diode DT,
(C-1) one end thereof is formed of the MIS-type-diode constituting region SC_{DT} which corresponds to an
5 extending portion of the channel forming region CH_1 of the first transistor TR_1 , and

(C-2) an electrode EL constituting the other end thereof is formed to be opposed to the MIS-type-diode constituting region SC_{DT} constituting one end of the MIS
10 type diode DT, through a wide gap thin film.

Further, in the semiconductor memory cell of Example 2, the gate G_1 of the first transistor TR_1 and the gate G_2 of the second transistor TR_2 are connected to a first line (word line) for memory cell selection.
15 The second region SC_2 is connected to the MIS-type-diode constituting region SC_{DT} , the third region SC_3 is connected to a write-in information setting line WISL, and the fourth region SC_4 is connected to a second line (for example, bit line for memory cell selection).
20 Further, the electrode EL constituting the other end of the MIS type diode DT is connected to a third line having a predetermined potential. Furthermore, the first region SC_1 is connected to a fourth line.

In another embodiment, the gate G_1 of the
25 first transistor TR_1 and the gate G_2 of the second transistor TR_2 are connected to the first line (word line), the other source/drain region of the first transistor TR_1 is connected to the second line (bit line), the other source/drain region of the second
30 transistor TR_2 is connected to the write-in information setting line WISL, and the other end of the MIS type diode DT is connected to the line (third line) having a predetermined potential through the high-resistance element R.

35 In the semiconductor memory cell of Example 2, the second region SC_2 is formed in the surface region of the first region SC_1 as well. Further, a second

-167-

high-concentration-impurity-containing layer SC_{11} having the first conductivity type (for example, n^{++} -type) is formed below the first region SC_1 , and the second high-concentration-impurity-containing layer SC_{11} works as the fourth line. Furthermore, a first high-concentration-impurity-containing layer SC_{10} having the first conductivity type (for example, n^{++} -type) is formed below the second region SC_2 . The semiconductor memory cell is formed in a well structure having the first conductivity type (for example, n -type).

The MIS-type-diode constituting region SC_{DT} and the second region SC_2 can be connected by forming a structure, for example, as shown in Fig. 20B, in which a portion of the second region SC_2 extends up to a vicinity of the surface of the semiconductor substrate and the MIS-type-diode constituting region SC_{DT} and the extending part of the second region SC_2 are brought into contact with each other outside the fourth region SC_4 . When the semiconductor memory cell is structured as described above, the wiring structure of the semiconductor memory cell can be simplified.

In a semiconductor memory cell whose schematic partial cross-sectional view is shown in Fig. 21, the MIS-type-diode constituting region SC_{DT} having the second conductivity type (for example, p^{+} -type) is formed in the form of a buried plug, and the MIS-type-diode constituting region SC_{DT} penetrates through the fourth region SC_4 until it reaches the second region SC_2 . When the semiconductor memory cell is structured as described above, the MIS-type-diode constituting region SC_{DT} and the second region SC_2 can be also connected. Except for this point, the semiconductor memory cell shown in Fig. 21 is substantially structurally the same as the semiconductor memory cell shown in Figs. 20A and 20B.

In the semiconductor memory cell shown in Figs. 20A and 20B or Fig. 21, there may be employed

-168-

another constitution in which the a second predetermined potential is applied to the second line to which the fourth region SC_4 is connected, and the fourth line to which the first region SC_1 is connected is used as a
5 line (bit line) for memory cell selection.

In the semiconductor memory cell of Example 2, the third region SC_3 is formed of semiconductor, and the impurity concentrations of the first region SC_1 and the third region SC_3 are properly controlled so that the
10 first region SC_1 and the third region SC_3 constitute a pn junction diode D, whereby there can be employed a constitution in which the fourth line is omitted and the first region SC_1 is connected to the write-in information setting line WISL through the third region
15 SC_3 as Fig. 5 shows the principle thereof. In this case, the wiring structure of the semiconductor memory cell can be simplified. In the so-constituted semiconductor memory cell, the gate G_1 of the first transistor TR_1 and the gate G_2 of the second transistor TR_2 are connected
20 to the first line (word line), one source/drain region of the first transistor TR_1 is connected to the write-in information setting line WISL through the pn junction diode D, the other source/drain region of the first transistor TR_1 is connected to the second line (for
25 example, bit line), the other source/drain region of the second transistor TR_2 is connected to the write-in information setting line WISL, and the other end of the MIS type diode DT is connected to the line (third line) having a predetermined potential through the high-
30 resistance element R. There may be employed another constitution in which a second predetermined potential is applied to the second line to which the fourth region SC_4 is connected and the fourth line to which the first region SC_1 is connected is used as a line (bit line) for
35 memory cell selection.

Fig. 6 shows the principle of a variant of the semiconductor memory cell of Example 2. Further,

-169-

Fig. 22A shows a schematic partial cross-sectional view of the variant, and Fig. 22B shows a schematic layout of regions thereof and a schematic cross-sectional view taken by cutting the regions including a MIS-type-diode constituting region SC_{DT} with a vertical plane. The semiconductor memory cell shown in Figs. 22A and 22B is a variant of the semiconductor memory cell shown in Figs. 20A and 20B. Further, Fig. 23 shows a variant of the semiconductor memory cell shown in Fig. 21. In these semiconductor memory cells, a diode-constituting region SC_D is formed in a surface region of the first region SC_1 and the diode-constituting region SC_D is composed, for example, of titanium silicide, TiN and the like. The first region SC_1 and the diode-constituting region SC_D constitute a majority carrier diode DS. In the above constitution, the fourth line can be omitted, and the first region SC_1 can be connected to the write-in information setting line WISL through the diode-constituting region SC_D , so that the wiring structure can be simplified. In the so-constituted semiconductor memory cell, the gate G_1 of the first transistor TR_1 and the gate G_2 of the second transistor TR_2 are connected to the first line (word line), one source/drain region of the first transistor TR_1 is connected to the write-in information setting line WISL through the majority carrier diode DS, the other source/drain region of the first transistor TR_1 is connected to the second line corresponding to the bit line, the other source/drain region of the second transistor TR_2 is connected to the write-in information setting line WISL, and the other end of the MIS type diode DT is connected to the line (third line) having a predetermined potential through the high-resistance element R. There may be employed another constitution in which a second predetermined potential is applied to the second line to which the fourth region SC_4 is connected and the write-in information setting line WISL is used as a bit line as

-170-

well.

Figs. 24A, 24B, 25A, 25B, 26A, 26B, 27, 28, 29 and 30 show other variants of the semiconductor memory cell of Example 2.

5 In the variants shown in Figs. 24A and 24B, a semiconductor memory cell having the structure shown in Figs. 20A and 20B is formed in a semiconductor layer SC_0 surrounded by an insulation material layer IL_0 on a supporting substrate SPS. In the variants shown in Figs.
10 25A and 25B, a semiconductor memory cell having the structure shown in Fig. 21 is formed in a semiconductor layer SC_0 surrounded by an insulation material layer IL_0 on a supporting substrate SPS. The difference between the semiconductor memory cells shown in Figs. 24A and
15 25A and the semiconductor memory cells shown in Figs. 24B and 25B is how far the third region SC_3 extends downwardly. In the semiconductor memory cells having structures shown in Figs. 24B and 25B, an electrode from a side of the third region SC_3 to the write-in
20 information setting line WISL can be taken. These semiconductor memory cells are substantially structurally the same as the semiconductor memory cell shown in Figs. 20A and 20B or Fig. 21 in other points.

In the variants shown in Figs. 26A and 26B
25 (see the showing of the principle in Fig. 6A), a semiconductor memory cell having the structure shown in Figs. 22A and 22B and Fig. 23 is formed in a semiconductor layer SC_0 surrounded by an insulation layer material IL_0 on a supporting substrate SPS. These
30 semiconductor memory cells in Figs. 26A and 26B are substantially structurally the same as the semiconductor memory cell shown in Figs. 22A and 22B and Fig. 23 in other points.

The semiconductor memory cells shown in Figs.
35 24A, 24B, 25A, 25B, 26A and 26B can be manufactured according to the already explained method of manufacturing an SOI structure or TFT structure.

-171-

A semiconductor memory cell shown in Fig. 27 is a variant of the semiconductor memory cell shown in Figs. 20A and 20B, a semiconductor memory cell shown in Fig. 28 is a variant of the semiconductor memory cell shown in Fig. 21, a semiconductor memory cell shown in Fig. 29 is a variant of the semiconductor memory cell shown in Figs. 22A and 22B, and a semiconductor memory cell shown in Fig. 30 is a variant of the semiconductor memory cell shown in Fig. 23. In the semiconductor memory cells shown in Figs. 27 to 30, the first region SC_1 is formed in a surface region of the second region SC_2 . Except for this point, the semiconductor memory cells shown in Figs. 27 to 30 are substantially structurally the same as those shown in Figs. 20A and 20B, Fig. 21, Figs. 22A and 22B and Fig. 23, respectively.

In the above-explained variants of the semiconductor memory cell of Example 2, shown in Figs. 24A, 24B, 25A, 25B, 27 and 28, there may be employed a constitution in which the second line to which the fourth region SC_4 is connected is used as a bit line and a second predetermined potential is applied to the fourth line to which the first region SC_1 is connected. Further, there may be employed another constitution in which a second predetermined potential is applied to the second line to which the fourth region SC_4 is connected and the fourth line to which the first region SC_1 is connected is used as a bit line for memory cell selection. Further, in the variants of the semiconductor memory cell of Example 2, shown in Figs. 26A, 26B, 29 and 30, there may be employed a constitution in which the second line to which the fourth region SC_4 is connected is used as a bit line, or a constitution in which a second predetermined potential is applied to the second line and the write-in information setting line WISL is used as a bit line as well.

-172-

Example 3

Example 3 is concerned with the semiconductor memory cells according to the first and fourth aspects of the present invention. As is shown in the principle drawing of Fig. 1 and the schematic partial cross-sectional view of Fig. 31A, the semiconductor memory cell of Example 3 comprises;

- (1) a first transistor TR_1 for readout, having a first conductivity type (for example, n-channel type) and having source/drain regions, a semi-conductive channel forming region CH_1 which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate G_1 capacitively coupled with the channel forming region CH_1 ,
- (2) a second transistor TR_2 for switching, having a second conductivity type (for example, p-channel type) and having source/drain regions, a semi-conductive channel forming region CH_2 which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate G_2 capacitively coupled with the channel forming region CH_2 , and
- (3) an MIS type diode for retaining information.

In the semiconductor memory cell of Example 3 shown in Fig. 31A, the gate G_1 of the first transistor TR_1 and the gate G_2 of the second transistor TR_2 are respectively formed on a first main surface A_1 and a second main surface A_2 which are opposite to each other thorough a semiconductor layer, and positions of these gates are deviated to some extent with regard to the perpendicular direction. Further, the semiconductor memory cell has a so-called SOI structure in which it is surrounded by an insulation material layer IL_0 formed on a supporting substrate SPS. In the semiconductor memory cell of Example 3 shown in Fig. 31A, the supporting substrate SPS, an insulating interlayer IL_1 , the gate G_2 of the second transistor TR_2 and the gate G_1 of the first transistor TR_1 are arranged in this order from

-173-

below.

Further, the semiconductor memory cell of Example 3 has;

(a) a semi-conductive first region SC_1 which is
5 formed in the semiconductor layer to extend over from the first main surface A_1 to the second main surface A_2 and has a first conductivity type (for example, n-type),

(b) a semi-conductive second region SC_2 which is
10 formed in the semiconductor layer to extend over from the first main surface A_1 to the second main surface A_2 , is in contact with the first region SC_1 and has a second conductivity type (for example, p^+ -type),

(c) a third region SC_3 which is formed in a
15 surface region including the second main surface A_2 of the first region SC_1 to be spaced from the second region SC_2 and is in contact with the first region SC_1 so as to form a rectifier junction together with the first region SC_1 , the third region SC_3 being a region which is semi-conductive and has the second conductivity type (for
20 example, p^{++} -type) opposite to the first conductivity type or which is conductive and is formed of a silicide, a metal or a metal compound,

(d) a fourth region SC_4 which is formed in a
25 surface region including the first main surface A_1 of the second region SC_2 to be spaced from the first region SC_1 and is in contact with the second region SC_2 so as to form a rectifier junction together with the second region SC_2 , the fourth region SC_4 being a region which is semi-conductive and has the first conductivity type
30 (for example, n^{++} -type) or which is conductive and is formed of a silicide, a metal or a metal compound,

(e) the gate G_1 of the first transistor TR_1 formed
on a first insulation layer formed on the first main
surface A_1 so as to bridge the first region SC_1 and the
35 fourth region SC_4 , and

(f) the gate G_2 of the second transistor TR_2 formed
on a second insulation layer formed on the second main

-174-

surface A_2 so as to bridge the second region SC_2 and the third region SC_3 .

Concerning the first transistor TR_1 ,

(A-1) one source/drain region is formed of a
5 surface region including the first main surface A_1 of the first region SC_1 ,

(A-2) the other source/drain region is formed of the fourth region SC_4 , and

(A-3) the channel forming region CH_1 is formed of
10 a surface region including the first main surface A_1 of the second region SC_2 , which surface region is interposed between the surface region including the first main surface A_1 of the first region SC_1 and the fourth region SC_4 .

15 Concerning the second transistor TR_2 ,

(B-1) one source/drain region is formed of a surface region including the second main surface A_2 of the second region SC_2 ,

(B-2) the other source/drain region is formed of
20 the third region SC_3 , and

(B-3) the channel forming region CH_2 is formed of a surface region including the second main surface A_2 of the first region SC_1 , which surface region is interposed between the surface region including the second main
25 surface A_2 of the second region SC_2 and the third region SC_3 .

Further, concerning the MIS type diode DT ,

(C-1) one end thereof is formed of part of the second region SC_2 , and

30 (C-2) an electrode EL constituting the other end thereof is formed to be opposed to said part of the second region SC_2 constituting one end of the MIS type diode DT through a wide gap thin film WG , and is composed of a conductive material.

35 In the examples shown in Figs. 31A and 31B, the MIS type diode DT is formed on the second main surface A_2 side, while it may be formed on the first

-175-

main surface A_1 side. In semiconductor memory cells to be explained hereinafter, the MIS type diode DT may be formed on any main surface side.

The gate G_1 of the first transistor TR_1 and
5 the gate G_2 of the second transistor TR_2 are connected to a first line (for example, word line) for memory cell selection, the third region SC_3 is connected to a write-in information setting line WISL, the fourth region SC_4 is connected to a second line (for example, bit line),
10 the electrode EL constituting the other end of the MIS type diode is connected to a third line having a predetermined potential, and the first region SC_1 is connected to a fourth line. The first region SC_1 is connected to the fourth line having a second
15 predetermined potential. There may be employed a constitution in which a second predetermined potential is applied to the second line to which the fourth region SC_4 is connected and the fourth line to which the first region SC_1 is connected is used as a line (bit line) for
20 memory cell selection.

Fig. 31B and Figs. 32A and 32B show schematic partial cross-sectional views of variants of the semiconductor memory cell of Example 3. In the variant shown in Fig. 31B, the positions of the gate G_1
25 of the first transistor TR_1 and the gate G_2 of the second transistor TR_2 are nearly aligned with regard to the perpendicular direction, differing from their positional relationship in Fig. 31A. In the above-constituted structure, the area of the semiconductor
30 memory cell can be decreased. In the variants shown in Figs. 32A and 32B, the supporting substrate SPS, the insulating interlayer IL_1 , the gate G_1 of the first transistor TR_1 and the second transistor TR_2 are formed in this order from below. The positional relationship
35 of these regions with regard to the perpendicular direction is reverse to the positional relationship of the regions of the semiconductor memory cell shown in

-176-

Figs. 31A and 31B. In the variant shown in Fig. 32B, the gate G_1 of the first transistor TR_1 and the gate G_2 of the second transistor TR_2 are nearly aligned with regard to the perpendicular direction, differing from
5 their positional relationship in Fig. 32A.

The process for manufacturing the semiconductor memory cell of Example 3 shown in Fig. 31B will be explained hereinafter, with reference to Figs. 33A, 33B, 34A, 34B, 35A, 35B, 36A, 36B and 37 showing
10 schematic partial cross-sectional views of a supporting substrate and the like.

[Step-200]

First, a silicon semiconductor substrate 10
is etched to form a projecting portion of the silicon
15 semiconductor substrate 10, in which projecting portion the semiconductor memory cell is to be formed. Then, a concave portion of the silicon semiconductor substrate 10 is buried with an insulation material layer 11 (IL_0), to form a state where the surface of projecting portion
20 of the silicon semiconductor substrate 10 (semiconductor substrate SCS) is exposed. The insulation material layer 11 corresponds to a device separation region. Then, the semi-conductive first region SC_1 having the first conductivity type (for example, n-type) is formed
25 in the projecting portion of the silicon semiconductor substrate 10. The formation of the first region SC_1 and the formation of the projecting portion of the silicon semiconductor substrate may be reversed. Then, a silicon oxide layer 12 (corresponding to a second
30 insulation layer) having a thickness, for example, of approximately 10 nm is formed on the surface of projecting portion of the silicon semiconductor substrate 10 according to a known silicon oxide layer forming method. This state is shown in the schematic
35 partial cross-sectional view of Fig. 33A. The surface of projecting portion of the silicon semiconductor substrate 10 corresponds to the second main surface A_2 .

-177-

The projection portion of the silicon semiconductor substrate 10 may have a thickness of 0.3 to 0.4 μm .

[Step-210]

Then, the second region SC_2 having the second conductivity type (for example, p^+ -type) is formed by an oblique ion implanting method using a resist 20 as a mask. In this manner, there can be obtained the first region SC_1 which is formed in a semiconductor layer 10A (corresponding to the projecting portion of the silicon semiconductor substrate 10) to extend over from a first main surface (to be described later) to the second main surface A_2 and has the first conductivity type (for example, n-type), and the semi-conductive second region SC_2 which is formed in the semiconductor layer 10A to extend over from the first main surface to the second main surface A_2 , is in contact with the first region SC_1 and has the second conductivity type (for example, p^+ -type) (see Fig. 33B). Then, the gate G_2 of the second transistor TR_2 , which is composed, for example, of polysilicon containing an impurity or has a polyside or polymetal structure, is formed. This state is shown in the schematic partial cross-sectional view of Fig. 34A.

[Step-220]

Then, with a resist 21 as a mask, ion implantation is carried out, and then oblique ion implantation is carried out, to form the third region SC_3 in a surface region including the second main surface A_2 of the first region SC_1 , which third region SC_3 is a p^{++} -type semi-conductive region spaced from the second region SC_2 and is in contact with the first region SC_1 so as to form a rectifier junction together with the first region SC_1 . This state is shown in the schematic partial cross-sectional view of Fig. 34B.

[Step-230]

Then, an insulating interlayer is formed on the entire surface, and the insulating interlayer is patterned using a patterned resist material as a mask,

-178-

to expose part of the second region SC_2 . A silicon oxide layer (SiO_2 layer) which is a wide gap thin film WG is formed on the exposed surface of the second region SC_2 . Then, a polysilicon thin layer containing an
5 impurity having the first conductivity type (for example, n-type) is formed on the entire surface, and the polysilicon layer is patterned, whereby the electrode EL constituting the other end of the MIS type diode connected to the wide gap thin film WG is formed and the
10 high-resistance element R extending from the above electrode EL is also formed. Then, an insulating interlayer 13A is formed on the entire surface, an opening portion is formed in the insulating interlayer 13A above the third region SC_3 , a wiring material layer
15 is formed on the entire surface of the insulating interlayer 13A including the inside of the opening portion, and then the wiring material layer is patterned, to form the write-in information setting line WISL connected to the third region SC_3 . The ion implanting
20 method is not necessarily required for forming the third region SC_3 .

When the write-in information setting line WISL is formed, a barrier layer or a glue layer composed, for example, titanium silicide or TiN is formed, and the
25 above barrier layer or the glue layer is also formed on the surface of the first region SC_1 exposed in the bottom of the opening portion. In this manner, the conductive third region SC_3 which is a common region with part of the write-in information setting line WISL
30 (more specifically, part of the barrier layer or the glue layer) can be formed in the surface region of the first region SC_1 . Then, as shown in Fig. 35A, an insulating interlayer 13B is formed on the entire surface, for example, from SiO_2 according to a CVD
35 method, and the surface of the insulating interlayer 13B is flattened by polishing. And, the surface of the insulating interlayer 13B and a supporting substrate 14

-179-

are bonded (see Fig. 35B), and then the silicon semiconductor substrate 10 is ground and polished from its reverse surface, to expose a bottom 11A of the insulation material layer 11 (see Fig. 36A). The semiconductor layer 10A corresponding to the projecting portion of the silicon semiconductor substrate 10 is retained in the insulation material layer 11. The surface of the semiconductor layer 10A corresponds to the first main surface A_1 .

10 [Step-240]

Then, for example, a silicon oxide layer (corresponding to the first insulation layer) having a thickness of approximately 10 nm is formed on the surface of the semiconductor layer 10A according to a known silicon oxide forming method, and the gate G_1 of the first transistor TR_1 , which is composed, for example, of polysilicon containing an impurity or has a polyside or polymetal structure, is formed according to a known method (see Fig. 36B). The gate G_1 of the first transistor TR_1 and the gate G_2 of the second transistor TR_2 are formed so as to have the semiconductor layer 10A therebetween, and these are nearly aligned in positional relationship with regard to the perpendicular direction.

[Step-250]

Then, with a resist 22 as a mask, ion implantation is carried out, and then oblique ion implantation is carried out, to form the fourth region SC_4 which is an n^{++} -type semi-conductive region (see Fig. 37).

30 [Step-260]

Then, an insulating interlayer is formed on the entire surface, opening portions are formed in the insulating interlayer above the fourth region SC_4 and in the insulating interlayer above the first region SC_1 positioned on the first main surface A_1 , and a wiring material layer is formed on the insulating interlayer including the insides of the opening portions. Then,

-180-

the wiring material layer is patterned to form the second line and the fourth line. In this manner, the semiconductor memory cell structured as shown in Fig. 31B is completed. The ion implantation method is not necessarily required for forming the fourth region SC₄. When the second line is formed, a barrier layer or a glue layer composed for example, of titanium silicide or TiN is formed and the barrier layer or the glue layer is also formed on the surface of the second region SC₂. In this manner, the conductive fourth region SC₄ which is a common region with part of the second line (more specifically, part of the barrier layer or the glue layer) can be formed on the surface of the second region SC₂, whereby there can be formed a structure in which the conductive region is a common region with part of the line. A structure in which the conductive region is composed of a compound formed by a reaction between the wiring material and silicon of the silicon semiconductor substrate is also included in the structure in which the conductive region is a common region with part of the line.

The process for manufacturing the semiconductor memory cell of Example 3 is not limited to the above process. For example, the second region SC₂ can be formed after the formation of the silicon oxide layer having a thickness, for example, of approximately 10 nm on the surface of the semiconductor layer 10A in [Step-240] instead of forming it in [Step-210]. The order of formation of the regions by ion implantation is dependent upon steps, while the regions can be formed essentially in any order. In the above-explained ion implanting methods, it is required to optimize conditions of ion implantation of an impurity by means of computer simulation or an experiment for optimizing impurity concentrations of the regions.

Example 4

The semiconductor memory cell of Example 4

-181-

is a variant of the semiconductor memory cell of Example 3. As is shown in the principle drawing of Fig. 2 and the schematic partial cross-sectional view of Fig. 38A, the first region SC_1 and the third region SC_3 constitute a diode D of the semiconductor memory cell of Example 3. When diode D is provided, unlike the semiconductor memory cell of Example 3, the fourth line is no longer necessary, and the first region SC_1 is connected to the write-in information setting line WISL through the third region SC_3 in place of being connected to the fourth line, so that the wiring structure can be simplified. The pn junction diode D can be formed by adjusting the impurity concentrations of the first region SC_1 and the third region SC_3 to proper values. When the pn junction is formed of the third region SC_3 and the first region SC_1 in the semiconductor memory cell of Example 4, improper setting of potential in the third region SC_3 or improper designing of the relationship between the impurity concentrations of the third region SC_3 and the counterpart of the first region SC_1 may cause a latch-up during the reading of information. For avoiding the above latch-up, the voltage to be applied to the write-in information setting line WISL is required to be a voltage (for example, 0.4 volt or less) at which no high forward current flows in the junction of the third region SC_3 and the first region SC_1 (the diode D). If the third region SC_3 is composed of a silicide, a metal or the like so that a Schottky junction is formed between the third region SC_3 and the first region SC_1 , and that majority carrier mainly constitutes a forward current, the latch-up can be avoided, and the limitation to the voltage to be applied to the write-in information setting line WISL is substantially removed. The fourth region SC_4 is connected to the second line (for example, bit line) for memory cell selection. There may be employed a constitution in which a second predetermined potential is applied to the second line to which the

fourth region SC_4 is connected and the write-in information setting line WISL to which the first region SC_1 is connected is used as a bit line as well.

Figs. 38B, 39A and 39B show schematic partial cross-sectional views of variants of the semiconductor memory cell of Example 4. In the variant shown in Fig. 38B, the gate G_1 of the first transistor TR_1 and the gate G_2 of the second transistor TR_2 are nearly aligned with regard to the perpendicular direction, differing from their positional relationship in Fig. 38A. In the above-constituted structure, the area of the semiconductor memory cell can be decreased. In the variants shown in Figs. 39A and 39B, the supporting substrate SPS, the insulating interlayer IL_1 , the gate G_1 of the first transistor TR_1 and the gate G_2 of the second transistor TR_2 are formed in this order from below. The positional relationship of these regions with regard to the perpendicular direction is reverse to the positional relationship of the regions of the semiconductor memory cell shown in Figs. 38A and 38B. In the variant shown in Fig. 39B, the gate G_1 of the first transistor TR_1 and the gate G_2 of the second transistor TR_2 are nearly aligned with regard to the perpendicular direction, differing from their positional relationship in Fig. 39A.

As shown in the principle drawing of Fig. 3, the diode can be formed of a Schottky junction. That is, as is shown in the schematic partial cross-sectional view of Fig. 40, the diode may be a majority carrier diode DS formed of a diode-constituting region SC_D of a silicide or a metal such as Mo or Al and the first region SC_1 . Fig. 40 shows a variant of the semiconductor memory cell of Example 4 shown in Fig. 38B.

In the semiconductor memory cell explained in Example 3, there may be employed a constitution in which the surface region including the first main surface A_1 of the first region SC_1 constituting the

-183-

other source/drain region of the first transistor TR_1 is formed of a region SC_{1A} containing a high concentration of an impurity having the first conductivity type (for example, n^{++} -type impurity), and the surface region including the second main surface A_2 of the second region SC_2 constituting the other source/drain region of the second transistor TR_2 is formed of a region SC_{2A} containing a high concentration of an impurity having the second conductivity type (for example, p^{++} -type impurity). Figs. 41A and 41B show variants obtained by structurally modifying the semiconductor memory cells shown in Figs. 31A and 31B as explained above.

Further, in the semiconductor memory cell explained in Example 4, there may be employed a constitution in which the surface region including the first main surface A_1 of the first region SC_1 constituting the other source/drain region of the first transistor TR_1 is formed of a region SC_{1A} containing a high concentration of an impurity having the first conductivity type (for example, n^{++} -type impurity) and the surface region including the second main surface A_2 of the second region SC_2 constituting the other source/drain region of the second transistor TR_2 is formed of a region SC_{2A} containing a high concentration of an impurity having the second conductivity type (for example, p^{++} -type impurity). Figs. 42A and 42B show variants obtained by structurally modifying the semiconductor memory cells shown in Figs. 38A and 39A as explained above.

The semiconductor memory cell according to the fourth aspect of the present invention can be applied to a so-called side gate type semiconductor memory cell. For example, Figs. 43A and 43B show schematic perspective views of examples in which the semiconductor memory cell explained in Example 3 is applied to a side gate type semiconductor memory cell. Showing of the MIS type diode is omitted. In the

-184-

semiconductor memory cell of the above type, the first region SC_1 , the second region SC_2 , the third region SC_3 and the fourth region SC_4 are formed in a nearly cuboidal semiconductor layer protruded from an insulation layer, as is shown in Fig. 43A. Further, the gate G_1 and the gate G_2 are formed in portions of side surfaces of the cuboidal semiconductor layer. As shown in the schematic perspective view of Fig. 43B, the gate G_1 and the gate G_2 may be formed in the form of a letter "L", in which these extend from portions on side surfaces of the semiconductor layer of the cuboid to portions on the top surface thereof. The layout of regions found by cutting the semiconductor memory cell along arrows A-A in Fig. 43A or along arrows B-B in Fig. 43B is as shown in Fig. 31B. In Figs. 43A and 43B, the regions and gates alone are shown, and showing of wiring lines is omitted.

In principle, the semiconductor memory cell of Example 4 can be manufactured by the method explained with regard to the semiconductor memory cell of Example 3, and detailed explanations of the method of producing the same are therefore omitted. In the method of manufacturing a semiconductor memory cell, explained in Example 3, the semiconductor memory cell having a so-called SOI structure is manufactured from a so-called bonded substrate obtained by forming a projecting portion in the semiconductor substrate, then, forming the insulator (insulation layer) on the entire surface, bonding the insulator and the supporting substrate to each other, and grinding and polishing the semiconductor substrate from its reverse surface. Alternatively, a semiconductor memory cell having a so-called TFT structure can be also manufactured instead. That is, the gate is formed on an insulator (insulation layer), then, for example, an amorphous silicon layer or a polysilicon layer is formed on the entire surface by a CVD method, then, a silicon layer is formed from the

-185-

amorphous or polysilicon layer by a known single crystallization method such as a zone melting crystallization method using laser beam or electron beam or a lateral solid phase crystal growth method in which
5 a crystal is grown through an opening formed in the insulator (insulation layer) and the silicon layer is used as the semiconductor layer to manufacture the semiconductor memory cell. Otherwise, the gate is formed on the supporting substrate, and then, for
10 example, a polysilicon layer or an amorphous silicon layer is formed on the entire surface and used as a semiconductor layer to manufacture the semiconductor memory cell.

Example 5

15 Example 5 is concerned with the semiconductor memory cell according to the fifth and twelfth aspects of the present invention. As is shown in the principle drawing of Fig. 45A, the semiconductor memory cell of Example 5 comprises;

20 (1) a first transistor TR_1 for readout, having a first conductivity type (for example, n-channel type) and having source/drain regions, a semi-conductive channel forming region CH_1 which is in contact with the source/drain regions and spaces out the source/drain
25 regions, and a gate G_1 capacitively coupled with the channel forming region CH_1 ,

(2) a second transistor TR_2 for switching, having a second conductivity type (for example, p-channel type) and having source/drain regions, a semi-conductive
30 channel forming region CH_2 which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate G_2 capacitively coupled with the channel forming region CH_2 ,

(3) a junction-field-effect transistor JF_1 for
35 current control, having source/drain regions, a channel region CH_{J1} and gate regions, and

(4) an MIS type diode DT for retaining information.

-186-

In the above semiconductor memory cell,
one source/drain region of the first transistor
 TR_1 corresponds to the channel forming region CH_2 of the
second transistor TR_2 and corresponds to one
5 source/drain region of the junction-field-effect
transistor JF_1 ,

one source/drain region of the second transistor
 TR_2 corresponds to the channel forming region CH_1 of the
first transistor TR_1 and corresponds to one gate region
10 of the junction-field-effect transistor JF_1 , and

one end of the MIS type diode DT is formed of an
extending portion of the channel forming region CH_1 of
the first transistor TR_1 , the other end of the MIS type
diode DT is formed of an electrode composed of a
15 conductive material, and the electrode is connected to
the line (third line) having a predetermined potential.
In Example 5, the first transistor TR_1 and the second
transistor TR_2 are substantially separately formed
transistors.

20 Further, the gate G_1 of the first transistor
 TR_1 and the gate G_2 of the second transistor TR_2 are
connected to a first line (for example, word line) for
memory cell selection, the other source/drain region of
the first transistor TR_1 is connected to a second line,
25 the other gate region of the junction-field-effect
transistor JF_1 is connected to a fourth line, one
source/drain region of the first transistor TR_1 is
connected to a write-in information setting line $WISL$
through the junction-field-effect transistor JF_1 and a
30 diode D , the other source/drain region of the second
transistor TR_2 is connected to the write-in information
setting line $WISL$, and the other end of the MIS type
diode DT is connected to a third line (corresponding to
the above line having a predetermined potential) through
35 a high-resistance element R . It is preferred to employ
a constitution in which the second line is used as a bit
line, or a constitution in which the write-in

-187-

information setting line WISL is used as a bit line as well and a second predetermined potential is applied to the second line.

A wide gap thin film WG is formed between
5 the extending portion of the channel forming region CH_1 of the first transistor TR_1 which extending portion constitutes the MIS type diode DT and the electrode EL. This will also apply in the semiconductor memory cell to be explained below.

10 As is shown in the partial cross-sectional view of the Fig. 51, the semiconductor memory cell of Example 5 comprises;

(1) a first transistor TR_1 for readout, having a first conductivity type (for example, n-channel type)
15 and having source/drain regions, a semi-conductive channel forming region CH_1 which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate G_1 capacitively coupled with the channel forming region CH_1 ,

20 (2) a second transistor TR_2 for switching, having a second conductivity type (for example, p-channel type) and having source/drain regions, a semi-conductive channel forming region CH_2 which is in contact with the source/drain regions and spaces out the source/drain
25 regions, and a gate G_2 capacitively coupled with the channel forming region CH_2 ,

(3) a junction-field-effect transistor JF_1 for current control, having source/drain regions, a channel region CH_{J1} and gate regions, and

30 (4) an MIS type diode DT for retaining information, and the above semiconductor memory cell has;

(a) a semi-conductive first region SC_1 having a second conductivity type (for example, p^+ -type),

(b) a semi-conductive second region SC_2 which is
35 formed in a surface region of the first region SC_1 and has a first conductivity type (for example, n^+ -type),

(c) a third region SC_3 which is formed in a

-188-

surface region of the second region SC_2 and is in contact with the second region SC_2 so as to form a rectifier junction together with the second region SC_2 , the third region SC_3 being a region which is semi-conductive and has the second conductivity type (for example, p^{++} -type) or which is formed of a silicide, a metal or a metal compound and is conductive,

(d) a fourth region SC_4 which is formed in a surface region of the first region SC_1 to be spaced from the second region SC_2 and is in contact with the first region SC_1 so as to form a rectifier junction together with the first region SC_1 , the fourth region SC_4 being a region which is semi-conductive and has the first conductivity type (for example, n^{+} -type) or which is formed of a silicide, a metal or a metal compound and is conductive, and

(e) a fifth region SC_5 which is formed in a surface region of the second region SC_2 to be spaced from the third region SC_3 and is in contact with the second region SC_2 so as to form a rectifier junction together with the second region SC_2 , the fifth region SC_5 being a region which is semi-conductive and has the second conductivity type (for example, p^{++} -type) or which is formed of a silicide, a metal or a metal compound and is conductive.

Concerning the first transistor TR_1 ,

(A-1) one source/drain region is formed of a portion of a surface region of the second region SC_2 ,

(A-2) the other source/drain region is formed of the fourth region SC_4 ,

(A-3) the channel forming region CH_1 is formed of a portion of a surface region of the first region SC_1 which portion is interposed between said portion of the surface region of the second region SC_2 and the fourth region SC_4 , and

(A-4) the gate G_1 is formed on the channel forming region CH_1 of the first transistor TR_1 through an

-189-

insulation layer.

Concerning the second transistor TR_2 ,

(B-1) one source/drain region is formed of other portion of the surface region of the first region SC_1 ,

5 (B-2) the other source/drain region is formed of the third region SC_3 ,

(B-3) the channel forming region CH_2 is formed of other portion of the surface region of the second region SC_2 which other portion is interposed between said other
10 portion of the surface region of the first region SC_1 and the third region SC_3 , and

(B-4) the gate G_2 is formed on the channel forming region CH_2 of the second transistor TR_2 through an insulation layer.

15 Concerning the junction-field-effect transistor JF_1 ,

(C-1) the gate regions are formed of the fifth region SC_5 and a part of the first region SC_1 which part is opposed to the fifth region SC_5 ,

20 (C-2) the channel region CH_{J1} is formed of part of the second region SC_2 which part is interposed between the fifth region SC_5 and said part of the first region SC_1 ,

(C-3) one source/drain region is formed of said
25 portion of the surface region of the second region SC_2 which portion extends from one end of the channel region CH_{J1} of the junction-field-effect transistor JF_1 and constitutes one source/drain region of the first transistor TR_1 , and

30 (C-4) the other source/drain region is formed of a portion of the second region SC_2 which portion extends from the other end of the channel region CH_{J1} of the junction-field-effect transistor JF_1 .

Concerning the MIS type diode DT ,

35 (D-1) one end thereof is formed of part SC_{1A} of the first region SC_1 , and

(D-2) an electrode constituting the other end

-190-

thereof is formed to be opposed to said part SC_{1A} of the first region SC₁ constituting one end of the MIS type diode DT, through a wide gap thin film WG.

The wide gap thin film WG can be composed of
5 a material in which the tunnel transition of carriers is caused depending upon a potential difference between the potential in the first region SC₁ (the channel forming region CH₁ of the first transistor TR₁) and the
potential in the other end (electrode EL) of the MIS
10 type diode DT. Specifically, it can be composed, for example, of an SiO₂ or SiON film having a thickness of 5 nm or smaller, or an SiN film having a thickness of 9 nm or smaller.

The electrode EL constituting the other end
15 of the MIS type diode DT is connected to the line (third line) through the high-resistance element R having a resistance of approximately 10^9 to 10^{12} Ω . Specifically, the electrode EL constituting the other end of the MIS type diode DT and the high-resistance element R are
20 integrally formed and are composed of a polysilicon thin layer containing an impurity having the first conductivity type.

In the above semiconductor memory cell,
further,

25 (E) the gate G₁ of the first transistor TR₁ and the gate G₂ of the second transistor TR₂ are connected to the first line (for example, word line) for memory cell selection,

(F) the third region SC₃ is connected to the
30 write-in information setting line WISL,

(G) the fourth region SC₄ is connected to the second line,

(H) the electrode EL constituting the other end of the MIS type diode DT is connected to the third line
35 having a predetermined potential, and

(I) the fifth region SC₅ is connected to the fourth line.

-191-

In the semiconductor memory cell of Example 5, the second region SC_2 and the third region SC_3 constitute a pn junction diode D, and the second region SC_2 is connected to the write-in information setting line WISL through the third region SC_3 . The above pn junction diode D can be formed by adjusting the impurity concentrations of the second region SC_2 and the third region SC_3 to proper values. It is preferred to employ a constitution in which the second line is used as a bit line, or a constitution in which the write-in information setting line WISL is used as a bit line as well and a second predetermined potential is applied to the second line.

The junction-field-effect transistor JF_1 is formed by

(X) optimizing the distance between the facing gate regions (the fifth region SC_5 and the part of the first region SC_1 which part is opposed to the fifth region SC_5), that is, the thickness of the channel region CH_{J1} , and

(Y) optimizing the impurity concentration of each of the facing gate regions (the fifth region SC_5 and the part of the first region SC_1 which part is opposed to the fifth region SC_5) and the impurity concentration of the channel region CH_{J1} .

In Example 5, the semiconductor memory cell (specifically, the first region SC_1) is formed in a well structure which is formed, for example, in an n-type semiconductor substrate and has the second conductivity type (for example, p-type).

In the semiconductor memory cell of Example 5, when a first high-concentration-impurity-containing layer SC_{10} having the first conductivity type (for example, n^{++} -type) is formed below the first region SC_1 , the potential or charge to be stored in the channel forming region CH_1 of the first transistor TR_1 for readout can be increased.

-192-

Fig. 52 shows a variant of the semiconductor memory cell of Example 5 shown in Fig. 51. In this variant, a semiconductor memory cell structured as shown in Fig. 51 is formed in a semiconductor layer SC_0 formed on an insulating interlayer IL_1 on a supporting substrate SPS. The semiconductor memory cell having the above structure can be manufactured according to the already explained method of forming an SOI structure or a TFT structure.

10 In the semiconductor memory cell shown in Fig. 51, as is shown in the principle drawing of Fig. 44, there may be employed an embodiment in which the formation of the pn junction diode D is omitted and the second region SC_2 corresponding to one source/drain region of the first transistor TR_1 is connected to a fifth line (not shown in Fig. 51). In the above embodiment, it is preferred to employ a constitution in which the second line is used as a bit line and a second predetermined potential is applied to the fifth line, or
15 a constitution in which the fifth line is used as a bit line and a second predetermined potential is applied to the second line.

Further, Figs. 53 to 60 show variants of the semiconductor memory cell of Example 5 shown in Fig. 51.

25 The semiconductor memory cell shown in the principle drawing of Fig. 45B and the schematic partial cross-sectional view of Fig. 53 further has a diode-constituting region SC_D which is formed in a surface region of the second region SC_2 and is in contact with
30 the second region SC_2 to form a rectifier junction together with the second region SC_2 , and the diode-constituting region SC_D and the second region SC_2 constitute a majority carrier diode DS of a Schottky junction type. One source/drain region of the first
35 transistor TR_1 is connected to the write-in information setting line WISL through the junction-field-effect transistor JF_1 and the majority carrier diode DS of a

-193-

Schottky junction type in place of being connected to the fifth line through the junction-field-effect transistor JF_1 . That is, the second region SC_2 is connected to the write-in information setting line WISL through the diode-constituting region SC_D . In the semiconductor memory cell shown in Fig. 53, the diode-constituting region SC_D is formed adjacently to the third region SC_3 , while the position of the diode-constituting region SC_D shall not be limited thereto.

As shown in the principle drawings of Fig. 46 and Figs. 47A and 47B, the other gate region of the junction-field-effect transistor JF_1 may be connected to the write-in information setting line WISL in place of being connected to the fourth line. That is, as is shown in the schematic partial cross-sectional views of Figs. 54, 55 and 56, the fifth region SC_5 may be connected to the write-in information setting line WISL in place of being connected to the fourth line. The semiconductor memory cell shown in Fig. 54 is a variant of the semiconductor memory cell shown in Fig. 51, and the semiconductor memory cells shown in Figs. 55 and 56 are variants of the semiconductor memory cell shown in Fig. 53. The semiconductor memory cells shown in Figs. 55 and 56 have the same constitutions except that the diode-constituting regions SC_D are formed in different positions.

In the semiconductor memory cell shown in the principle drawing of Fig. 48 and the schematic partial cross-sectional view of Fig. 57, one source/drain region of the first transistor TR_1 is connected to the fourth line through the junction-field-effect transistor JF_1 and a diode D_1 in place of being connected to the fifth line through the junction-field-effect transistor JF_1 . That is, the semiconductor memory cell further has a diode-constituting region SC_D which is formed in a surface region of the second region SC_2 and is in contact with the second region SC_2 to form

-194-

a rectifier junction together with the second region SC_2 . The diode-constituting region SC_D and the second region SC_2 constitute the diode D_1 , and the second region SC_2 is connected to the fourth line through the diode-constituting region SC_D . In this case, it is preferred to employ a constitution in which the second line is used as a bit line. The diode-constituting region SC_D is formed preferably adjacently to the fifth region SC_5 , since the structure of the semiconductor memory cell can be simplified.

In the semiconductor memory cell shown in the principle drawing of Fig. 50A and the schematic partial cross-sectional view of Fig. 58, the other gate region of the junction-field-effect transistor JF_1 is connected to one gate region of the junction-field-effect transistor JF_1 in place of being connected to the fourth line. That is, the fifth region SC_5 is connected to the first region SC_1 in place of being connected to the fourth line. Further, the second region SC_2 and the third region SC_3 constitute a pn junction diode D , and the second region SC_2 is connected to the write-in information setting line WISL through the third region SC_3 . In this case, it is preferred to employ a constitution in which the second line is used as a bit line, or a constitution in which the write-in information setting line WISL is used as a bit line as well and a second predetermined potential is applied to the second line. As is shown in the principle drawing of Fig. 49, there may be employed a constitution in which the pn junction diode D is omitted and the second region SC_2 corresponding to one source/drain region of the first transistor TR_1 is connected to a fifth line (not shown in Fig. 58). In this case, it is preferred to employ a constitution in which the second line is used as a bit line and a second predetermined potential is applied to the fifth line, or a constitution in which the fifth line is used as a bit line and a second

-195-

predetermined potential is applied to the second line.

As is shown in the schematic partial cross-sectional view of Fig. 59 obtained by cutting the semiconductor memory cell with a vertical plane in parallel with the direction in which the gate extends, the fifth region SC_5 and the first region SC_1 can be connected, for example, by forming a structure in which a portion of the first region SC_1 extends up to a vicinity of the surface of the semiconductor substrate and the fifth region SC_5 and the extending portion of the first region SC_1 are brought into contact with each other outside the second region SC_2 . When the semiconductor memory cell is structured as described above, the wiring structure of the semiconductor memory cell can be simplified.

In the semiconductor memory cell shown in the principle drawing of Fig. 50B and the schematic partial cross-sectional view of Fig. 60, the fifth region SC_5 is also connected to the first region SC_1 in place of being connected to the fourth line. Further, it has a diode-constituting region SC_D which is formed in a surface region of the second region SC_2 and is in contact with the second region SC_2 to form a rectifier junction together with the second region SC_2 , the diode-constituting region SC_D and the second region SC_2 constitute a majority carrier diode DS of a Schottky junction type, and the second region SC_2 is connected to the write-in information setting line WISL through the diode-constituting region SC_D . In this case, it is preferred to employ a constitution in which the second line is used as a bit line, or a constitution in which the write-in information setting line WISL is used as a bit line as well and a second predetermined potential is applied to the second line.

35 Example 6

Example 6 is concerned with the semiconductor memory cell according to the fifth and

-196-

thirteenth aspects of the present invention. Fig. 62A shows the principle of the semiconductor memory cell of Example 6. In the semiconductor memory cell of Example 6, the other gate region of the junction-field-effect transistor JF_1 is connected to one gate region of the junction-field-effect transistor JF_1 in place of being connected to the fourth line. More specifically, one end of the MIS type diode DT and the other gate region of the junction-field-effect transistor JF_1 are formed as a common region. The fifth region SC_5 constituting the other gate region of the junction-field-effect transistor JF_1 corresponds to an extending portion of the channel forming region CH_1 of the first transistor TR_1 .

That is, as is shown in the schematic partial cross-sectional view of Fig. 63, the semiconductor memory cell of Example 6 comprises;

- (1) a first transistor TR_1 for readout, having a first conductivity type (for example, n-channel type), and having source/drain regions, a semi-conductive channel forming region CH_1 which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate G_1 capacitively coupled with the channel forming region CH_1 ,
- (2) a second transistor TR_2 for switching, having a second conductivity type (for example, p-channel type), and having source/drain regions, a semi-conductive channel forming region CH_2 which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate G_2 capacitively coupled with the channel forming region CH_2 ,
- (3) a junction-field-effect transistor JF_1 for current control, having source/drain regions, a channel region CH_{J1} and gate regions, and
- (4) an MIS type diode DT for retaining information, and

the semiconductor memory cell has;

-197-

(a) a semi-conductive first region SC_1 having a second conductivity type (for example, p^+ -type),

(b) a semi-conductive second region SC_2 which is formed in a surface region of the first region SC_1 and
5 has a first conductivity type (for example, n^+ -type),

(c) a third region SC_3 which is formed in a surface region of the second region SC_2 and is in contact with the second region SC_2 so as to form a rectifier junction together with the second region SC_2 ,
10 the third region SC_3 being a region which is semi-conductive and has the second conductivity type (for example, p^{++} -type) or which is formed of a silicide, a metal or a metal compound and is conductive,

(d) a fourth region SC_4 which is formed in a
15 surface region of the first region SC_1 to be spaced from the second region SC_2 and is in contact with the first region SC_1 so as to form a rectifier junction together with the first region SC_1 , the fourth region SC_4 being a region which is semi-conductive and has the first
20 conductivity type (for example, n^+ -type) or which is formed of a silicide, a metal or a metal compound and is conductive, and

(e) a semi-conductive fifth region SC_5 which is formed in a surface region of the second region SC_2 to
25 be spaced from the third region SC_3 and has the second conductivity type (for example, p^{++} -type).

Concerning the first transistor TR_1 ,

(A-1) one source/drain region is formed of a portion of a surface region of the second region SC_2 ,
30 (A-2) the other source/drain region is formed of the fourth region SC_4 ,

(A-3) the channel forming region CH_1 is formed of a portion of a surface region of the first region SC_1 which portion is interposed between said portion of the
35 surface region of the second region SC_2 and the fourth region SC_4 , and

(A-4) the gate G_1 is formed on the channel forming

-198-

region CH_1 of the first transistor TR_1 through an insulation layer.

Concerning the second transistor TR_2 ,

(B-1) one source/drain region is formed of other
5 portion of the surface region of the first region SC_1 ,

(B-2) the other source/drain region is formed of the third region SC_3 ,

(B-3) the channel forming region CH_2 is formed of other portion of the surface region of the second region
10 SC_2 which other portion is interposed between said other portion of the surface region of the first region SC_1 and the third region SC_3 , and

(B-4) the gate G_2 is formed on the channel forming region CH_2 of the second transistor through an
15 insulation layer.

Further, concerning the junction-field-effect transistor JF_1 ,

(C-1) the gate regions are formed of the fifth region SC_5 and part of the first region SC_1 which part
20 is opposed to the fifth region SC_5 ,

(C-2) the channel region CH_{J1} is formed of part of the second region SC_2 which part is interposed between the fifth region SC_5 and said portion of the first region SC_1 ,

(C-3) one source/drain region is formed of said
25 portion of the surface region of the second region SC_2 which portion extends from one end of the channel region CH_{J1} of the junction-field-effect transistor JF_1 and constitutes one source/drain region of the first
30 transistor TR_1 , and

(C-4) the other source/drain region is formed of a portion of the second region SC_2 which portion extends from the other end of the channel region CH_{J1} of the junction-field-effect transistor JF_1 .

35 Concerning the MIS type diode DT , further,

(D-1) one end thereof is formed of the fifth region SC_5 , and

-199-

(D-2) an electrode constituting the other end thereof is formed to be opposed to the fifth region SC_5 constituting one end of the MIS type diode DT, through a wide gap thin film WG.

5 The wide gap thin film WG can be composed of a material in which the tunnel transition of carriers is caused depending upon a potential difference between the potential in the fifth region SC_5 (corresponding to the extending portion of the channel forming region CH_1 of
10 the first transistor TR_1) and the potential in the other end (electrode EL) of the MIS type diode DT. Specifically, it can be composed, for example, of an SiO_2 or $SiON$ film having a thickness of 5 nm or smaller, or an SiN film having a thickness of 9 nm or smaller.

15 The electrode EL constituting the other end of the MIS type diode DT is connected to the line (third line) through a high-resistance element R having a resistance of approximately 10^9 to $10^{12} \Omega$. Specifically, the electrode EL constituting the other end of the MIS
20 type diode DT and the high-resistance element are integrally formed and are composed of a polysilicon thin layer containing an impurity having the first conductivity type.

25 In the above semiconductor memory cell, further,

(E) the gate G_1 of the first transistor TR_1 and the gate G_1 of the second transistor TR_2 are connected to a first line (for example, word line) for memory cell selection,

30 (F) the third region SC_3 is connected to a write-in information setting line WISL,

(G) the fourth region SC_4 is connected to a second line,

(H) the fifth region SC_5 is connected to the first
35 region SC_1 , and

(I) the electrode EL constituting the other end of the MIS type diode DT is connected to a third line

-200-

having a predetermined potential.

In the semiconductor memory cell of Example 6, the second region SC_2 and the third region SC_3 constitute a pn junction diode D, and the second region SC_2 is connected to the write-in information setting line WISL through the third region SC_3 . The above pn junction diode can be formed by adjusting the impurity concentrations of the second region SC_2 and the third region SC_3 to proper values. It is preferred to employ a constitution in which the second line is used as a bit line, or a constitution in which the write-in information setting line WISL is used as a bit line as well and a second predetermined potential is applied to the second line.

The junction-field-effect transistor JF_1 is formed by

(X) optimizing the distance between the facing gate regions (the fifth region SC_5 and the part of the first region SC_1 which part is opposed to the fifth region SC_5), that is, thickness of the channel region CH_{J1} , and

(Y) optimizing the impurity concentration of each of the facing gate regions (the fifth region SC_5 and the part of the first region SC_1 which part is opposed to the fifth region SC_5) and the impurity concentration of the channel region CH_{J1} .

In Example 6, the semiconductor memory cell (specifically, the first region SC_1) is formed in a well structure which is formed, for example, in an n-type semiconductor substrate and has the second conductivity type (for example, p-type).

In the semiconductor memory cell of Example 6, when a first high-concentration-impurity-containing layer SC_{10} having the first conductivity type (for example, n^{++} -type) is formed below the first region SC_1 , the potential or charge to be stored in the channel forming region CH_1 of the first transistor TR_1 for readout can be increased.

-201-

In the semiconductor memory cell shown in Fig. 63, as is shown in the principle drawing of Fig. 61, there may be employed an embodiment in which the formation of the pn junction diode D is omitted and the

5 second region SC_2 corresponding to one source/drain region of the first transistor TR_1 is connected to a fifth line (not shown in Fig. 63). In the above embodiment, it is preferred to employ a constitution in which the second line is used as a bit line and a second

10 predetermined potential is applied to the fifth line, or a constitution in which the fifth line is used as a bit line and a second predetermined potential is applied to the second line.

The semiconductor memory cell shown in the

15 principle drawing of Fig. 62B and the schematic partial cross-sectional view of Fig. 64 further has a diode-constituting region SC_D which is formed in a surface region of the second region SC_2 and is in contact with the second region SC_2 to form a rectifier junction

20 together with the second region SC_2 , and the diode-constituting region SC_D and the second region SC_2 constitute a majority carrier diode DS of a Schottky junction type. One source/drain region of the first transistor TR_1 is connected to the write-in information

25 setting line WISL through the junction-field-effect transistor JF_1 and the majority carrier diode DS of a Schottky junction type in place of being connected to the fifth line through the junction-field-effect transistor JF_1 . That is, the second region SC_2 is

30 connected to the write-in information setting line WISL through the diode-constituting region SC_D . In the semiconductor memory cell shown in Fig. 64, the diode-constituting region SC_D is formed adjacently to the third region SC_3 , while the position of the diode-

35 constituting region SC_D shall not be limited thereto.

Example 7

Example 7 is concerned with the

-202-

semiconductor memory cell according to the seventh and fourteenth aspects of the present invention. Fig. 65 shows the principle of the semiconductor memory cell of Example 7. In the semiconductor memory cell of Example 7, the other gate region of the junction-field-effect transistor JF_1 is connected to the write-in information setting line WISL in place of being connected to the fourth line.

Further, as shown in the schematic partial cross-sectional view of Fig. 69A and the schematic layout of regions in Fig. 69B, the semiconductor memory cell of Example 7 differs from the semiconductor memory cell of Example 5 in that the fifth region SC_5 is omitted and that the first transistor TR_1 and the second transistor TR_2 share a gate. That is, the semiconductor memory cell of Example 7 comprises;

(1) a first transistor TR_1 for readout, having a first conductivity type (for example, n-channel type), and having source/drain regions, a semi-conductive channel forming region CH_1 which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate G capacitively coupled with the channel forming region CH_1 ,

(2) a second transistor TR_2 for switching, having a second conductivity type (for example, p-channel type) and having source/drain regions, a semi-conductive channel forming region CH_2 which is in contact with the source/drain regions and spaces out the source/drain regions, and the gate G capacitively coupled with the channel forming region CH_2 ,

(3) a junction-field-effect transistor JF_1 for current control, having source/drain regions, a channel region CH_{J1} and gate regions, and

(4) an MIS type diode DT for retaining information, and the semiconductor memory cell has;

(a) a semi-conductive first region SC_1 having a first conductivity type (for example, n-type),

-203-

(b) a semi-conductive second region SC_2 which is in contact with the first region SC_1 and has a second conductivity type (for example, p^+ -type),

(c) a third region SC_3 which is formed in a
5 surface region of the first region SC_1 and is in contact with the first region SC_1 so as to form a rectifier junction together with the first region SC_1 , the third region SC_3 being a region which is semi-conductive and has the second conductivity type (for example, p^{++} -type)
10 or which is formed of a silicide, a metal or a metal compound and is conductive,

(d) a fourth region SC_4 which is formed in a surface region of the second region SC_2 and is in contact with the second region SC_2 so as to form a
15 rectifier junction together with the second region SC_2 , the fourth region SC_4 being a region which is semi-conductive and has the first conductivity type (for example, n^{++} -type) or which is formed of a silicide, a metal or a metal compound and is conductive, and

20 (e) the gate G which is formed, through an insulation layer, so as to bridge the first region SC_1 and the fourth region SC_4 and so as to bridge the second region SC_2 and the third region SC_3 and is shared by the first transistor TR_1 and the second transistor TR_2 .

25 The first region SC_1 and the second region SC_2 are in contact with each other. In the semiconductor memory cell shown in Fig. 69, specifically, the second region SC_2 is formed in a surface region of the first region SC_1 .

30 Concerning the first transistor TR_1 ,

(A-1) one source/drain region is formed of a surface region of the first region SC_1 ,

(A-2) the other source/drain region is formed of the fourth region SC_4 , and

35 (A-3) the channel forming region CH_1 is formed of a surface region of the second region SC_2 which surface region is interposed between the surface region of the

-204-

first region SC_1 and the fourth region SC_4 .

Concerning the second transistor TR_2 ,

(B-1) one source/drain region is formed of the surface region of the second region SC_2 which surface
5 region constitutes the channel forming region CH_1 of the first transistor TR_1 ,

(B-2) the other source/drain region is formed of the third region SC_3 , and

(B-3) the channel forming region CH_2 is formed of
10 the surface region of the first region SC_1 which surface region constitutes one source/drain region of the first transistor TR_1 .

Further, concerning the junction-field-effect transistor JF_1 ,

15 (C-1) the gate regions are formed of the third region SC_3 and part of the second region SC_2 which part is opposed to the third region SC_3 ,

(C-2) the channel region CH_{J1} is formed of part of the first region SC_1 which part is interposed between
20 the third region SC_3 and said part of the second region SC_2 ,

(C-3) one source/drain region is formed of the surface region of the first region SC_1 which surface region extends from one end of the channel region CH_{J1}
25 of the junction-field-effect transistor JF_1 and constitutes one source/drain region of the first transistor TR_1 , and

(C-4) the other source/drain region is formed of a portion of the first region SC_1 which portion extends
30 from the other end of the channel region CH_{J1} of the junction-field-effect transistor JF_1 .

Concerning the MIS type diode DT ,

(D-1) one end thereof is formed of part SC_{2A} of the second region SC_2 , and

35 (D-2) an electrode constituting the other end thereof is formed to be opposed to said part SC_{2A} of the second region SC_2 which part constitutes one end of the

-205-

MIS type diode DT, through a wide gap thin film WG.

The wide gap thin film WG can be composed of a material in which the tunnel transition of carriers is caused depending upon a potential difference between the
5 potential in the second region SC₂ (the channel forming region CH₁ of the first transistor TR₁) and the potential in the other end (electrode EL) of the MIS type diode DT. Specifically, it can be composed, for example, of an SiO₂ or SiON film having a thickness of 5
10 nm or smaller, or an SiN film having a thickness of 9 nm or smaller.

The electrode EL constituting the other end of the MIS type diode DT is connected to the line (third line) through a high-resistance element R having a
15 resistance of approximately 10^9 to 10^{12} Ω . Specifically, the electrode EL constituting the other end of the MIS type diode DT and the high-resistance element are integrally formed and are composed of a polysilicon thin layer containing an impurity having the first
20 conductivity type.

In the above semiconductor memory cell, further,

(E) the gate G is connected to a first line (for example, word line) for memory cell selection,

25 (F) the third region SC₃ is connected to a write-in information setting line WISL,

(G) the fourth region SC₄ is connected to a second line, and

(H) the electrode EL constituting the other end of
30 the MIS type diode DT is connected to a third line having a predetermined potential.

It is preferred to employ a constitution in which the first region SC₁ is connected to a fifth line, the second line is used as a bit line and a second
35 predetermined potential is applied to the fifth line, or a constitution in which the first region SC₁ is connected to a fifth line, the fifth line is used as a

-206-

bit line and a second predetermined potential is applied to the second line.

In Example 7, the semiconductor memory cell (specifically, the first region SC_1) is formed in a well structure which is formed, for example, in an p-type semiconductor substrate and has the first conductivity type (for example, n-type).

In the semiconductor memory cell of Example 7, when a first high-concentration-impurity-containing layer SC_{10} having the first conductivity type (for example, n^{++} -type) is formed below the second region SC_2 , the potential or charge to be stored in the channel forming region CH_1 of the first transistor TR_1 for readout can be increased. Further, a second high-concentration-impurity-containing layer SC_{11} which works as the fifth line and has the first conductivity type (for example, n^{++} -type) is formed below the first region SC_1 .

The junction-field-effect transistor JF_1 is formed by

(X) optimizing the distance between the facing gate regions (the third region SC_3 and the part of the second region SC_2 which part is opposed to the third region SC_3), that is, the thickness of the channel region CH_{J1} , and

(Y) optimizing the impurity concentration of each of the facing gate regions (the third region SC_3 and the part of the second region SC_2 which part is opposed to the third region SC_3) and the impurity concentration of the channel region CH_{J1} .

Figs. 70 to 91 show schematic partial cross-sectional views of variants of the semiconductor memory cell of Example 7.

In the semiconductor memory cell shown in Fig. 70, a first conductivity type region SC_{12} is formed by ion-implanting an impurity having the first conductivity type to the channel region CH_{J1} of the

-207-

junction-field-effect transistor JF_1 by an oblique ion-implanting method. In this manner, the impurity concentration of the channel region CH_{J1} can be controlled, and the performance of the junction-field-effect transistor JF_1 can be stabilized. A constitution including the formation of the first conductivity type region SC_{12} can be applied to various semiconductor memory cells of the present invention although it differs depending upon the layout of the first region SC_1 , the second region SC_2 and the third region SC_3 .

In the semiconductor memory cell shown in the drawing of the principle of Fig. 66A and the schematic partial cross-sectional view of Fig. 71, the first region SC_1 and the third region SC_3 constitute a pn junction diode D, and the first region SC_1 is connected to the write-in information setting line WISL through the third region SC_3 . The above pn junction diode D can be formed by adjusting the impurity concentrations of the first region SC_1 and the third region SC_3 to proper values. Further, in the semiconductor memory cell shown in the drawing of the principle of Fig. 66B, the schematic partial cross-sectional view of Fig. 72A and the schematic layout of Fig. 72A, there is further provided a diode-constituting region SC_D which is formed in a surface region of the first region SC_1 and is in contact with the first region SC_1 to form a rectifier junction together with the first region SC_1 , the diode-constituting region SC_D and the first region SC_1 constitute a majority carrier diode DS, and the first region SC_1 is connected to the write-in information setting line WISL through the diode-constituting region SC_D . In these cases, it is preferred to employ a constitution in which the second line is used as a bit line, or a constitution in which the write-in information setting line WISL is used as a bit line as well and a second predetermined potential is applied to the second line.

-208-

In the variants shown in Figs. 73A and 73B, the semiconductor memory cell structured as shown in Fig. 69 is formed in a semiconductor layer SC_0 surrounded by an insulation material layer IL_0 on a supporting substrate SPS. The difference between the semiconductor memory cell shown in Fig. 73A and the semiconductor memory cell shown in Fig. 73B is how far the third region SC_3 extends downwardly. When the semiconductor memory cell structured as shown in Fig. 73B is employed, an electrode from a side of the third region SC_3 to the write-in information setting line WISL can be taken out. These semiconductor memory cells are substantially structurally the same as the semiconductor memory cell shown in Fig. 69 in other points. In the variant shown in Fig. 74, the semiconductor memory cell structured as shown in Figs. 72A and 72B is formed in a semiconductor layer SC_0 surrounded by an insulation material layer IL_0 on a supporting substrate SPS. The semiconductor memory cell shown in Fig. 74 is substantially structurally the same as the semiconductor memory cell shown in Fig. 72 in other points. The semiconductor memory cells having the above structures can be manufactured according to the already explained method of manufacturing an SOI structure or a TFT structure.

The semiconductor memory cell of Example 7 shown in Figs. 69A and 69B can be modified as shown in Figs. 75A, 75B and 76. Fig. 75A shows a schematic partial cross-sectional view of the semiconductor memory cell, Fig. 75B shows a schematic layout of regions, and Fig. 76 shows a schematic partial cross-sectional view taken along arrows in Fig. 75B. In the above semiconductor memory cell, a portion SC_{2B} of the second region SC_2 extends up to a surface of the semiconductor substrate beside the fourth region SC_4 . The extending portion SC_{2B} of the second region SC_2 corresponds to one end of the MIS type diode DT. The electrode EL constituting the other end of the MIS type diode DT is

-209-

formed on the extending portion SC_{2B} of the second region SC_2 through the wide gap thin film WG. The high-resistance element R integrally extends from the electrode EL. The electrode EL and the high-resistance element R are composed of a polysilicon thin layer containing an impurity having the first conductivity type (for example, n-type). The second line (for example, bit line) is formed on a second insulating interlayer IL_2 and extends in the direction perpendicular to the paper surface of Fig. 76. The second region SC_2 structure shown in Figs. 75A, 75B and 76 can be applied to various variants of the semiconductor memory cell of the present invention.

As is shown in the principle drawing of Fig. 67, the schematic partial cross-sectional view of Fig. 77A and the schematic layout of Fig. 77B, there may be employed a constitution in which a semi-conductive MIS-type-diode constituting region SC_{DT} having the second conductivity type (for example, p^+ -type) is formed in a surface region of the fourth region SC_4 and the MIS-type-diode constituting region SC_{DT} and the second region SC_2 are connected to each other. In the MIS type diode DT, one end thereof is formed of the MIS-type-diode constituting region SC_{DT} which corresponds to an extending portion of the channel forming region CH_1 of the first transistor TR_1 or an extending portion of the second region SC_2 , and an electrode EL constituting the other end thereof is formed so as to be opposed to the MIS-type-diode constituting region SC_{DT} constituting one end of the MIS type diode DT through the wide gap thin film and is composed of a conductive material.

The MIS-type-diode constituting region SC_{DT} and the second region SC_2 can be connected to each other, for example, by forming a structure in which a portion of the second region SC_2 is extended to a vicinity of the surface of the semiconductor substrate so that the MIS-type-diode constituting region SC_{DT} and the

-210-

extending portion of the second region SC_2 are in contact with each other outside the fourth region SC_4 , as is shown in the schematic partial cross-sectional view of Fig. 77C. The above MIS-type-diode constituting region SC_{DT} corresponds to the extending portion of the channel forming region CH_1 of the first transistor TR_1 or the extending portion of the second region SC_2 . When the semiconductor memory cell is structured as described above, the wiring structure of the semiconductor memory cell can be simplified.

In a semiconductor memory cell shown in the schematic partial cross-sectional view of Fig. 78, a MIS-type-diode constituting region SC_{DT} having the second conductivity type (for example, p^+ -type) is formed in a buried plug form, and the MIS-type-diode constituting region SC_{DT} through the fourth region SC_4 until it reaches the second region SC_2 . The above MIS-type-diode constituting region SC_{DT} corresponds to the extending portion of channel forming region CH_1 of the first transistor TR_1 or the extending portion of the second region SC_2 . In the above structure, the MIS-type-diode constituting region SC_{DT} and the second region SC_2 can be connected to each other as well. The semiconductor memory cell shown in Fig. 78 can be substantially structurally the same as the semiconductor memory cell shown in Fig. 69 except for the above point.

Semiconductor memory cells shown in schematic partial cross-sectional views of Figs. 79 and 80 (see Figs. 68A and 68B for their principle, respectively) are the variants of the semiconductor memory cell of Example 7 shown in Fig. 77 or 78, and have a constitution in which the first region SC_1 and the third region SC_3 constitute a pn junction D and the first region SC_1 is connected to the write-in information setting line WISL through the third region SC_3 . Further, semiconductor memory cells shown in schematic partial cross-sectional views of Figs. 81 and

-211-

82 are the variants of the semiconductor memory cell of Example 7 shown in Fig. 77 and 78, and have a constitution in which further provided is a diode-constituting region SC_D which is formed in a surface region of the first region SC_1 and is in contact with the first region SC_1 to form a rectifier junction together with the first region SC_1 , the diode-constituting region SC_D and the first region SC_1 constitute a majority carrier diode DS, and the first region SC_1 is connected to the write-in information setting line WISL through the diode-constituting region SC_D . Further, semiconductor memory cells shown in the schematic partial cross-sectional views of Figs. 83A and 83B are the variants of the semiconductor memory cell of Example 7 shown in Fig. 73A and 73B, and have a constitution in which further provided is a semi-conductive MIS-type-diode constituting region SC_{DT} having the second conductivity type (for example, p^+ -type) in a surface region of the fourth region SC_4 , and the MIS-type-diode constituting region SC_{DT} is connected to the second region SC_2 . Further, semiconductor memory cells shown in schematic partial cross-sectional views of Figs. 84A and 84B are the variants of the semiconductor memory cell of Example 7 shown in Fig. 73A and 73B, and have a constitution in which a MIS-type-diode constituting region SC_{DT} having the second conductivity type (for example, p^+ -type) is formed in a buried plug form and the MIS-type-diode constituting region SC_{DT} penetrates through the fourth region SC_4 until it reaches the second region SC_2 . Further, a semiconductor memory cell shown in the schematic partial cross-sectional view of Fig. 85A is the variant of the semiconductor memory cell of Example 7 shown in Fig. 74, and has a constitution in which further provided is a MIS-type-diode constituting region SC_{DT} having the second conductivity type (for example, p^+ -type) in a surface region of the fourth region SC_4 and the MIS-

-212-

type-diode constituting region SC_{DT} is connected to the second region SC_2 . Further, a semiconductor memory cell shown in the schematic partial cross-sectional view of Fig. 85B is the variant of the semiconductor memory cell of Example 7, shown in Fig. 74, and has a constitution in which a MIS-type-diode constituting region SC_{DT} having the second conductivity type (for example, p^+ -type) is formed in a buried plug form and the MIS-type-diode constituting region SC_{DT} penetrates through the fourth region SC_4 until it reaches the second region SC_2 .

In a variant of the semiconductor memory cell shown in Fig. 86, the first region SC_1 and the second region SC_2 are in contact with each other. Specifically, the variant shown in Fig. 86 has a constitution in which the first region SC_1 is formed in a surface region of the second region SC_2 , the first region SC_1 and the third region SC_3 constitute a pn junction diode D , and the first region SC_1 is connected to the write-in information setting line WISL through the third region SC_3 .

A variant of the semiconductor memory cell shown in Fig. 87 has a constitution in which the first region SC_1 is formed in a surface region of the second region SC_2 , further, there is provided a diode-constituting region SC_D which is formed in a surface region of the first region SC_1 and is in contact with the first region SC_1 to form a rectifier junction together with the first region SC_1 , the diode-constituting region SC_D and the first region SC_1 form a majority carrier diode DS , and the first region SC_1 is connected to the write-in information setting line WISL through the diode-constituting region SC_D .

Semiconductor memory cells shown in Figs. 88 and 89 have a constitution in which the first region SC_1 is formed in a surface region of the second region SC_2 , a semi-conductive MIS-type-diode constituting region SC_{DT} having a second conductivity type (for example, p^+ -

-213-

type) is formed in a surface region of the fourth region SC_4 , and the MIS-type-diode constituting region SC_{DT} is connected to the second region SC_2 . That is, the MIS-type-diode constituting region SC_{DT} corresponds to the

5 extending portion of the channel forming region CH_1 of the first transistor TR_1 or the extending portion of the second region SC_2 . The semiconductor memory cell shown in Fig. 88 has a constitution in which the first region SC_1 and the third region SC_3 constitute a pn junction

10 diode D , and the first region SC_1 is connected to the write-in information setting line $WISL$ through the third region SC_3 . The semiconductor memory cell shown in Fig. 89 has a constitution in which there is further provided a diode-constituting region SC_D which is formed in a

15 surface region of the first region SC_1 and is in contact with the first region SC_1 to form a rectifier junction together with the first region SC_1 , the diode-constituting region SC_D and the first region SC_1 constitute a majority carrier diode DS , and the first

20 region SC_1 is connected to the write-in information setting line $WISL$ through the diode-constituting region SC_D .

Semiconductor memory cells shown in Figs. 90 and 91 have a constitution in which the first region SC_1

25 is formed in a surface region of the second region SC_2 , a MIS-type-diode constituting region SC_{DT} having the second conductivity type (for example, p^+ -type) is formed in a buried plug form, and the MIS-type-diode constituting region SC_{DT} penetrates through the fourth

30 region SC_4 until it reaches the second region SC_2 . That is, the above MIS-type-diode constituting region SC_{DT} corresponds to the extending portion of channel forming region CH_1 of the first transistor TR_1 or the extending portion of the second region SC_2 as well. The

35 semiconductor memory cell shown in Fig. 90 also has a constitution in which the first region SC_1 and the third region SC_3 constitute a pn junction diode D , and the

-214-

first region SC_1 is connected to the write-in information setting line WISL through the third region SC_3 . The semiconductor memory cell shown in Fig. 91 has a constitution in which there is further provided a diode-constituting region SC_D which is formed in a surface region of the first region SC_1 and is in contact with the first region SC_1 to form a rectifier junction together with the first region SC_1 , the diode-constituting region SC_D and the first region SC_1 constitute a majority carrier diode DS, and the first region SC_1 is connected to the write-in information setting line WISL through the diode-constituting region SC_D .

Example 8

Example 8 is concerned with the semiconductor according to the sixth and fifteenth aspects of the present invention. As is shown in the principle drawing of Fig. 93A, the semiconductor memory cell of Example 8 comprises;

(1) a first transistor TR_1 for readout, having a first conductivity type (for example, n-channel type) and having source/drain regions, a semi-conductive channel forming region CH_1 which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate G_1 capacitively coupled with the channel forming region CH_1 ,

(2) a second transistor TR_2 for switching, having a second conductivity type (for example, p-channel type) and having source/drain regions, a semi-conductive channel forming region CH_2 which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate G_2 capacitively coupled with the channel forming region CH_2 ,

(3) a junction-field-effect transistor JF_1 for current control, having source/drain regions, a channel region CH_{J1} and gate regions, and

(4) an MIS type diode DT for retaining information.

-215-

In the above semiconductor memory cell,
one source/drain region of the first transistor
 TR_1 corresponds to the channel forming region CH_2 of the
second transistor TR_2 ,

5 the other source/drain region of the first
transistor TR_1 corresponds to one source/drain region of
the junction-field-effect transistor JF_1 ,

one source/drain region of the second transistor
 TR_2 corresponds to the channel forming region CH_1 of the
10 first transistor TR_1 and also corresponds to one gate
region of the junction-field-effect transistor JF_1 ,

one end of the MIS type diode DT is formed of an
extending portion of the channel forming region CH_1 of
the first transistor TR_1 , and the other end of the MIS
15 type diode DT is formed of an electrode EL composed of a
conductive material and is connected to the line (third
line) having a predetermined potential. In Example 8,
the first transistor TR_1 and the second transistor TR_2
are constituted of substantially separate transistors,
20 respectively.

Further, the gate G_1 of the first transistor
 TR_1 and the gate G_2 of the second transistor TR_2 are
connected to a first line (for example, word line) for
memory cell selection, the other source/drain region of
25 the first transistor TR_1 is connected to a second line
through the junction-field-effect transistor JF_1 , the
other gate region of the junction-field-effect
transistor JF_1 is connected to a fourth line, one
source/drain region of the first transistor TR_1 is
30 connected to a write-in information setting line $WISL$
through a diode D , the other source/drain region of the
second transistor TR_2 is connected to the write-in
information setting line $WISL$, and the other end of the
MIS type diode DT is connected to a third line
35 (corresponding to the above line) having a predetermined
potential through a high-resistance element R . It is
preferred to employ a constitution in which the second

-216-

line is used as a bit line, or a constitution in which the write-in information setting line WISL is used as a bit line as well and a second predetermined potential is applied to the second line.

5 As shown in the schematic partial cross-sectional view of Fig. 98, the semiconductor memory cell of Example 8 differs from the semiconductor memory cell of Example 5 in a position where the junction-field-effect transistor JF_1 is formed. That is, the
10 semiconductor memory cell of Example 8 comprises;

- (1) a first transistor TR_1 for readout, having a first conductivity type (for example, n-channel type) and having source/drain regions, a semi-conductive channel forming region CH_1 which is in contact with the
15 source/drain regions and spaces out the source/drain regions, and a gate G_1 capacitively coupled with the channel forming region CH_1 ,
- (2) a second transistor TR_2 for switching, having a second conductivity type (for example, p-channel type)
20 and having source/drain regions, a semi-conductive channel forming region CH_2 which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate G_2 capacitively coupled with the channel forming region CH_2 ,
- 25 (3) a junction-field-effect transistor JF_1 for current control, having source/drain regions, a channel region CH_{J1} and gate regions, and

- (4) an MIS type diode DT for retaining information.

The semiconductor memory cell has;

- 30 (a) a semi-conductive first region SC_1 having a second conductivity type (for example, p^+ -type),
- (b) a semi-conductive second region SC_2 which is formed in a surface region of the first region SC_1 and has a first conductivity type (for example, n^+ -type),
- 35 (c) a third region SC_3 which is formed in a surface region of the second region SC_2 and is in contact with the second region SC_2 so as to form a

-217-

rectifier junction together with the second region SC_2 , the third region SC_3 being a region which is semi-conductive and has the second conductivity type (for example, p^{++} -type) or which is formed of a silicide, a metal or a metal compound and is conductive,

(d) a semi-conductive fourth region SC_4 which is formed in a surface region of the first region SC_1 to be spaced from the second region SC_2 and has the first conductivity type (for example, n^{+} -type), and

(e) a fifth region SC_5 which is formed in a surface region of the fourth region SC_4 and is in contact with the fourth region SC_4 so as to form a rectifier junction together with the fourth region SC_4 , the fifth region SC_5 being a region which is semi-conductive and has the second conductivity type (for example, p^{++} -type) or which is formed of a silicide, a metal or a metal compound and is conductive.

Concerning the first transistor TR_1 ,

(A-1) one source/drain region is formed of a portion of a surface region of the second region SC_2 ,

(A-2) the other source/drain region is formed of a surface region of the fourth region SC_4 ,

(A-3) the channel forming region CH_1 is formed of a portion of a surface region of the first region SC_1 which portion is interposed between said portion of the surface region of the second region SC_2 and the surface region of the fourth region SC_4 , and

(A-4) the gate G_1 is formed on the channel forming region CH_1 of the first transistor TR_1 through an insulation layer.

Concerning the second transistor TR_2 ,

(B-1) one source/drain region is formed of other portion of the surface region of the first region SC_1 ,

(B-2) the other source/drain region is formed of the third region SC_3 ,

(B-3) the channel forming region CH_2 is formed of other portion of the surface region of the second region

-218-

SC₂ which other portion is interposed between said other portion of the surface region of the first region SC₁ and the third region SC₃, and

(B-4) the gate G₂ is formed on the channel forming region CH₂ of the second transistor TR₂ through an insulation layer.

Further, concerning the junction-field-effect transistor JF₁,

(C-1) the gate regions are formed of the fifth region SC₅ and part of the first region SC₁ which part is opposed to the fifth region SC₅,

(C-2) the channel region CH_{J1} is formed of part of the fourth region SC₄ which part is interposed between the fifth region SC₅ and said part of the first region SC₁,

(C-3) one source/drain region is formed of the surface region of the fourth region SC₄ which surface region extends from one end of the channel region CH_{J1} of the junction-field-effect transistor JF₁ and constitutes the other source/drain region of the first transistor TR₁, and

(C-4) the other source/drain region is formed of a portion of the fourth region SC₄ which portion extends from the other end of the channel region CH_{J1} of the junction-field-effect transistor JF₁.

Concerning the MIS type diode DT,

(D-1) one end thereof is formed of part SC_{1A} of the first region SC₁, and

(D-2) an electrode constituting the other end thereof is formed to be opposed to said part SC_{1A} of the first region SC₁ which part constitutes one end of the MIS type diode DT, through a wide gap thin film WG.

The wide gap thin film WG can be composed of a material in which the tunnel transition of carriers is caused depending upon a potential difference between the potential in the first region SC₁ (the channel forming region CH₁ of the first transistor TR₁) and the

-219-

potential in the other end (electrode EL) of the MIS type diode DT. Specifically, it can be composed, for example, of an SiO₂ or SiON film having a thickness of 5 nm or smaller, or an SiN film having a thickness of 9 nm or smaller.

The electrode EL constituting the other end of the MIS type diode DT is connected to the line (third line) through the high-resistance element R having a resistance of approximately 10^9 to 10^{12} Ω . Specifically, the electrode EL constituting the other end of the MIS type diode DT and the high-resistance element R are integrally formed and are composed of a polysilicon thin layer containing an impurity having the first conductivity type.

In the above semiconductor memory cell, further,

(E) the gate G₁ of the first transistor TR₁ and the gate G₂ of the second transistor TR₂ are connected to a first line (for example, word line) for memory cell selection,

(F) the third region SC₃ is connected to a write-in information setting line WISL,

(G) the portion of the fourth region SC₄ which portion constitutes the other source/drain region of the junction-field-effect transistor JF₁ is connected to a second line,

(H) the electrode EL constituting the other end of the MIS type diode DT is connected to a third line having a predetermined potential, and

(I) the fifth region SC₅ is connected to a fourth line.

In the semiconductor memory cell of Example 8, the second region SC₂ and the third region SC₃ constitute a pn junction diode D, and the second region SC₂ is connected to the write-in information setting line WISL through the third region SC₃. The above pn junction diode D can be formed by adjusting the impurity

-220-

concentrations of the second region SC_2 and the third region SC_3 to proper values. It is preferred to employ a constitution in which the second line is used as a bit line, or a constitution in which the write-in
 5 information setting line WISL is used as a bit line as well and a second predetermined potential is applied to the second line.

The junction-field-effect transistor JF_1 is formed by

10 (X) optimizing the distance between the facing gate regions (the fifth region SC_5 and the part of the first region SC_1 which part is opposed to the fifth region SC_5), that is, the thickness of the channel region CH_{J1} , and

15 (Y) optimizing the impurity concentration of each of the facing gate regions (the fifth region SC_5 and the part of the first region SC_1 which part is opposed to the fifth region SC_5) and the impurity concentration of the channel region CH_{J1} .

20 In Example 8, the semiconductor memory cell (specifically, the first region SC_1) is formed in a well structure which is formed, for example, in an n-type semiconductor substrate and has the second conductivity type (for example, p-type).

25 In the semiconductor memory cell of Example 8, when a first high-concentration-impurity-containing layer SC_{10} having the first conductivity type (for example, n^{++} -type) is formed below the first region SC_1 , the potential or charge to be stored in the channel
 30 forming region CH_1 of the first transistor TR_1 for readout can be increased.

In the semiconductor memory cell shown in Fig. 98, as is shown in the principle drawing of Fig. 92, there may be employed an embodiment in which the
 35 formation of the pn junction diode D is omitted and the second region SC_2 corresponding to one source/drain region of the first transistor TR_1 is connected to a

-221-

fifth line (not shown in Fig. 98). In this case, it is preferred to employ a constitution in which the second line is used as a bit line and a second predetermined potential is applied to the fifth line, or a
5 constitution in which the fifth line is used as a bit line and a second predetermined potential is applied to the second line.

Figs. 99 to 103 show variants of the semiconductor memory cell shown in Fig. 98.

10 In the semiconductor memory cell shown in the principle drawing of Fig. 93B and the schematic partial cross-sectional view of Fig. 99, there is further provided a diode-constituting region SC_D which is formed in a surface region of the second region SC_2
15 and is in contact with the second region SC_2 to form a rectifier junction together with the second region SC_2 , and the diode-constituting region SC_D and the second region SC_2 constitute a majority carrier diode DS of a Schottky junction type. One source/drain region of the
20 first transistor TR_1 is connected to the write-in information setting line WISL through the majority carrier diode DS of a Schottky junction type in place of being connected to the fifth line. That is, the second region SC_2 is connected to the write-in information
25 setting line WISL through the diode-constituting region SC_D . In the semiconductor memory cell shown in Fig. 99, the diode-constituting region SC_D is formed adjacently to the third region SC_3 , while the position of the diode-constituting region SC_D shall not be limited
30 thereto. It is preferred to employ a constitution in which the second line is used as a bit line, or a constitution in which the write-in information setting line WISL is used as a bit line as well and a second predetermined potential is applied to the second line.

35 As is shown in the principle drawings of Figs. 95A and 95B, the other gate region of the junction-field-effect transistor JF_1 may be connected to

-222-

the write-in information setting line WISL in place of being connected to the fourth line. That is, as is shown in the schematic partial cross-sectional views of Figs. 100 and 101, the fifth region SC_5 may be connected to the write-in information setting line WISL in place of being connected to the fourth line. The semiconductor memory cell shown in Fig. 10 is a variant of the semiconductor memory cell shown in Fig. 98, and the semiconductor memory cell shown in Fig. 101 is a variant of the semiconductor memory cell shown in Fig. 99.

As is shown in the principle drawing of Fig. 94, there may be employed a constitution in which the formation of the pn junction diode D is omitted and the second region SC_2 corresponding to one source/drain region of the first transistor TR_1 is connected to a fifth line (not shown in Fig. 100). In this case, it is preferred to employ a constitution in which the second line is used as a bit line and a second predetermined potential is applied to the fifth line, or a constitution in which the fifth line is used as a bit line and a second predetermined potential is applied to the second line.

In semiconductor memory cells shown in the principle drawings of Figs. 97A and 97B and the schematic partial cross-sectional views of Figs. 102 and 103, the fifth region SC_5 is connected to the first region SC_1 in place of being connected to the fourth line. That is, the other gate region of the junction-field-effect transistor JF_1 is connected to one gate region of the junction-field-effect transistor JF_1 in place of being connected to the fourth line. Further, in the semiconductor memory cell shown in the schematic partial cross-sectional view of Fig. 102, the second region SC_2 and the third region SC_3 constitute a pn junction diode D, and the second region SC_2 is connected to the write-in information setting line WISL through

-223-

the third region SC_3 . In the semiconductor memory cell shown in the schematic partial cross-sectional view of Fig. 103, there is further provided a diode-constituting region SC_D which is formed in a surface region of the second region SC_2 and is in contact with the second region SC_2 to form a rectifier junction together with the second region SC_2 , the diode-constituting region SC_D and the second region SC_2 constitute a majority carrier diode DS of a Schottky junction type, and the second region SC_2 is connected to the write-in information setting line WISL through the diode-constituting region SC_D . In the above embodiments in which the diode or the majority carrier diode is provided, it is preferred to employ a constitution in which the second line is used as a bit line, or a constitution in which the write-in information setting line WISL is used as a bit line as well and a second predetermined potential is applied to the second line.

As is shown in the principle drawing of Fig. 96, there may be employed a constitution in which the formation of the pn junction diode D is omitted and the second region SC_2 corresponding to one source/drain region of the first transistor TR_1 is connected to a fifth line (not shown in Fig. 102). In this case, it is preferred to employ a constitution in which the second line is used as a bit line and a second predetermined potential is applied to the fifth line, or a constitution in which the fifth line is used as a bit line and a second predetermined potential is applied to the second line.

Example 9

Example 9 is concerned with the semiconductor memory cell according to the sixth and sixteenth aspects of the present invention. In the semiconductor memory cell of Example 9, the other gate region of the junction-field-effect transistor JF_1 is connected to one gate region of the junction-field-

-224-

effect transistor JF_1 in place of being connected to the fourth line. More specifically, one end of the MIS type diode DT and the other gate region of the junction-field-effect transistor JF_1 are formed as a common
5 region. Further, the fifth region SC_5 constituting the other gate region of the junction-field-effect transistor JF_1 corresponds to an extending portion of the channel forming region CH_1 of the first transistor TR_1 .

10 That is, as is shown in the schematic partial cross-sectional view of Fig. 106 and the principle drawing of Fig. 105A, the semiconductor memory cell of Example 9 comprises;

(1) a first transistor TR_1 for readout, having a
15 first conductivity type (for example, n-channel type), and having source/drain regions, a semi-conductive channel forming region CH_1 which is in contact with the source/drain regions and spaces out the source/drain regions, and a gate G_1 capacitively coupled with the
20 channel forming region CH_1 ,

(2) a second transistor TR_2 for switching, having a second conductivity type (for example, p-channel type), and having source/drain regions, a semi-conductive channel forming region CH_2 which is in contact with the
25 source/drain regions and spaces out the source/drain regions, and a gate G_2 capacitively coupled with the channel forming region CH_2 ,

(3) a junction-field-effect transistor JF_1 for current control, having source/drain regions, a channel
30 region CH_{J1} and gate regions, and

(4) an MIS type diode DT for retaining information, the semiconductor memory cell having;

(a) a semi-conductive first region SC_1 having a second conductivity type (for example, p^+ -type),

35 (b) a semi-conductive second region SC_2 which is formed in a surface region of the first region SC_1 and has a first conductivity type (for example, n^+ -type),

-225-

(c) a third region SC_3 which is formed in a surface region of the second region SC_2 and is in contact with the second region SC_2 so as to form a rectifier junction together with the second region SC_2 ,
5 the third region SC_3 being a region which is semi-conductive and has the second conductivity type (for example, p^{++} -type) or which is conductive and is composed of a silicide, a metal or a metal compound,

(d) a semi-conductive fourth region SC_4 which is
10 formed in a surface region of the first region SC_1 to be spaced from the second region SC_2 and has the first conductivity type (for example, n^+ -type), and

(e) a semi-conductive fifth region SC_5 which is formed in a surface region of the fourth region SC_4 and
15 has the second conductivity type (for example, p^{++} -type).

Concerning the first transistor TR_1 ,

(A-1) one source/drain region is formed of a portion of a surface region of the second region SC_2 ,

(A-2) the other source/drain region is formed of a
20 surface region of the fourth region SC_4 ,

(A-3) the channel forming region CH_1 is formed of a portion of a surface region of the first region SC_1 which portion is interposed between said portion of the surface region of the second region SC_2 and the surface
25 region of the fourth region SC_4 , and

(A-4) the gate G_1 is formed on the channel forming region CH_1 through an insulation layer.

Concerning the second transistor TR_2 ,

(B-1) one source/drain region is formed of other
30 portion of the surface region of the first region SC_1 ,

(B-2) the other source/drain region is formed of the third region SC_3 ,

(B-3) the channel forming region CH_2 is formed of other portion of the surface region of the second region
35 SC_2 which other portion is interposed between said other portion of the surface region of the first region SC_1 and the third region SC_3 , and

-226-

(B-4) the gate G_2 is formed on the channel forming region CH_2 through an insulation layer.

Concerning the junction-field-effect transistor JF_1 ,

5 (C-1) the gate regions are formed of the fifth region SC_5 and part of the first region SC_1 which part is opposed to the fifth region SC_5 ,

(C-2) the channel region CH_{J1} is formed of part of the fourth region SC_4 which part is interposed between
10 the fifth region SC_5 and said part of the first region SC_1 ,

(C-3) one source/drain region is formed of the surface region of the fourth region SC_4 which surface region extends from one end of the channel region CH_{J1}
15 of the junction-field-effect transistor JF_1 and constitutes the other source/drain region of the first transistor TR_1 , and

(C-4) the other source/drain region is formed of a portion of the fourth region SC_4 which portion extends
20 from the other end of the channel region CH_{J1} of the junction-field-effect transistor JF_1 .

Concerning the MIS type diode DT ,

(D-1) one end thereof is formed of the fifth region SC_5 , and

25 (D-2) an electrode constituting the other end thereof is formed to be opposed to the fifth region SC_5 which constitutes one end of the MIS type diode DT , through a wide gap thin film WG .

The wide gap thin film WG can be composed of
30 a material in which the tunnel transition of carriers is caused depending upon a potential difference between the potential in the fifth region SC_5 (corresponding to the extending portion of the channel forming region CH_1 of the first transistor TR_1) and the potential in the other
35 end (electrode EL) of the MIS type diode DT .

Specifically, it can be composed, for example, of an SiO_2 or $SiON$ film having a thickness of 5 nm or smaller,

-227-

or an SiN film having a thickness of 9 nm or smaller.

The electrode EL constituting the other end of the MIS type diode DT is connected to the line (third line) through a high-resistance element R having a
5 resistance of approximately 10^9 to $10^{12} \Omega$. Specifically, the electrode EL constituting the other end of the MIS type diode DT and the high-resistance element R are integrally formed and are composed of a polysilicon thin layer containing an impurity having the first
10 conductivity type.

In the above semiconductor memory cell, further,

(E) the gate G_1 of the first transistor TR_1 and the gate G_2 of the second transistor TR_2 are connected to a
15 first line (for example, word line) for memory cell selection,

(F) the third region SC_3 is connected to a write-in information setting line WISL,

(G) the portion of the fourth region SC_4 which
20 portion constitutes the other source/drain region of the junction-field-effect transistor JF_1 is connected to a second line,

(H) the fifth region SC_5 is connected to the first region SC_1 , and

(I) the electrode EL constituting the other end of
25 the MIS type diode DT is connected to a third line having a predetermined potential.

In the semiconductor memory cell of Example 9, the second region SC_2 and the third region SC_3
30 constitute a pn junction diode D, and the second region SC_2 is connected to the write-in information setting line WISL through the third region SC_3 . The above pn junction diode D can be formed by adjusting the impurity concentrations of the second region SC_2 and the third
35 region SC_3 to proper values. It is preferred to employ a constitution in which the second line is used as a bit line, or a constitution in which the write-in

-228-

information setting line WISL is used as a bit line as well and a second predetermined potential is applied to the second line.

The junction-field-effect transistor JF_1 is
5 formed by

(X) optimizing the distance between the facing gate regions (the fifth region SC_5 and the part of the first region SC_1 which part is opposed to the fifth region SC_5), that is, the thickness of the channel
10 region CH_{J1}), and

(Y) optimizing the impurity concentration of each of the facing gate regions (the fifth region SC_5 and the part of the first region SC_1 which part is opposed to the fifth region SC_5) and the impurity concentration of
15 the channel region CH_{J1} .

In Example 9, the semiconductor memory cell (specifically, the first region SC_1) is formed in a well structure which is formed, for example, in an n-type semiconductor substrate and has the second conductivity
20 type (for example, p-type).

In the semiconductor memory cell of Example 9, when a first high-concentration-impurity-containing layer SC_{10} having the first conductivity type (for example, n^{++} -type) is formed below the first region SC_1 ,
25 the potential or charge to be stored in the channel forming region CH_1 of the first transistor TR_1 for readout can be increased.

In the semiconductor memory cell shown in Fig. 106, as is shown in the principle drawing of Fig.
30 104, there may be employed an embodiment in which the formation of the pn junction diode D is omitted and the second region SC_2 corresponding to one source/drain region of the first transistor TR_1 is connected to a fifth line (not shown in Fig. 106). In this case, it is
35 preferred to employ a constitution in which the second line is used as a bit line and a second predetermined potential is applied to the fifth line, or a

-229-

constitution in which the fifth line is used as a bit line and a second predetermined potential is applied to the second line.

In a semiconductor memory cell shown in the principle drawing of Fig. 105B and the schematic partial cross-sectional view of Fig. 107, there is further provided a diode-constituting region SC_D which is formed in a surface region of the second region SC_2 and is in contact with the second region SC_2 to form a rectifier junction together with the second region SC_2 , and the diode-constituting region SC_D and the second region SC_2 constitute a majority carrier diode DS of a Schottky junction type. One source/drain region of the first transistor TR_1 is connected to the write-in information setting line WISL through the majority carrier diode DS of a Schottky junction type in place of being connected to the fifth line. That is, the second region SC_2 is connected to the write-in information setting line WISL through the diode-constituting region SC_D . In the semiconductor memory cell shown in Fig. 107, the diode-constituting region SC_D is formed adjacently to the third region SC_3 , while the position of the diode-constituting region SC_D shall not be limited thereto. It is preferred to employ a constitution in which the second line is used as a bit line, or a constitution in which the write-in information setting line WISL is used as a bit line as well and a second predetermined potential is applied to the second line.

Example 10

Example 10 is concerned with the semiconductor memory cell according to the sixth and seventeenth aspects of the present invention. The semiconductor memory cell of Example 10 differs from the semiconductor memory cell of Example 8 in that the gate is shared by the first transistor TR_1 and the second transistor TR_2 . That is, as is shown in the schematic partial cross-sectional view of Fig. 114 or 120 and the