

Description

This invention relates to an automatic call transfer system for use in carrying out automatic transfer of a call by the use of an exchange.

A recent development of an electronic technique enables realization of various additional functions in the field of telephone exchange. Automatic transfer of a terminating call is known as one of such additional functions and serves to automatically transfer the terminating call in a limited area from a certain telephone set to another one by tracing a destination.

A conventional automatic call transfer system has been used wherein a destination directory number is manually registered into an exchange by a person when he leaves a seat assigned to him.

Another conventional system carries out automatic call transfer by the use of an automatic dialing set. With this system, a destination directory number is manually set by each person into the automatic dialing set and each call for the person in question is automatically transferred through a transfer line to a destination telephone assigned with the destination directory number.

At any rate, a manual operation should be carried out to set the destination directory number each time on occurrence of requests of transfer and is therefore troublesome for each person.

In addition, a person should have a destination directory number changed by any other person when moves among a plurality of different destinations or changes a destination on the midway. No change of the destination directory number results in wrong transfer of a call. EP-A1-0 075 123 relates to an automatic system for locating a person with a mobile communication network for use in automatically carrying out a transfer of a call to the person to be located. In this system, each person carries a transmitter transmitting a specific personal identification signal to a receiver situated in the receivable zone of the transmitter. The receiver is connected to a location information system which is part of the mobile communication network. Said location information system is connected to a call transferring means which transfers a call to a telephone set in the receivable zone of the corresponding person. From US-A-4,313,035 a method of providing person locator service for called subscribers is known. According to this method, a subscriber having assigned to him a specific person locator number may update the information stored at a centralized database concerning his location. A calling party may reach this called subscriber by using the personal number unique to this subscriber and the call is automatically completed by the system to the telephone number at the location of the subscriber stored at the central-

ized database.

When a single directory number is used in common to a plurality of persons, inconvenience takes place such that a busy time becomes long. Furthermore, the transfer operation is carried out irrespective of an emergent call or a nonemergent one.

It is an object of this invention to provide an automatic call transfer system wherein no manual operation is necessary on carrying out transfer of a call.

It is another object of this invention to provide an automatic call transfer system of the type described, which can trace a destination directory number even when a person happens to move to a different destination, changing an initial destination on the midway to the different destination.

It is still another object of this invention to provide an automatic call transfer system of the type described, wherein inconvenience does not take place even when a telephone set is used in common to a plurality of persons.

It is yet another object of this invention to provide an automatic call transfer system of the type described, wherein transfer of a call can be requested by a particular person alone to prevent a nonemergent call from being transferred.

An automatic call transfer system to which this invention is applicable is for use in automatically carrying out call transfer by the use of an exchange which is coupled through subscriber lines to telephone sets, respectively. The telephone sets are specified by line numbers corresponding to the subscriber lines, respectively, and are distributed in an area so as to be utilized by persons movable in the area. A person identification number is assigned to each of specific ones of the persons so as to identify each specific person. The system comprises a plurality of receiving means coupled to the exchange and having receivable zones into which the area is divided so that telephone sets are included in each of the receivable zones. Each of the receiving means is for receiving an identification number signal representative of the person identification number. The system further comprises signal generating means conveyed by each specific person for generating the identification number signal such that it is received by a selected one of the receiving means when each specific person is staying in the receivable zone for the selected one of said receiving means. The exchange comprises memory means coupled to the receivers for memorizing specific at least one of the line numbers of the receivable zone for the selected one of the receiving means in correspondence to the identification number signal and call transferring means coupled to the memory means and responsive to the call carrying the person

identification number for transferring the call to the telephone set specified by the specific at least one of the line numbers with reference to the memorized identification number signal and which is staying in the receivable zone for said selected one of said receiving means. According to the present invention at least two telephone sets are included in each receivable zone, the memory means memorizes at least two specific line numbers, and the call transferring means transferring the call is for further transferring the call to another one of the telephone sets that is located in the receivable zone for said selected one of said receiving means when said specific one of the line numbers is kept in a busy state. The invention is further described in the following by way of example and with reference to the drawing, in which:

Fig. 1 is a schematic block diagram of an automatic call transfer system according to a first embodiment of this invention;

Fig. 2 is a time chart for use in describing operation of a radio transmitter illustrated in Fig. 1;

Fig. 3 is a block diagram of an exchange for use in the automatic call transfer system illustrated in Fig. 1;

Fig. 4 is a flow chart for use in describing operation of the transmitter, the exchange, and a receiver which are all illustrated in Fig. 1;

Fig. 5 is a flow chart for use in describing another operation of the exchange illustrated in Fig. 3;

Fig. 6, depicted below Fig. 2, is a time chart for use in describing operation of an automatic call transfer system according to a second embodiment of this invention;

Fig. 7 is a block diagram of a radio transmitter for use in the automatic call transfer system illustrated in conjunction with Fig. 6; and

Fig. 8 is a block diagram of a radio receiver operable in cooperation with the radio transmitter illustrated in Fig. 7.

Referring to Fig. 1, an automatic call transfer system according to a first embodiment of this invention is for use in carrying out automatic call transfer by the use of an exchange 11 which will be described later and which may, for example, be a private branch exchange. The illustrated system comprises a plurality of telephone sets T_{10} , T_{11} , T_{20} , T_{21} , and T_{30} distributed in a limited area of an office, a factory, or the like. The telephone sets T (suffixes omitted) are coupled to the exchange 11 through subscriber lines L_{10} , L_{11} , L_{21} , L_{22} , and L_{30} , respectively, and assigned with directory numbers TE corresponding to line numbers LN_{10} , LN_{11} , LN_{21} , LN_{22} , and LN_{30} of the subscriber lines L_{10} through L_{30} , respectively.

It is assumed that each of the telephone sets T

is assigned or dispensed to a single person A, B, C, D, or E, and disposed at his seat, although it is usable by any other persons and that specific ones A, D, and E of the persons are given first through third person identification numbers ID_1 , ID_2 , and ID_3 peculiar thereto. The persons A, D, and E will be named first, second, and third persons, respectively. Each of the persons A to E is assumed to free to move in the area.

In the example being illustrated, the area is divided into first through third zones Z_1 , Z_2 , and Z_3 which are determined by first through third radio receivers RX_1 , RX_2 , and RX_3 , respectively. The first through third zones may partially be intersected to each other. The first through third radio receivers RX_1 , RX_2 , and RX_3 are disposed at center portions of the first through third zones Z_1 , Z_2 , and Z_3 , respectively, and are connected to the exchange 11 through selected ones L_{10} , L_{20} , and L_{30} of the subscriber lines of the first through third zones Z_1 to Z_3 . Inasmuch as the selected subscriber lines L_{10} , L_{20} , and L_{30} are also connected to the telephone sets T_{10} , T_{20} , and T_{30} , the first through third radio receivers RX_1 , RX_2 , and RX_3 are connected to the selected subscriber lines L_{10} , L_{20} , and L_{30} in parallel to the telephone sets T_{10} , T_{20} , and T_{30} . From this fact, it is readily understood that the area is divided so that at least one of the telephone sets is placed in each of the first through third zones Z_1 , Z_2 , and Z_3 .

The line numbers LN_{10} , LN_{20} , and LN_{30} for the selected subscriber lines L_{10} , L_{20} , and L_{30} may be called first, second, and third line numbers, respectively.

The first through third persons A, D, and E are possessed of first through third portable radio transmitters TX_1 , TX_2 , and TX_3 (will simply be called radio transmitters) which generate, as radio signals, first through third identification number signals representative of the first through third person identification numbers ID_1 to ID_3 , respectively. Each radio signal may be of an ultra high frequency band and is produced by the portable radio transmitters TX with electric power of, for example, 0.1 milliwatt.

Temporarily referring to Fig. 2, the portable radio transmitters TX are assumed to be equal in number to n in Fig. 2 and produce the given or assigned identification number signals (ID) as successions of first through n -th bursts, respectively. For example, the first portable radio transmitter TX_1 produces the first bursts having a first period t_1 , as illustrated along a top line TX_1 of Fig. 2. Each of the first bursts carries the first identification number signal (ID_1). The second portable radio transmitter TX_2 produces the second bursts appearing in a second period t_2 which is different from the first period t_1 . Like each of the first bursts,

each of the second bursts conveys the second identification number signal (ID_2). Likewise, the n -th bursts have an n -th period t_n inherent to the n -th bursts and carry an n -th identification number signal (ID_n).

Thus, the burst successions have different periods from one another in consideration of collision among the identification number signals (ID) in a single one of the zones Z . For example, a plurality of the burst successions illustrated in Fig. 2 collide with one another at a time instant t_0 . When the collision takes place in the same zone Z_1 , Z_2 , or Z_3 , each radio receiver RX_1 , RX_2 , or RX_3 can not receive and reproduce any identification number signals ID . However, the collision is dissolved when the next following burst is received because of the different periods of the burst successions.

Turning back to Fig. 1, each of the first through third identification number signals (ID_1) to (ID_3) can be received by the first through third receivers RX_1 to RX_3 in the first through third zones Z_1 to Z_3 . In this sense, each of the first through third zones Z_1 to Z_3 may be called a receivable zone for the radio signals, namely, the first through third identification number signals (ID_1) to (ID_3). Practically, each of the first through third zones Z_1 to Z_3 may have a radius between 5 meters and 10 meters in consideration of the electric power of the first through third radio transmitters TX_1 to TX_3 . This implies that the radio receivers may be spaced with a distance of 10-20 meters left therebetween.

With this system, the radio receivers RX transfer the person identification numbers ID (suffix omitted) as electric identification signals to the exchange 11 through the first through third subscriber lines L_{10} , L_{20} , and L_{30} in response to the radio signals carrying the first through third identification signals.

Referring to Fig. 3 together with Fig. 1, the illustrated exchange 11 accommodates the subscriber lines L (suffixes omitted) clustered into a plurality of groups G_1 , G_2 , and G_3 which are distributed to different ones of the receivable zones Z . Let the groups G_1 , G_2 , and G_3 include the subscriber lines L_{10} , L_{11} ; L_{20} , L_{21} ; and L_{30} (Fig. 1) connected to the telephone sets of the first through third zones Z_1 to Z_3 , respectively. The exchange 11 also accommodates a plurality of external lines EXT , such as main wires, connected to another exchange or the like.

As is known in the art, the exchange 11 comprises a central control unit (CC) 21 and a switch or line unit 22 operable under control of the central control unit 21 to connect or disconnect the subscriber lines L , the external lines, and the like.

In Fig. 3, the exchange 11 further comprises a subscriber memory 25 for temporarily memorizing status of each subscriber. The illustrated subscrib-

er memory 25 is connected to the central control unit 21 and the switch unit 22 through buses and has a line number (LN) area 26 and an identification (ID) memory area 27. The line number area 26 has first local addresses which correspond to the line numbers LN , respectively, and which are loaded in a known manner with electric signals necessary for the exchange 11. The identification memory area 27 has second local addresses which correspond to the person identification numbers ID , respectively, and each of which is loaded with the line numbers LN assigned to the subscriber lines L . Each line number LN in the identification memory area 27 specifies a neighboring one of the subscriber lines, namely, telephone sets near to each person. Thus, the person identification numbers ID are made to correspond to the line numbers in the identification memory area 27. It is therefore possible to detect each position of the specific persons by searching the identification memory area 27 by the use of the person identification numbers ID and by reading the line numbers LN out of the identification number area 27.

The illustrated exchange 11 further comprises an identification number receiver ($ID\ REC$) 31 for receiving the identification number signals (ID) and first and second talkie units or trunks, namely, audio response units or trunks TK_1 and TK_2 which are operable in a manner to be described later.

Referring to Fig. 4 together with Figs. 1 through 3, operation of the system will be exemplified in connection with the first person A which is given the first identification number ID_1 and his seat in the first zone Z_1 , as illustrated in Fig. 1. The first zone Z_1 may be called a home zone for the first person A. The first person A always has the first radio transmitter TX_1 with him either in his pocket or otherwise. The first identification number ID_1 is generated in the manner described with reference to Fig. 2 by the first radio transmitter TX_1 as the radio signal, as illustrated at a transmitter step TS_1 in Fig. 4.

The radio signal representative of the first identification number ID_1 is received by the first radio receiver RX_1 placed in the first zone Z_1 as long as the first person A is present in his own seat, as shown at a first receiver step RS_1 in Fig. 4. As previously mentioned in conjunction with Fig. 2, the first identification number ID_1 is carried by each burst intermittently appearing at the first period t_1 . On reception of the first identification number ID_1 only one time, the first person A in question may happen to merely pass by and may not be staying in the first zone Z_1 .

In order to confirm stay of the first person A in the first zone Z_1 , the first radio receiver RX_1 monitors whether or not the first identification number ID_1 is consecutively received twice or more, as

shown at a second receiver step RS_2 in Fig. 4. When the first identification number ID_1 is successively received plural times, the second step RS_2 proceeds to a third receiver step RS_3 . Otherwise, the second receiver step RS_2 returns back to the first step RS_1 .

At the third receiver step RS_3 , the first radio receiver RX_1 judges whether or not the first identification number ID_1 was already registered in the first radio receiver RX_1 . If the first identification number ID_1 is not registered in the first radio receiver RX_1 yet, the first radio receiver RX_1 registers the first identification number ID_1 at a fourth receiver step RS_4 through the subscriber line L_{10} .

When the first identification number ID_1 was already registered in the first radio receiver RX_1 , the first radio receiver RX_1 must monitor whether or not the registered number, namely, the first identification number ID_1 is to be erased or released from the exchange 11 because the first person A may move from the first zone Z_1 to another one. For this purpose, the first radio receiver RX_1 supervises lapse of a first predetermined duration T_1 by the use of a timer (not shown) at a fifth receiver step RS_5 . The first predetermined duration T_1 may be, for example, one minute.

After lapse of the predetermined duration T_1 , the fifth receiver step RS_5 is followed by a sixth receiver step RS_6 at which the receiver RX_1 judges whether or not the first identification number ID_1 is being received by the first radio receiver RX_1 . On reception of the first identification number ID_1 , the sixth receiver step RS_6 returns back to the first receiver step RS_1 . Otherwise, the sixth receiver step RS_6 is followed by a seventh receiver step RS_7 at which the first radio receiver RX_1 sends the exchange 11 an erasure signal indicative of erasure of the registered, namely, first identification number.

In Fig. 4, the exchange 11 is put into a standby or waiting state at a first exchange step ES_1 for awaiting reception of any electric identification number signals representative of the person identification numbers ID . At a second exchange step ES_2 following the first exchange step ES_1 , the exchange 11 receives the first identification number ID_1 at the identification number receiver (ID REC) 31 (Fig. 3) thereof. The central control unit 21 is operated at a third exchange step ES_3 in a known manner to detect the line number of the subscriber line through which the first identification number ID_1 is received. In the example being illustrated, the line number LN_{10} of the subscriber line L_{10} is detected by the central control unit 21.

After detection of the line number LN_{10} , the central control unit 21 detects whether or not the received identification number, namely, ID_1 is sent

from the home zone Z_1 , as shown at a fourth exchange step ES_4 . If the first identification number ID_1 is sent from the home zone Z_1 , the central control unit 21 accesses the identification memory area 27 (Fig. 3) at a fifth exchange step ES_5 to memorize the line number LN_{10} in a specific one of the second memory addresses that is assigned to the first identification number ID_1 . Thus, the line number LN_{10} for the first person A is memorized in the identification number memory 27 in correspondence to the first identification number ID_1 for the first person A as long as he is staying in the first or home zone Z_1 .

On the other hand, when the first identification number ID_1 is not sent from the first or home zone Z_1 , the specific address for the first identification number ID_1 is loaded at a sixth exchange step ES_6 with a selected one of the line numbers which are assigned to each of the remaining zones, namely, the second or the third zones Z_2 or Z_3 . The selected line number may be, for example, a pilot number of each zone. In the example being illustrated, the line numbers LN_{20} and LN_{30} are memorized in the specific address for the first identification number ID_1 when the first person A is staying in the second and the third zones Z_2 and Z_3 , respectively.

At a seventh exchange step ES_7 , the central control unit 21 judges whether or not the erasure signal is sent from the first radio receiver RX_1 to erase contents of the specific address which are related to the first identification number ID_1 . Responsive to the erasure signal, the central control unit 21 erases the contents of the specific address, as shown at an eighth exchange step ES_8 .

The erasure signal is produced either during a short absence of the first person A or during his long absence. During the short absence, the first person A may be in course of moving from one zone to another. During the long absence, the first person A is probably absent from the limited area. Under the circumstances, registration is made at a ninth exchange step ES_9 in the specific address for the first identification number ID_1 to indicate that the first person A is in course of movement. After the registration, the central control unit 21 times a second predetermined duration T_2 of, for example, five minutes at a tenth exchange step ES_{10} .

Lapse of the second predetermined duration T_2 may regard the first person A as absent from the limited area. In the example, the central control unit 21 detects presence or absence of a request for registration related to the first identification number ID_1 at an eleventh exchange step ES_{11} after lapse of the second predetermined duration T_2 . Thereafter, the central control unit 21 registers absence of the first person A in the specific address for the first identification number ID_1 at a twelfth exchange

step ES₂.

After registration of absence, the twelfth exchange step ES₁₂ is followed by the second exchange step ES₂ mentioned before.

It is readily understood from the above that the line number LN₁₀ for the telephone set T₁₀ is memorized in the specific address assigned to the first identification number ID₁ as long as the specific person A is present in the first zone Z₁.

Let the first person A leave his seat and meet another person C in the second zone Z₂ to make arrangements with him. In this event, the radio signal generated by the first radio transmitter TX₁ can not be received by the first radio receiver RX₁ because it is very weak in intensity as mentioned before when the first person A arrives at the seat of another person C. Instead, the second radio receiver TX₂ in the second zone Z₂ receives the radio signal of the first radio transmitter TX₁. Inasmuch as the second radio receiver TX₂ and the telephone set T₂₀ are connected to the subscriber line L₂₀ in common, the first identification number ID₁ is sent through the subscriber line L₂₀ to the exchange 11. When the first identification number ID₁ is detected from the radio signal twice or more in the manner illustrated in conjunction with Fig. 4, the identification memory area 27 is renewed from the line number LN₁₀ into the line number LN₂₀ at the specific address assigned to the first identification number ID₁.

This means that a terminating call for the first person A is transferred to the telephone set T₂₀ placed at the seat of the second person D while the first person A is staying in the second zone Z₂. In other words, the terminating call for the first person A is not transferred to the telephone set T₂₁ placed at the seat of the person C talking with the first person A. However, no problem might occur because each zone is very narrow.

Thus, the identification memory area 27 is successively and automatically renewed at the specific address assigned to the first identification number ID₁ as the first person A moves in the limited area. Similar operation is carried out as regards the second and the third persons D and E.

From the above, it is readily understood that the identification memory area 27 is renewed only when each specific person changes the zones from one to another. Accordingly, it is possible to prevent the subscriber lines, such as L₁₀, L₂₀, and L₃₀, from being occupied by the radio receivers for a long time. Consequently, usual communication is also carried out through the subscriber lines L₁₀, L₂₀ and L₃₀.

Referring to Fig. 5 afresh and Figs. 1 and 3 again, operation of the central control unit 21 will be described on the assumption that the exchange 11 receives a terminating call through one of the

subscriber lines L and the external lines EXT, as shown at a first processing step PS₁ in Fig. 5. The terminating call is accompanied either by a directory number TEL or by a person identification number ID. If the directory number TEL is detected at a second processing step PS₂, the central control unit 21 rings one of the telephone sets that is indicated by the directory number TEL, as shown at a third processing step PS₃.

If the terminating call carries the person identification number ID, the central control unit 21 accesses the identification memory area 27 at a fourth processing step PS₄ to detect contents of an address assigned to the person identification number ID at a fifth processing step PS₅. When the contents of the address in question are indicative of the fact that the person for the person identification number ID is in course of moving, as illustrated at the ninth exchange step ES₉, the central control unit 21 energizes the first talkie unit TK₁ (Fig. 3) at a sixth processing step PS₆. The first talkie unit TK₁ gives information upon a short absence in the form of an audio signal.

Unless the person under consideration is in course of movement, the fifth processing step PS₅ is followed by a seventh processing step PS₇ at which the central processing unit 21 judges whether or not he is absent from the limited area. When absence of the person is registered in the manner illustrated in conjunction with the twelfth exchange step ES₁₂ of Fig. 4, the second talkie unit TK₂ is energized to give information upon a long absence of the person assigned with the person identification number ID in question at an eighth processing step PS₈. Otherwise, the seventh processing step PS₇ is succeeded by a ninth processing step PS₉ at which the line number LN is detected from the contents of the address for the person identification number ID.

The central control unit 21 judges at a tenth processing step PS₁₀ whether or not the subscriber line L specified by the line number LN is put into a busy state. Unless the subscriber line LN is busy, the central control unit 21 rings one of the telephone sets that is placed in a destination one of the zones Z and is connected to the subscriber line LN in the destination zone, as shown at an eleventh processing step PS₁₁.

In the example being illustrated, the telephone sets in the destination zone are successively searched to detect an idle one of the telephone sets in the order of priority predetermined in the destination zone when one of the telephone sets in the destination zone is put into a busy state. For this purpose, the central control unit 21 matches states of the subscriber lines L included in the destination zone in the order of the priority. For example, judgement is made at a twelfth process-

ing step PS₁₂ to indicate whether or not the subscriber line of second priority is busy. Similarly, judgement is made as regards the subscriber line of third priority at a thirteenth processing step PS₁₃.

At any rate, one of the telephone sets is rung in the destination zone at the eleventh processing step PS₁₁. If an idle one of the subscriber lines L is found out. Thus, a destination of each specific person is automatically sought by the central control unit 21 with reference to each person identification number ID to ring a neighboring one of the telephone sets through the switch unit 22. When all of the subscriber lines L are regarded as busy at a fourteenth processing step PS₁₄, a busy tone is produced as shown at a fifteenth processing step PS₁₅. Thus, a combination of the central control unit 21 and the switch unit 22 serves to transfer the terminating call and may be called a call transfer member.

From the above, it is readily understood that the above-mentioned call transfer is carried out only when one of the person identification numbers ID is given to the exchange 11. If a particular one of persons is informed of the one of the person identification numbers assigned to a specific person and calls the specific person by the use of the one person identification number only in case of emergency, an emergent call alone is favorably transferred to the specific person. In addition, the call transfer is carried out without any manual operation.

Referring to Figs. 6, 7, and 8, an automatic call transfer system according to a second embodiment of this invention carries out automatic call transfer by the use of first through n-th burst successions as illustrated along top through bottom lines TX₁ to TX_n of Fig. 6. More particularly, each burst succession has a pair of bursts each of which carries a person identification number assigned to each specific person. The bursts of each pair consist of a leading and a trailing one.

The illustrated leading bursts of each burst succession are repeated at a period peculiar to the burst succession, like the burst successions illustrated in Fig. 2. Therefore, the first burst succession illustrated along the top line TX₁ of Fig. 6 includes the leading bursts appearing in the first period t_1 as shown in Fig. 2. Likewise, the second through n-th burst successions TX₂ to TX_n include the leading bursts having the second through n-th periods t_2 to t_n , respectively.

The leading bursts of each burst succession are followed by the trailing bursts spaced apart from the leading ones with a time interval Δt_1 , Δt_2 , ..., up to Δt_n left therebetween. The time intervals Δt_1 through Δt_n are inherent to the burst successions TX₁ to TX_n, respectively, and shorter than the

periods, respectively. Thus, each burst succession has the period, such as t_1 , t_2 , ..., or t_n , and the time interval, such as Δt_1 , Δt_2 , ..., or Δt_n , peculiar thereto.

Let the leading bursts of the first through n-th burst successions happen to appear in a single zone simultaneously with one another at a time instant t_n in Fig. 6. In this event, the radio receiver RX can not distinguish the person identification numbers ID from one another. However, the radio receiver can receive each person identification number twice after both of each time interval Δt (suffixes omitted) and each period t . The person identification numbers are therefore rapidly detected twice or more from each burst succession in comparison with the burst successions illustrated in Fig. 2.

In Fig. 7, each radio transmitter TX comprises first and second timers 36 and 37 for measuring each period t and each time interval Δt both of which are peculiar to the burst succession, respectively. The first and second timers 36 and 37 are always energized by a battery 39 to produce a succession of first pulses P_1 at each period t and a succession of second pulses P_2 appearing when each time interval Δt lapses after the first pulses P_1 . The first and the second pulses P_1 and P_2 last during the bursts.

A switch 41 is closed during presence of the first and the second pulses P_1 and P_2 to intermittently connect the battery 39 to an identification signal circuit 43. The identification signal circuit 43 comprises an identification (ID) number generator 45, a modulator 46, and an amplifier 47, which are all simultaneously energized by the battery 39. The person identification number is intermittently generated by the identification number generator 45 and is subjected to modulation and amplification by the modulator 46 and the amplifier 47 to be produced as a radio signal through an antenna 48.

The radio signal is received by a radio receiver RX illustrated in Fig. 8 and is sent through a reception antenna 51 to a decoding circuit 52 to be decoded into a decoded signal representative of the person identification number ID. The decoded signal is memorized in an identification number memory 53 and is counted by a counter 54 which is counted up at every reception of the decoded signal. When the same decoded signal is received twice or more, the identification number memory 53 sends the decoded signal through a sender 56 and a selector 57 to one of the subscriber lines indicated at L_{a1} , L_{a2} , ..., and L_{am} .

A busy detector 59 is coupled to the sender 56 and the selector 57. The busy detector 59 successively searches the subscriber lines L_{a1} to L_{am} to detect an idle one of the subscriber lines L_{a1} to L_{am} . On detection of the idle subscriber line, the

busy detector 59 connects the selector 57 to the idle subscriber line. As a result, the decoded signal carrying the person identification number is sent through the idle subscriber line to the exchange 11. The illustrated radio receiver RX is assigned with a plurality of the subscriber lines L_{a1} to L_{am} .

As mentioned before, the terminating call is automatically transferred to each of the specific persons given the person identification numbers even when each specific person frequently changes a destination from one to another in the limited area and even when each specific person forgets to inform of change of the destination. In addition, the above-mentioned call transfer can be individually carried out about each of persons to which a single telephone is dispensed, when the different person identification numbers are assigned to the respective persons.

The periods t_1 through t_n of the bursts may be decided in consideration of the number of the specific persons, areas of the zones, and electric power of the radio transmitters. Preferably, the periods t are longer than a time necessary for passing through each zone. Anyway, production of the bursts results in a reduction of electric power consumption in each radio transmitter TX.

In addition, each of the radio receivers may convert the person identification number ID into an electric signal of a frequency band higher than an audio frequency band. The electric signal may thereafter be subjected to demodulation by the exchange 11 to be rendered into the audio frequency band. Instead of searching an idle of the subscriber lines, an offering connection may be made to preferentially carry out call transfer on reception of a terminating call when a subscriber line in question is busy.

While this invention has thus far been described in conjunction with a few embodiments thereof, it will readily be possible for those skilled in the art to put this invention into practice in various other manners. For example, each radio receiver may directly transfer the received person identification numbers ID to the exchange 11 without passing through the identification memory 53 as illustrated in Fig. 8. In this event, the central control unit 21 should carry out operations as illustrated at the second through seventh receiver steps RS_2 to RS_7 (Fig. 4) instead of the radio receivers RX, although the subscriber lines L_{10} , L_{20} , and L_{30} may be occupied by the radio receivers RX for a long time. The radio receivers RX may not always be connected in parallel to the telephone sets, such as T_{10} , T_{20} , and T_{30} , but may be connected through exclusive lines. The bursts illustrated in Figs. 2 and 6 may be variable in their periods and time intervals to avoid concurrent occurrence of the bursts. In lieu of the bursts, the person identifica-

tion numbers ID may be produced in a frequency division fashion when the exchange 11 has a comparatively small capacity and may be continuously produced by each radio transmitter. The exchange may not be a private branch exchange. When the receivable zones Z_1 , Z_2 , and Z_3 are partially intersected to one another, each person identification number may be received by a plurality of the radio receivers RX. If an intersected portion includes the home zone, the person identification number may be registered in the home zone in preference to the other zone or zones. If no home zone is included in the intersected portion, the person identification number may be registered in one of the receivable zones that receives a new one of the person identification numbers. The receivable zones may not always cover the whole of the limited area because the short absence can be indicated in the illustrated system.

Furthermore, ultrasonic waves may be used to couple the transmitters TX to the receivers RX instead of the radio signals. An inductive radio method may be used to couple the transmitters TX and the receivers RX.

In any event, no manual operation is necessary to register each line number of the destination zone because each line numbers is successively and automatically memorized and renewed in the identification memory area 27.

Claims

1. An automatic call transfer system for use in automatically carrying out transfer of a call by the use of an exchange which is coupled through subscriber lines to telephone sets, respectively, said telephone sets being specified by line numbers corresponding to said subscriber lines, respectively, and being distributed in an area so as to be utilized by persons movable in said area, wherein

a person identification number is assigned to each of specific ones of said persons so as to identify said each specific person;

said system comprising:

a plurality of receiving means (RX) coupled to said exchange and being associated with receivable zones into which said area is divided, telephone sets being included in the receivable zones, each of said receiving means being for receiving an identification number signal representative of said person identification number; and

signal generating means (TX) conveyed by

busy detector 59 connects the selector 57 to the idle subscriber line. As a result, the decoded signal carrying the person identification number is sent through the idle subscriber line to the exchange 11. The illustrated radio receiver RX is assigned with a plurality of the subscriber lines L_{a1} to L_{am} .

As mentioned before, the terminating call is automatically transferred to each of the specific persons given the person identification numbers even when each specific person frequently changes a destination from one to another in the limited area and even when each specific person forgets to inform of change of the destination. In addition, the above-mentioned call transfer can be individually carried out about each of persons to which a single telephone is dispensed, when the different person identification numbers are assigned to the respective persons.

The periods t_1 through t_n of the bursts may be decided in consideration of the number of the specific persons, areas of the zones, and electric power of the radio transmitters. Preferably, the periods t are longer than a time necessary for passing through each zone. Anyway, production of the bursts results in a reduction of electric power consumption in each radio transmitter TX.

In addition, each of the radio receivers may convert the person identification number ID into an electric signal of a frequency band higher than an audio frequency band. The electric signal may thereafter be subjected to demodulation by the exchange 11 to be rendered into the audio frequency band. Instead of searching an idle of the subscriber lines, an offering connection may be made to preferentially carry out call transfer on reception of a terminating call when a subscriber line in question is busy.

While this invention has thus far been described in conjunction with a few embodiments thereof, it will readily be possible for those skilled in the art to put this invention into practice in various other manners. For example, each radio receiver may directly transfer the received person identification numbers ID to the exchange 11 without passing through the identification memory 53 as illustrated in Fig. 8. In this event, the central control unit 21 should carry out operations as illustrated at the second through seventh receiver steps RS₂ to RS₇ (Fig. 4) instead of the radio receivers RX, although the subscriber lines L_{10} , L_{20} , and L_{30} may be occupied by the radio receivers RX for a long time. The radio receivers RX may not always be connected in parallel to the telephone sets, such as T_{10} , T_{20} , and T_{30} , but may be connected through exclusive lines. The bursts illustrated in Figs. 2 and 6 may be variable in their periods and time intervals to avoid concurrent occurrence of the bursts. In lieu of the bursts, the person identifica-

tion numbers ID may be produced in a frequency division fashion when the exchange 11 has a comparatively small capacity and may be continuously produced by each radio transmitter. The exchange may not be a private branch exchange. When the receivable zones Z_1 , Z_2 , and Z_3 are partially intersected to one another, each person identification number may be received by a plurality of the radio receivers RX. If an intersected portion includes the home zone, the person identification number may be registered in the home zone in preference to the other zone or zones. If no home zone is included in the intersected portion, the person identification number may be registered in one of the receivable zones that receives a new one of the person identification numbers. The receivable zones may not always cover the whole of the limited area because the short absence can be indicated in the illustrated system.

Furthermore, ultrasonic waves may be used to couple the transmitters TX to the receivers RX instead of the radio signals. An inductive radio method may be used to couple the transmitters TX and the receivers RX.

In any event, no manual operation is necessary to register each line number of the destination zone because each line numbers is successively and automatically memorized and renewed in the identification memory area 27.

Claims

1. An automatic call transfer system for use in automatically carrying out transfer of a call by the use of an exchange which is coupled through subscriber lines to telephone sets, respectively, said telephone sets being specified by line numbers corresponding to said subscriber lines, respectively, and being distributed in an area so as to be utilized by persons movable in said area, wherein

a person identification number is assigned to each of specific ones of said persons so as to identify said each specific person;

said system comprising:

a plurality of receiving means (RX) coupled to said exchange and being associated with receivable zones into which said area is divided, telephone sets being included in the receivable zones, each of said receiving means being for receiving an identification number signal representative of said person identification number; and

signal generating means (TX) conveyed by



said each specific person for generating said identification number signal such that it is received by a selected one of said receiving means when said each specific person is staying in the receivable zone for said selected one of said receiving means;

said exchange comprising:

memory means (25) coupled to said receiving means for memorizing a specific line number of the receivable zone for said selected one of said receiving means in correspondence to said identification number signal; and

call transferring means (21) coupled to said memory means and responsive to the call carrying said person identification number for transferring the call to the telephone set which is specified by said specific line numbers with reference to the memorized identification number signal and which is staying in the receivable zone for said selected one of said receiving means,

characterized in

- a) that at least two telephone sets are included in each receivable zone,
- b) that the memory means (25) memorizes at least two specific line numbers, and
- c) that the call transferring means (21) transferring the call is for further transferring the call to another one of the telephone sets that is located in the receivable zone for said selected one of said receiving means when said specific one of the line numbers is kept in a busy state (PS10 to PS13).

2. An automatic call transfer system as claimed in Claim 1, wherein said signal generating means (TX) produces said identification number signal in the form of a radio signal while each of said receiving means (RX) produces an electric identification signal representative of said person identification number in response to said radio signal.

3. An automatic call transfer system as claimed in Claim 2, wherein said signal generating means (TX) comprises:

burst producing means (45) for producing a succession of bursts each of which carries said identification number signal and has a predetermined period peculiar to said person identification number; and

means (46, 47, 48) for producing said suc-

cession as said radio signal.

4. An automatic call transfer system as claimed in Claim 2, wherein said signal generating means (TX) comprises:

burst pair producing means (45) for repeatedly producing a pair of bursts each of which carries said person identification number, said bursts of each pair appearing with a burst interval left therebetween and being specific to said person identification number; and

means (46, 47, 48) for producing said pair of bursts as said radio signal.

5. An automatic call transfer system as claimed in any of claims 2 to 4, wherein each of said receiving means (RX) comprises:

local memory means (53) for memorizing said electric identification signal; and

sending means (56) for sending said memorized electric identification signal to said exchange only on occurrence of variation of the person identification number conveyed by said radio signal.

6. An automatic call transfer system as claimed in Claim 5, wherein each of said receiving means further comprises:

monitoring means (59) coupled to said sending means and the subscriber lines for each receivable zone for monitoring the subscriber lines to detect an idle one of the subscriber lines and to deliver said memorized electric identification signal to said idle subscriber line.

7. An automatic call transfer system as claimed in any of claims 1 to 6, wherein said signal generating means (TX) is coupled to each of said receivers (RX) by the use of ultrasonic waves.

Revendications

1. Système automatique de transfert d'appel pour utilisation dans la réalisation de manière automatique de transfert d'un appel par l'utilisation d'un central qui est couplé par l'intermédiaire de lignes d'abonné à des postes téléphoniques, respectivement, les postes téléphoniques étant spécifiés par des numéros de ligne correspondant aux lignes d'abonné respectivement, et étant répartis dans une zone qui peut être utilisée par des personnes se déplaçant dans la zone, dans lequel

un numéro d'identification de personne est affecté à chaque personne des personnes spécifiques de façon à identifier chaque personne



spécifique ;

le système comprenant :

une multitude de moyens de réception (RX) couplés au central et étant associés à des zones qui peuvent recevoir, dans lesquelles la surface est divisée, des postes téléphoniques étant compris dans les zones qui peuvent recevoir, chacun des moyens de réception servant à recevoir un signal de numéro d'identification représentatif du numéro d'identification de la personne ; et

un moyen de génération de signaux (TX) véhiculé par chaque personne spécifique pour produire le signal de numéro d'identification de sorte qu'il est reçu par un moyen sélectionné des moyens de réception lorsque chaque personne spécifique se trouve dans la zone qui peut recevoir pour le moyen sélectionné des moyens de réception ;

le central comprenant :

un moyen de mémoire (25) couplé aux moyens de réception pour mémoriser un numéro de ligne spécifique de la zone qui peut recevoir pour le moyen sélectionné des moyens de réception en correspondance au signal de numéro d'identification ; et

un moyen de transfert d'appel (21) couplé au moyen de mémoire et sensible à l'appel véhiculant le numéro d'identification de personne pour transférer l'appel vers le poste téléphonique qui est spécifié par les numéros de ligne spécifiques par référence au signal de numéro d'identification mémorisé et qui se trouve dans la zone qui peut recevoir pour le moyen sélectionné des moyens de réception, caractérisé en ce que

a) au moins deux postes téléphoniques sont compris dans chaque zone qui peut recevoir,

b) le moyen de mémoire (25) mémorise au moins deux numéros de ligne spécifiques, et

c) que le moyen de transfert d'appel (21) transférant l'appel est destiné à transférer de plus l'appel à un autre poste des postes téléphoniques qui est situé dans la zone qui peut recevoir pour le moyen sélectionné des moyens de réception lorsque le numéro de ligne spécifique des numéros de ligne reste dans un état d'occupation (PS₁₀ à PS₁₃).

2. Système automatique de transfert d'appel selon la revendication 1, dans lequel le moyen de génération de signal (TX) produit le signal de numéro d'identification sous la forme d'un signal radio tandis que chacun des moyens de réception (RX) produit un signal d'identification

électrique représentatif du numéro d'identification de la personne en réponse au signal radio.

3. Système automatique de transfert d'appel selon la revendication 2, dans lequel le moyen de génération de signal (TX) comprend :

un moyen de production de paquets (45) pour produire une suite de paquets dont chacun véhicule le signal de numéro d'identification et présente une période particulière prédéterminée au numéro d'identification de personne ; et

un moyen (46, 47, 48) pour produire la suite comme signal radio.

4. Système automatique de transfert d'appel selon la revendication 2, dans lequel le moyen de génération de signal (TX) comprend :

un moyen de production de paire de paquets (45) pour produire de manière répétée une paire de paquets dont chacun véhicule le numéro d'identification de personne, les paquets de chaque paire apparaissant avec un intervalle de paquet laissé entre eux et étant spécifique au numéro d'identification de personne ; et

un moyen (46, 47, 48) pour produire la paire de paquets comme signal radio.

5. Système automatique de transfert d'appel selon l'une quelconque des revendications 2 à 4, dans lequel chacun des moyens de réception (RX) comprend :

un moyen de mémoire locale (53) pour mémoriser le signal d'identification électrique ; et

un moyen d'envoi (56) pour envoyer le signal d'identification électrique mémorisé vers le central seulement sur la présence d'un changement du numéro d'identification de personne véhiculé par le signal radio.

6. Système automatique de transfert d'appel selon la revendication 5, dans lequel chacun des moyens de réception comprend de plus :

un moyen de surveillance (59) couplé au moyen d'envoi et aux lignes d'abonné pour chaque zone qui peut recevoir pour surveiller les lignes d'abonné afin de détecter une ligne libre parmi les lignes d'abonné et pour délivrer le signal d'identification électrique mémorisé à la ligne d'abonné libre.

7. Système automatique de transfert d'appel selon l'une quelconque des revendications 1 à 6, dans lequel le moyen de génération de signal (TX) est couplé à chacun des récepteurs (RX) par l'utilisation d'ondes ultrasonores.



Patentansprüche

1. Automatisches Anrufweiterleitungssystem zur Verwendung beim automatischen Durchführen einer Anrufweiterleitung mittels einer Vermittlung, die über Teilnehmerleitungen jeweils mit Telefonapparaten verbunden ist, wobei die Telefonnummern mit den Leitungsnummern, die jeweils den Teilnehmerleitungen entsprechen, bestimmt werden und in einem Bereich verteilt sind, so daß diese von Personen, die sich in diesem Bereich bewegen, genutzt werden können, wobei

eine Personenidentifikationsnummer jeder der bestimmten Personen zugeordnet wird, so daß diese bestimmte Person identifizierbar ist,

das System aufweist:

mehrere Empfangseinrichtungen (RX), die mit der Vermittlung verbunden sind und zu Empfangszonen, in die der Bereich unterteilt ist, zugeordnet sind, Telefonapparate in diesen Empfangszonen vorhanden sind, jede der Empfangseinrichtungen zum Empfangen eines Identifikationsnummersignals dient, daß die Personenidentifikationsnummer darstellt und

Signalerzeugungseinrichtungen (TX), die von jeder bestimmten Person mitgeführt werden, zum Erzeugen des Identifikationsnummersignals, das von einer der ausgewählten Empfangseinrichtungen empfangen wird, wenn sich jede bestimmte Person in der Empfangszone dieser ausgewählten Empfangseinrichtung aufhält,

die Vermittlung aufweist:

eine Speichereinrichtung (25), die mit den Empfangseinrichtungen verbunden ist, zum Speichern einer bestimmten Leitungsnummer der Empfangszone für die ausgewählte Empfangseinrichtung entsprechend dem Identifikationsnummersignal, und

eine Anrufweiterleitungseinrichtung (21), die mit der Speichereinrichtung verbunden ist und auf den Anruf anspricht, mit der die Personenidentifikationsnummer trägt, zum Weiterleiten des Anrufs an den Telefonapparat, der durch die bestimmten Leitungsnummern mit Bezug auf das gespeicherte Identifikationsnummersignal bezeichnet und die sich in der Empfangszone für die ausgewählte Empfangseinrichtung aufhält,

dadurch gekennzeichnet,

a) daß mindestens zwei Telefonapparate in jeder Empfangszone vorhanden sind,
b) daß die Speichereinrichtung (25) mindestens zwei bestimmte Leitungsnummern speichert und
c) daß die Anrufweiterleitungseinrichtung (21) zum Weiterleiten des Anrufers diesen Anruf an einen anderen der Telefonapparate weiterleitet, der in der Empfangszone für die ausgewählte Empfangseinrichtung angeordnet ist, wenn die eine bestimmte Leitungsnummer in einem Besetzungszustand (PS10 bis PS13) gehalten wird.

2. Automatisches Anrufweiterleitungssystem nach Anspruch 1, wobei die Signalerzeugungseinrichtung (TX) das Identifikationsnummersignal in der Form eines Funksignals erzeugt während jede der Empfangseinrichtungen (RX) ein elektrisches Identifikationssignal, das die Personenidentifikationsnummer darstellt, in Abhängigkeit von dem Funksignal erzeugt.

3. Automatisches Anrufweiterleitungssystem nach Anspruch 2, wobei die Signalerzeugungseinrichtung (TX) aufweist:

eine Impulsfolgeerzeugungseinrichtung (45) zum Erzeugen einer Folge von Impulsfolgen, die jeweils das Identifikationsnummersignal tragen und eine bestimmte für die Personenidentifikationsnummer einzigartige Zeitdauer haben und

Einrichtungen (46, 47, 48) zum Erzeugen dieser Folge als das Funksignal.

4. Automatisches Anrufweiterleitungssystem nach Anspruch 2, wobei die Signalerzeugungseinrichtung (TX) aufweist:

eine Impulsfolge-Paar-Erzeugungseinrichtung (45) zum wiederholten Erzeugen eines Pulsfolgepaars, das jeweils die Personenidentifikationsnummer trägt, wobei die Impulsfolgen jedes Paares mit einem zwischen ihnen liegenden Impulsfolgeintervall auftreten, der für die Personenidentifikationsnummer bestimmt ist und

Einrichtungen (46, 47, 48) zum Erzeugen dieses Impulsfolgepaars als das Funksignal.

5. Automatisches Anrufweiterleitungssystem nach einem der Ansprüche 2 bis 4, wobei jede der Empfangseinrichtungen (RX) aufweist:



eine lokale Speichereinrichtung (53) zum Speichern des elektrischen Identifikationssignals, und

5

eine Sendeeinrichtung (56), die das gespeicherte elektrische Identifikationssignal nur beim Auftreten einer Veränderung der Personenidentifikationsnummer, die von dem Funksignal getragen wird, an die Vermittlung sendet.

10

6. Automatisches Anrufweiterleitungssystem nach Anspruch 5, wobei jede der Empfangseinrichtungen ferner aufweist:

15

eine Überwachungseinrichtung (59), die mit der Sendeeinrichtung und den Teilnehmerleitungen für jede Empfangszone verbunden ist, zum Überwachen der Teilnehmerleitungen, so daß eine freie Teilnehmerleitung erkannt wird und das gespeicherte elektrische Identifikationssignal an die freie Teilnehmerleitung geliefert wird.

20

7. Automatisches Anrufweiterleitungssystem nach einem der Ansprüche 1 bis 6, wobei die Signalerzeugungseinrichtung (TX) mit jedem der Empfänger (RX) mittels Ultraschallwellen verbunden ist.

25

30

35

40

45

50

55



* C L M S *

12