

TIMEPIECE WITH POWER-RESERVE INDICATION

FIELD OF THE INVENTION

The present invention concerns, generally, a timepiece with a micro-generator with a power-reserve indicator. The invention concerns more particularly means for providing this power-reserve indication. It also concerns the implementation method
5 for indicating the power-reserve.

BACKGROUND OF THE INVENTION

There is known from the prior art, particularly from EP Patent No. 0 762 243 in the name of the present Applicant, a timepiece, shown in Figure 1, including a
10 mechanical power source, formed by a barrel 1 which houses a manually or automatically wound spring 1a, the winding device not being shown here.

Barrel 1 is mechanically coupled to magnetised rotor 2a of an electric generator 2 via gear trains 3. Generator 2 includes at least a coil 2b which generates an alternating voltage U_g , when magnetised rotor 2a is driven in rotation, generating a
15 magnetic field symbolised by means of an arrow and to which said at least one coil 2b is coupled.

The terminals of coil 2b (or coils) are connected to a rectifier 4 supplying at its output a rectified voltage U_a , for powering regulator circuit 6, which will be discussed hereinafter.

20 Analogue display members for a time indication 5, typically a set of hands or any other conventional mechanical time display means, are mechanically coupled to the barrel via the gear trains 3 of the movement and they are connected in rotation to rotor 2a. The rotational speed of hands 5 is kept at a constant mean value owing to regulator circuit 6, which is for enslaving the generator frequency to a reference

switching member 7, for example a transistor, for braking generator 2 in order to regulate its frequency to a reference frequency advantageously corresponding to a correct time indication by the time indication display members 5.

The timepiece according to this document also includes a power-reserve
5 indicator 9. This device includes a counter 9a counting the successive braking signals 8 during a determined period of time by means of an additional frequency divider 9b. A memory 9c is connected at output to counter 9b so as to store the date counted during the determined time period, to the output of which a decoder 9d is connected,
10 converting the stored data into a power-reserve display means control signal 9e including successive dashes which are illuminated or appear up to a point corresponding to the value of the measured or calculated variable, accomplished either by a coloured strip, or a liquid crystal cell.

The solution recommended in EP Patent No. 0 762 243 has, however, the drawback of directly using the generator power to provide the power-reserve
15 indication, which has the effect of increasing the total power drawn from the generator, i.e. the power necessary to provide the time indicator and the power necessary to provide the power-reserve indication. Thus, in most cases, the total power necessary represents an instantaneous power greater than the maximum capacity that the generator can provide, which may prove harmful, on the one hand, to
20 the accuracy of the time indication and, on the other hand, to the actual supply of the power-reserve indication. And, at best, for those cases where the indications provided remain correct, the autonomy of the timepiece is greatly reduced.

There is also known from the prior art, particular from EP Patent No. 0 875 807 filed in the name of the present Applicant, a timepiece whose generator autonomy is
25 Higher. Such a timepiece, shown in Figure 2, includes, in addition to known elements, which have the same reference numerals and were already described with reference to Figure 1, a storage device 10 for storing and returning the electrical energy formed

energy provided by generator 2. This excess of electrical energy is of course supplied by the barrel spring 1a and originates from the conversion by generator 2 of at least a part of the spring's mechanical energy.

5 If the motor torque provided by barrel spring 1a becomes less than the operating threshold torque of the timepiece, the electrical energy produced by generator 2 becomes insufficient to power the various circuits of regulator circuit 6 correctly. But, accumulator 10a is then at least partially charged, such that storage device 10 keeps voltage U_a at a value such that the components of regulator circuit 6 operate properly. The electrical energy necessary for such operation is then supplied,
10 at least partially, by accumulator 10a.

Thus, the autonomy of this timepiece, which includes a storage device 10 capable of storing, in the form of electrical energy, a part of the mechanical energy contained in its barrel spring, is increased owing to means which enables this electrical energy to be used for operating the timepiece after the barrel spring is no
15 longer sufficiently wound.

Nonetheless, a timepiece as described in EP Patent No. 0 875 807 only enables the instantaneous excess power to be stored compared to that necessary to make the timepiece operate properly. Thus, the use of this excess of instantaneous power to provide an additional indication, like for example the power reserve, would
20 have the same drawbacks as those described in conjunction with EP Patent No. 0 762 243, namely directly using the power drawn from the generator, with the effect of greatly reducing the timepiece's autonomy, which is contrary to the desired objective.

SUMMARY OF THE INVENTION

25 In order to overcome the drawbacks of the prior art, the idea according to the invention is to provide a reliable power-reserve indication at the user's request, without disturbing the normal operation of the timepiece, i.e. while providing a correct time

actuating means for actuating, upon request, the power-reserve indicating means of the timepiece, owing to the previously stored electrical energy. In this way, the autonomy of the timepiece is not reduced, and, moreover, the necessary accumulation means are simple, reliable and of reduced size, like for example a
5 capacitor with a value of the order of 10 microfarads.

The present invention therefore concerns a timepiece with a generator whose features are listed in claim 1.

Advantageous embodiments of the present invention form the subject of the dependent claims.

10 The present invention also concerns the method of indicating the power-reserve for such a timepiece.

BRIEF DESCRIPTION OF THE DRAWINGS

Other features and advantages of the present invention will appear more
15 clearly upon reading the following detailed description of embodiments of the invention given solely by way of non-limiting example and illustrated by the annexed drawings, in which:

- Figure 1, already described, shows a timepiece having a generator with a power-reserve indicator according to the prior art;

20 - Figure 2, already described, shows a timepiece having a generator with prolonged autonomy according to another prior art;

- Figure 3 shows a timepiece having a power-reserve indicator according to a preferred embodiment of the invention;

25 - Figures 4a-4c show alternative embodiments of the power-reserve indicator means; and

- Figure 5 shows an example of an implementation method for the power-reserve indication.

indicator. The idea is to be able to accumulate, in a reasonable lapse of time, for example a few minutes, sufficient energy to momentarily display the power-reserve. A quantity of energy of between 40 and 80 microJoules has proved ample. This energy must also be able to be released in a short time lag, i.e. there must be available an
5 instantaneous power that is considerably higher (up to a thousand times greater) than the mean dissipated braking power, depending upon the type of power-reserve indicator used.

Reference will now be made to Figure 3, which shows a simplified diagram of a timepiece according to a preferred embodiment of the invention. A certain number of
10 elements can be seen that are identical to those presented within the scope of the prior art in Figures 1 and 2, such elements will not be detailed again here and their reference numerals remain unchanged.

Thus, there is again shown a timepiece fitted with a mechanical energy source formed by a barrel 1 which houses a barrel spring 1a. The barrel is mechanically
15 coupled, on the one hand, to generator 2 whose alternating voltage U_g generated at its output, is rectified via an active rectifier 4, and, on the other hand, to time indication display means 5, conventionally hands, via gear trains 3 of the watch movement. The rotational speed of the hands is kept at a constant mean value owing to the monitoring circuit 6, or regulator circuit, for enslaving the frequency of generator 2 to a reference
20 frequency, such that the speed of the hands corresponds to the speed required to obtain a correct time indication.

The timepiece further includes electrical energy accumulation means 11 arranged to be able to accumulate the electrical energy dissipated during braking periods of generator 2, - i.e. during short-circuits applied to the generator via switching
25 means 7. Switching means 7 are actuated by regulator circuit 6 when the generator frequency is higher than the reference frequency, i.e. when the rotational speed of rotor 2a is higher than the hand speed corresponding to a correct time indication.

connected transistor, which leads the current in a single direction and a storage capacitor. It will of course be noted that other charge pumps could be used.

Accumulation element 11b can be a simple storage capacitor whose charge increases a little more upon each braking. Given the yield of such a charge pump 11a,

5 accumulation element 11b, preferably a storage capacitor having a capacity of the order of 10 microfarads at 3 or 4 volts, allows an energy of the order of 40 to 80 microJoules to be accumulated after several minutes braking.

It will be noted in this regard that once accumulation element 11b is charged, accumulation means 11 continues to ensure optimum impedance adaptation, and
10 consequently braking of the generator.

According to an alternative embodiment, the timepiece includes an indicator, not shown here, arranged on the dial to indicate when accumulation element 11b is sufficiently charged to power a power-reserve indication device 12. This power-reserve indication device 12 includes power-reserve display means 12a and a control
15 system 12b for said display means. Control system 12b has been shown independently here of regulator circuit 6, it will be noted however that it could just as well be integrated in regulator circuit 6.

The power-reserve display control system is actuated (signal P) by actuating means 13 of the timepiece accessible from the exterior, like for example a push-
20 button called a "request button". The role of this control system is to provide accurate indication of the power-reserve (signal R) on the basis of a measurement (signal C) of the power-reserve transmitted by regulator circuit 6. The energy necessary for displaying the power-reserve is provided by the accumulation means (signal A).

Various methods can be implemented for measuring the power-reserve. A first
25 method consists in providing control system 12b with means for counting the successive brakings over successive time periods of a determined duration and for elaborating a power-reserve display signal from the number of brakings occurring

Several power-reserve display means can be used, depending upon the method chosen. Various examples of power-reserve indication devices are shown in Figures 4a-4c. In these Figures, control system 12b has been integrated in regulator circuit 6. A regulator circuit 14 can thus be seen receiving the various signals A, C and
5 P respectively supplying the electrical energy necessary for the power-reserve display, the power-reserve indication and the request for such a power-reserve indication.

Figure 4a shows a first example using digital power-reserve display means. Said display means are formed by an LCD (Liquid Crystal Display) type display 15a arranged on the dial of the timepiece. The power-reserve indication is preferably
10 displayed as a percentage with respect to the maximum power-reserve, corresponding to the completely wound spring, or in remaining power-reserve hours. These display means can be used with one of the first two methods explained hereinbefore.

Preferably, the LCD display is left active for a determined period of time, sufficient to allow the user time to read the power-reserve indication after he has
15 actuated the request push-button.

Figure 4b shows a second example using optical power-reserve display means. Said display means are formed by a light-emitting diode 15b with high visible yield through an aperture made in the dial of the timepiece. In this case, regulator circuit 14 preferably delivers current pulses I_r , each of these pulses representing a
20 percentage of the total power-reserve, for example 20%. Thus, 5 pulses represent 100% of the power-reserve, namely maximum power-reserve. These display means can be used with one of the first two methods explained hereinbefore.

Figure 4c shows a third example using electromechanical power-reserve display means. Said display means are formed by an analogue display member, for
25 example a hand 15c, moving opposite graduations representative of the power-reserve, arranged in a window in the dial of the timepiece. This analogue display member 15c is driven by a stepping motor 16, for example of the two-directional Lavet

quantity, corresponding for example to one step of the motor. Advantageously, the position of the power-reserve indicator is able to be adjusted manually (signal P) via a push-button, in order to correct any shift between the position of the motor and that of the indicator. In fact, such a shift may appear if there a shock occurs precisely while
5 the motor is adapting the position of the analogue display member.

A second variant of this third example consists in providing a zero reset for analogue display member 15c when the request push-button is actuated. Thus, signal P received by regulator circuit 14 first of all commands the display member to be reset to zero, then, secondly, the power-reserve indication. The display member then
10 remains fixed in the power-reserve indication position until the next request by the user.

A third variant of this third example consists simply in adjusting the position of the display member upon each request made by the user without any prior zero reset.

The present invention also concerns the method of indicating the power-
15 reserve for such a timepiece. The method includes a preliminary step of winding the barrel spring sufficiently such that the timepiece can operate properly. With the exception of the first variant of the third example presented in Figure 4c, the method then includes the following steps of:

- 20 1. accumulating electrical energy by charging the accumulation means with the power dissipated during successive generator brakings;
2. requesting a power-reserve indication by actuating the actuating means provided for this purpose;
3. measuring the power-reserve indication in accordance with any of the aforementioned methods;
- 25 4. displaying the measured indication with the corresponding power-reserve display means.

An intermediate step 1b (between steps 1 and 2) can be provided. This step 1b

power-reserve measurement methods explained hereinbefore not to the various
aforementioned examples of power-reserve display means.

It will also be noted that other accumulation means can be used for storing the
electrical energy dissipated during the generator braking periods. As regards the
5 actuating means, it is possible to use by way of alternative, a shock detector on the
timepiece glass, or even a stem-crown.

It will further be noted that it is possible to increase the autonomy of the
timepiece according to the invention by providing an additional storage device like that
disclosed in EP Patent No. 0 875 807, this additional device being charged by means
of the excess electrical energy with respect to the energy necessary for proper
operation, when the generator is not being braked.

CLAIMS

1. Timepiece including a mechanical power source (1) coupled, on the one hand, to first time related information display means (5) and, on the other hand, to a generator (2), a regulator circuit (6; 14) for enslaving the generator frequency to a reference frequency, said regulator circuit including switching means (7) arranged for
5 electrically braking the generator when the generator frequency is higher than the reference frequency, and second power-reserve display means (12a; 15a, 15b) controlled by means for measuring the power-reserve (12b; 14), said timepiece being characterised in that it further includes means (11) for accumulating the electrical energy dissipated during generator braking periods and means (13) for actuating said
10 second display means to display the power-reserve by means of the electrical energy accumulated by said accumulation means (11).

2. Timepiece according to claim 1, characterised in that said electrical energy accumulation means (11) are formed by a voltage step-up circuit (11a) electrically connected to the generator (2) during braking periods and controlled by the
15 regulator circuit (6) so as to accumulate the energy dissipated during said periods in a storage capacitor (11b).

3. Timepiece according to claim 1 or 2, characterised in that the actuating means (13) are a control member accessible from outside the timepiece.

4. Timepiece according to any of claims 1 to 3, characterised in that the
20 power-reserve measuring means (12b; 14) include means for fixing successive time periods of a predetermined length, means for counting, during each of said fixed periods, the number of times that the generator is braked by the switching means and means controlled by the actuating means to provide, as a function of the result of counting, power-reserve information to the second display means (15a; 15b).

25 5. Timepiece according to any of claims 1 to 3, characterised in that the

8. Timepiece according to any of claims 1 to 3, wherein the generator (2) includes at least one coil (2b) and characterised in that the power-reserve measuring means (12b) include an additional coil electrically coupled to said at least one coil of the generator during braking periods by the switching means (7) and an electrically
5 controlled motor (16) controlled by said actuating means (13), for providing, as - reserve information to the second display means (15c).

9. Timepiece according to claim 8, characterised in that the second display means are electromechanical means formed by an analogue member (15c) driven by said electrically controlled motor (16).

10. Timepiece including a mechanical energy source (1) coupled, on the one hand, to first time information display means (5) and, on the other hand, to a generator (2), a regulator circuit (6; 14) for enslaving the generator frequency to a reference frequency, said regulator circuit including switching means (7) arranged for electrically braking the generator when the generator frequency is higher than the
15 reference frequency, and second power-reserve display means (12a; 15c) controlled by power-reserve measuring means (12b; 14, 16), said timepiece being characterised in that it further includes means for accumulating (11) the electrical energy dissipated during the generator braking periods, and in that said power-reserve measuring means automatically adapt the position of said second display means to display the
20 power-reserve by means of the electrical energy accumulated by said accumulation means.

11. Timepiece according to claim 10, wherein the generator (2) includes at least one coil (2b) and characterised in that the power-reserve measuring means (14, 16) include an additional coil electrically coupled to said at least one coil of the
25 generator during braking periods by the switching means (7) and an electrically controlled motor (16) controlled by said regulator circuit (14), to provide, as a function of an electrical quantity transmitted during electrical coupling, power-reserve