

Method and apparatus for determining an optimum power level

The present invention relates generally to recordable optical storage systems, and more specifically to a method of and an apparatus for determination of an optimal laser power for use with recordable optical storage systems and optical storage discs.

5 As is well known, CD-R (Compact Disc-Recordable) discs and the like are made up of an optical stack. The stack commonly consists of polycarbonate substrate, a sensitive dye layer, a gold or silver alloy reflector and a protective lacquer coating. Data is written to a disc by focusing a high power laser onto the dye layer so as to heat an area such that the reflectivity of the area is altered. The areas form a spiral track of variable length
10 marks (low reflective areas), and lands (highly reflective areas between the marks). The resulting pattern of the marks and lands encodes the data to be stored on the disc. Each transition between a mark area and a land area corresponds to the physical encoding of a data “1” value. The lands are typically 3 to 11 clock cycles in length (3T to 11T where ‘T’ represents the data clock period).

15 Precise mark length is critical if data is to be represented accurately. For example, if an optical reader reads a disc with a number of 3T marks or lands that are too long, these could be misinterpreted as 4T features. This misinterpretation may result in incorrect data retrieval, and, in extreme cases, read-failure.

20 For this reason, it is essential that optical recorders are able to monitor and maintain the quality of disc writing in order to ensure the accuracy of all the mark and land lengths over the particular disc being written.

 In order to achieve accurate mark/land lengths, there will be an optimum laser recording power for the disc/recorder combination being used. The optimum laser recording power that should be used when recording a disc (e.g. CD-R, CD-RW (Compact Disc-
25 ReWritable), DVD±R (DVD Recordable), DVD±RW (DVD ReWritable), DVD-RAM etc.) is therefore dependent upon the actual disc, the recorder being used and also the speed at which the recording is taking place.

 The optimum laser recording power should be determined for each recorder/disc combination at the actual recording speed. Such determination is called an

Optimum Power Control (OPC) procedure. The optimum laser recording power will allow the recorder to produce the correct mark/land lengths for a given disc at a given recording speed.

Two different OPC procedures are currently in use for Recordable (R), and ReWriteable (RW) optical storage discs. For R-discs 'beta' and 'jitter' (or 'sigma') OPC methods are generally used, whilst for RW-discs a 'gamma' method is used as the OPC procedure. The jitter/sigma OPC procedure is one of the most commonly used methods. Jitter is a statistical measurement of the variation in mark or land length around a mean value for each run length, and is a general measure of timing errors which occur when a player/recorder reads data.

These presently used OPC methods are based upon information being used which is pre-stored on the disc (see for example DVD+R, Basic Format Specification, System Description, or Recordable Compact Disc Systems, Part II: CD-R, System Description). Information may be pre-stored onto a disc which provides a recorder for example with an indicative power level with which to begin an OPC procedure. This information may not, however, always be correct, and can result in OPC failure.

A further disadvantage of presently used jitter/sigma OPC procedures is the requirement for large amounts of disc area for recording test patterns in order to average out variations (such as disc eccentricity for example) along the circumference of the disc. The large test areas which are needed detract from the space available for data storage, and the tests also take a long time to perform.

There is therefore a need for a fast, space efficient sigma (σ) OPC method which is also independent of information stored on a disc.

According to the present invention there is provided a fast σ -OPC procedure which may be executed at inner and/or outer test zones of a disc, and which overcomes the problems associated with conventional jitter OPC procedures.

According to a first aspect of the present invention there is provided a method of determining an optimum power level for a laser device for writing to an optical storage medium, the method comprising defining a test region of the optical storage medium, using a laser device having an operating output power level, writing a predetermined data pattern to the test region, measuring jitter values for the predetermined data pattern, and selecting an

optimum operating output power level of the laser device for writing data to the optical storage medium in dependence upon the measured jitter values, the optimum power level minimising the jitter value for the optical storage medium, characterised in that, during writing of the predetermined data pattern to the test region in a first scan of the medium, the operating output power level of the laser device is varied according to a first predetermined profile, and, during writing of the predetermined data pattern to the test region in a second scan of the medium, the operating output power level of the laser device is varied according to a second predetermined profile, different to the first predetermined profile.

According to a second aspect of the present invention there is provided apparatus for determining an optimum power level for a laser device for writing to an optical storage medium, the apparatus comprising, means for defining a test region of the optical storage medium, a laser device having an operating output power level, operable to write a predetermined data pattern to the test region, means for measuring jitter values for the predetermined data pattern, and means selecting an optimum operating output power level of the laser device for writing data to the optical storage medium in dependence upon the measured jitter values, the optimum power level minimising the jitter value for the optical storage medium, characterised by power adjustment means operable, during writing of the predetermined data pattern to the test region in a first scan of the medium, to vary the operating output power level of the laser device according to a first predetermined profile, and, during writing of the predetermined data pattern to the test region in a second scan of the medium, to vary the operating output power level of the laser device according to a second predetermined profile, different to the first predetermined profile.

Laser write power is stepped every ADIP/ATIP (Address in Pre-groove/Absolute Time in Pre-groove) frame, and at each power step jitter is measured a number of times (after writing is finished) in order to obtain an average for that ADIP/ATIP frame (and hence power level).

According to the present invention, the laser write power may also be stepped a number of times per ADIP/ATIP frame.

The method of the present invention provides significant advantages over presently used OPC procedures in terms of speed, disc space usage, and due to the fact that it may be used for all recordable optical storage disc media independently of the information pre-stored thereon (e.g. CD-R, CD-RW, DVD±R, DVD±RW, DVD±R_DL (DL = Double Layer), DVD±RW_DL, DVD-RAM, Blu-ray Disc, etc.).

In an exemplary embodiment of the present invention, a two track jitter OPC procedure is provided.

5 These and other objects, features and advantages of the invention will be apparent from the following more particular descriptions of embodiments of the invention as illustrated in the accompanying drawings, where

Figure 1 represents a side view of typical CD-RW disc;

Figure 2 represents a two-track OPC procedure in accordance with the present invention;

10 Figure 3 is a graph representing adjustments made to laser power levels in accordance with the present invention;

Figure 4 is a flow chart of the method of the present invention;

Figure 5 depicts arrays of power and jitter values according to an exemplary embodiment of the present invention;

15 Figure 6 depicts arrays of average power and jitter values according to an exemplary embodiment of the present invention;

Figure 7 further depicts arrays of power and jitter values according to an exemplary embodiment of the present invention;

20 Figure 8 further depicts arrays of average power and jitter values according to an exemplary embodiment of the present invention;

Figure 9 depicts an array of average power values according to an exemplary embodiment of the present invention;

Figure 10 depicts an array of average jitter values according to an exemplary embodiment of the present invention;

25 Figure 11 is a graph of average jitter measurement versus average power level in accordance with an exemplary embodiment of the present invention; and

Figure 12 is a further graph of average jitter measurement versus average power level in accordance with an exemplary embodiment of the present invention.

30 The σ -OPC procedure of the present invention is executed using the test zones of a disc. In order to provide fast and space efficient OPC, an embodiment of the present invention provides an σ -OPC procedure using only two revolutions of the disc.

Although the present invention will be described primarily with reference to CD-R(W) and DVD-R(W) discs, it will be appreciated that the present invention is applicable

to any optical recording medium where an optimum laser power is desired for writing information to the medium. For example the present invention is also applicable, but not limited, to DVD-R_DL, DVD-RW_DL, and Blu-ray Disc, etc.

Figure 1 shows a side view of a standard CD-RW disc. A 'power-calibration area' (PCA) 1 is defined as a test zone for the disc, and any OPC procedure is generally carried out in this region of the disc. A program memory area (PMA) 3, lead-in and lead-out areas 5,9 and program area 7 are provided on the disc, but are not relevant to the present invention, and will not therefore be discussed. The areas 3, 5, 7, and 9 are merely included for completeness, and to emphasise that the present invention is applicable to all standard disc types.

The present invention utilises so-called 'ADIP' (ADdress in Pre-Groove) and 'ATIP' (Absolute Time In Pre-Groove) frames present on optical recording media.

All discs have a pre-cut spiral groove that oscillates slightly. The groove keeps the write head tracking properly, and the oscillation (sinusoidal with a frequency of 22.05KHz at nominal speed for CD-R(W) discs) provides timing information to the recorder.

The oscillation is frequency-modulated with a +/-1KHz signal, which creates an absolute time clocking signal, known as the Absolute Time In Pregroove (ATIP). The oscillation can therefore be thought of as providing a timing signal. For DVD+R(W) discs the oscillation has a frequency of 817kHz at nominal speed. For DVD-R(W) discs the frequency of oscillation at nominal speed is 140.6kHz. Timing information comes from this modulated signal.

When information is read from the disc the oscillation can be demodulated to form the timing signal from which time information may be derived. Thus the position on the disc during writing/reading can be determined by this ATIP (Absolute Time In Pre-groove) information.

For DVD+R(W) discs there is a phase modulated time signal. In the same fashion to CD-R(W) discs, time information may be derived from the phase oscillation in order to give the position of the disc during reading/writing. This information is called ADIP (ADdress In Pre-groove) for DVD-R(W) discs.

There are certain number of ADIP/ATIP frames per disc revolution. According to the present invention, the OPC procedure is carried out on a small area of a disc, so that a constant number of ATIP/ADIP frames per revolution are used. Specifically, according to an exemplary embodiment of the present invention, 9 ATIPs frames are used for

CD-R(W) discs, and 7 ADIP frames are used for DVD-R(W) discs per revolution (at the inside of the optical disc).

Figure 2 shows a two-track σ -OPC procedure in accordance with the present invention, and figure 3 illustrates power level changes during that procedure.

5 According to the embodiment exemplified by figures 2 and 3, the laser power level is changed for each ADIP/ATIP frame, θ . The power level is determined by dividing the difference between the minimum and maximum laser write powers available for a given recorder/disc combination and the number of steps required. The minimum and maximum laser write powers may, for example be pre-programmed parameters of the recorder.

10 Alternatively, a standard start power could be used which is then stepped by a predetermined amount every time a new power level is required.

During a first revolution, test data is written to a disc at a particular laser power level in an ADIP/ATIP frame. The laser power level is then adjusted as shown in figure 3 and the test data is written to the next ADIP/ATIP frame at this new power level.

15 The procedure continues for the first revolution of the disc until the desired number of power levels have been sampled. The same procedure is then followed for a second revolution with the power levels changed as shown in figure 3.

As shown in figure 2, the power level changes during the second revolution 11 are different in sequence to those used during the first revolution 13. This shift ensures that ADIP/ATIP frames written with a given power level during the first and second revolutions will not coincide on the disc.

20 According to the exemplary embodiment of the present invention as shown in figures 2 and 3, at the start of writing the next track 11 the sequence of power levels 103 are changed as shown in figure 3. In this way, any possible problems associated with non-homogeneities of the disc along its circumference are averaged out.

Specifically, adjacent ATIP/ADIP frames in concentric tracks do not contain information written at the same laser power level. As a result, a non-homogeneity along the circumference of the disc will not cause an anomalous reading at a particular laser power.

After writing according to the sequence as depicted in figure 3, jitter is
30 measured a number of times at every ADIP/ATIP frame, and is averaged. Jitter may be measured using conventional techniques. For example, a timing measurement circuit in the recorder/player in question may be used in order to provide jitter measurements in relation to a clock signal for example.

The method of the present invention as exemplified by figures 2 and 3 is depicted diagrammatically in figure 4 which shows a flow chart in accordance with the method of the present invention.

At step 1001, a power level is selected by the recorder. At step 1003, test
 5 information is written to an ADIP/ATIP frame using the power level selected at step 1001. At step 1005, the recorder determines whether the procedure is complete for a particular revolution, i.e. if all necessary power levels have been sampled. If yes, then it is determined at step 1007 whether further revolutions for the OPC procedure are required.

If further measurements are deemed necessary at step 1005, a new power level
 10 is selected at step 1001, and the OPC procedure continues.

If further revolutions are necessary at step 1007, a new laser write power is selected for the new revolution at step 1001. Alternatively, if no further revolutions are required, jitter is measured for the revolutions at step 1009.

Therefore, the method as outlined in figure 4 is repeated for each revolution of
 15 the disc. Jitter measurements start after the writing has been completed for each revolution.

It will be appreciated that the laser power levels need not necessarily be adjusted as depicted in figure 3, but may be adjusted in any manner provided that adjacent ADIP/ATIP frames in concentric tracks are not written with the same power level for the reasons outlined above.

When using an inner disc test zone, for example, 7 ADIP frames (for
 20 DVD+R(W)) are used per revolution, or 9 ATIP frames (for CD-R(W)) are used per revolution.

After writing with the different powers on ADIP/ATIP frame positions, jitter is measured. Once jitter has been measured at each ADIP/ATIP frame, enough information
 25 is available to average out the variations along the circumference of the disc. This will be explained in more detail below.

A table is shown below, which shows the jitter measurements for the power levels used during the test revolutions. In the table, n is the number of ADIP/ATIP frames that are written per revolution during the OPC procedure.

30

Power Level	Jitter Measurement (1 st revolution)	Jitter Measurement (2 nd revolution)
P_0	$\sigma_{0,1}$	$\sigma_{0,2}$
...	...	...
P_{n-1}	$\sigma_{(n-1),1}$	$\sigma_{(n-1),2}$

Figure 5 is a diagrammatic representation of two arrays obtained for power and jitter measurements using seven laser power levels per revolution for two revolutions. Jitter is measured at each power level for each revolution. For example, during a first revolution at a power level P_0 , a jitter value $\sigma_{0,1}$ is obtained. Here, the subscript 0.1 indicates that it is the first (1) jitter measurement obtained from the first (zero-th) power level (0). Similarly, the seventh (6) jitter measurement (i.e. at the seventh power level) during the second (2) revolution is $\sigma_{6,2}$. The results are arranged in power level order P_0 to P_6 , even though the power levels are applied in different orders for the different revolutions.

Figure 6 depicts how, in an exemplary embodiment, the results from the measurements of figure 5 are averaged, the results of which are placed into two new arrays for power and jitter respectively.

In figure 6, two consecutive power and jitter values for both a first and a second revolution are averaged to provide the values of the new array. So, for example, the first two power levels for each revolution are P_0 and P_1 , and the corresponding jitter measurements for the first and second revolutions are $\sigma_{0,1}, \sigma_{1,1}$ and $\sigma_{0,2}, \sigma_{1,2}$ respectively. The two power levels are averaged to give the value $P_{0,1}$ according to equation (1) below, and the four jitter measurements for the two revolutions at the two power levels are averaged to give $\sigma_{0,1}$ according to equation (2) below.

Therefore, averaging two consecutive power and jitter values (as described above) is performed using the following equations:

$$P_{0,p} = (P_p + P_{p+1}) / 2 \quad \forall p \in N : 0 \leq p \leq n-2 \quad (1)$$

$$\sigma_{0,p} = (\sigma_{p,1} + \sigma_{p,2} + \sigma_{(p+1),1} + \sigma_{(p+1),2}) / 4 \quad \forall p \in N : 0 \leq p \leq n-2 \quad (2)$$

Similarly, figures 7 and 8 show how three consecutive power and jitter values are averaged and placed into two further new arrays according to equations (3) and (4) below. Therefore,
 5 averaging of three consecutive power and jitter values of the above table is performed using the following equations:

$$P_{0q} = (P_q + P_{q+1} + P_{q+2})/3 \quad \forall q \in N : 0 \leq q \leq n-3 \quad (3)$$

$$10 \quad \sigma 2_q = (\sigma_{q,1} + \sigma_{q,2} + \sigma_{(q+1),1} + \sigma_{(q+1),2} + \sigma_{(q+2),1} + \sigma_{(q+2),2})/6$$

for $\forall q \in N : 0 \leq q \leq n-3$ (4)

The values from the four new arrays are now placed into two arrays as shown in figures 9 and 10.

15 The four power/jitter arrays defined by equations (1) to (4) may now be stored into the two separate arrays given below:

$$Ps_{2p} = Po_p \quad \sigma s_{2p} = \sigma 1_p \quad \forall p \in N : 0 \leq p \leq n-2 \quad (5)$$

$$Ps_{2,q+1} = Po_q \quad \sigma s_{2,q+1} = \sigma 2_q \quad \forall q \in N : 0 \leq q \leq n-3 \quad (6)$$

20 This has the advantage of providing more samples which will enable a more accurate fit to be obtained when the average jitter is plotted against the average power.

It has been observed that the relationship between the averaged power levels P_s , and the averaged jitter values σ_s is quadratic in nature as depicted in figure 11. The “+” marks 20 represent two averaged power and jitter values, and the “x” marks 22 represent three averaged power and jitter values.

25 In order to determine the power level that represents the minimum level of jitter, the minimum of the function relating σ_s and P_s ($\sigma_s = f(P_s)$) should be found (ideally by second order curve fitting). Given that the new function is observed to be quadratic, by finding solutions to the equation (in which a, b and c are constants):

$$\sigma_s = aP_s^2 + bP_s + c \quad (7)$$

when $d\sigma_s / dP_s = 0$, we can calculate $P_s = P_{w\sigma}$, where $P_{w\sigma}$ is the optimal power.

Figure 12 shows a typical plot of σ_s vs. P_s . When $d\sigma_s / dP_s = 0$, we have:

5

$$2aP_{w\sigma} + b = 0 \quad (8)$$

and so

$$10 \quad P_{w\sigma} = -b/(2a) \quad (9)$$

where a and b are coefficients obtained from the polynomial regression. The new optimal power $P_{w\sigma}$ corresponds to a minimal jitter value of the fitted curve.

Therefore, $P_{w\sigma}$ is the optimum laser write power, i.e. the laser power that
 15 produces the minimum jitter value of the fitted curve, which is symmetrical about this minimum for a given disc/recorder combination at a given write speed.

It will be appreciated that in the exemplary embodiment given above, averages of two and three power and jitter values were used in order to calculate the optimum laser power. Averages over a larger or smaller number of power levels and associated jitter values
 20 are also possible however, and the above is only to illustrate the present invention. For example, if even greater accuracy of $P_{w\sigma}$ is required, an average over 2, 3, 4 and 5 power levels and associated jitter values could be used to obtain the curve of figure 12.

CLAIMS:

1. A method of determining an optimum power level for a laser device for writing to an optical storage medium, the method comprising:
 - defining a test region of the optical storage medium;
 - writing a predetermined data pattern to the test region using a laser device
 - 5 having an operating output power level;
 - measuring jitter values for the predetermined data pattern; and
 - selecting an optimum operating output power level of the laser device for writing data to the optical storage medium in dependence upon the measured jitter values, the optimum power level minimising the jitter value for the optical storage medium,
 - 10 characterised in that,
 - during writing of the predetermined data pattern to the test region in a first scan of the medium, the operating output power level of the laser device is varied according to a first predetermined profile, and, during writing of the predetermined data pattern to the test region in a second scan of the medium, the operating output power level of the laser
 - 15 device is varied according to a second predetermined profile,
 - said predetermined profiles comprising a plurality of operating output power level steps, and
 - said second predetermined profile being different from said first predetermined profile such that that the operating output power level ($P_{1,1} \dots P_{n,1}$) for writing the predetermined data pattern to a specific angular area ($\theta_1 \dots \theta_n$) on the optical storage medium in the first scan of
 - 20 the medium is different from the operating output power level ($P_{1,2} \dots P_{n,2}$) for writing the predetermined data pattern to said specific angular area ($\theta_1 \dots \theta_n$) on the optical storage medium in the second scan of the medium.
2. A method as claimed in claim 1, wherein at least one jitter value is measured
- 25 for each of the operating output power level steps of the first and second predetermined profiles.
3. A method as claimed in claim 2, wherein the step of selecting the optimum power level comprises:

determining a function which relates jitter value to power level, over the range of operating output power levels in the first and second predetermined profiles;

determining from said function an optimum power level that minimises the jitter value.

5

4. A method as claimed in claim 3, wherein the step of determining the function relating jitter value to power level comprises:

for respective pairs of consecutive operating output power levels, obtaining respective average power levels and respective average jitter values from the jitter values corresponding to those consecutive operating output power levels; and

10

determining a function which relates the average jitter values to the average power levels.

5. A method as claimed in claim 3, wherein the step of determining the function relating jitter value to power level comprises:

15

for respective triads of consecutive operating output power levels, obtaining respective average power levels and respective average jitter values from the jitter values corresponding to those consecutive operating output power levels; and

determining a function which relates the average jitter values to the average power levels.

20

6. A method as claimed in claim 3, wherein the step of determining the function relating jitter value to power level comprises:

for respective pairs of consecutive operating output power levels, obtaining respective average power levels and respective average jitter values from the jitter values corresponding to those consecutive operating output power levels;

25

for respective triads of consecutive operating output power levels, obtaining respective average power levels and respective average jitter values from the jitter values corresponding to those consecutive operating output power levels; and

30

determining a function which relates the average jitter values to the average power levels.

7. A method as claimed in any one of claims 4, 5 or 6, wherein the function is a quadratic function of the form $\sigma = aP^2 + bP + C$, where σ represents jitter value, P represents

power level and a, b and c are constants, and the optimum power level is determined by setting the differential of the function to zero ($d\sigma/dP=0$, $P_{\text{optimum}}=-b/2a$).

8. A method as claimed in any one of claims 1 to 7, wherein the optical storage
5 medium is a disc having address in pre-groove frames (ADIP) defined therein, and wherein the operating output power level is varied for each ADIP frame of the disc.
9. A method as claimed in any one of claims 1 to 7, wherein the optical storage
medium is a disc having absolute time in pre-groove frames (ATIP) defined therein, and
10 wherein the laser power level is varied for each ATIP frame of the disc.
- .
10. Apparatus for determining an optimum power level for a laser device for
15 writing to an optical storage medium, the apparatus comprising:
 - means for defining a test region of the optical storage medium;
 - a laser device having an operating output power level, operable to write a
predetermined data pattern to the test region;
 - means for measuring jitter values for the predetermined data pattern; and
 - 20 means selecting an optimum operating output power level of the laser device
for writing data to the optical storage medium in dependence upon the measured jitter values,
the optimum power level minimising the jitter value for the optical storage medium,
characterised by power adjustment means operable, during writing of the
predetermined data pattern to the test region in a first scan of the medium, to vary the
25 operating output power level of the laser device according to a first predetermined profile,
and, during writing of the predetermined data pattern to the test region in a second scan of the
medium, to vary the operating output power level of the laser device according to a second
predetermined profile,
said predetermined profiles comprising a plurality of operating output power level steps, and
30 said second predetermined profile being different from said first predetermined profile such
that that the operating output power level ($P_{1,1} \dots P_{n,1}$) for writing the predetermined data
pattern to a specific angular area ($\theta_1 \dots \theta_n$) on the optical storage medium in the first scan of
the medium is different from the operating output power level ($P_{1,2} \dots P_{n,2}$) for writing the

predetermined data pattern to said specific angular area ($\theta_1 \dots \theta_n$) on the optical storage medium in the second scan of the medium.

11. Apparatus as claimed in claim 10, wherein said means for selecting the optimum power level comprises:
 - means for determining a function which relates jitter value to power level, over the range of operating output power levels in the first and second predetermined profiles;
 - means for determining from said function an optimum power level that minimises the jitter value.
12. Apparatus as claimed in claim 11, wherein said means for determining the function relating jitter value to power level comprises:
 - means for obtaining, for respective pairs of consecutive operating output power levels, respective average power levels and respective average jitter values from the jitter values corresponding to those consecutive operating output power levels; and
 - means for determining a function which relates the average jitter values to the average power levels.
13. Apparatus as claimed in claim 11, wherein said means for determining the function relating jitter value to power level comprises:
 - means for obtaining, for respective triads of consecutive operating output power levels, respective average power levels and respective average jitter values from the jitter values corresponding to those consecutive operating output power levels; and
 - means for determining a function which relates the average jitter values to the average power levels.
14. Apparatus as claimed in claim 11, wherein said means for determining the function relating jitter value to power level comprises:
 - means for obtaining, for respective pairs of consecutive operating output power levels, respective average power levels and respective average jitter values from the jitter values corresponding to those consecutive operating output power levels;

means for obtaining, for respective triads of consecutive operating output power levels, respective average power levels and respective average jitter values from the jitter values corresponding to those consecutive operating output power levels; and

5 means for determining a function which relates the average jitter values to the average power levels.

15. Apparatus as claimed in any one of claims 10 to 14, for use with an optical storage medium being a disc having address in pre-groove frames (ADIP) defined therein, characterized in that the power adjustment means is operable to vary the operating output
10 power level for each ADIP frame of the disc.

16. Apparatus as claimed in any one of claims 10 to 14, for use with an optical storage medium being a disc having absolute time in pre-groove frames (ATIP) defined therein, characterized in that the power adjustment means is operable to vary the operating
15 output power level for each ATIP frame of the disc.

17. Recording apparatus for recording data to a disc, comprising an apparatus for determining an optimum power level according to any of the claims 10 to 16.