

MONITORING SYSTEM

The present invention relates to a system for monitoring the performance of a network. The system is
5 suitable for use, for example, in a TPON (Telephony on a Passive Optical Network) system, but also may be used in other contexts.

Conventionally, installed optical fibre networks have been tested to detect a fault such as a break in the
10 network by connecting a dedicated optical time domain reflectometer (OTDR) to the network. The OTDR typically comprises a high power optical source which transmits a pulse onto the network. Light back-scattered from faults in the network is detected and correlated with the
15 transmitted pulse to determine the location of the fault giving rise to the back-scattered signal.

As described in the present applicant's earlier international application WO 91/02959 the use of dedicated OTDR equipment has significant disadvantages. In
20 particular it requires the interruption of the service normally carried on the network and so is normally used only after a failure occurs and is not suitable for continual monitoring of the network. The system described and claimed in the above cited application proposes the
25 transmission of an appropriately coded OTDR signal as a part of each downstream data frame sent onto the network. In the preferred example the test pulse sequence is a Barker or Golay code transmitted in a header portion of a multiplexed data frame. Although this arrangement does
30 make it possible to monitor the network continually there is then the disadvantage of a significant transmission overhead associated with the dedicated OTDR codes and a subsequent loss of bandwidth which might otherwise be used for data or for other system control functions.

35 According to a first aspect of the present invention, there is provided a system for monitoring a network in which a station connected to the network and including a

This Sheet Has Been Replaced



transmitter for outputting a signal modulated with outgoing traffic onto the network and a receiver for receiving a signal from the network further comprises a monitoring circuit including means for introducing a variable delay in a signal
5 from the transmitter and means for combining the delayed signal with the received signal so as to produce an output dependent upon the correlation of the signal from the transmitter and the received signal at the given delay.

The system of the present invention rather than using a
10 dedicated OTDR probe signal as with the prior art systems, continually monitors the correlation between the output signal and the received signal as a function of a variable delay between those signals. In this manner, at a delay corresponding to the location of a fault in the network a peak
15 in the correlation output is detected. This approach is able to provide improved sensitivity by comparison with the prior art systems since the entire signal power transmitted is monitored for reflections.

If the network is duplex then the receiver is arranged to
20 receive a signal modulated with incoming traffic, and if the network is simplex then there will be a respective transmitter/receiver pair for both the downstream (transmit) and upstream (receive) paths of the network, each pair having an associated monitoring circuit. The transmitter associated
25 with the receive path may also be arranged to transmit outgoing traffic.

Preferably the network is an optical network and the transmitter and receiver are arranged to transmit and receive optical signals. Preferably the system further comprises
30 means for progressively varying the delay.

The system of the present invention brings particular advantages when used in the context of an optical network. It often happens in such a network that a local fault in one branch of the network leaves other parts of the network
35 functioning normally. Accordingly using the system of the present invention it is possible for transmission and reception of data to continue as normal on the other parts of the network while the local fault is detected and appropriate measures to correct the fault taken. This contrasts with the



prior art systems, where it would have been necessary to interrupt the operation of the entire network in order to connect a dedicated OTDR.

According to a second aspect of the present invention, there is provided a method of monitoring a network in which a station connected to the network includes a transmitter which outputs a signal modulated with outgoing traffic onto the network and a receiver which receives a signal from the network, the method comprising introducing a variable delay in a signal from the transmitter and combining the delayed signal with a signal received from the network so as to produce an output dependent upon the correlation of the signal from the transmitter and the received signal at the given delay.

Examples of the system and method in accordance with this invention will now be described in detail with reference to the accompanying drawings, in which:

Figure 1 is a block diagram showing schematically a head-end station incorporating the monitoring system of the present invention;

Figure 2 shows the head-end station incorporating means for cancelling a reflection; and

Figure 3 shows an alternative of the Figure 2 embodiment.

A head-end station 1 for use in a TPON (Telephony on a Passive Optical Network) system includes a transmitter stage 2 and a receiver stage 3 coupled to a duplex optical fibre network 4. The head-end station is arranged to transmit and receive data in multiple access time division multiplex frames using a Bit Transport System (BTS) as described in detail in the present applicant's U.S. Patent No. 4977593. The transmitter stage 2 comprises an input for traffic data and a data scrambler which scrambles the broadcast data stream using a pseudo-random binary sequence (PRBS) generator. Scrambling the data in this manner ensures that the broadcast data stream has a long autocorrelation length. A complementary process is carried out in the receiver stage with the data passing through a data de-scrambler and then to the traffic output.

The head-end station 1 includes an electro-optical converter 5 connected to output optical signals onto the

This Sheet Has Been Replaced



3a

network 4 in response to data output by the transmitter stage together with an opto-electrical converter 6 connected in a complementary fashion to convert incoming optical signals 5 received from the network 4 into an analogue electrical signal which is input to the receiver _____

This Sheet Has Been Replaced



stage 3. The transmitter stage 2 and the E/O convertor 5 together comprise the "transmitter" of the present invention. Similarly, the receiver stage 3 and the O/E convertor 6 comprise the "receiver" of the present invention.

The head-end station includes a monitoring circuit 7 which, as described below, continually monitors the return from the network as data is transmitted.

The monitoring circuit 7 operates in the electrical analogue domain. One of the inputs of the monitoring circuit 7 is connected in common with the electro-optical converter 5 at the output of the transmitter stage. The other input to the monitoring circuit 7 is connected in common with the input to the receiver stage so as to receive the electrical output from the opto-electrical converter 6. The input to the monitoring circuit taken from the transmitter stage is fed through a programmable delay line and then combined with the signal taken from the input to the receiver stage, at an Exclusive Or Gate. The signal taken from the input to the receiver passes through an amplifier 8 before being combined with the output from the programmable delay line. The resultant signal contains a DC component proportional to the degree of correlation between the incoming signal, which includes any signal back-scattered from fibre faults etc, and the signal originally transmitted. The delay applied by the delay line is progressively scanned, and any peaks in the correlation as a function of the delay identified. Such peaks indicate a high probability of a significant reflection at a fibre distance corresponding to the delay in question.

The output from the monitoring circuit is supplied to a control processor 9. The control processor 9 also provides the control input which determines the delay applied by the programmable delay line. The control processor 9 may be arranged to store a reference scan of the network taken at commissioning time. Subsequent scans

This Sheet Has Been Replaced



are then compared with the reference scan. Any significant deviations in the reference scan will then provide a clear indication of actual or incipient faults. When a fault is detected, the control processor 9 may output an appropriate alarm signal to the maintenance and diagnostics system of the network. The processor 9 may also display the output of the monitoring circuit on a suitable display device such as a CRO.

If a fault in the network is such as to cause the transmission of data to be suspended, the system of the present invention may still be used to locate and diagnose the fault. In this case, a constant input is applied to the data scrambler 2 in place of the traffic input. That constant input is then modulated in accordance with the pseudo-random binary sequence and output onto the network. The return from the network is then analysed as described above.

Although in the embodiment described above the correlation of the signals is carried out in the electrical domain other arrangements are possible in which, for example, the signals are mixed optically to provide the required correlation signal. Also, although it has special advantages when used in the context of an optical network, the present invention is also applicable, for example, to an electrical coaxial communications network.

This Sheet Has Been Replaced



In the embodiment shown in Figure 2 there are provided cancellation means constituted by the processor 9 and a subtractor 10, the processor 9 being arranged upon detection of a reflection to control the subtractor 10 for subtractively combining the output of the delay line, suitably scaled and in analogue form, with the output of the opto-electrical converter 6 so as to cancel that reflection of the data transmission before processing by the data de-scrambler. In an alternative embodiment, shown in Figure 3, the cancellation means are constituted by a finite impulse response filter 11 to which is fed the output of the transmitter stage 2, the processor 9 which determines and establishes the coefficients of the filter 11, a digital to analogue converter 12 which converts the output of the filter, and a subtractor 13 for combining the output of converter 12 with the output of converter 6. This latter implementation is an effective combination of the delayed signal with the received signal. If the processor 9 has sufficient processing power then cancellation of several reflections can be performed simultaneously.

The delay line of the monitoring circuit 7 may be a finite impulse response filter controlled by suitable coefficients generated by the processor 9, and designed such as to provide a suitable output for driving the converter 12 whereby filter 11 can be omitted.

This aspect of reflection cancellation is mainly of importance where the optical fibre network is a duplex arrangement as shown in the drawings, but may be of use in a simplex arrangement to cancel reflections of the transmitted signal, if the reflected amplitude is not insignificant.

In such a simplex arrangement, separate simplex optical fibre networks are provided for the downstream and upstream transmissions, respectively. In this case a separate optical transmitter will be coupled to the receive port of the head-end station and will preferably be driven by the electrical output of the downstream transmitter which may be attenuated. Similarly, a separate optical receiver will be coupled to the transmit port, and preferably separate reflection detection circuitry provided for the two networks. In other words at



the transmitting section of the head-end station there will be circuitry, as shown in Figure 1, with the exception of a receiver stage 3, and similarly at the receiving section the corresponding circuitry will omit the transmitter stage 2 and
5 the electro-optical converter (transmitter) will be driven, as mentioned, by the output from the transmitter stage in the transmitting section of the head-end station.

This Sheet Has Been Replaced



CLAIMS

1. A system for monitoring a network in which a station connected to the network and including a transmitter for outputting a signal modulated with outgoing traffic onto the network and a receiver for receiving a signal from the network further comprises a monitoring circuit including means for introducing a variable delay in a signal from the transmitter and means for combining the delayed signal with the received signal so as to produce an output dependent upon the correlation of the signal from the transmitter and the received signal at the given delay.
2. A system as claimed in claim 1, for monitoring a network having a single duplex path to the station, wherein said receiver is arranged to receive a signal modulated with incoming traffic.
3. A system as claimed in claim 1, for monitoring a network having separate simplex transmit and receive paths, and including a further transmitter for outputting a signal onto the receive path of the network and a further receiver for receiving from said receive path a signal modulated with incoming traffic, and a further monitoring circuit associated with the receive path.
4. A system as claimed in claim 3, wherein said further transmitter is arranged to output a signal modulated with said outgoing traffic.
5. A system according to any one of the preceding claims, in which the network is an optical network and the transmitter(s) and receiver(s) are arranged to transmit and receive optical signals.
6. A system according to any one of the preceding claims, in which the or each monitoring means further comprises means for progressively varying the delay.



This Sheet Has Been Replaced



7. A system according to any one of the preceding claims, in which the or each monitoring means include a first input connected to receive an electrical signal output from its associated transmitter, a second input connected to receive an electrical signal input to its associated receiver, and a programmable delay line connected to the first input, and the means for combining have inputs connected respectively to the output from the programmable delay line and to the second input of the monitoring circuit.
8. A system as claimed in any one of the preceding claims, wherein the or each combining means has an associated cancellation means responsive to a correlation peak from said combining means for subtractively combining, actually or effectively, the delayed signal with the received signal such as to cancel a reflection of the signal outputted onto the network.
9. A method of monitoring a network in which a station connected to the network includes a transmitter which outputs a signal modulated with outgoing traffic onto the network and a receiver which receives a signal from the network, the method comprising introducing a variable delay in a signal from the transmitter and combining the delayed signal with a signal received from the network so as to produce an output dependent upon the correlation of the signal from the transmitter and the received signal at the given delay.
10. A method as claimed in claim 9, for monitoring a network having a single duplex path to the station, wherein the signal received from the network is modulated with incoming traffic.
11. A method as claimed in claim 9, for monitoring a network having separate simplex transmit and receive paths to the station, including transmitting with a further transmitter a signal onto the receive path of the network, receiving with a further receiver from said receive path a signal modulated with incoming traffic, introducing a variable delay in a signal from said further transmitter and combining this latter



This Sheet Has Been Replaced



delayed signal with a signal received from said receive path so as to produce an output dependent upon the correlation of the signal from said further transmitter and the signal received from said receive path at the given delay.

12. A method according to any one of claims 9 to 11, in which the network is an optical network and the transmitter and receiver transmit and receive optical signals.

13. A method according to any one of claims 9 to 12, further comprising progressively varying the delay introduced between the signal from the or each transmitter and the associated received signal.

14. A method according to any one of claims 9 to 13 including applying an electrical signal output from the or each transmitter to a first input of a respective monitoring circuit, supplying an electrical signal input to the associated receiver to a second input of the respective monitoring circuit, passing the signal from the first input of the respective monitoring circuit through a respective programmable delay line, and combining the output of the respective programmable delay line and the signal from the second input of the respective monitoring circuit.

15. A method as claimed in any one of claims 9 to 14, including subtractively combining, actually or effectively, the or each delayed signal with an associated signal received from the network, in response to a correlation peak, such as to cancel from the received signal a reflection of the signal outputted onto the network.



This Sheet Has Been Replaced

