

SENSING SESSION ESTABLISHMENT METHOD AND COMMUNICATION APPARATUS

[0001] This application claims priority to Chinese Patent Application No. 202110797771.8, filed with the China National Intellectual Property Administration on July 14, 2021 and entitled "SENSING SESSION ESTABLISHMENT METHOD AND COMMUNICATION APPARATUS", which is incorporated herein by reference in its entirety.

TECHNICAL FIELD

[0002] This application relates to the field of communication technologies, and in particular, to a sensing session establishment method and a communication apparatus.

BACKGROUND

[0003] With development of communication technologies such as wireless fidelity (wireless-fidelity, Wi-Fi), various wireless communication devices have been widely used in people's daily life. Sensing measurement may be performed on environment information or other information (for example, human body movement information) based on channel information of these devices in a wireless communication process. A technology in which sensing measurement is performed on a sensing target (that is, the environment information or other information) based on channel information is referred to as a wireless sensing technology.

[0004] However, signaling or a data frame in the Wi-Fi communication technology is usually used for channel measurement, communication configuration, channel estimation, or the like, and cannot meet a function requirement of the wireless sensing technology.

SUMMARY

[0005] Embodiments of this application provide a sensing session establishment method and a communication apparatus, so that an access point can flexibly manage a station participating in a sensing session to perform sensing measurement. This helps meet a sensing measurement requirement.

[0006] According to a first aspect, an embodiment of this application provides a sensing

session establishment method. The method includes: An access point AP sends a first frame to a first station STA, where the first frame includes first information, the first information indicates a first role of the first STA in a sensing session, the first role of the first STA in the sensing session is a transmitter and/or a receiver, and the first STA is a STA participating in the sensing session in a second STA associated with the AP; and the AP receives a second frame from the first STA, where the second frame includes confirm information for the first frame.

[0007] According to the sensing session establishment method in the first aspect, for each STA participating in the sensing session, the AP allocates a role in the sensing session to the STA by sending the first frame to the STA, so that the AP can flexibly manage, by using the first frame, the role of the STA participating in the sensing session. This helps satisfy (meet) a function requirement of a wireless sensing technology as much as possible in Wi-Fi communication.

[0008] In an optional implementation, the first frame further includes a first sensing parameter, and the first sensing parameter is used by the first station to perform sensing measurement and/or sensing data reporting in the sensing session. With the optional implementation is implemented, the AP may manage, by using the first frame, the sensing parameter of the STA participating in the sensing session.

[0009] In an optional implementation, the first sensing parameter includes one or more of the following parameters: an operation parameter, a feedback type, a sensing type, or a feedback address.

[0010] In an optional implementation, the first frame includes a common information field and a user information field, and the first information is located in the common information field and/or the user information field; the first frame includes a station information field, and the first information is located in the station information field; or the first frame includes a common information field and a station information field, and the first information is located in the common information field and/or the station information field.

[0011] In an optional implementation, the second frame includes a confirm element field, and the confirm information is located in the confirm element field.

[0012] In an optional implementation, the AP sends a third frame to a plurality of second STAs, where the third frame includes second information, and the second information is used to request the second STA to participate in the sensing session. Further, the AP receives a fourth frame from the plurality of second STAs, where the fourth frame includes third information, and the third information indicates whether the second STA confirms to participate in the sensing session. The AP determines the first STA from the plurality of second STAs based on the third information from the plurality of second STAs. With the optional implementation is implemented, the AP may determine, from the plurality of STAs associated with the AP, a part of STAs to participate in the

sensing session. This reduces a quantity of STAs participating in the sensing session, and saves communication transmission resources.

[0013] In an optional implementation, when the third information indicates that the second STA confirms to participate in the sensing session, the third information further includes a second role supported by the second STA in the sensing session and a second sensing parameter corresponding to the second role. The AP determines the first STA from the plurality of second STAs based on a role of the AP in the sensing session and the third information from the plurality of second STAs.

[0014] With the optional implementation is implemented, if the STA associated with the AP confirms to participate in the sensing session, the STA sends the third information to the AP. The third information is used to notify the AP of the second role that can be supported by the STA in the sensing session and the second sensing parameter corresponding to the second role. Further, the AP may allocate a role in the sensing session to the STA based on the second role and the second sensing parameter, to improve efficiency of managing the STA in the sensing session by the AP.

[0015] In an optional implementation, when the role of the AP in the sensing session is not a transmitter and the role of the AP in the sensing session is not a receiver, third information from a third STA indicates that the third STA participates in the sensing session, and third information from a fourth STA indicates that the fourth STA participates in the sensing session, the AP determines the third STA and the fourth STA as the first STAs. A second role corresponding to the third STA is a receiver in the sensing session, and a second role corresponding to the fourth STA is a transmitter in the sensing session. With the optional implementation is implemented, when the AP is neither a transmitter nor a receiver in the sensing session, and does not participate in receiving/sending of the sensing signal, in STAs that are determined by the AP and that participate in the sensing session, there is at least one STA whose role is a receiver and at least one STA whose role is a transmitter, to ensure that there is at least one complete communication link of the sensing signal.

[0016] In an optional implementation, the third STA and the fourth STA are a same STA.

[0017] In an optional implementation, when the role of the AP in the sensing session is a transmitter, and third information from a fifth STA indicates that the fifth STA participates in the sensing session, the AP determines the fifth STA as the first STA. The fifth STA is one of the plurality of second STAs, and a second role corresponding to the fifth STA is a receiver in the sensing session. With the optional implementation is implemented, when the AP is a transmitter in the sensing session, in STAs that are determined by the AP and that participate in the sensing session, there is at least one STA whose role is a receiver, to ensure that there is at least one

complete communication link of the sensing signal.

[0018] In an optional implementation, when the role of the AP in the sensing session is a receiver, third information from a sixth STA indicates that the sixth STA participates in the sensing session, the AP determines the sixth STA as the first STA. The sixth STA is one of the plurality of second STAs, and a second role corresponding to the sixth STA is a transmitter in the sensing session. With the optional implementation is implemented, when the AP is a receiver in the sensing session, in STAs that are determined by the AP and that participate in the sensing session, there is at least one STA whose role is a transmitter, to ensure that there is at least one complete communication link of the sensing signal.

[0019] In an optional implementation, the AP determines the first sensing parameter based on the second sensing parameter. With the optional implementation is implemented, the AP determines, based on a recommended sensing parameter (that is, the second sensing parameter) fed back by the STA, the sensing parameter used when the STA participates in the sensing session, to improve efficiency of configuring a parameter for the STA by the AP.

[0020] In an optional implementation, the third frame includes a common information field, and the second information is located in the common information field; or the third frame includes a sensing request element field, and the second information is located in the sensing request element field.

[0021] In an optional implementation, the fourth frame includes a sensing confirm element field, and the third information is located in the sensing confirm element field; or the fourth frame includes a sensing response element field, and the third information is located in the sensing response element field.

[0022] In an optional implementation, the first frame includes a sensing request element field, and the first information is located in the sensing request element field.

[0023] In an optional implementation, the second frame includes a sensing response element field, and the confirm information is located in the sensing response field.

[0024] In an optional implementation, the AP sends a fifth frame to a plurality of second STAs, where the fifth frame includes fourth information, and the fourth information is used to request the second STA to participate in the sensing session by using a third role and a fourth sensing parameter; the AP receives a sixth frame from the plurality of second STAs, where the sixth frame includes fifth information, and the fifth information indicates whether the second STA confirms to participate in the sensing session by using the third role and the fourth sensing parameter; and the AP determines the first STA from the plurality of second STAs based on the fifth information from the plurality of second STAs. With the optional implementation is implemented, the AP may determine, from the plurality of STAs associated with the AP, a part of STAs to participate in the

sensing session. This reduces a quantity of STAs participating in the sensing session, and saves communication transmission resources. In addition, when requesting the plurality of STAs associated with the AP to participate in the sensing session, the AP allocates a role and a sensing parameter to each STA. If the STA agrees to participate in the sensing session by using the role and the sensing parameter allocated by the AP, the AP may not allocate a role and a sensing parameter to the STA subsequently. That is, a quantity of communication times between the AP and the STA can be reduced, and communication transmission resources can be saved.

[0025] In an optional implementation, when fifth information from a third STA indicates that the third STA participates in the sensing session based on a third role corresponding to the third STA and the fourth sensing parameter, and fifth information from a fourth STA indicates that the fourth STA participates in the sensing session based on a third role corresponding to the fourth STA and the fourth sensing parameter, the AP determines the third STA and the fourth STA as the first STAs. The third role corresponding to the third STA is a receiver in the sensing session, and the third role corresponding to the fourth STA is a transmitter in the sensing session. With the optional implementation is implemented, in STAs that are determined by the AP and that participate in the sensing session, there is at least one STA whose role is a transmitter, to ensure that there is at least one complete communication link of the sensing signal.

[0026] In an optional implementation, the third STA and the fourth STA are a same STA.

[0027] In an optional implementation, the AP determines the first STA from the plurality of second STAs based on a role of the AP in the sensing session and the fifth information from the plurality of second STAs.

[0028] In an optional implementation, when the role of the AP in the sensing session is a transmitter, and fifth information from a fifth STA indicates that the fifth STA participates in the sensing session based on a third role corresponding to the fifth STA, the AP determines the fifth STA as the first STA. The fifth STA is one of the plurality of second STAs, and the third role corresponding to the fifth STA is a receiver in the sensing session. Alternatively, when the role of the AP in the sensing session is a receiver, and fifth information from a sixth STA indicates that the sixth STA participates in the sensing session based on a third role corresponding to the sixth STA, the AP determines the sixth STA as the first STA. The sixth STA is one of the plurality of second STAs, and the third role corresponding to the sixth STA is a transmitter in the sensing session. With the optional implementation is implemented, when the AP is a transmitter in the sensing session, in STAs that are determined by the AP and that participate in the sensing session, there is at least one STA whose role is a receiver; or when the AP is a receiver in the sensing session, in STAs that are determined by the AP and that participate in the sensing session, there is at least one STA whose role is a transmitter, to ensure that there is at least one complete communication

link of the sensing signal in the sensing session.

[0029] In an optional implementation, when the fifth information from the fifth STA indicates that the fifth STA participates in the sensing session based on the third role corresponding to the fifth STA, but the fifth STA does not participate in the sensing session based on a fourth sensing parameter corresponding to the fifth STA, or when the fifth information from the sixth STA indicates that the sixth STA participates in the sensing session based on the third role corresponding to the sixth STA, but the sixth STA does not participate in the sensing session based on a fourth sensing parameter corresponding to the sixth STA, the fifth information further includes a fifth sensing parameter of the first STA; and the AP determines, based on the fifth sensing parameter of the first STA, the first sensing parameter corresponding to the first STA. With the optional implementation is implemented, when the STA determines to participate in the sensing session based on the role allocated by the AP to the STA, but does not agree to participate in the sensing session based on the sensing parameter allocated by the AP to the STA, the STA may feed back a suggested parameter (that is, the fifth sensing parameter) of the STA in the role to the AP. Further, the AP determines, based on the suggested parameter fed back by the STA, a sensing parameter used when the STA participates in the sensing session, to improve efficiency of configuring a parameter for the STA by the AP.

[0030] In an optional implementation, the fifth frame includes a sensing request element field, and the fourth information is located in the sensing request element field.

[0031] In an optional implementation, the sixth frame includes a sensing response element field, and the fifth information is located in the sensing response element field.

[0032] In an optional implementation, the AP receives sensing requirement information from an initiator STA. With the optional implementation is implemented, when the STA serves as a sensing initiator, the STA sends a sensing requirement to the AP, and the AP performs any one or more of the foregoing implementations based on the sensing requirement sent by the STA, to coordinate and manage station devices participating in the sensing session.

[0033] According to a second aspect, an embodiment of this application provides a sensing session establishment method. The method includes: A station STA receives a first frame from an access point AP, where the first frame includes first information, the first information indicates a first role of the STA in a sensing session, and the first role of the STA in the sensing session is a transmitter and/or a receiver; and the STA sends a second frame to the AP, where the second frame includes confirm information for the first frame.

[0034] For beneficial effects of the sensing session establishment method according to the second aspect, refer to the beneficial effects of the sensing session establishment method according to the first aspect. Details are not described herein again.

[0035] In an optional implementation, the first frame further includes a first sensing parameter, and the first sensing parameter is used by the STA to perform sensing measurement and/or sensing data reporting in the sensing session.

[0036] In an optional implementation, the first sensing parameter includes one or more of the following parameters: an operation parameter, a feedback type, a sensing type, or a feedback address.

[0037] In an optional implementation, the first frame includes a common information field and a user information field, and the first information is located in the common information field and/or the user information field; the first frame includes a station information field, and the first information is located in the station information field; or the first frame includes a common information field and a station information field, and the first information is located in the common information field and/or the station information field.

[0038] In an optional implementation, the second frame includes a confirm element field, and the confirm information is located in the confirm element field.

[0039] In an optional implementation, the STA receives a third frame from the AP, where the third frame includes second information, and the second information is used to request the STA to participate in the sensing session; and the STA sends a fourth frame to the AP, where the fourth frame includes third information, and the third information indicates whether the STA confirms to participate in the sensing session.

[0040] In an optional implementation, when the third information indicates that the STA confirms to participate in the sensing session, the third information further includes a second role supported by the STA in the sensing session and a second sensing parameter corresponding to the second role.

[0041] In an optional implementation, the third frame includes a common information field, and the second information is located in the common information field; or the third frame includes a sensing request element field, and the second information is located in the sensing request element field.

[0042] In an optional implementation, the fourth frame includes a sensing confirm element field, and the third information is located in the sensing confirm element field; or the fourth frame includes a sensing response element field, and the third information is located in the sensing response element field.

[0043] In an optional implementation, the first frame includes a sensing request element field, and the first information is located in the sensing request element field.

[0044] In an optional implementation, the second frame includes a sensing response element field, and the confirm information is located in the sensing response field.

[0045] In an optional implementation, the STA receives a fifth frame from the AP, where the fifth frame includes fourth information, and the fourth information is used to request the STA to participate in the sensing session by using a third role and a fourth sensing parameter; and the STA sends a sixth frame to the AP, where the sixth frame includes fifth information, and the fifth information indicates whether the STA confirms to participate in the sensing session by using the third role and the fourth sensing parameter.

[0046] In an optional implementation, when the fifth information indicates that the STA participates in the sensing session based on the third role, but the STA does not participate in the sensing session based on the fourth sensing parameter, the fifth information further includes a fifth sensing parameter of the STA.

[0047] In an optional implementation, the fifth frame includes a sensing request element field, and the fourth information is located in the sensing request element field.

[0048] In an optional implementation, the sixth frame includes a sensing response element field, and the fifth information is located in the sensing response element field.

[0049] In an optional implementation, the STA sends sensing requirement information to the AP.

[0050] According to a third aspect, this application provides a communication apparatus. The apparatus may be an apparatus in an access point, or an apparatus that can be used together with an access point; or the apparatus may be an apparatus in a station, or an apparatus that can be used together with a station. The communication apparatus may alternatively be a chip system. The communication apparatus may perform the method of the access point according to the first aspect or the second aspect; or the communication apparatus may perform the method of the station according to the first aspect or the second aspect. A function of the communication apparatus may be implemented by hardware, or may be implemented by hardware by executing corresponding software. The hardware or the software includes one or more units corresponding to the functions. The unit may be software and/or hardware. For operations performed by the communication apparatus and beneficial effects thereof, refer to the method according to the first aspect or the second aspect, and the beneficial effects thereof. Repeated content is not described again.

[0051] According to a fourth aspect, this application provides a communication apparatus. The communication apparatus includes a processor and a memory. The memory is configured to store one or more computer programs, and the one or more computer programs include computer-executable instructions. When the communication apparatus runs, the processor executes the one or more computer programs stored in the memory, to enable the communication apparatus to perform the method of the access point according to the first aspect or the second aspect, or perform the method of the station according to the first aspect or the second aspect.

[0052] According to a fifth aspect, this application provides a computer-readable storage medium. The computer-readable storage medium is configured to store a computer program or instructions. When the computer program or instructions are run, the methods performed by the station or the access point according to the foregoing aspects are implemented.

- 5 **[0053]** According to a sixth aspect, a computer program product including instructions is provided. When the computer program product is run on a computer, the methods according to the foregoing aspects are implemented.

BRIEF DESCRIPTION OF DRAWINGS

[0054] FIG. 1 is a schematic diagram of a system architecture according to this application;

- 10 **[0055]** FIG. 2 is a schematic diagram of a D2D communication scenario according to this application;

[0056] FIG. 3 is a schematic diagram of an application scenario of a wireless sensing technology according to this application;

- 15 **[0057]** FIG. 4 is a schematic diagram of a channel sounding procedure according to this application;

[0058] FIG. 5a is a schematic diagram of a phase included in a sensing session according to this application;

[0059] FIG. 5b is a schematic diagram of a measurement phase according to this application;

[0060] FIG. 5c is a schematic diagram of a reporting phase according to this application;

- 20 **[0061]** FIG. 6a is a flowchart of a sensing session establishment method according to this application;

[0062] FIG. 6b-1 and FIG. 6b-2 are a schematic diagram of a frame structure according to this application;

[0063] FIG. 6c is a schematic diagram of another frame structure according to this application;

- 25 **[0064]** FIG. 6d is a schematic diagram of still another frame structure according to this application;

[0065] FIG. 6e is a schematic diagram of still another frame structure according to this application;

- 30 **[0066]** FIG. 6f is a schematic diagram of still another frame structure according to this application;

[0067] FIG. 6g is a schematic diagram of still another frame structure according to this application;

[0068] FIG. 6h is a schematic diagram of an application scenario according to this application;

- [0069]** FIG. 7a is a flowchart of another sensing session establishment method according to this application;
- [0070]** FIG. 7b is a schematic diagram of still another frame structure according to this application;
- 5 **[0071]** FIG. 7c is a schematic diagram of still another frame structure according to this application;
- [0072]** FIG. 7d is a schematic diagram of still another frame structure according to this application;
- [0073]** FIG. 7e is a schematic diagram of still another frame structure according to this application;
- 10 **[0074]** FIG. 7f is a schematic diagram of another application scenario according to this application;
- [0075]** FIG. 8a is a flowchart of still another sensing session establishment method according to this application;
- 15 **[0076]** FIG. 8b-1 and FIG. 8b-2 are a schematic diagram of still another frame structure according to this application;
- [0077]** FIG. 8c is a schematic diagram of still another application scenario according to this application;
- [0078]** FIG. 9a is a schematic diagram of still another sensing application scenario according to this application;
- 20 **[0079]** FIG. 9b is a schematic diagram of a sensing session according to this application;
- [0080]** FIG. 9c is a schematic diagram of another sensing session according to this application;
- [0081]** FIG. 9d is a schematic diagram of still another sensing session according to this application;
- 25 **[0082]** FIG. 9e is a schematic diagram of still another sensing session according to this application;
- [0083]** FIG. 9f is a schematic diagram of still another sensing session according to this application;
- [0084]** FIG. 9g is a schematic diagram of still another sensing session according to this application;
- 30 **[0085]** FIG. 10a is a schematic diagram of still another sensing application scenario according to this application;
- [0086]** FIG. 10b is a schematic diagram of a sensing session according to this application;
- [0087]** FIG. 10c is a schematic diagram of another sensing session according to this application;
- 35 **[0088]** FIG. 10d is a schematic diagram of still another sensing session according to this

application;

[0089] FIG. 11a is a schematic diagram of still another sensing application scenario according to this application;

[0090] FIG. 11b is a schematic diagram of a sensing session according to this application;

5 [0091] FIG. 11c is a schematic diagram of another sensing session according to this application;

[0092] FIG. 11d is a schematic diagram of still another sensing session according to this application;

[0093] FIG. 11e is a schematic diagram of still another sensing session according to this application;

10 [0094] FIG. 11f is a schematic diagram of still another sensing session according to this application;

[0095] FIG. 11g is a schematic diagram of still another sensing session according to this application; and

[0096] FIG. 12 is a schematic block diagram of a communication apparatus according to an
15 embodiment of this application.

DESCRIPTION OF EMBODIMENTS

[0097] To make objectives, technical solutions, and advantages of this application clearer, the following further describes this application in detail with reference to the accompanying drawings.

[0098] In the specification, the claims, and the accompanying drawings of this application,
20 terms "first", "second", and the like are intended to distinguish between different objects but do not indicate a particular order. In addition, terms "including" and "having" and any other variants thereof are intended to cover a non-exclusive inclusion. For example, a process, a method, a system, a product, or a device that includes a series of steps or units is not limited to the listed steps or units, but optionally further includes an unlisted step or unit, or optionally further includes another
25 inherent step or unit of the process, the method, the product, or the device.

[0099] An "embodiment" mentioned in this specification means that a particular feature, structure, or characteristic described with reference to this embodiment may be included in at least one embodiment of this application. The phrase shown in various locations in the specification may not necessarily refer to a same embodiment, and is not an independent or optional
30 embodiment exclusive from another embodiment. It is explicitly and implicitly understood by a person skilled in the art that embodiments described in the specification may be combined with another embodiment.

[00100] In this application, "at least one (item)" means one or more, "a plurality of" means two

or more, "at least two (item)" means two or three or more, and "and/or" is used to describe an association relationship between associated objects and indicates that three relationships may exist. For example, "A and/or B" may indicate the following three cases: Only A exists, only B exists, and both A and B exist, where A and B may be singular or plural. The character "/" generally indicates an "or" relationship between the associated objects. "At least one of the following items (pieces)" or a similar expression thereof refers to any combination of these items, including any combination of singular items (pieces) or plural items (pieces). For example, at least one of a, b, or c may indicate a, b, c, a and b, a and c, b and c, or a, b, and c, where a, b, and c may be singular or plural.

[00101] To better understand embodiments of this application, the following first describes a system architecture in embodiments of this application.

[00102] The system architecture in this application includes one or more first wireless devices and one or more second wireless devices. The first wireless device may be an access point (access point, AP) station, and the second wireless device may be a non-access point station (non-access point station, non-AP STA). For ease of description, in this specification, a station of an access point type is referred to as an access point (AP), and a station of a non-access point type is referred to as a station (station, STA).

[00103] FIG. 1 is a schematic diagram of a system architecture 10 according to an embodiment of this application. In FIG. 1, an example in which a first wireless device is an access point (that is, a device 20 in the system architecture 10) and a second wireless device is a station (that is, a device 30 in the system architecture 10) is used.

[00104] The access point may be an access point used by a terminal device (such as a mobile phone) to access a wired (or wireless) network, and is mainly deployed at home, in a building, and in a park. A typical coverage radius is tens of meters to 100-odd meters. Certainly, the access point may alternatively be deployed outdoors. The access point is equivalent to a bridge that connects the wired network and the wireless network. A main function of the access point is to connect various wireless network clients together and then connect the wireless network to the Ethernet. Specifically, the access point may be a terminal device (such as a mobile phone) or a network device (such as a router) with a Wi-Fi chip. The access point may be a device that supports the 802.11be standard or a standard after 802.11be.

[00105] The station may be a wireless communication chip, a wireless sensor, or a wireless communication terminal. For example, the station may be a mobile phone, a tablet computer, a set-top box, a smart television set, a smart wearable device, a vehicle-mounted communication device, or a computer that supports a Wi-Fi communication function.

[00106] The access point and the station interact with each other by using a wireless network

protocol, for example, a Wi-Fi protocol. The access point may send a downlink measurement packet, and coordinate the station to perform channel measurement. The station may feed back information to the access point based on a measurement result, so that the access point determines wireless sensing or information in another field based on the information fed back by the station.

5 It should be learned that there may be a plurality of stations in a coverage area of one access point, and the access point may perform proper resource scheduling on each station to improve a system throughput, robustness, and the like.

[00107] To facilitate understanding of content of this solution, the following describes some terms in embodiments of this application, to help a person skilled in the art have a better
10 understanding.

[00108] 1. Channel state information (channel state information, CSI)

[00109] The CSI is a channel measurement result obtained by a station (station, STA) by measuring a training packet sent by an access point (access point, AP), and is used to reflect a current status of a wireless channel. In the Wi-Fi protocol, the CSI is measured for each orthogonal
15 frequency division multiplexing (orthogonal frequency-division multiplexing, OFDM) subcarrier group, to obtain a CSI matrix corresponding to the subcarrier group. A size of the CSI matrix is a quantity of transmit antennas multiplied by a quantity of receive antennas. Each matrix element is a complex number including real and imaginary parts. Therefore, when there are a large quantity of antennas and a large quantity of subcarriers, an overall data amount of the CSI may reach more
20 than 3000 bytes per packet. This consumes a large quantity of communication bandwidth resources.

[00110] A transmitter and a receiver do not need to be synchronized. An illumination signal may be a common communication physical layer protocol data unit (physical layer protocol data unit, PPDU) or a modified communication PPDU, and may be classified into coordinated CSI sensing and non-coordinated CSI sensing based on a working manner of the illumination signal.
25 In coordinated CSI sensing, a sensing transmitter participates in a sensing session and sends an illumination signal to illuminate a region of interest, and a sensing receiver receives the signal to measure the region of interest, that is, obtains information related to a location of a measured target by performing related processing on the CSI. In non-coordinated CSI sensing, there is no dedicated sensing transmitter in the sensing session, and the sensing receiver measures the region of interest
30 by occasionally receiving the illumination signal in an environment.

[00111] 2. Device-to-device communication (device-to-device, D2D)

[00112] A device in a D2D communication scenario may be a relay endpoint directional multi-gigabit station (relay endpoint directional multi-gigabit STA, REDS), a device configured to transmit a signal is referred to as a source REDS, and a device configured to receive a signal is
35 referred to as a target REDS. FIG. 2 is a D2D communication scenario according to this application.

In the D2D communication scenario, a STA 1 is a source REDS, a STA 2 is a target REDS, and a STA 3 is a relay directional multi-gigabit station (relay directional multi-gigabit STA, RDS). Generally, the STA 1 and the STA 2 directly communicate with each other through a direct link 20. When the direct link 20 between the STA 1 and the STA 2 is interrupted, a frame for redirection addressing of the STA 1 is transmitted to the target REDS (the STA 2) by using the STA 3. The STA 3 forwards the frame received from the STA 1 to the STA 2, and forwards the frame received from the STA 2 to the STA 1. After the direct link 20 between the STA 1 and the STA 2 is restored, direct communication between the STA 1 and the STA 2 may be restored.

[00113] 3. Wireless sensing technology

[00114] In an application process of the wireless sensing technology, devices participating in sensing may be classified into a sensing initiator and a sensing responder, or a sensing signal transmitter and a sensing signal receiver. A device configured to respond to the sensing initiator may be understood as a sensing responder, for example, a sensing signal transmitter and a sensing signal receiver. Refer to FIG. 3. When the wireless sensing technology is used to sense a human body movement, a wireless sensing system includes a sensing initiator 301, a sensing signal transmitter 302, a sensing signal receiver 303, and a sensing target 304. In the system shown in FIG. 3, the sensing initiator 301 is configured to initiate a sensing session, that is, may be understood as notifying the sensing signal transmitter 302 to transmit a sensing signal to the sensing signal receiver 303. In this case, both the sensing signal transmitter 302 and the sensing signal receiver 303 are sensing responders. The sensing signal received by the sensing signal receiver 303 includes a direct path signal S1 and a reflected signal S2 reflected by the sensing target 304. In this way, when the sensing target 304 moves, the reflected signal S2 changes, and a superimposed sensing signal received by the sensing signal receiver 303 also changes accordingly. In this case, the sensing signal receiver 303 detects that a channel of a wireless link changes (which is represented as a change of an amplitude and a phase of channel information). Generally, the channel of the wireless link is quantized and represented as channel information in a communication protocol, for example, channel state information (channel state information, CSI). Further, the sensing initiator 301 may initiate channel sounding on the sensing signal receiver 303 at a specific time interval, and learn, based on a change of CSI reported by the receiver 303, whether the sensing target 304 moves and what specific action the sensing target 304 performs.

[00115] It should be understood that the sensing initiator, also referred to as an initiator, is configured to initiate a sensing session to the sensing responder based on a sensing requirement; the sensing signal transmitter (also referred to as a sensing transmitter or transmitter) is configured to transmit a sensing signal; and the sensing signal receiver (also referred to as a sensing receiver or receiver) is configured to receive the sensing signal, obtain a sensing measurement result, and

report the sensing measurement result to the sensing initiator. The sensing initiator may be classified into the following two types based on whether the sensing initiator participates in receiving/sending of the sensing signal: an independent sensing initiator and a non-independent sensing initiator. The non-independent sensing initiator refers to a sensing initiator that participates in receiving/sending of the sensing signal. That is, in the sensing session, the sensing initiator further has a function of the sensing transmitter or the sensing receiver. The independent sensing initiator refers to a sensing initiator that does not participate in transmitting the sensing signal. That is, in the sensing session, the sensing initiator does not have a function of the sensing transmitter or the sensing receiver.

[00116] 4. Channel sounding procedure

[00117] FIG. 4 shows a solution in which a sensing initiator broadcasts a null data packet (null data packet, NDP) to enable a plurality of sensing responders to simultaneously perform channel measurement. First, in this solution, the sensing initiator sends a null data packet announcement (null data packet announcement, NDPA) message to notify the plurality of sensing responders to perform channel measurement. Then, the sensing initiator sends an NDP measurement packet. The plurality of sensing responders simultaneously perform channel measurement. After the sensing responder performs channel measurement, a first sensing responder notified in the NDPA feeds back channel information. In this case, the sensing initiator may select a part of the channel information for feedback, or indicate that a channel does not change in feedback. Then, the sensing initiator sequentially uses a Poll message to request another sensing responder to perform channel information feedback, and the another sensing responder sequentially perform feedback.

[00118] 5. Sensing session

[00119] As shown in FIG. 5a, the sensing session usually includes one or more of the following phases: an establishment phase, a measurement phase, a reporting phase, and a termination phase.

[00120] 5.1 Establishment phase

[00121] In the establishment phase, a sensing initiator establishes a sensing session and determines an operation parameter (for example, a parameter of a sensing transmitter and a parameter of a sensing receiver) associated with the sensing session, and may exchange the parameter with a STA.

[00122] 5.2 Measurement phase

[00123] In the measurement phase, the sensing transmitter sends a sensing signal to the sensing receiver. After receiving the sensing signal, the sensing receiver performs corresponding processing on the sensing signal to obtain a sensing measurement result. For example, corresponding processing on the sensing signal is channel estimation. Specifically, an initiator (beamformer) sends an NDP, and the receiver (beamformee) receives the NDP and compares the

NDP with original information to obtain CSI information. Because the CSI information includes information such as an arrival time and an angle of the sensing signal, the receiver may further process the CSI information by using a specific algorithm, and extract the information such as the arrival time and the angle of the sensing signal from the CSI information, to obtain the sensing measurement result.

[00124] The following describes the measurement phase in detail based on the type of the sensing initiator (an independent initiator or a non-independent initiator). For simplicity, the measurement phase is described by using an example in which an AP serves as an initiator in a sensing session. As shown in FIG. 5b, devices participating in the sensing session include the AP, a STA 1, and a STA 2.

[00125] When the AP is an independent initiator (that is, the AP does not participate in receiving/sending of a sensing signal), the STA 1 serves as a sensing signal transmitter, and the STA 2 serves as a sensing signal receiver, the measurement phase is shown in case 1 in FIG. 5b. The STA 1 sends a sensing signal to the STA 2, and the STA 2 receives the sensing signal and performs measurement.

[00126] When the AP is a non-independent initiator (that is, the AP participates in receiving/sending of a sensing signal), the AP is a sensing signal transmitter, and both the STA 1 and the STA 2 are sensing signal receivers, the measurement phase is explicit measurement (that is, the initiator is also a transmitter). As shown in case 2 in FIG. 5b, the AP sends a sensing signal to both the STA 1 and the STA 2, and the STA 1 and the STA 2 separately receive the sensing signal and perform measurement.

[00127] When the AP is a non-independent initiator (that is, the AP participates in receiving/sending of a sensing signal), only the AP is a sensing signal receiver in the sensing session, and both the STA 1 and the STA 2 are sensing signal transmitters, the measurement phase is implicit measurement (that is, only the initiator is a receiver). As shown in case 3 in FIG. 5b, the STA 1 and the STA 2 separately send a sensing signal to the AP, and the AP receives the sensing signal from both the STA 1 and the STA 2 and performs measurement.

[00128] When the AP is a non-independent initiator (that is, the AP participates in receiving/sending of a sensing signal), the AP is a sensing signal receiver in the sensing session, the STA 1 is a sensing signal transmitter, and the STA 2 is a sensing signal receiver, the measurement phase is a combination of explicit and implicit measurement (that is, in addition to the case where the initiator is the receiver, there is another receiver in the sensing session). As shown in case 4 in FIG. 5b, the STA 1 sends a sensing signal to both the AP and the STA 2, and the AP and the STA 2 separately receive the sensing signal from the STA 1 and perform measurement.

[00129] 5.3 Reporting phase

[00130] In the reporting phase, the receiver sends the measurement result obtained in the measurement phase to the initiator. As shown in FIG. 5c, the manner in which the receiver sends the measurement result to the initiator includes: a polling-based manner (as shown in case 1 in FIG. 5c), a scheduling-based manner (as shown in case 2 in FIG. 5c), and a contention-based manner (as shown in a case 3 in FIG. 5c). It should be learned that, for convenience, in FIG. 5c, a case in which the AP is an initiator in the sensing session, the STA 1 is a receiver, and the STA 2 is a receiver is used as an example for description, and should not be considered as a specific limitation on this application.

[00131] In the polling-based manner, the initiator sends a Poll frame to the receiver, and the receiver that receives the Poll frame feeds back the measurement result to the transmitter until all the receivers complete feedback. For example, as shown in case 1 in FIG. 5c, the AP sends a Poll frame to both the STA 1 and the STA 2, the STA 1 feeds back a measurement result of the STA 1 to the AP based on the Poll frame, and the STA 2 feeds back a measurement result of the STA 2 to the AP based on the Poll frame.

[00132] In the scheduling-based manner, the initiator sends a feedback trigger (feedback trigger) frame to the receiver, and the receiver sends the measurement result of the receiver to the initiator based on the feedback trigger frame. For example, as shown in case 2 in FIG. 5c, the AP sends a feedback trigger frame to both the STA 1 and the STA 2, the STA 1 feeds back a measurement result of the STA 1 to the AP based on the feedback trigger frame, and the STA 2 feeds back a measurement result of the STA 2 to the AP based on the feedback trigger frame.

[00133] In the contention-based manner, receivers contend with each other, and independently send a measurement result to the initiator based on a channel contention sequence. For example, as shown in case 3 in FIG. 5c, the STA 1 and the STA 2 contend for a channel resource, and the STA 2 first obtains the channel resource through contention. In this case, the STA 2 first feeds back a measurement result of the STA 2 to the AP, and then the STA 1 feeds back a measurement result of the STA 1 to the AP.

[00134] 5.4 Termination phase

[00135] In the termination phase, the STA (which may be understood as a STA participating in the sensing session) stops measurement and terminates the sensing session.

[00136] Generally, in a wireless sensing system, a sensing initiator, a sensing responder, a sensing signal transmitter, and a sensing signal receiver are all fixed at a specific location (or may be understood as a stationary device). According to the sensing measurement procedure shown in FIG. 3, when the sensing target is far away from the sensing signal transmitter (or the sensing signal receiver), accuracy of sensing measurement is reduced. In addition, if a small quantity of

devices participate in sensing measurement, measurement precision of the sensing target may be reduced because information about the sensing target is not completely obtained. If a large quantity of devices participate in sensing measurement, the sensing initiator needs to poll all sensing signal receivers to obtain all information about the sensing target. As a result, a delay of obtaining information is increased, and further, measurement precision of the sensing target may be reduced.

[00137] In this application, the AP manages the devices participating in sensing, so that the devices participating in the sensing session and roles of the devices in the sensing session can be flexibly determined. This avoids a case in which there are a large quantity or a small quantity of devices participating in the sensing session, and may also avoid a case in which a device that is far away from the sensing target is determined as the sensing transmitter (or the sensing receiver). In this way, a delay of obtaining information is reduced and measurement precision of the sensing target is improved.

[00138] The following further describes a sensing session establishment method and a communication apparatus provided in this application with reference to the accompanying drawings.

[00139] FIG. 6a is a schematic flowchart of a sensing session establishment method according to an embodiment of this application. As shown in FIG. 6a, the sensing session establishment method includes the following step 601 and step 602. The method shown in FIG. 6a may be performed by an AP and a STA. Alternatively, the method shown in FIG. 6a may be performed by a chip in an AP and a chip in a STA. In FIG. 6a, an example in which the method is performed by the AP and the STA is used for description.

[00140] 601: The AP sends a first frame to a first STA, where the first frame includes first information, and the first information indicates a first role of the first STA in a sensing session. The first role of the first STA in the sensing session is a transmitter and/or a receiver. The first STA is a STA participating in the sensing session in a second STA associated with the AP.

[00141] In other words, the second STA is a STA associated with the AP, that is, the STA is within a signal range of the AP and has a communication connection to the AP. The first STA is a STA participating in the sensing session in the second STA, and the first STA may be a part of second STAs, or may be all of second STAs. This is not specifically limited in this application.

The AP sends the first frame to the first STA, to allocate a role of the first STA in the sensing session to the first STA.

[00142] For example, a STA 1, a STA 2, and a STA 3 are STAs (that is, the second STAs) associated with the AP, and the STAs (that is, the first STAs) participating in the sensing session are the STA 1 and the STA 2. In this case, the AP sends the first frame to the STA 1, and the first frame indicates that a role of the STA 1 in the sensing session is a transmitter and a receiver. The

AP and the STA 2 send a first frame, where the first frame indicates that a role of the STA 2 in the sensing session is a receiver.

[00143] In a possible implementation, the first frame further includes a first sensing parameter, and the first sensing parameter is used by the first STA to perform sensing measurement and/or sensing data reporting in the sensing session. The first sensing parameter includes but is not limited to one or more of the following parameters: an operation parameter, a feedback type, a sensing type, or a feedback address. The feedback address may be understood as indicating a device to which the STA feeds back a sensing report. The feedback type indicates a specific sensing report type used by the STA to provide feedback. The feedback type includes but is not limited to: CSI, compressed CSI, or measurement result information (speed information, angle information, distance information, or the like). The operation parameter indicates information such as a speed, duration, or an angle at which the STA receives/sends a data packet.

[00144] In other words, when allocating the first role participating in the sensing session to each STA participating in the sensing session, the AP further allocates the first sensing parameter corresponding to the first role to the STA, so that the STA can participate in the sensing session by using the first role and the first sensing parameter.

[00145] For example, the STA 1 is a STA associated with the AP and participating in a sensing session, and the AP sends a first frame to the STA 1. First information in the first frame includes: a first role (that is, a receiver), a first sensing parameter (that is, 10 data packets are received within 1 ms), a feedback type (that is, CSI), and a feedback address (that is, a MAC address of the AP). That is, the AP indicates to the STA 1 by using the first frame, where the STA 1 is a receiver in the sensing session, a receiving speed of the STA 1 in a sensing measurement phase is receiving 10 data packets every 1 ms, and the STA 1 feeds back CSI to the AP in a sensing report phase.

[00146] For this scenario, the following separately describes in detail frame structures of the first frame.

[00147] Structure 1: The first frame includes a common information field and a user information field, and the first information is located in the common information field and/or the user information field.

[00148] In this case, the common information field is used to configure the same configuration content of the STAs participating in the sensing session, and may be understood as configuration information shared by the STAs participating in the sensing session in the first information, that is, common parameter information. User information fields are in a one-to-one correspondence with the STAs participating in the sensing session, and the user information field is used to configure the configuration content specific to the STAs participating in the sensing session, and may be understood as parameter information specific to the STAs participating in the sensing session in

the first information, that is, parameter information other than the common parameter information in the first information.

[00149] For example, in a sensing session, the AP requests the STA 1 to participate in the sensing session by using a first role including both a receiver and a transmitter, and requests the STA 2 to participate in the sensing session by using a first role including a receiver. First information corresponding to the STA 1 includes: A feedback address is an AP, a feedback type is CSI, a first role is a receiver and a transmitter, and an operation parameter is that the STA 1 sends 10 data packets every 1 ms when serving as a transmitter, and receives 10 data packets every 1 ms when serving as a receiver. First information corresponding to the STA 2 includes: A feedback address is an AP, a feedback type is CSI, a first role is a receiver, and an operation parameter is receiving 10 data packets every 1 ms. In this case, the AP sends the first frame to the STA 1 and the STA 2. The common information field in the frame includes that the feedback address is the AP and the feedback type is the CSI in the first information (that is, a part of configuration information shared by the STA 1 and the STA 2 in the first information). The user information field corresponding to the STA 1 in the frame includes a part of first information specific to the STA 1: The first role is a receiver and a transmitter, and the operation parameter is that the STA 1 sends 10 data packets every 1 ms when serving as a transmitter, and receives 10 data packets every 1 ms when serving as a receiver. The user information field corresponding to the STA 2 in the frame includes a part of first information specific to the STA 2: The first role is a receiver, and the operation parameter is receiving 10 data packets every 1 ms.

[00150] For example, FIG. 6b-1 and FIG. 6b-2 are a schematic diagram of a frame structure according to this application. The first frame is a trigger (Trigger) frame, and the Trigger frame includes a common information (Common Info) field and a user information (User Info) field. The following describes in detail the Common Info field and the User Info field of the first frame.

[00151] 1. Common Info field

[00152] FIG. 6b-1 and FIG. 6b-2 are a schematic diagram of an expanded structure of the Common Info field of the first frame shown by a module 60. The Common Info field includes a trigger type (Trigger Type) subfield and a trigger dependent common information (Trigger Dependent Common Info) subfield.

[00153] 1.1 Trigger Type subfield

[00154] The Trigger Type subfield indicates a function type of the Trigger frame. For example, when a value of the Trigger Type subfield is 9, it indicates that the Trigger frame is used to trigger a sensing (Sensing) operation.

[00155] 1.2 Trigger Dependent Common Info subfield

[00156] The Trigger Dependent Common Info subfield is used to configure common parameter

information in the first information. For example, the Trigger Dependent Common Info subfield in FIG. 6b-1 and FIG. 6b-2 includes a sensing result destination (Sensing Results Destination field) subfield, and the Sensing Results Destination field is used to notify all receivers of MAC addresses of target devices (that is, devices receiving the feedback results) when the receivers feed back the measurement results.

[00157] 2. User Info field

[00158] FIG. 6b-1 and FIG. 6b-2 are a schematic diagram of an expanded structure of the User Info field of the first frame shown by a module 61. The User Info field includes a trigger dependent user information (Trigger Dependent User Info) subfield. The Trigger Dependent User Info subfield is used to configure specific first information (which may be understood as parameter information other than the common parameter information of the STA) corresponding to the STA in the first information. The Trigger Dependent User Info subfield may include a sensing request information (Sensing Request Info) subfield and a sensing type (Sensing Type) subfield.

[00159] 2.1 Sensing Request Info subfield

[00160] The Sensing Request Info subfield includes a sensing role indication (Sensing Roles Indication) subfield and a sensing feedback type (Sensing Feedback Type) subfield.

[00161] The Sensing Roles Indication subfield indicates a role function. For example, the Sensing Roles Indication subfield includes two bits. When a value of the two bits is 00, it indicates that a role is a receiver (or may be a transmitter); when a value of the two bits is 01, it indicates that a role is a transmitter (or may be a receiver); or when a value of the two bits is 10, it indicates that a role is both a receiver and a transmitter (self-sending and self-receiving).

[00162] The Sensing Feedback Type subfield indicates that the feedback type is CSI, compressed CSI, a final result, or the like to feed back a result. 0 indicates original CSI feedback; 1 indicates compressed CSI feedback; 2 indicates final result speed information; 3 indicates final result angle information; 4 indicates final result distance information; and the like.

[00163] 2.2 Sensing Type subfield

[00164] The Sensing Type subfield indicates a data sending type (which may be understood as the foregoing operation parameter). For example, the Sensing Type subfield indicates two data sending types: a burst-based (burst) type or a continuous sending-based type. For the burst-based type (that is, Type 1 of the Sensing Type subfield shown by the module 61 in FIG. 6b-1 and FIG. 6b-2), the Sensing Type subfield includes a pattern (pattern) subfield, a group measurement duration (Group measurement duration) subfield, a number of group (Number of Group) subfield, and an interval between group (Interval between Group) subfield. It can be learned that, in the burst-based type, the Sensing Type subfield indicates sending duration, a quantity of sending times in a group, and an interval between groups. For the continuous sending-based type (that is, Type 2

of the Sensing Type subfield shown by the module 61 in FIG. 6b-1 and FIG. 6b-2), the Sensing Type subfield includes a value of a pattern (pattern) subfield, a measurement duration (Measurement duration) subfield, and a number (Number) subfield. In the continuous sending-based type, the Sensing Type subfield indicates information such as total sending duration, a total quantity of sent data packets, and a packet/beam sending period/interval.

[00165] For example, in the burst-based type, the Sensing Type subfield includes a pattern (pattern) subfield, a group measurement duration (Group measurement duration) subfield, a number of group (Number of Group) subfield, and an interval between group (Interval between Group) subfield. The pattern subfield indicates a frequency pattern for sending data based on a burst. For example, when a field value of the pattern subfield is 0, it indicates that sending is performed at a low frequency. When a field value of the pattern subfield is 1, it indicates that sending is performed at a high frequency. The group measurement duration (Group measurement duration) subfield indicates sending duration of a single packet group. The number of group (Number of Group) subfield indicates a quantity of sent NDPs in a single packet group. The interval between group (Interval between Group) subfield indicates an interval between packet groups.

[00166] Structure 2: The first frame includes a station information field, and the first information is located in the station information field.

[00167] For example, FIG. 6c is a schematic diagram of another frame structure of the first frame according to this application. The first frame is an announce (Announce) frame, and the Announce frame includes a station information (STA Info) subfield and a sounding dialog token (Sounding Dialog Token) subfield.

[00168] 1. Sounding Dialog Token subfield

[00169] The Sounding Dialog Token subfield includes an announcement type (Announcement Type) indication subfield, and the Announcement Type subfield indicates an announcement type of the announce frame. The announcement type includes: a very high throughput (Very-High-Throughput, VHT), high efficiency (High-Efficiency, HE), ranging (Ranging), and an extremely high throughput (Extremely High Throughput, EHT).

[00170] For example, the Announcement Type subfield includes two bits, and the Announcement Type subfield indicates the announcement type of the announce frame based on values of the two bits. As shown in Table 1, Table 1 shows a correspondence between a field value of the Announcement Type and the announcement type. When the Announcement Type subfield is set to 00, it indicates that the frame is a VHT announce frame. When the Announcement Type subfield is set to 01, it indicates that the frame is an HE announce frame. When the Announcement Type subfield is set to 10, it indicates that the frame is a Ranging announce frame. When the

Announcement Type subfield is set to 11, it indicates that the frame is an EHT announce frame. It should be learned that the Sensing announce frame may be represented by reusing a VHT/HE or the like.

Table 1

Announcement Type field value (field value)	Announce frame type
00	VHT
01	HE (Sensing)
10	Ranging
11	EHT

[00171] 2. Station information (STA Info) subfield

[00172] The first frame includes a plurality of station information (STA Info) subfields, that is, a STA Info 1 subfield to a STA Info n subfield shown in FIG. 6c. STA Info subfields are in a one-to-one correspondence with the STAs. The following uses the STA Info n subfield as an example for description. The STA Info n subfield includes a sensing information (Sensing Info) subfield, a sensing type (Sensing Type) subfield, and a sensing result destination (Sensing Results Destination) subfield.

[00173] 2.1 Sensing Results Destination subfield

[00174] The Sensing Results Destination subfield is used to notify the receiver of a MAC address of a destination terminal (that is, a device receiving the measurement result) that feeds back the measurement result.

[00175] 2.2 Sensing Type subfield

[00176] The Sensing Type subfield indicates a data sending type. The data sending type includes a burst-based (burst) type or a continuous sending-based type. For the burst-based type, the Sensing Type subfield includes a pattern (pattern) subfield, a group measurement duration (Group measurement duration) subfield, a number of group (Number of Group) subfield, and an interval between group (Interval between Group) subfield. It can be learned that, in the burst-based type, the Sensing Type subfield indicates sending duration, a quantity of sending times in a group, and an interval between groups. For the continuous sending-based type, the Sensing Type subfield includes a value of a pattern (pattern) subfield, a measurement duration (Measurement duration) subfield, and a number (Number) subfield. In the continuous sending-based type, the Sensing Type subfield indicates information such as total sending duration, a total quantity of sent data packets, and a packet/beam sending period/interval.

[00177] For example, in the burst-based type, the Sensing Type subfield includes a pattern

(pattern) subfield, a group measurement duration (Group measurement duration) subfield, a number of group (Number of Group) subfield, and an interval between group (Interval between Group) subfield. The pattern subfield indicates a frequency pattern for sending data based on a burst. For example, when a field value of the pattern subfield is 0, it indicates that sending is performed at a low frequency. When a field value of the pattern subfield is 1, it indicates that sending is performed at a high frequency. The group measurement duration (Group measurement duration) subfield indicates sending duration of a single packet group. The number of group (Number of Group) subfield indicates a quantity of sent NDPs in a single packet group. The interval between group (Interval between Group) subfield indicates an interval between packet groups.

[00178] 2.3 Sensing Feedback Type subfield

[00179] The Sensing Feedback Type subfield is used to configure a type of a measurement result fed back by the device. The type of feeding back the measurement result includes but is not limited to: CSI feedback, compressed CSI feedback, final result feedback (speed information, angle information, distance information, or the like), or the like.

[00180] For example, when a field value of the Sensing Feedback Type subfield is 0, it indicates that the CSI is fed back; when a field value of the Sensing Feedback Type subfield is 1, it indicates that the compressed CSI is fed back; when a field value of the Sensing Feedback Type subfield is 2, it indicates that the final result speed information is fed back; when a field value of the Sensing Feedback Type subfield is 3, it indicates that the final result angle information is fed back; or when a field value of the Sensing Feedback Type subfield is 4, it indicates that the final result distance information is fed back, and the like.

[00181] Structure 3: The first frame includes a common information field and a station information field, and the first information is located in the common information field and/or the station information field.

[00182] In this case, the common information field is used to configure the same configuration content of the STAs participating in the sensing session, and may be understood as configuration information shared by the STAs participating in the sensing session in the first information, that is, common parameter information. Station information fields are in a one-to-one correspondence with the STAs participating in the sensing session, and the user information field is used to configure the configuration content specific to the STAs participating in the sensing session, and may be understood as parameter information specific to the STAs participating in the sensing session in the first information, that is, parameter information other than the common parameter information in the first information.

[00183] For example, FIG. 6d is a schematic diagram of still another frame structure of the first

frame according to this application. The first frame is a sensing announcement (Sensing Announcement) frame, and the Sensing Announcement frame includes a common information (Common Info) field and a station information (STA Info) field. The following describes in detail the Common Info field and the STA Info field of the first frame.

5 **[00184]** 1. Common Info field

[00185] The Common Info field includes a Sensing Results Destination subfield, and the Sensing Results Destination subfield is used to notify the receiver to send a measurement result (for example, CSI or compressed CSI) to a terminal device corresponding to the MAC address.

[00186] 2. STA Info field

10 **[00187]** The first frame includes a plurality of station information (STA Info) subfields, that is, a STA Info 1 subfield to a STA Info n subfield shown in FIG. 6d. STA Info subfields are in a one-to-one correspondence with the STAs. Each STA Info subfield includes a sensing information (Sensing Info) subfield and a sensing type (Sensing Type) subfield.

[00188] 2.1 Sensing Info subfield

15 **[00189]** The Sensing Info subfield includes a sensing role indication (Sensing Role Indication) subfield and a sensing feedback type (Sensing Feedback Type) subfield.

[00190] The Sensing Role Indication subfield is used to configure a role of the STA participating in the sensing session. For example, the Sensing Roles Indication subfield includes two bits. When a value of the two bits is 00, it indicates that the role is a receiver (or may be a transmitter); when
20 a value of the two bits is 01, it indicates that the role is a transmitter (or may be a receiver); or when a value of the two bits is 10, it indicates that the role is both a receiver and a transmitter (self-sending and self-receiving).

[00191] The Sensing Feedback Type subfield is used to configure a type of a measurement result fed back by the device. The type of feeding back the measurement result includes but is not limited
25 to: CSI feedback, compressed CSI feedback, final result feedback (speed information, angle information, distance information, or the like), or the like.

[00192] 2.2 Sensing Type subfield

[00193] The Sensing Type subfield indicates a data sending type (which may be understood as the foregoing operation parameter). The data sending type includes a burst-based (burst) type or a
30 continuous sending-based type. For the burst-based type, the Sensing Type subfield includes a pattern (pattern) subfield, a group measurement duration (Group measurement duration) subfield, a number of group (Number of Group) subfield, and an interval between group (Interval between Group) subfield. It can be learned that, in the burst-based type, the Sensing Type subfield indicates sending duration, a quantity of sending times in a group, and an interval between groups. For the
35 continuous sending-based type, the Sensing Type subfield includes a value of a pattern (pattern)

subfield, a measurement duration (Measurement duration) subfield, and a number (Number) subfield. In the continuous sending-based type, the Sensing Type subfield indicates information such as total sending duration, a total quantity of sent data packets, and a packet/beam sending period/interval.

5 **[00194]** For example, in the burst-based type, the Sensing Type subfield includes a pattern (pattern) subfield, a group measurement duration (Group measurement duration) subfield, a number of group (Number of Group) subfield, and an interval between group (Interval between Group) subfield. The pattern subfield indicates a frequency pattern for sending data based on a burst. For example, when a field value of the pattern subfield is 0, it indicates that sending is performed at a low frequency. When a field value of the pattern subfield is 1, it indicates that sending is performed at a high frequency. The group measurement duration (Group measurement duration) subfield indicates sending duration of a single packet group. The number of group (Number of Group) subfield indicates a quantity of sent NDPs in a single packet group. The interval between group (Interval between Group) subfield indicates an interval between packet groups.

15 **[00195]** Structure 4: The first frame includes a sensing request element field, and the first information is located in the sensing request element field.

20 **[00196]** For example, FIG. 6e is a schematic diagram of a structure of the first frame according to this application. The first frame is a sensing request (Sensing Request) frame, the sensing request (Sensing Request) frame includes a sensing request element (Sensing Request Element) field, and the first information is located in the Sensing Request Element field.

25 **[00197]** Specifically, the sensing request element (Sensing Request Element) field includes a sensing request information (Sensing Request Info) subfield, a sensing type (Sensing Type) subfield, and a sensing result destination (Sensing Results Destination) subfield.

30 **[00198]** 1. Sensing Request information (Sensing Request Info) subfield

30 **[00199]** The Sensing Request Info subfield includes a standalone indication (Standalone Indication) subfield, a sensing request indication (Sensing Request Indication) subfield, a sensing role indication (Sensing Roles Indication) subfield, and a sensing feedback type (Sensing Feedback Type) subfield.

30 **[00200]** 1.1 Standalone indication (Standalone Indication) subfield

35 **[00201]** It should be stated that, when a device (for example, the STA) receiving the first frame is a sensing initiator, the first frame includes the Standalone Indication subfield. The Standalone Indication subfield indicates whether the initiator participates in receiving/sending of the sensing signal. For example, when a field value of the Standalone Indication subfield is 1, it indicates that the initiator participates in receiving/sending of the sensing signal; or when a field value of the

Standalone Indication subfield is 0, it indicates that the initiator does not participate in receiving/sending of the sensing signal.

[00202] 1.2 Sensing request indication (Sensing Request Indication) subfield

[00203] The Sensing Request Indication subfield is used to request the STA to feed back whether the STA is willing to participate in the sensing session. For example, when a field value of the Sensing Request Indication subfield is 1, it indicates that the STA is requested to feed back whether the STA is willing to participate in the sensing session. For example, Table 2 shows a correspondence between a field value of the Sensing Request Indication subfield and indication information.

Table 2

Field value of the Sensing Request Indication	Indication information
1	Request the STA to participate in the sensing session
0	Reserved field

[00204] It should be learned that, when the STA receiving the first frame has confirmed to participate in the sensing session, the sensing request information (Sensing Request Info) subfield may not include the sensing request indication (Sensing Request Indication) subfield. For example, when the AP considers (or learns) that the STA 1 participates in the sensing session by default, and the AP needs only to allocate a sensing parameter or a role to the STA 1, the first frame sent by the AP to the STA 1 may not include the sensing request indication (Sensing Request Indication) subfield requesting the STA 1 to participate in the sensing session.

[00205] 1.3 Sensing role indication (Sensing Roles Indication) subfield

[00206] The Sensing Role Indication subfield indicates a role of the STA participating in the sensing session. The role in the sensing session includes but is not limited to an initiator (transmitter) and a receiver (receiver). For example, Table 3 shows a correspondence between a field value of the Sensing Roles Indication subfield and indication information.

Table 3

Field value of the Sensing Role Indication	Indication information
00	Transmitter
01	Receiver
10	Transmitter and receiver
11	Reserved field

[00207] The Sensing Roles Indication subfield includes two bits. When a value of the two bits is 00, it indicates that the role is a receiver (or may be a transmitter); when a value of the two bits is 01, it indicates that the role is a transmitter (or may be a receiver); or when a value of the two bits is 10, it indicates that the role is both a receiver and a transmitter (self-sending and self-receiving).

[00208] It should be learned that, when the device (for example, the STA) receiving the first frame is a sensing initiator, or when the role of the device (for example, the STA) receiving the first frame in the sensing session is learned by default (or by default), the first frame may not include the Sensing Roles Indication subfield.

[00209] 1.4 Sensing feedback type (Sensing Feedback Type) subfield

[00210] The Sensing Feedback Type subfield is used to configure a type of a measurement result fed back (or referred to as reported) by the STA. The type of feeding back the measurement result includes but is not limited to: a CSI feedback manner, a compressed CSI feedback manner, or a final sensing measurement result (for example, information such as a speed, an angle, or a distance) feedback manner.

[00211] For example, when a field value of the Sensing Feedback Type subfield is 0, it indicates that the type of the measurement result reported by the STA is CSI feedback; when a field value of the Sensing Feedback Type subfield is 1, it indicates that the type of the measurement result reported by the STA is compressed CSI feedback; when a field value of the Sensing Feedback Type subfield is 2, it indicates that the type of the measurement result reported by the STA is final result speed information feedback; when a field value of the Sensing Feedback Type subfield is 3, it indicates that the type of the measurement result reported by the STA is final result angle information feedback; or when a field value of the Sensing Feedback Type subfield is 4, it indicates that the type of the measurement result reported by the STA is final result distance information feedback.

[00212] It should be learned that, when the receiver is an initiator (that is, may be understood as a device receiving the measurement result), the first frame received by the receiver does not include the sensing feedback type (Sensing Feedback Type) subfield; or when the AP considers by default that the STA serving as the receiver already learns the type of the measurement result fed back (or when the type of the measurement result fed back is a default type), the first frame received by the receiver does not include the sensing feedback type (Sensing Feedback Type) subfield.

[00213] In an optional case, if the STA receiving the first frame is an initiator in the sensing session, the sensing request information (Sensing Request Info) subfield of the first frame may

further include a standalone indication (Standalone Indication) subfield. The Standalone Indication subfield is used to request the STA to feed back whether the STA participates in receiving/sending of the sensing signal (that is, whether the STA further participates in the sensing session as a receiver and/or a transmitter).

5 **[00214]** 2. Sensing type (Sensing Type) subfield

[00215] The Sensing Type subfield indicates a data sending type (which may be understood as the foregoing operation parameter), and the data sending type includes a burst-based (burst) type or a continuous sending-based type. For the burst-based type, the Sensing Type subfield includes a pattern (pattern) subfield, a group measurement duration (Group measurement duration) subfield, 10 a number of group (Number of Group) subfield, and an interval between group (Interval between Group) subfield. It can be learned that, in the burst-based type, the Sensing Type subfield indicates sending duration, a quantity of sending times in a group, and an interval between groups. For the continuous sending-based type, the Sensing Type subfield includes a value of a pattern (pattern) subfield, a measurement duration (Measurement duration) subfield, and a number (Number) 15 subfield. In the continuous sending-based type, the Sensing Type subfield indicates information such as total sending duration, a total quantity of sent data packets, and a packet/beam sending period/interval.

[00216] For example, in the burst-based type, the Sensing Type subfield includes a pattern (pattern) subfield, a group measurement duration (Group measurement duration) subfield, a 20 number of group (Number of Group) subfield, and an interval between group (Interval between Group) subfield. The pattern subfield indicates a frequency pattern for sending data based on a burst. For example, when a field value of the pattern subfield is 0, it indicates that sending is performed at a low frequency. When a field value of the pattern subfield is 1, it indicates that sending is performed at a high frequency. The group measurement duration (Group measurement 25 duration) subfield indicates sending duration of a single packet group. The number of group (Number of Group) subfield indicates a quantity of sent NDPs in a single packet group. The interval between group (Interval between Group) subfield indicates an interval between packet groups.

[00217] It should be learned that, when the receiver is an initiator (that is, may be understood 30 as a device receiving the measurement result), the first frame received by the receiver may not include the sensing type (Sensing Type) subfield; or when the AP considers by default that the STA serving as the receiver already learns the data sending type (or understood that the data sending type is a default type), the first frame received by the receiver may not include the sensing type (Sensing Type) subfield.

35 **[00218]** 3. Sensing result destination (Sensing Results Destination) subfield

[00219] The Sensing Results Destination subfield is used to notify all receivers of MAC addresses of target devices (that is, devices receiving feedback results) when the receivers feed back the measurement results.

[00220] It should be noted that, when the device (such as the STA) receiving the first frame is the initiator or already learns the destination MAC address for feeding back the measurement result, the first frame may not include the Sensing Results Destination subfield.

[00221] 602: The AP receives a second frame from the first STA, where the second frame includes confirm information for the first frame.

[00222] After the AP sends the first frame to the first STA, the first STA sends the second frame to the AP. The second frame includes the confirm information for the first frame.

[00223] In a possible implementation, the second frame includes a confirm element field, and the confirm information is located in the confirm element field.

[00224] The following describes the frame structure of the second frame in detail based on the frame structure of the first frame in 601.

[00225] Structure 1: For the first frame described in structure 1, structure 2, and structure 3 in 601, the second frame includes a confirm element field, and the confirm information for the first frame is located in the confirm element field.

[00226] For example, FIG. 6f is a schematic diagram of a frame structure of the second frame according to this application. The second frame is a confirm (Confirm) frame, the Confirm frame includes a confirm element (Confirm Element) field, and the confirm information is configured in the Confirm Element field. Specifically, the Confirm Element field may include a confirm information (Confirm Info) subfield and a parameter modification (Parameter Modification) subfield.

[00227] 1. Confirm indication (Confirm Indication) subfield

[00228] A value of the confirm indication (Confirm Indication) subfield indicates whether the STA agrees to participate in the sensing session. For example, when a field value of the Confirm Indication subfield is 0, it indicates that the STA does not agree to participate in the sensing session; when a field value of the Confirm Indication subfield is 1, it indicates that the STA agrees to participate in the sensing session, and accepts a first sensing parameter allocated by the AP by using the first frame; or when a field value of the Confirm Indication subfield is 2, it indicates that the STA agrees to participate in the sensing session, but does not accept a first sensing parameter allocated by the AP by using the first frame.

[00229] 2. Parameter modification (Parameter Modification) subfield

[00230] When a field value of the Confirm Indication subfield is 2, that is, the STA agrees to participate in the sensing session, but does not accept the first sensing parameter allocated by the

AP by using the first frame, the Parameter Modification subfield includes a suggested (or recommended) parameter fed back by the STA by using the second frame.

[00231] Structure 2: For the first frame described in structure 4 in 601, the second frame includes a sensing response element field, and the confirm information for the first frame is located in the sensing response element field.

[00232] For example, FIG. 6g is a schematic diagram of a structure of the second frame according to this application. The second frame is a sensing response (Sensing Response) frame. The Sensing Response frame includes a sensing response element (Sensing Response Element) subfield, and the confirm information for the first frame is located in the Sensing Response Element subfield.

[00233] Specifically, the Sensing Response Element subfield includes a sensing response information (Sensing Response Info) subfield. The Sensing Response Info subfield includes a sensing response indication (Sensing Response Indication) subfield. The Sensing Response Indication subfield indicates whether the STA sending the second frame confirms to participate in the sensing session, that is, the confirm information for the first frame is located in the Sensing Response Indication subfield. For example, Table 4 shows a correspondence between a field value of the Sensing Response Indication and the indication information.

Table 4

Field value of the Sensing Response Indication	Indication information
0	Not participating in the sensing session
1	Confirm to participate in the sensing session and accept a parameter allocated to the STA in a sensing request frame
2	Confirm to participate in the sensing session, but accept no parameter allocated to the STA in the sensing request frame and feed back a suggested parameter of the STA
3	Reserved field

[00234] If a field value of the Sensing Response Indication subfield is 0, it indicates that the STA does not participate in the sensing session; if a field value of the Sensing Response Indication subfield is 1, it indicates that the STA confirms to participate in the sensing session, and accepts the sensing parameter allocated by the AP to the STA by using the first frame; or if the field value of the Sensing Response Indication subfield is 2, it indicates that the STA confirms to participate in the sensing session, but does not accept the sensing parameter allocated by the AP to the STA

by using the first frame, and feeds back the suggested parameter of the STA.

[00235] In an optional case, if the STA confirms to participate in the sensing session, but does not accept the sensing parameter allocated by the AP to the STA by using the first frame, in addition to the sensing response information (Sensing Response Info) subfield, the sensing response element (Sensing Response Element) subfield included in the first frame further includes a parameter modification (Parameter Modification) subfield. The parameter modification (Parameter Modification) subfield is used to store the recommended parameter fed back by the STA.

[00236] In an application scenario, FIG. 6h is an application scenario of the first frame and the second frame according to an embodiment of this application. The AP is an initiator, and the STA 1 and the STA 2 are the foregoing first STAs.

[00237] In this case, as shown in case 2 in FIG. 6h, the AP sends (for example, sends by broadcast) the first frame (in FIG. 6h, the first frame is used as a Trigger frame for illustration) to the STA 1 and the STA 2, to configure a role and a sensing parameter for both the STA 1 and the STA 2 to participate in the sensing session. After receiving the first frame, the STA 1 sends the second frame (in FIG. 6h, the first frame is used as a Confirm frame for illustration) to the AP, and confirms to accept the first information that is in the first frame and that is configured by the AP for the STA 1. After receiving the first frame, the STA 2 sends the second frame to the AP, and confirms to accept the first information that is in the first frame and that is configured by the AP for the STA 2.

[00238] In this case, as shown in case 1 in FIG. 6h, the AP sends the first frame in 601 (for example, the first frame in 601 is a sensing request frame in structure 4) to both the STA 1 and the STA 2, and configures a role and a sensing parameter for both the STA 1 and the STA 2 to participate in the sensing session. After receiving the first frame, the STA 1 sends the second frame (for example, the sensing response frame in structure 2 in 602) to the AP, and confirms to accept the first information that is in the first frame and that is configured by the AP for the STA 1. After receiving the first frame, the STA 2 sends the second frame (for example, the sensing response frame in structure 2 in 602) to the AP, and confirms to accept the first information that is in the first frame and that is configured by the AP for the STA 2.

[00239] According to such a sensing session establishment method, the AP may allocate, by using the first frame, a role and a parameter to each STA participating in the sensing session, to manage the role and the parameter when each STA participates in the sensing session. This helps implement a function requirement of the wireless sensing technology.

[00240] FIG. 7a is a schematic flowchart of another sensing session establishment method according to an embodiment of this application. As shown in FIG. 7a, the sensing session

establishment method includes the following step 701 to step 705. The method shown in FIG. 7a may be performed by an AP and a STA. Alternatively, the method shown in FIG. 7a may be performed by a chip in an AP and a chip in a STA. In FIG. 7a, an example in which the method is performed by the AP and the STA is used for description.

5 **[00241]** 701: The AP sends a third frame to a plurality of second STAs, where the third frame includes second information, and the second information is used to request the second STA to participate in the sensing session.

10 **[00242]** The second STA is a STA associated with the AP, that is, the STA is within a signal range of the AP and has a communication connection to the AP. It should be learned that, that the AP sends a third frame to a plurality of second STAs may be understood as that the AP sends the third frame to all second STAs, to request all the second STAs to participate in the sensing session; or may be understood as that the AP determines a plurality of second STAs (a part of second STAs) from all the second STAs, and sends the third frame to the plurality of second STAs (the part of second STAs), to request the plurality of second STAs (the part of second STAs) to participate in
15 the sensing session. This is not specifically limited in this application.

[00243] The following describes a frame structure of the third frame in detail.

[00244] Structure 1: The third frame includes a common information field, and the second information is located in the common information field.

20 **[00245]** For example, FIG. 7b is a schematic diagram of a structure of the third frame according to this application. The third frame is a sensing trigger (Sensing Trigger) frame. The sensing trigger frame includes a common information (Common Info) field, and the common information field is used to configure first information (which may be understood as common parameter information) shared by all STAs participating in the sensing session. For example, when the AP sends second information to a plurality of second STAs, the second information is used to request each second
25 STA to participate in the sensing session, and feed back a receiving/sending capability and a parameter of the second STA. In this case, it may be understood that the second information received by the plurality of second STAs is the same, and the second information is configured in a common information (Common Info) field of the third frame.

30 **[00246]** The common information (Common Info) field includes a trigger type (Trigger Type) subfield and a trigger dependent common information (Trigger Dependent Common Info) subfield. The Trigger Type subfield indicates a function type of the Sensing Trigger frame. For example, when a value of the Trigger Type subfield is 8, it indicates that the Sensing Trigger frame is used to trigger a Sensing operation. The trigger dependent common information (Trigger Dependent Common Info) subfield includes a sensing request element (Sensing Request Element) subfield.
35 The sensing request element (Sensing Request Element) subfield includes a sensing request

information (Sensing Request Info) field. The sensing request information (Sensing Request Info) field includes a sensing request indication (Sensing Request Indication) subfield, a sensing feedback type (Sensing Feedback Type) subfield, a sensing capability request (Sensing capability Request) subfield, and a sensing type (Sensing Type) subfield. The following describes in detail subfields included in the sensing request information (Sensing Request Info) field.

[00247] 1. Sensing request indication (Sensing Request Indication) subfield

[00248] The Sensing Request Indication subfield is used to request the STA to feed back whether the STA is willing to participate in the sensing session. For example, when a field value of the Sensing Request Indication subfield is 1, it indicates that the STA is requested to feed back whether the STA is willing to participate in the sensing session.

[00249] 2. Sensing feedback type (Sensing Feedback Type) subfield

[00250] The Sensing Feedback Type subfield is used to configure a type of a measurement result fed back by the device. The type of feeding back the measurement result includes but is not limited to: CSI feedback, compressed CSI feedback, final result feedback (speed information, angle information, distance information, or the like), or the like.

[00251] 3. Sensing capability request (Sensing capability Request) subfield

[00252] The Sensing capability Request subfield indicates (or requests) the STA to feed back a role supported by the STA in the sensing session. In this case, the STA needs to feed back all roles supported by the STA in the sensing session.

[00253] In a possible case, the Sensing capability Request subfield may be further used to request a role recommended (or referred to as suggested) by the STA in the sensing session. In this case, the STA may feed back a part of all the roles supported by the STA in the sensing session.

[00254] 4. Sensing type (Sensing Type) subfield

[00255] The Sensing Type subfield is used to request the STA to feed back a sensing type of the STA, and the sensing type includes but is not limited to a data sending type and the like.

[00256] In an optional case, if the STA is an initiator in the sensing session, the sensing request information (Sensing Request Info) subfield may further include a standalone indication (Standalone Indication) subfield. The Standalone Indication subfield is used to request the STA to feed back whether the STA participates in receiving/sending of the sensing signal (that is, whether the initiator STA further participates in the sensing session as a receiver and/or a transmitter).

[00257] Structure 2: The third frame includes a sensing request element field, and the second information is located in the sensing request element field.

[00258] For example, FIG. 7c is a schematic diagram of another structure of the third frame according to this application. The third frame is a sensing request (Sensing Request) frame. The Sensing Request frame includes a sensing request element (Sensing Request Element) field. The

second information is located in the Sensing Request Element field.

[00259] Specifically, the Sensing Request Element field includes a sensing request information (Sensing Request Info) subfield, and the Sensing Request Info subfield includes a sensing request indication (Sensing Request Indication) subfield, a sensing feedback type (Sensing Feedback Type) subfield, a sensing capability request (Sensing capability Request) subfield, and a sensing type (Sensing Type) subfield.

[00260] 1. Sensing request indication (Sensing Request Indication) subfield

[00261] The Sensing Request Indication subfield is used to request the STA to feed back whether the STA is willing to participate in the sensing session. For example, when a field value of the Sensing Request Indication subfield is 1, it indicates that the STA is requested to feed back whether the STA is willing to participate in the sensing session.

[00262] 2. Sensing feedback type (Sensing Feedback Type) subfield

[00263] The Sensing Feedback Type subfield is used to request the STA to feed back a type that is of a feedback measurement result and that is supported by the STA. The type of feeding back the measurement result includes but is not limited to: CSI feedback, compressed CSI feedback, final result feedback (speed information, angle information, distance information, or the like), or the like.

[00264] 3. Sensing capability request (Sensing capability Request) subfield

[00265] The Sensing capability Request subfield is used to request the STA to feed back a role supported by the STA in the sensing session. In this case, the STA needs to feed back all roles supported by the STA in the sensing session.

[00266] In a possible case, the Sensing capability Request subfield may be further used to request a role recommended (or referred to as suggested) by the STA in the sensing session. In this case, the STA may feed back a part of all the roles supported by the STA in the sensing session.

[00267] 4. Sensing type (Sensing Type) subfield

[00268] The Sensing Type subfield is used to request the STA to feed back a sensing type of the STA, and the sensing type includes but is not limited to a data sending type and the like.

[00269] In an optional case, if the STA is an initiator in the sensing session, the sensing request information (Sensing Request Info) subfield may further include a standalone indication (Standalone Indication) subfield. The Standalone Indication subfield is used to request the STA to feed back whether the STA participates in receiving/sending of the sensing signal (that is, whether the STA further participates in the sensing session as a receiver and/or a transmitter).

[00270] 702: The AP receives a fourth frame from the plurality of second STAs, where the fourth frame includes third information, and the third information indicates whether the second STA confirms to participate in the sensing session.

[00271] For each of the plurality of second STAs, after the second STA receives the third frame sent by the AP, the second STA determines, based on an actual situation of the second STA (a current task of the STA, a capability of a processor, or the like), whether to participate in the sensing session. Further, the second STA sends, to the AP by using the fourth frame, indication information (that is, the third information) indicating whether the second STA participates in the sensing session.

[00272] In a possible implementation, if the second STA participates in the sensing session (that is, the third information indicates that the second STA confirms to participate in the sensing session), the third information may further include a second role supported by the second STA in the sensing session and a second sensing parameter corresponding to the second role. For example, after the second STA receives the third frame sent by the AP, the second STA confirms to participate in the sensing session, and the second STA sends the fourth frame to the AP. The fourth frame further indicates that the second STA may receive 10 data packets every 1 ms when the second STA supports participating in the sensing session as a receiver, and may send 7 data packets every 1 ms when the second STA supports participating in the sensing session as a transmitter.

[00273] In a possible implementation, when the third information further includes the second role supported by the second STA in the sensing session and the second sensing parameter corresponding to the second role, the AP determines the first sensing parameter based on the second sensing parameter. For example, a STA 1 and a STA 2 are second STAs associated with the AP. Third information of the STA 1 indicates that a second role supported by the STA 1 is a transmitter, and a second sensing parameter corresponding to the second role is sending 10 data packets every 1 ms. Third information of the STA 2 indicates that a second role supported by the STA 2 is a receiver, and a second sensing parameter corresponding to the second role is receiving 5 data packets every 1 ms. In this case, after the AP determines the STA 1 and the STA 2 as first STAs, the AP may determine, based on the second sensing parameter indicated in the third information of the STA 1 and the second sensing parameter indicated in the third information of the STA 2, that a first sensing parameter of the STA 1 is sending five data packets every 1 ms, and a first sensing parameter of the STA 2 is receiving five data packets every 1 ms.

[00274] The following describes in detail a frame structure of the fourth frame based on the two structures of the third frame in the foregoing 701.

[00275] Structure 1: The fourth frame includes a sensing confirm element field, and the third information is located in the sensing confirm element field.

[00276] The frame structure of the fourth frame corresponds to structure 1 "the third frame includes a common information field, and the second information is located in the common information field" in the foregoing 701.

[00277] For example, FIG. 7d is a schematic diagram of a structure of the fourth frame according to this application. The fourth frame is a sensing confirm (Sensing Confirm) frame. The sensing confirm (Sensing Confirm) frame includes a sensing confirm element (Sensing Confirm Element) field, and the sensing confirm element (Sensing Confirm Element) field includes a confirm information (Confirm Info) subfield and a sensing type (Sensing Type) subfield. The following separately describes in detail the confirm information (Confirm Info) subfield and the sensing type (Sensing Type) subfield in the third frame.

[00278] 1. Confirm information (Confirm Info) subfield

[00279] The confirm information (Confirm Info) subfield includes a confirm indication (Confirm Indication) subfield, a sensing feedback type (Sensing Feedback Type) subfield, and a sensing capability response (Sensing capability Response) subfield.

[00280] 1.1 Confirm indication (Confirm Indication) subfield

[00281] The Confirm Indication subfield indicates whether the STA sending the fourth frame confirms to participate in the sensing session. For example, if a field value corresponding to the Confirm Indication subfield is 0, it indicates that the STA does not participate in the sensing session. If a field value corresponding to the Confirm Indication subfield is 1, it indicates that the STA confirms to participate in the sensing session.

[00282] 1.2 Sensing feedback type (Sensing Feedback Type) subfield

[00283] The Sensing Feedback Type subfield indicates a type (or referred to as a manner) of a measurement result fed back by the STA sending the fourth frame. The type of the measurement result fed back by the STA includes but is not limited to: a CSI feedback manner, a compressed CSI feedback manner, a final sensing measurement result (for example, information such as a speed, an angle, or a distance) feedback manner, or the like.

[00284] For example, when a field value of the Sensing Feedback Type subfield is 0, it indicates that the type of the measurement result reported by the STA is CSI feedback; when a field value of the Sensing Feedback Type subfield is 1, it indicates that the type of the measurement result reported by the STA is compressed CSI feedback; when a field value of the Sensing Feedback Type subfield is 2, it indicates that the type of the measurement result reported by the STA is final result speed information feedback; when a field value of the Sensing Feedback Type subfield is 3, it indicates that the type of the measurement result reported by the STA is final result angle information feedback; or when a field value of the Sensing Feedback Type subfield is 4, it indicates that the type of the measurement result reported by the STA is final result distance information feedback.

[00285] 1.3 Sensing capability response (Sensing capability Response) subfield

[00286] The Sensing capability Response subfield indicates a receiving/sending capability of

the STA sending the fourth frame. For example, the Sensing capability Response subfield in the fourth frame sent by the STA 1 indicates that a data packet receiving rate is receiving 10 data packets within 1 ms when the STA 1 serves as a receiver; or a data packet transmitting rate is receiving 10 data packets within 1 ms when the STA 1 serves as a transmitter.

5 **[00287]** 2. Sensing type (Sensing Type) subfield

[00288] The Sensing Type subfield indicates a data sending type of the STA sending the fourth frame, and the data sending type includes a burst-based type or a continuous sending-based type. For the burst-based type, the Sensing Type subfield includes a pattern (pattern) subfield, a group measurement duration (Group measurement duration) subfield, a number of group (Number of Group) subfield, and an interval between group (Interval between Group) subfield. It can be learned that, in the burst-based type, the Sensing Type subfield indicates sending duration, a quantity of sending times in a group, and an interval between groups. For the continuous sending-based type, the Sensing Type subfield includes a value of a pattern (pattern) subfield, a measurement duration (Measurement duration) subfield, and a number (Number) subfield. In the continuous sending-based type, the Sensing Type subfield indicates information such as total sending duration, a total quantity of sent data packets, and a packet/beam sending period/interval.

[00289] For example, in the burst-based type, the Sensing Type subfield includes a pattern (pattern) subfield, a group measurement duration (Group measurement duration) subfield, a number of group (Number of Group) subfield, and an interval between group (Interval between Group) subfield. The pattern subfield indicates a frequency pattern for sending data based on a burst. For example, when a field value of the pattern subfield is 0, it indicates that sending is performed at a low frequency. When a field value of the pattern subfield is 1, it indicates that sending is performed at a high frequency. The group measurement duration (Group measurement duration) subfield indicates sending duration of a single packet group. The number of group (Number of Group) subfield indicates a quantity of sent NDPs in a single packet group. The interval between group (Interval between Group) subfield indicates an interval between packet groups.

[00290] Structure 2: The fourth frame includes a sensing response element field, and the third information is located in the sensing response element field.

30 **[00291]** The frame structure of the fourth frame corresponds to structure 2 "the third frame includes a sensing request element field, and the second information is located in the sensing request element field" in the foregoing 701.

[00292] For example, FIG. 7e is a schematic diagram of another structure of the fourth frame according to this application. The fourth frame is a sensing response (Sensing Response) frame.

35 The Sensing Response frame includes a sensing response element (Sensing Response Element)

subfield, and the third information is located in the Sensing Response Element subfield.

[00293] Specifically, the Sensing Response Element subfield includes a sensing response information (Sensing Response Info) subfield. The Sensing Response Info subfield includes a sensing response indication (Sensing Response Indication) subfield, a sensing feedback type (Sensing Feedback Type) subfield, and a sensing capability response (Sensing capability Response) subfield.

[00294] The Sensing Response Indication subfield indicates whether the STA sending the fourth frame confirms to participate in the sensing session. For example, Table 5 shows a correspondence between a field value of the Sensing Response Indication and the indication information.

Table 5

Field value of the Sensing Response Indication	Indication information
0	Not participating in the sensing session
1	Confirm to participate in the sensing session

[00295] If a field value of the Sensing Response Indication subfield is 0, it indicates that the STA does not participate in the sensing session; or if a field value of the Sensing Response Indication subfield is 1, it indicates that the STA confirms to participate in the sensing session.

[00296] The Sensing Feedback Type subfield indicates a type (or referred to as a manner) of a measurement result fed back by the STA sending the fourth frame. The type of the measurement result fed back by the STA includes but is not limited to: a CSI feedback manner, a compressed CSI feedback manner, a final sensing measurement result (for example, information such as a speed, an angle, or a distance) feedback manner, or the like. For example, when a field value of the Sensing Feedback Type subfield is 0, it indicates that the type of the measurement result reported by the STA is CSI feedback; when a field value of the Sensing Feedback Type subfield is 1, it indicates that the type of the measurement result reported by the STA is compressed CSI feedback; when a field value of the Sensing Feedback Type subfield is 2, it indicates that the type of the measurement result reported by the STA is final result speed information feedback; when a field value of the Sensing Feedback Type subfield is 3, it indicates that the type of the measurement result reported by the STA is final result angle information feedback; or when a field value of the Sensing Feedback Type subfield is 4, it indicates that the type of the measurement result reported by the STA is final result distance information feedback.

[00297] The Sensing capability Response subfield indicates a receiving/sending capability of the STA sending the fourth frame. For example, the Sensing capability Response subfield in the fourth frame sent by the STA 1 indicates that a data packet receiving rate is receiving 10 data

packets within 1 ms when the STA 1 serves as a receiver; or a data packet transmitting rate is receiving 10 data packets within 1 ms when the STA 1 serves as a transmitter.

[00298] 703: The AP determines the first STA from the plurality of second STAs based on the third information from the plurality of second STAs.

5 **[00299]** After the AP sends the third frame to the plurality of second STAs to request the plurality of second STAs to participate in the sensing session, the AP determines, from the plurality of second STAs based on the third information of each of the plurality of second STAs, the first STA participating in the sensing session. For example, after the AP sends the third frame to the STA 1, the STA 2, and the STA 3, the AP determines, from the STA 1, the STA 2, and the STA 3
10 based on the third information of the STA 1, the third information of the STA 2, and the third information of the STA 3, that the first STAs participating in the sensing session are the STA 1 and the STA 2.

[00300] In a possible implementation, the third information corresponding to each of the plurality of second STAs indicates that the second STA determines to participate in the sensing
15 session, and the AP may determine all the plurality of second STAs as the first STAs.

[00301] For example, the STA 1, the STA 2, and the STA 3 are a plurality of second STAs associated with the AP, and the AP sends a third frame to the STA 1, the STA 2, and the STA 3, to request the STA 1, the STA 2, and the STA 3 to participate in the sensing session. The third information in the fourth frame sent by the STA 1 to the AP indicates that the STA 1 participates
20 in the sensing session, and a role (that is, the second role) supported by the STA 1 is a transmitter and a receiver. The third information in the fourth frame sent by the STA 2 to the AP indicates that the STA 2 determines to participate in the sensing session, and a role (that is, the second role) supported by the STA 2 is a receiver. The third information in the fourth frame sent by the STA 3 to the AP indicates that the STA 3 determines to participate in the sensing session, and a role (that
25 is, the second role) supported by the STA 1 is a transmitter. That is, if the STA 1, the STA 2, and the STA 3 all determine to participate in the sensing session, the AP determines all the second STAs (that is, the STA 1, the STA 2, and the STA 3) as the first STAs.

[00302] In another possible implementation, the AP determines the first STA from the plurality of second STAs based on a role of the AP in the sensing session and the third information from the
30 plurality of second STAs.

[00303] It can be learned from the process of participating in the sensing session for sensing in FIG. 3 that there may be at least one transmitter and at least one receiver in a sensing session, to form at least one complete communication link (including the receiver and the transmitter, which may be considered as a complete communication link) of a sensing signal. Because the AP may
35 alternatively participate in receiving/sending of the sensing signal (that is, the AP is a receiver or

a transmitter), in a process of determining, from the plurality of second STAs, the first STA participating in the sensing session, the AP may make a decision based on a role of the AP in the sensing session. Specifically, the AP determines the first STA from the plurality of second STAs based on the role of the AP in the sensing session. The following includes possible cases.

5 **[00304]** Case 1: The role of the AP in the sensing session is neither a transmitter nor a receiver.

[00305] In a sensing scenario corresponding to this possible case, the AP is an independent sensing initiator, and the AP does not participate in receiving/sending of a sensing signal. In this case, to form at least one complete communication link of the sensing signal, first STAs determined by the AP include at least one first STA whose role is a receiver and at least one first STA whose
10 role is a transmitter.

[00306] In other words, when the role of the AP in the sensing session is neither a transmitter nor a receiver, third information from a third STA indicates that the third STA participates in the sensing session, and third information from a fourth STA indicates that the fourth STA participates in the sensing session, the AP determines the third STA and the fourth STA as the first STAs. The
15 third STA is a STA in the second STAs, a second role corresponding to the third STA is a receiver in the sensing session, the fourth STA is a STA in the second STAs, and a second role corresponding to the fourth STA is a transmitter in the sensing session.

[00307] For example, the AP does not participate in receiving/sending of the sensing signal, and the STA 1, the STA 2, and the STA 3 are the plurality of second STAs associated with the AP. The
20 AP sends a third frame to the STA 1, the STA 2, and the STA 3, to request the STA 1, the STA 2, and the STA 3 to participate in the sensing session. The third information in the fourth frame sent by the STA 1 to the AP indicates that the STA 1 participates in the sensing session, and a role (that is, the second role) supported by the STA 1 is a transmitter. The third information in the fourth frame sent by the STA 2 to the AP indicates that the STA 2 determines to participate in the sensing
25 session, and a role (that is, the second role) supported by the STA 2 is a receiver. The third information in the fourth frame sent by the STA 3 to the AP indicates that the STA 3 does not participate in the sensing session. It can be learned that, although only a part of the plurality of second STAs confirm to participate in the sensing session, the STA 2 (that is, the foregoing third STA) in the part of the second STAs that confirm to participate in the sensing session confirms to
30 participate in the sensing session as a receiver, and the STA 1 (that is, the foregoing fourth STA) confirms to participate in the sensing session as a transmitter. The STA 1 and the STA 2 can form a complete communication link, and the AP determines the STA 1 and the STA 2 as the first STAs.

[00308] In this case, in another possible implementation, the third STA and the fourth STA are a same STA, that is, the STA is both a receiver and a transmitter in the sensing session.

35 **[00309]** Case 2: The role of the AP in the sensing session is a transmitter.

[00310] In a sensing scenario corresponding to this possible case, the AP is a non-independent sensing initiator (in this case, the AP is a sensing initiator and a transmitter), or the AP is a transmitter in the sensing session. In this case, to form at least one complete communication link of a sensing signal, first STAs determined by the AP include at least one first STA whose corresponding role is a receiver.

[00311] In other words, when the role of the AP in the sensing session is a transmitter, and third information from a fifth STA indicates that the fifth STA participates in the sensing session, the AP determines the fifth STA as the first STA. The fifth STA is one of the plurality of second STAs, and a second role corresponding to the fifth STA is a receiver in the sensing session.

[00312] For example, in the sensing session, the AP is a sensing signal transmitter, and the STA 1, the STA 2, and the STA 3 are the plurality of second STAs associated with the AP. The AP sends a third frame to the STA 1, the STA 2, and the STA 3, to request the STA 1, the STA 2, and the STA 3 to participate in the sensing session. The third information in the fourth frame sent by the STA 1 to the AP indicates that the STA 1 participates in the sensing session, and a role (that is, the second role) supported by the STA 1 is a transmitter. The third information in the fourth frame sent by the STA 2 to the AP indicates that the STA 2 determines to participate in the sensing session, and a role (that is, the second role) supported by the STA 2 is a receiver. The third information in the fourth frame sent by the STA 3 to the AP indicates that the STA 3 does not participate in the sensing session. It can be learned that, although only a part of the plurality of second STAs confirm to participate in the sensing session, the STA 2 (that is, the fifth STA) in the part of the second STAs confirms to participate in the sensing session as a receiver, and the AP needs to determine the STA 2 as a STA (that is, the first STA) participating in the sensing session.

[00313] Case 3: The role of the AP in the sensing session is a receiver.

[00314] In a sensing scenario corresponding to this possible case, the AP is a non-independent sensing initiator (in this case, the AP is a sensing initiator and a receiver), or the AP is a receiver in the sensing session. In this case, to form at least one complete communication link of a sensing signal, first STAs determined by the AP include at least one first STA whose role is a transmitter.

[00315] In other words, when the role of the AP in the sensing session is a receiver, third information from a sixth STA indicates that the sixth STA participates in the sensing session, the AP determines the sixth STA as the first STA. The sixth STA is one of the plurality of second STAs, and a second role corresponding to the sixth STA is a transmitter in the sensing session.

[00316] For example, in the sensing session, the AP is a sensing signal receiver, and the STA 1, the STA 2, and the STA 3 are the plurality of second STAs associated with the AP. The AP sends a third frame to the STA 1, the STA 2, and the STA 3, to request the STA 1, the STA 2, and the STA 3 to participate in the sensing session. The third information in the fourth frame sent by the STA 1

to the AP indicates that the STA 1 participates in the sensing session, and a role (that is, the second role) supported by the STA 1 is a transmitter. The third information in the fourth frame sent by the STA 2 to the AP indicates that the STA 2 determines to participate in the sensing session, and a role (that is, the second role) supported by the STA 2 is a receiver. The third information in the fourth frame sent by the STA 3 to the AP indicates that the STA 3 does not participate in the sensing session. It can be learned that, although only a part of the plurality of second STAs confirm to participate in the sensing session, the STA 1 (that is, the sixth STA) in the part of the second STAs confirms to participate in the sensing session as a transmitter, and the AP needs to determine the STA 1 as a STA (that is, the first STA) participating in the sensing session.

[00317] It should be learned that the foregoing possible cases (the case 1, the case 2, and the case 3 in 703) in which the AP determines the first STA from the plurality of second STAs are to form at least one complete communication link (at least one receiver and/or at least one transmitter) of the sensing signal in the sensing session. This may be understood as a minimum condition for establishing the sensing session, and cannot be considered as a limitation on the technical solutions of this application.

[00318] In a possible implementation, that the AP determines the first STA from the plurality of second STAs means that in addition to ensuring that there is at least one complete communication link (at least one receiver and/or at least one transmitter) of the sensing signal in the sensing session, the AP may further determine the first STA from the plurality of second STAs based on a determining criterion. Specifically, the determining criterion includes but is not limited to a bandwidth capability criterion, a criterion of a quantity of STAs in the sensing session, a parameter criterion, and the like.

[00319] The bandwidth capability criterion is to determine the first STA by using a standard of improving a transmission rate or a throughput in the sensing session. The criterion of the quantity of STAs in the sensing session may be understood as to determine the first STA by using a standard of increasing as many STAs as possible participating in the sensing session.

[00320] For example, the STA 1, the STA 2, and the STA 3 are second STAs associated with the AP. The third information of the STA 1 indicates that the second role of the STA 1 is a transmitter, and the second sensing parameter is sending 10 data packets every 1 ms. The third indication information of the STA 2 indicates that the second role of the STA 2 is a receiver, and the second sensing parameter is receiving eight data packets every 1 ms. The third indication information of the STA 3 indicates that the second role of the STA 3 is a receiver, and the second sensing parameter is receiving five data packets every 1 ms. The AP may determine the STA 1 and the STA 2 as the first STAs based on the bandwidth capability criterion. The STA 1 is a transmitter, and sends eight data packets every 1 ms. The STA 2 is a receiver, and receives eight data packets every 1 ms. The

AP may determine the STA 1, the STA 2, and the STA 3 as the first STAs based on the criterion of the quantity of STAs in the sensing session, and determine that the STA 1 is a transmitter and sends five data packets every 1 ms, and both the STA 2 and the STA 3 are receivers and receive five data packets every 1 ms.

5 **[00321]** 704: The AP sends a first frame to a first STA, where the first frame includes first information, and the first information indicates a first role of the first STA in a sensing session.

[00322] 705: The AP receives a second frame from the first STA, where the second frame includes confirm information for the first frame.

10 **[00323]** For specific implementations of 704 to 705, refer to the specific implementations of 601 to 602. Details are not described herein again in this application.

[00324] In an application scenario, FIG. 7f is an application scenario according to an embodiment of this application. In this application scenario, the AP is an initiator, and the STA 1 and the STA 2 are the second STAs associated with the AP.

15 **[00325]** In case 1 in FIG. 7f, the AP sends the third frame (for example, the sensing request frame) in structure 2 in the foregoing 701 to both the STA 1 and the STA 2. After receiving the third frame (for example, the sensing request frame) in structure 2, the STA 1 sends the fourth frame (for example, the sensing response frame) in structure 2 in the foregoing 702 to the AP, to confirm to participate in the sensing session. After receiving the third frame (for example, the sensing request frame) in structure 2, the STA 2 sends the fourth frame (for example, the sensing response frame) in structure 2 in the foregoing 702 to the AP, to confirm to participate in the sensing session. Further, the AP determines the STA 1 and the STA 2 as the first STAs participating in the sensing session, and the AP sends (for example, sends by broadcast) the first frame (for example, the Trigger frame) to the STA 1 and the STA 2, to configure a role and a sensing parameter for both the STA 1 and the STA 2 to participate in the sensing session. After receiving the first frame, the STA 1 sends the second frame (for example, the Confirm frame) to the AP, and confirms to accept the first information that is in the first frame and that is configured by the AP for the STA 1. After receiving the first frame, the STA 2 sends the second frame to the AP, and confirms to accept the first information that is in the first frame and that is configured by the AP for the STA 2.

30 **[00326]** In case 2 in FIG. 7f, the AP sends the third frame (for example, the sensing trigger frame) in structure 1 in the foregoing 701 to both the STA 1 and the STA 2. After receiving the third frame (for example, the sensing trigger frame) in structure 1, the STA 1 sends the fourth frame (for example, the sensing confirm frame) in structure 1 in the foregoing 702 to the AP, to confirm to participate in the sensing session. After receiving the third frame (for example, the sensing trigger frame) in structure 1, the STA 2 sends the fourth frame (for example, the sensing

confirm frame) in structure 1 in the foregoing 702 to the AP, to confirm to participate in the sensing session. Further, the AP determines the STA 1 and the STA 2 as the first STAs participating in the sensing session, and the AP sends (for example, sends by broadcast) the first frame (for example, the Trigger frame) to the STA 1 and the STA 2, to configure a role and a sensing parameter for both the STA 1 and the STA 2 to participate in the sensing session. After receiving the first frame, the STA 1 sends the second frame (for example, the Confirm frame) to the AP, and confirms to accept the first information that is in the first frame and that is configured by the AP for the STA 1. After receiving the first frame, the STA 2 sends the second frame to the AP, and confirms to accept the first information that is in the first frame and that is configured by the AP for the STA 2.

[00327] In conclusion, the AP sends, to the plurality of second STAs, the third frame used to request the second STA to participate in the sensing session. After receiving the third frame, each second STA sends, to the AP, the fourth frame indicating whether the second STA confirms to participate in the sensing session (that is, the third information). Further, the AP may determine, from the plurality of second STAs based on the third information sent by each second STA, the first STA participating in the sensing session. This reduces devices participating in the session sensing, and saves communication transmission resources.

[00328] FIG. 8a is a schematic flowchart of still another sensing session establishment method according to an embodiment of this application. As shown in FIG. 8a, the sensing session establishment method includes the following step 801 to step 805. The method shown in FIG. 8a may be performed by an AP and a STA. Alternatively, the method shown in FIG. 8a may be performed by a chip in an AP and a chip in a STA. In FIG. 8a, an example in which the method is performed by the AP and the STA is used for description.

[00329] 801: The AP sends a fifth frame to a plurality of second STAs, where the fifth frame includes fourth information, and the fourth information is used to request the second STA to participate in the sensing session by using a third role and a fourth sensing parameter.

[00330] In other words, when the AP sends the fourth information to the plurality of second STAs to request each of the plurality of second STAs to participate in the sensing session, for each of the plurality of second STAs, the AP allocates, to each second STA, a role (that is, the third role) and a sensing parameter (that is, the fourth sensing parameter) of the second STA participating in the sensing session. For example, the STA 1 and the STA 2 are STAs associated with the AP, and the AP sends the fifth frame to the STA 1 and the STA 2, to request the STA 1 and the STA 2 to participate in the sensing session, and indicates that a role of the STA 1 participating in the sensing session is a receiver, and a role of the STA 2 participating in the sensing session is a transmitter. In this case, the fourth information in the fifth frame corresponding to the STA 1 includes: The third

role is a receiver, and the fourth sensing parameter is receiving 10 data packets every 1 ms. The fourth information in the fifth frame corresponding to the STA 2 includes: The third role is a transmitter, and the fourth sensing parameter is sensing 10 data packets every 1 ms.

[00331] It should be learned that, that the AP sends a fifth frame to a plurality of second STAs may be understood as that the AP sends the fifth frame to all second STAs, to request all the second STAs to participate in the sensing session; or may be understood as that the AP determines a plurality of second STAs (a part of second STAs) from all the second STAs, and sends the fifth frame to the plurality of second STAs (the part of second STAs), to request the plurality of second STAs (the part of second STAs) to participate in the sensing session. This is not specifically limited in this application.

[00332] The following describes a frame structure of the fifth frame in detail.

[00333] Structure 1: The fifth frame includes a sensing request element field, and the fourth information is located in the sensing request element field.

[00334] For example, for the frame structure of the fifth frame, refer to the schematic diagram of the frame structure shown in FIG. 6e. The fifth frame is a sensing request (Sensing Request) frame, the sensing request (Sensing Request) frame includes a sensing request element (Sensing Request Element) field, and the fourth information is located in the Sensing Request Element field. Specifically, for specific descriptions of the fifth frame, refer to the foregoing related descriptions of the fields included in the frame structure shown in FIG. 6e. Details are not described herein again.

[00335] It should be learned that, for the fifth frame described in structure 1, the AP may send the fifth frame to each second STA in a one-by-one sending manner.

[00336] Structure 2: The fifth frame includes a common information (Common Info) field and a user information (User Info) field, and the fourth information is located in the common information (Common Info) field and/or the user information (User Info) field.

[00337] In this case, the common information field is used to configure the same parameter information of the STAs participating in the sensing session, and may be understood as configuration information shared by the STAs participating in the sensing session in the fourth information, that is, common parameter information. User information fields are in a one-to-one correspondence with the STAs participating in the sensing session, and the user information field is used to configure the configuration content specific to the STAs participating in the sensing session, and may be understood as parameter information specific to the STAs participating in the sensing session in the fourth information, that is, parameter information other than the common parameter information in the fourth information.

[00338] For example, FIG. 8b-1 and FIG. 8b-2 are a schematic diagram of a frame structure of

the fifth frame according to this application. The fifth frame is a trigger (Trigger) frame, and the Trigger frame includes a common information (Common Info) field and a user information (User Info) field. The following describes in detail the Common Info field and the User Info field of the fifth frame.

5 **[00339]** 1. Common Info field

[00340] FIG. 8b-1 and FIG. 8b-2 are a schematic diagram of an expanded structure of the Common Info field of the fifth frame shown by a module 80. The Common Info field includes a trigger type (Trigger Type) subfield and a trigger dependent common information (Trigger Dependent Common Info) subfield. For specific structures of the Trigger Type subfield and the
10 Trigger Dependent Common Info subfield, refer to descriptions of related fields of the module 60 in FIG. 6b-1 and FIG. 6b-2 in the foregoing 601. Details are not described herein again.

[00341] 2. User Info field

[00342] FIG. 8b-1 and FIG. 8b-2 are a schematic diagram of an expanded structure of the User Info field of the fifth frame shown by a module 81. The User Info field includes a trigger dependent
15 user information (Trigger Dependent User Info) subfield. The Trigger Dependent User Info subfield is used to configure specific fourth information (which may be understood as parameter information other than the common parameter information of the STA) corresponding to the STA in the fourth information. The Trigger Dependent User Info subfield may include a sensing request information (Sensing Request Info) subfield and a sensing type (Sensing Type) subfield.

20 **[00343]** 2.1 Sensing Request Info subfield

[00344] The Sensing Request Info subfield includes a sensing request indication (Sensing Request Indication) subfield, a sensing role indication (Sensing Roles Indication) subfield, and a sensing feedback type (Sensing Feedback Type) subfield.

[00345] The Sensing Request Indication subfield indicates to request a device to participate in
25 the sensing session. For example, when a field value of the Sensing Request Indication subfield is 1, it indicates that the fifth frame is used to request whether the device is willing to participate in the sensing session. It should be learned that, when the STA receiving the fifth frame has confirmed to participate in the sensing session, the fifth frame may not include the sensing request indication (Sensing Request Indication) subfield. For example, when the AP considers (or learns) that the
30 STA 1 participates in the sensing session by default, and the AP needs only to allocate a sensing parameter or a role to the STA 1, the fifth frame sent by the AP to the STA 1 may not include the sensing request indication (Sensing Request Indication) subfield requesting the STA 1 to participate in the sensing session.

[00346] The Sensing Roles Indication subfield indicates a role function. For example, the
35 Sensing Roles Indication subfield includes two bits. When a value of the two bits is 00, it indicates

that a role is a receiver (or may be a transmitter); when a value of the two bits is 01, it indicates that a role is a transmitter (or may be a receiver); or when a value of the two bits is 10, it indicates that a role is both a receiver and a transmitter (self-sending and self-receiving). It should be learned that, when the device (for example, the STA) receiving the fifth frame already learns the role of the device participating in the sensing session, the fifth frame may not include the Sensing Roles Indication subfield.

[00347] The Sensing Feedback Type subfield indicates that the feedback type is CSI, compressed CSI, a final result, or the like to feed back a result. 0 indicates original CSI feedback; 1 indicates compressed CSI feedback; 2 indicates final result speed information; 3 indicates final result angle information; 4 indicates final result distance information; and the like. It should be learned that when the receiver is an initiator (that is, may be understood as a device receiving the measurement result), the fifth frame received by the receiver does not include the sensing feedback type (Sensing Feedback Type) subfield; or when the AP considers by default that the STA serving as the receiver already learns the type of the measurement result fed back (or when the type of the measurement result fed back is a default type), the fifth frame received by the receiver does not include the sensing feedback type (Sensing Feedback Type) subfield. It should be learned that when the device receiving the fifth frame is an initiator (that is, may be understood as a device receiving the measurement result), the fifth frame received by the device does not include the Sensing Feedback Type subfield; or when the AP considers by default that the STA serving as the receiver already learns the type of the measurement result fed back (or when the type of the measurement result fed back is a default type), the fifth frame received by the receiver does not include the Sensing Feedback Type subfield.

[00348] 2.2 Sensing Type subfield

[00349] The Sensing Type subfield indicates a data sending type (which may be understood as the foregoing operation parameter). For example, the Sensing Type subfield indicates two data sending types: a burst-based (burst) type or a continuous sending-based type. For the burst-based type, the Sensing Type subfield includes a pattern (pattern) subfield, a group measurement duration (Group measurement duration) subfield, a number of group (Number of Group) subfield, and an interval between group (Interval between Group) subfield. It can be learned that, in the burst-based type, the Sensing Type subfield indicates sending duration, a quantity of sending times in a group, and an interval between groups. For the continuous sending-based type, the Sensing Type subfield includes a value of a pattern (pattern) subfield, a measurement duration (Measurement duration) subfield, and a number (Number) subfield. In the continuous sending-based type, the Sensing Type subfield indicates information such as total sending duration, a total quantity of sent data packets, and a packet/beam sending period/interval.

[00350] For example, in the burst-based type, the Sensing Type subfield includes a pattern (pattern) subfield, a group measurement duration (Group measurement duration) subfield, a number of group (Number of Group) subfield, and an interval between group (Interval between Group) subfield. The pattern subfield indicates a frequency pattern for sending data based on a burst. For example, when a field value of the pattern subfield is 0, it indicates that sending is performed at a low frequency. When a field value of the pattern subfield is 1, it indicates that sending is performed at a high frequency. The group measurement duration (Group measurement duration) subfield indicates sending duration of a single packet group. The number of group (Number of Group) subfield indicates a quantity of sent NDPs in a single packet group. The interval between group (Interval between Group) subfield indicates an interval between packet groups.

[00351] It should be learned that, when the receiver is an initiator (that is, may be understood as a device receiving the measurement result), the fifth frame received by the receiver may not include the sensing type (Sensing Type) subfield; or when the AP considers by default that the STA serving as the receiver already learns the data sending type (or understood that the data sending type is a default type), the fifth frame received by the receiver may not include the sensing type (Sensing Type) subfield.

[00352] It should be learned that, for the fifth frame described in structure 1, the AP may send the fifth frame to all second STA in a unified sending (or understood as broadcast) manner, and it may be understood that all the second STA simultaneously receives the fifth frame.

[00353] 802: The AP receives a sixth frame from the plurality of second STAs, where the sixth frame includes fifth information, and the fifth information indicates whether the second STA confirms to participate in the sensing session by using the third role and the fourth sensing parameter.

[00354] For each of the plurality of second STAs, after the second STA receives the fifth frame sent by the AP, the second STA determines, based on an actual situation of the second STA (a current task of the STA, a capability of a processor, or the like), whether to participate in the sensing session by using the third role and the fourth sensing parameter that are allocated to the fifth frame. For example, the STA 1 is a second STA associated with the AP, and the fourth information corresponding to the STA 1 indicates that the third role is a transmitter, and the fourth sensing parameter is sending 10 data packets every 1 ms. In this case, the fifth information fed back by the STA 1 to the AP may include the following: 1. The STA 1 confirms to participate in the sensing session as a transmitter (that is, the third role) and by sending 10 data packets every 1 ms (the fourth sensing parameter). 2. The STA 1 confirms to participate in the sensing session as a transmitter (that is, the third role), but cannot transmit a sensing signal by sending 10 data packets

every 1 ms (the fourth sensing parameter). When the STA accepts the third role configured by the AP by using the fourth information but does not accept the fourth sensing parameter, the fifth information may further include a suggested sensing parameter corresponding to the third role fed back by the STA. For example, when the STA 1 confirms to participate in the sensing session as the transmitter (that is, the third role), but cannot transmit the sensing signal by sending 10 data packets every 1 ms (the fourth sensing parameter), it is suggested that the data packets are sent by sending five data packets every 1 ms (that is, the suggested sensing parameter). 3. The STA 1 refuses to participate in the sensing session.

[00355] The following describes in detail the sixth frame based on the two structures of the fifth frame in the foregoing 801.

[00356] Structure 1: The sixth frame includes a sensing response element (Sensing Response Element) field, and the fifth information is located in the sensing response element (Sensing Response Element) field.

[00357] The frame structure of the sixth frame corresponds to structure 1 "the fifth frame includes a sensing request element field, and the fourth information is located in the sensing request element field" in the foregoing 801.

[00358] For example, FIG. 6g is a schematic diagram of a structure of the sixth frame according to this application. The sixth frame is a sensing response (Sensing Response) frame. The Sensing Response frame includes a sensing response element (Sensing Response Element) subfield, and the fifth information is located in the Sensing Response Element subfield. Specifically, for specific descriptions of the sixth frame, refer to the foregoing related descriptions of the fields included in the frame structure shown in FIG. 6g. Details are not described herein again.

[00359] Structure 2: The sixth frame includes a confirm element (Confirm Element) field, and the fifth information is located in the confirm element (Confirm Element) field.

[00360] The frame structure of the sixth frame corresponds to structure 2 "the fifth frame includes a common information (Common Info) field and a user information (User Info) field, and the fourth information is located in the common information (Common Info) field and/or the user information (User Info) field" in the foregoing 801.

[00361] For example, FIG. 6f is a schematic diagram of a frame structure of the sixth frame according to this application. The sixth frame is a confirm (Confirm) frame, the Confirm frame includes a confirm element (Confirm Element) field, and the fifth information is configured in the Confirm Element field. Specifically, the Confirm Element field may include a confirm information (Confirm Info) subfield and a parameter modification (Parameter Modification) subfield.

[00362] 1. Confirm indication (Confirm Indication) subfield

[00363] A value of the confirm indication (Confirm Indication) subfield indicates whether the

STA agrees to participate in the sensing session. For example, when a field value of the Confirm Indication subfield is 0, it indicates that the STA does not agree to participate in the sensing session; when a field value of the Confirm Indication subfield is 1, it indicates that the STA agrees to participate in the sensing session, and accepts the fourth sensing parameter allocated by the AP by using the fifth frame; or when a field value of the Confirm Indication subfield is 2, it indicates that the STA agrees to participate in the sensing session, but does not accept the fourth sensing parameter allocated by the AP by using the fifth frame.

[00364] 2. Parameter modification (Parameter Modification) subfield

[00365] When a field value of the Confirm Indication subfield is 2, that is, the STA agrees to participate in the sensing session, but does not accept the fourth sensing parameter allocated by the AP by using the fifth frame, the Parameter Modification subfield includes a suggested (or recommended) parameter fed back by the STA by using the sixth frame.

[00366] It should be learned that, when a field value of the Confirm Indication subfield indicates that the STA does not agree to participate in the sensing session, or a field value of the Confirm Indication subfield indicates that the STA agrees to participate in the sensing session and accepts the first sensing parameter allocated by the AP by using the fifth frame, the sixth frame may not include the parameter modification (Parameter Modification) subfield.

[00367] 803: The AP determines the first STA from the plurality of second STAs based on the fifth information from the plurality of second STAs.

[00368] It can be learned from the process of participating in the sensing session for sensing in FIG. 3 that there may be at least one transmitter and at least one receiver in a sensing session, to form at least one complete communication link. For each of the plurality of second STAs, after the second STA receives the fifth frame sent by the AP, the fifth indication information fed back by the second STA may include the following content: 1. The second STA confirms to participate in the sensing session by using the third role and the fourth sensing parameter; 2. The second STA confirms to participate in the sensing session by using the third role, but does not participate in the sensing session by using the fourth sensing parameter; and 3. The second STA participates in the sensing session.

[00369] To form at least one complete communication link of the sensing signal, regardless of whether the AP participates in receiving/sending of the sensing signal, first STAs determined by the AP from the plurality of second STAs include at least one first STA whose role is a receiver and at least one first STA whose role is a transmitter.

[00370] In other words, in a possible implementation, the fifth information from the third STA indicates that the third STA confirms to participate in the sensing session based on the third role corresponding to the third STA and the fourth sensing parameter. In addition, when the fifth

information from the fourth STA indicates that the fourth STA participates in the sensing session based on the third role corresponding to the fourth STA and the fourth sensing parameter, the AP determines the third STA and the fourth STA as the first STAs. The third STA is one of the plurality of second STAs, and a third role corresponding to the third STA is a receiver in the sensing session.

5 The fourth STA is one of the plurality of fourth STAs, and a third role corresponding to the fourth STA is a transmitter in the sensing session.

[00371] For example, the AP does not participate in receiving/sending of the sensing signal, and the STA 1, the STA 2, and the STA 3 are the plurality of second STAs associated with the AP. The AP sends a fifth frame to the STA 1, the STA 2, and the STA 3, to request the STA 1, the STA 2,
10 and the STA 3 to participate in the sensing session. Fourth information sent by the AP to the STA 1 by using the fifth frame indicates that the third role is a transmitter, and the fourth sensing parameter is sending 10 data packets every 1 ms. Fourth information sent by the AP to the STA 2 by using the fifth frame indicates that the third role is a receiver, and the fourth sensing parameter is receiving 10 data packets every 1 ms. Fourth information sent by the AP to the STA 3 by using
15 the fifth frame indicates that the third role is a receiver, and the fourth sensing parameter is receiving 10 data packets every 1 ms. If the STA 1 sends a sixth frame to the AP, the STA 1 confirms to participate in the sensing session as a transmitter (the third role corresponding to the STA 1) and by sending 10 data packets every 1 ms (the fourth sensing parameter corresponding to the STA 1). If the STA 2 sends a sixth frame to the AP, the STA 2 confirms to participate in the sensing session
20 as a receiver (the third role corresponding to the STA 2) and by receiving 10 data packets every 1 ms (the fourth sensing parameter corresponding to the STA 2). If the STA 3 sends a sixth frame to the AP, the STA 3 confirms to participate in the sensing session as a receiver (the third role corresponding to the STA 3) and by receiving 10 data packets every 1 ms (the fourth sensing parameter corresponding to the STA 3). In this case, the AP determines the STA 1, the STA 2, and
25 the STA 3 as the first STAs participating in the sensing session.

[00372] In another possible implementation, when the AP participates in receiving/sending of the sensing signal (that is, the AP is a transmitter and/or a receiver), the AP may determine the first STA from the plurality of second STAs based on a role of the AP in the sensing session and the fifth information from the plurality of second STAs.

30 **[00373]** Specifically, there may be a case in which the AP is a transmitter and a case in which the AP is a receiver. The following describes the two cases in detail.

[00374] Case 1: The role of the AP in the sensing session is a transmitter.

[00375] In a sensing scenario corresponding to this possible case, the AP is a non-independent sensing initiator (in this case, the AP is an initiator and a transmitter), or the AP is a transmitter in
35 the sensing session. In this case, to form at least one complete communication link of a sensing

signal, first STAs determined by the AP include at least one first STA whose corresponding role is a receiver.

[00376] In other words, when the role of the AP in the sensing session is a transmitter, and the fifth information from the fifth STA indicates that the fifth STA participates in the sensing session based on the third role corresponding to the fifth STA, the AP determines the fifth STA as the first STA. The fifth STA is one of the plurality of second STAs, and the third role corresponding to the fifth STA is a receiver in the sensing session.

[00377] That the fifth information from the fifth STA indicates that the fifth STA participates in the sensing session based on the third role corresponding to the fifth STA includes the following two possible cases.

[00378] In a possible case, if the fifth information from the fifth STA indicates that the fifth STA participates in the sensing session based on the third role and the fourth sensing parameter, the AP determines the fifth STA as the first STA. The fifth STA is one of the plurality of second STAs, and the third role corresponding to the fifth STA is a receiver in the sensing session. In this possible case, the AP determines the fifth STA as the first STA, determines the third role corresponding to the fifth STA as the first role of the fifth STA participating in the sensing session, and determines the fourth sensing parameter corresponding to the fifth STA as the first sensing parameter of the fifth STA participating in the sensing session.

[00379] For example, in the sensing session, the AP is a sensing signal transmitter, and the STA 1 and the STA 2 are the plurality of second STAs associated with the AP. The AP sends a fifth frame to the STA 1 and the STA 2, to request the STA 1 and the STA 2 to participate in the sensing session, and allocates a third role and a fourth sensing parameter to both the STA 1 and the STA 2. The AP receives the fifth information sent by the STA 1 and the STA 2. The fifth information sent by the STA 1 to the AP indicates that the STA 1 confirms to participate in the sensing session as a receiver (the third role corresponding to the STA 1) and by receiving 10 data packets every 1 ms (the fourth sensing parameter corresponding to the STA 1). The fifth information sent by the STA 2 to the AP indicates that the STA 2 refuses to participate in the sensing session as a transmitter (the third role corresponding to the STA 2) and by sending 10 data packets every 1 ms (the fourth sensing parameter corresponding to the STA 2). It can be learned that, although only a part of the plurality of second STAs confirm to participate in the sensing session, the STA 1 (that is, the fifth STA) in the part of the second STAs confirms to participate in the sensing session as a receiver, and the AP needs to determine the STA 1 as a STA (that is, the first STA) participating in the sensing session, and determine the fourth sensing parameter (that is, receiving 10 data packets every 1 ms) of the STA 1 as the first sensing parameter.

[00380] In another possible implementation, if the fifth information from the fifth STA indicates

that the fifth STA participates in the sensing session based on the third role, but does not participate in the sensing session based on the fourth sensing parameter corresponding to the fifth STA, the AP determines the fifth STA as the first STA. The fifth information further includes a suggested parameter (that is, a fifth sensing parameter) of the fifth STA participating in the sensing session by using the third role. In this possible case, the AP determines the fifth STA as the first STA, and determines the fifth sensing parameter fed back by the fifth STA as the first sensing parameter of the fifth STA participating in the sensing session.

[00381] For example, in the sensing session, the AP is a sensing signal transmitter, and the STA 1 and the STA 2 are the plurality of second STAs associated with the AP. The AP sends a fifth frame to the STA 1 and the STA 2, to request the STA 1 and the STA 2 to participate in the sensing session, and allocates a third role and a fourth sensing parameter to both the STA 1 and the STA 2. The AP receives the fifth information sent by the STA 1 and the STA 2. The fifth information sent by the STA 1 to the AP indicates that the STA 1 confirms to participate in the sensing session as a receiver (the third role corresponding to the STA 1), but the STA 1 refuses to participate in the sensing session by receiving 10 data packets every 1 ms (the fourth sensing parameter corresponding to the STA 1). It is recommended that the STA 1 participates in the sensing session by receiving 5 data packets every 1 ms (the fifth sensing parameter fed back by the STA 1). The fifth information sent by the STA 2 to the AP indicates that the STA 2 refuses to participate in the sensing session as a transmitter (the third role corresponding to the STA 2) and by sending 10 data packets every 1 ms (the fourth sensing parameter corresponding to the STA 2). The AP determines the STA 1 as a STA (that is, the first STA) participating in the sensing session, and determines the fifth sensing parameter of the STA 1 (receiving five data packets every 1 ms) as the first sensing parameter.

[00382] Case 2: The role of the AP in the sensing session is a receiver.

[00383] In a sensing scenario corresponding to this possible case, the AP is a non-independent sensing initiator (in this case, the AP is an initiator and a receiver), or the AP is a receiver in the sensing session. In this case, to form at least one complete communication link of a sensing signal, first STAs determined by the AP include at least one first STA whose corresponding role is a transmitter.

[00384] In other words, when the role of the AP in the sensing session is a receiver, and the fifth information from the sixth STA indicates that the sixth STA participates in the sensing session based on the third role corresponding to the sixth STA, the AP determines the sixth STA as the first STA. The sixth STA is one of the plurality of second STAs, and a third role corresponding to the sixth STA is a transmitter in the sensing session.

[00385] That the fifth information from the sixth STA indicates that the sixth STA participates

in the sensing session based on the third role corresponding to the sixth STA includes the following two possible cases.

[00386] In a possible case, if the fifth information from the sixth STA indicates that the sixth STA participates in the sensing session based on the third role and the fourth sensing parameter, the AP determines the sixth STA as the first STA. The sixth STA is one of the plurality of second STAs, and the third role corresponding to the sixth STA is a transmitter in the sensing session. In this possible case, the AP determines the sixth STA as the first STA, determines the third role corresponding to the sixth STA as the first role of the sixth STA participating in the sensing session, and determines the fourth sensing parameter corresponding to the sixth STA as the first sensing parameter of the sixth STA participating in the sensing session.

[00387] For example, in the sensing session, the AP is a sensing signal receiver, and the STA 1 and the STA 2 are the plurality of second STAs associated with the AP. The AP sends a fifth frame to the STA 1 and the STA 2, to request the STA 1 and the STA 2 to participate in the sensing session, and allocates a third role and a fourth sensing parameter to both the STA 1 and the STA 2. The AP receives the fifth information sent by the STA 1 and the STA 2. The fifth information sent by the STA 1 to the AP indicates that the STA 1 refuses to participate in the sensing session as a receiver (the third role corresponding to the STA 1) and by receiving 10 data packets every 1 ms (the fourth sensing parameter corresponding to the STA 1). The fifth information sent by the STA 2 to the AP indicates that the STA 2 confirms to participate in the sensing session as a transmitter (the third role corresponding to the STA 2) and by sending 10 data packets every 1 ms (the fourth sensing parameter corresponding to the STA 2). The AP determines the STA 2 as a STA (that is, the first STA) participating in the sensing session, and determines the fourth sensing parameter of the STA 2 (sending 10 data packets every 1 ms) as the first sensing parameter.

[00388] In another possible implementation, if the fifth information from the sixth STA indicates that the sixth STA participates in the sensing session based on the third role, but does not participate in the sensing session based on the fourth sensing parameter corresponding to the sixth STA, the AP determines the sixth STA as the first STA. The fifth information further includes a suggested parameter (that is, a fifth sensing parameter) of the sixth STA participating in the sensing session by using the third role. In this possible case, the AP determines the sixth STA as the first STA, and determines the fifth sensing parameter fed back by the sixth STA as the first sensing parameter of the sixth STA participating in the sensing session.

[00389] For example, in the sensing session, the AP is a sensing signal receiver, and the STA 1 and the STA 2 are the plurality of second STAs associated with the AP. The AP sends a fifth frame to the STA 1 and the STA 2, to request the STA 1 and the STA 2 to participate in the sensing session, and allocates a third role and a fourth sensing parameter to both the STA 1 and the STA 2. The AP

receives the fifth information sent by the STA 1 and the STA 2. The fifth information sent by the STA 1 to the AP indicates that the STA 1 refuses to participate in the sensing session as a receiver (the third role corresponding to the STA 1) and by receiving 10 data packets every 1 ms (the fourth sensing parameter corresponding to the STA 1). The fifth information sent by the STA 2 to the AP indicates that the STA 2 confirms to participate in the sensing session as a transmitter (the third role corresponding to the STA 2), but refuses to participate in the sensing session by sending 10 data packets every 1 ms (the fourth sensing parameter corresponding to the STA 2). It is recommended that the STA 2 participates in the sensing session by sending 5 data packets every 1 ms (the fifth sensing parameter fed back by the STA 2). The AP determines the STA 2 as a STA (that is, the first STA) participating in the sensing session, and determines the fifth sensing parameter of the STA 2 (sending 5 data packets every 1 ms) as the first sensing parameter.

[00390] It should be noted that, if a complete communication link of a sensing signal cannot be formed in one sensing session, the AP may reallocate a role or a sensing parameter of each second STA by using the fifth frame according to step 801. This is not discussed in this application.

[00391] 804: The AP sends a first frame to a first STA, where the first frame includes first information, and the first information indicates a first role of the first STA in a sensing session.

[00392] 805: The AP receives a second frame from the first STA, where the second frame includes confirm information for the first frame.

[00393] For specific implementations of 804 and 805, refer to the specific implementations of 601 and 602. Details are not described herein again in this application.

[00394] In a scenario, FIG. 8c is an application scenario according to an embodiment of this application. In this application scenario, the AP is an initiator, and the STA 1 and the STA 2 are the second STAs associated with the AP.

[00395] As shown in case 1 in FIG. 8c, the AP sends the fifth frame (for example, the sensing request frame in structure 1) in the foregoing 801 to both the STA 1 and the STA 2, configures the third role and the fourth sensing parameter of the STA 1 participating in the sensing session, and configures the third role and the fourth sensing parameter of the STA 2 participating in the sensing session. After receiving the fifth frame (for example, the sensing request frame in structure 1), the STA 1 sends the sixth frame (for example, the sensing response frame in structure 1) in the foregoing 802 to the AP, and feeds back, to the AP, whether the STA 1 participates in the sensing session by using the third role and the fourth sensing parameter corresponding to the STA 1. After receiving the fifth frame (for example, the sensing request frame in structure 1), the STA 2 sends the sixth frame (for example, the sensing response frame in structure 1) in the foregoing 802 to the AP, and feeds back, to the AP, whether the STA 2 participates in the sensing session by using the third role and the fourth sensing parameter corresponding to the STA 2. The AP determines, based

on the sixth frame fed back by the STA 1 and the STA 2, whether to reallocate a role and/or a parameter. When the AP needs to reallocate a role or a sensing parameter of the STA 1 and/or the STA 2, the AP sends the fifth frame (for example, the sensing request frame in structure 1) in the foregoing 801 again to the STA 1 and the STA 2, configures the third role and the fourth sensing parameter of the STA 1 participating in the sensing session, and configures the third role and the fourth sensing parameter of the STA 2 participating in the sensing session until the sixth frame sent by the STA 1 to the AP indicates that the STA 1 confirms to participate in the sensing session by using the third role and the fourth sensing parameter that correspond to the STA 1, and/or the sixth frame sent by the STA 2 to the AP indicates that the STA 2 confirms to participate in the sensing session by using the third role and the fourth sensing parameter that correspond to the STA 2.

[00396] Similarly, in case 2 in FIG. 8c, the AP sends the fifth frame (for example, a trigger frame) in structure 2 in the foregoing 801 to both the STA 1 and the STA 2, configures the third role and the fourth sensing parameter of the STA 1 participating in the sensing session, and configures the third role and the fourth sensing parameter of the STA 2 participating in the sensing session until the STA 1 sends the sixth frame (for example, a confirm frame) in structure 2 in the foregoing 802 to the AP, and confirms to participate in the sensing session by using the third role and the fourth sensing parameter that correspond to the STA 1; and/or the STA 2 sends the sixth frame (for example, a confirm frame) in structure 2 in the foregoing 802 to the AP until the STA 2 confirms to participate in the sensing session by using the third role and the fourth sensing parameter that correspond to the STA 2.

[00397] In conclusion, when the AP sends, to the plurality of second STAs, the fifth frame used to request the second STA to participate in the sensing session, the fifth frame further configures a role and a sensing parameter for each second STA to participate in the sensing session. After each second STA receives the fifth frame, each second STA sends, to the AP, the sixth frame indicating whether the second STA confirms to participate in the sensing session. Further, the AP may determine, from the plurality of second STAs based on the sixth frame sent by each second STA, the first STA participating in the sensing session. This reduces devices participating in the session sensing, and saves communication transmission resources.

[00398] It should be noted that, in this application, content carried in each frame is merely described as an example, and it may be considered that deletion, addition, or modification of content carried in a frame according to the frame structure described in the present invention of this application falls within the protection scope of this application. For example, in the session establishment method provided in FIG. 8a, the AP sends the fifth frame to the plurality of second STAs, the fifth frame is used to request the plurality of second STAs to participate in the sensing

session, and the fifth frame further configures a role for each second STA to participate in the sensing session. For each of the plurality of second STAs, the second STA sends the sixth frame to the AP based on the fifth frame. Specifically, content included in the sixth frame includes: When the second STA confirms to participate in the sensing session based on the role allocated in the fifth frame, in addition to indicating that the second frame confirms to participate in the sensing session based on the role allocated in the fifth frame, the sixth frame further indicates a suggested (or supported) sensing parameter that is fed back by the second STA and that participates in the sensing session. When the second STA does not participate in the sensing session based on the role allocated in the fifth frame, in addition to indicating that the second frame does not participate in the sensing session based on the role allocated in the fifth frame, the sixth frame further indicates a suggested (or supported) role and a corresponding sensing parameter that are fed back by the second STA and that participate in the sensing session. When the second STA does not participate in the sensing session, the sixth frame indicates that the second STA does not participate in the sensing session. Further, the AP may determine, from the plurality of second STAs based on the sixth frame fed back by the plurality of second STAs, the first STA participating in the sensing session.

[00399] To intuitively understand the sensing session establishment method described in this application, the following describes an application scenario to which the sensing session establishment method is applied. It should be understood that the following application scenario is merely an example for description, and cannot be considered as a limitation on this application.

[00400] FIG. 9a is an application scenario of a sensing session according to this application.

[00401] In an application scenario corresponding to FIG. 9a, an AP is a non-independent sensing initiator (that is, the AP serves as a sensing initiator, and the AP further participates in receiving/sending of a sensing signal), and a STA 1 and a STA 2 are STAs associated with the AP (that is, the foregoing second STAs). The following uses an example in which the AP serves as a sensing initiator and a sensing signal transmitter for schematic description.

[00402] In a sensing session establishment phase, if the AP establishes the sensing session by using the method shown in FIG. 6a, a schematic diagram of the sensing procedure in the application scenario in FIG. 9a is shown in FIG. 9b. In the sensing session establishment phase, the AP sends a first frame (a trigger frame in FIG. 9b) to the STA 1 and the STA 2 by using the method shown in FIG. 6a, and configures a role and a sensing parameter for both the STA 1 and the STA 2 to participate in the sensing session. After receiving the first frame, the STA 1 sends a second frame (for example, a confirm frame in FIG. 9b) to the AP, and confirms to accept first information that is in the first frame and that is configured by the AP for the STA 1. After receiving the first frame, the STA 2 sends a second frame to the AP, and confirms to accept first information

that is in the first frame and that is configured by the AP for the STA 2. In a measurement phase, the AP sends a sensing signal to the STA 1 and the STA 2. After receiving the sensing signal, the STA 1 and the STA 2 perform signal processing measurement to obtain a measurement result. In a reporting phase, the AP sends a Poll frame to both the STA 1 and the STA 2, so that the STA 1 and the STA 2 send the measurement result to the AP after receiving the Poll frame. It should be noted that, in the reporting phase, the AP may alternatively obtain measurement results of the STA 1 and the STA 2 in a scheduling-based manner (as shown in case 2 in FIG. 5c) or a contention-based manner (as shown in case 3 in FIG. 5c).

[00403] In the sensing session establishment phase, if the AP establishes the sensing session by using the method shown in FIG. 7a, a schematic diagram of the sensing procedure in the application scenario in FIG. 9a is shown in FIG. 9c. In the sensing session establishment phase, the AP sends a third frame (a sensing request frame in FIG. 9c) to both the STA 1 and the STA 2 by using the method shown in FIG. 7a, to request the STA 1 and the STA 2 to participate in the sensing session. After the STA 1 receives the third frame from the AP, the STA 1 sends a fourth frame (for example, a sensing response frame in FIG. 9c) to the AP, and indicates, in the fourth frame, a receiving/sending capability of the STA 1 (which may be understood as a role supported in the sensing session) and a corresponding sensing parameter. After the STA 2 receives the third frame from the AP, the STA 2 sends a fourth frame (for example, a sensing response frame in FIG. 9c) to the AP, and indicates, in the fourth frame, a receiving/sending capability of the STA 2 (which may be understood as a role supported in the sensing session) and a corresponding sensing parameter. Further, the AP determines the STA 1 and the STA 2 as first STAs participating in the sensing session, and the AP sends (for example, sends by broadcast) a first frame (for example, the Trigger frame) to the STA 1 and the STA 2 based on the fourth frame (for example, a sensing response frame in FIG. 9c) fed back by both the STA 1 and the STA 2, to configure a role and a sensing parameter for both the STA 1 and the STA 2 to participate in the sensing session. After receiving the first frame, the STA 1 sends a second frame (for example, the Confirm frame) to the AP, and confirms to accept first information that is in the first frame and that is configured by the AP for the STA 1. After receiving the first frame, the STA 2 sends a second frame to the AP, and confirms to accept first information that is in the first frame and that is configured by the AP for the STA 2. In a measurement phase, the AP sends a sensing signal to the STA 1 and the STA 2. After receiving the sensing signal, the STA 1 and the STA 2 perform signal processing measurement to obtain a measurement result. In a reporting phase, the AP sends a Poll frame to both the STA 1 and the STA 2, so that the STA 1 and the STA 2 send the measurement result to the AP after receiving the Poll frame. It should be noted that, in the reporting phase, the AP may alternatively obtain the measurement result of the STA 1 and the STA 2 in a scheduling-based

manner (as shown in case 2 in FIG. 5c) or a contention-based manner (as shown in case 3 in FIG. 5c).

[00404] In the sensing session establishment phase, if the AP establishes the sensing session by using the method shown in FIG. 8a, a schematic diagram of the sensing procedure in the application scenario in FIG. 9a is shown in FIG. 9d. In the sensing session establishment phase, the AP sends a fifth frame (a trigger frame in FIG. 9d) to the STA 1 and the STA 2 by using the method shown in FIG. 8a, to request the STA 1 and the STA 2 to participate in the sensing session, and configures a role and a sensing parameter for both the STA 1 and the STA 2 to participate in the sensing session. After the STA 1 and the STA 2 receive the fifth frame from the AP, the STA 1 and the STA 2 separately send a sixth frame (for example, a confirm frame in FIG. 9d) to the AP. If the sixth frame in FIG. 9c indicates that the STA receiving/sending the sixth frame refuses to participate in the sensing session by using the role and/or the sensing parameter configured in the fifth frame, the AP sends the fifth frame to the STA 1 and the STA 2 again, and configures the role and the sensing parameter for the STA 1 and the STA 2 to participate in the sensing session until the sixth frame sent by the STA 1 to the AP indicates that the STA 1 confirms to participate in the sensing session by using the third role and the fourth sensing parameter that correspond to the STA 1, and/or the sixth frame sent by the STA 2 to the AP indicates that the STA 2 confirms to participate in the sensing session by using the third role and the fourth sensing parameter that correspond to the STA 2. In a measurement phase, the AP sends a sensing signal to the STA 1 and the STA 2. After receiving the sensing signal, the STA 1 and the STA 2 perform signal processing measurement to obtain a measurement result. In a reporting phase, the AP sends a Poll frame to both the STA 1 and the STA 2, so that the STA 1 and the STA 2 send the measurement result to the AP after receiving the Poll frame. It should be noted that, in the reporting phase, the AP may alternatively obtain the measurement result of the STA 1 and the STA 2 in a scheduling-based manner (as shown in case 2 in FIG. 5c) or a contention-based manner (as shown in case 3 in FIG. 5c).

[00405] In another application scenario corresponding to FIG. 9a, when the STA has a sensing requirement, the STA usually cannot schedule and manage the STA participating in the sensing session. Therefore, in this case, when the STA serves as an initiator, the STA usually needs to cooperate with the AP to perform sensing. For example, the STA 1 is a non-independent sensing initiator (that is, the STA 1 serves as a sensing initiator, and the STA 1 further participates in receiving/sending of a sensing signal), and the STA 1 and the STA 2 are STAs associated with the AP (that is, the foregoing second STAs). The following uses an example in which the AP serves as a sensing signal transmitter for schematic description.

[00406] In a sensing session establishment phase, the STA 1 (an initiator) sends a sensing

request frame to the AP, to request the AP to participate in the sensing session. After receiving the sensing request frame, the AP feeds back (or sends) a sensing response frame to the STA 1, and the sensing response frame indicates whether the AP confirms to participate in the sensing session. When the AP agrees to participate in the sensing session, the AP performs coordinated scheduling on the STAs (for example, the STA 1 and the STA 2) participating in the sensing session. It should be learned that, for a specific frame structure of the sensing request frame sent by the STA 1 to the AP, refer to the first frame in structure 4 in the foregoing 601 (that is, as shown in FIG. 6e). In this case, the STA 1 serves as an initiator, and the Sensing Request Element field in the sensing request frame sent by the STA to the AP further includes another station information (Other STA Info) subfield in addition to a sensing request information (Sensing Request Info) subfield. The another station information (Other STA Info) subfield indicates information such as an address of another STA participating in the sensing session. In other words, when the STA 1 is an initiator, the STA 1 sends a sensing request (Sensing Request) frame to the AP, to request the AP to participate in the sensing session. When the STA 1 learns the information of the address of the another STA participating in the sensing session, the STA 1 may further indicate, to the AP by using the another station information (Other STA Info) subfield, information such as the address of the another STA participating in the sensing session.

[00407] If the AP establishes the sensing session by using the method shown in FIG. 6a, a schematic diagram of the sensing procedure in the application scenario in FIG. 9a is shown in FIG. 9e. In the sensing session establishment phase, the AP sends a first frame (a trigger frame in FIG. 9e) to the STA 1 and the STA 2 by using the method shown in FIG. 6a, and configures a role and a sensing parameter for both the STA 1 and the STA 2 to participate in the sensing session. After receiving the first frame, the STA 1 sends a second frame (for example, a response frame in FIG. 9e) to the AP, and confirms to accept first information that is in the first frame and that is configured by the AP for the STA 1. After receiving the first frame, the STA 2 sends a second frame to the AP, and confirms to accept first information that is in the first frame and that is configured by the AP for the STA 2. In a measurement phase, the AP sends a sensing signal to the STA 1 and the STA 2. After receiving the sensing signal, the STA 1 and the STA 2 perform signal processing measurement to obtain a measurement result. In a reporting phase, the AP sends a Poll frame to both the STA 1 and the STA 2, so that the STA 1 and the STA 2 send the measurement result to the AP after receiving the Poll frame. Further, because the STA 1 is an initiator, the AP sends, to the STA 1, the measurement result sent by the STA 1 and the STA 2.

[00408] It should be noted that, in the reporting phase, the AP may alternatively obtain the measurement result of the STA 1 and the STA 2 in a scheduling-based manner (as shown in case 2 in FIG. 5c) or a contention-based manner (as shown in case 3 in FIG. 5c).

[00409] If the AP establishes the sensing session by using the method shown in FIG. 7a, a schematic diagram of the sensing procedure in the application scenario in FIG. 9a is shown in FIG. 9f. In the sensing session establishment phase, the AP sends a third frame (a sensing request frame in FIG. 9f) to both the STA 1 and the STA 2 by using the method shown in FIG. 7a, to request the STA 1 and the STA 2 to participate in the sensing session. After the STA 1 receives the third frame from the AP, the STA 1 sends a fourth frame (for example, a sensing response frame in FIG. 9f) to the AP, and indicates, in the fourth frame, a receiving/sending capability of the STA 1 (which may be understood as a role supported in the sensing session) and a corresponding sensing parameter. After the STA 2 receives the third frame from the AP, the STA 2 sends a fourth frame (for example, a sensing response frame in FIG. 9f) to the AP, and indicates, in the fourth frame, a receiving/sending capability of the STA 2 (which may be understood as a role supported in the sensing session) and a corresponding sensing parameter. Further, the AP determines the STA 1 and the STA 2 as first STAs participating in the sensing session, and the AP sends (for example, sends by broadcast) a first frame (for example, a trigger frame) to the STA 1 and the STA 2 based on the fourth frame (for example, a sensing response frame in FIG. 9f) fed back by both the STA 1 and the STA 2, to configure a role and a sensing parameter for both the STA 1 and the STA 2 to participate in the sensing session. After receiving the first frame, the STA 1 sends a second frame (for example, a confirm frame) to the AP, and confirms to accept first information that is in the first frame and that is configured by the AP for the STA 1. After receiving the first frame, the STA 2 sends a second frame to the AP, and confirms to accept first information that is in the first frame and that is configured by the AP for the STA 2. In a measurement phase, the AP sends a sensing signal to the STA 1 and the STA 2. After receiving the sensing signal, the STA 1 and the STA 2 perform signal processing measurement to obtain a measurement result. In a reporting phase, the AP sends a Poll frame to both the STA 1 and the STA 2, so that the STA 1 and the STA 2 send the measurement result to the AP after receiving the Poll frame. Further, because the STA 1 is an initiator, the AP sends, to the STA 1, the measurement result sent by the STA 1 and the STA 2.

[00410] It should be noted that, in the reporting phase, the AP may alternatively obtain the measurement result of the STA 1 and the STA 2 in a scheduling-based manner (as shown in case 2 in FIG. 5c) or a contention-based manner (as shown in case 3 in FIG. 5c).

[00411] If the AP establishes the sensing session by using the method shown in FIG. 8a, a schematic diagram of the sensing procedure in the application scenario in FIG. 9a is shown in FIG. 9g. In the sensing session establishment phase, the AP sends a fifth frame (a trigger frame in FIG. 9d) to the STA 1 and the STA 2 by using the method shown in FIG. 8a, to request the STA 1 and the STA 2 to participate in the sensing session, and configures a role and a sensing parameter for both the STA 1 and the STA 2 to participate in the sensing session. After the STA 1 and the STA 2

receive the fifth frame from the AP, the STA 1 and the STA 2 separately send a sixth frame (for example, a confirm frame in FIG. 9d) to the AP. If the sixth frame in FIG. 9d indicates that the STA receiving/sending the sixth frame refuses to participate in the sensing session by using the role and/or the sensing parameter configured in the fifth frame, the AP sends the fifth frame to the STA 1 and the STA 2 again, and configures the role and the sensing parameter for the STA 1 and the STA 2 to participate in the sensing session until the sixth frame sent by the STA 1 to the AP indicates that the STA 1 confirms to participate in the sensing session by using the third role and the fourth sensing parameter that correspond to the STA 1, and/or the sixth frame sent by the STA 2 to the AP indicates that the STA 2 confirms to participate in the sensing session by using the third role and the fourth sensing parameter that correspond to the STA 2. In a measurement phase, the AP sends a sensing signal to the STA 1 and the STA 2. After receiving the sensing signal, the STA 1 and the STA 2 perform signal processing measurement to obtain a measurement result. In a reporting phase, the AP sends a Poll frame to both the STA 1 and the STA 2, so that the STA 1 and the STA 2 send the measurement result to the AP after receiving the Poll frame. It should be noted that, in the reporting phase, the AP may alternatively obtain the measurement result of the STA 1 and the STA 2 in a scheduling-based manner (as shown in case 2 in FIG. 5c) or a contention-based manner (as shown in case 3 in FIG. 5c). Further, because the STA 1 is an initiator, the AP sends, to the STA 1, the measurement result sent by the STA 1 and the STA 2.

[00412] FIG. 10a is an application scenario of a sensing session according to this application.

[00413] In an application scenario corresponding to FIG. 10a, an AP is an independent sensing initiator (that is, the AP serves as a sensing initiator, and the AP does not participate in receiving/sending of a sensing signal), and a STA 1, a STA 2, and a STA 3 are STAs associated with the AP (that is, the foregoing second STAs).

[00414] In a sensing session establishment phase, if the AP establishes the sensing session by using the method shown in FIG. 6a, a schematic diagram of the sensing procedure in the application scenario in FIG. 10a is shown in FIG. 10b. In the sensing session establishment phase, the AP sends a first frame (for example, a trigger frame in FIG. 10b) to the STA 1, the STA 2, and the STA 3 by using the method shown in FIG. 6a, to configure a role and a sensing parameter for each of the STA 1, the STA 2, and the STA 3 to participate in the sensing session. After receiving the first frame, the STA 1 sends a second frame (for example, a response frame in FIG. 10b) to the AP, and confirms to accept first information that is in the first frame and that is configured by the AP for the STA 1. After receiving the first frame, the STA 2 sends a second frame to the AP, and confirms to accept first information that is in the first frame and that is configured by the AP for the STA 2. After receiving the first frame, the STA 3 sends a second frame to the AP, and confirms to accept first information that is in the first frame and that is configured by the AP for the STA 3.

In a measurement phase, the STA 1 sends a sensing signal to the STA 2 and the STA 3. After receiving the sensing signal, the STA 2 and the STA 3 perform signal processing measurement to obtain a measurement result. In a reporting phase, the AP sends a Poll frame to both the STA 2 and the STA 3, so that the STA 2 and the STA 3 send the measurement result to the AP after receiving the Poll frame. It should be noted that, in the reporting phase, the AP may alternatively obtain the measurement result of the STA 2 and the STA 3 in a scheduling-based manner (as shown in case 2 in FIG. 5c) or a contention-based manner (as shown in case 3 in FIG. 5c).

[00415] In the sensing session establishment phase, if the AP establishes the sensing session by using the method shown in FIG. 7a, a schematic diagram of the sensing procedure in the application scenario in FIG. 10a is shown in FIG. 10c. In the sensing session establishment phase, the AP sends a third frame (a sensing request frame in FIG. 10c) to each of the STA 1, the STA 2, and the STA 3 by using the method shown in FIG. 7a, to request the STA 1, the STA 2, and the STA 3 to participate in the sensing session. After the STA 1 receives the third frame from the AP, the STA 1 sends a fourth frame (for example, a sensing response frame in FIG. 9c) to the AP, and indicates, in the fourth frame, a receiving/sending capability of the STA 1 (for example, a role supported in the sensing session is a transmitter) and a corresponding sensing parameter. After the STA 2 receives the third frame from the AP, the STA 2 sends a fourth frame (for example, a sensing response frame in FIG. 9c) to the AP, and indicates, in the fourth frame, a receiving/sending capability of the STA 2 (for example, a role supported in the sensing session is a receiver) and a corresponding sensing parameter. After the STA 3 receives the third frame from the AP, the STA 3 sends a fourth frame (for example, a sensing response frame in FIG. 9c) to the AP, and indicates, in the fourth frame, a receiving/sending capability of the STA 3 (for example, a role supported in the sensing session is a receiver) and a corresponding sensing parameter. Further, the AP determines the STA 1, the STA 2, and the STA 3 as first STAs participating in the sensing session, and the AP sends (for example, sends by broadcast) a first frame (for example, a Trigger frame) to the STA 1, the STA 2, and the STA 3 based on a fourth frame (for example, a sensing response frame in FIG. 9c) fed back by each of the STA 1, the STA 2, and the STA 3, and configures a role and a sensing parameter for each of the STA 1, the STA 2, and the STA 3 to participate in the sensing session. After receiving the first frame, the STA 1 sends a second frame (for example, a Confirm frame) to the AP, and confirms to accept first information that is in the first frame and that is configured by the AP for the STA 1. After receiving the first frame, the STA 2 sends a second frame to the AP, and confirms to accept first information that is in the first frame and that is configured by the AP for the STA 2. After receiving the first frame, the STA 3 sends a second frame to the AP, and confirms to accept first information that is in the first frame and that is configured by the AP for the STA 3. In a measurement phase, the STA 1 sends a sensing signal to the STA 2

and the STA 3. After receiving the sensing signal, the STA 2 and the STA 3 perform signal processing measurement to obtain a measurement result. In a reporting phase, the AP sends a Poll frame to both the STA 2 and the STA 3, so that the STA 2 and the STA 3 send the measurement result to the AP after receiving the Poll frame. It should be noted that, in the reporting phase, the AP may alternatively obtain the measurement result of the STA 2 and the STA 3 in a scheduling-based manner (as shown in case 2 in FIG. 5c) or a contention-based manner (as shown in case 3 in FIG. 5c).

[00416] In the sensing session establishment phase, if the AP establishes the sensing session by using the method shown in FIG. 8a, a schematic diagram of the sensing procedure in the application scenario in FIG. 10a is shown in FIG. 10d. In the sensing session establishment phase, the AP sends a fifth frame (a trigger frame in FIG. 10d) to the STA 1, the STA 2, and the STA 3 by using the method shown in FIG. 8a, to request the STA 1, the STA 2, and the STA 3 to participate in the sensing session, and configures a role and a sensing parameter for each of the STA 1, the STA 2, and the STA 3 to participate in the sensing session. After the STA 1, the STA 2, and the STA 3 receive the fifth frame from the AP, the STA 1, the STA 2, and the STA 3 separately send a sixth frame (for example, a confirm frame in FIG. 10d) to the AP. If the sixth frame sent by a STA (the STA 1, the STA 2, or the STA 3) in FIG. 10d indicates that the STA refuses to participate in the sensing session by using the role and/or the sensing parameter configured in the fifth frame, the AP sends the fifth frame to the STA 1, the STA 2, and STA 3 again, and configures the role and the sensing parameter for the STA 1, the STA 2, and the STA 3 to participate in the sensing session until the sixth frame sent by the STA 1 to the AP indicates that the STA 1 confirms to participate in the sensing session by using the third role and the fourth sensing parameter that correspond to the STA 1, and/or the sixth frame sent by the STA 2 to the AP indicates that the STA 2 confirms to participate in the sensing session by using the third role and the fourth sensing parameter that correspond to the STA 2, and/or the sixth frame sent by the STA 3 to the AP indicates that the STA 3 confirms to participate in the sensing session by using the third role and the fourth sensing parameter that correspond to the STA 3. In a measurement phase, the STA 1 sends a sensing signal to the STA 2 and the STA 3. After receiving the sensing signal, the STA 2 and the STA 3 perform signal processing measurement to obtain a measurement result. In a reporting phase, the AP sends a Poll frame to both the STA 2 and the STA 3, so that the STA 2 and the STA 3 send the measurement result to the AP after receiving the Poll frame. It should be noted that, in the reporting phase, the AP may alternatively obtain the measurement result of the STA 2 and the STA 3 in a scheduling-based manner (as shown in case 2 in FIG. 5c) or a contention-based manner (as shown in case 3 in FIG. 5c).

[00417] FIG. 11a is an application scenario of a sensing session according to this application.

In this application scenario, an AP is an independent sensing initiator (that is, the AP serves as a sensing initiator, and the AP does not participate in receiving/sending of a sensing signal), and a STA 1, a STA 2, and a STA 3 are STAs associated with the AP (that is, the foregoing second STAs). The STA 1 has a strong function. It may be understood that the STA 1 has a capability of coordinating another STA to participate in the sensing session (including but not limited to a capability of sending a sensing request frame to request the another STA to participate in the sensing session, and a capability of configuring a role or a sensing parameter for the another STA), or it may be understood that the STA 1 and another STA (the STA 2 or the STA 3) are not STAs at the same level, and the level of the STA 1 is higher than that of the another STA (the STA 2 or the STA 3).

[00418] In a sensing session implementation procedure, the AP sends a sensing request frame to the STA 1, to request the STA 1 to participate in the sensing session. After receiving the sensing request frame, the STA 1 feeds back (or sends) a sensing response frame to the AP, and the sensing response frame indicates whether the STA 1 confirms to participate in the sensing session. When the STA 1 agrees to participate in the sensing session, the STA 1 performs coordinated scheduling on the STAs (for example, the STA 2 and the STA 3) participating in the sensing session.

[00419] In an application scenario corresponding to FIG. 11a, in a sensing session establishment phase, the STA 1 sends a first frame (a trigger frame in FIG. 11b) to the STA 2 and the STA 3 by using the method shown in FIG. 6a, and configures a role and a sensing parameter for both the STA 2 and STA 3 to participate in the sensing session. After receiving the first frame, the STA 2 sends a second frame (for example, a confirm frame in FIG. 11b) to the STA 1, and confirms to accept first information that is in the first frame and that is configured by the AP for the STA 2. After receiving the first frame, the STA 3 sends a second frame to the STA 1, and confirms to accept first information that is in the first frame and that is configured by the AP for the STA 3. In a measurement phase, the STA 1 sends a sensing signal to the STA 2 and the STA 3. After receiving the sensing signal, the STA 2 and the STA 3 perform signal processing measurement to obtain a measurement result. In a reporting phase, the STA 1 sends a Poll frame to both the STA 2 and the STA 3, so that the STA 2 and the STA 3 send the measurement result to the STA 1 after receiving the Poll frame. Further, the STA 1 sends, to the AP, a measurement report received from the STA 2 and the STA 3. It should be noted that, in the reporting phase, the STA 1 may alternatively obtain the measurement result of the STA 2 and the STA 3 in a scheduling-based manner (as shown in case 2 in FIG. 5c) or a contention-based manner (as shown in case 3 in FIG. 5c).

[00420] In the sensing session establishment phase, if the AP establishes the sensing session by using the method shown in FIG. 7a, a schematic diagram of the sensing procedure in the application scenario in FIG. 10a is shown in FIG. 11c. In the sensing session establishment phase,

the STA 1 sends a third frame (a sensing request frame in FIG. 11c) to both the STA 2 and the STA 3 by using the method shown in FIG. 7a, to request the STA 2 and the STA 3 to participate in the sensing session. After the STA 2 receives the third frame from the STA 1, the STA 2 sends a fourth frame (for example, a sensing response frame in FIG. 11c) to the STA 1, and indicates, in the fourth frame, a receiving/sending capability of the STA 2 (for example, a role supported in a sensing session is a receiver) and a corresponding sensing parameter. After the STA 3 receives the third frame from the STA 1, the STA 3 sends a fourth frame (for example, a sensing response frame in FIG. 9c) to the STA 1, and indicates, in the fourth frame, a receiving/sending capability of the STA 3 (for example, a role supported in a sensing session is a receiver) and a corresponding sensing parameter. Further, the STA 1 determines the STA 2 and the STA 3 as first STAs participating in the sensing session, and the STA 1 sends (for example, sends by broadcast) a first frame (for example, a trigger frame) to the STA 2 and the STA 3 based on the fourth frame (for example, a sensing response frame in FIG. 11c) fed back by both the STA 2 and the STA 3, to configure a role and a sensing parameter for both the STA 2 and the STA 3 to participate in the sensing session. After receiving the first frame, the STA 2 sends a second frame (for example, a confirm frame) to the STA 1, and confirms to accept first information that is in the first frame and that is configured by the AP for the STA 2. After receiving the first frame, the STA 3 sends a second frame to the STA 1, and confirms to accept first information that is in the first frame and that is configured by the AP for the STA 3. In a measurement phase, the STA 1 sends a sensing signal to the STA 2 and the STA 3. After receiving the sensing signal, the STA 2 and the STA 3 perform signal processing measurement to obtain a measurement result. In a reporting phase, the STA 1 sends a Poll frame to both the STA 2 and the STA 3, so that the STA 2 and the STA 3 send the measurement result to the STA 1 after receiving the Poll frame. Further, the STA 1 sends, to the AP, a measurement report received from the STA 2 and the STA 3. It should be noted that, in the reporting phase, the STA 1 may alternatively obtain the measurement result of the STA 2 and the STA 3 in a scheduling-based manner (as shown in case 2 in FIG. 5c) or a contention-based manner (as shown in case 3 in FIG. 5c).

[00421] In the sensing session establishment phase, if the STA 1 establishes the sensing session by using the method shown in FIG. 8a, a schematic diagram of the sensing procedure in the application scenario in FIG. 11a is shown in FIG. 11d. In the sensing session establishment phase, the STA 1 sends a fifth frame (a trigger frame in FIG. 11d) to the STA 2 and the STA 3 by using the method shown in FIG. 8a, to request the STA 2 and the STA 3 to participate in the sensing session, and configures a role and a sensing parameter for both the STA 2 and the STA 3 to participate in the sensing session. After the STA 2 and the STA 3 receive the fifth frame from the STA 1, the STA 2 and the STA 3 separately send a sixth frame (for example, a confirm frame in

FIG. 11d) to the AP. If the sixth frame sent by another STA (the STA 2 or the STA 3) other than the STA 1 in FIG. 11d indicates that the STA receiving/sending the sixth frame refuses to participate in the sensing session by using the role and/or the sensing parameter configured in the fifth frame, the STA 1 sends the fifth frame to the STA 2 and the STA 3 again, and configures the role and the sensing parameter for the STA 2 and the STA 3 to participate in the sensing session until the sixth frame sent by the STA 2 to the AP indicates that the STA 2 confirms to participate in the sensing session by using the third role and the fourth sensing parameter that correspond to the STA 2, and/or the sixth frame sent by the STA 3 to the AP indicates that the STA 3 confirms to participate in the sensing session by using the third role and the fourth sensing parameter that correspond to the STA 3. In a measurement phase, the STA 1 sends a sensing signal to the STA 2 and the STA 3. After receiving the sensing signal, the STA 2 and the STA 3 perform signal processing measurement to obtain a measurement result. In a reporting phase, the STA 1 sends a Poll frame to both the STA 2 and the STA 3, so that the STA 2 and the STA 3 send the measurement result to the STA 1 after receiving the Poll frame. Further, the STA 1 sends, to the AP, a measurement report received from the STA 2 and the STA 3. It should be noted that, in the reporting phase, the STA 1 may alternatively obtain the measurement result of the STA 2 and the STA 3 in a scheduling-based manner (as shown in case 2 in FIG. 5c) or a contention-based manner (as shown in case 3 in FIG. 5c).

[00422] In another application scenario corresponding to FIG. 11a, in a sensing session establishment phase, the AP sends a first frame (a trigger frame in FIG. 11e) to the STA 1, the STA 2, and the STA 3 by using the method shown in FIG. 6a, and configures a role and a sensing parameter for each of the STA 1, STA 2, and STA 3 to participate in the sensing session. After receiving the first frame, the STA 1 sends a second frame (for example, a confirm frame in FIG. 11e) to the STA 1, and confirms to accept first information that is in the first frame and that is configured by the AP for the STA 1. After receiving the first frame, the STA 2 sends a second frame (for example, a confirm frame in FIG. 11e) to the STA 1, and confirms to accept first information that is in the first frame and that is configured by the AP for the STA 2. After receiving the first frame, the STA 3 sends a second frame to the STA 1, and confirms to accept first information that is in the first frame and that is configured by the AP for the STA 3. In a measurement phase, the STA 1 sends a sensing signal to the STA 2 and the STA 3. After receiving the sensing signal, the STA 2 and the STA 3 perform signal processing measurement to obtain a measurement result. In a reporting phase, the STA 1 sends a Poll frame to both the STA 2 and the STA 3, so that the STA 2 and the STA 3 send the measurement result to the STA 1 after receiving the Poll frame. Further, the STA 1 sends, to the AP, a measurement report received from the STA 2 and the STA 3. It should be noted that, in the reporting phase, the STA 1 may alternatively obtain the measurement result

of the STA 2 and the STA 3 in a scheduling-based manner (as shown in case 2 in FIG. 5c) or a contention-based manner (as shown in case 3 in FIG. 5c).

[00423] In the sensing session establishment phase, if the AP establishes the sensing session by using the method shown in FIG. 7a, a schematic diagram of the sensing procedure in the application scenario in FIG. 10a is shown in FIG. 11f. In the sensing session establishment phase, the AP sends a third frame (a sensing request frame in FIG. 11f) to each of the STA 1, the STA 2, and the STA 3 by using the method shown in FIG. 7a, to request the STA 1, the STA 2, and the STA 3 to participate in the sensing session. After the STA 1 receives the third frame from the AP, the STA 1 sends a fourth frame (for example, a sensing response frame in FIG. 11c) to the AP, and indicates, in the fourth frame, a receiving/sending capability of the STA 1 (for example, a role supported in the sensing session is a transmitter) and a corresponding sensing parameter. After the STA 2 receives the third frame from the AP, the STA 2 sends a fourth frame (for example, a sensing response frame in FIG. 11f) to the AP, and indicates, in the fourth frame, a receiving/sending capability of the STA 2 (for example, a role supported in the sensing session is a receiver) and a corresponding sensing parameter. After the STA 3 receives the third frame from the AP, the STA 3 sends a fourth frame (for example, a sensing response frame in FIG. 11f) to the AP, and indicates, in the fourth frame, a receiving/sending capability of the STA 3 (for example, a role supported in the sensing session is a receiver) and a corresponding sensing parameter. Further, the AP determines the STA 1, the STA 2, and the STA 3 as first STAs participating in the sensing session, and the AP sends (for example, sends by broadcast) a first frame (for example, a Trigger frame) to the STA 2, and the STA 3 based on a fourth frame (for example, a sensing response frame in FIG. 11f) fed back by each of the STA 1, the STA 2, and the STA 3, and configures a role and a sensing parameter for each of the STA 1, the STA 2, and the STA 3 to participate in the sensing session. After receiving the first frame, the STA 1 sends a second frame (for example, a Confirm frame) to the AP, and confirms to accept first information that is in the first frame and that is configured by the AP for the STA 1. After receiving the first frame, the STA 2 sends a second frame (for example, a Confirm frame) to the AP, and confirms to accept first information that is in the first frame and that is configured by the AP for the STA 2. After receiving the first frame, the STA 3 sends a second frame to the AP, and confirms to accept first information that is in the first frame and that is configured by the AP for the STA 3. In a measurement phase, the STA 1 sends a sensing signal to the STA 2 and the STA 3. After receiving the sensing signal, the STA 2 and the STA 3 perform signal processing measurement to obtain a measurement result. In a reporting phase, the STA 1 sends a Poll frame to both the STA 2 and the STA 3, so that the STA 2 and the STA 3 send the measurement result to the STA 1 after receiving the Poll frame. Further, the STA 1 sends, to the AP, a measurement report received from the STA 2 and the STA 3. It should be noted that, in the

reporting phase, the AP may alternatively obtain the measurement result of the STA 2 and the STA 3 in a scheduling-based manner (as shown in case 2 in FIG. 5c) or a contention-based manner (as shown in case 3 in FIG. 5c).

[00424] In the sensing session establishment phase, if the AP establishes the sensing session by using the method shown in FIG. 8a, a schematic diagram of the sensing procedure in the application scenario in FIG. 11a is shown in FIG. 11g. In the sensing session establishment phase, the AP sends a fifth frame (a trigger frame in FIG. 11g) to the STA 1, the STA 2, and the STA 3 by using the method shown in FIG. 8a, to request the STA 1, the STA 2, and the STA 3 to participate in the sensing session, and configures a role and a sensing parameter for each of the STA 1, the STA 2, and the STA 3 to participate in the sensing session. After the STA 1, the STA 2, and the STA 3 receive the fifth frame from the AP, the STA 1, the STA 2, and the STA 3 separately send a sixth frame (for example, a confirm frame in FIG. 11g) to the AP. If the sixth frame sent by another STA (the STA 2 or the STA 3) other than the STA 1 in FIG. 11g indicates that the STA receiving/sending the sixth frame refuses to participate in the sensing session by using the role and/or the sensing parameter configured in the fifth frame, the AP sends the fifth frame to the STA 1, the STA 2, and STA 3 again, and configures the role and the sensing parameter for the STA 1, the STA 2, and the STA 3 to participate in the sensing session until the sixth frame sent by the STA 1 to the AP indicates that the STA 1 confirms to participate in the sensing session by using the third role and the fourth sensing parameter that correspond to the STA 1, and/or the sixth frame sent by the STA 2 to the AP indicates that the STA 2 confirms to participate in the sensing session by using the third role and the fourth sensing parameter that correspond to the STA 2, and/or the sixth frame sent by the STA 3 to the AP indicates that the STA 3 confirms to participate in the sensing session by using the third role and the fourth sensing parameter that correspond to the STA 3. In a measurement phase, the STA 1 sends a sensing signal to the STA 2 and the STA 3. After receiving the sensing signal, the STA 2 and the STA 3 perform signal processing measurement to obtain a measurement result. In a reporting phase, the STA 1 sends a Poll frame to both the STA 2 and the STA 3, so that the STA 2 and the STA 3 send the measurement result to the STA 1 after receiving the Poll frame. Further, the STA 1 sends, to the AP, a measurement report received from the STA 2 and the STA 3. It should be noted that, in the reporting phase, the STA 1 may alternatively obtain the measurement result of the STA 2 and the STA 3 in a scheduling-based manner (as shown in case 2 in FIG. 5c) or a contention-based manner (as shown in case 3 in FIG. 5c).

[00425] FIG. 12 is a schematic diagram of a structure of a communication apparatus according to an embodiment of this application. The communication apparatus 1200 may be the AP or a circuit system of the AP according to any one of the embodiments shown in FIG. 6a, FIG. 7a, or FIG. 8a, and is configured to implement the method corresponding to the AP according to the

foregoing method embodiments. Alternatively, the communication apparatus 1200 may be the STA or a circuit system of the STA according to any one of the embodiments shown in FIG. 6a, FIG. 7a, or FIG. 8a, and is configured to implement the method corresponding to the STA according to the foregoing method embodiments. For a specific function, refer to the description in the foregoing method embodiments. For example, the circuit system is a chip system.

[00426] The communication apparatus 1200 includes one or more processors 1201. The processor 1201 may alternatively be referred to as a processing unit, and may implement a specific control function. The processor 1201 may be a general-purpose processor, a dedicated processor, or the like. For example, the processor 1201 may be a baseband processor, a central processing unit, and the like. The baseband processor may be configured to process a communication protocol and communication data. The central processing unit may be configured to control the communication apparatus 1200, execute a software program, and/or process data. Different processors may be independent components, or may be disposed in one or more processing circuits, for example, integrated into one or more application-specific integrated circuits.

[00427] Optionally, the communication apparatus 1200 includes one or more memories 1202, configured to store instructions 1204. The instructions 1204 may be run on the processor, so that the communication apparatus 1200 performs the method described in the foregoing method embodiments. Optionally, the memory 1202 may further store data. The processor and the memory may be separately disposed, or may be integrated together.

[00428] Optionally, the communication apparatus 1200 may include instructions 1203 (which may alternatively be referred to as code or a program sometimes), and the instructions 1203 may be run on the processor, so that the communication apparatus 1200 performs the method described in the foregoing embodiments. The processor 1201 may store data.

[00429] Optionally, the communication apparatus 1200 may further include a transceiver 1205 and an antenna 1206. The transceiver 1205 may be referred to as a transceiver unit, a transceiver machine, a transceiver circuit, a transceiver, an input/output interface, or the like, and is configured to implement sending and receiving functions of the communication apparatus 1200 by using the antenna 1206.

[00430] Optionally, the communication apparatus 1200 may further include one or more of the following components: a wireless communication module, an audio module, an external memory interface, an internal memory, a universal serial bus (universal serial bus, USB) interface, a power management module, an antenna, a loudspeaker, a microphone, an input/output module, a sensor module, a motor, a camera, a display, or the like. It may be understood that, in some embodiments, the communication apparatus 1200 may include more or fewer components, or some components are integrated, or some components are split. These components can be hardware, software, or a

combination implementation of software and hardware.

[00431] The processor 1201 and the transceiver 1205 described in embodiments of this application may be implemented on an integrated circuit (integrated circuit, IC), an analog IC, a radio frequency integrated circuit (radio frequency identification, RFID), a mixed-signal IC, an application-specific integrated circuit (application specific integrated circuit, ASIC), a printed circuit board (printed circuit board, PCB), an electronic device, or the like. The communication apparatus described in this specification may be an independent device (for example, an independent integrated circuit or a mobile phone), or may be a part of a large device (for example, a module that may be embedded in another device). For details, refer to the foregoing descriptions of the AP and the STA. Details are not described herein again.

[00432] An embodiment of this application provides an access point device. The access point device (referred to as an AP for ease of description) may be used in the foregoing embodiments. The terminal device AP includes a corresponding means (means), unit, and/or circuit for implementing functions of the AP according to any one of embodiments shown in FIG. 6a, FIG. 7a, or FIG. 8a. For example, the AP includes a transceiver module, configured to support the AP in implementing sending and receiving functions, and a processing module, configured to support the AP in processing a signal.

[00433] An embodiment of this application further provides a station device. The station device (referred to as a STA for ease of description) may be used in the foregoing embodiments. The STA includes a corresponding means (means), unit, and/or circuit for implementing functions of the STA according to any one of the embodiments shown in FIG. 6a, FIG. 7a, or FIG. 8a. For example, the STA includes a transceiver module, configured to support the STA in implementing sending and receiving functions, and a processing module, configured to support the STA in processing a signal.

[00434] When several embodiments provided in this application are implemented in a form of software functional units and sold or used as independent products, the product may be stored in a computer-readable storage medium. The computer software product is stored in a storage medium, and includes several instructions for instructing a computer device (which may be a personal computer, a server, a network device, or the like) to perform all or some of the steps of the method described in embodiments of this application. The foregoing computer-readable storage medium may be any usable medium that can be accessed by a computer. The following provides an example but does not impose a limitation: The computer-readable medium may include a random access memory (random access memory, RAM), a read-only memory (read-only memory, ROM), or any other medium that can be used to carry or store expected program code in a form of instructions or a data structure and can be accessed by a computer.

[00435] The foregoing descriptions are merely specific implementations of this application, but are not intended to limit the protection scope of embodiments of this application. Any variation or replacement readily figured out by a person skilled in the art within the technical scope disclosed in embodiments of this application shall fall within the protection scope of embodiments of this application. Therefore, the protection scope of embodiments of this application shall be subject to the protection scope of the claims.

5

CLAIMS

What is claimed is:

1. A sensing session establishment method, wherein the method comprises:

5 sending, by an access point AP, a first frame to a first station STA, wherein the first frame comprises first information, the first information indicates a first role of the first STA in a sensing session, the first role of the first STA in the sensing session is a transmitter and/or a receiver, and the first STA is a STA participating in the sensing session in a second STA associated with the AP; and

10 receiving, by the AP, a second frame from the first STA, wherein the second frame comprises confirm information for the first frame.

2. The method according to claim 1, wherein the first frame further comprises a first sensing parameter, and the first sensing parameter is used by the first STA to perform sensing measurement and/or sensing data reporting in the sensing session.

15 3. The method according to claim 2, wherein the first sensing parameter comprises one or more of the following parameters: an operation parameter, a feedback type, a sensing type, or a feedback address.

4. The method according to any one of claims 1 to 3, wherein that the first frame comprises first information specifically comprises:

20 the first frame comprises a common information field and a user information field, and the first information is located in the common information field and/or the user information field;

the first frame comprises a station information field, and the first information is located in the station information field; or

the first frame comprises a common information field and a station information field, and the first information is located in the common information field and/or the station information field.

25 5. The method according to any one of claims 1 to 4, wherein that the second frame comprises confirm information for the first frame specifically comprises:

the second frame comprises a confirm element field, and the confirm information is located in the confirm element field.

30 6. The method according to any one of claims 1 to 5, wherein before the sending, by an AP, a first frame to a first STA, the method further comprises:

sending, by the AP, a third frame to a plurality of second STAs, wherein the third frame comprises second information, and the second information is used to request the second STA to participate in the sensing session;

receiving, by the AP, a fourth frame from the plurality of second STAs, wherein the fourth

frame comprises third information, and the third information indicates whether the second STA confirms to participate in the sensing session; and

determining, by the AP, the first STA from the plurality of second STAs based on the third information from the plurality of second STAs.

5 7. The method according to claim 6, wherein when the third information indicates that the second STA confirms to participate in the sensing session, the third information further comprises a second role supported by the second STA in the sensing session and a second sensing parameter corresponding to the second role; and

10 the determining, by the AP, the first STA from the plurality of second STAs based on the third information from the plurality of second STAs comprises:

determining, by the AP, the first STA from the plurality of second STAs based on a role of the AP in the sensing session and the third information from the plurality of second STAs.

15 8. The method according to claim 7, wherein the role of the AP in the sensing session is not a transmitter and the role of the AP in the sensing session is not a receiver, and the determining, by the AP, the first STA from the plurality of second STAs based on a role of the AP in the sensing session and the third information from the plurality of second STAs comprises:

20 when third information from a third STA indicates that the third STA participates in the sensing session, and third information from a fourth STA indicates that the fourth STA participates in the sensing session, determining, by the AP, the third STA and the fourth STA as the first STAs, wherein

a second role corresponding to the third STA is a receiver in the sensing session, and a second role corresponding to the fourth STA is a transmitter in the sensing session.

25 9. The method according to claim 8, wherein the third STA and the fourth STA are a same STA.

30 10. The method according to claim 7, wherein the role of the AP in the sensing session is a transmitter, and the determining, by the AP, the first STA from the plurality of second STAs based on a role of the AP in the sensing session and the third information from the plurality of second STAs comprises:

when third information from a fifth STA indicates that the fifth STA participates in the sensing session, determining, by the AP, the fifth STA as the first STA, wherein

the fifth STA is one of the plurality of second STAs, and a second role corresponding to the fifth STA is a receiver in the sensing session.

35 11. The method according to claim 7, wherein the role of the AP in the sensing session is a receiver, and the determining, by the AP, the first STA from the plurality of second STAs based on a role of the AP in the sensing session and the third information from the plurality of second STAs

comprises:

when third information from a sixth STA indicates that the sixth STA participates in the sensing session, determining, by the AP, the sixth STA as the first STA, wherein

the sixth STA is one of the plurality of second STAs, and a second role corresponding to the sixth STA is a transmitter in the sensing session.

12. The method according to any one of claims 7 to 11, wherein the method further comprises: determining, by the AP, the first sensing parameter based on the second sensing parameter.

13. The method according to any one of claims 6 to 12, wherein that the third frame comprises second information specifically comprises:

the third frame comprises a common information field, and the second information is located in the common information field; or

the third frame comprises a sensing request element field, and the second information is located in the sensing request element field.

14. The method according to any one of claims 6 to 13, wherein that the fourth frame comprises third information specifically comprises:

the fourth frame comprises a sensing confirm element field, and the third information is located in the sensing confirm element field; or

the fourth frame comprises a sensing response element field, and the third information is located in the sensing response element field.

15. The method according to any one of claims 1 to 3, wherein that the first frame comprises first information specifically comprises:

the first frame comprises a sensing request element field, and the first information is located in the sensing request element field.

16. The method according to claim 15, wherein that the second frame comprises confirm information for the first frame specifically comprises:

the second frame comprises a sensing response element field, and the confirm information is located in the sensing response field.

17. The method according to claim 15 or 16, wherein the method further comprises:

sending, by the AP, a fifth frame to a plurality of second STAs, wherein the fifth frame comprises fourth information, and the fourth information is used to request the second STA to participate in the sensing session by using a third role and a fourth sensing parameter;

receiving, by the AP, a sixth frame from the plurality of second STAs, wherein the sixth frame comprises fifth information, and the fifth information indicates whether the second STA confirms to participate in the sensing session by using the third role and the fourth sensing parameter; and

determining, by the AP, the first STA from the plurality of second STAs based on the fifth

information from the plurality of second STAs.

18. The method according to claim 17, wherein the determining, by the AP, the first STA from the plurality of second STAs based on the fifth information from the plurality of second STAs comprises:

5 when fifth information from a third STA indicates that the third STA participates in the sensing session based on a third role corresponding to the third STA and the fourth sensing parameter, and fifth information from a fourth STA indicates that the fourth STA participates in the sensing session based on a third role corresponding to the fourth STA and the fourth sensing parameter, determining, by the AP, the third STA and the fourth STA as the first STAs, wherein

10 the third role corresponding to the third STA is a receiver in the sensing session, and the third role corresponding to the fourth STA is a transmitter in the sensing session.

19. The method according to claim 18, wherein the third STA and the fourth STA are a same STA.

20. The method according to claim 17, wherein the determining, by the AP, the first STA from the plurality of second STAs based on the fifth information from the plurality of second STAs comprises:

determining, by the AP, the first STA from the plurality of second STAs based on a role of the AP in the sensing session and the fifth information from the plurality of second STAs.

21. The method according to claim 20, wherein the determining, by the AP, the first STA from the plurality of second STAs based on a role of the AP in the sensing session and the fifth information from the plurality of second STAs comprises:

25 when the role of the AP in the sensing session is a transmitter, and fifth information from a fifth STA indicates that the fifth STA participates in the sensing session based on a third role corresponding to the fifth STA, determining, by the AP, the fifth STA as the first STA, wherein the fifth STA is one of the plurality of second STAs, and the third role corresponding to the fifth STA is a receiver in the sensing session; or

30 when the role of the AP in the sensing session is a receiver, and fifth information from a sixth STA indicates that the sixth STA participates in the sensing session based on a third role corresponding to the sixth STA, determining, by the AP, the sixth STA as the first STA, wherein the sixth STA is one of the plurality of second STAs, and the third role corresponding to the sixth STA is a transmitter in the sensing session.

22. The method according to claim 21, wherein when the fifth information from the fifth STA indicates that the fifth STA participates in the sensing session based on the third role corresponding to the fifth STA, but the fifth STA does not participate in the sensing session based on a fourth sensing parameter corresponding to the fifth STA, or when the fifth information from the sixth

STA indicates that the sixth STA participates in the sensing session based on the third role corresponding to the sixth STA, but the sixth STA does not participate in the sensing session based on a fourth sensing parameter corresponding to the sixth STA, the fifth information further comprises a fifth sensing parameter of the first STA; and

5 the method further comprises:

 determining, by the AP based on the fifth sensing parameter of the first STA, the first sensing parameter corresponding to the first STA.

23. The method according to any one of claims 17 to 22, wherein that the fifth frame comprises fourth information specifically comprises:

10 the fifth frame comprises a sensing request element field, and the fourth information is located in the sensing request element field.

24. The method according to any one of claims 17 to 23, wherein that the sixth frame comprises fifth information specifically comprises:

15 the sixth frame comprises a sensing response element field, and the fifth information is located in the sensing response element field.

25. The method according to any one of claims 1 to 24, wherein the method further comprises: receiving, by the AP, sensing requirement information from an initiator STA.

26. A sensing session establishment method, wherein the method comprises:

20 receiving, by a station STA, a first frame from an access point AP, wherein the first frame comprises first information, the first information indicates a first role of the STA in a sensing session, and the first role of the STA in the sensing session is a transmitter and/or a receiver; and

 sending, by the STA, a second frame to the AP, wherein the second frame comprises confirm information for the first frame.

27. The method according to claim 26, wherein the first frame further comprises a first
25 sensing parameter, and the first sensing parameter is used by the STA to perform sensing measurement and/or sensing data reporting in the sensing session.

28. The method according to claim 27, wherein the first sensing parameter comprises one or more of the following parameters: an operation parameter, a feedback type, a sensing type, or a feedback address.

30 29. The method according to any one of claims 26 to 28, wherein that the first frame comprises first information specifically comprises:

 the first frame comprises a common information field and a user information field, and the first information is located in the common information field and/or the user information field;

35 the first frame comprises a station information field, and the first information is located in the station information field; or

the first frame comprises a common information field and a station information field, and the first information is located in the common information field and/or the station information field.

30. The method according to any one of claims 26 to 29, wherein that the second frame comprises confirm information for the first frame specifically comprises:

5 the second frame comprises a confirm element field, and the confirm information is located in the confirm element field.

31. The method according to any one of claims 26 to 30, wherein the method further comprises:

10 receiving, by the STA, a third frame from the AP, wherein the third frame comprises second information, and the second information is used to request the STA to participate in the sensing session; and

 sending, by the STA, a fourth frame to the AP, wherein the fourth frame comprises third information, and the third information indicates whether the STA confirms to participate in the sensing session.

15 32. The method according to claim 31, wherein when the third information indicates that the STA confirms to participate in the sensing session, the third information further comprises a second role supported by the STA in the sensing session and a second sensing parameter corresponding to the second role.

20 33. The method according to claim 31 or 32, wherein that the third frame comprises second information specifically comprises:

 the third frame comprises a common information field, and the second information is located in the common information field; or

 the third frame comprises a sensing request element field, and the second information is located in the sensing request element field.

25 34. The method according to any one of claims 31 to 33, wherein that the fourth frame comprises third information specifically comprises:

 the fourth frame comprises a sensing confirm element field, and the third information is located in the sensing confirm element field; or

30 the fourth frame comprises a sensing response element field, and the third information is located in the sensing response element field.

35 35. The method according to any one of claims 26 to 28, wherein that the first frame comprises first information specifically comprises:

 the first frame comprises a sensing request element field, and the first information is located in the sensing request element field.

 36. The method according to claim 35, wherein that the second frame comprises confirm

information for the first frame specifically comprises:

the second frame comprises a sensing response element field, and the confirm information is located in the sensing response field.

37. The method according to claim 35 or 36, wherein the method further comprises:

5 receiving, by the STA, a fifth frame from the AP, wherein the fifth frame comprises fourth information, and the fourth information is used to request the STA to participate in the sensing session by using a third role and a fourth sensing parameter; and

10 sending, by the STA, a sixth frame to the AP, wherein the sixth frame comprises fifth information, and the fifth information indicates whether the STA confirms to participate in the sensing session by using the third role and the fourth sensing parameter.

38. The method according to claim 37, wherein when the fifth information indicates that the STA participates in the sensing session based on the third role, but the STA does not participate in the sensing session based on the fourth sensing parameter, the fifth information further comprises a fifth sensing parameter of the STA.

15 39. The method according to claim 37 or 38, wherein that the fifth frame comprises fourth information specifically comprises:

the fifth frame comprises a sensing request element field, and the fourth information is located in the sensing request element field.

20 40. The method according to any one of claims 37 to 39, wherein that the sixth frame comprises fifth information specifically comprises:

the sixth frame comprises a sensing response element field, and the fifth information is located in the sensing response element field.

41. The method according to any one of claims 26 to 40, wherein the method further comprises:

25 sending, by the STA, sensing requirement information to the AP.

42. A communication apparatus, comprising a processor and a memory, wherein the memory is configured to store one or more computer programs, the one or more computer programs comprise computer-executable instructions, and when the communication apparatus runs, the processor executes the one or more computer programs stored in the memory, to enable the
30 communication apparatus to perform the method according to any one of claims 1 to 25, or perform the method according to any one of claims 26 to 41.

43. A computer program product, wherein when the computer program product runs on a computer, the computer is enabled to perform the method according to any one of claims 1 to 25, or perform the method according to any one of claims 26 to 41.

35