



159159

- 1 -



G00002

TITLE OF THE INVENTION

WIRELESS COMMUNICATION DEVICE AND WIRELESS
COMMUNICATION METHOD

BACKGROUND OF THE INVENTION

5 The present invention relates to a wireless
communication device which communicates with a wireless
card or wireless tag used for a credit card, reward
card, or individual identification medium (e.g., a
bankbook, employee card, or passport), and a wireless
10 communication method applied to the wireless communica-
tion device.

 Recently, wireless cards have widely spread for
reasons of information security and portability.
Organizations such as ISO standardize the communication
15 method so that wireless readers/writers and wireless
cards available from various manufacturers can be
utilized without any problem. For example, Jpn. Pat.
Appln. KOKAI Publication No. 9-179954 discloses a
technique for a wireless information processing
20 apparatus which reads/writes data from/on a portable
wireless card via a wireless communication medium.

 However, when the transmission/reception antenna
of the wireless reader/writer and the antenna of the
wireless card are in tight contact with each other
25 and have a similar shape, cross coupling between the
antennas becomes strong, and their antenna characteris-
tics influence each other. The antenna characteristic

of the wireless reader/writer may greatly deviate from the communication frequency of the wireless card.

Along with this, the wireless reader/writer may not normally receive a response from the wireless card.

5 That is, the wireless reader/writer and wireless card which meet the standard of ISO or the like may not be able to communicate with each other.

BRIEF SUMMARY OF THE INVENTION

10 It is an object of the present invention to provide a wireless communication device and wireless communication method capable of solving a communication error caused by the antenna characteristic and realizing a normal communication environment.

15 A wireless communication device according to an aspect of the present invention comprises a main body antenna to communicate with an antenna of a wireless card, and antenna position setting means capable of setting a plurality of types of positional relationships between the antenna of the wireless card and the main body antenna.

20 A wireless communication method according to another aspect of the present invention comprises performing communication between an antenna of a wireless card and a main body antenna which are set
25 to a predetermined positional relationship, changing the positional relationship between the antenna of the wireless card and the main body antenna, as needed,

and performing communication between the antenna of the wireless card and the main body antenna.

Additional objects and advantages of the invention will be set forth in the description which follows, and in part will be obvious from the description, or
5 may be learned by practice of the invention. The objects and advantages of the invention may be realized and obtained by means of the instrumentalities and combinations particularly pointed out hereinafter.

10 BRIEF DESCRIPTION OF THE SEVERAL VIEWS OF THE DRAWING

The accompanying drawings, which are incorporated in and constitute a part of the specification, illustrate presently preferred embodiments of the invention, and together with the general description
15 given above and the detailed description of the preferred embodiments given below, serve to explain the principles of the invention.

FIG. 1 is a block diagram showing an example of the schematic arrangement of a wireless communication device (wireless reader/writer) according to an embodi-
20 ment of the present invention;

FIG. 2 is a view showing an example of a state in which no wireless card antenna exists near the wireless reader/writer antenna;

25 FIG. 3 is a view showing an example of a state in which predetermined conditions are met and cross coupling between the wireless reader/writer antenna and

the wireless card antenna becomes strong and greatly influences their antenna characteristics;

FIG. 4 is a view showing an example of a state in which the wireless card antenna exists near the wireless reader/writer antenna but does not greatly influence their antenna characteristics;

FIG. 5 is a graph showing an example of the frequency characteristic of the wireless reader/writer antenna in the states shown in FIGS. 2 to 4;

FIG. 6 is a view for explaining wireless card antenna position A, wireless card antenna position B, and wireless card antenna position C;

FIG. 7 is a flowchart showing an overall positional relationship change process;

FIG. 8 is a flowchart showing a partial process in the positional relationship change process in FIG. 7, i.e., a positional relationship adjustment process based on communication log information; and

FIG. 9 is a view for explaining wireless card antenna position D, wireless card antenna position E, and wireless card antenna position F.

DETAILED DESCRIPTION OF THE INVENTION

A preferred embodiment of the present invention will be described below with reference to the several views of the accompanying drawing.

FIG. 1 is a block diagram showing an example of the schematic arrangement of a wireless communication

device (to be referred to as a wireless reader/writer hereinafter) according to the embodiment of the present invention. A wireless reader/writer 1000 comprises a wireless reader/writer antenna (main body antenna) 100, control processor 1100, modulation circuit 1200, demodulation circuit 1300, wireless card conveyance/position adjustment unit 1400, and power supply circuit 1500.

The wireless reader/writer 1000 assumes communication in a communication environment at a distance of 20 mm or less between the antenna plane of the wireless reader/writer antenna 100 and that of a wireless card antenna 200. The control processor 1100 instructs the wireless card conveyance/position adjustment unit 1400 to convey a wireless card 2000 to a predetermined position. The wireless card conveyance/position adjustment unit 1400 conveys the wireless card 2000 in accordance with the instruction from the control processor 1100.

The control processor 1100 creates transmission data to the wireless card 2000. The modulation circuit 1200 modulates the transmission data, and converts it into a transmission signal. The transmission signal is transmitted from the wireless reader/writer antenna 100 to the wireless card 2000.

A response signal output from the wireless card antenna 200 of the wireless card 2000 is received

by the wireless reader/writer antenna 100. The demodulation circuit 1300 demodulates the received response signal. The control processor 1100 processes the demodulated response signal, and instructs each unit on the next process.

The power supply circuit 1500 supplies power to each unit of the wireless reader/writer 1000.

The resonant frequency variation phenomenon in the wireless reader/writer antenna 100 of the wireless reader/writer 1000 and the antenna 200 of the wireless card 2000 will be explained with reference to FIGS. 2 to 4.

When the wireless card antenna 200 does not exist near the wireless reader/writer antenna 100, as shown in FIG. 2, the resonant frequency of the wireless reader/writer antenna 100 is f_0 around the communication frequency used to communicate with the wireless card 2000, as represented by the solid line (case 1) in FIG. 5.

When the following conditions (1) to (4) are met between the wireless reader/writer antenna 100 and the wireless card antenna 200, as shown in FIG. 3 (case 2), cross coupling between the antennas becomes strong and greatly influences their antenna characteristics.

(1) Arrangement in which the two antenna planes are parallel and close to each other.

(2) Arrangement in which the centers of the two

antenna planes overlap each other or are close to each other.

(3) The shapes of the two antennas are similar.

5 (4) The sizes of the two antennas are almost equal.

Under these conditions, the antenna resonant frequency of the wireless reader/writer antenna 100 becomes f_b , and greatly deviates from f_0 around the communication frequency used to communicate with the
10 wireless card 2000, as represented by the dotted line (case 2) in FIG. 5.

The wireless reader/writer 1000 and wireless card 2000 are formed with antenna shapes unique to their manufacturers. In some rare occasions, cross coupling
15 between the antennas becomes strong, as described above. The antenna characteristic of the wireless reader/writer 1000 varies more than expected, and the resonant frequency changes to a frequency not suitable for communication with the wireless card 2000. In this
20 case, the wireless reader/writer 1000 cannot receive any response from the wireless card 2000, failing in communication.

When the two antennas are shifted so that the centers of the antenna planes of the wireless card
25 antenna 200 and wireless reader/writer antenna 100 do not overlap each other, as shown in FIG. 4 (case 3), cross coupling between the antennas reduces, and the

resonant frequency of the wireless reader/writer antenna 100 changes to f_a which is almost the same as one obtained when only the wireless reader/writer 1000 is arranged, as represented by the dotted line (case 3) in FIG. 5. As a result, the wireless reader/writer antenna 100 can receive a response from the wireless card 2000 and normally communicate with it.

However, the shift of the positions of the two antennas means an increase in the relative distance between them. Since the wireless card 2000 does not have any battery, its operating power depends on transmission radio waves from the wireless reader/writer 1000. That is, the wireless card 2000 receives transmission radio waves from the wireless reader/writer 1000, and converts them into power. Thus, if the relative distance between the wireless reader/writer 1000 and the wireless card 2000 becomes large, the wireless card 2000 may become short of operating power.

From this, the optimal positional relationship between the wireless reader/writer antenna 100 and the wireless card antenna 200 for normal communication between the wireless reader/writer 1000 and the wireless card 2000 changes depending on the shapes and LSI characteristics of various wireless card antennas 200.

The wireless communication device (wireless

reader/writer 1000) and wireless communication method
of the present invention implement normal communication
with various types of wireless cards 2000 by properly
adjusting the position of the wireless card antenna
5 200, as needed.

Adjustment of the antenna positional relationship
in the parallel direction by the wireless communication
device (wireless reader/writer 1000) and wireless
communication method of the present invention will be
10 explained.

The wireless card conveyance/position adjustment
unit 1400 of the wireless reader/writer 1000 can set a
plurality of types of positional relationships between
the wireless reader/writer antenna 100 and the wireless
15 card antenna 200. For example, as shown in FIG. 6,
the wireless card conveyance/position adjustment unit
1400 can receive the wireless card 2000 and convey the
received wireless card 2000 to wireless card antenna
position A, wireless card antenna position B, and
20 wireless card antenna position C. In other words,
the wireless card conveyance/position adjustment
unit 1400 can change the positional relationship
between the wireless reader/writer antenna 100 and
the wireless card antenna 200, as needed. This can
25 reduce the influence of cross coupling between the
wireless reader/writer antenna 100 and the wireless
card antenna 200 on their antenna characteristics.

Consequently, one wireless reader/writer 1000 can appropriately communicate with various wireless cards 2000.

5 Details of wireless card antenna position A, wireless card antenna position B, and wireless card antenna position C are as follows.

As a premise, the antenna planes of the wireless reader/writer antenna 100 and wireless card antenna 200 are parallel to each other.

10 Wireless card antenna position B: at this position, the center (barycenter) of the antenna plane of the wireless card antenna 200 is located on the perpendicular to an antenna plane passing through the center (barycenter) of the antenna plane of the
15 wireless reader/writer antenna 100.

Wireless card antenna position A: at this position, the wireless card 2000 slides parallel in a direction opposite to the card insertion direction from wireless card antenna position B. For example,
20 as shown in FIG. 6, the wireless card 2000 slides by a distance a from wireless card antenna position B.

Wireless card antenna position C: at this position, the wireless card 2000 slides parallel in the card insertion direction from wireless card antenna
25 position B. For example, as shown in FIG. 6, the wireless card 2000 slides by a distance c from wireless card antenna position B.

A process of changing the positional relationship between the wireless reader/writer antenna 100 and the wireless card antenna 200 according to the embodiment of the present invention will be explained with
5 reference to FIGS. 7 and 8. FIG. 7 is a flowchart showing the overall positional relationship change process. FIG. 8 is a flowchart showing a partial process in the positional relationship change process in FIG. 7.

10 A method of adjusting the positional relationship between the wireless reader/writer antenna 100 and the wireless card antenna 200 by adjusting the position of the wireless card 2000, i.e., that of the wireless card antenna 200 will be exemplified. However, the present
15 invention is not limited to this. For example, the positional relationship may be adjusted by adjusting the position of the wireless reader/writer antenna 100. The positional relationship may also be adjusted by adjusting the positions of the wireless reader/writer
20 antenna 100 and wireless card antenna 200.

As shown in FIG. 7, if the wireless card 2000 is inserted into the wireless reader/writer 1000, i.e., the wireless card conveyance/position adjustment unit 1400 receives the wireless card 2000 (YES in ST11),
25 the positional relationship between the wireless reader/writer antenna 100 and the wireless card antenna 200 is adjusted, as needed. A case (YES in ST12)

in which the flow does not advance to a positional relationship adjustment process based on communication log information will be explained first. The communication log information will be described later.

5 For example, the wireless card conveyance/position adjustment unit 1400 sets the wireless card 2000 at wireless card antenna position A (ST13). The wireless reader/writer antenna 100 transmits a transmission signal, and the control processor 1100 confirms
10 whether the wireless reader/writer 1000 can normally communicate with the wireless card 2000 set at wireless card antenna position A (ST14). If the wireless reader/writer 1000 and the wireless card 2000 set at wireless card antenna position A can normally
15 communicate with each other (YES in ST14), the control processor 1100 holds communication log information "communication is OK at wireless card antenna position A" (ST19). The wireless card conveyance/position adjustment unit 1400 discharges (returns) the received
20 wireless card 2000 (ST21).

 If the wireless reader/writer 1000 and the wireless card 2000 set at wireless card antenna position A cannot normally communicate with each other (NO in ST14), the wireless card conveyance/position
25 adjustment unit 1400 sets the wireless card 2000 at wireless card antenna position B (ST15). The wireless reader/writer antenna 100 transmits a transmission

signal, and the control processor 1100 confirms
whether the wireless reader/writer 1000 can normally
communicate with the wireless card 2000 set at wireless
card antenna position B (ST16). If the wireless
5 reader/writer 1000 and the wireless card 2000 set
at wireless card antenna position B can normally
communicate with each other (YES in ST16), the control
processor 1100 holds communication log information
"communication is OK at wireless card antenna position
10 B" (ST19). The wireless card conveyance/position
adjustment unit 1400 discharges (returns) the received
wireless card 2000 (ST21).

If the wireless reader/writer 1000 and the
wireless card 2000 set at wireless card antenna
15 position B cannot normally communicate with each other
(NO in ST16), the wireless card conveyance/position
adjustment unit 1400 sets the wireless card 2000 at
wireless card antenna position C (ST17). The wireless
reader/writer antenna 100 transmits a transmission
20 signal, and the control processor 1100 confirms
whether the wireless reader/writer 1000 can normally
communicate with the wireless card 2000 set at wireless
card antenna position C (ST18). If the wireless
reader/writer 1000 and the wireless card 2000 set
25 at wireless card antenna position C can normally
communicate with each other (YES in ST18), the control
processor 1100 holds communication log information

"communication is OK at wireless card antenna position C" (ST19). The wireless card conveyance/position adjustment unit 1400 discharges (returns) the received wireless card 2000 (ST21).

5 If the wireless reader/writer 1000 and the wireless card 2000 set at wireless card antenna position C cannot normally communicate with each other (NO in ST18), that is, if the wireless reader/writer 1000 and wireless card 2000 cannot normally communicate
10 with each other even by setting the wireless card 2000 at wireless card antenna position A, wireless card antenna position B, or wireless card antenna position C, a communication error occurs (ST20), and the wireless card conveyance/position adjustment unit
15 1400 discharges (returns) the received wireless card 2000 (ST21).

 As described above, even when the wireless reader/writer 1000 and wireless card 2000 cannot normally communicate with each other at a specific
20 wireless card antenna position, a communication error by the antenna characteristic can be solved by position adjustment to implement normal communication.

 The positional relationship adjustment process based on communication log information will be
25 explained with reference to the flowchart shown in FIG. 8. When the wireless reader/writer 1000 and wireless card 2000 normally communicate with each

other in previous communication, as shown in FIG. 7, their positional relationship and communication result are held as communication log information in ST19.

In subsequent communication, the communication log
5 information is utilized to efficiently select and set the wireless card antenna position. If the wireless reader/writer 1000 and wireless card 2000 normally communicate with each other at least once in previous communication, subsequent communication can use the
10 communication log information (YES in ST12). That is, the positional relationship adjustment process based on the communication log information can be executed (ST22).

For example, if the communication log information
15 represents that the position at which previous communication can be normally achieved is wireless card antenna position A (YES in ST2201), the wireless card conveyance/position adjustment unit 1400 preferentially (first) sets the wireless card 2000 at wireless card
20 antenna position A on the basis of the communication log information (ST2204). The wireless reader/writer antenna 100 transmits a transmission signal, and the control processor 1100 confirms whether the wireless reader/writer 1000 can normally communicate with
25 the wireless card 2000 set at wireless card antenna position A (ST2205). If the wireless reader/writer 1000 and the wireless card 2000 set at wireless card

antenna position A can normally communicate with each other (YES in ST2205), the control processor 1100 updates the communication log information (ST2216). That is, the control processor 1100 holds communication
5 log information "communication is OK at wireless card antenna position A". The wireless reader/writer 1000 often uses a wireless card 2000 manufactured by the same manufacturer as that of the wireless reader/writer 1000. Normal communication can be efficiently imple-
10 mented in the next communication by preferentially setting the position represented by the communication log information at which previous communication can be normally established.

If the wireless reader/writer 1000 and the wire-
15 less card 2000 set at wireless card antenna position A cannot normally communicate with each other (NO in ST2205), the wireless card conveyance/position adjustment unit 1400 sets the wireless card 2000 at wireless card antenna position B (ST2206). The
20 wireless reader/writer antenna 100 transmits a transmission signal, and the control processor 1100 confirms whether the wireless reader/writer 1000 can normally communicate with the wireless card 2000 set at wireless card antenna position B (ST2207). If the
25 wireless reader/writer 1000 and the wireless card 2000 set at wireless card antenna position B can normally communicate with each other (YES in ST2207), the

control processor 1100 updates the communication log information (ST2216). That is, the control processor 1100 holds communication log information "communication is OK at wireless card antenna position B".

5 If the wireless reader/writer 1000 and the wireless card 2000 set at wireless card antenna position B cannot normally communicate with each other (NO in ST2207), the wireless card conveyance/position adjustment unit 1400 sets the wireless card 2000
10 at wireless card antenna position C (ST2208). The wireless reader/writer antenna 100 transmits a transmission signal, and the control processor 1100 confirms whether the wireless reader/writer 1000 can normally communicate with the wireless card 2000 set at wireless
15 card antenna position C (ST2209). If the wireless reader/writer 1000 and the wireless card 2000 set at wireless card antenna position C can normally communicate with each other (YES in ST2209), the control processor 1100 updates the communication log
20 information (ST2216). That is, the control processor 1100 holds communication log information "communication is OK at wireless card antenna position C".

 If the wireless reader/writer 1000 and the wireless card 2000 set at wireless card antenna position C cannot normally communicate with each other (NO
25 in ST2209), that is, if the wireless reader/writer 1000 and wireless card 2000 cannot normally communicate with

each other even by setting the wireless card 2000 at wireless card antenna position A, wireless card antenna position B, or wireless card antenna position C (YES in ST2210), a communication error occurs (ST2217).

5 If the communication log information represents that the position at which previous communication can be normally achieved is wireless card antenna position B (YES in ST2202), the wireless card conveyance/
position adjustment unit 1400 preferentially (first)
10 sets the wireless card 2000 at wireless card antenna position B on the basis of the communication log information (ST2206). The wireless reader/writer antenna 100 transmits a transmission signal, and the control processor 1100 confirms whether the wireless
15 reader/writer 1000 can normally communicate with the wireless card 2000 set at wireless card antenna position B (ST2207). If the wireless reader/writer 1000 and the wireless card 2000 set at wireless card antenna position B can normally communicate with each
20 other (YES in ST2207), the control processor 1100 updates the communication log information (ST2216). That is, the control processor 1100 holds communication log information "communication is OK at wireless card antenna position B".

25 If the wireless reader/writer 1000 and the wireless card 2000 set at wireless card antenna position B cannot normally communicate with each other

(NO in ST2207), the wireless card conveyance/position adjustment unit 1400 sets the wireless card 2000 at wireless card antenna position C (ST2208). The wireless reader/writer antenna 100 transmits a
5 transmission signal, and the control processor 1100 confirms whether the wireless reader/writer 1000 can normally communicate with the wireless card 2000 set at wireless card antenna position C (ST2209). If the wireless reader/writer 1000 and the wireless card
10 2000 set at wireless card antenna position C can normally communicate with each other (YES in ST2209), the control processor 1100 updates the communication log information (ST2216). That is, the control processor 1100 holds communication log information
15 "communication is OK at wireless card antenna position C".

Even if the wireless reader/writer 1000 and the wireless card 2000 set at wireless card antenna position C cannot normally communicate with each other
20 (NO in ST2207), a communication error has not been confirmed at all wireless card antenna positions (NO in ST2210). Thus, the wireless card conveyance/position adjustment unit 1400 sets the wireless card 2000 at wireless card antenna position A (ST2211). The
25 wireless reader/writer antenna 100 transmits a transmission signal, and the control processor 1100 confirms whether the wireless reader/writer 1000 can

normally communicate with the wireless card 2000 set at wireless card antenna position A (ST2212). If the wireless reader/writer 1000 and the wireless card 2000 set at wireless card antenna position A can normally communicate with each other (YES in ST2212), the control processor 1100 updates the communication log information (ST2216). That is, the control processor 1100 holds communication log information "communication is OK at wireless card antenna position A".

If the wireless reader/writer 1000 and the wireless card 2000 set at wireless card antenna position A cannot normally communicate with each other (NO in ST2212), that is, if the wireless reader/writer 1000 and wireless card 2000 cannot normally communicate with each other even by setting the wireless card 2000 at wireless card antenna position B, wireless card antenna position C, or wireless card antenna position A (YES in ST2213), a communication error occurs (ST2217).

If the communication log information represents that the position at which previous communication can be normally achieved is wireless card antenna position C (YES in ST2203), the wireless card conveyance/position adjustment unit 1400 preferentially (first) sets the wireless card 2000 at wireless card antenna position C on the basis of the communication log information (ST2208). The wireless reader/writer antenna 100 transmits a transmission signal, and the

control processor 1100 confirms whether the wireless reader/writer 1000 can normally communicate with the wireless card 2000 set at wireless card antenna position C (ST2209). If the wireless reader/writer 5 1000 and the wireless card 2000 set at wireless card antenna position C can normally communicate with each other (YES in ST2209), the control processor 1100 updates the communication log information (ST2216). That is, the control processor 1100 holds communication 10 log information "communication is OK at wireless card antenna position C".

Even if the wireless reader/writer 1000 and the wireless card 2000 set at wireless card antenna position C cannot normally communicate with each other 15 (NO in ST2209), a communication error has not been confirmed at all wireless card antenna positions (NO in ST2210). Thus, the wireless card conveyance/position adjustment unit 1400 sets the wireless card 2000 at wireless card antenna position A (ST2211). The 20 wireless reader/writer antenna 100 transmits a transmission signal, and the control processor 1100 confirms whether the wireless reader/writer 1000 can normally communicate with the wireless card 2000 set at wireless card antenna position A (ST2212). If the 25 wireless reader/writer 1000 and the wireless card 2000 set at wireless card antenna position A can normally communicate with each other (YES in ST2212), the

control processor 1100 updates the communication log information (ST2216). That is, the control processor 1100 holds communication log information "communication is OK at wireless card antenna position A".

5 Even if the wireless reader/writer 1000 and the wireless card 2000 set at wireless card antenna position A cannot normally communicate with each other (NO in ST2212), a communication error has not been confirmed at all wireless card antenna positions (NO in
10 ST2213). Thus, the wireless card conveyance/position adjustment unit 1400 sets the wireless card 2000 at wireless card antenna position B (ST2214). The wireless reader/writer antenna 100 transmits a transmission signal, and the control processor 1100 confirms
15 whether the wireless reader/writer 1000 can normally communicate with the wireless card 2000 set at wireless card antenna position B (ST2215). If the wireless reader/writer 1000 and the wireless card 2000 set at wireless card antenna position B can normally
20 communicate with each other (YES in ST2215), the control processor 1100 updates the communication log information (ST2216). That is, the control processor 1100 holds communication log information "communication is OK at wireless card antenna position B".

25 If the wireless reader/writer 1000 and the wireless card 2000 set at wireless card antenna position B cannot normally communicate with each other (NO

in ST2215), that is, if the wireless reader/writer 1000 and wireless card 2000 cannot normally communicate with each other even by setting the wireless card 2000 at wireless card antenna position C, wireless card antenna position A, or wireless card antenna position B (YES in
5 ST2215), a communication error occurs (ST2217).

Adjustment of the antenna positional relationship in the vertical direction by the wireless communication device (wireless reader/writer 1000) and wireless
10 communication method of the present invention will be explained. Adjustment in the parallel direction has been described, and adjustment in the vertical direction (to be described below) can also be applied to the present invention.

15 For example, as shown in FIG. 9, the wireless card conveyance/position adjustment unit 1400 can receive the wireless card 2000 and convey the received wireless card 2000 to wireless card antenna position D, wireless card antenna position E, and wireless card antenna
20 position F. In other words, the wireless card conveyance/position adjustment unit 1400 can change the positional relationship between the wireless reader/writer antenna 100 and the wireless card antenna 200, as needed. This can reduce the influence of cross
25 coupling between the wireless reader/writer antenna 100 and the wireless card antenna 200 on their antenna characteristics. As a result, one wireless

reader/writer 1000 can appropriately communicate with various wireless cards 2000.

Details of wireless card antenna position D, wireless card antenna position E, and wireless card antenna position F are as follows.

As a premise, the antenna planes of the wireless reader/writer antenna 100 and wireless card antenna 200 are parallel to each other.

Wireless card antenna position E: at this position, the center (barycenter) of the antenna plane of the wireless card antenna 200 is located on the perpendicular to an antenna plane passing through the center (barycenter) of the antenna plane of the wireless reader/writer antenna 100. The distance between the centers of the two antenna planes is a distance e .

Wireless card antenna position D: at this position, the center (barycenter) of the antenna plane of the wireless card antenna 200 is located on the perpendicular to an antenna plane passing through the center (barycenter) of the antenna plane of the wireless reader/writer antenna 100. The distance between the centers of the two antenna planes is a distance d (distance $d < \text{distance } e$).

Wireless card antenna position F: at this position, the center (barycenter) of the antenna plane of the wireless card antenna 200 is located on the

perpendicular to an antenna plane passing through
the center (barycenter) of the antenna plane of the
wireless reader/writer antenna 100. The distance
between the centers of the two antenna planes is a
5 distance $\underline{f}$ (distance $f > \text{distance } e$).

When $d < e < f$, the wireless reader/writer antenna
100 may be greatly influenced by the antenna charac-
teristic from the wireless card antenna 200 in the
order of $d > e > f$.

10 The present invention can adopt a combination
of the above-mentioned adjustment in the parallel
direction and adjustment in the vertical direction.
Also in this case, the influence of cross coupling
between the wireless reader/writer antenna 100 and
15 the wireless card antenna 200 on their antenna
characteristics can be reduced. One wireless
reader/writer 1000 can properly communicate with
various wireless cards 2000.

In the above description, the positional
20 relationship between the wireless reader/writer antenna
100 and the wireless card antenna 200 is changed by
changing the position of the wireless card 2000, i.e.,
that of the wireless card antenna 200. However, the
present invention is not limited to this. For example,
25 the position of the wireless card 2000 may be fixed,
and only that of the wireless reader/writer antenna
100 may be changed. Alternatively, the positions of

both the wireless card 2000 and wireless reader/writer antenna 100 may be changed.

As has been described above, the wireless communication device (wireless reader/writer 1000) and
5 wireless communication method of the present invention can set a plurality of types of antenna positional relationships. The probability of communication errors can be decreased for various types of wireless cards, and the wireless communication device can appropriately
10 communicate with various types of wireless cards. By utilizing communication log information, the process time can be shortened in an environment where many identical wireless cards are available.

The present invention can provide a wireless
15 communication device and wireless communication method capable of solving a communication error caused by the antenna characteristic and realizing a normal communication environment.

Additional advantages and modifications will
20 readily occur to those skilled in the art. Therefore, the invention in its broader aspects is not limited to the specific details and representative embodiments shown and described herein. Accordingly, various modifications may be made without departing from the
25 spirit or scope of the general inventive concept as defined by the appended claims and their equivalents.

WHAT IS CLAIMED IS:

1. A wireless communication device comprising:
a main body antenna to communicate with an antenna
of a wireless card;

5 antenna position setting means capable of setting
a plurality of types of positional relationships
between the antenna of the wireless card and the main
body antenna;

communication means for performing communication
10 between the antenna of the wireless card and the
main body antenna which are set to a predetermined
positional relationship by the antenna position setting
means; and

positional relationship control means for
15 controlling setting of the positional relationship
between the antenna of the wireless card and the main
body antenna by the antenna position setting means,
as needed on the basis of a communication state by the
communication means.

20 2. A device according to claim 1, wherein while
maintaining a plane of the antenna of the wireless card
and a plane of the main body antenna parallel to each
other, the antenna position setting means can set the
plurality of types of the positional relationships
25 between the antenna of the wireless card and the main
body antenna.

3. A device according to claim 1, wherein while

maintaining a plane of the antenna of the wireless card
and a plane of the main body antenna parallel to each
other, the antenna position setting means can set the
plurality of types of the positional relationships
5 between the antenna of the wireless card and the main
body antenna in a direction parallel to the plane of
the antenna of the wireless card and the plane of the
main body antenna.

4. A device according to claim 1, wherein while
10 maintaining a plane of the antenna of the wireless card
and a plane of the main body antenna parallel to each
other, the antenna position setting means can set the
plurality of types of the positional relationships
between the antenna of the wireless card and the main
15 body antenna in a direction perpendicular to the plane
of the antenna of the wireless card and the plane of
the main body antenna.

5. A device according to claim 1, wherein the
positional relationship control means stores as
20 communication log information a communication result
of the antenna of the wireless card and the main body
antenna and the positional relationship between the
antenna of the wireless card and the main body antenna
in a first communication process, and controls initial
25 setting of the positional relationship between the
antenna of the wireless card and the main body antenna
on the basis of the communication log information in a

second communication process subsequent to the first communication process.

6. A wireless communication method comprising:

performing communication between an antenna of a wireless card and a main body antenna which are set to a predetermined positional relationship;

changing the positional relationship between the antenna of the wireless card and the main body antenna, as needed on the basis of a communication state between the antenna of the wireless card and the main body antenna which are set to the predetermined positional relationship; and

performing communication between the antenna of the wireless card and the main body antenna which are set to the changed positional relationship.

7. A method according to claim 6, wherein while a plane of the antenna of the wireless card and a plane of the main body antenna are maintained parallel to each other, the positional relationship between the antenna of the wireless card and the main body antenna is changed.

8. A method according to claim 6, wherein while a plane of the antenna of the wireless card and a plane of the main body antenna are maintained parallel to each other, the positional relationship between the antenna of the wireless card and the main body antenna is changed in a direction parallel to the plane of the

antenna of the wireless card and the plane of the main body antenna.

5 9. A method according to claim 6, wherein while a plane of the antenna of the wireless card and a plane of the main body antenna are maintained parallel to each other, the positional relationship between the antenna of the wireless card and the main body antenna is changed in a direction perpendicular to the plane of the antenna of the wireless card and the plane of the main body antenna.

10

15 10. A method according to claim 6, wherein a communication result of the antenna of the wireless card and the main body antenna and the positional relationship between the antenna of the wireless card and the main body antenna are stored as communication log information in a first communication process, and initial setting of the positional relationship between the antenna of the wireless card and the main body antenna is controlled on the basis of the communication log information in a second communication process subsequent to the first communication process.

20