

Apparatus for the correction of temperature drift for a pressure sensor, a pressure control apparatus, and a pressure-type flow rate control apparatus

Background of the invention

5

Field of the invention

The present invention relates to a pressure sensor, a pressure control apparatus and a pressure-type flow rate control apparatus for use mainly in semiconductor manufacturing facilities, chemical plants, etc. More particularly, the present invention concerns apparatus for correcting temperature drift – for use in a pressure sensor, a pressure control apparatus, and a pressure-type flow rate control apparatus – which accurately detects the pressure of a fluid by automatically negating or correcting a temperature drift, thus controlling the pressure and flow rate of fluid, where the output of a pressure sensor for measuring the pressure of the fluid drifts as a result of a temperature change.

Description of the prior art

In semiconductor manufacturing facilities, chemical plants, etc., a plurality of gases as materials are commonly supplied at specific flow rates, and are reacted in a reaction vessel to produce an object or target gas. In this process, if the material gases are not supplied accurately, then the chemical reaction proceeds unevenly, and it can occur that material gases remain unreacted in the produced object gas. Especially, where the material gases are flammable, there is a danger of gas explosions. In order for the material gases to react in a well-balanced manner, it is necessary to control accurately the flow rates of the gases to be supplied.

Hitherto, the flow rates of gases have been controlled through the use of the following arrangements: an orifice is mounted in a pipe, a theoretical flow rate formula is selected that can indicate as accurately as possible the flow rate of a gas passing through said orifice, and the flow rate of the gas passing through the orifice is calculated using the flow rate formula. In the flow rate formula that has been used hitherto, the fluid is assumed to be incompressible, and the flow rate Q_c is expressed as:

$$Q_c = KP_2^{1/2} (P_1 - P_2)^{1/2}$$

where P_1 is the pressure on an upstream side of the orifice,

P_2 is the pressure on a downstream side of the orifice, and

K is a proportional constant which depends on the fluid temperature.

In the flow rate formula, the flow rate is calculated from two pressure parameters P_1 and P_2 . However, since the actual gas flow comprises a compressible fluid, the above theoretical flow rate formula is not very precise. On the other hand, if the ratio P_2/P_1 of above-mentioned pressures is reduced below a critical value of about 0.5, then the flow velocity of the gas passing through the orifice reaches sonic velocity, and it is known that under sonic velocity conditions, the theoretical formula is:

$$Q_c = KP_1$$

It is known that as long as critical conditions are satisfied, the flow rate simply depends only on the upstream side pressure P_1 , and yields accurately the rate of a compressible fluid passing through the orifice.

For approximate flow rate control of an incompressible fluid, therefore, the theoretical flow rate formula:

$$Q_c = KP_2^{1/2} (P_1 - P_2)^{1/2}$$

is used. Under critical conditions ($P_2 / P_1 < \text{about } 0.5$), the theoretical flow rate formula:

$$Q_c = KP_1$$

is predominantly used for controlling the flow-rate of a fluid. Where either of these flow rate formulae is used, the measurement of the fluid pressures, P_1 and/or P_2 , is a prerequisite. That is, in the case of former, the simultaneous measurement of P_1 and P_2 is necessary, and in the latter case the measurement of the upstream side pressure P_1 is required.

In order to measure fluid pressure, it is necessary to install a pressure sensor in the fluid. The pressure sensor therefore becomes very sensitive to the fluid temperature, and the sensor temperature immediately becomes equal to the fluid temperature T . In other words, equilibrium between the fluid temperature T and the temperature of the sensor is immediately established. In order to measure the fluid pressure accurately, it is necessary to reduce the size of the pressure sensor to such an extent that the flow of the fluid is undisturbed. Accordingly, it will be appreciated that equilibrium is reached very quickly.

On the other hand, the gaseous fluid flowing through the pipe is controlled so that the fluid flows as far as possible at a constant temperature. However, it is known that over a period of many hours, the temperature of a flow of gas fluctuates considerably. Furthermore, when a gas fluid is replaced by another gas, it can happen that an high temperature gas flows for a certain period of time, whilst a low temperature gas flows for

another period of time. Accordingly, if a fluid of fluctuating temperature is measured using the same pressure sensor, then the temperature drift characteristics of the pressure sensor output present a problem such that the detected pressure of the fluid needs to be corrected.

5 Prior art pressure sensors invariably display a temperature drift, irrespective of the method of pressure detection. "Temperature drift" means that when the ambient temperature around the pressure sensor changes, the output of the pressure sensor changes under constant pressure. It is found that this output drift correlates to the fluid temperature.

10 Some pressure sensors have a built-in temperature compensation circuit, but even here, if the temperature drift is $0.05\%/^{\circ}\text{C}$, for example, then an output drift of 4% will occur when the temperature changes from 20 to 100°C .

15 Pressure sensors are available in various different types. Consider a strain gauge for example: A strain gauge converts pressure into a voltage such that with pressure plotted on an abscissa axis, the ordinate axis corresponds to output voltage. Of course, if the absolute pressure is zero, then the output voltage will be zero, and it is expected that with an increase in absolute pressure, the output voltage will rise.

20 The sensor output recorded when zero pressure is applied to the pressure sensor is called the "zero-point output". The temperature drift of the zero-point output, which is the fluctuation in the zero-point output occurring in accordance with temperature change, is called the "zero-point pressure drift". On the other hand, the temperature drift of the sensor output observed when pressure is applied is called the "span output drift". In order to obtain an accurate sensor output, it is necessary to adjust for both zero-point output drift and span output drift.

25 More specifically, assume that the pressure sensor has no zero-point output drift, and that its zero-point voltage is 0 (V). Also assume that when the absolute pressure of the fluid is $1.0 (\times 10^2 \text{ kPaA})$, i.e. 1 atm, the output voltage is 20 mV. When the fluid temperature changes under these conditions, the output voltage naturally deviates from 20 mV. This fluctuation is the above-mentioned span output drift. In practice, since some zero-point output is always present, the span output drift at any arbitrary pressure is displaced by the zero-point voltage.

30 As described above, in a pressure-type flow rate control apparatus that controls a fluid passing through an orifice by measuring an upstream side pressure P_1 or a downstream side pressure P_2 , temperature fluctuation characteristics called the zero-point output drift and the span output drift are included in the output voltage of the pressure

sensor. If the output voltage is converted directly into a voltage, therefore, the pressures P_1 , P_2 will contain errors. If the flow rate is calculated in accordance with the aforesaid flow rate formula, then those errors will be introduced into the calculated flow rate, Q_c . This is the problem of temperature drift in pressure-type flow rate control apparatus.

- 5 The zero point and span temperature drift characteristics of a pressure sensor are different as between different pressure sensors. It is desirable to obtain an accurate sensor output by providing a method of correcting the temperature drift.

Summary of the Invention

- 10 In accordance with the invention, there is provided an apparatus for correcting temperature drift for use in a pressure sensor for measuring the pressure of a fluid, said apparatus comprising a temperature sensor for measuring the temperature of the fluid, a memory means for storing a relation between the fluid temperature and an output drift of the pressure sensor, and a temperature drift correcting means for calculating the amount of the output drift of the pressure sensor from data in the memory means when the fluid
- 15 temperature changes, and negating said output drift of the pressure sensor with said calculated amount of the output drift, thereby correcting the temperature drift, such that even if the temperature of fluid changes, the fluid pressure can be measured accurately, wherein said memory means stores a relation between the fluid temperature and a zero-point output drift of the pressure sensor at zero pressure, and the temperature drift
- 20 correcting means calculates the amount of the zero-point output drift when the fluid temperature changes and negatives the zero-point output drift of the pressure sensor with the calculated amount of the zero-point output drift, thereby correcting the temperature drift, and wherein the memory means stores a relation between the temperature of the fluid and a span output drift of the pressure sensor under any arbitrary pressure, and the amount
- 25 of the span output drift is calculated from the memory means when the temperature of fluid changes, and the calculated amount of the span output drift is added to or subtracted from the output of the pressure sensor, thereby correcting the temperature drift.

- 30 In another aspect, there is provided an apparatus for correcting temperature drift for use in a pressure control apparatus comprising a control valve for pressure control and a pressure sensor for measuring the pressure of a fluid, the apparatus for correcting temperature drift comprising a memory means for storing a relation between the fluid

temperature and an output drift of the pressure sensor, and a temperature drift correcting means which calculates the amount of the output drift of the pressure sensor from data in the memory means when the fluid temperature changes, and negatives the output drift of the pressure sensor with the calculated amount of the output drift, thereby correcting the temperature drift, such that even if the fluid temperature changes, the pressure of fluid is accurately controlled, wherein said memory means stores a relation between the fluid temperature and a zero-point output drift of the pressure sensor at zero pressure, and the temperature drift correcting means calculates the amount of the zero-point output drift when the fluid temperature changes and negatives the zero-point output drift of the pressure sensor with the calculated amount of the zero-point output drift, thereby correcting the temperature drift, and wherein the memory means stores a relation between the temperature of the fluid and a span output drift of the pressure sensor under any arbitrary pressure, and the amount of the span output drift is calculated from the memory means when the temperature of fluid changes, and the calculated amount of the span output drift is added to or subtracted from the output of the pressure sensor, thereby correcting the temperature drift.

In another aspect, there is provided an apparatus for correcting temperature drift for use in a pressure-type flow rate control apparatus comprising an orifice for flow rate control, a control valve provided in a pipe on an upstream side of the orifice, and an upstream side pressure sensor provided between said orifice and the control valve for detecting an upstream side pressure P_1 , such that the flow rate of a fluid passing through the orifice can be controlled on the basis of the upstream side pressure P_1 , the apparatus for correcting temperature drift comprising a temperature sensor for measuring the temperature of the fluid, a memory means for storing a relation between the temperature of the fluid and an output drift of the upstream side pressure sensor, and a temperature drift correcting means which calculates the amount of the output drift of the upstream side sensor from data in the memory means when the temperature of fluid changes, and offsets the output drift of the upstream side pressure sensor with the calculated amount of the output drift, thereby correcting the temperature drift, such that even if the temperature of fluid fluctuates, the flow rate of fluid can be accurately controlled, wherein said memory means stores a relation between the fluid temperature and a zero-point output drift of the

pressure sensor at zero pressure, and the temperature drift correcting means calculates the amount of the zero-point output drift when the fluid temperature changes and negatives the zero-point output drift of the pressure sensor with the calculated amount of the zero-point output drift, thereby correcting the temperature drift, and wherein the memory means
5 stores a relation between the temperature of the fluid and a span output drift of the pressure sensor under any arbitrary pressure, and the amount of the span output drift is calculated from the memory means when the temperature of fluid changes, and the calculated amount of the span output drift is added to or subtracted from the output of the pressure sensor, thereby correcting the temperature drift.

10 In another aspect, there is provided an apparatus for correcting temperature drift for use in a pressure-type flow rate control apparatus comprising an orifice for flow rate control, a control valve provided in a pipe on an upstream side of the orifice, an upstream side pressure sensor provided between the orifice and the control valve for detecting an upstream side pressure P_1 , and a downstream side pressure sensor provided in a pipe on a
15 downstream side of the orifice for detecting a downstream side pressure P_2 such that the flow rate of a fluid passing through the orifice can be controlled on the basis of the upstream side pressure P_1 and the downstream side pressure P_2 , the apparatus for correcting temperature drift comprising a temperature sensor for measuring the temperature of the fluid, a memory means for storing a relation between the temperature of
20 the fluid and output drifts of the upstream side pressure sensor and downstream side pressure sensor, and a temperature drift correcting means which calculates the amounts of the output drifts of the upstream side pressure sensor and downstream side pressure sensor from data in the memory means when the fluid temperature changes, and offsets the output drifts of the upstream side pressure sensor and downstream side pressure sensor with the
25 calculated output drift amounts, thereby correcting the temperature drifts, such that even if the fluid temperature changes, the flow rate of fluid is accurately controlled, wherein said memory means stores a relation between the fluid temperature and a zero-point output drift of the pressure sensor at zero pressure, and the temperature drift correcting means calculates the amount of the zero-point output drift when the fluid temperature changes and
30 negatives the zero-point output drift of the pressure sensor with the calculated amount of the zero-point output drift, thereby correcting the temperature drift, and wherein the

memory means stores a relation between the temperature of the fluid and a span output drift of the pressure sensor under any arbitrary pressure, and the amount of the span output drift is calculated from the memory means when the temperature of fluid changes, and the calculated amount of the span output drift is added to or subtracted from the output of the pressure sensor, thereby correcting the temperature drift.

Preferably, the above described apparatus is for use in a gas supply system, in which gas is caused to flow as a fluid, for controlling the gas pressure and the gas flow rate.

Brief Description of the Drawings

FIG. 1 is a schematic diagram of flow rate control using a pressure-type flow rate control apparatus which operates under critical conditions.

FIG. 2 is a simplified block circuit diagram for the correction of zero-point output drift in a pressure-type flow rate control apparatus.

FIG. 3 is an explanatory diagram of the correction of zero-point output drift and normalisation.

FIG. 4 is an explanatory diagram of a method for measuring the output drift of a pressure sensor.

FIG. 5 is a diagram of the zero-point output drift (ZERO DRIFT) temperature characteristics of a pressure sensor.

FIG. 6 is a diagram of the output drift (SPAN DRIFT) temperature characteristics of a pressure sensor.

FIG. 7 is a detailed schematic block diagram of a control circuit for a pressure-type flow rate control apparatus.

FIG. 8 is a flow chart of a zero-point output correcting means 62.

FIG. 9 is a flow diagram of the operation of a span correcting means 66.

FIG. 10 is a schematic diagram of fluid control using a pressure-type flow rate control apparatus which operates under non-critical conditions.

FIG. 11 is a detailed schematic block diagram of the control circuit of FIG. 10.

FIG. 12 is a schematic diagram of flow rate control using an improved pressure-type flow rate control apparatus which operates under non-critical conditions.

Reference Numbers

- 2: improved pressure-type flow rate control apparatus;
- 4: orifice;
- 4a: orifice hole;
- 5 6: upstream side pipe;
- 8: downstream side pipe;
- 10: upstream side pressure sensor;
- 12: downstream side pressure sensor;
- 14: temperature sensor;
- 10 16: control circuit;
- 17: flow rate calculating means;
- 18: flow rate setting means;
- 19: comparison circuit;
- 20: valve drive apparatus;
- 15 22: control valve;
- 24: gas tank;
- 26: regulator;
- 27: supply side pipe;
- 28: valve;
- 20 29: control side pipe;
- 30: valve;
- 32: chamber;

	34: vacuum pump;
	40: offset D/A converter;
	40a: D/A converter for rough adjustment;
	40b: D/A converter for fine adjustment;
5	40c: buffer;
	40d: buffer;
	40e: buffer;
	41: CPU;
	42: fixed amplifier;
10	42a: offset terminal;
	44: variable amplifier;
	46: variable amplifier;
	48: A/D converter;
	50: constant temperature bath;
15	52: reference pressure generator;
	56: fixed amplifier;
	58: A/D converter;
	60: temperature drift correcting means;
	62: zero point correcting means;
20	64: memory means;
	66: span correcting means;
	68: gas temperature correcting means;
	72: A/D converter;
	74: fixed amplifier;
25	76: fixed amplifier;
	78: A/D converter;
	DP: vacuum pump;
	P ₁ : upstream side pressure;
	P ₂ : downstream side pressure;
30	Q _c : calculated flow rate;
	Q _s : set flow rate;
	ΔQ : flow rate difference;
	v ₀ : zero point drift voltage;

v: output voltage;

V: pressure voltage

Description of the preferred embodiments

By analysing the zero-point output drift and span output drift of a pressure sensor
5 caused by a temperature change, the inventors have succeeded in developing a method of
correcting the temperature drift, not only for the pressure sensor, but also for a pressure
control apparatus, and a pressure-type flow rate control apparatus in which the pressure
sensor is used.

Embodiments of the apparatus for correcting temperature drift for a pressure-type
10 flow rate control apparatus according to the present invention will be described below with
reference to the drawings.

FIG. 1 is a schematic diagram of flow rate control using a pressure-type flow rate
control apparatus which operates under critical
conditions. In said pressure-type flow rate control apparatus 2, it is a prerequisite that a
15 fluid to be supplied is under critical conditions, i.e. that the velocity of the fluid flowing
out of an orifice 4 is at sonic velocity. The flow rate can therefore be expressed as :

$$Q = KP_1.$$

Pressure is measured only by an upstream side pressure sensor 10.

Said pressure-type flow rate control apparatus 2 comprises said orifice 4 having an
20 orifice hole 4a, an upstream side pipe 6, a downstream side pipe 8, an upstream side
pressure sensor 10, a temperature sensor 14, a control circuit 16, a valve drive unit 20, and
a control valve 22.

The control circuit 16 comprises an electronic circuit, a microcomputer, and a built-
in programme, as its principal components. However, said control circuit 16 may comprise
25 an electronic circuit alone, or an electronic circuit and a personal computer. Said control
circuit 16 comprises an electronic circuit system, such as an amplification circuit and an
A/D converter (not shown), a flow rate calculating means 17 for calculating a flow rate Q_c
using an empirical flow rate formula, a flow rate setting means 18 for transmitting a set
flow rate Q_s for the fluid, and a comparison means 19 for determining $\Delta Q (= Q_s - Q_c)$, the
30 difference between the calculated flow rate Q_c and the set flow rate Q_s . The flow rate
difference ΔQ may be calculated as $Q_c - Q_s$.

On the upstream side of said improved pressure-type flow rate control apparatus 2,
the following components are connected: a gas tank 24 containing an high pressure gas, a

regulator 26 for regulating properly the pressure of the gas in the high-pressure gas tank, and a valve 28 for leading said gas from a supply side pipe 27 to said control valve 22.

Further, on the downstream side of the improved pressure-type flow rate control apparatus 2, the following components are connected: a control side pipe 29 for flowing
5 gas at said regulated flow rate, a valve 30 for feeding said gas to a chamber 32, and a vacuum pump 34. The chamber 32 is a reaction chamber for producing a target gas from supplied material gases. For example, material gases H_2 and O_2 form H_2O moisture gas in the reaction chamber.

Next, the control operation of the improved pressure-type flow rate control
10 apparatus 2 will be explained. On the upstream side, a gas under specific pressure is supplied to the supply side pipe 27. Further, the rate of gas flow to the upstream side pipe 6 is controlled by the control valve 22, whose opening is regulated by said valve drive unit 20. At the same time, on the downstream side, the downstream side pipe 8 is maintained at a set low pressure by the dry pump 34.

By means of evacuation by the vacuum pump 34, the downstream side pressure P_2
15 within said downstream side pipe 8 is held substantially lower than the upstream side pressure P_1 , and is automatically set such that critical conditions, i.e. $P_2/P_1 < \text{about } 0.5$, always apply. For this reason, the velocity of the gas flowing out of the orifice hole 4a is sonic velocity. The flow rate Q of the gas passing through the orifice 4 can therefore be
20 calculated by $Q = KP_1$.

The upstream side pressure P_1 is measured using the pressure sensor 10. To
measure the pressure accurately, the upstream side pressure sensor 10 is installed with its sensor part in contact with the gas flow. The sensor part is designed to be dimensionally
very small so as not to disturb the gas flow. The temperature of the sensor part is therefore
25 almost equal to the gas temperature T .

Furthermore, the gas temperature T is measured by the temperature sensor 14. Said
temperature sensor 14 measures the temperature near the orifice 4, so that the gas flow is
not disturbed, and if the gas and the orifice are in thermal equilibrium, then the two are
identical in temperature. The orifice temperature can therefore be measured as the gas
30 temperature.

The upstream side pressure P_1 and the gas temperature T are obtained as voltages
and converted into digital signals by an amplification circuit or an A/D converter (not
shown). Said digital signals are inputted to the flow rate calculating means 17, and the

proportional coefficient K is calculated from the gas temperature T and the physical properties of the gas. Furthermore, by using the upstream side pressure P_1 , the calculated flow rate Q_c can be determined by $Q_c = KP_1$

5 The set flow rate Q_s is inputted from the flow rate setting means 18, and the flow rate difference ΔQ is calculated as $\Delta Q = Q_s - Q_c$ by said comparison means 19. In order to calculate said flow rate difference ΔQ , the formula $\Delta Q = Q_c - Q_s$ may be used.

Said flow rate difference ΔQ is outputted to the valve drive unit 20, and the opening of the control valve 22 is controlled so as to reduce ΔQ to zero. By means of this opening adjustment, the upstream side pressure P_1 of the gas is adjusted so that the
10 calculated flow rate Q_c obtained from $Q_c = KP_1$ is equal to the set flow rate.

As mentioned above, the temperature of the sensor part of the pressure sensor 10 is equal to the gas temperature T , and if the gas temperature T changes, then the temperature of the sensor changes correspondingly. However, the pressure sensor is temperature dependent, and the output voltage of the pressure sensor drifts as the temperature
15 changes. The correction of this output drift will now be described.

FIG. 2 is a simplified block circuit diagram for the correction of zero-point output drift in the pressure-type flow rate control apparatus. The output voltage v of the pressure sensor 10 is amplified up to the pressure voltage V by a fixed amplifier 42 and a variable amplifier 44. The pressure voltage V is inputted to a CPU 41 via an A/D converter 48.
20 Furthermore, the output of the fixed amplifier 42 is also outputted to another variable amplifier 46, and the output of said other variable amplifier 46 also gives the pressure voltage V , and is displayed as the upstream side pressure P_1 on a display panel.

Assume, by way of example, that the upstream side pressure sensor 10 used in this embodiment outputs 100 mV when it detects an absolute pressure $P_1 = 7$ atm, i.e. $7 (\times 10^2$ kPaA). If the upstream side pressure P_1 is controlled in the range $P_1 = 0 \sim 3 (\times 10^2$ kPaA)
25 using said sensor 10, then the output voltage v of the upstream side pressure sensor 10 will be in the range $v = 0 \sim 42.86$ mV.

If the maximum voltage 42.86 mV of said output voltage v is normalised to a peak value of 5V, then the amplification is 117 times. The amplification of 117 times is
30 achieved in the present embodiment by an amplification of 100 times using the fixed amplifier 42 and an amplification of 1.17 times using the variable amplifiers 44 and 46.

However, the output of the pressure sensor 10 drifts as the temperature changes. The output drift displayed when the pressure is zero will be called the “zero-point output drift”, and the drift under any arbitrary pressure will be called the “output drift”.

5 The zero-point output drift is corrected by adjusting an input voltage to an offset terminal 42a of the fixed amplifier 42.

Specifically, correction of the above-mentioned zero-point output drift is effected by an offset D/A converter 40. That is, when, with the pressure at zero, the output voltage v has a certain value v_0 , $-v_0$ is applied to the offset terminal 42a to reduce said zero-point output drift voltage v_0 to zero. As a result, even if a pressure v_0 is inputted to the fixed
10 amplifier 42 when the pressure is zero, the effective input voltage is $v_0 + (-v_0) = 0$, and the zero-point output drift is corrected.

The offset D/A converter 40 comprises a D/A converter 40a for rough adjustment (ROUGH) having a buffer 40c, a D/A converter 40b for fine adjustment (FINE) having a buffer 40d, and a summing buffer 40e. As already described, an inverted zero-point
15 correction voltage $-v_0$ of the zero point drift voltage v_0 is applied to the offset terminal 42a by the circuits for rough adjustment and fine adjustment to cancel out the zero-point output drift voltage v_0 , thereby correcting the zero-point output drift.

FIG. 3 is an explanatory diagram of zero-point drift correction and normalisation. The abscissa axis plots the upstream side pressure P_1 , while the ordinate axis plots the
20 output voltage v and pressure voltage V . Assume that the pressure range is $P_1 = 0 \sim P_{1m}$, and the maximum pressure is $P_{1m} = 3.0 (\times 10^2 \text{ kPaA})$. Assume that when the gas temperature T is T_0 , the zero-point output drift is $v_0 = -2.0 \text{ mV}$. Assume that at the maximum pressure P_{1m} , the sensor maximum output is $v_1 = 40.8 \text{ mV}$.

The fine dotted line between v_0 and v_1 shows the temperature characteristics of the
25 pressure sensor 10. If $-v_0$ is applied to the offset terminal 42a, then $v_0 + (-v_0) = 0$, i.e. v_0 is negatived and corrected to 0 mV , which is shown as “Zero-Adj”. As a result, at the maximum pressure P_{1m} too, $v_1 + (-v_0) = 40.8 + 2.0 = 42.8 \text{ mV}$. The output of pressure sensor 10 is therefore corrected to $0 \sim 42.8 \text{ mV}$ by correcting the zero-point output drift. This correction is shown as the thick broken line.

30 Next, normalisation of the pressure sensor 10 is carried out. When the output of the pressure sensor is $0 \sim v_1 + (-v_0)$ after Zero-Adj, that is $0 \sim 42.8 \text{ mV}$, it is normalised to a peak value of 5 V . In other words, to amplify 42.8 mV to 5 V , the amplification provided

by the variable amplifiers 44, 46 will be 1.17. As a result, the two-stage amplification is set at $M = 100 \times 1.17 = 117$. This correction is shown as "Span-Adj".

The maximum voltage V_m is therefore given as $V_m = M (v_1 - v_0)$. The output v of the pressure sensor 10 under an arbitrary pressure P_1 is amplified to $V = M (v - v_0)$. Said amplified output V is indicated by the thick solid line. Under critical conditions, this thick solid line indicates $V = a (T_0)P_1$. The proportional constant $a (T_0)$ represents a proportional constant when the gas temperature T is T_0 .

FIG. 4 is an explanatory diagram of a method of measuring the output drift of a pressure sensor. The pressure sensor 10, as incorporated in a pressure-type flow rate control apparatus, is mounted in a constant temperature bath 50. A vacuum pump DP and a reference pressure generator 52 disposed outside the constant temperature bath 50 are connected to the pressure-type flow rate control apparatus by a pipe.

The pressure within the pipe is held at zero (vacuum), i.e. $P_1 = 0$ ($\times 10^2$ kPaA), by the vacuum pump DP, and the zero-point output drift voltage v_0 of the pressure sensor 10 is measured as the temperature is changed. Furthermore, by switching over the valves, the pressure P_1 of the reference pressure generator 52 is set at a specific pressure, and while the temperature is changed, the output voltage v of pressure sensor 10 is measured.

FIG. 5 is one example of a temperature characteristics diagram of the zero-point output drift (ZERO DRIFT) of a pressure sensor. The abscissa axis represents gas temperature T , whilst the ordinate axis represents the relative ratio $k (T)$ of the zero-point output drift voltage v_0 . The thin dotted line at 0% indicates an ideal line without drift, whilst the thin solid, polygonal line indicates an actual, measured zero-point output drift. This drift is zero at 60°C and about 2.0% at 85°C. Said relative ratio $k (T)$ is converted into the zero-point output drift voltage v_0 and applied to the above-mentioned offset terminal 42a.

FIG. 6 is a temperature characteristics diagram of the output drift (SPAN DRIFT) of a pressure sensor. The abscissa axis represents the gas temperature T , whilst the ordinate axis indicates the relative ratio $\Delta (T)$ of span output drift voltage v at a given pressure. The output drift was measured at three different pressures, 1.5, 2.0, 3.0 ($\times 10^2$ kPaA), and it was found that as the pressure changes, the output drift changes slightly. At a low temperature, such, for example, as not higher than 60°C, it was found that the difference in pressure can be ignored. Correction can therefore be made using the average drift, assuming that the output drift is constant at all arbitrary pressures.

FIG. 7 is a detailed schematic block diagram of a control circuit in a pressure-type flow rate control apparatus. The pressure sensor 10, fixed amplifier 42, variable amplifiers 44, 46, A/D converter 48, offset D/A converter 40 are all the same as those in FIG. 2, and will not be explained further.

5 The gas temperature output measured by the temperature sensor 14 is amplified to a gas temperature T by the fixed amplifier 56 and is inputted to the CPU 41 *via* an A/D converter 58. Said gas temperature T is inputted to a temperature drift correcting means 60 and a gas temperature correcting means 68.

10 Said temperature drift correcting means 60 comprises a zero point correction means 62, a memory means 64, and a span correction means 66. In said memory means 64, the following data are stored: the relative ratio $k(T)$ of the zero-point output drift as shown in FIG. 5, and the relative ratio $\Delta(T)$ of the output drift as shown in FIG. 6.

15 When the gas temperature T is inputted to the zero point correcting means 62, the corresponding relative ratio data $k \bullet \bullet$, relating to the zero-point output drift, is obtained from the memory means 64, and the relative ratio $k(T)$ at gas temperature T is calculated. From this calculated relative ratio $k(T)$, the zero-point output drift voltage v_0 is determined, and the inverted voltage $-v$ is applied to the offset terminal 42a through the offset D/A converter 40; the zero-point output drift is thus automatically corrected.

20 Further, when the gas temperature T is inputted to the span correction means 66, the corresponding relative data $\Delta \bullet \bullet$, relating to the span output drift, is obtained from the memory means 64, and the relative ratio $\Delta(T)$ at gas temperature T is calculated. The span output drift is determined using the calculated relative ratio $\Delta(T)$. By subtracting the span output drift from the pressure voltage V inputted from A/D converter 48, an accurate upstream side pressure P_1 is obtained.

25 Furthermore, when the gas temperature T is inputted to the gas temperature correcting means 68, an accurate proportional constant K is determined on the basis of inputted physical data, and from said proportional constant K and said upstream side pressure P_1 , a calculated flow rate Q_c is obtained from $Q_c = KP_1$. Said calculated flow rate Q_c is outputted *via* a D/A converter 72 and a fixed amplifier 74, and is displayed on an exterior display device (not shown).

30 Said set flow rate Q_s inputted from the flow rate setting means 18 as the flow rate of fluid to be supplied is inputted to the comparison means 19 *via* a fixed amplifier 76 and an A/D converter 78. On the other hand, the calculated flow rate Q_c is inputted to the

comparison means 19 from the gas temperature correction means 68, and the flow rate difference ΔQ is calculated by $\Delta Q = Q_c - Q_s$ and outputted to the valve drive unit 20.

Said valve drive unit 20 controls the opening of the control valve 22 so as to bring the flow rate different ΔQ to zero. By adjusting the opening of the control valve 22, the upstream side pressure P_1 is controlled. As a result, the control valve 22 is automatically regulated so that ΔQ becomes zero and the calculated flow rate Q_c is equal to the set flow rate Q_s .

FIG. 8 is a flow diagram of the operation of the zero point correction means 62 according to the present invention. At step m1, the gas temperature T is inputted, and at step m2 the relative ratio $k(T)$ at gas temperature T is derived from the relative ratio data in the memory means 64. At step m3, the zero-point output drift voltage v_0 is calculated from relative ratio $k(T)$ and the output voltage v of the pressure sensor 10. At step m4, said voltage v_0 is inverted, and at step m5 - v_0 is applied to said offset terminal 42a. The zero point is thus corrected.

FIG. 9 is a flow diagram of the operation of the span correction means 66 according to the present invention. At step n1, the gas temperature T is inputted. Contemporaneously, at step n2, the output voltage v measured by the pressure sensor 10 is subjected to zero-point output correction and inputted as a pressure voltage V .

At step n3, the relative ratio $\Delta(T)$ of drift at gas temperature T is determined on the basis of the relative ratio data in the memory means 64. At step n4, a temperature-corrected pressure voltage V' is calculated from said relative ratio $\Delta(T)$ and the above-mentioned pressure voltage V . Said temperature-corrected pressure voltage V' is an accurate upstream side pressure P_1 . At step n5, said upstream side pressure P_1 is inputted to the gas temperature correction means 68.

FIG. 10 is a schematic diagram of flow rate control according to the present invention using a pressure-type flow rate control apparatus which operates under non-critical conditions. In said pressure-type flow rate control apparatus 2, it is a prerequisite that the fluid to be supplied is under non-critical conditions, i.e. the velocity of fluid flowing from the orifice 4 is lower than sonic velocity.

When the fluid is under non-critical conditions, one of the theoretical flow rate formulae for a fluid passing through an orifice is derived from Bernoulli's theorem which holds good for an incompressible fluid, and is given as:

$$Q = KP_2^{1/2} (P_1 - P_2)^{1/2}$$

In this case, the gas flow rate is controlled using this theoretical flow rate formula.

According to this flow rate formula, the flow rate Q of the fluid passing through the orifice is calculated from the upstream side pressure P_1 and the downstream side pressure P_2 . While the upstream side pressure P_1 is measured by the pressure sensor 10, and the downstream side pressure P_2 is constantly measured by the downstream side pressure sensor 12, therefore, the calculated flow rate Q_c is obtained from :

$$Q_c = KP_2^{1/2} (P_1 - P_2)^{1/2}$$

What is different from FIG. 1 is that an electronic circuit system and a software system are added in which the downstream side pressure P_2 is measured by the downstream side pressure sensor 12, and the measured value is inputted to the control circuit 16. The same electronic circuit system and software system as those that are connected to the upstream side pressure sensor 10 are provided in parallel for this purpose.

FIG. 11 is a detailed schematic block diagram of the control circuit of FIG 10.

The electronic circuit system that is connected to the downstream side pressure sensor 12 includes a fixed amplifier (AMP), a variable amplifier (VAMP), a variable amplifier for display (VAMP), an A/D converter, and an offset D/A converter. This electronic circuit system is mounted in the input system of said CPU 41.

In addition, the software system for the upstream side pressure sensor 10 is used commonly. That is, said software system comprehends said memory means 64 for storing data relating to the zero-point output drift and span output drift of the downstream side pressure sensor 12, said zero point correction means 62 for correcting the zero-point output drift, and said span correction means 66 for correcting said span output drift, both using these data. The software systems are installed in the CPU 41.

By providing such electronic circuit and software systems, and installing the flow rate calculating means 17 for calculating $Q_c = KP_2^{1/2} (P_1 - P_2)^{1/2}$ in the control circuit 16, and at same time by providing the comparison-means 19 for calculating the flow rate difference $\Delta Q = Q_s - Q_c$, the flow rate is controlled to obtain a target flow rate. The operation and effects of the other components are the same as those in FIG. 1 and will not be explained further.

FIG. 12 is a schematic diagram of flow rate control using an improved pressure-type flow rate control apparatus which operates under non-critical conditions. In said pressure-type flow rate control apparatus 2, it is a

prerequisite that the fluid to be supplied is under non-critical conditions, but an improved theoretical flow rate formula is used.

Since actual gaseous fluids are expandable and compressible, and since accordingly Bernoulli's theorem, which assumes incompressibility, holds good only approximately, the flow rate formula represented by $Q_c = KP_2^{1/2} (P_1 - P_2)^{1/2}$ is only an approximate formula. Improving on this approximate formula, the inventors have found a formula that can represent actual flow rates with great precision.

In the improved flow rate formula, the equation:

$$Q_c = KP_2^m (P_1 - P_2)^n$$

is used. The two parameters m , n are introduced as fitting exponents, that is, for matching actual flow rates to the flow rate formula. The values obtained were $m = 0.47152$, $n = 0.59492$. Using these values, actual flow rates can be calculated with great precision.

In this example, the flow rate calculation means 17 is provided using the improved flow rate formula. Except in this respect, this example is wholly the same as that shown in FIG. 10. That is, the systems for correcting the temperature drifts of the upstream side pressure sensor 10 and the downstream side pressure sensor 12 are the same as those in FIG. 11, and will not be explained further.

The present invention has just been described with regard to pressure-type flow rate control apparatus, but it can also be used for the correction of temperature drift (zero-point output drift and span output drift) of the pressure sensor itself. Furthermore, the present invention can be used to correct the temperature drift of a pressure control apparatus with a built-in pressure sensor.

Needless to say, the present invention is not restricted to the above-mentioned embodiments and examples. It is to be understood that the present invention covers a variety of examples and design changes within its technical scope, without departing from the spirit or scope of the present invention.

Effects of the Invention

The first aspect of the invention provides a pressure sensor that can accurately detect pressure by providing a temperature drift correcting means by which the temperature drift of the output of the pressure sensor can be cancelled.

The second aspect of the invention provides a pressure control apparatus having a pressure sensor and a control valve, which can control pressure with precision, whilst accurately

detecting the pressure, by having a temperature drift correcting means that can negate the temperature drift of the pressure sensor output.

The third aspect of the invention has a memory means for storing a relation between the fluid temperature and the output drift of an upstream side sensor, and a temperature drift
 5 correction means which calculates the amount of the output drift of the upstream side pressure sensor from data in the memory means when the fluid temperature changes, and offsets the output drift of the upstream side sensor with the calculated amount of output drift, thereby correcting the temperature drift. As a result, even if a pressure sensor having any temperature characteristics is used, the upstream side pressure P_1 can be accurately
 0 detected merely by storing the temperature characteristics in the memory means. The flow rate can therefore be controlled accurately in pressure-type flow rate control apparatuses where $Q_c = KP_1$ is used as the flow rate formula.

The fourth aspect of the invention has a memory means for storing a relation between the fluid temperature and the output drifts of an upstream side sensor and a downstream side
 5 sensor, and a temperature drift correcting means which calculates the amounts of the output drift of the upstream side sensor and the downstream side sensor from data in memory means when the fluid temperature changes, and negatives the output drifts of the upstream side sensor and downstream side sensor with the calculated output drift amounts. As a result, even if a pressure sensor having any temperature characteristics is used, the
 1 upstream side pressure P_1 and downstream side P_2 can be accurately detected merely by storing the temperature characteristics of the pressure sensors in the memory means. Hence, in a pressure-type flow rate control apparatus where $Q_c = KP_2^{1/2} (P_1 - P_2)^{1/2}$ or $Q_c = KP_2^m (P_1 - P_2)^n$ is used, the flow rate can be accurately controlled.

According to each of the above aspects, since the relation at zero pressure between the fluid temperature and the zero-point output drift of the pressure sensor is stored in the memory means, the amount of the zero-point output drift can be calculated from data in the memory means, even if the fluid temperature changes to any level, whereby the zero-point output drift of the pressure sensor can be negated on the basis of the calculated zero-point output drift amount, thereby correcting the temperature drift.

Further, since the relation under any arbitrary pressure between the fluid temperature and the span output drift of the pressure sensor is stored in the memory means, the amount of the span output drift can be calculated from data in the memory means even if the fluid temperature changes to any level under any

arbitrary pressure, such that the span output drift of the pressure sensor can be automatically negated with the calculated span output drift amount, thereby correcting the temperature drift.

- 5 According to a preferred embodiment, even if the temperature of the flowing gaseous fluid undergoes any changes, the gas pressure can be detected accurately, thus making it possible to improve the control efficiency of the gaseous fluid in semiconductor manufacturing facilities, chemical production plants, etc.

Claims

1. An apparatus for correcting temperature drift for use in a pressure sensor for measuring the pressure of a fluid, said apparatus comprising a temperature sensor for measuring the temperature of the fluid, a memory means for storing a relation between the fluid temperature and an output drift of the pressure sensor, and a temperature drift correcting means 60, provided with a span drift correcting means 66 wherewith the output voltage v of the pressure sensor 10 is inputted through a fixed amplifier 42, a variable amplifier 44 and an A/D converter 48, and a zero-point correcting means 62 wherewith the reverse voltage $-v_o$ of the zero-point drift voltage v_o is outputted to the afore-mentioned offset terminal 42a of the fixed amplifier 42 through the offset D/A converter 40, for calculating the amount of the output drift of the pressure sensor from data in the memory means when the fluid temperature changes, and negating said output drift of the pressure sensor with said calculated amount of the output drift, thereby correcting the temperature drift, such that even if the temperature of fluid changes, the fluid pressure can be measured accurately, wherein
said memory means stores a relation between the fluid temperature and a zero-point output drift of the pressure sensor at zero pressure, and the temperature drift correcting means calculates the amount of the zero-point output drift when the fluid temperature changes and negates the zero-point output drift of the pressure sensor with the calculated amount of the zero-point output drift, thereby correcting the temperature drift, and wherein
the memory means stores a relation between the temperature of the fluid and a span output drift of the pressure sensor under any arbitrary pressure, and the amount of the span output drift is calculated from the memory means when the temperature of fluid changes, and the calculated amount of the span output drift is added to or subtracted from the output of the pressure sensor, thereby correcting the temperature drift.

2. An apparatus for correcting temperature drift for use in a pressure control apparatus comprising a control valve for pressure control and a pressure sensor for measuring the pressure of a fluid, the apparatus for correcting temperature drift comprising a memory means for storing a relation between the fluid temperature and an output drift of the pressure sensor, and a temperature drift correcting means 60, provided with a span drift correcting means 66 wherewith the output voltage v of the pressure sensor 10 is inputted through a fixed amplifier 42, a variable amplifier 44 and an A/D converter 48, and a zero-point correcting means 62 wherewith the reverse voltage $-v_0$ of the zero-point drift voltage v_0 is outputted to the afore-mentioned offset terminal 42a of the fixed amplifier 42 through the offset D/A converter 40, which calculates the amount of the output drift of the pressure sensor from data in the memory means when the fluid temperature changes, and negates the output drift of the pressure sensor with the calculated amount of the output drift, thereby correcting the temperature drift, such that even if the fluid temperature changes, the pressure of fluid is accurately controlled , wherein
said memory means stores a relation between the fluid temperature and a zero-point output drift of the pressure sensor at zero pressure, and the temperature drift correcting means calculates the amount of the zero-point output drift when the fluid temperature changes and negates the zero-point output drift of the pressure sensor with the calculated amount of the zero-point output drift, thereby correcting the temperature drift, and wherein
the memory means stores a relation between the temperature of the fluid and a span output drift of the pressure sensor under any arbitrary pressure, and the amount of the span output drift is calculated from the memory means when the temperature of fluid changes, and the calculated amount of the span output drift is added to or subtracted from the output of the pressure sensor, thereby correcting the temperature drift.

3. An apparatus for correcting temperature drift for use in a pressure-type flow rate control apparatus comprising an orifice for flow rate control, a control valve provided in a pipe on an upstream side of the orifice, and an upstream side pressure sensor provided between said orifice and the control valve for detecting an upstream side pressure P_1 , such that the flow rate of a fluid passing through the orifice can be controlled on the basis of the upstream side pressure P_1 , the apparatus for correcting temperature drift comprising a temperature sensor for measuring the temperature of the fluid, a memory means for storing a relation between the temperature of the fluid and an output drift of the upstream side pressure sensor, and a temperature drift correcting means 60, provided with a span drift correcting means 66 wherewith the output voltage v of the pressure sensor 10 is inputted through a fixed amplifier 42, a variable amplifier 44 and an A/D converter 48, and a zero-point correcting means 62 wherewith the reverse voltage- v_o of the zero-point drift voltage v_o is outputted to the afore-mentioned offset terminal 42a of the fixed amplifier 42 through the offset D/A converter 40, which calculates the amount of the output drift of the upstream side sensor from data in the memory means when the temperature of fluid changes, and offsets the output drift of the upstream side pressure sensor with the calculated amount of the output drift, thereby correcting the temperature drift, such that even if the temperature of fluid fluctuates, the flow rate of fluid can be accurately controlled, wherein said memory means stores a relation between the fluid temperature and a zero-point output drift of the pressure sensor at zero pressure, and the temperature drift correcting means calculates the amount of the zero-point output drift when the fluid temperature changes and negates the zero-point output drift of the pressure sensor with the calculated amount of the zero-point output drift, thereby correcting the temperature drift, and wherein
the memory means stores a relation between the temperature of the fluid and a span output drift of the pressure sensor under any arbitrary pressure, and the

added to or subtracted from the output of the pressure sensor, thereby correcting the temperature drift.

4. An apparatus for correcting temperature drift for use in a pressure-type flow rate control apparatus comprising an orifice for flow rate control, a control valve provided in a pipe on an upstream side of the orifice, an upstream side pressure sensor provided between the orifice and the control valve for detecting an upstream side pressure P_1 , and a downstream side pressure sensor provided in a pipe on a downstream side of the orifice for detecting a downstream side pressure P_2 such that the flow rate of a fluid passing through the orifice can be controlled on the basis of the upstream side pressure P_1 and the downstream side pressure P_2 , the apparatus for correcting temperature drift comprising a temperature sensor for measuring the temperature of the fluid, a memory means for storing a relation between the temperature of the fluid and output drifts of the upstream side pressure sensor and downstream side pressure sensor, and a temperature drift correcting means 60, provided with a span drift correcting means 66 wherewith the output voltage v of the upstream side pressure sensor 10 is inputted through a fixed amplifier 42, a variable amplifier 44 and an A/D converter 48, and the output voltage of the downstream side pressure sensor 12 is inputted through a fixed amplifier, a variable amplifier and an A/D converter, and a zero-point correcting means 62 wherewith the reverse voltage $-v_o$ of the zero-point output drift voltage v_o is outputted to the offset terminal 42a of the fixed amplifier 42 of the afore-mentioned upstream side pressure sensor output voltage and to the offset terminal of the fixed amplifier of the downstream side pressure sensor output voltage through the offset D/A converter, which calculates the amounts of the output drifts of the upstream side pressure sensor and downstream side pressure sensor from data in the memory means when the fluid temperature changes, and offsets the output drifts of the upstream side pressure sensor and downstream side pressure sensor with the calculated output drift amounts, thereby correcting the temperature drifts, such that even if the fluid temperature changes, the flow rate of fluid is accurately controlled, wherein said memory means stores a relation

21c

between the fluid temperature and a zero-point output drift of the pressure sensor at zero pressure, and the temperature drift correcting means calculates the amount of the zero-point output drift when the fluid temperature changes and negates the zero-point output drift of the pressure sensor with the calculated amount of the zero-point output drift, thereby correcting the temperature drift, and wherein the memory means stores a relation between the temperature of the fluid and a span output drift of the pressure sensor under any arbitrary pressure, and the amount of the span output drift is calculated from the memory means when the temperature of fluid changes, and the calculated amount of the span output drift is added to or subtracted from the output of the pressure sensor, thereby correcting the temperature drift.