



9604435-9
IPOS copy

REPLACED SHEETS		SG
☐ Description	: paged ..1.... to paged ..21....	
☒ Claim(s)	: paged ..22.. to paged ..35....	
☒ Drawing(s)	: paged ..1113.. to paged ..13113....	
☒ Abstract	: paged ..76.. to paged ..<....	

1


STUDLESS THIN FILM MAGNETIC HEAD
AND PROCESS FOR MAKING THE SAME

The present invention relates to magnetic thin film heads (TFH) for recording and reading magnetic transitions on a moving magnetic medium. It is applicable to either inductive or magnetoresistive (MR) elements.

In particular, the present invention relates to a method of etching deep vias through the thick alumina overcoat in order to expose underlying bonding pads, thereby completely eliminating fabrication of the studs (or bonding posts), a method of etching the undercoat to define scribe-line grooves of streets and alleys across the wafer for sawing (or dicing) and machining of the sliders, and a method of pattern-etching the alumina undercoat, prior to the wafer fabrication, to create precise craters for recessed structures or open vias to the substrate for lightning arresters.

Magnetic TFH transducers are known in the prior art. Please refer, for example, to U.S. Pat. Nos. 4,016,601; 4,190,872; 4,652,954; 4,791,719 for inductive devices and U.S. Pat. Nos. 4,190,871 and 4,315,291 for magnetoresistive (MR) devices.

In the operation of a typical inductive TFH device a moving magnetic storage medium is placed near the exposed pole-tips of the TFH transducer. During the read operation, the changing magnetic flux of the moving storage medium induces a changing magnetic flux upon the pole-tips and the gap between them. The magnetic flux is carried through the pole-tips and yoke core around spiralling conductor coil winding turns located between the yoke arms. The changing magnetic flux induces an electrical voltage across the conductor coil. The electrical voltage is representative of the magnetic pattern stored on the moving magnetic storage medium. During the write operation, an electrical current is caused to flow through the conductor coil. The



current in the coil induces a magnetic field across the gap between pole-tips. A fringe field extends into the nearby moving magnetic storage medium, inducing (or writing) a magnetic domain (in the medium) in the same direction. Impressing current pulses of alternating polarity across the coil causes the writing of magnetic domains of alternating polarity in the storage medium.

Magnetoresistive (MR) TFH devices can only operate in the read mode. The electrical resistance of an MR element varies with its magnetisation orientation. Magnetic flux from the moving magnetic storage medium induces changes in this orientation. As a result, the resistance of the MR element to a sensing electric current changes accordingly. The varying voltage signal is representative of the magnetic pattern stored on the magnetic medium.

In the manufacturing of TFH transducers for magnetic recording, a large number of devices are fabricated simultaneously in deposited and patterned layers on a ceramic wafer. When completed, the wafer is cut (or diced) and machined into individual slider transducers. The main elements of a TFH inductive transducer, roughly in the order in which they are deposited, are the (alumina) undercoat, the bottom magnetic pole, the flux gap material to provide spacing between the bottom and top magnetic pole-tips, one or more levels of electrical conductive coil winding interposed within insulation layers, the top magnetic pole, elevated studs (or posts) for connecting the coil to bonding pads (above the overcoat), a thick (alumina) overcoat, and the bonding pads.

Usually the studs are made of about 25-50 μ m thick copper, plated through a thick photoresist mask right after the completion of the top magnetic pole and prior to the deposition of thick alumina overcoat. For reasons of uniformity and reproducibility, the studs are designed to extend to a level about 10 μ m above the highest spot of the TFH device (the back yoke of the top pole). For each coil level the stud thickness must be increased by at least 6-9 μ m. For similar reasons, the alumina overcoat thickness must exceed the stud thickness by about 10 μ m, requiring an overcoat about 35-60 μ m thick. Following the overcoat deposition, the studs are covered by the



alumina overcoat. The wafer is then lapped (ground) down to expose the copper studs. Next, (gold) bonding pads are fabricated over the alumina overcoat to contact the exposed studs. The pads are later used for bonding wires to external circuitry to the read/write channel.

Fabrication of studs and bonding pads is described in U.S. Pat. No. 4,219,853, for example. It is similar in both inductive and MR devices. For TFH devices combining an inductive write element and an MR read element, one on top of the other, the stud and alumina overcoat operations have to be repeated. This may bring the total thickness of the studs to about 40-70 μ m, and the total alumina overcoat thickness to about 50-80 μ m. As the alumina deposition process is relatively slow, about 1-2 μ m/hour, it can easily become the bottleneck (1-3 days) in the process flow. Furthermore, alumina sputtering equipment is very costly. As a result, the alumina overcoat deposition is by far the costliest and the slowest step in TFH wafer fabrication.

The integrity and chipping resistance of the alumina overcoat are directly related to its thickness and stress. The thicker the alumina layer, the more stress it incorporates. The alumina overcoat's stress also adversely affects the noise performance of the TFH device, since it is in direct contact with the top magnetic pole. Moreover, tall features of the device, such as the studs, impair the integrity of the deposited alumina in the local surrounding area. Sawing and machining operations subject the alumina overcoat to local stresses which often result in excessive chipping and rejects.

Very thick studs require a relatively long plating time and the thickness uniformity is quite difficult to control. To achieve the required thickness, stud plating dictates the use of a dry film photoresist which is difficult to strip and process. The usual fabrication of studs and bonding pads demands numerous steps of photomasking, deposition of seed-layers, plating, stripping, and etching. The elaborate structure of the studs and bonding pads, including coil leads, permalloy, and all the seed-layers, may involve some 10-15 individual metallic layers deposited in succession on top of each other. The probability of bonding failures due to inadequate adhesion between any two



of these metallic layers is directly proportional to the number of these layers. Thus reliability of the bond strength is adversely affected by the large number of the metallic layers in the structure. The poor integrity of the alumina overcoat in the locales surrounding the studs further degrades the bond strength and often impairs the fabrication of bonding pads due to "loops" of collapsed alumina around the studs. The latter appear following the lapping of the alumina overcoat to expose the studs, and are due to the poor integrity of the alumina surrounding the studs.

Copper residues and contamination, originating from copper seed-layers used for the coil and stud platings, may cause shorts and impair the corrosion resistance of the TFH device. Copper coil seed-layer residues are often found to be responsible for intensified corrosion susceptibility of exposed pole-tips in the air bearing surface (ABS). This poor corrosion resistance is due to galvanic action between the two dissimilar metals (Cu and Ni-Fe) contacting at the corners (or wings) of the pole-tips. Similarly, the copper seed-layer of the studs is often found to degrade coil-to-core resistance due to full or partial shorts. The copper coil itself is sometimes subject to capricious variations of its electrical resistance due to corrosion and oxidation of the copper turns during elevated temperature curing cycles of the photoresist insulation layers.

The present invention provides an economical method for fast and precise patterning of thick sputter-deposited alumina layers by etching through appropriate metallic masks. It further provides improvements in product design and performance of magnetic heads which avoid the above-described shortcomings of the prior art. In particular, the precise patterning of thick alumina layers by etching enables the fabrication of studless TFH devices, scribe-line grooves for dicing, recessed craters for TFH devices, and lightning arresters.


Elimination of the studs simplifies the wafer fabrication in a very substantial way. It curtails about 20-30% of the total wafer processing steps and reduces the alumina overcoat thickness by about 30-50%. It thus produces the substantial benefits of reducing processing costs, decreasing device noise, and improving throughput,



consistency, bonding strength, and corrosion resistance. Alumina chipping is usually a major contributor to yield loss. Etching scribe-line grooves facilitates significant reduction of alumina chipping during slider machining and later in tests and service. It thus significantly improves total device yields. Pattern-etching precise craters in the alumina undercoat facilitates the fabrication of TFH devices with recessed structures or features. These can improve device planarity and alleviate problems associated with tall features of multi-level coil designs. They can also improve the symmetry of pole-tips configuration. Similarly, etching vias through the alumina undercoat layer enables the construction of lightning arresters by electrically connecting the magnetic core to the substrate, which will be grounded in the process of packaging the slider. The lightning arresters provide grounding to prevent arcing between the magnetic core and rotating disk.

In accordance with the present invention, the patterning of thick sputter-deposited alumina layers is accomplished by, first, depositing compatible metallic layers on the alumina, coating the metallic layers with photoresist, patterning the photoresist by photolithography, etching the metallic layers (in sequence) through the photoresist mask, stripping the photoresist, etching the thick alumina layer through the metallic mask, and removing (in sequence) the metallic masking layers. A preferred etchant comprising dilute HF in water (1:2 by volume ratio) has been found to provide fast (about $1\mu\text{m}/\text{min}$), extraordinarily uniform (better than $\sigma = 1\%$ across a wafer), and accurate etching of thick alumina layers. The etching can be conveniently performed by spray or immersion. A compatible metallic mask must be used with the dilute HF etchant since photoresist masks lift-off from the alumina surface after a very short time. A preferred metallic mask comprises a very thin (10-30nm) Cr or Ti adhesion layer covered by a gold (Au) layer, about 0.3-0.5 μm thick. To avoid porosity in the gold layer and for economic reasons, at least one half of the gold thickness can be plated from an high purity (99.9%) "soft" gold bath.

In accordance with the present invention a studless TFH device with gold coil



and bonding pads, patterned and plated simultaneously, is provided. Following the alumina overcoat deposition, vias are etched through it to expose the bonding pads. This eliminates copper altogether from the TFH device, resulting in less maintenance and significantly improved reliability, corrosion resistance, and consistency of the coil resistance. Similarly, the thick alumina is pattern-etched to form scribe-line grooves which minimise alumina chipping during sawing and machining. Other improvements in a TFH device resulting from deep alumina pattern-etching include the formation of recessed craters to improve planarity and pole-tips symmetry and the formation of vias to the substrate for lightning arresters connecting the magnetic core to the substrate.

An object of the present invention is to provide a method of pattern-etching through an alumina layer.

Another object is to provide a studless TFH device.

A further object of the present invention is to provide a simple, fast, and low cost method to eliminate many processing steps and increase throughput in the process of fabricating a TFH device.

Embodiments of the present invention will now be described with reference to the accompanying drawings, of which:

Fig. 1 shows a cross-section of a typical prior-art stud and bonding pad structure;

Figs. 2(a) and 2(b) show cross-sections of alternative bonding pad structures embodying the present invention;

Figs. 3(a) to 3(h) are cross-sectional views, at various stages, during the patterning of thick alumina, such as used for the studless pads of the present invention;

Fig. 4 is a cross-sectional view of a scribe-line groove after pattern-etching; and

Fig. 5 is a cross-sectional view of a recessed crater after pattern-etching.

A schematic (not to scale) cross-section of a typical prior-art stud and bonding pad structure is shown in Fig. 1. An alumina undercoat 12 is first deposited over a ceramic substrate 10. The wafer is then subjected to the deposition and patterning of



many layers. A typical succession of the metallic layers in the stud area may include a Cr (or Ti) seed-layer 14, a Cu seed-layer 16, a first level plated Cu coil 18, a Cr (or Ti) seed-layer 20, a Cu seed-layer 22, a second level plated coil 24, a Ni-Fe seed-layer 26 for the top pole, a first plated Ni-Fe layer 28 of the top pole, a second plated Ni-Fe layer 30, a Cu seed-layer 32 for the stud, a plated Cu stud 34, alumina overcoat 35, a Ni-Fe seed-layer 36 for the bonding pad, and a gold bonding pad 38. A wire 39 is bonded to gold bonding pad 38, typically by thermocompression or ultrasonic compression techniques.

In some cases the stud structure may include other layers, such as a Ni-Fe seed-layer and plated layers of the bottom pole (between layers 12 and 14), or a Cr (or Ti) seed-layer under Cu seed-layer 32 for the stud, or under Ni-Fe seed-layer 36 for the bonding pad, or under Ni-Fe seed-layer 26 for the pole plating. In other cases, several of these layers are omitted. Typically the stud and bonding pad structure comprise about 10-15 individual metallic layers. In some cases, the bonding pad structure is placed on the alumina overcoat in a partial overlapping and staggering position relative to the stud structure. Bonding is made to the off-set portion of the pad to ensure adequate bonding strength. Such elaborate structures of the studs and bonding pads are susceptible to bonding failure due to the large number of metallic layers in the structure. In addition, the poor integrity of the alumina overcoat in the region surrounding the tall stud further impairs reliability and bonding strength.

According to a preferred embodiment of the present invention, the entire stud fabrication is eliminated, resulting in a simple bonding pad structure of only two metallic layers, shown in Fig. 2(a). A single seed-layer 36, such as Ni-Fe or W, is bonded to an alumina undercoat 12, which overlies a substrate 10. Seed layer 36 must be compatible for gold plating and must have good to moderate electrical conductivity and strong adhesion to alumina. Other metals and alloys suitable for this purpose include Mo, Ni-Co, Ni-Co-Fe, Cd, and In. The thickness of seed-layer 36 in Fig. 2(a) is in the range 60-200nm, and preferably in the range 100-150nm. This structure has



only two metallic layers in the pad. An Au bonding pad 38 is preferably plated simultaneously with the coil turns and leads (not shown) through an appropriate photoresist mask. Both the coil and the bonding pads will then consist of the same (Au) metal.

If the coil consists of more than a single level, different pads may be deposited and patterned simultaneously with different coil levels. Alternatively, one or more pads may be deposited and patterned repeatedly with more than one coil level. Such pads, however, will have more metallic layers in their structure. Following the coil/pad plating and stripping of the photoresist mask, seed-layer 36 must be removed from between the Au-plated areas. Using a different metal or alloy for seed-layer 36 from that used for pad 38 enables its removal by selective chemical etching, as described in U.S. Patent No. 5,059,278 to Cohen et al., incorporated herein by reference. Wire 39 is bonded to the (Au) bonding pad 38 through the etched vias in the alumina overcoat 40.

In another embodiment, the pad structure comprises a total of three or more metallic layers, as shown in Fig. 2(b). The structure combines at least two seed-layers. The first seed-layer comprises an adhesion layer 14 of Cr or Ti or another refractory metal such as W, Ta, Mo, Nb, V, Zr, and Hf, or an alloy comprising one or more of these metals. The function of this layer is to enhance adhesion between alumina and the following gold layer (gold alone has poor affinity to oxygen and, therefore, poor adhesion to alumina). The thickness of the adhesion seed-layer 14 can be in the range 5-50nm, and preferably in the range 10-30nm. The layer is usually deposited by a vacuum technique such as sputtering or evaporation.

An Au seed-layer 37 is similarly deposited by sputtering or evaporation. It provides a low electrical resistance and compatible metallic surface for the plating of a gold pad 38. Other metals or alloys compatible with gold plating and having good electrical conductivity may also be used for the second metallic seed-layer 37. They include Ni-Fe, W, Mo, Cu, Ag, Pd, Pt, Rh, Ir, and alloys comprising one or more of



these metals. In contrast, most refractory metals possess high electrical resistivity and are incompatible for gold plating. The thickness of the Au seed-layer 37 is in the range 50-300nm, and preferably in the range 70-100nm. Plated gold pad 38 has a thickness in the range 1.0-5.0 μ m, and preferably in the range 2.0-4.0 μ m. Again, the coil turns and leads and bonding pads may be plated simultaneously through a suitable photoresist mask. Alternatively, the coil may comprise gold or another highly conductive metal which is deposited and patterned separately from the bonding pad 38.

Other combinations may also be used. In particular, bonding pad 38 of Figs. 2(a) and 2(b) may comprise Au, Cu, Ag, Pd, Pt, Rh, Ir, and alloys comprising one or more elements thereof. Usually the same layer is also used for the coil winding turns. Alternatively, the coil turns may comprise a different metal or alloy than the pad. For example, the coil turns may comprise Cu, Ag, Pd, Pt, Rh, Ir, and alloys comprising one or more elements thereof, while the bonding pad may comprise gold. However, different metals or alloys in the coil and pads require further processing steps, which add to manufacturing complexity and cost. It may be noted that although Al has both excellent conductivity and adhesion to alumina, it is incompatible for plating (of the coil). It is thus unsuitable as a seed-layer for any plating. However, Al as a single layer may be used simultaneously for both the coil and the bonding pad, if deposited by a vacuum technique (such as sputtering or evaporation) and patterned by etching. Appropriate etching techniques for Al patterning include ion milling and reactive ion etching (RIE). Wet etching of Al lacks the fine resolution required for the coil definition. When Al is used in this mode, seed-layer 36 of Fig 2(a) and seed-layers 14 and 37 of Fig 2(b) are eliminated, resulting in an even simpler structure.

The noble metals Au, Cu, Ag, Pd, Pt, Rh, Ir, and alloys comprising one or more metals thereof may also be deposited as a continuous layer by plating or by a vacuum technique, and then pattern-etched simultaneously for both the coil turns and pads by ion milling or by RIE. The dry etching technique requires an appropriate etch mask combining both the coil and the pads patterns. It is formed over the top



continuous metal layer. The remains of the etch mask are removed following the dry etching. Top layer noble metals require an intermediate adhesion layer similar to seed layer 36 in Fig. 2(a) and seed layer 14 in Fig. 2(b). Alternatively, the coil turns may comprise a different metal than the bonding pads and fabricated by different techniques. For example, the coil turns may comprise sputter or evaporation deposited Al and may be patterned by ion milling or RIE, while the bonding pads may consist of plated gold.

Patterning of thick alumina layers requires an etching mask which is substantially free of pores and not etched or adversely affected by the alumina etchant. When using dilute HF etchant for the alumina layer, etching masks based on photoresist alone are inadequate since they lift-off after only a short time in contact with the etchant. The dilute HF rapidly attacks the bond between the alumina and the photoresist. Metal masks must be used for the prolonged etching. The metal mask must have excellent adhesion to the alumina layer and it should be substantially free of pores. It must also be immune against attack by the etchant.

Figures 3(a) through 3(h) illustrate the major steps involved during the patterning of thick alumina, according to a preferred embodiment of this invention. Fig. 3(a) shows the structure after a photoresist layer 48 has been coated over the metallic mask layers and patterned by photolithography. Prior to coating the photoresist layer, successive seed-layers 42 of Cr or Ti and 44 of Au or Ni-Fe were deposited by a vacuum technique over a thick alumina layer 40. Seed-layer 42 must provide excellent adhesion to the alumina surface. It comprises a refractory metal from the group Cr, Ti, W, Ta, Mo, Nb, V, Zr, Hf, and alloys comprising one or more of these metals. The thickness of adhesion seed-layer 42 can be in the range 5-50nm, and preferably in the range 10-30nm. Since most refractory metals (such as Cr, Ti, Ta, Nb, V, Zr, and Hf) are incompatible for gold plating and have poor electrical conductivity, seed-layer 44, with good conductivity and compatibility for gold plating, is deposited over adhesion seed-layer 42. Gold is excellent for this purpose and is the preferred choice for seed-layer 44. However, it requires an expensive gold sputtering target. Alternatively, seed-




layer 44 may comprise a metal from the group Ni-Fe, Ag, Pd, Pt, Rh, Ir, W, Mo, and alloys comprising one or more metals thereof. A single seed-layer 44 comprising Ni-Fe, W, Mo, or an alloy comprising one or more of these metals, possesses good adhesion and electrical conductivity and is compatible for gold plating. It can thus simplify the metallic mask by eliminating layer 42. The advantage of using Ni-Fe for seed-layer 44 is that it is already being utilised in the TFH fabrication process. The thickness of seed-layer 44 can be in the range 50-500nm, and preferably in the range 70-150nm. Usually vacuum deposition produces layers 42 and 44 which are quite porous and permeable and, therefore, inadequate for use alone as the metallic mask for thick alumina etching.

After deposition of layers 42 and 44, the wafer is placed in a high purity (99.9%) "soft" gold plating bath, and a layer 46 of gold is plated over seed-layer 44. To ensure that plated gold layer 46 be free of pores, its thickness should exceed about 0.1-0.2 μ m. Usually the thickness of layer 46 is in the range 0.1-1.0 μ m, and preferably in the range 0.2-0.5 μ m. Although it would be simpler to utilise Au seed-layer 44 alone, without the plated Au layer 46, sputter-deposited layers contain some pores even at thicknesses of more than 1.0 μ m. Furthermore, thick ($\geq 2\mu$ m) sputter-deposited Au layers significantly increase the manufacturing cost due to the very expensive gold targets. Photoresist mask layer 48 is coated over the metallic mask layers and patterned by a regular photolithography technique.

Next, the pattern is transferred to the metallic layers to form the etching mask. Fig. 3(b) shows the structure after pattern-etching gold layers 46 and 44 through the photoresist mask. A convenient etchant for the gold layers is based on a dilute solution of KI and I₂ in water:

Potassium Iodide	KI	100 - 200 g/l
Iodine	I ₂	25 - 50 g/l

This etchant is compatible with the positive photoresist mask. It takes about 1-2 minutes to etch Au layers 46 and 44 using this etchant at room temperature. It can be applied by immersion with moderate agitation, or by spraying. Lower concentrations



and temperature decrease the etch rate, while higher concentrations and temperature increase it.

Following the pattern-etching of Au layers 46 and 44, the pattern has to be further transferred by etching the Cr or Ti adhesion layer 42. First the photoresist layer 48 is removed using a conventional stripping method, such as by dipping in or spraying with a commercial photoresist stripper, dilute KOH, or flood-light-exposure and developing. Next, using Au layers 46 and 44 as a mask, the wafer is placed in an appropriate selective etchant which only etches the Cr or Ti layer 42 but does not attack the Au mask. Alternatively, if the photoresist is compatible with the etchant, it may be left in place during the etching of layer 42 and then removed. An appropriate etchant for Cr in layer 42 consists of a basic potassium ferricyanide:

Potassium Hydroxide	KOH	50 g/l
Potassium Ferricyanide	$K_3Fe(CN)_6$	200 g/l

This etchant is basic and, therefore, the (positive) photoresist mask is incompatible with it and must be removed prior to the etching. Using this etchant, it takes less than 1 minute to etch a Cr layer with thickness of 30nm at room temperature. This etchant may also be applied by immersion or by spraying. The wafer is now ready for the deep alumina etch.

Fig. 3(c) shows the stage after etch-transfer through all the metallic layers and removal of the photoresist mask.

Fig. 3(d) shows the structure after partial etching through the thick alumina layer. An excellent etchant for alumina layer 40 is based on dilute (1:2) HF in water:


Hydrofluoric Acid (48%)	HF	1 volume
Water	H_2O	2 volumes

This corresponds to an HF concentration by weight of 16%. The etchant is used by dipping with moderate agitation or by spraying. At room temperature the etch rate is about $1.0 \mu\text{m}/\text{min}$. The etch rate is dependent on the quality, density, and integrity of the alumina layer. It is a function of sputter deposition parameters such as the substrate



temperature, bias, gas pressure, power, and deposition rate. It is strongly affected by the local micro-topography and related alumina integrity. The etch rate of alumina of poor integrity in the vicinity of elevated features can be an order of magnitude faster than over a flat surface, far from the elevated features. Using the dilute HF (1:2) etchant, it was found that the etch rate across the wafer was highly uniform; $\sigma \leq 1\%$. This unusual etch uniformity is likely due to an interfacial kinetic control, as opposed to the more common mass transport control in most etching processes. The latter are sensitive to the degree of agitation, resulting in faster etching near edges and corners due to more vigorous agitation there. The interfacial reaction controlling the etching of alumina by dilute HF may involve the breaking of Al-O bonds in order to form soluble fluoride complex ions. The etch rate increases by raising the temperature or by using higher HF concentration. As the HF concentration decreases, the reaction becomes less interfacial kinetic controlled and more mass transport controlled. The operating temperature range can be 10-90°C, and preferably room temperature, for convenience. The etchant comprises HF and water in concentration range 10-100% v/v of concentrated (48%) HF, and preferably in the range 20-50% v/v of concentrated (48%) HF in water. The latter corresponds to a volume ratio range of 1:4 - 1:1 of (48%) HF and water and to a HF concentration in the range of 10% to 25% by weight. Other chemicals, such as alcohols or ethylene glycol, may also be added to or substituted for the water.

Figs. 3(e) and 3(f) show the structure after completing the etching through the thick alumina layer 40 and after removal of the metallic mask layers, respectively. The Au bonding pad 38 serves as an etch stopper. The metallic mask layers are removed, in a reverse order of their deposition, by successive immersion or spraying first in a gold etchant (for layers 46 and 44) and then in a Cr (or Ti) etchant (for layer 42). Preferably, the metallic mask layers can be removed by sputter-etching or ion-milling. These etching techniques will also etch a similar thickness of the Au pad 38. As Au pad 38 is much thicker than the mask layers, the slight decrease in its thickness is



usually not significant. Also, the initial thickness of pad 38 can be adjusted to compensate for this loss. Alternatively, a wet lift-off technique can be used, such as etching Cr layer 42 with an etchant based on acidic ceric ammonium sulphate (or nitrate) which rapidly attacks the bond between Cr layer 42 and alumina layer 40. This will cause the lift-off of the Au mask layers 44 and 46. An example of such an etchant is CR-14 manufactured by Cyantek Chemicals of Fremont, California.

An alternative method to prevent etching of the Au pad 38 is to deposit and pattern an intermediate protective layer 38A of Cr (or Ti), as shown in Fig.3(g), on top of the Au pad 38A, prior to the deposition of alumina layer 40. The thickness of protective layer 38A is similar to that of layer 42 (about 10-30nm for Cr or Ti). The intermediate layer 38A protects Au pad 38 during the wet etching of Au layers 46 and 44. Protective layer 38A offers the additional benefit of improved adhesion to the thick alumina layer 40. It is then removed from the via area during the wet etching of Cr (or Ti) layer 42, exposing Au pad 38 for subsequent bonding, as shown in Fig. 3(h). Protective layer 38A may also comprise a different metal or alloy than layer 42, such as plated or sputtered Ni-Fe. It can be etched by an appropriate selective etchant prior to or following the removal of layer 42. For example, layer 38A may consist of a 50-200nm thick Ni-Fe layer plated immediately after the simultaneous plating of Au pad 38, using the same photoresist plating mask or another mask (exposing only the pad area). A selective etchant for this layer comprises nitric acid, phosphoric acid, and water in a volume ratio of 1:1:8, as described in U.S. Patent No. 5,059,278.

As a part of the packaging process, after the wafer has been diced, a wire is bonded to Au bonding pad 38, typically by known thermocompression or ultrasonic compression techniques. A firm mechanical bond is then formed by surrounding the wire-pad bond with epoxy. The epoxy should preferably fill the via to the bonding pad so as to create an extremely strong mechanical bond between the wire and the TFH.

Alumina integrity in the region around the bonding pad vias is not impaired by the etching action. It is similar to regions of the alumina layer removed from the vias,



since it was not deposited over elevated features. Furthermore, due to the elimination of the studs the required alumina overcoat thickness is significantly reduced. It incorporates less (integrated) stress, resulting in less chipping during machining, testing, and service, and the noise level is lowered. Further benefits of the reduced alumina overcoat thickness include improved yields and reliability and significantly higher throughput and lower cost.

Fig. 4 shows a scribe-line groove etched through the combined alumina layers of overcoat 40, gap 13, and undercoat 12 using similar methods of etching through thick alumina, as described above. In this case the substrate 10 (usually comprising Al_2O_3 -TiC) serves as the etch stopper. Removal of the sputter-deposited alumina in the wafer's streets and alleys grooves facilitates significant reduction of alumina chipping during the slider sawing and machining. The saw blade can be aligned precisely inside the grooves, without having to cut through the alumina layers, thereby maintaining alumina integrity and eliminating its chipping due to mechanical stress and damage. The etched scribe-line grooves also assist less wobble of the saw blade, preserving narrow cut lines and minimising kerf. The scribe-line grooves can be etched during the same operation of etching the bonding pad vias, as described above. However, the combined groove and pad via mask pattern must be properly designed with smaller pad via openings to compensate for the lateral expansion during the extra etching time of the gap and undercoat layers. The combined etching of the bonding pad vias and scribe-lines has the further benefits of significantly reduced alumina overcoat layer thickness, shorter etch time, better resolution, improved alumina integrity (lower integrated stress and elimination of elevated features), improved yields and reliability, higher throughput, and lower cost.

Fig. 5 shows a recessed crater formed in the alumina undercoat layer 12, using methods of etching through thick alumina similar to those described above. The crater depth can be controlled by removing the wafer from the etchant at any time before undercoat 12 has been etched through, or by placing an etch-stopper layer at the



required depth. The etch-stopper may comprise a pore-free compatible metallic layer, cured photoresist layer, or the substrate itself. Due to the very uniform etch rate across the wafer, the craters are of very uniform depth. Alumina integrity in the vicinity and around the craters is not impaired by the etching action. It is similar to the bulk of the alumina layer far removed from the craters. Such craters can be used to fabricate in them at least a portion of the bottom magnetic pole, for example, in order to improve total device planarity and symmetry. Other device features or layers can also be fabricated inside such craters. These may include at least portions of the gap, one or more levels of insulation and/or coil layers or the metallic bonding pads.

Lightning arresters can be constructed by etching vias through the alumina undercoat to expose the substrate and then electrically connecting the magnetic core to the substrate. Electrical connection between the magnetic core and the substrate is established by depositing and patterning a metallic layer through the vias following the alumina vias etching. Alternatively, a metallic layer may be deposited and patterned over the substrate prior to the deposition of the alumina undercoat. This metallic layer serves as the etch-stopper during the etching of the alumina vias. The metallic layer is connected through the vias to the magnetic core following the etching of the alumina vias, to ensure good electrical contact between the magnetic core and the lightning arrester. Grounding the magnetic core electrically prevents arcing between the head and a rotating disk. The magnetic core is grounded by connecting it to the grounded substrate. The lightning arrester can be deposited and patterned either as part of the deposition of one of the magnetic poles, or it can be constructed as a separate layer preceding or following the deposition of either the bottom or the top magnetic pole.

EXAMPLES

Example 1.

Bonding pad vias were etched through the alumina overcoat using a metallic etch mask similar to the one shown in Fig. 3(a). The Au pad 38 was $3.2\mu\text{m}$ thick and the



alumina overcoat 40 was about $35\mu\text{m}$ thick. A 30nm thick Cr seed-layer 42 was sputter deposited over the alumina layer 40. This was immediately followed by sputtering a 100nm thick Au seed-layer 44. The wafer was then placed in a high purity "soft" gold plating bath (PAG 401, by Sel Rex) and was plated with a 500nm thick gold layer 46. A positive photoresist layer 48 was then coated, exposed and patterned with the pad areas opened, by a regular photolithographic process. The wafer was then placed in a gold etchant comprising KI (200 g/l), I_2 (50 g/l), and pure water. Etching was done at room temperature by immersion with moderate agitation. Inspection after 60 seconds etching revealed that the gold was cleared in the via areas, as shown in Fig. 3(b). An extra etching time of 30 seconds was used to ensure complete Au etching everywhere. Photoresist mask 48 was then removed using successive immersions in hot and cold acetone with moderate agitation. The thickness of the Au layer across the wafer was measured with a Dektak surface profilometer. Next, the Cr seed-layer 42 was pattern-etched using the gold layers 44 and 46 as etch mask. The etchant comprised KOH (50 g/l), $\text{K}_3\text{Fe}(\text{CN})_6$ (200 g/l), and pure water. Etching was carried out by immersion with moderate agitation at room temperature. Inspection after 35 seconds of etching revealed that the Cr was cleared in the via areas, as shown in Fig. 3(c). An extra etching time of 90 seconds was used to ensure complete etching. This completed the pattern transfer to the metal mask. The wafer was then immersed with moderate agitation in dilute HF (1:2) in water at room temperature to etch the alumina layer 40. Etching was interrupted after a partial etching of 30 minutes, as shown in Fig. 3(d). The partially etched alumina step height was measured across the wafer (in exactly the same spots as after the Au mask etching) with a Dektak surface profilometer. The total step variation from the centre ($29.49\mu\text{m}$) to the edge of the wafer ($29.69\mu\text{m}$) was only $0.20\mu\text{m}$, corresponding to $\sigma = 0.48\%$. Alumina etching was then resumed for another 7 minutes. At that time, the Au pad 38 was exposed, as shown in Fig. 3(e). Next the Au mask layers 46 and 44 were removed by etching in the iodine/iodide Au etchant for 60 seconds. The wafer was then rinsed and placed in the Cr etchant for 2.0 minutes to



remove the Cr seed-layer 42. This completed the pattern-etching of deep vias through the alumina overcoat to the gold bonding pad, as shown in Fig. 3(f). No pin-holes or other defects were seen in the protected areas, and line definition was excellent.

Example 2.

The configuration and etching procedures were used as in Example 1, except that the plated Au layer 46 was only about $0.2\mu\text{m}$ thick. Also, a single sputter-etching step was used to remove all the metallic mask layers after completion of the alumina etching. Again, even with the thinner Au mask layer, no pin-holes or other defects were observed in the protected areas and line definition was excellent.

The wafers of Examples 1 and 2 were tested for bonding strength. Gold plated Cu wires were bonded through the alumina vias to the gold pads. Bonding tool alignment (to the pads) and whipping were greatly eased by the vias. The bonding strength of these studless devices was compared by a pull-test against regularly fabricated devices with thick copper studs. The studless devices exhibited excellent bonding strength, over 65 grams force in the pull-test. In all tests of the studless devices the applied force was either the maximum deliverable by the tester, or failures were attributable to wire breaking. For comparison, the regular devices with studs exhibited failures at about 28-35 grams force, with failures often due to bond breaking.

Example 3.

Scribe-line grooves were etched through the alumina overcoat, gap, and undercoat layers using a metallic etch mask similar to that used in Examples 1 and 2, but with a sputtered 100nm thick Ni-Fe seed-layer (44 in Fig. 3(a)) instead of an Au seed-layer. Also, the substrate 10 itself served as the alumina etch stopper, see Fig. 4. The thickness of the combined alumina layers was about $55\mu\text{m}$, and the plated Au layer 46 was about 500nm thick. Following the pattern etch of the Au layer 46 (as in Examples 1 and 2), the Ni-Fe seed-layer was pattern-etched by an etchant comprising 1



volume of (concentrated) nitric acid, 1 volume of (concentrated) phosphoric acid, and 8 volumes of pure water, as described in U.S. Patent No. 5,059,278. Etching was done by immersion with moderate agitation and at room temperature. Etching duration was 4.0 minutes to ensure complete clearing of the Ni-Fe in the groove areas. The photoresist mask 48 was then removed by dipping in a 5% (w/o) KOH solution in water, at room temperature and with moderate agitation. Next the Cr seed-layer 42 was pattern-etched as in Examples 1 and 2. The thickness of the combined metallic mask layers was then measured across the wafer by a Dektak profilometer. The combined alumina layers were then etched in the dilute HF (1:2) etchant, similar to Examples 1 and 2. Alumina etching was interrupted after 50 minutes, and the step height was measured by a Dektak profilometer across the wafer (in exactly the same spots as after the etching of the Cr mask layer). The total step variation from the centre of the wafer ($49.59\mu\text{m}$) to the edge of the wafer ($49.98\mu\text{m}$) was only $0.40\mu\text{m}$, corresponding to $\sigma = 0.55\%$. The wafer was then replaced in the alumina etchant for 5 more minutes and the step height measured again in the same locations. This time the centre measured $52.45\mu\text{m}$, but the edge measured $55.30\mu\text{m}$; the variation being $2.85\mu\text{m}$. The large variation this time was due to non-uniform thickness of the alumina layers. Etching was complete through the alumina thickness in the centre, but was not complete near the edge of the wafer due to thicker alumina there. This was further verified by resuming the alumina etching for another 5 minutes (for a total of 60 minutes). This time the total variation from the centre ($52.45\mu\text{m}$) to the edge of the wafer ($56.31\mu\text{m}$) was $3.86\mu\text{m}$ ($\sigma = 5.02\%$). There was no increase in the step height in the centre and only a small increase near the edge, indicating that etching was almost complete after 55 minutes. In a microscopic inspection it was also noticed that after 55 minutes of etching, areas near the wafer edge showed rainbow interference colours. These did not appear at the centre of the wafers. The rainbow colours are indicative of the presence of some alumina residue of varying thickness. The rainbow interference colours disappeared from areas near the edge after 60 minutes etch. The deep alumina etching technique, combined



with step height measurements, provides a convenient and precise method for evaluating the thickness of the alumina layers across a wafer. The metallic mask layers were then removed by sputter etching. Once again, no pin-holes or other defects were detected and line definition was excellent. This is remarkable, considering that the thickness of the etched alumina layer was about $55\mu\text{m}$.

The wafer with the etched streets and alleys scribe-line grooves was sawed and machined into regular rows and sliders using the grooves as guides for the saw blade. Alumina chipping was compared against regular wafers without the scribe-line grooves. The latter showed significantly more alumina chipping than the first. The wafer with the etched alumina grooves displayed clean cuts with no detectable alumina chipping.

Example 4.

Several other combinations of metallic layers, already in use in the manufacture of thin film heads, were tried as masks for etching thick alumina layers. They included the following:

- (a) A 30nm thick single sputtered Cr layer: [Cr(sp)].
- (b) A 200nm thick single sputtered Ni-Fe layer: [Ni-Fe(sp)].
- (c) A sputtered 200nm thick Ni-Fe layer over a 30nm thick sputtered Cr layer: [Ni-Fe(sp)/Cr(sp)].
- (d) A plated $1.0\mu\text{m}$ thick Ni-Fe layer over a 100nm thick sputtered Ni-Fe layer: [Ni-Fe(pl)/Ni-Fe(sp)].
- (e) A sputtered 200nm thick Cu layer over a 30nm thick sputtered Cr layer: [Cu(sp)/Cr(sp)].
- (f) A sputtered 200nm thick Cu layer over a 100nm thick sputtered Ni-Fe layer: [Cu(sp)/Ni-Fe(sp)].
- (g) A plated $1.0\mu\text{m}$ thick Cu layer over a 100nm thick Cu sputtered layer over a 30nm thick sputtered Cr layer: [Cu(pl)/Cu(sp)/Cr(sp)].

In all of these experiments the metallic masks provided only a limited protection and



only for short exposure times. Although Cr and Ni-Fe layers by themselves are not attacked or etched by the dilute HF etchant, they are porous. As a result, with time, the etchant penetrates through pin-hole pores in the mask, gradually increasing the pin-hole size and attacking the alumina underneath. The worst case was the single Cr mask of experiment (a). Visible holes could be seen (under the microscope) after only a few minutes of exposure to the dilute (1:2) HF etchant. They increased in size with exposure time. After a 10 minutes exposure with this mask, defective areas with large holes covered about 30-50% of the protected masked areas. The wafer looked like Swiss cheese. The porosity of these metallic layers decreased as their thickness increased. The masks of experiments (b), (c), and (d) provided increasing protection, in this order. However, even a plated $1.0\mu\text{m}$ thick Ni-Fe layer was not completely free of pores. Pin-holes were already detected on the mask of (d) after about 30 minutes of etching, and their size was significant after 50 minutes of etching. The Cu layers usually include fewer pores than the Cr or Ni-Fe layers, but they are slowly attacked (or etched) by the HF (1:2) etchant. The mask of experiment (g) provided adequate protection for up to about 35 minutes in the dilute HF (1:2) etchant.


While the invention has been particularly described with reference to preferred embodiments, it will be understood by those skilled in the art that various changes in form and detail may be made therein without departing from the scope of the present invention. Accordingly, examples herein disclosed are to be considered merely as illustrative and the invention to be limited only as specified in the claims.



CLAIMS

1. A process of etching alumina comprising the step of exposing the alumina to an etchant comprising a mixture of HF and water, wherein the concentration of HF is in the range of 10% to 25% by weight.
2. A process for pattern-etching an alumina layer, including the steps of: depositing an alumina layer; depositing over the alumina layer an adhesion metallic layer; depositing over the adhesion metallic layer at least one additional metallic layer including a top metallic layer; forming a photoresist mask pattern over the top metallic layer; pattern-etching the top metallic layer through the photoresist mask; pattern-etching through the top metallic layer, in reverse order of deposition, the other metallic layer or layers; pattern-etching the alumina layer with an alumina etchant comprising HF through the metallic layers; and removing the metallic layers.
3. A process as claimed in claim 2, in which the alumina etchant comprises a solution of HF in water in the range of 10% to 25% by weight.
4. A process for forming a studless TFH device including the process of any one of claims 1, 2 or 3 wherein the alumina layer is an overcoat layer and further including the step of depositing and patterning bonding pads prior to the step of depositing the alumina layer, and wherein the step of etching the alumina layer comprises forming vias to the bonding pads.
5. A process as claimed in claim 4, in which the step of depositing and patterning the bonding pads comprises the step of simultaneously depositing and patterning both the coil and the bonding pads, the coil and the bonding pads comprising the same metal.





6. A process as claimed in claim 5, in which the step of depositing and patterning the bonding pads includes the steps of: depositing a metallic seed-layer selected from the group consisting of Ni-Fe, W, Mo, Ni-Co, Ni-Co-Fe, Cd, In, and alloys comprising one or more of these metals; forming a photoresist mask incorporating patterns for the coil and the bonding pads; plating through the photoresist mask a metal bonding pad layer selected from the group consisting of Au, Cu, Ag, Pd, Pt, Rh, Ir, and alloys comprising one or more elements thereof; removing the photoresist mask; and etching the metallic seed-layer from areas between the plated pattern of the metal bonding pad layer.

7. A process as claimed in claim 5, in which the step of depositing and patterning the bonding pads includes the steps of: depositing a metallic seed-layer selected from the group consisting of Ni-Fe, W, Mo, Ni-Co, Ni-Co-Fe, Cd, In, and alloys comprising one or more of these metals; depositing by plating or by a vacuum technique a metal bonding pad layer selected from the group consisting of Au, Cu, Ag, Pd, Pt, Rh, Ir, and alloys comprising one or more elements thereof; forming an etch mask incorporating patterns for the coil and the pads over the bonding pad layer; pattern-etching the bonding pad layer and the metallic seed-layer through the etch mask by ion-milling or by reactive ion etching (RIE); and removing the remains of the etch mask.

8. A process as claimed in claim 6 or 7, in which the metallic seed-layer comprises Ni-Fe or W and the bonding pad layer comprises Au.

9. A process as claimed in any one of claims 6 to 8, in which the step of depositing a metallic seed-layer comprises the steps of depositing a first adhesion metallic seed-layer selected from the group consisting of Cr, Ti, W, Mo, Nb, V, Zr, Hf, and alloys comprising one or more of these elements, and depositing a second metallic seed-layer





selected from the group consisting of Au, Ni-Fe, W, Mo, Cu, Ag, Pd, Pt, Rh, Ir, and alloys comprising one or more of these metals following the step of depositing the first adhesion metallic seed-layer.

10. A process as claimed in claim 9 in which the first adhesion metallic seed-layer comprises Cr or Ti and the second metallic seed-layer comprises Au.

11. A process as claimed in any one of claims 4 to 10, further including etching scribe-line grooves through the alumina overcoat and an alumina undercoat in the TFH device.

12. A process as claimed in any one of claims 4 to 11, further including etching a crater for a recessed structure in the alumina layer in the TFH device wherein the depth of the crater is controlled by interrupting the etching action after a predetermined period of time.

13. A process as claimed in any one of claims 4 to 12, further including constructing lightning arresters in the TFH device by etching vias through an alumina undercoat for connecting a magnetic core with a substrate, wherein the vias are etched through the alumina undercoat to expose the substrate and including the further step of electrically connecting the magnetic core to the substrate through the vias.


14. A studless thin film head (TFH) device comprising: a substrate; a coil; a metallic bonding pad layer; an alumina overcoat; vias extending through the alumina overcoat to the bonding pad layer; and wires bonded to the bonding pad layer through the vias, wherein the integrity of the alumina overcoat in areas adjacent the vias is substantially the same as the integrity of the alumina overcoat in areas removed from the vias.





15. A TFH device having one or more alumina layers and fabricated with scribe-line grooves etched through the alumina layers.
16. A studless TFH device as in claim 14 further comprising an alumina undercoat and having scribe-line grooves extending through the alumina overcoat and the alumina undercoat to the substrate.
17. A TFH device comprising at least one feature or layer thereof placed in a crater etched in an alumina layer.
18. A TFH device comprising a lightning arrester electrically connecting a magnetic core to a substrate through a via extending through at least one alumina layer.





ABSTRACT

STUDLESS THIN FILM MAGNETIC HEAD
AND PROCESS FOR MAKING THE SAME

A method for pattern-etching thick alumina layers is disclosed, typically for use in the manufacture of thin film heads (TFH) by using compatible metallic mask layers (42, 44, 46) and a dilute (1:2) HF in water etchant. The deep alumina etching facilitates a studless TFH device where the coil and bonding pads (38) are deposited and patterned simultaneously, and vias are later etched through the alumina overcoat layer (40) to expose the bonding pads. The method also enables the etching of scribe-line grooves (13) of street and alleys across the wafer for sawing and machining of sliders. These grooves eliminate most alumina chipping due to stress and damage introduced by the sawing and machining operations. Similarly, pattern-etching of the alumina undercoat (12) facilitates the formation of precise craters for recessed structures. These can improve planarity and alleviate problems related to adverse topography and elevated features of TFH devices.

Fig. 3(a)

This Sheet Has Been Replaced




Figure 1.




Figure 2(a).





Figure 2(b).




Figure 3(a).





Figure 3(b).

This Sheet Has Been Replaced





Figure 3(c).

This Sheet Has Been Replaced




Figure 3(d).

This Sheet Has Been Replaced





Figure 3(e).

This Sheet Has Been Replaced





Figure 3(f).




Figure 3(g).




Figure 3(h).





Figure 4





Figure 5

REPLACEMENT SHEETS		SG
☒ Description	: paged 1.. to paged 21	
☒ Claim(s)	: paged 22 to paged 25	
☒ Drawing(s)	: paged 1.. to paged 13	
☒ Abstract	: paged 26 to paged	
DATE OF RECEIPT		08/10/96

1

STUDLESS THIN FILM MAGNETIC HEAD AND PROCESS FOR MAKING THE SAME

The present invention relates to magnetic thin film heads (TFH) for recording and reading magnetic transitions on a moving magnetic medium. It is applicable to either inductive or magnetoresistive (MR) elements.

In particular, the present invention relates to a method of etching deep vias through the thick alumina overcoat in order to expose underlying bonding pads, thereby completely eliminating fabrication of the studs (or bonding posts), a method of etching the undercoat to define scribe-line grooves of streets and alleys across the wafer for sawing (or dicing) and machining of the sliders, and a method of pattern-etching the alumina undercoat, prior to the wafer fabrication, to create precise craters for recessed structures or open vias to the substrate for lightning arresters.

Magnetic TFH transducers are known in the prior art. Please refer, for example, to U.S. Pat. Nos. 4,016,601; 4,190,872; 4,652,954; 4,791,719 for inductive devices and U.S. Pat. Nos. 4,190,871 and 4,315,291 for magnetoresistive (MR) devices.

In the operation of a typical inductive TFH device a moving magnetic storage medium is placed near the exposed pole-tips of the TFH transducer. During the read operation, the changing magnetic flux of the moving storage medium induces a changing magnetic flux upon the pole-tips and the gap between them. The magnetic flux is carried through the pole-tips and yoke core around spiralling conductor coil winding turns located between the yoke arms. The changing magnetic flux induces an electrical voltage across the conductor coil. The electrical voltage is representative of the magnetic pattern stored on the moving magnetic storage medium. During the write operation, an electrical current is caused to flow through the conductor coil. The

This is the replacement sheet
Date: 23 OCT 1996

current in the coil induces a magnetic field across the gap between pole-tips. A fringe field extends into the nearby moving magnetic storage medium, inducing (or writing) a magnetic domain (in the medium) in the same direction. Impressing current pulses of alternating polarity across the coil causes the writing of magnetic domains of alternating polarity in the storage medium.

Magnetoresistive (MR) TFH devices can only operate in the read mode. The electrical resistance of an MR element varies with its magnetisation orientation. Magnetic flux from the moving magnetic storage medium induces changes in this orientation. As a result, the resistance of the MR element to a sensing electric current changes accordingly. The varying voltage signal is representative of the magnetic pattern stored on the magnetic medium.

In the manufacturing of TFH transducers for magnetic recording, a large number of devices are fabricated simultaneously in deposited and patterned layers on a ceramic wafer. When completed, the wafer is cut (or diced) and machined into individual slider transducers. The main elements of a TFH inductive transducer, roughly in the order in which they are deposited, are the (alumina) undercoat, the bottom magnetic pole, the flux gap material to provide spacing between the bottom and top magnetic pole-tips, one or more levels of electrical conductive coil winding interposed within insulation layers, the top magnetic pole, elevated studs (or posts) for connecting the coil to bonding pads (above the overcoat), a thick (alumina) overcoat, and the bonding pads.

Usually the studs are made of about 25-50 μ m thick copper, plated through a thick photoresist mask right after the completion of the top magnetic pole and prior to the deposition of thick alumina overcoat. For reasons of uniformity and reproducibility, the studs are designed to extend to a level about 10 μ m above the highest spot of the TFH device (the back yoke of the top pole). For each coil level the stud thickness must be increased by at least 6-9 μ m. For similar reasons, the alumina overcoat thickness must exceed the stud thickness by about 10 μ m, requiring an overcoat about 35-60 μ m thick. Following the overcoat deposition, the studs are covered by the

alumina overcoat. The wafer is then lapped (ground) down to expose the copper studs. Next, (gold) bonding pads are fabricated over the alumina overcoat to contact the exposed studs. The pads are later used for bonding wires to external circuitry to the read/write channel.

Fabrication of studs and bonding pads is described in U.S. Pat. No. 4,219,853, for example. It is similar in both inductive and MR devices. For TFH devices combining an inductive write element and an MR read element, one on top of the other, the stud and alumina overcoat operations have to be repeated. This may bring the total thickness of the studs to about 40-70 μ m, and the total alumina overcoat thickness to about 50-80 μ m. As the alumina deposition process is relatively slow, about 1-2 μ m/hour, it can easily become the bottleneck (1-3 days) in the process flow. Furthermore, alumina sputtering equipment is very costly. As a result, the alumina overcoat deposition is by far the costliest and the slowest step in TFH wafer fabrication.

The integrity and chipping resistance of the alumina overcoat are directly related to its thickness and stress. The thicker the alumina layer, the more stress it incorporates. The alumina overcoat's stress also adversely affects the noise performance of the TFH device, since it is in direct contact with the top magnetic pole. Moreover, tall features of the device, such as the studs, impair the integrity of the deposited alumina in the local surrounding area. Sawing and machining operations subject the alumina overcoat to local stresses which often result in excessive chipping and rejects.

Very thick studs require a relatively long plating time and the thickness uniformity is quite difficult to control. To achieve the required thickness, stud plating dictates the use of a dry film photoresist which is difficult to strip and process. The usual fabrication of studs and bonding pads demands numerous steps of photomasking, deposition of seed-layers, plating, stripping, and etching. The elaborate structure of the studs and bonding pads, including coil leads, permalloy, and all the seed-layers, may involve some 10-15 individual metallic layers deposited in succession on top of each other. The probability of bonding failures due to inadequate adhesion between any two

This is the replacement sheet

Date: 23 OCT 1996



of these metallic layers is directly proportional to the number of these layers. Thus reliability of the bond strength is adversely affected by the large number of the metallic layers in the structure. The poor integrity of the alumina overcoat in the locales surrounding the studs further degrades the bond strength and often impairs the fabrication of bonding pads due to "loops" of collapsed alumina around the studs. The latter appear following the lapping of the alumina overcoat to expose the studs, and are due to the poor integrity of the alumina surrounding the studs.

Copper residues and contamination, originating from copper seed-layers used for the coil and stud platings, may cause shorts and impair the corrosion resistance of the TFH device. Copper coil seed-layer residues are often found to be responsible for intensified corrosion susceptibility of exposed pole-tips in the air bearing surface (ABS). This poor corrosion resistance is due to galvanic action between the two dissimilar metals (Cu and Ni-Fe) contacting at the corners (or wings) of the pole-tips. Similarly, the copper seed-layer of the studs is often found to degrade coil-to-core resistance due to full or partial shorts. The copper coil itself is sometimes subject to capricious variations of its electrical resistance due to corrosion and oxidation of the copper turns during elevated temperature curing cycles of the photoresist insulation layers.

The present invention provides an economical method for fast and precise patterning of thick sputter-deposited alumina layers by etching through appropriate metallic masks. It further provides improvements in product design and performance of magnetic heads which avoid the above-described shortcomings of the prior art. In particular, the precise patterning of thick alumina layers by etching enables the fabrication of studless TFH devices, scribe-line grooves for dicing, recessed craters for TFH devices, and lightning arresters.

Elimination of the studs simplifies the wafer fabrication in a very substantial way. It curtails about 20-30% of the total wafer processing steps and reduces the alumina overcoat thickness by about 30-50%. It thus produces the substantial benefits of reducing processing costs, decreasing device noise, and improving throughput,

This is the replacement sheet

Date:

23 OCT 1998

consistency, bonding strength, and corrosion resistance. Alumina chipping is usually a major contributor to yield loss. Etching scribe-line grooves facilitates significant reduction of alumina chipping during slider machining and later in tests and service. It thus significantly improves total device yields. Pattern-etching precise craters in the alumina undercoat facilitates the fabrication of TFH devices with recessed structures or features. These can improve device planarity and alleviate problems associated with tall features of multi-level coil designs. They can also improve the symmetry of pole-tips configuration. Similarly, etching vias through the alumina undercoat layer enables the construction of lightning arresters by electrically connecting the magnetic core to the substrate, which will be grounded in the process of packaging the slider. The lightning arresters provide grounding to prevent arcing between the magnetic core and rotating disk.

In accordance with the present invention, the patterning of thick sputter-deposited alumina layers is accomplished by, first, depositing compatible metallic layers on the alumina, coating the metallic layers with photoresist; patterning the photoresist by photolithography, etching the metallic layers (in sequence) through the photoresist mask, stripping the photoresist, etching the thick alumina layer through the metallic mask, and removing (in sequence) the metallic masking layers. A preferred etchant comprising dilute HF in water (1:2 by volume ratio) has been found to provide fast (about $1\mu\text{m}/\text{min}$), extraordinarily uniform (better than $\sigma = 1\%$ across a wafer), and accurate etching of thick alumina layers. The etching can be conveniently performed by spray or immersion. A compatible metallic mask must be used with the dilute HF etchant since photoresist masks lift-off from the alumina surface after a very short time. A preferred metallic mask comprises a very thin (10-30nm) Cr or Ti adhesion layer covered by a gold (Au) layer, about $0.3\text{-}0.5\mu\text{m}$ thick. To avoid porosity in the gold layer and for economic reasons, at least one half of the gold thickness can be plated from an high purity (99.9%) "soft" gold bath.

In accordance with the present invention a studless TFH device with gold coil

This is the replacement sheet

Date: 23 OCT 1996

and bonding pads, patterned and plated simultaneously, is provided. Following the alumina overcoat deposition, vias are etched through it to expose the bonding pads. This eliminates copper altogether from the TFH device, resulting in less maintenance and significantly improved reliability, corrosion resistance, and consistency of the coil resistance. Similarly, the thick alumina is pattern-etched to form scribe-line grooves which minimise alumina chipping during sawing and machining. Other improvements in a TFH device resulting from deep alumina pattern-etching include the formation of recessed craters to improve planarity and pole-tips symmetry and the formation of vias to the substrate for lightning arresters connecting the magnetic core to the substrate.

An object of the present invention is to provide a method of pattern-etching through an alumina layer.

Another object is to provide a studless TFH device.

A further object of the present invention is to provide a simple, fast, and low cost method to eliminate many processing steps and increase throughput in the process of fabricating a TFH device.

Embodiments of the present invention will now be described with reference to the accompanying drawings, of which:

Fig. 1 shows a cross-section of a typical prior-art stud and bonding pad structure;

Figs. 2(a) and 2(b) show cross-sections of alternative bonding pad structures embodying the present invention;

Figs. 3(a) to 3(h) are cross-sectional views, at various stages, during the patterning of thick alumina, such as used for the studless pads of the present invention;

Fig. 4 is a cross-sectional view of a scribe-line groove after pattern-etching; and

Fig. 5 is a cross-sectional view of a recessed crater after pattern-etching.

A schematic (not to scale) cross-section of a typical prior-art stud and bonding pad structure is shown in Fig. 1. An alumina undercoat 12 is first deposited over a ceramic substrate 10. The wafer is then subjected to the deposition and patterning of

This is the replacement sheet

Date: **23 OCT 1996**


many layers. A typical succession of the metallic layers in the stud area may include a Cr (or Ti) seed-layer 14, a Cu seed-layer 16, a first level plated Cu coil 18, a Cr (or Ti) seed-layer 20, a Cu seed-layer 22, a second level plated coil 24, a Ni-Fe seed-layer 26 for the top pole, a first plated Ni-Fe layer 28 of the top pole, a second plated Ni-Fe layer 30, a Cu seed-layer 32 for the stud, a plated Cu stud 34, alumina overcoat 35, a Ni-Fe seed-layer 36 for the bonding pad, and a gold bonding pad 38. A wire 39 is bonded to gold bonding pad 38, typically by thermocompression or ultrasonic compression techniques.

In some cases the stud structure may include other layers, such as a Ni-Fe seed-layer and plated layers of the bottom pole (between layers 12 and 14), or a Cr (or Ti) seed-layer under Cu seed-layer 32 for the stud, or under Ni-Fe seed-layer 36 for the bonding pad, or under Ni-Fe seed-layer 26 for the pole plating. In other cases, several of these layers are omitted. Typically the stud and bonding pad structure comprise about 10-15 individual metallic layers. In some cases, the bonding pad structure is placed on the alumina overcoat in a partial overlapping and staggering position relative to the stud structure. Bonding is made to the off-set portion of the pad to ensure adequate bonding strength. Such elaborate structures of the studs and bonding pads are susceptible to bonding failure due to the large number of metallic layers in the structure. In addition, the poor integrity of the alumina overcoat in the region surrounding the tall stud further impairs reliability and bonding strength.

According to a preferred embodiment of the present invention, the entire stud fabrication is eliminated, resulting in a simple bonding pad structure of only two metallic layers, shown in Fig. 2(a). A single seed-layer 36, such as Ni-Fe or W, is bonded to an alumina undercoat 12, which overlies a substrate 10. Seed layer 36 must be compatible for gold plating and must have good to moderate electrical conductivity and strong adhesion to alumina. Other metals and alloys suitable for this purpose include Mo, Ni-Co, Ni-Co-Fe, Cd, and In. The thickness of seed-layer 36 in Fig. 2(a) is in the range 60-200nm, and preferably in the range 100-150nm. This structure has

This is the replacement sheet

Date: 23 OCT 1998



only two metallic layers in the pad. An Au bonding pad 38 is preferably plated simultaneously with the coil turns and leads (not shown) through an appropriate photoresist mask. Both the coil and the bonding pads will then consist of the same (Au) metal.

If the coil consists of more than a single level, different pads may be deposited and patterned simultaneously with different coil levels. Alternatively, one or more pads may be deposited and patterned repeatedly with more than one coil level. Such pads, however, will have more metallic layers in their structure. Following the coil/pad plating and stripping of the photoresist mask, seed-layer 36 must be removed from between the Au-plated areas. Using a different metal or alloy for seed-layer 36 from that used for pad 38 enables its removal by selective chemical etching, as described in U.S. Patent No. 5,059,278 to Cohen et al., incorporated herein by reference. Wire 39 is bonded to the (Au) bonding pad 38 through the etched vias in the alumina overcoat 40.

In another embodiment, the pad structure comprises a total of three or more metallic layers, as shown in Fig. 2(b). The structure combines at least two seed-layers. The first seed-layer comprises an adhesion layer 14 of Cr or Ti or another refractory metal such as W, Ta, Mo, Nb, V, Zr, and Hf, or an alloy comprising one or more of these metals. The function of this layer is to enhance adhesion between alumina and the following gold layer (gold alone has poor affinity to oxygen and, therefore, poor adhesion to alumina). The thickness of the adhesion seed-layer 14 can be in the range 5-50nm, and preferably in the range 10-30nm. The layer is usually deposited by a vacuum technique such as sputtering or evaporation.

An Au seed-layer 37 is similarly deposited by sputtering or evaporation. It provides a low electrical resistance and compatible metallic surface for the plating of a gold pad 38. Other metals or alloys compatible with gold plating and having good electrical conductivity may also be used for the second metallic seed-layer 37. They include Ni-Fe, W, Mo, Cu, Ag, Pd, Pt, Rh, Ir, and alloys comprising one or more of

This is the replacement sheet

Date: 23 OCT 1996

these metals. In contrast, most refractory metals possess high electrical resistivity and are incompatible for gold plating. The thickness of the Au seed-layer 37 is in the range 50-300nm, and preferably in the range 70-100nm. Plated gold pad 38 has a thickness in the range 1.0-5.0 μ m, and preferably in the range 2.0-4.0 μ m. Again, the coil turns and leads and bonding pads may be plated simultaneously through a suitable photoresist mask. Alternatively, the coil may comprise gold or another highly conductive metal which is deposited and patterned separately from the bonding pad 38.

Other combinations may also be used. In particular, bonding pad 38 of Figs. 2(a) and 2(b) may comprise Au, Cu, Ag, Pd, Pt, Rh, Ir, and alloys comprising one or more elements thereof. Usually the same layer is also used for the coil winding turns. Alternatively, the coil turns may comprise a different metal or alloy than the pad. For example, the coil turns may comprise Cu, Ag, Pd, Pt, Rh, Ir, and alloys comprising one or more elements thereof, while the bonding pad may comprise gold. However, different metals or alloys in the coil and pads require further processing steps, which add to manufacturing complexity and cost. It may be noted that although Al has both excellent conductivity and adhesion to alumina, it is incompatible for plating (of the coil). It is thus unsuitable as a seed-layer for any plating. However, Al as a single layer may be used simultaneously for both the coil and the bonding pad, if deposited by a vacuum technique (such as sputtering or evaporation) and patterned by etching. Appropriate etching techniques for Al patterning include ion milling and reactive ion etching (RIE). Wet etching of Al lacks the fine resolution required for the coil definition. When Al is used in this mode, seed-layer 36 of Fig 2(a) and seed-layers 14 and 37 of Fig 2(b) are eliminated, resulting in an even simpler structure.

The noble metals Au, Cu, Ag, Pd, Pt, Rh, Ir, and alloys comprising one or more metals thereof may also be deposited as a continuous layer by plating or by a vacuum technique, and then pattern-etched simultaneously for both the coil turns and pads by ion milling or by RIE. The dry etching technique requires an appropriate etch mask combining both the coil and the pads patterns. It is formed over the top

This is the replacement sheet

Date: 23 OCT 1998

continuous metal layer. The remains of the etch mask are removed following the dry etching. Top layer noble metals require an intermediate adhesion layer similar to seed layer 36 in Fig. 2(a) and seed layer 14 in Fig. 2(b). Alternatively, the coil turns may comprise a different metal than the bonding pads and fabricated by different techniques. For example, the coil turns may comprise sputter or evaporation deposited Al and may be patterned by ion milling or RIE, while the bonding pads may consist of plated gold.

Patterning of thick alumina layers requires an etching mask which is substantially free of pores and not etched or adversely affected by the alumina etchant. When using dilute HF etchant for the alumina layer, etching masks based on photoresist alone are inadequate since they lift-off after only a short time in contact with the etchant. The dilute HF rapidly attacks the bond between the alumina and the photoresist. Metal masks must be used for the prolonged etching. The metal mask must have excellent adhesion to the alumina layer and it should be substantially free of pores. It must also be immune against attack by the etchant.

Figures 3(a) through 3(h) illustrate the major steps involved during the patterning of thick alumina, according to a preferred embodiment of this invention. Fig. 3(a) shows the structure after a photoresist layer 48 has been coated over the metallic mask layers and patterned by photolithography. Prior to coating the photoresist layer, successive seed-layers 42 of Cr or Ti and 44 of Au or Ni-Fe were deposited by a vacuum technique over a thick alumina layer 40. Seed-layer 42 must provide excellent adhesion to the alumina surface. It comprises a refractory metal from the group Cr, Ti, W, Ta, Mo, Nb, V, Zr, Hf, and alloys comprising one or more of these metals. The thickness of adhesion seed-layer 42 can be in the range 5-50nm, and preferably in the range 10-30nm. Since most refractory metals (such as Cr, Ti, Ta, Nb, V, Zr, and Hf) are incompatible for gold plating and have poor electrical conductivity, seed-layer 44, with good conductivity and compatibility for gold plating, is deposited over adhesion seed-layer 42. Gold is excellent for this purpose and is the preferred choice for seed-layer 44. However, it requires an expensive gold sputtering target. Alternatively, seed-

This is the replacement sheet

Date:

23 OCT 1995

layer 44 may comprise a metal from the group Ni-Fe, Ag, Pd, Pt, Rh, Ir, W, Mo, and alloys comprising one or more metals thereof. A single seed-layer 44 comprising Ni-Fe, W, Mo, or an alloy comprising one or more of these metals, possesses good adhesion and electrical conductivity and is compatible for gold plating. It can thus simplify the metallic mask by eliminating layer 42. The advantage of using Ni-Fe for seed-layer 44 is that it is already being utilised in the TFH fabrication process. The thickness of seed-layer 44 can be in the range 50-500nm, and preferably in the range 70-150nm. Usually vacuum deposition produces layers 42 and 44 which are quite porous and permeable and, therefore, inadequate for use alone as the metallic mask for thick alumina etching.

After deposition of layers 42 and 44, the wafer is placed in a high purity (99.9%) "soft" gold plating bath, and a layer 46 of gold is plated over seed-layer 44. To ensure that plated gold layer 46 be free of pores, its thickness should exceed about 0.1-0.2 μ m. Usually the thickness of layer 46 is in the range 0.1-1.0 μ m, and preferably in the range 0.2-0.5 μ m. Although it would be simpler to utilise Au seed-layer 44 alone, without the plated Au layer 46, sputter-deposited layers contain some pores even at thicknesses of more than 1.0 μ m. Furthermore, thick ($\geq 2\mu$ m) sputter-deposited Au layers significantly increase the manufacturing cost due to the very expensive gold targets. Photoresist mask layer 48 is coated over the metallic mask layers and patterned by a regular photolithography technique.

Next, the pattern is transferred to the metallic layers to form the etching mask. Fig. 3(b) shows the structure after pattern-etching gold layers 46 and 44 through the photoresist mask. A convenient etchant for the gold layers is based on a dilute solution of KI and I₂ in water:

Potassium Iodide	KI	100 - 200 g/l
Iodine	I ₂	25 - 50 g/l

This etchant is compatible with the positive photoresist mask. It takes about 1-2 minutes to etch Au layers 46 and 44 using this etchant at room temperature. It can be applied by immersion with moderate agitation, or by spraying. Lower concentrations

This is the replacement sheet

Date: 23 OCT 1996

and temperature decrease the etch rate, while higher concentrations and temperature increase it.

Following the pattern-etching of Au layers 46 and 44, the pattern has to be further transferred by etching the Cr or Ti adhesion layer 42. First the photoresist layer 48 is removed using a conventional stripping method, such as by dipping in or spraying with a commercial photoresist stripper, dilute KOH, or flood-light-exposure and developing. Next, using Au layers 46 and 44 as a mask, the wafer is placed in an appropriate selective etchant which only etches the Cr or Ti layer 42 but does not attack the Au mask. Alternatively, if the photoresist is compatible with the etchant, it may be left in place during the etching of layer 42 and then removed. An appropriate etchant for Cr in layer 42 consists of a basic potassium ferricyanide:

Potassium Hydroxide	KOH	50 g/l
Potassium Ferricyanide	$K_3Fe(CN)_6$	200 g/l

This etchant is basic and, therefore, the (positive) photoresist mask is incompatible with it and must be removed prior to the etching. Using this etchant, it takes less than 1 minute to etch a Cr layer with thickness of 30nm at room temperature. This etchant may also be applied by immersion or by spraying. The wafer is now ready for the deep alumina etch.

Fig. 3(c) shows the stage after etch-transfer through all the metallic layers and removal of the photoresist mask.

Fig. 3(d) shows the structure after partial etching through the thick alumina layer. An excellent etchant for alumina layer 40 is based on dilute (1:2) HF in water:

Hydrofluoric Acid (48%)	HF	1 volume
Water	H_2O	2 volumes

This corresponds to an HF concentration by weight of 16%. The etchant is used by dipping with moderate agitation or by spraying. At room temperature the etch rate is about 1.0 $\mu\text{m}/\text{min}$. The etch rate is dependent on the quality, density, and integrity of the alumina layer. It is a function of sputter deposition parameters such as the substrate

This is the replacement sheet

Date: 23 OCT 1986

temperature, bias, gas pressure, power, and deposition rate. It is strongly affected by the local micro-topography and related alumina integrity. The etch rate of alumina of poor integrity in the vicinity of elevated features can be an order of magnitude faster than over a flat surface, far from the elevated features. Using the dilute HF (1:2) etchant, it was found that the etch rate across the wafer was highly uniform; $\sigma \leq 1\%$. This unusual etch uniformity is likely due to an interfacial kinetic control, as opposed to the more common mass transport control in most etching processes. The latter are sensitive to the degree of agitation, resulting in faster etching near edges and corners due to more vigorous agitation there. The interfacial reaction controlling the etching of alumina by dilute HF may involve the breaking of Al-O bonds in order to form soluble fluoride complex ions. The etch rate increases by raising the temperature or by using higher HF concentration. As the HF concentration decreases, the reaction becomes less interfacial kinetic controlled and more mass transport controlled. The operating temperature range can be 10-90°C, and preferably room temperature, for convenience. The etchant comprises HF and water in concentration range 10-100% v/v of concentrated (48%) HF, and preferably in the range 20-50% v/v of concentrated (48%) HF in water. The latter corresponds to a volume ratio range of 1:4 - 1:1 of (48%) HF and water and to a HF concentration in the range of 10% to 25% by weight. Other chemicals, such as alcohols or ethylene glycol, may also be added to or substituted for the water.

Figs. 3(e) and 3(f) show the structure after completing the etching through the thick alumina layer 40 and after removal of the metallic mask layers, respectively. The Au bonding pad 38 serves as an etch stopper. The metallic mask layers are removed, in a reverse order of their deposition, by successive immersion or spraying first in a gold etchant (for layers 46 and 44) and then in a Cr (or Ti) etchant (for layer 42). Preferably, the metallic mask layers can be removed by sputter-etching or ion-milling. These etching techniques will also etch a similar thickness of the Au pad 38. As Au pad 38 is much thicker than the mask layers, the slight decrease in its thickness is

This is the replacement sheet

Date: **23 OCT 1996**

usually not significant. Also, the initial thickness of pad 38 can be adjusted to compensate for this loss. Alternatively, a wet lift-off technique can be used, such as etching Cr layer 42 with an etchant based on acidic ceric ammonium sulphate (or nitrate) which rapidly attacks the bond between Cr layer 42 and alumina layer 40. This will cause the lift-off of the Au mask layers 44 and 46. An example of such an etchant is CR-14 manufactured by Cyantek Chemicals of Fremont, California.

An alternative method to prevent etching of the Au pad 38 is to deposit and pattern an intermediate protective layer 38A of Cr (or Ti), as shown in Fig.3(g), on top of the Au pad 38A, prior to the deposition of alumina layer 40. The thickness of protective layer 38A is similar to that of layer 42 (about 10-30nm for Cr or Ti). The intermediate layer 38A protects Au pad 38 during the wet etching of Au layers 46 and 44. Protective layer 38A offers the additional benefit of improved adhesion to the thick alumina layer 40. It is then removed from the via area during the wet etching of Cr (or Ti) layer 42, exposing Au pad 38 for subsequent bonding, as shown in Fig. 3(h). Protective layer 38A may also comprise a different metal or alloy than layer 42, such as plated or sputtered Ni-Fe. It can be etched by an appropriate selective etchant prior to or following the removal of layer 42. For example, layer 38A may consist of a 50-200nm thick Ni-Fe layer plated immediately after the simultaneous plating of Au pad 38, using the same photoresist plating mask or another mask (exposing only the pad area). A selective etchant for this layer comprises nitric acid, phosphoric acid, and water in a volume ratio of 1:1:8, as described in U.S. Patent No. 5,059,278.

As a part of the packaging process, after the wafer has been diced, a wire is bonded to Au bonding pad 38, typically by known thermocompression or ultrasonic compression techniques. A firm mechanical bond is then formed by surrounding the wire-pad bond with epoxy. The epoxy should preferably fill the via to the bonding pad so as to create an extremely strong mechanical bond between the wire and the TFH.

Alumina integrity in the region around the bonding pad vias is not impaired by the etching action. It is similar to regions of the alumina layer removed from the vias,

This is the replacement sheet

Date: 23 OCT 1996

since it was not deposited over elevated features. Furthermore, due to the elimination of the studs the required alumina overcoat thickness is significantly reduced. It incorporates less (integrated) stress, resulting in less chipping during machining, testing, and service, and the noise level is lowered. Further benefits of the reduced alumina overcoat thickness include improved yields and reliability and significantly higher throughput and lower cost.

Fig. 4 shows a scribe-line groove etched through the combined alumina layers of overcoat 40, gap 13, and undercoat 12 using similar methods of etching through thick alumina, as described above. In this case the substrate 10 (usually comprising Al_2O_3 -TiC) serves as the etch stopper. Removal of the sputter-deposited alumina in the wafer's streets and alleys grooves facilitates significant reduction of alumina chipping during the slider sawing and machining. The saw blade can be aligned precisely inside the grooves, without having to cut through the alumina layers, thereby maintaining alumina integrity and eliminating its chipping due to mechanical stress and damage. The etched scribe-line grooves also assist less wobble of the saw blade, preserving narrow cut lines and minimising kerf. The scribe-line grooves can be etched during the same operation of etching the bonding pad vias, as described above. However, the combined groove and pad via mask pattern must be properly designed with smaller pad via openings to compensate for the lateral expansion during the extra etching time of the gap and undercoat layers. The combined etching of the bonding pad vias and scribe-lines has the further benefits of significantly reduced alumina overcoat layer thickness, shorter etch time, better resolution, improved alumina integrity (lower integrated stress and elimination of elevated features), improved yields and reliability, higher throughput, and lower cost.

Fig. 5 shows a recessed crater formed in the alumina undercoat layer 12, using methods of etching through thick alumina similar to those described above. The crater depth can be controlled by removing the wafer from the etchant at any time before undercoat 12 has been etched through, or by placing an etch-stopper layer at the

This is the replacement sheet

Date: 23 OCT 1996

required depth. The etch-stopper may comprise a pore-free compatible metallic layer, cured photoresist layer, or the substrate itself. Due to the very uniform etch rate across the wafer, the craters are of very uniform depth. Alumina integrity in the vicinity and around the craters is not impaired by the etching action. It is similar to the bulk of the alumina layer far removed from the craters. Such craters can be used to fabricate in them at least a portion of the bottom magnetic pole, for example, in order to improve total device planarity and symmetry. Other device features or layers can also be fabricated inside such craters. These may include at least portions of the gap, one or more levels of insulation and/or coil layers or the metallic bonding pads.

Lightning arresters can be constructed by etching vias through the alumina undercoat to expose the substrate and then electrically connecting the magnetic core to the substrate. Electrical connection between the magnetic core and the substrate is established by depositing and patterning a metallic layer through the vias following the alumina vias etching. Alternatively, a metallic layer may be deposited and patterned over the substrate prior to the deposition of the alumina undercoat. This metallic layer serves as the etch-stopper during the etching of the alumina vias. The metallic layer is connected through the vias to the magnetic core following the etching of the alumina vias, to ensure good electrical contact between the magnetic core and the lightning arrester. Grounding the magnetic core electrically prevents arcing between the head and a rotating disk. The magnetic core is grounded by connecting it to the grounded substrate. The lightning arrester can be deposited and patterned either as part of the deposition of one of the magnetic poles, or it can be constructed as a separate layer preceding or following the deposition of either the bottom or the top magnetic pole.

EXAMPLES

Example 1.

Bonding pad vias were etched through the alumina overcoat using a metallic etch mask similar to the one shown in Fig. 3(a). The Au pad 38 was $3.2\mu\text{m}$ thick and the

This is the replacement sheet

Date: 23 OCT 1996

alumina overcoat 40 was about $35\mu\text{m}$ thick. A 30nm thick Cr seed-layer 42 was sputter deposited over the alumina layer 40. This was immediately followed by sputtering a 100nm thick Au seed-layer 44. The wafer was then placed in a high purity "soft" gold plating bath (PAG 401, by Sel Rex) and was plated with a 500nm thick gold layer 46. A positive photoresist layer 48 was then coated, exposed and patterned with the pad areas opened, by a regular photolithographic process. The wafer was then placed in a gold etchant comprising KI (200 g/l), I_2 (50 g/l), and pure water. Etching was done at room temperature by immersion with moderate agitation. Inspection after 60 seconds etching revealed that the gold was cleared in the via areas, as shown in Fig. 3(b). An extra etching time of 30 seconds was used to ensure complete Au etching everywhere. Photoresist mask 48 was then removed using successive immersions in hot and cold acetone with moderate agitation. The thickness of the Au layer across the wafer was measured with a Dektak surface profilometer. Next, the Cr seed-layer 42 was pattern-etched using the gold layers 44 and 46 as etch mask. The etchant comprised KOH (50 g/l), $\text{K}_3\text{Fe}(\text{CN})_6$ (200 g/l), and pure water. Etching was carried out by immersion with moderate agitation at room temperature. Inspection after 35 seconds of etching revealed that the Cr was cleared in the via areas, as shown in Fig. 3(c). An extra etching time of 90 seconds was used to ensure complete etching. This completed the pattern transfer to the metal mask. The wafer was then immersed with moderate agitation in dilute HF (1:2) in water at room temperature to etch the alumina layer 40. Etching was interrupted after a partial etching of 30 minutes, as shown in Fig. 3(d). The partially etched alumina step height was measured across the wafer (in exactly the same spots as after the Au mask etching) with a Dektak surface profilometer. The total step variation from the centre ($29.49\mu\text{m}$) to the edge of the wafer ($29.69\mu\text{m}$) was only $0.20\mu\text{m}$, corresponding to $\sigma = 0.48\%$. Alumina etching was then resumed for another 7 minutes. At that time, the Au pad 38 was exposed, as shown in Fig. 3(e). Next the Au mask layers 46 and 44 were removed by etching in the iodine/iodide Au etchant for 60 seconds. The wafer was then rinsed and placed in the Cr etchant for 2.0 minutes to

This is the replacement sheet

Date: 23 OCT 1996

remove the Cr seed-layer 42. This completed the pattern-etching of deep vias through the alumina overcoat to the gold bonding pad, as shown in Fig. 3(f). No pin-holes or other defects were seen in the protected areas, and line definition was excellent.

Example 2.

The configuration and etching procedures were used as in Example 1, except that the plated Au layer 46 was only about $0.2\mu\text{m}$ thick. Also, a single sputter-etching step was used to remove all the metallic mask layers after completion of the alumina etching. Again, even with the thinner Au mask layer, no pin-holes or other defects were observed in the protected areas and line definition was excellent.

The wafers of Examples 1 and 2 were tested for bonding strength. Gold plated Cu wires were bonded through the alumina vias to the gold pads. Bonding tool alignment (to the pads) and whipping were greatly eased by the vias. The bonding strength of these studless devices was compared by a pull-test against regularly fabricated devices with thick copper studs. The studless devices exhibited excellent bonding strength, over 65 grams force in the pull-test. In all tests of the studless devices the applied force was either the maximum deliverable by the tester, or failures were attributable to wire breaking. For comparison, the regular devices with studs exhibited failures at about 28-35 grams force, with failures often due to bond breaking.

Example 3.

Scribe-line grooves were etched through the alumina overcoat, gap, and undercoat layers using a metallic etch mask similar to that used in Examples 1 and 2, but with a sputtered 100nm thick Ni-Fe seed-layer (44 in Fig. 3(a)) instead of an Au seed-layer. Also, the substrate 10 itself served as the alumina etch stopper, see Fig. 4. The thickness of the combined alumina layers was about $55\mu\text{m}$, and the plated Au layer 46 was about 500nm thick. Following the pattern etch of the Au layer 46 (as in Examples 1 and 2), the Ni-Fe seed-layer was pattern-etched by an etchant comprising 1

This is the replacement sheet

Date: 23 OCT 1996

volume of (concentrated) nitric acid, 1 volume of (concentrated) phosphoric acid, and 8 volumes of pure water, as described in U.S. Patent No. 5,059,278. Etching was done by immersion with moderate agitation and at room temperature. Etching duration was 4.0 minutes to ensure complete clearing of the Ni-Fe in the groove areas. The photoresist mask 48 was then removed by dipping in a 5% (w/o) KOH solution in water, at room temperature and with moderate agitation. Next the Cr seed-layer 42 was pattern-etched as in Examples 1 and 2. The thickness of the combined metallic mask layers was then measured across the wafer by a Dektak profilometer. The combined alumina layers were then etched in the dilute HF (1:2) etchant, similar to Examples 1 and 2. Alumina etching was interrupted after 50 minutes, and the step height was measured by a Dektak profilometer across the wafer (in exactly the same spots as after the etching of the Cr mask layer). The total step variation from the centre of the wafer ($49.59\mu\text{m}$) to the edge of the wafer ($49.98\mu\text{m}$) was only $0.40\mu\text{m}$, corresponding to $\sigma = 0.55\%$. The wafer was then replaced in the alumina etchant for 5 more minutes and the step height measured again in the same locations. This time the centre measured $52.45\mu\text{m}$, but the edge measured $55.30\mu\text{m}$; the variation being $2.85\mu\text{m}$. The large variation this time was due to non-uniform thickness of the alumina layers. Etching was complete through the alumina thickness in the centre, but was not complete near the edge of the wafer due to thicker alumina there. This was further verified by resuming the alumina etching for another 5 minutes (for a total of 60 minutes). This time the total variation from the centre ($52.45\mu\text{m}$) to the edge of the wafer ($56.31\mu\text{m}$) was $3.86\mu\text{m}$ ($\sigma = 5.02\%$). There was no increase in the step height in the centre and only a small increase near the edge, indicating that etching was almost complete after 55 minutes. In a microscopic inspection it was also noticed that after 55 minutes of etching, areas near the wafer edge showed rainbow interference colours. These did not appear at the centre of the wafers. The rainbow colours are indicative of the presence of some alumina residue of varying thickness. The rainbow interference colours disappeared from areas near the edge after 60 minutes etch. The deep alumina etching technique, combined

This is the replacement sheet

Date: **23 OCT 1996**

with step height measurements, provides a convenient and precise method for evaluating the thickness of the alumina layers across a wafer. The metallic mask layers were then removed by sputter etching. Once again, no pin-holes or other defects were detected and line definition was excellent. This is remarkable, considering that the thickness of the etched alumina layer was about $55\mu\text{m}$.

The wafer with the etched streets and alleys scribe-line grooves was sawed and machined into regular rows and sliders using the grooves as guides for the saw blade. Alumina chipping was compared against regular wafers without the scribe-line grooves. The latter showed significantly more alumina chipping than the first. The wafer with the etched alumina grooves displayed clean cuts with no detectable alumina chipping.

Example 4.


Several other combinations of metallic layers, already in use in the manufacture of thin film heads, were tried as masks for etching thick alumina layers. They included the following:

- (a) A 30nm thick single sputtered Cr layer: [Cr(sp)].
- (b) A 200nm thick single sputtered Ni-Fe layer: [Ni-Fe(sp)].
- (c) A sputtered 200nm thick Ni-Fe layer over a 30nm thick sputtered Cr layer: [Ni-Fe(sp)/Cr(sp)].
- (d) A plated $1.0\mu\text{m}$ thick Ni-Fe layer over a 100nm thick sputtered Ni-Fe layer: [Ni-Fe(pl)/Ni-Fe(sp)].
- (e) A sputtered 200nm thick Cu layer over a 30nm thick sputtered Cr layer: [Cu(sp)/Cr(sp)].
- (f) A sputtered 200nm thick Cu layer over a 100nm thick sputtered Ni-Fe layer: [Cu(sp)/Ni-Fe(sp)].
- (g) A plated $1.0\mu\text{m}$ thick Cu layer over a 100nm thick Cu sputtered layer over a 30nm thick sputtered Cr layer: [Cu(pl)/Cu(sp)/Cr(sp)].

In all of these experiments the metallic masks provided only a limited protection and

This is the replacement sheet

Date: **23 OCT 1996**




only for short exposure times. Although Cr and Ni-Fe layers by themselves are not attacked or etched by the dilute HF etchant, they are porous. As a result, with time, the etchant penetrates through pin-hole pores in the mask, gradually increasing the pin-hole size and attacking the alumina underneath. The worst case was the single Cr mask of experiment (a). Visible holes could be seen (under the microscope) after only a few minutes of exposure to the dilute (1:2) HF etchant. They increased in size with exposure time. After a 10 minutes exposure with this mask, defective areas with large holes covered about 30-50% of the protected masked areas. The wafer looked like Swiss cheese. The porosity of these metallic layers decreased as their thickness increased. The masks of experiments (b), (c), and (d) provided increasing protection, in this order. However, even a plated $1.0\mu\text{m}$ thick Ni-Fe layer was not completely free of pores. Pin-holes were already detected on the mask of (d) after about 30 minutes of etching, and their size was significant after 50 minutes of etching. The Cu layers usually include fewer pores than the Cr or Ni-Fe layers, but they are slowly attacked (or etched) by the HF (1:2) etchant. The mask of experiment (g) provided adequate protection for up to about 35 minutes in the dilute HF (1:2) etchant.

While the invention has been particularly described with reference to preferred embodiments, it will be understood by those skilled in the art that various changes in form and detail may be made therein without departing from the scope of the present invention. Accordingly, examples herein disclosed are to be considered merely as illustrative and the invention to be limited only as specified in the claims.

This is the replacement sheet

Date: **23 OCT 1986**

**CLAIMS**

1. A process of etching alumina comprising the step of exposing the alumina to an etchant comprising a mixture of HF and water, wherein the concentration of HF is in the range of 10% to 25% by weight.
2. A process for pattern-etching an alumina layer, including the steps of: depositing an alumina layer; depositing over the alumina layer an adhesion metallic layer; depositing over the adhesion metallic layer at least one additional metallic layer including a top metallic layer; forming a photoresist mask pattern over the top metallic layer; pattern-etching the top metallic layer through the photoresist mask; pattern-etching through the top metallic layer, in reverse order of deposition, the other metallic layer or layers; pattern-etching the alumina layer with an alumina etchant comprising HF through the metallic layers; and removing the metallic layers.
3. A process as claimed in claim 2, in which the alumina etchant comprises a solution of HF in water in the range of 10% to 25% by weight.
4. A process for forming a studless TFH device including the process of any one of claims 1, 2 or 3 wherein the alumina layer is an overcoat layer and further including the step of depositing and patterning bonding pads prior to the step of depositing the alumina layer, and wherein the step of etching the alumina layer comprises forming vias to the bonding pads.
5. A process as claimed in claim 4, in which the step of depositing and patterning the bonding pads comprises the step of simultaneously depositing and patterning both the coil and the bonding pads, the coil and the bonding pads comprising the same metal.



This is the replacement sheet

Date: 23 OCT 1996



THIS SHEET HAS BEEN
REPLACED

6. A process as claimed in claim 5, in which the step of depositing and patterning the bonding pads includes the steps of: depositing a metallic seed-layer selected from the group consisting of Ni-Fe, W, Mo, Ni-Co, Ni-Co-Fe, Cd, In, and alloys comprising one or more of these metals; forming a photoresist mask incorporating patterns for the coil and the bonding pads; plating through the photoresist mask a metal bonding pad layer selected from the group consisting of Au, Cu, Ag, Pd, Pt, Rh, Ir, and alloys comprising one or more elements thereof; removing the photoresist mask; and etching the metallic seed-layer from areas between the plated pattern of the metal bonding pad layer.

7. A process as claimed in claim 5, in which the step of depositing and patterning the bonding pads includes the steps of: depositing a metallic seed-layer selected from the group consisting of Ni-Fe, W, Mo, Ni-Co, Ni-Co-Fe, Cd, In, and alloys comprising one or more of these metals; depositing by plating or by a vacuum technique a metal bonding pad layer selected from the group consisting of Au, Cu, Ag, Pd, Pt, Rh, Ir, and alloys comprising one or more elements thereof; forming an etch mask incorporating patterns for the coil and the pads over the bonding pad layer; pattern-etching the bonding pad layer and the metallic seed-layer through the etch mask by ion-milling or by reactive ion etching (RIE); and removing the remains of the etch mask.

8. A process as claimed in claim 6 or 7, in which the metallic seed-layer comprises Ni-Fe or W and the bonding pad layer comprises Au.

9. A process as claimed in any one of claims 6 to 8, in which the step of depositing a metallic seed-layer comprises the steps of depositing a first adhesion metallic seed-layer selected from the group consisting of Cr, Ti, W, Mo, Nb, V, Zr, Hf, and alloys comprising one or more of these elements, and depositing a second metallic seed-layer

This is the replacement sheet

Date: 23 OCT 1996





THIS SHEET HAS BEEN
REPLACED

selected from the group consisting of Au, Ni-Fe, W, Mo, Cu, Ag, Pd, Pt, Rh, Ir, and alloys comprising one or more of these metals following the step of depositing the first adhesion metallic seed-layer.

10. A process as claimed in claim 9 in which the first adhesion metallic seed-layer comprises Cr or Ti and the second metallic seed-layer comprises Au.

11. A process as claimed in any one of claims 4 to 10, further including etching scribe-line grooves through the alumina overcoat and an alumina undercoat in the TFH device.

12. A process as claimed in any one of claims 4 to 11, further including etching a crater for a recessed structure in the alumina layer in the TFH device wherein the depth of the crater is controlled by interrupting the etching action after a predetermined period of time.

13. A process as claimed in any one of claims 4 to 12, further including constructing lightning arresters in the TFH device by etching vias through an alumina undercoat for connecting a magnetic core with a substrate, wherein the vias are etched through the alumina undercoat to expose the substrate and including the further step of electrically connecting the magnetic core to the substrate through the vias.

14. A studless thin film head (TFH) device comprising: a substrate; a coil; a metallic bonding pad layer; an alumina overcoat; vias extending through the alumina overcoat to the bonding pad layer; and wires bonded to the bonding pad layer through the vias, wherein the integrity of the alumina overcoat in areas adjacent the vias is substantially the same as the integrity of the alumina overcoat in areas removed from the vias.



This is the replacement sheet

Date: 23 OCT 1996



15. A TFH device having one or more alumina layers and fabricated with scribe-line grooves etched through the alumina layers.
16. A studless TFH device as in claim 14 further comprising an alumina undercoat and having scribe-line grooves extending through the alumina overcoat and the alumina undercoat to the substrate.
17. A TFH device comprising at least one feature or layer thereof placed in a crater etched in an alumina layer.
18. A TFH device comprising a lightning arrester electrically connecting a magnetic core to a substrate through a via extending through at least one alumina layer.



ABSTRACT**STUDLESS THIN FILM MAGNETIC HEAD
AND PROCESS FOR MAKING THE SAME**

A method for pattern-etching thick alumina layers is disclosed, typically for use in the manufacture of thin film heads (TFH) by using compatible metallic mask layers (42, 44, 46) and a dilute (1:2) HF in water etchant. The deep alumina etching facilitates a studless TFH device where the coil and bonding pads (38) are deposited and patterned simultaneously, and vias are later etched through the alumina overcoat layer (40) to expose the bonding pads. The method also enables the etching of scribe-line grooves (13) of street and alleys across the wafer for sawing and machining of sliders. These grooves eliminate most alumina chipping due to stress and damage introduced by the sawing and machining operations. Similarly, pattern-etching of the alumina undercoat (12) facilitates the formation of precise craters for recessed structures. These can improve planarity and alleviate problems related to adverse topography and elevated features of TFH devices.

Fig. 3 a

This is the replacement sheet

Date: 23 OCT 1986




Figure 1.

This is the replacement sheet

Date: 23 OCT 1996





Figure 2 a .

This is the replacement sheet

Date: 23 OCT 1996



This is the replacement sheet

Date: 23 OCT 1996

Figure 2 b .




Figure 3 a .

This is the replacement sheet

Date: **23 OCT 1996**




Figure 3 b .

This is the replacement sheet

Date: **23 OCT 1996**




Figure 3 c..

This is the replacement sheet
 Date: **23 OCT 1996**




Figure 3 d .

This is the replacement sheet

Date: **23 OCT 1996**




Figure 3 e .

This is the replacement sheet

Date: 23 OCT 1996




Figure 3 f .

This is the replacement sheet

Date: **23 OCT 1996**




Figure 3 g .

This is the replacement sheet

Date: **23 OCT 1996**




Figure 3'h .

This is the replacement sheet

Date: 23 OCT 1996





Figure 4

This is the replacement sheet


Date: 23 OCT 1988



This is the replacement sheet

Date: 23 OCT 1998


Figure 5



of these metallic layers is directly proportional to the number of these layers. Thus reliability of the bond strength is adversely affected by the large number of the metallic layers in the structure. The poor integrity of the alumina overcoat in the locales surrounding the studs further degrades the bond strength and often impairs the fabrication of bonding pads due to "loops" of collapsed alumina around the studs. The latter appear following the lapping of the alumina overcoat to expose the studs, and are due to the poor integrity of the alumina surrounding the studs.

Copper residues and contamination, originating from copper seed-layers used for the coil and stud platings, may cause shorts and impair the corrosion resistance of the TFH device. Copper coil seed-layer residues are often found to be responsible for intensified corrosion susceptibility of exposed pole-tips in the air bearing surface (ABS). This poor corrosion resistance is due to galvanic action between the two dissimilar metals (Cu and Ni-Fe) contacting at the corners (or wings) of the pole-tips. Similarly, the copper seed-layer of the studs is often found to degrade coil-to-core resistance due to full or partial shorts. The copper coil itself is sometimes subject to capricious variations of its electrical resistance due to corrosion and oxidation of the copper turns during elevated temperature curing cycles of the photoresist insulation layers.

US-A-5093173 discloses a magnetic disc with an improved substrate. IEEE transactions on magnetics, Vol. 25, No. 5, 1 September 1989, pages 3686 - 3688, JP-A-55030826 and JP-A-63029311 each disclose pattern etching of alumina by wet etching but none address the problems enumerated above.



4a

The present invention defines a process for pattern etching an alumina layer according to claim 1.

The present invention provides an economical method for fast and precise patterning of thick sputter-deposited alumina layers by etching through appropriate metallic masks. It further provides improvements in product design and performance of magnetic heads which avoid the above-described shortcomings of the prior art. In particular, the precise patterning of thick alumina layers by etching enables the fabrication of studless TFH devices, scribe-line grooves for dicing, recessed craters for TFH devices, and lightning arrestors.

Elimination of the studs simplifies the wafer fabrication in a very substantial way. It curtails about 20-30% of the total wafer processing steps and reduces the alumina overcoat thickness by about 30-50%. It thus produces the substantial benefits of reducing processing costs, decreasing device noise, and improving throughout,

only two metallic layers in the pad. An Au bonding pad 38 is preferably plated simultaneously with the coil turns and leads (not shown) through an appropriate photoresist mask. Both the coil and the bonding pads will then consist of the same (Au) metal.

If the coil consists of more than a single level, different pads may be deposited and patterned simultaneously with different coil levels. Alternatively, one or more pads may be deposited and patterned repeatedly with more than one coil level. Such pads, however, will have more metallic layers in their structure. Following the coil/pad plating and stripping of the photoresist mask, seed-layer 36 must be removed from between the Au-plated areas. Using a different metal or alloy for seed-layer 36 from that used for pad 38 enables its removal by selective chemical etching, as described in U.S. Patent No. 5,059,278 to Cohen et al..

Wire 39 is bonded to the (Au) bonding pad 38 through the etched vias in the alumina overcoat 40.

In another embodiment, the pad structure comprises a total of three or more metallic layers, as shown in Fig. 2(b). The structure combines at least two seed-layers. The first seed-layer comprises an adhesion layer 14 of Cr or Ti or another refractory metal such as W, Ta, Mo, Nb, V, Zr, and Hf, or an alloy comprising one or more of these metals. The function of this layer is to enhance adhesion between alumina and the following gold layer (gold alone has poor affinity to oxygen and, therefore, poor adhesion to alumina). The thickness of the adhesion seed-layer 14 can be in the range 5-50nm, and preferably in the range 10-30nm. The layer is usually deposited by a vacuum technique such as sputtering or evaporation.

An Au seed-layer 37 is similarly deposited by sputtering or evaporation. It provides a low electrical resistance and compatible metallic surface for the plating of a gold pad 38. Other metals or alloys compatible with gold plating and having good electrical conductivity may also be used for the second metallic seed-layer 37. They include Ni-Fe, W, Mo, Cu, Ag, Pd, Pt, Rh, Ir, and alloys comprising one or more of

This is the replacement sheet

Date: 06 AUG 1999

06 AUG 1999

only for short exposure times. Although Cr and Ni-Fe layers by themselves are not attacked or etched by the dilute HF etchant, they are porous. As a result, with time, the etchant penetrates through pin-hole pores in the mask, gradually increasing the pin-hole size and attacking the alumina underneath. The worst case was the single Cr mask of experiment (a). Visible holes could be seen (under the microscope) after only a few minutes of exposure to the dilute (1:2) HF etchant. They increased in size with exposure time. After a 10 minutes exposure with this mask, defective areas with large holes covered about 30-50% of the protected masked areas. The wafer looked like Swiss cheese. The porosity of these metallic layers decreased as their thickness increased. The masks of experiments (b), (c), and (d) provided increasing protection, in this order. However, even a plated 1.0 μ m thick Ni-Fe layer was not completely free of pores. Pin-holes were already detected on the mask of (d) after about 30 minutes of etching, and their size was significant after 50 minutes of etching. The Cu layers usually include fewer pores than the Cr or Ni-Fe layers, but they are slowly attacked (or etched) by the HF (1:2) etchant. The mask of experiment (g) provided adequate protection for up to about 35 minutes in the dilute HF (1:2) etchant.

While the invention has been particularly described with reference to preferred embodiments, it will be understood by those skilled in the art that various changes in form and detail may be made therein without departing from the scope of the present invention as defined by the appended claims. Accordingly, examples herein disclosed are to be considered merely as illustrative and the invention to be limited only as specified in the claims.




Claims:

1. A process for pattern etching an alumina layer comprising the steps of:
depositing an alumina layer (40);
depositing over the alumina layer a metallic mask (42,44,46) comprising at least one metallic layer;
forming a photoresist mask (48) having at least one opening over the metallic mask;
pattern etching at least one opening in the metallic mask to expose a surface of the alumina layer by etching at least one metallic layer through the at least one opening in the photoresist mask; and
pattern etching the alumina layer with a wet alumina etchant through the at least one opening of the metallic mask, wherein the metallic mask is not substantially etched by that etchant.
2. A process as claimed in claim 1, in which said wet etchant comprises HF.
3. A process as claimed in claim 2, in which said etchant comprises HF in water in the range of 10% to 25% by weight.
4. A process for forming a studless TFH device including the process of any one of claims 1, 2 or 3, wherein the alumina layer is an overcoat layer and further including the step of depositing and patterning bonding pads (38) prior to the step of depositing the alumina layer, and wherein the step of etching the alumina layer comprises forming vias to the bonding pads.
5. A process as claimed in claim 4, in which the step of depositing and patterning the bonding pads comprises the step of simultaneously depositing and patterning both the coil

This is the replacement sheet

Date: 06 AUG 1999




and the bonding pads, the coil and the bonding pads comprising the same metal.

6. A process as claimed in claim 4 or 5, in which the step of depositing and patterning the bonding pads includes the steps of: depositing a metallic seed-layer (36;14,37) selected from the group consisting of Ni-Fe, W, Mo, Ni-Co, Ni-Co-Fe, Cd, In, and alloys comprising one or more of these metals; forming a photoresist mask incorporating patterns for the bonding pads and coil; plating through the photoresist mask a metal bonding pad layer selected from the group consisting of Au, Cu, Ag, Pd, Pt, Rh, Ir, and alloys comprising one or more elements thereof; removing the photoresist mask; and etching the metallic seed-layer from areas between the plated pattern of the metal bonding pad layer.

7. A process as claimed in claim 5, in which the step of depositing and patterning the bonding pads includes the steps of: depositing a metallic seed-layer (36;14,37) selected from the group consisting of Ni-Fe, W, Mo, Ni-Co, Ni-Co-Fe, Cd, In, and alloys comprising one or more of these metals; depositing by plating or by a vacuum technique a metal bonding pad layer selected from the group consisting of Au, Cu, Ag, Pd, Pt, Rh, Ir, and alloys comprising one or more elements thereof; forming an etch mask incorporating patterns for the coil and the pads over the bonding pad layer; pattern-etching the bonding pad layer and the metallic seed-layer through the etch mask by ion-milling or by reactive ion etching (RIE); and removing the remains of the etch mask.

8. A process as claimed in claim 6 or 7, in which the metallic seed-layer comprises Ni-Fe or W and the bonding pad layer comprises Au.

9. A process as claimed in any one of claims 6 to 8, in which the step of depositing a metallic seed-layer comprises the steps of depositing a first adhesion metallic seed-layer



(14) selected from the group consisting of Cr, Ti, W, Ta, Mo, Nb, V, Zr, Hf, and alloys comprising one or more of these elements, and depositing a second metallic seed-layer (37) selected from the group consisting of Au, Ni-Fe, W, Mo, Cu, Ag, Pd, Pt, Rh, Ir, and alloys comprising one or more of these metals following the step of depositing the first adhesion metallic seed-layer.

10. A process as claimed in claim 9 in which the first adhesion metallic seed-layer comprises Cr or Ti and the second metallic seed-layer comprises Au.

11. A process as claimed in any one of claims 4 to 10, further including etching scribe-line grooves through the alumina overcoat and an alumina undercoat in the TFH device.

12. A process as claimed in any one of claims 4 to 11, further including etching a crater for a recessed structure in the alumina layer in the TFH device wherein the depth of the crater is controlled by interrupting the etching action after a predetermined period of time.

13. A process as claimed in any one of claims 4 to 12, further including constructing lightning arresters in the TFH device by etching vias through an alumina undercoat for connecting a magnetic core with a substrate, wherein the vias are etched through the alumina undercoat to expose the substrate and including the further step of electrically connecting the magnetic core to the substrate through the vias.

14. A studless thin film head (TFH) device comprising: a substrate (10); a coil; a metallic bonding pad layer (38); an alumina overcoat (40); vias extending through the alumina overcoat to the bonding pad layer; and wires (39) bonded to the bonding pad layer through the vias, wherein the vias are formed in the alumina overcoat in accordance



REPLACEMENT SHEET

06 AUG 1999

25

with the pattern etching process as claimed in any one of the preceding claims.

15. A studless TFH device as in claim 14 further comprising an alumina undercoat (12) and having scribe-line grooves extending through the alumina overcoat and the alumina undercoat to the substrate.

16. A TFH device having one or more alumina layers and fabricated with scribe-line grooves pattern etched through the alumina layers in accordance with the process as claimed in any one of claims 1 to 13.

17. A TFH device comprising at least one feature or layer thereof placed in a crater pattern etched in an alumina layer in accordance with any one of claims 1 to 13.

18. A TFH device comprising a lightning arrester electrically connecting a magnetic core to a substrate through a via extending through at least one alumina layer, wherein said via is formed by pattern etching in accordance with any one of claims 1 to 13.

19. A wafer having a substrate (10), at least one alumina layer (12, 40) and one or more thin film head (TFH) devices, said wafer having scribe line grooves extending through the at least one alumina layer to the substrate between the thin film head devices, said scribe line grooves being pattern etched in said alumina layer by a process according to any one of claims 1 to 13.