

METHOD OF MOUNTING CONDENSER MICROPHONE ON MAIN PCB AND CONDENSER MICROPHONE ADAPTED FOR THE SAME

5

BACKGROUND OF THE INVENTION

FIELD OF THE INVENTION

The present invention relates to a method of mounting a condenser microphone, and more particularly, to a method of mounting a condenser microphone on a main printed circuit board (PCB) and a condenser microphone adapted for the method.

10

DESCRIPTION OF THE PRIOR ART

15

Generally, customers have desires for high functionality and miniaturization of electronics products. Hence, manufacturers of electronic products are trying to make smaller products with all their heart in order to meet such desires. Surface mount technology (SMT) should be used to miniaturize products, but the SMT cannot be used to elements having a weak resistance against temperature because a high temperature is applied to the parts during reflow of surface mount device (SMD).

20

Additionally, when assuming that SMT is used, it is necessary to direct a front surface of the main PCB, on which elements are mounted, toward an inward direction of an electronic product during the mounting of the PCB considering thickness of the elements themselves.

25

However, in a conventional condenser microphone, it is difficult to mount a main PCB such that the front surface of the main PCB is directed toward an opposite direction of sound source, that is, such that the front surface is directed toward an inner space of a casing of the condenser microphone, because the casing has sound holes as shown in Figs. 1A and 1B. If the front surface of the main PCB is mounted in the opposite direction of the sound source, sound quality goes bad because delivery path of sound wave increases.

30

FIG. 1A is a perspective view of a conventional condenser microphone mounted on a main PCB, and FIG. 2B is a side sectional view of a conventional condenser

microphone mounted on a main PCB.

Referring to FIGS. 1A and 1B, a condenser microphone 10 includes a casing 12 having sound holes 12a. A PCB 14 of the condenser microphone 10 is mounted on a main PCB 20 and soldered such that connecting terminals 14a and 14b of the microphone 10 and bonded to a land of the main PCB 20. To allow sound waves to be directly transferred to the microphone 10 from a sound source, it is necessary to mount the main PCB 20 such that an element surface 20a of the main PCB 20 is directed toward the sound source. To meet such a need, a space as much as the thickness of the element is required. Non-described reference numeral 20b indicates an opposite surface to the element surface of the main PCB 20.

SUMMARY OF THE INVENTION

Accordingly, the present invention is directed to a method of mounting a condenser microphone on a main PCB and condenser microphone adapted for the same that substantially obviates one or more problems due to limitations and disadvantages of the related art.

An object of the present invention is to provide a method of mounting a condenser microphone on main PCB and condenser microphone for the same, in which a the condenser microphone of which sound holes are formed in a PCB of the condenser microphone instead of the casing of the condenser microphone, is mounted on a main PCB, and the main PCB is provided with a through hole so that the condenser microphone can be freely mounted on the main PCB.

Additional advantages, objects, and features of the invention will be set forth in part in the description which follows and in part will become apparent to those having ordinary skill in the art upon examination of the following or may be learned from practice of the invention. The objectives and other advantages of the invention may be realized and attained by the structure particularly pointed out in the written description and claims hereof as well as the appended drawings.

To achieve these objects and other advantages and in accordance with the purpose of the invention, as embodied and broadly described herein, there is provided a

method of mounting a condenser microphone on a main PCB. The method includes the steps of: assembling the condenser microphone by assembling elements of the condenser microphone such that a vibration plate including a couple of a diaphragm and a backplate is directed toward an opened surface of a casing of the condenser microphone, the casing having a closed bottom surface and an opened surface opposite
5 to the closed bottom surface, mounting a PCB having a sound hole on the casing and curling the opened surface of the casing such that a connecting terminal of the PCB is protruded compared to a curled surface; positioning the assembled condenser microphone on a main PCB such that the sound hole of the PCB of the condenser
10 microphone is in accordance with a through hole formed in the main PCB; and soldering the connecting terminal of the condenser microphone to a land of the main PCB.

According to another aspect of the present invention, there is provided a condenser microphone including: a barrel-shaped casing having a closed bottom surface and an opened opposite surface, the opened surface being curled; an insulation ring
15 inserted onto the casing, for protecting interior elements from external heat and providing an insulation function; a first metal ring disposed in the insulation ring and contacting the bottom surface of the casing; a backplate disposed in the insulation ring and contacting the first metal ring; a spacer disposed in the insulation ring and
20 contacting the backplate; a diaphragm inserted into the insulation ring to face the backplate, wherein the spacer is disposed between the diaphragm and the backplate; a polar ring disposed in the insulation ring, for supporting the diaphragm; a second metal ring disposed in the insulation ring, for supporting the polar ring and providing an electrical connection passage to the diaphragm; and a PCB electrically connected with
25 the diaphragm and the backplate through the second metal ring and the casing respectively, the PCB having a sound hole and a connecting terminal protruding compared to a curled surface of the casing.

According to a further aspect of the present invention, there is provided a condenser microphone including: a barrel-shaped casing having a closed bottom surface and an opened opposite surface, the opened surface being curled; an insulation ring
30

disposed in the casing, for protecting interior parts from external heat and providing an insulation function; a metal ring disposed in the insulation ring and contacting the bottom surface; a backplate disposed in the insulation ring and contacting the metal ring; a spacer disposed in the insulation ring and contacting the backplate; a diaphragm
5 inserted in the insulation ring to face the backplate, wherein the spacer is disposed between the diaphragm and the backplate; a polar ring disposed in the insulation ring, for supporting the diaphragm; an integral base ring supporting the insulation ring and the polar ring, and having a conductive layer formed on an inner circumference thereof, for providing the diaphragm with an electrical connection through the polar ring; and a
10 PCB electrically connected with the diaphragm and the backplate through the conductive layer and the casing respectively, the PCB having a sound hole and a connecting terminal protruding compared to a curled surface of the casing.

It is to be understood that both the foregoing general description and the following detailed description of the present invention are exemplary and explanatory
15 and are intended to provide further explanation of the invention as claimed.

BRIEF DESCRIPTION OF THE DRAWINGS

The accompanying drawings, which are included to provide a further understanding of the invention and are incorporated in and constitute a part of this
20 application, illustrate embodiment(s) of the invention and together with the description serve to explain the principle of the invention. In the drawings:

FIG. 1A is a perspective view of a conventional condenser microphone mounted on a main PCB;

FIG. 1B is a side sectional view of a conventional condenser microphone
25 mounted on a main PCB;

FIG. 2A is a perspective view of a condenser microphone mounted on a main PCB according to the present invention;

FIG. 2B is a side sectional view of a condenser microphone mounted on a main PCB according to the present invention;

30 FIG. 3 is an appearance view of a condenser microphone adapted for a method

of mounting a condenser microphone according to the present invention;

FIG. 4 is a side sectional view of a condenser microphone according to an embodiment of the present invention; and

FIG. 5 is a side sectional view of a condenser microphone according to another embodiment of the present invention.

DESCRIPTION OF THE PREFERRED EMBODIMENTS

Reference will now be made in detail to the preferred embodiments of the present invention, examples of which are illustrated in the accompanying drawings. Wherever possible, the same reference numbers will be used throughout the drawings to refer to the same or like parts.

Concept of the invention

FIG. 2A is a perspective view of a condenser microphone mounted on a main PCB according to the present invention, and FIG. 2B is a side sectional view of a condenser microphone mounted on a main PCB according to the present invention.

Referring to FIGs. 2A and 2B, a condenser microphone 100 according to the present invention is mounted on an element mounting surface 200a of a main PCB 200 around a through hole 202 formed in the main PCB 200 by an ordinary soldering method or a SMD reflow such that sound waves are delivered via the through hole 202. According to the mounting method as described above, since the main PCB 200 can be mounted such that the element surface 200a is directed toward an inner surface of the condenser microphone 100, there is required a minimum space or thickness to mount the main PCB to electronic products like portable phone, tape recorder and so on.

For this purpose, the condenser microphone 100 has a sound hole 110a formed in a PCB 110 thereof not in a casing 102 thereof. The assembled condenser microphone 100 is seated on the element surface 200a of the main PCB 200 centering on the through hole 202 of the main PCB 200, and then connecting terminals 112 and 114 of the condenser microphone 100 are soldered with a pattern (land) of the main PCB 200, thereby completing the mounting.

A sound wave from a sound source is delivered to the condenser microphone 100 through the through hole 202 of the main PCB 200 and the sound hole 110a formed in the PCB 110 of the condenser microphone 100. The sound wave delivered to an inner space (chamber) of the microphone 100 vibrates a diaphragm and thus a gap
5 between the diaphragm and a backplate is varied such that an electrostatic capacity is varied and the sound wave is converted into an electrical signal. According to the above construction, although the main PCB 200 with the condenser microphone 100 mounted thereon is installed such that the element surface 200a thereof is directed toward an inside of an electronic product if necessary, the short delivery path of the
10 sound wave from the sound source enables a maintenance of good sound quality.

FIG. 3 illustrates a condenser microphone adapted for applying the mounting method of the present invention to the SMD method.

As shown in FIGs. 3A to 3A, a condenser microphone 300 has a sound hole 304, which is formed not at a casing 302 thereof but at a PCB 200 thereof, to be suitably
15 mounted on a main PCB 200 by an SMD method. Connecting terminals 306 and 308 are protruded compared to a curled surface of the casing 302 and are preferably designed to include doughnut-shaped inner and outer circular plates. The doughnut-shaped outer circular plate 306 has preferably three gas exhaust grooves inclined outwardly in order to exhaust a gas generated during the SMD reflow process.

20

First embodiment

FIG. 4 is a side sectional view of a condenser microphone adapted to the present invention. The condenser microphone 400 includes a barrel-shaped casing 402 of which a bottom is closed and an opposite surface is opened, an insulation ring 404 made
25 of heat resistant material and inserted in the casing 402 in order to protect inner elements from heat, and a PCB 418 formed with a sound hole 418a and IC and MLCC mounted thereon. Inside the insulation ring 404 are disposed a first barrel-shaped metal ring 406, a backplate 408, a spacer 410, a diaphragm 412, a polar ring 414 and a second barrel-shaped metal ring 416.

30 Referring to FIG. 4, the backplate 408 is contacted and supported to the bottom

surface of the casing 402 through the first metal ring 406. The diaphragm 412 is supported toward the PCB 418 by the polar ring 414 and the second metal ring 416. The PCB 418 is formed with the sound hole 418a in order to pass a sound wave from a sound source.

5 An electret material attached to the backplate 408, the spacer 410, the diaphragm 412 and the insulation ring 404 are made of heat resistant and chemical resistant materials such as fluororesins, polymers or plastics. That is, the above heat resistant materials enables using the SMD method to manufacture the microphone of the present invention, and have various shapes of a film, a sheet or a roll and a bulk. In detail, the
10 polymers (plastics) include ASA, Nylon 6, Nylon 66, Nylon 46, LCP, PBT, PC, PC/ABS, PC/PBT, PEEK, PEN, PES, PET, PMMA, POM, PTFE, SAN, PPS, SBR, TPU and so on, and the fluororesins include PTFE (TFE), FEP, PFA, ETFE, CTFE, PVDF, PVE, PCTFE, ECTFE, EPE, Nylon 6, PP, hard PVC and so on.

 During the SMD reflow process, a heat resistant cream solder is used in order to
15 protect the elements (IC, MLCC) attached on the PCB 418 from breakaway. The cream solder includes Sn/Ag, Sn/Cu, Sn/Ag/Cu, Sn/Ag/Cu/Sb (The CASTING™ Alloy), Sn/Ag/Cu/Bi (The OATEY™ Alloy) and so on.

 Meanwhile, as shown in FIG. 3, connecting terminals 420 and 422 of the PCB 418 are protruded compared to a curled surface of the casing 402 such that the
20 microphone 400 can be mounted on the main PCB 200 (for example, a main PCB for a portable phone) using an SMD method. The connecting terminals 420 and 422 include a circular terminal 422 formed at an inner portion of the PCB 418 in order to provide Vdd connection, and circular ground terminals 420 spaced away from each other and formed at an outer periphery of the PCB 418. The terminal 420 has three gas exhaust
25 grooves 310 for exhausting gas generated during the SMD bonding process.

 Operation of the condenser microphone constructed as above will now be described.

 When Vdd and GND voltages are applied to the connecting terminals 420 and 422 of the microphone 400 connected to the main PCB 200, the microphone 400
30 operates. The diaphragm 412 is electrically connected to the PCB 418 by the polar

ring 414 and the second metal ring 416, and the backplate 408 is electrically connected to the PCB 418 by the first metal ring 406 and the casing 402.

A sound wave created by a user passes through the through hole 202 of the main PCB 200 and the sound hole 418a of the PCB 418. Then, the sound wave that has passed through the holes vibrates the diaphragm 412, so that a gap between the diaphragm 412 and the backplate 408 is varied. Owing to the variation of the gap, an electrostatic capacity formed by the diaphragm 412 and the backplate 408 is varied, thereby obtaining electrical signals (voltage) corresponding to a variation of the sound wave. The signals are applied to the IC of the PCB 418 through the electrical connection path described above, amplified and delivered to the main PCB 200 through the connecting terminals 420 and 422.

Second embodiment

FIG. 5 is a side sectional view of a condenser microphone adapted to the present invention. The condenser microphone 500 includes a casing 502 having a closed bottom surface and an opened surface opposite to the bottom surface, an insulation ring 504 formed of heat resistant material and inserted in the casing 502 and an integral base ring 516. A metal ring 506, a backplate 508, a spacer 510, a diaphragm 512 and a polar ring 514 are disposed inside the insulation ring 504. The insulation ring 504 and the polar ring 514 are supported by the integral base ring 516 toward the PCB 518. The diaphragm 512 and the polar ring 514 can be made integrally. A conductive layer 516a is formed on an inner circumference of the integral base ring 516 in order to electrically connect the diaphragm 512 and the PCB 518 through the polar ring 514. The PCB 518 is formed with a sound hole 518a and elements (IC, MLCC) mounted thereon.

Operation of the condenser microphone according to the present invention will now be described.

When Vdd and GND voltages are applied to connecting terminals 520 and 522 connected to the main PCB 200, the microphone 500 operates. The diaphragm 512 is electrically connected to the PCB 518 via the polar ring 514 and the conduction layer

516a of the integral base ring 516, and the backplate 508 is electrically connected to the PCB 518 via the metal ring 506 and the casing 502.

5 A sound wave created by a user passes through the through hole 202 of the main PCB 200 and the sound hole 518a of the PCB 518. The sound wave that has passed through the holes vibrates the diaphragm 512, so that a gap between the diaphragm 512 and the backplate 508 is varied. Owing to the variation of the gap, an electrostatic capacity formed by the diaphragm 512 and the backplate 508 is varied, thereby obtaining electrical signals (voltage). The signals are applied to the IC of the PCB 518 through the electrical connection path described above, amplified and delivered to the
10 main PCB 200 through the connecting terminals 520 and 522.

As described above, the microphone according to the present invention has a sound hole, which is formed in the PCB not in the casing such that the microphone is operated by a pressure of a sound wave introduced through a through hole of the main PCB, whereby the main PCB can be mounted with various choices. That is, if
15 necessary, the main PCB can be mounted such that its elements surface is directed toward an inside of an electronic product, thereby maintaining good sound quality thanks to a short delivery path of sound wave.

It will be apparent to those skilled in the art that various modifications and variations can be made in the present invention. Thus, it is intended that the present
20 invention covers the modifications and variations of this invention provided they come within the scope of the appended claims and their equivalents.

WHAT IS CLAIMED:

1. A method of mounting a condenser microphone on a main PCB, the method comprising the steps of:

assembling the condenser microphone by assembling elements of the condenser microphone such that a vibration plate including a couple of a diaphragm and a backplate is directed toward an opened surface of a casing of the condenser microphone, the casing having a closed bottom surface and an opened surface opposite to the closed bottom surface, mounting a PCB having a sound hole on the casing and curling the opened surface of the casing such that a connecting terminal of the PCB is protruded compared to a curled surface;

positioning the assembled condenser microphone on a main PCB such that the sound hole of the PCB of the condenser microphone is in accordance with a through hole formed in the main PCB; and

soldering the connecting terminal of the condenser microphone to a land of the main PCB,

the condenser microphone adapted to be mounted on a main PCB, comprising:

a barrel-shaped casing having a closed bottom surface and an opened opposite surface, the opened surface being curled;

an insulation ring inserted onto the casing, for protecting interior elements from external heat and providing an insulation function;

a first metal ring disposed in the insulation ring and contacting the bottom surface of the casing;

a backplate disposed in the insulation ring and contacting the first metal ring;

a spacer disposed in the insulation ring and contacting the backplate;

a diaphragm inserted into the insulation ring to face the backplate, wherein the spacer is disposed between the diaphragm and the backplate;

a polar ring disposed in the insulation ring, for supporting the diaphragm;

a second metal ring disposed in the insulation ring, for supporting the polar ring and providing an electrical connection passage to the diaphragm; and

a PCB electrically connected with the diaphragm and the backplate through the second metal ring and the casing respectively, the PCB having a sound hole and a connecting terminal protruding compared to a curled surface of the casing.