

THREE DIMENSIONAL MEMORY AND METHODS OF FORMING THE SAME

Priority Application

5 This patent application claims priority benefit from U.S. Application No. 12/825,211 filed 28 June 2010, which is incorporated herein by reference.

Background

10 Non-volatile memory devices such as flash memory devices are used in many computers and electronic devices to store information. A flash memory device usually has a write operation to store information (e.g., data and instruction codes), a read operation to retrieve the stored information, and an erase operation to clear information from the memory. As demand for higher
15 density memory device increases, three-dimensional (3D) memory devices have been proposed. An example of a conventional 3D memory device is described by Jiyoung Kim et al. in an article titled “Novel 3-D Structure for Ultra High Density Flash Memory with Vertical-Array-Transistor (VRAT) and Planarized Integration on the same Plane (PIPE)”, published in the 2008 Symposium on
20 VLSI Technology Digest of Technical Papers, pages 22-23. Since 3D memory devices are relatively new, manufacturing these devices can pose fabrication process challenges.

Brief Description of the Drawings

25 FIG. 1 shows a block diagram of a memory device having a memory array with memory cells, according to an embodiment of the invention.

 FIG. 2 shows a schematic diagram of a portion of a memory device having data lines located below memory cells, according to an embodiment of the invention.

30 FIG. 3 shows a three-dimensional view of a portion of the memory device of FIG. 2, according to an embodiment of the invention.

 FIG. 4 shows a portion of a control gate and a memory cell of the memory device of FIG. 3, according to an embodiment of the invention.

FIG. 5 through FIG. 29 show various processes of forming a memory device having data lines located below memory cells, according to an embodiment of the invention.

FIG. 30 shows a schematic diagram of a portion of a memory device
5 having data lines located above memory cells, according to an embodiment of the invention.

FIG. 31 shows a three-dimensional view of a portion of the memory device of FIG. 30, according to an embodiment of the invention.

FIG. 32 through FIG. 38 show various processes of forming a memory
10 device with data lines located above memory cells, according to an embodiment of the invention.

Detailed Description

FIG. 1 shows a block diagram of a memory device 100 having a memory
15 array 102 with memory cells 110 according to an embodiment of the invention. Memory cells 110 can be arranged in rows and columns along with access lines 123 (e.g., wordlines having signals WL0 through WLM) and lines 124 (e.g., bit lines having signals BL0 through BLN). Memory device 100 uses lines 124 and 128 to transfer information within memory cells 110. Memory cells 110 can be
20 physically located in multiple device levels such that one group of memory cells 110 can be stacked on one or more groups of other memory cells 110. Row decoder 132 and column decoder 134 decode address signals A0 through AX on lines 125 (e.g., address lines) to determine which memory cells 110 are to be accessed. Row and column level decoders 136 and 138 of row and column
25 decoders 132 and 134, respectively, determine which of the multiple device levels of memory device 100 that the memory cells 110 to be accessed are located.

A sense amplifier circuit 140 operates to determine the value of information read from memory cells 110 and provide the information in the form
30 of signals to lines 124 and 128. Sense amplifier circuit 140 can also use the signals on lines 124 and 128 to determine the value of information to be written to memory cells 110. Memory device 100 can include circuitry 150 to transfer information between memory array 102 and lines (e.g., data lines) 126. Signals

DQ0 through DQN on lines 126 can represent information read from or written into memory cells 110. Lines 126 can include nodes within memory device 100 or nodes (e.g., pins or solder balls) on a package where memory device 100 resides. Other devices external to memory device 100 (e.g., a memory controller or a processor) may communicate with memory device 100 through lines 125, 126, and 127.

Memory device 100 performs memory operations such as a read operation to read information from memory cells 110 and a write operation (sometime referred to as a programming operation) to store information into memory cells 110. A memory control unit 118 controls the memory operations based on control signals on lines 127. Examples of the control signals on lines 127 include one or more clock signals and other signals to indicate which operation, (e.g., a write or read operation) that memory device 100 performs. Other devices external to memory device 100 (e.g., a processor or a memory controller) may control the values of the control signals on lines 127. Specific values of a combination of the signals on these lines can produce a command (e.g., a write or read command) that causes memory device 100 to perform a corresponding memory operation (e.g., a write or read operation).

Each of memory cells 110 can store information representing a value of a single bit or a value of multiple bits such as two, three, four, or other numbers of bits. For example, each of memory cells 110 can store information representing a binary value "0" or "1" of a single bit. In another example, each of memory cells 110 can store information representing a value of multiple bits, such as one of four possible values "00", "01", "10", and "11" of two bits, one of eight possible values "000", "001", "010", "011", "100", "101", "110" and "111", or one of other values of other number of multiple bits.

Memory device 100 can receive a supply voltage, including supply voltage signals Vcc and Vss, on lines 141 and 142, respectively. Supply voltage signal Vss may operate at a ground potential (e.g., having a value of approximately zero volts). Supply voltage signal Vcc may include an external voltage supplied to memory device 100 from an external power source such as a battery or an alternating-current to direct-current (AC-DC) converter circuitry.

Circuitry 150 of memory device 100 can include a select circuit 152 and an input/output (I/O) circuit 116. Select circuit 152 responds to signals SEL0 through SELn to select the signals on lines 124 and 128 that can represent the information read from or written into memory cells 110. Column decoder 134
5 selectively activates the SEL0 through SELn signals based on address signals A0 through AX. Select circuit 152 selects the signals on lines 124 and 128 to provide communication between memory array 102 and I/O circuit 116 during read and write operations.

Memory device 100 can be a non-volatile memory device and memory
10 cells 110 can be non-volatile memory cells such that memory cells 110 can retain information stored thereon when power (e.g., Vcc or Vss, or both) is disconnected from memory device 100. For example, memory device 100 can be a flash memory device such as a NAND flash or a NOR flash memory device, or other kinds of memory devices, such as a variable resistance memory device
15 (e.g., phase change random-access-memory (PCRAM), resistive RAM (RRAM), etc.).

One skilled in the art may recognize that memory device 100 may include other features that are not shown in FIG. 1, to help focus on the embodiments described herein.

20 Memory device 100 may include at least one of the memory devices and memory cells described below with reference to FIG. 2 through FIG. 38.

FIG. 2 shows a schematic diagram of a portion of a memory device 200 having data lines 251, 252, and 253 located below memory cells 210, 211, and 212, according to an embodiment of the invention. Memory cells 210, 211, and
25 212 can be grouped into groups, such as a group of memory cells 210, a group of memory cells 211, and a group of memory cells 212. As shown in FIG. 2, the memory cells in each group share the same control gate, such as control gate 221, 222, or 223 (with associated signals WL0, WL1, and WL2). The memory cells are coupled in series as strings, such as strings 215 and 216. Each string
30 can include one of the memory cells from different groups and is coupled between one of transistors 231 and one of transistors 232.

As shown in FIG. 2, transistors 231 have gates coupled to select lines 241, 242, and 243 (with associated signals SGD0, SGD1, and SGD2).

Transistors 231 have nodes (e.g., sources) coupled to data lines 251, 252, and 253 (with associated signals BL0, BL1, and BL2). Data lines 251, 252, and 253 sometimes correspond to bit lines or sense lines of a non-volatile memory device.

5 Transistors 232 have gates coupled to select lines 261, 262, and 263 (with associated signals SGS0, SGS1, and SGS2). Transistors 232 have nodes (e.g., drains) coupled to a common source 270 of memory cell strings in a non-volatile memory device.

FIG. 2 shows three groups of memory cells with associated components
10 coupled to them, as an example. The number of groups of memory cells and their associated components (e.g., control gates and data lines) can vary.

Memory device 200 uses control gates 221, 221, and 223 to control
access to memory cells 210, 211, and 212 during a read operation to sense (e.g.,
read) information stored in memory cells 210, 211, and 212, and during a write
15 operation to store information into memory cells 210, 211, and 212. Memory device 200 uses data lines 251, 252, and 253 to transfer the information read from these memory cells during a read operation.

Transistors 231 and 232 are responsive to signals SGD0, SGD1, and
SGD2, and signals SGS0, GS1, and SGS2, respectively, to selectively couple
20 the memory cells to data lines 251, 252, and 253 and common source 270 during a read or write operation.

To help focus on the description herein, the description herein omits
detailed description of operations of memory device, such as write, read, and
erase operation. One skill in the art would recognize these operations. For
25 example, in an erase operation of memory device 200, a voltage of approximately 20 volts can be applied to data lines 251, 252, and 253 while control gates 221, 221, and 223, select lines 241, 242, and 243, and select lines 261, 262, and 263 can be “floated” (e.g., leave unconnected to a voltage). In this erase operation, electrons from memory elements of memory cells 210, 211, and
30 212 may move to data lines 251, 253, and 253.

FIG. 3 shows a 3D view of a portion of memory device 200, according to
an embodiment of the invention. FIG. 3 also shows X, Y, and Z directions, and
device levels 301, 302, and 303 arranged in the Z-direction. Memory cells 210

of the same group can be arranged in rows and columns in the X-direction and Y-direction. Each group of memory cells is located in different device levels 301, 302, or 303. For example, the group having memory cells 210 is located in device level 301. The group having memory cells 211 is located in device level 302. The group having memory cells 212 is located in device level 303.

As shown in FIG. 3, memory cells 210, 211, and 212 in each string (e.g., memory cells between transistors 231 and 232) are substantially vertically aligned in the Z-direction with respect to a substrate underneath data lines 251, 252, and 253. The substrate is not shown in FIG. 3, but can be similar to substrate 503 of FIG. 5 and FIG. 6. FIG. 3 also shows a channel 241 and a conductive material portion 242 extending vertically in the Z-direction and through memory element 430 of memory cells 210, 211, and 212 in the same string between transistors 231 and 232, which corresponds to transistors 231 and 232 of FIG. 2. As shown in FIG. 3, transistor 231 can include a double-gate coupled to a body 391 (e.g., transistor channel) to control (turn on or off) the transistor. The structure of the double-gate can include two segments of the same select line 241 (as shown in FIG. 3), such that the two segments are located on only two respective sides of body 391.

Memory device 200 in FIG. 3 also can include contacts 329, 349, and 359. Contacts 329 provide electrical connections to control gates 221, 222, and 223. Contacts 349 provide electrical connections to select lines 241, 242, 243, and 244. Contacts 359 provide electrical connections to and from data lines 251, 252, and 253. Select line 244 and the memory cell associated with it in the Z-direction are not shown in FIG. 2.

FIG. 4 shows a portion of control gate 221 and a memory cell 210 of memory device 200 of FIG. 3. Control gates 222 and 223 and memory cells 211 and 212 of FIG. 2 have structures similar to control gate 221 and memory cell 210, respectively. As shown in FIG. 4, control gate 221 can include a homogenous material with cavities 420, each cavity being filled with various components, including materials different from the homogenous material. The various components include: a memory element 430; a channel 441, a conductive material portion 442, and dielectrics 421 and 427. Dielectric 421 can include multiple materials 422, 423, and 424 arranged as different layers. As

shown in FIG. 4, memory element 430 of each memory cell 210 has a ring shape (e.g., donut shape) with an inner side 451 and an outer side 452. Each of the other memory cells 211 and 212 shown in FIG. 3 also has a ring shape. As shown in FIG. 3, within memory cells 210, 211, and 212 in the same string (e.g.,
5 between transistors 231 and 232), the entire ring-shape memory element 430 of each memory cell is substantially vertically aligned (in the Z-direction) with the entire ring-shape memory element of each of the other memory cells in the same string.

Each memory element 430 can store information, such as based on the
10 amount of charge (e.g., number of electrons) therein. In each such memory element 430, the amount of charge corresponds to the value of information store that memory element. The amount of charge can be controlled in a write operation or in erase operation. For example, electrons from channel 441 or
conductive material portion 442, or both, can move to memory element 430
15 during a write operation due to a tunneling effect known to those skilled in the art. In an erase operation, electrons from memory element 430 can move back to channel 441 or conductive material portion 442, or both, to data lines 251, 253, and 253 (FIG. 2 and FIG. 3). Alternative embodiments might use a memory element 430 that can store information, such as based on the resistance of the
20 element 430, for example.

Memory device 200 of FIG. 3 can be formed using processes similar to or identical to those described below with reference to FIG. 5 through FIG. 29.

FIG. 5 through FIG. 29 show various processes of forming a memory device 500 having data lines located below memory cells, according to an
25 embodiment of the invention. Memory device 500 (shown in more details in FIG. 29) can correspond to memory device 300 of FIG. 3.

FIG. 5 shows memory device 500 having a substrate 503, which can include materials 501 and 502 arranged as layers. Material 501 can include bulk silicon or could be another semiconductor material. Material 502 can be a
30 dielectric material, for example, silicon oxide. FIG. 5 also shows materials 504 and 505 formed over substrate 503. Forming materials 504 and 505 can include depositing a conductive material over substrate 503 and then depositing another conductive material over material 504. Material 504 can include a metal or other

conductive materials. Material 505 can include undoped polysilicon or doped polysilicon, such as p-type silicon or another conductive materials.

FIG. 5 also shows an X-direction, a Y-direction perpendicular to the X-direction, and a Z-direction perpendicular to both the X-direction and the Y-direction. As shown in FIG. 5, materials 504 and 505 can be formed as different layers, one layer over (e.g., on) one or more other layers in the Z-direction.

As used herein, the term “on” used with respect to two or more materials, one “on” the other, means at least some contact between the materials, while “over” or “overlying” could refer to either a material being “on” another material or where there is one or more additional intervening materials between the materials (e.g., contact is not necessarily required). The term “on”, “over”, or “overlying” does not imply any directionality as used herein unless otherwise explicitly stated as such.

FIG. 6 shows memory device 500 after data lines 651, 652, and 653 and device structures 605 have been formed. A process such as etching (e.g., dry etching) can be used to remove portions of materials 504 and 505 (FIG. 5) to form trenches 511 and 512, which have trench bottoms at material 502. Each of data lines 651, 652, and 653 and each of device structures 605 has a greater dimension (e.g., length) extending in the X-direction. A mask (not shown in FIG. 6) having separate openings extending in the X-direction can be used to form trenches 511 and 512. As shown in FIG. 6, trenches 511 and 512 divide material 504 (FIG. 5) into separate data lines 651, 652, and 653, which can correspond to data lines 251, 252, and 253 of FIG. 2.

FIG. 7 shows memory device 500 after pillars 705 have been formed in area 701 of memory device 500. Pillars 705 are not formed in area 702 of memory device 500. For simplicity, FIG. 7 through FIG. 29 do not show substrate 503 of FIG. 6. In FIG. 7, a process such as etching (e.g., dry etch) can be used to remove portions of device structures 605 to form trenches 711, 712, and 713 in the Y-direction, perpendicular to trenches 511 and 512, such that pillars 705 can be formed as shown in FIG. 7. A mask (not shown in FIG. 7) having separate openings extending in the Y-direction can be used to form trenches 711, 712, and 713. Each pillar 705 can include a height in the Z-direction of approximately 20 to 50 nanometers. As shown in FIG. 7, pillars 705

are arranged in rows and columns (e.g., in a matrix) in the X-direction and Y-direction. For simplicity, FIG. 7 does not show a dielectric material filled in trenches 511 and 512. However, forming memory device 500 in FIG. 7 also can include forming a dielectric material (e.g., silicon oxide) to fill trenches 511 and
5 512 up to a top surface 715 of device structure 605.

FIG. 8 shows memory device 500 after dielectric 831 and select lines 841, 842, 843, and 844 have been formed. Select lines 841, 842, 843, and 844 can correspond to select lines 241, 242, 243, and 244, respectively, of FIG. 3. In FIG. 8, dielectrics 831 are formed to electrically isolate select lines 841, 842,
10 843, and 844 from pillars 705. Dielectrics 831 can be formed by, for example, depositing a dielectric material (e.g., silicon oxide) on at least two sides of each pillar 705 or by oxidizing pillars 705. After dielectrics 831 are formed, select lines 841, 842, 843, and 844 can be formed by, for example, depositing a
15 conductive material over pillars 705 and trenches 711, 712, and 713 (FIG. 7) and then removing (e.g., etching) a portion of the conductive material to form select lines 841, 842, 843, and 844 having the structure shown in FIG. 8. Examples of the conductive materials for select lines 841, 842, 843, and 844 include polysilicon, metal, or other conductive materials, such as TiN and TaN.

FIG. 8 also shows doped regions 833, which can be formed by inserting
20 (e.g., implanting) n-type impurities into selective portions of device structure 605. Examples of n-type impurities include elements such as phosphorus (P) or arsenic (As). The remaining portion of device structures 605 that has not been inserted with n-type impurities may maintain its original material, such as p-type silicon, as described above with reference to FIG. 5.

FIG. 9 shows memory device 500 with select lines 941, 942, 943, and 944, which are alternative structures for select lines 841, 842, 843, and 844 of FIG. 8. In FIG. 8, opposite sides of each pillar 705 are associated with two different segments of the same select line 841, 842, 843, or 844. In FIG. 9, except for the top surfaces of pillars 705, each pillar 705 can be completely
25 surrounded by the material of one of the select line 941, 942, 943, or 944 (e.g., four sides of each pillar 705 are associated with four different segments of the same select line). Higher efficient memory device may be achieved with select lines 941, 942, 943, and 944 in comparison to select lines 841, 842, 843, and
30

844. Select lines 941, 942, 943, and 944 can also be alternative structures for select lines 241, 242, 243, and 244, respectively, of FIG. 3. Thus, each transistor 231 of FIG. 2 and FIG. 3 can include a surrounded gate with a structure shown in FIG. 9. Thus, instead of a double-gate shown in FIG. 3, each transistor 231 of
5 FIG. 3 can alternatively include a surrounded gate having four different segments of the same select line (such as select line 941) surrounding body 391 (FIG. 3).

FIG. 10 shows memory device 500 after materials 1001 through 1007 are formed over pillars 705 and select lines 841, 842, 843, and 844. Materials 1001
10 through 1007 can be formed in both areas 701 and 702 of memory device 500. However, to focus on the description herein, FIG. 10 does not show some portions of materials 1001 through 1007 in area 702. The description below with reference to FIG. 28 and FIG. 29 describes forming additional components (e.g., components similar to contacts 329 of FIG. 3) in area 702 of memory
15 device 500.

In FIG. 10 through FIG. 29, for simplicity, some number designations associated with some components of memory device 500 may not be repeated from one figure to another figure. In FIG. 10, before forming materials 1001 through 1007, a dielectric material (not shown in FIG. 10), such as silicon oxide,
20 can be formed to fill gaps 1041, 1042, and 1043. Forming materials 1001 through 1007 can include alternately depositing dielectric material and conductive material in an interleave fashion, such that these materials are alternately stacked over each other in the Z-direction, as shown in FIG. 10. Materials 1001, 1003, 1005, and 1007 can include dielectric materials, such as
25 silicon oxide. Materials 1002, 1004, and 1006 can include conductive materials, such as metal or polysilicon (e.g., n-type silicon for p-type silicon). As shown in FIG. 10, materials 1001 through 1007 are formed such that materials 1002, 1004, and 1006 are electrically isolated from each other by materials 1001, 1003, 1005, and 1007.

30 FIG. 11 shows memory device 500 after openings (e.g., holes) 1101 have been formed in material 1002 through 1107. Holes 1101 are formed such that each hole 1101 can be aligned substantially directly over a corresponding pillar 705, as illustrated in FIG. 11. Forming holes 1101 can include removing (e.g.,

etching) a portion of each of materials 1002 through 1007, stopping at material 1001, such that at least a portion of material 1001 or the entire material 1001 remains to separate holes 1101 from pillars 705. Forming holes 1101 results in forming cavities 1110 in each of materials 1003, 1005, and 1007, and cavities 5 1120 in each of materials 1002, 1004, and 1006. As shown in FIG. 12, cavities 1110 in the materials 1003, 1005, and 1007 are substantially aligned directly over cavities 1120 in the other materials 1002, 1004, and 1006. Each cavity 1110 and each cavity 1120 may have substantially the same diameter, D1. Diameter D1 can also be considered the diameter of each hole 1101 at the 10 location of each cavity 1110 and each cavity 1120.

FIG. 12 shows memory device 500 after cavities 1220 have been formed in materials 1002, 1004, and 1006 (used to form control gates 1221, 1222, and 1223). Forming cavities 1220 can include enlarging the size of cavities 1120 (FIG. 11) while keeping the size of cavities 1110 substantially unchanged (e.g., 15 remaining substantially at diameter D1). For example, enlarging the size of cavities 1120 (FIG. 11) can include selectively removing (e.g., selective wet or dry etching) a portion of each of materials 1002, 1004, and 1006 at each cavity 1120 (FIG. 11) such that the diameter of each cavity 1220 increases to substantially diameter D2, while the diameter D1 at each cavity 1110 remains 20 substantially unchanged. Diameter D2 is greater than diameter D1. Forming cavities 1120 in materials 1002, 1004, and 1006 also form control gates 1221, 1222, and 1223, which can correspond to control gates control gates 221, 222, and 223 of FIG. 2.

FIG. 13 shows more details of control gate 1221 of FIG. 12. Control 25 gates 1222 and 1223 of FIG. 12 have a similar structure as control gate 1221. As shown in FIG. 13, control gate 1221 can include a homogenous material with cavities 1220 of FIG. 11 being arranged in rows and columns in the X-direction and Y-direction. Each cavity 1220 can include a sidewall 1225.

FIG. 14 and FIG. 15 shows memory device 500 after dielectrics 1421 and 30 memory elements 1430 have been formed in cavities 1220. For simplicity, FIG. 15 does not show dielectrics 1421 and memory elements 1430 in all cavities 1220. Each dielectric 1421 can be formed on sidewall 1225, such that each dielectric 1421 and can be located between the material of control gate 1221 and

memory element 1430, and such that memory element 1430 can be electrically isolated from the material of control gate 1221 by at least a portion of dielectric 1421. Forming dielectric 1421 can include forming multiple materials 1422, 1423, and 1424 (FIG. 15) at different times, one material after another. Forming
5 material 1422 can include oxidizing a portion (e.g., a surface) of sidewall 1225 to form dielectric material (e.g., silicon oxide) on sidewall 1225. Alternatively, forming material 1422 can include depositing dielectric material (e.g., silicon oxide) on sidewall 1225. Forming material 1423 can include depositing dielectric material (e.g., silicon nitride) on material 1422, wherein a portion of
10 that dielectric material may also form on sidewall 1425 of each cavity 1110. Forming material 1424 can include depositing dielectric material (e.g., silicon oxide) on material 1423.

Memory elements 1430 can be formed after dielectrics 1421 are formed. As shown in FIG. 15, each memory element 1430 has a ring shape (e.g., a donut
15 shape) with an inner side 1451 and an outer side 1452 of FIG. 14. Forming memory elements 1430 can include depositing a material in holes 1101. Since cavities 1220 of FIG. 14 are substantially aligned with cavities 1110, the material (that forms memory element 1430) may fill both cavities 1110 and 1120. Then, a portion (e.g., center portion in each hole) of the material that
20 forms memory elements 1430 can be removed (e.g., by etching in the same, single, etching step) such that the material in cavities 1110 can be removed (e.g., completely removed) and the material in cavities 1220 is not completely removed but partially removed. As shown in FIG. 14, after the material that forms memory elements 1430 is removed from cavities 1110, a portion of
25 dielectric material 1423 (e.g., silicon nitride, that was formed on material 1422) may be exposed. As shown in FIG. 14, after the material that forms memory elements 1430 is partially removed from cavities 1220, memory element 1430 (formed by the remaining material in a cavity 1220) associated with the same hole 1101 may have its inner side 1451 substantially aligned with sidewall 1425
30 (or sidewall 1425 with portions of materials 1422 and 1423 of cavities 1110) of cavities 1110.

The material of memory elements 1430 can include, for example, semiconductor material (e.g., polysilicon), dielectric charge trapping material,

such as silicon nitride or other dielectric charge trapping materials, or a variable resistance material, such as a phase change material (e.g., GST). During removing (e.g., etching) a portion of the material that forms memory elements 1430, portions 1401 of material 1001 located over pillars 705 can also be
5 removed to reduce the thickness of portions 1401.

FIG. 16 and FIG. 17 show memory device 500 after dielectric 1627 has been formed on inner side 1451 of memory element 1430 and in cavities 1110. Forming dielectric 1627 can include depositing dielectric material (e.g., silicon oxide) on inner side 1451. Alternatively, forming dielectric 1627 can include
10 oxidizing a portion (e.g., inner side 1451) of memory element 1430. Forming dielectric 1627 (e.g., by oxidation) may also consume material 1423 (FIG. 14) formed on material 1422, which formed on sidewall 1425 of cavities 1110. Thus, dielectric 1627 may also form in cavities over material 1422.

FIG. 18 and FIG. 19 show memory device 500 after channels 1841 have
15 been formed on dielectrics 1627 in both cavities 1110 and 1220. Forming channels 1841 can include depositing a conductive material on dielectrics 1627. An etching process can be used to reduce the thickness of the conductive material after it is deposited. The conductive material of channels 1841 can include doped polysilicon, which can have the same material type (e.g., p-type)
20 as pillars 705. FIG. 18 also shows a formation of openings 1801, which can be formed by removing (e.g., by etching) portions 1401 (FIG. 14) located over pillars 705. As shown in FIG. 19, channel 1841 is facing memory elements 1430 and is electrically isolated from memory element 1430 by at least a portion of dielectric 1627.

25 FIG. 20 shows memory device 500 after a conductive material 2001 has been formed by, for example, depositing undoped or lightly doped polysilicon to place channels 1841 in electrical communication with pillars 705. As shown in FIG. 20, conductive material 2001 forms a continuous conductive path between channels 1841 and data lines 651, 652, and 653 through pillars 705.

30 FIG. 21 shows memory device 500 after dielectric material 2101 (e.g., silicon oxide) has been formed over conductive material 2001.

FIG. 22 shows memory device 500 after a formation of openings (e.g., holes 2201), a conductive material portion 2260, and conductive material

portions 2241. Holes 2201 are formed such that each hole 2201 can be aligned substantially directly over channels 1841, as illustrated in FIG. 22. Forming holes 2201 can include removing (e.g., etching) a portion of dielectric material 2101 and a portion of conductive material 2001 (FIG. 21), stopping at a location
5 in material 1007. Holes 2201 can be formed such that after a portion of conductive material 2001 is removed during the formation of holes 2201, conductive material 2001 is separated into conductive material portion 2260 and conductive material portions 2241, as illustrated in FIG. 22.

FIG. 23 shows memory device 500 after doped regions 2301 have been
10 formed. Forming doped regions 2301 can include inserting (e.g., implanting) n-type impurities into top parts of conductive material portions 2241. Doped regions 2301 can provide a relatively low resistance connection between channels 1841 and other components of memory device 500.

FIG. 24 shows memory device 500 after dielectrics 2401 and channels
15 2402 have been formed. Dielectrics 2401 (e.g., silicon oxide) is formed on sidewalls of conductive material portion 2260 at the location of holes 2201. Channels 2402 are formed on sidewalls of dielectric material 2101 and on dielectrics 2401.

FIG. 25 shows memory device 500 after conductive material 2501 has
20 been formed in each of holes 2201, such that channel 2402 can be electrically coupled to channel 1841 through conductive material 2501, doped region 2301, and conductive material portion 2241. Forming conductive material 2501 in each of holes 2201 can include depositing a conductive material (e.g., polysilicon) over material, such that the conductive material fills holes 2201.
25 Then, a top portion of the conductive material can be removed by, for example, etching back the conductive material or by chemical mechanical planarization (CMP).

FIG. 26 shows memory device 500 after doped regions 2601 and select
lines 2661, 2662, and 2663 have been formed. Forming doped regions 2601 can
30 include inserting (e.g., implanting) n-type impurities into top portions of conductive material 2501. Forming select lines 2661, 2662, and 2663 can include removing parts of dielectric material 2101 and conductive material portion 2260 to form trenches 2602, which have trench bottoms partially

extending into material 1007. As shown in FIG. 26, trenches 2602 separate conductive material portion 2260 into select lines 2661, 2662, and 2663, which can correspond to select lines 261, 262, and 263 of FIG. 2.

FIG. 27 shows memory device 500 after material 2701 and a common source 2770 have been formed. Forming material 2701 can include depositing a dielectric material (e.g., silicon dioxide) over material 2101, such that the dielectric material fills trenches 2602. Then, a top portion of the dielectric material can be removed by, for example, etching back the dielectric material or by CMP. Forming common source 2770 can include depositing a conductive material (e.g., metal) over materials 2701 and 2101.

FIG. 28 shows memory device 500 after materials 1001 through 1007 in area 702 (FIG. 10) are processed (e.g., by patterning) to form a stair like pattern with material between the stairs are not shown in FIG. 28. As mentioned above in the description of FIG. 10, some portions of materials 1001 through 1007 are omitted from area 702 of FIG. 10 through FIG. 27 for clarity. FIG. 28 shows material 1001 through 1007 in area 702 after they have been processed to form the stair like pattern. As shown in FIG. 28, control gates 1221, 1222, and 1223 are formed from materials 1002, 1004, and 1006, respectively, which are formed in the stair like pattern.

FIG. 29 shows memory device 500 after contacts 2929, 2949, and 2959 have been formed. Contacts 2929 provide electrical connections to control gates 1221, 1222, and 1223. Contacts 2949 provide electrical connections to select lines 841, 842, 843, and 844. Contacts 2959 provide electrical connections to and from data lines 651, 652, and 653.

As shown in FIG. 29, memory device 500 can include components and memory cells 2910, 2911, and 2912 similar to or identical to components and memory cells 210, 211, and 212 of memory device 300 described above with reference to FIG. 2 and FIG. 3.

One skilled in the art may readily recognize that additional processes may be performed to form additional features of a memory device, such as memory device 500 described above. Thus, to help focus on the embodiments described herein, FIG. 5 through FIG. 29 described above and FIG. 30 through

FIG. 38 described below show only some of the features of a memory device, such as memory device 500.

FIG. 30 shows a schematic diagram of a portion of a memory device 300 having data lines 251, 252, and 253 located above memory cells 210, 211, and 212, according to an embodiment of the invention. Memory device 300 can include components similar to those of memory device 200 of FIG. 3. Thus, for simplicity, similar or same components between memory device 200 and memory device 3000 are given the same number designations. The detailed description of these similar components is not repeated in FIG. 30. Main differences between memory device 3000 and memory device 200 include the locations of data lines 251, 252, and 253 and common source 3070 of memory device 3000 to enable global erase operation. As shown in FIG. 30, data lines 251, 252, and 253 are located above memory cells 210, 211, and 212. Common source 3070 is located below memory cells 210, 211, and 212 and can couple directly to at least a portion of a substrate of memory device 3000 (e.g., substrate 3101 in FIG. 31). This main difference may allow voltages to be applied to various components of memory device 3000 in a different way during an erase operation and memory device 3000 function differently (e.g., during the global erase operation) in comparison with the erase operation (e.g., local erase operation) of memory device 200. For example, in an erase operation of memory device 3000, a voltage of approximately 20 volts can be applied to common source 3070, while control gates 221, 221, and 223, data lines 251, 252, and 253, select lines 241, 242, and 243, and select lines 261, 262, and 26 can be “floated”. In this erase operation, electrons from memory elements of memory cells 210, 211, and 212 may move (e.g., by tunneling) to common source 3070 (e.g., global erase). In memory 200, as described above with reference to FIG. 2, FIG. 3, and FIG. 4, during an erase operation, electrons from memory elements of memory cells 210, 211, and 212 may move to data lines 251, 253, and 253 (e.g., local erase)

FIG. 31 shows a 3D view of a portion of the memory device 3000 of FIG. 30, according to an embodiment of the invention. As shown in FIG. 31, data lines 251, 252, and 253 are located above memory cells 210, 211, and 212, common source 3070 is located below memory cells 210, 211, and 212 and is

coupled to a substrate 3101. Substrate 3101 can include semiconductor material, such as p-type silicon.

As shown in FIG. 31, memory cells 210, 211, and 212 in each string (e.g., memory cells between transistors 231 and 232) are substantially vertically aligned in the Z-direction with respect to substrate 3101. Transistor 232 can include a double-gate or surrounded gate similar to the double-gate (FIG. 3) or surrounded gate (FIG. 9) of transistor 231 of FIG. 3. FIG. 31 also shows a channel 441 and a conductive material portion 442 extending vertically in the Z-direction and through memory element 430 of memory cells 210, 211, and 212 in the same string between transistors 231 and 232, which corresponds to transistors 231 and 232 of FIG. 30.

Memory element 430 in each of memory cells 210, 211, and 212 has a ring shape. As shown in FIG. 31, within memory cells 210, 211, and 212 in the same string, the entire ring-shape memory element 430 of each memory cell is substantially vertically aligned (in the Z-direction) with the entire ring-shape memory element of each of the other memory cells in the same string.

FIG. 32 through FIG. 38 show various processes of forming a memory device 3200 having data lines located above memory cells, according to an embodiment of the invention. Memory device 3200 (shown in more details in FIG. 38) can correspond to memory device 3000 of FIG. 31.

FIG. 32 shows memory device 3200 having a substrate 3201 and trenches 3211, 3212, and 3213, and substrate portions 3270 and 3271 formed on a top portion of substrate 3201. Substrate 3201 can include semiconductor material, such as bulk silicon. Top substrate portions 3270 and 3271 can be formed by inserting (e.g., implanting) p-type impurities into a top portion of substrate 3201. Thus, substrate portions 3270 and 3271 can include p-type silicon. Forming trenches 3211, 3212, and 3213 and substrate portion 3270 can include removing (e.g., etching) a portion of substrate portion 3271. During a write or read operation of memory device 3200, substrate portion 3270 can be coupled to a potential, such as to ground. During an erase operation of memory device 3200, substrate portion 3270 can be coupled to a voltage, for example, approximately 20 volts.

FIG. 33 shows memory device 3200 after material 3301 has been formed in trenches 3211, 3212, and 3213 (FIG. 32). Forming material 3301 can include depositing dielectric material (e.g., silicon oxide) over substrate 3201 to fill trenches 3211, 3212, and 3213. Then, a top portion of the dielectric material can
5 be removed by, for example, CMP.

FIG. 34 shows memory device 3200 after material 3401 and trenches 3411, 3412, and 3413, and device structures 3460 have been formed. Forming material 3401 can include depositing dielectric material (e.g., silicon oxide, or silicon nitride) over substrate 3201 and material 3301. Forming trenches 3411,
10 3412, and 3413 can include removing (e.g., etching) portions of substrate 3201, material 3301, and material 3401. Device structures 3460 are formed as a result of the formation of trenches 3411, 3412, and 3413.

FIG. 35 shows memory device 3200 after a formation of doped regions 3501, material 3502, and select lines 3561, 3562, and 3563. Forming doped
15 regions 3501 can include inserting (e.g., implanting) n-type impurities into selective portions of substrate portion 3271. Material 3502 (e.g., silicon oxide) can be formed on both sides of each device structure 3460 to electrically isolate select lines 3561, 3562, and 3563 from device structures 3460. Materials of select lines 3561, 3562, and 3563 can include one or more conductive materials,
20 such as one or more metals, alloys, other conductive materials, or a combination thereof. Select lines 3561, 3562, and 3563 can correspond to select lines 261, 262, and 263 of memory device 3000 of FIG. 30.

FIG. 36 shows memory device 3200 after material 3601 have been formed in trenches 3411, 3412, and 3413. Forming material 3601 can include
25 depositing dielectric material (e.g., silicon dioxide) to fill trenches 3411, 3412, and 3413. Then, a top portion of the dielectric material can be removed by, for example, etching back the conductive material or by CMP, stopping at substrate portion 3270.

FIG. 37 shows memory device 3200 after grooves 3701 have been
30 formed by removing (e.g., by wet etching) a top portion of the material used to form select lines 3561, 3562, and 3563. Alternatively, forming grooves 3701 can be omitted.

FIG. 38 shows memory device 3200 after other components have been formed. The processes for forming the components of memory device 3200 in FIG. 38 can include similar or identical processes for forming the component of memory device 500 described above with reference to FIG. 10 through FIG. 29.

5 For example, control gates 3821, 3822, and 3823 of FIG. 38 can be formed using processes similar to or identical to those of forming control gates 1221, 1222, and 1223 of memory device 500 described above with reference to FIG. 5 through FIG. 29. Data lines 3851, 3852, and 3853 of FIG. 38, can correspond to data lines 251, 252, and 253 of FIG. 30 and FIG. 31. As

10 shown in FIG. 38, memory device 3200 can include memory cells 3810, 3811, and 3812, which can be formed using processes similar to or identical to those of forming memory cells 2910, 2911, and 2912 of memory device 500 described above with reference to FIG. 5 through FIG. 29.

One or more embodiments described herein include a memory device

15 and methods of forming the memory device. One such memory device can include a first group of memory cells, each cell of the first group being formed in a respective cavity of a first control gate located in one device level of the memory device. The memory device also can include a second group of memory cells, each cell of the second group being formed in a cavity of in a

20 second control gate located in another device level of the memory device. Additional apparatus and methods are described. Other embodiments including additional apparatus and methods are described above with reference to FIG. 1 through FIG. 38.

The illustrations of apparatus such as memory devices 100, 200, 500,

25 3000, and 3200, and memory cells 210, 211, 212, 2910, 2911, 2912, 3010, 3811, and 3812 are intended to provide a general understanding of the structure of various embodiments and not a complete description of all the elements and features of the apparatus that might make use of the structures described herein.

The apparatus of various embodiments may include or be included in

30 electronic circuitry used in high-speed computers, communication and signal processing circuitry, memory modules, portable memory storage devices (e.g., thumb drives), single or multi-processor modules, single or multiple embedded processors, multi-core processors, data switches, and application-specific

modules including multilayer, multi-chip modules. Such apparatus may further be included as sub-components within a variety of electronic systems, such as televisions, cellular telephones, personal computers (e.g., laptop computers, desktop computers, handheld computers, tablet computers, etc.), workstations, 5 radios, video players, audio players (e.g., MP3 (Motion Picture Experts Group, Audio Layer 3) players), vehicles, medical devices (e.g., heart monitor, blood pressure monitor, etc.), set top boxes, and others.

The above description and the drawings illustrate some embodiments of the invention to enable those skilled in the art to practice the embodiments of the 10 invention. Other embodiments may incorporate structural, logical, electrical, process, and other changes. Examples merely typify possible variations. Portions and features of some embodiments may be included in, or substituted for, those of others. Many other embodiments will be apparent to those of skill in the art upon studying and understanding the above description.

15 The Abstract is provided to comply with 37 C.F.R. §1.72(b) requiring an abstract that will allow the reader to quickly ascertain the nature and gist of the technical disclosure. The Abstract of the Disclosure is submitted with the understanding that it will not be used to interpret or limit the scope or meaning of the claims.

20

What is claimed is:

1. An apparatus comprising:
first memory cells located in a first device level of a memory device;
5 second memory cells located in a second device level of the memory device;
a first control gate formed in the first device level, the first control gate to control access to the first memory cells, wherein each of the first memory cells includes a memory element formed in a cavity of the first control gate; and
10 a second control gate formed in the second device level, the second control gate to control access to the second memory cells, wherein each of the second memory cells includes a memory element formed in a cavity of the second control gate.
- 15 2. The apparatus of claim 1, wherein each of the first and second memory cells include multiple memory cells arranged in a first direction and multiple memory cells arranged in a second direction, further comprising:
a common source; and
data lines configured to be selectively coupled to the common source and
20 the memory cells through a conductive material, the conductive material extending through the first and second memory cells in a third direction, the third direction being substantially perpendicular to the first and second directions.
- 25 3. The apparatus of claim 2, wherein the common source is formed over a substrate of the memory device, such that the common source is between the first and second memory cells and the substrate to allow electrons from the memory element of at least one of the first and second memory cells to move to the common source during an erase operation.
- 30 4. The apparatus of claim 2, wherein the common source is formed over a substrate of the memory device, such that the first and second memory cells are between the common source and the substrate.

5. The apparatus of claim 1, wherein the first memory cells are substantially vertically aligned with the second memory cells.
- 5 6. The apparatus of claim 1, wherein the memory element of each of the first memory cells is substantially vertically aligned with the memory element of one of the second memory cells.
7. The apparatus of claim 1, further comprising transistors to selectively
10 couple the first and second memory cells to data lines associated with the first and second memory cells during a memory operation of the memory device, wherein at least one of the transistors comprises a double-gate.
8. The apparatus of claim 1, further comprising transistors to selectively
15 couple the first and second memory cells to data lines associated with the first and second memory cells during a memory operation of the memory device, wherein at least one of the transistors comprises a surrounded gate.
9. An apparatus comprising:
20 a first non-volatile memory cell including a first memory element, the first memory element having a ring shape;
a second non-volatile memory cell including a second memory element, the second memory element having a ring shape; and
a conductive material extending through the first and second memory
25 elements.
10. The apparatus of claim 9, further comprising:
a first additional conductive material configured to operate as a control gate to access the first memory cell, wherein the first memory element and the
30 first additional conductive material are located in a first device level of a memory device in which the first and second memory cells are located; and
a second additional conductive material configured to operate as a control gate to access the second memory cell, wherein the second memory

element and the second additional conductive material are located in a second device level of the memory device.

11. The apparatus of claim 10, wherein each of the memory cells further
5 includes a first dielectric between the respective memory element and the conductive material.

12. The apparatus of claim 11, wherein each of the memory cells further
10 includes a second dielectric between the respective memory element and the respective additional conductive material.

13. The apparatus of claim 9, further comprising a data line over a substrate
to carry signals representing values of information stored in the first and second
memory cells, wherein the data line is located between the substrate and the first
15 memory cell.

14. The apparatus of claim 9, further comprising a data line over a substrate
to carry signals representing values of information stored in the first and second
memory cells, wherein the first and second memory cells are located between the
20 substrate and the data line.

15. An apparatus comprising:
a first conductive material located in a first device level of a memory
device, the first conductive material including a first cavity, the first cavity
25 having a first sidewall;
a second conductive material located in a second device level of the
memory device, the second conductive material including a second cavity, the
second cavity having a second sidewall;
a first dielectric formed on the first sidewall and the second sidewall;
30 a first memory element located in the first cavity and electrically isolated
from the first conductive material by a first portion of the first dielectric;

a second memory element located in the second cavity and electrically isolated from the second conductive material by a second portion of the first dielectric;

5 a second dielectric formed on a side of the first memory element and on a side of the second memory element; and

a conductive channel extending from the first device level to the second device level and facing the first and second memory elements, such that the conductive channel is electrically isolated from the first and second memory elements by at least a respective portion of the second dielectric.

10

16. The apparatus of claim 15, wherein the first and second memory elements comprise polysilicon.

15 17. The apparatus of claim 15, wherein the first and second memory elements comprise a dielectric material.

18. The apparatus of claim 17, wherein the dielectric material comprises silicon nitride.

20 19. The apparatus of claim 15, further comprising dielectric material between the first and second conductive materials.

20. The apparatus of claim 15, further comprising:
a substrate; and
25 a data line configured to be selectively coupled to the conductive channel, wherein the data line is located between the second conductive material and the substrate.

21. The apparatus of claim 15, further comprising:
30 a substrate; and
a data line configured to be selectively coupled to the conductive channel, wherein the first and second memory elements are located between the data line and the substrate.

22. A method comprising:
forming a first non-volatile memory cell including a first memory
element having a ring shape;
5 forming a non-volatile second memory cell including a second memory
element having a ring shape; and
forming a conductive material extending through the first and second
memory elements.
- 10 23. The method of claim 22, wherein forming the first memory cell
comprises forming a first cavity in a first conductive material, wherein the first
memory element is formed in the first cavity, wherein forming the second
memory cell comprises forming a second cavity in a second conductive material,
and wherein the second memory element is formed in the second cavity.
- 15 24. The method of claim 23, wherein the first cavity is substantially aligned
over the second cavity.
25. The method of claim 22, further comprising:
20 forming a data line over a substrate, wherein the data line is located
between the substrate and the first and second memory cells.
26. The method of claim 22, further comprising:
forming a data line over a substrate, wherein the first and second memory
25 cells are located between the substrate and the data line.
27. A method comprising:
forming conductive material layers and dielectric material layers such
that the conductive material layers are electrically isolated from each other by
30 the dielectric material layers;
forming cavities in each of the conductive material layers; and
forming a memory element in each of the cavities.

28. The method of claim 27, wherein each of the conductive material layers is between two of the dielectric material layers and at least one of the conductive material layers is between two of the conductive material layers.
- 5 29. The method of claim 27, wherein the memory element comprises polysilicon.
30. The method of claim 27, wherein the memory element comprises a dielectric material.
- 10 31. The method of claim 27, wherein forming the cavities includes:
forming initial cavities in the conductive material layers; and
enlarging a size of the initial cavities to form the cavities in each of the conductive material layers.
- 15 32. The method of claim 31, further comprising:
forming openings through the conductive material layers and the dielectric material layers to form the initial cavities.
- 20 33. The method of claim 32, wherein second cavities are formed in each of the dielectric material layers when the openings are formed, and a size of the second cavities remains substantially unchanged when the size of the initial cavities is enlarged.
- 25 34. The method of claim 33, wherein each of the second cavities and each of the initial cavities has a substantially same diameter.
- 30