

INTERFACE DEVICE

FIELD OF THE INVENTION

5 [001] The present invention relates to a configurable /
reconfigurable interface device for interfacing a Multimedia
stream transmission source or receiver to a computer. This
includes transferring, processing, manipulating and presenting of
audio / video streams.

10

BACKGROUND OF THE INVENTION

Description of the Related Prior Art

15 [002] Devices such as set top boxes, modulators, etc, have ports
to interface various types of Multimedia streams. Examples of
Multimedia streams are MPEG2 transport stream, MPEG4
transport stream, MPEG7 transport stream, digital television
transport stream, and high definition television transport
stream. To process the Multimedia stream the device coupled to
20 the transport medium must comply with required, electrical
characteristics and the transport stream protocol. Currently an
individual module for each type of input stream must be
specifically constructed and configured to meet the electrical
and protocol characteristics for the type of Multimedia stream
25 being received.

[003] Examples of prior art are presented in the following patent
documents by way of example: (1) EP 0910208 A2 (2) WO 97/26762 A1
(3) US 6008777 A and (4) US 2003143985 A1

30

[004] EP 0910208 A2 in its prior art sites three Japanese Patent
Kokai Publications: a) JP-A-8-307784 which uses PC (Personal
Computer) based tuner reception of analog TV. (b) JP-A-8-237154
which has limitation of using special purpose LSI to decode the
35 TS (Transport Stream) on the tuner card before transmitting to
the PC. (c) JP-A-5-328320 sets out a model for receiving analog
terrestrial character multiplexer TV broadcast reception by the

PC via an RS-232 interface. However this arrangement does not deal with Transport Stream (TS).

5 [005] The art of reception dealt in EP 0910208 A2 relates to CA based and free-view digital TV broadcast. However the system has inherent limitations; (a) the receiver hardware interfaces to system bus and utilizes hardware based DMA technique to transfer stream data from the interface board to PC. (b) The program identification needs to be carried out by hardware PID filtering
10 in the interface card. (c) The stream handling and playing is limited to MPEG-2.

[006] WO 97/26762 A1, discloses a "bus interface", connecting the adapter card and personal computer, that allows the digital data
15 from a demodulator to be transmitted to the PC. The "bus interface" means the same as "interface converting means" that is sited in the claim of patent document US 2003143985.

[007] This claim is too generic. It is known to and is
20 implemented, for specific applications, in many individual specific forms by the engineers skilled in the art. E.g. when interfacing; Digital TV TS to modulators, PC Internet card, Camcorder via Firewire, Digital Audio in DAB etc.

25 [008] Another limitation is that WO 97/26762 A1, Ignored to propose a computer/PC specific interface for stream transportation; hardware/software that is required to generate logic signal in sympathy with the protocol associated with the stream, to match the hardware interface requirement of external
30 devices.

[009] US 6008777 A discloses an arrangement where by local PC TV signal is converted to PAL/NTSC analog TV signal and transmitted. The limitation in this invention is that it only deals with
35 analog TV signals.

[010] US 2003143985 proposes the streaming "moving image" by "transmitting apparatus" of "formatted data bit stream" via "interface converting means". The "interface converting means", means the same as the "bus interface" sited in the claim of
5 patent document WO 97/26762.

[011] This claim associated with the transmission is also too generic. It is known and is implemented, for specific applications, in many individual specific forms by the engineers
10 skilled in the art.

[012] Another limitation is that US 2003143985, it did not propose a computer/PC specific interface for stream transportation; hardware/software that is required to generate
15 logic signal in sympathy with the protocol associated with the stream, to match the hardware interface requirement of external devices.

[013] The present invention provides an interface unit that is configured / reconfigured to receive or transmit a plurality of
20 types of digital bit stream. Thus allowing a variation of single interface unit to be configured / reconfigured and adapted for independent applications.

[014] An optional object of the invention is to receive / transmit a digital bit stream according to the electrical characteristics of a Multimedia stream receiver/transmitter and the bit stream protocols of a plurality of Multimedia stream
25 types.

30

BRIEF SUMMARY OF INVENTION

[015] According to one aspect of the invention there is provided an interface between a digital device for transmitting / receiving
35 a Multimedia stream and a computer, the interface comprising:

(a) a Multimedia stream transmitter/receiver (transceiver) for transmitting digitally streamed content to a digital device or receiving digitally streamed content from the digital device;

5 (b) a computer bus interface for receiving/transmitting data via a computer bus of a computer for use by the computer or as provided by the computer; and

(c) a data converter for converting media streams received
10 by the external device into stream data useable by the computer when provided to the computer bus; and

(d) a data converter for converting streamed data received
15 from the computer into digitally streamed data for used by the external stream receiver.

[016] Preferably the Multimedia stream transceiver is configured / reconfigured to meet electrical characteristics of the digital device. Preferably the data converter is configured /
20 reconfigured to meet data transmission protocols of the digital device. Preferably the computer bus interface is configured to meet electrical characteristics of the computer bus and to meet data transmission protocol of the computer bus.

25 [017] Preferably the data converter is configured / reconfigured to convert data into a selected Multimedia stream format, the selected format being signalled to the data converter in data provided by the computer via the computer bus.

30 [018] Preferably the data converter is also configured / reconfigured to convert the Multimedia stream from a selected format into data usable by the computer when provided to the computer bus, the selected format being signalled to the data converter in the data provided by the computer via the computer
35 bus.

[019] Alternatively the data converter is configured /
reconfigured to recognise the format of the Multimedia stream and
signal the recognised format to the computer in data provided to
the computer bus.

5

[020] Preferably the computer bus is a Universal Serial Bus (USB).
Alternatively the computer bus is a Peripheral Component
Interconnect (PCI) bus.

10 [021] Preferably the data converter is a microcontroller.
Preferably the microcontroller includes a general programmable
interface. The general programmable interface is configured /
reconfigured to enable the data converter to meet the data
transmission protocols of the digital device.

15

[022] Preferably the Multimedia stream type is one of an ATSC
compliant transport stream, DVB compliant transport stream MPEG 2,
MPEG 4, MPEG 7, digital satellite TV, TV tuner data, DVB/T, AC3,
MP3, Dolby stereo, IEEE1394, IEEE488 or digital radio format. The
20 Multimedia stream includes encoded video or sound information.

[023] Preferably the data converter generates one or more control
signals for control of the Multimedia stream delivery to the
digital device. Preferably the control signals are generated
25 according to protocol requirements of the transport stream type
(e.g. DVB Transport Stream requires a clock, packet sync. and data
valid control signals).

[024] Preferably the transceiver generates a digital clock signal
30 and/or digital control signals. In one embodiment the transceiver
includes an MPEG2 Transport Streamer I/O port.

[025] Preferably the transceiver transmission rate is controlled
by a signal provided by the computer via the computer bus.
35 Preferably the data is provided by the computer bus to the
computer bus interface in bursts, which are buffered by the
transceiver and transmitted to the transmission medium in a

Multimedia stream at the transmission rate. Preferably the transceiver buffers the Multimedia stream sent by the digital device. Preferably the buffer is a FIFO buffer.

- 5 [026] Preferably the Multimedia stream transmitter is configured / reconfigured to generate two or more independent media streams. Preferably each media stream is produced from a multiplexed data stream, the multiplexed data stream is provided to a respective buffer and de-multiplexed by a dual or multi phase clock signal.

10

[027] Preferably the Multimedia stream transceiver converts voltage levels from those used by the data converter to those required by the digital device and vice versa.

- 15 [028] Preferably the data converter is controlled by data provided by a computer program executed on the computer.

[029] Preferably the computer program provides data to the data converter via the computer bus and in turn via the computer bus interface.

20

[030] Preferably the computer program includes a module for providing a Graphical User Interface (GUI) for interaction with a user of the computer.

25

[031] Preferably the computer program includes a system driver for providing control of the operation of the data converter and/or transceiver and/or digital device.

- 30 [032] Preferably the computer program includes a library for displaying of video, audio playing or data transfers to specific applications according to data stream standards.

[033] Preferably the GUI provides control of the display of video or playing of sound coded in the Multimedia stream received by the stream receiver.

35

[034] Preferably the data converter includes a serial bus input/output port that is configured / reconfigured to generate serial bus signals for activation or control of the digital device. Preferably the serial bus signals are generated by software running on the microcontroller or hardware/firmware of the interface. Preferably the serial bus signals are generated according to instructions provided by the computer in data sent to the microcontroller and stored in the interface. Preferably the serial bus signals are generated to be compliant with a suitable standard, e.g. IIC, RS-232 etc.

[035] According to another aspect of the invention there is provided a computer to digital device interface comprising:

- (a) a computer bus interface for receiving data from a computer bus of a computer as provided by the computer;
- (b) a stream transmitter for transmitting digitally streamed content to the digital device; and
- (c) a data converter for converting data received by the computer bus interface into digitally streamed data for transmission by the stream transmitter.

[036] Preferably the interface further comprises an input/output (I/O) port. Preferably the I/O port is configured / reconfigured to de-multiplex the streamed data to two or more Multimedia streams.

[037] According to yet another aspect of the invention there is provided a digital device to computer interface comprising:

- (a) a Multimedia stream receiver for receiving digitally streamed content from the digital device;
- (b) a computer bus interface for providing data to a computer bus of a computer for use by the computer; and

(c) a data converter for converting data received by the external stream transmitter into data useable by the computer.

5 [038] According to another aspect of the present invention a digital stream transmission medium to computer interface comprising:

(a) a Multimedia stream transmitter/receiver for transmitting streamed contents or receiving streamed contents;

10 (b) a computer bus interface for receiving stream via a computer bus for use by the computer; (c) a computer bus interface for transmitting stream received via a computer bus;

(d) a data converter for converting data received by the stream transmitter into data useable by the computer; and

15 (e) a data converter for converting data received from the computer into digitally streamed signals for an external receiver.

BRIEF DESCRIPTION OF DIAGRAMS

[039]

20 Figure 1 is a schematic representation of a preferred form of a system including a preferred embodiment of an interface according to the present invention;

Figure 2 is a schematic representation of a preferred form of the interface of Figure 1, configured to operate as a stream generator/driver;

25 Figure 3 is a schematic representation of a preferred form of implementation of the stream generator of Figure 2;

30 Figure 4 is a schematic representation of a preferred embodiment of the system including a more preferred embodiment of the interface of present invention for providing digital television content data to an external stream receiving device;

35

Figure 5 (a) is a schematic representation of another preferred form of the output of the interface according to the present invention, which is configured as a dual stream generator/driver;

5 Figure 5(b) is a schematic representation of the output of the interface of Figure 5(a) with additional components to further split the stream into multiple streams;

Figure 6 is a schematic representation of another preferred form of an interface of Figure 1, configured to receive a Multimedia stream and provide it to a computer;

Figure 7 is a schematic representation of a preferred form of the interface of Figure 6 configured to operate as a stream receiver;

15 Figure 8 is a schematic representation of a preferred embodiment of the system including a more preferred embodiment of the interface of the present invention for receiving digital television from an external digital TV stream transmission device and providing it to a computer;

Figure 9 is a schematic representation of another preferred embodiment of the system including a more preferred embodiment of the interface of the present invention for receiving digital signal from a source and providing it to a computer;

Figure 10 is a state diagram of a state machine of one embodiment of the interface of Figure 1;

30 Figure 11 is a software model for execution on a computer for controlling the computer to use the interface of Figure 1; and

Figure 12 is a system model representing the stream flow associated with the data and control signal generation of the transceiver.

DETAILED DESCRIPTION OF PREFERRED EMBODIMENTS

[040] Referring to Figure 1, there is shown a system 1 including a computer 2, an interface unit (data converter) 4, and an external device 6. The external device 6 is a stream transmitter/receiver. The computer 2 is preferably a personal computer (PC). The PC 2 is configured to generate digital content in a suitable format, pre-coded or otherwise, to transmit to the external device 6 via the interface unit 4 or to receive digital content transmitted from the external device 6 via the interface unit 4. The interface unit 4 communicates with the computer 2 by computer bus 8, preferably external buses. The interface unit 4 also transmits /receives the digital content as a utilizing an external device 6 via transport medium 10. The transport medium 10 is formed by multi-cord cable, ribbon cable, (with suitable interface) wireless, etc.

[041] A control signal cable 23 is optionally extended between the interface unit 4 and the external device 6 to provide function related control of the external device 6. This will be described further below.

[042] The characteristics of the signal sent over the transport medium 10 nominally comprise a digital signal consisting of 8 or 16-bits of data, clock and control signals at TTL or LVDS compatible voltage levels. Alternatively data/ control packets may be carried by radio frequency compatible with, Bluetooth, Wi-Fi (IEEE 802.11 b/a/g) or emerging UWB wireless standard or other standard protocols.

[043] Referring to Figure 2, in this system the interface unit 4 operates as a stream generator (streamer), and the external device 6 operates as a receiver. The PC 2 is configured to transmit digital content and control signals in a suitable format (for example, format 32 in Figure 12) to the stream generator 4 via the computer bus 8, this is conceived as external bus of the PC preferably high speed bus such as USB, Firewire etc. The

stream generator 4, sends the Multimedia stream and control signals in the appropriate format (for example, format 33 in Figure 12) to the receiver 6 via transport medium 10.

5 [044] Referring to Figure 3, the stream generator 4 includes a bus interface 12, a microprocessor 14, a First In First Out (FIFO) buffer 16, a Programmable Logic Device (PLD) (data converter) 18, and an Input/Output (I/O) port 20. The bus interface 12 interacts with the PC bus 8 to send and receive control and data signals according to the protocol of the PC bus 8. The microprocessor 14 is configured to control the bus interface 12, configure the FIFO buffer 16, program the PLD 18, and coordinate the data transfer from the bus interface 12 to FIFO buffer 16. Data is normally sent from the PC bus 8 in burst mode. The FIFO buffer 16 controls the flow of data transferred over the transport medium 10 by storing data sent over the computer bus 8 and by releasing this data to the I/O port 20 when requested by the PLD 18. The PLD 18 implements the Multimedia stream protocol required by the external device 6. It also interact with the external device 6 by control signals sent over the cable 23. The I/O Port 20 converts the TTL signal from the PLD 18 into an electrical form that is compatible with the transport medium 10 and external device 6.

25 [045] The PLD 18 is programmed to operate according to instructions stored on non-volatile memory by the microprocessor 14. The microprocessor 14 under the command of PC will reconfigure PLD 18. This is useful when the PLD 18 is programmed to provide digitally streamed data in one format and it is desired to send it in another format.

[046] Referring to Figure 4, in this embodiment the stream generator is configured to generate a MPEG2 Transport Stream (TS). The PC bus 8 is a Universal Serial Bus (USB) bus. A Cypress CY7C68013 microcontroller is used to perform the role of bus interface 12, microprocessor 14, FIFO buffer 16 and PLD 18. Here the bus interface 12 is a serial interface engine for USB.

The microprocessor 14 is a Cypress enhanced Intel 8051, CY7C68013 CPU. The FIFO buffer 16 is a pure slave FIFO buffer. The PLD 18 is in the form of a state machine, called a General Purpose Interface (GPIF) by CY7C68013. It acts as a master of the FIFO buffer 16, CY7C68013. The CY7C68013 GPIF offers a maximum of 6 control outputs, 6 control inputs and 9 address lines. It has up to seven programmable states. The operation of the GPIF 18 is controlled by programming stored on the non-volatile memory.

[047] To generate a MPEG2 Transport Stream in DVB Standard Parallel format, two data flow control signals are required in addition to the actual streamed data. A Packet Sync signal is asserted at the beginning of every TS packet. A Data Valid signal is asserted when the output contains useful TS data. These two signals are generated by a computer program which runs on the PC 2. The computer program is one of the software modules 25 in Figure 11 and is described further below.

[048] The I/O port 20 comprises a TTL to LVDS voltage converter. The output format conforms to a DVB Standard Parallel Interface, which consists of 8 data lines, two data flow control signal lines (which carry the Packet Sync. and Data Valid signals), and a clock signal line. The GPIF is programmed to generate the clock signal and the control signals from the data received from the PC 2. The Packet Sync. signal is asserted at the first byte of every Transport Stream (TS) packet, and the Data Valid signal is used to indicate when the output contains useful data.

[049] These two control signals are treated as normal data in the data sent to the stream generator 4 by the PC 2. One bit representing Packet Sync will be set to one on the first byte of every TS packet, and another bit representing Data Valid will be set to one for every useful data.

[050] Referring to Figure 12, the computer program 25 executing on PC 2 is used to preprocess the stream data 30 and generates the two control signals to be sent along with the TS packet data

30 to the stream generator 4 in a 16 bit format. The even bytes are used for TS packet data and the odd bytes are used for the control signals. These will be reflected in the signals 32 sent on the computer bus 8 to the stream generator 4.

5

[051] The GPIF 18 is configured as a 16-bit output port which divides the 16 bit data 33 into TS data (lines 0 to 7) and control signals (lines 8 & 9). The remaining bits (10 to 15) are unused.

10

[052] In operation the bus interface 12 and the PLD 18 are initialized to operate in the required mode for streamer operation. This includes the USB functionality, GPIF control modes and GPIF port functionality to transport data, and generate data flow control signals and the clock signal.

15

[053] Referring to Figure 10, the GPIF functions as a state machine having three types of states, namely: non-decision point, decision point and idle state. The GPIF allows a maximum of 6 non-idle states to be defined.

20

[054] The GPIF 18 contains several programmable control output pins. Each state determines the logic level of these output pins, the time delay, and also decides on whether to drive the data or whether to advance the FIFO buffer 16 pointer to fetch the next data. These operations are specified in each state definition data.

25

[055] The GPIF 18 is programmed according to the following steps. The time delay for each GPIF state is determined based on the transport stream data rate. The GPIF 18 receives an input clock signal of 48MHz from a clock signal generator (not shown). Thus, the inherent accuracy is one input clock period (20.8ns).

30

[056] For the implementation of the streamer, at least two non-decision point states are used. One of the GPIF control output pins is used as the output clock for the data stream.

35

[057] Four of the states are used to control the clock output. A GPIF transaction is regarded as reading or writing one byte (or one word if the GPIF is configured with a 16-bit port). A transaction starts in State 1. The first half of the four clock output control states (States 1 and 2) will set the clock output pin to be logic low. The other half of the four clock output control states (States 3 and 4) set the clock output to logic high. The state machine will remain in State 1 for n input clock cycles, where n is a quarter of the number of 20.8ns cycles required for one output clock cycle. The state machine will then move to State 2, where it will remain for another n input clock cycles. The state machine will then move to State 3, where the clock output pin is set to logical one. The state machine remains in this state for a further n input clock cycles and then moves to State 4, where it remains for $n-2$ input clock cycles and then moves to State 5. In State 5 the next data is fetched from the FIFO buffer 16 by advancing the buffer pointer. This state lasts for one input clock cycle and is a decision point, which is programmed to unconditionally branch to the next state, State 6. State 6 is a one input clock cycle idle state to end one transaction. After entering the idle state, State 6, the transaction will start all over again if there is data available.

[058] The GPIF will monitor the FIFO buffer 16 empty flag. If there is no data, the transfer will be halted. This is achieved by the microcontroller implementing a transaction counter. The transaction count is initialised to a high number and configured to count down by one for each completed transaction. If the counter reaches zero the state machine remains in the idle state. As more data is received from the PC 2 the transaction counter is re-initialised to the high number and the transfer is resumed.

[059] Referring to Figure 11, on the PC side, a device driver 27 is used to move data between the computer program 25 and the stream generator 4 through the USB 8. The driver does not need to have any knowledge of the stream format. It just treats any data

as a byte stream. Another driver 28 is responsible for handling the PC bus communication protocol, which in this case is USB.

[060] Referring to Figure 5(a), in this embodiment the output port operates as a dual output port, which includes a bi-phase clock generator 40 and two latch buffers 42 and 43 or instead of the buffers, a de-multiplexer. The rest of the system is similar to that in Figure 4. The stream output from the GPIF 18, consists of two data streams, which are multiplexed in byte intervals. The output clock runs at twice the speed of the stream clock. The output clock is used by the Bi-phase Clock Generator 40 to generate a Bi-phase Clock signal. The Bi-phase signal is used to select one of two output buffers 42 or 43 or to select the data to be separated by the de-multiplexer. Each output stream (from the buffers 42 & 43, or the de-multiplexer) is transmitted to separate transport mediums 10.

[061] Using the same method, it is possible to add virtually any numbers of outputs. For example, to add one additional output, two streams are multiplexed into one using the same method described above, and a third stream is then multiplexed with the previous resulting stream. The design of a further de-multiplexing output port is shown in Figure 5(b).

[062] The two output streams must have the same streaming rate. However, if one of the streams is slower than the other it is possible to insert dummy packets in the slower stream to maintain the stream rate. The multiplexing process is then straight forward. For example, the first byte of the multiplexed stream will contain the first byte of stream one, the second byte of the multiplexed stream will contain the control byte of stream one, the third byte will contain the first byte of stream two, the forth byte will contain the control byte of stream two, the fifth byte will be the second byte of stream one, and so forth.

[063] Referring to Figure 6, in this system, the interface unit 4 operates as a stream receiver, and the external device 6 operates

as a transmitter. The interface 4 receives the Multimedia stream via one or more transport mediums 10 and provides it to the PC 2. Cable 23 carries additional control signals to the external device 6. These control signals relate to the control of the operation of the external device and not the control of the data flow.

[064] Referring to Figure 7, the stream receiver 4 includes a bus interface 12, a microprocessor 14, a FIFO buffer 16, a Programmable Logic Device (PLD) 18, and an I/O port 20. The roles of these modules are similar to those in the stream generator of Figure 3, except that the data transfer direction is now from the external device 6 to the PC 2.

[065] Referring to Figure 8, in this embodiment the stream receiver is configured to receive a MPEG2 Transport Stream. The PC bus 8 is a USB bus. A Cypress CY7C68013 microcontroller is used to act as the bus interface 12, microprocessor 14, and FIFO 16. Here the bus interface 12 is a Serial Interface Engine (SIE) for USB. The microprocessor 14 is a Cypress enhanced Intel 8051 CPU. The cable 23 operates as a serial bus, namely as an IIC bus.

[066] The microprocessor 14 and the SIE 12 handle the USB communication with the PC 2. The FIFO buffer 16 is a slave buffer. The external stream transmitter 6 is a digital TV tuner. The tuner 6 for example is tuned to receive media transport streams; DTV Serial interface; DVB, Digital Terrestrial TV. The Multimedia stream format conforms to DTV Standard Parallel Interface, which contains parallel data synchronized to a tuner generated clock signal. Optionally tuner supporting any Digital TV (DTV) standard is used. If the output signal of the tuner is in TTL form it connects directly to the input pins of the microcontroller. Thus the I/O port 20 (Fig 3) merely passes the signals therethrough or is bypassed entirely. The data is transferred directly to the FIFO buffer 16 using timing signals provided by the tuner clock signal. If the stream produced by the tuner 6 is a MPEG2 TS, the Packet Sync. and the Data Valid

control inputs are not used. Therefore, the PLD 18 is also omitted or not by-passed.

[067] In operation the microprocessor 14 will first initialize the bus interface 12 and FIFO buffer 16. It also configures the I/O port 20 and PLD 18 to be by-passed. The Packet Sync. and Data Valid control signals are discarded. The stream data will be put into the FIFO buffer 16 first and inturn transferred to the PC 2 via USB 8 when the PC 2 sends a request for data. To achieve a high bit rate, the FIFO buffer 16 is configured to bypass the microprocessor and directly interface with SIE 12.

[068] On the PC side, the same device drivers are used for Stream Receiver as the ones for the Stream Generator to handle USB communication protocol and interface control.

[069] In Figure 9 the digital stream source 6 is a Signal Conditioner and Digital Stream Generator (SC & DSG). The SC & DSG modulates/encodes signals from either an analogue source or a digital source and applies the resulting digital stream to the transport medium 10. The digital stream is received by the interface unit 4 from the transmission medium 10. Using the input stream, containing data and associated clock signal (provided by the external device), the stream receiver 4 processes the data in similar manner to the description above for Figure 8. The GPIF 18 is programmed to implement the stream protocol to handle external handshaking signals to synchronize the communication with the external device 4. The I/O port 20 is used to convert the output electrical signal levels of the external digital source 6 to the logic level required by the PLD 18. The Serial Bus 23 is any serial bus standard (e.g. IIC). Again is provides operational control signals to the external device 6.

[070] Referring to Figure 10, the PC 2 operates under an operating system 24. Several software modules 25, 26 and 27 are used by the PC 2 operating system 24 to process the MPEG2 Transport Stream (TS), display videos, and/or play audios.

Suitable operating systems include Microsoft's Windows 2000 or Windows XP as well as various forms of Linux. In particular one of the modules 25, the computer program for generating data flow control signals that accompany the content data over the transport medium to the digital device 4.

[071] The operating system 24 will include a computer bus driver 28, for example a USB driver, PCI driver, IEEE 1394 etc., the appropriated one of which is used depending the computer bus 8 used.

[072] A Graphical User Interface (GUI) 26 is included in the operating system 24 or is supplied with the software modules 25 and 27 to provide a convenient method of interaction of a user with the software modules 25 to control the operation of the interface unit 4 and to control the PC 2 to provide the digital content to the external device 6 via interface unit 4 or use the digital content provided by the external device 6 via interface unit 4.

[073] An MPEG2 Transport Stream (TS) consists of a stream of packets 30. The TS packet has a constant size of 188 bytes. Each packet has a packet identifier (PID). There are several different types of packets, e.g. Program Specific Information (PSI) packet, Elementary Stream Packet, Network Information Packet, etc. A Transport Stream will normally consist of multiple TV programs. PSI packets are used to describe the contents the stream. PSI is actually a two level table. PID 0 is reserved for one type of PSI packet called Program Association Table (PAT). This table gives the PIDs of yet another PSI packet called Program Map Table (PMT). Each PMT corresponds to one program. It contains the PIDs for the video, audio and/or other data stream packets. Based on these tables, a computer program 25 picks the right packets for playing video / audio.

[074] One or more software modules 25 are used to handle various the protocols defined in Digital Television (DTV) Standards (DVB-

T, DVB-C, DVB-S, ATSC, etc.) These software modules is developed using the Microsoft DirectX Software Development Kit (SDK) 9.0. Specifically, Microsoft TV Technology in DirectShow (part of DirectX SDK) is used. The Microsoft DirectX SDK document is
5 available from Microsoft Corporation. DirectShow provides modules, which makes the underlying DTV Standard transparent to the user.

[075] One of the software modules 25 is used to control the tuner
10 device via the device driver 27. The software module is implemented as a DirectShow compatible Filter. The device driver 27 forwards the tuner related commands to the microcontroller through the USB. The microcontroller uses the serial bus 23 to communicate with the tuner device or other digital device 6 .
15 The tuner device 6 accepts control data via serial bus 23. A firmware program 29 running on microcontroller will pass the commands to tuner device 6 via the serial bus port 23.

[076] One of the software modules 25 is used to capture the data
20 stream received by the device driver 27. The core of this module is implemented in plain C++ with a wrap filter used to make it DirectShow compatible.

[077] Another of the software modules 25 is used to extract PSI
25 packets from the Transport Stream. A suitable software module is Microsoft's BDA Network Information Filter.

[078] Yet another of the software modules 25 is used to select
one or more programs (audio, visual, or data stream) out of the
30 Transport Stream. The core of this module is implemented in plain C++ with a wrap filter used written to make it DirectShow compatible.

[079] One (or more) software module(s) 25 is (are) used to decode
35 the stream to its constituent audio, visual, or data stream for rendering. The video decoder is any DirectShow compatible MPEG2 / MPEG4 decoder.

[080] One of the software modules 25 enables picture in picture facilities on the PC 2 to display multiple videos (in small windows) while tuned to a channel. A suitable module is
5 Microsoft's Video Mixing Renderer filter.

[081] Other software 31 is installed on the PC 2 to interact with the GUI 26, the digital data 30 or interface unit via driver
27.

10

[082] A person skilled in the art will realise that the use of a software programmable logic device (PLD) in the present invention allows the implementation of a plurality of communication protocols and device handshaking which is reprogrammed to
15 implement various communication protocols or handshaking between the interface unit 4 and the external device 6. This provides a generic way of transmitting/receiving data stream to/from a PC. Because it is software programmable, the user changes the communication protocol from the PC without there being any
20 changes to the interface unit.

[083] The skilled addressee will realise that modifications and variations can be made to the present invention without departing from the basic invention concept. Such a modification
25 implements a more complex handshaking interface (e.g. IDE), in this case, other PLD or programmable logic device (CPLD) or Field Programmable Gate Arrays (FPGA) chips is used to replace the GPIF. These chips are available from the following IC manufactures, Atmel's (AT40K and AT40KAL Series), Altera, Xilinx
30 (Spartan-3 FPGAs Vertex II Family devices) or Lattice (ispXPGA Family of FPGAs).

[084] Modifications and variations as would be obvious to the skilled addressees are intended to fall within the scope of the
35 present invention, the nature of which should be determined from the foregoing description and appended claims. It is to be

understood that the invention is not limited to the embodiments thereof.

CLAIMS

1. A "configurable / reconfigurable" interface for interfacing
a digital device (unit) for transmitting or receiving a
5 digital stream to a computer, the interface comprising:
a bidirectional configurable / reconfigurable interface
unit (4) containing a data converter (18) for a computer
bus (8) to facilitate the transfer of digital stream;
a bidirectional configurable / reconfigurable streamer
10 system (1) that is configured / reconfigured to match
electrical characteristics of the digital stream device -
external interface (6);
a bidirectional configurable / reconfigurable streamer
system (1) that is adopted to support characteristic of the
15 protocol of a stream that is being transferred.
2. An interface according to claim 1, wherein the data
converter (18) is configured / reconfigured to convert data
into a selected Multimedia stream format, the selected
20 protocol format being signalled to the data converter in
data provided by the computer (2) via the computer bus (8).
3. An interface according to claim 1, wherein the data
converter (18) is configured / reconfigured to convert the
25 Multimedia stream, from the protocol format provided by an
external device (6), into data usable by the computer (2),
the selected format being signalled to data converter (18)
in the data provided by the computer (2) via the computer
bus (8).
- 30 4. An interface according to claim 3, wherein the data
converter (18) is reconfigured to recognise the incoming
Multimedia stream format based on control packets received
from the external device (6).
- 35 5. An interface according to claim 1, wherein the computer bus
(8) is a Universal Serial Bus (USB), but not limited to it.

6. An interface according to claim 1, wherein the data converter (18) is a microcontroller (22).
- 5 7. An interface according to claim 6, wherein the microcontroller (22) includes a general programmable interface (18).
8. An interface according to claim 1, wherein the data
10 converter (18) is a state-machine.
9. An interface according to claim 8, wherein the state-machine (18) is a PLD or programmable logic arrays (PLA) or general programmable interface, that is configured /
15 reconfigured by program.
10. An interface according to claim 1, wherein the Multimedia stream type is one of an ATSC or DVB or ISDB or DMB compliant transport stream, any Digital TV standard
20 compliant transport stream, MPEG 2, MPEG 4, MPEG 7, satellite TV, TV tuner data, AC3, MP3, Dolby stereo, IEEE1394, IEEE488 or digital radio format. In addition includes data acquisition formats.
- 25 11. 11. An interface according to claim 10, wherein the tuner type (6, Fig 7) is terrestrial, cable, satellite and handheld device, but not limited to these.
12. An interface according to claim 1, wherein the Multimedia
30 stream is video or sound or data, formatted in any protocols.
13. An interface according to claim 1, wherein the data
35 converter (18) generates one or more control signals (23) for control of the Multimedia stream delivery to the external device (6).

14. An interface according to claim 12, wherein the control signals (23) are generated according to protocol requirements of the transport stream type, the transceiver generates a digital clock signal or digital control signals.
- 5
15. An interface according to claim 1, wherein the transceiver transmission rate is controlled by a signal provided by the computer (2) to the data converter (18) via the computer bus (8).
- 10
16. An interface according to claim 1, wherein the data is provided by the computer bus (8) to the computer bus interface (12) in bursts or in continuous data which are buffered (16) by the transceiver (18) and transmitted to the transmission medium (10) in a digital stream, at commanded
- 15
17. An interface according to claim 16, wherein the transceiver buffers (16) the Multimedia stream sent by the external device (6).
- 20
18. An interface according to claim 16, wherein the interface includes a buffer (16) for buffering the data passing therethrough.
- 25
19. An interface according to claim 1, wherein the data converter (18) is configured / reconfigured by data provided by a computer program (Fig 11).
- 30
20. An interface according to claim 19, wherein the computer program (Fig 11) provides data to the data converter (16) via the computer bus (8) and in turn via the computer bus interface (12).
- 35
21. An interface according to claim 19, wherein the computer program (Fig 11) includes a system driver for providing

control of the operation of data converter (18) or transceiver (20) or digital device (6).

22. An interface according to claim 19, wherein the computer program (Fig 11) controls the display of video or playing of sound, coded in the Multimedia stream(s) provided by the External stream receiver, in a single or multiple windows (picture-in-picture).
23. An interface according to claim 1, wherein the computer program (Fig 11) interfaces with the operating system (OS) of the computer (2).
24. An interface according to claim 1, wherein the data converter (18) includes a serial bus input / output port that is configured / reconfigured to generate serial bus signals for activation or control of the digital device (6).
25. An interface according to claim 24, wherein the serial bus signals (23) are generated by software running on the microcontroller (4) or hardware / firmware of the interface.
26. An interface according to claim 24, wherein the serial bus signals (23) are generated according to instructions provided by the computer (Fig 11) in data sent to the microcontroller (4) and stored in the interface (4).
27. An interface according to claim 24, wherein the serial bus signals (23) are generated to be compliant with standard associated with external device.
28. An interface according to claim 1, wherein the interface comprises bidirectional port (20).
29. According to claims 1-28, a configurable / reconfigurable receiver system (Fig 6) to facilitate the transfer of

Multimedia stream, of differing standards, from an external device (6, Fig 6).

- 5 30. According to claim 29, a digital broadcast receiving system.
In one embodiment the receiver is USB interfaced Digital TV receiver, utilising Tuner Fronted Fig 8.
- 10 31. According to claims 1-28, a configurable / reconfigurable transmitter system (1, Fig 2) to facilitate the transfer of Multimedia stream from a computer (2) via a computer bus (8) to an external stream transmitter (6).
- 15 32. According to claim 31, a digital media transmitter system.
In one embodiment the receiver is USB interfaced MPEG2 stream driver (Fig 4).
- 20 33. An interface according to claim 32, wherein the Multimedia stream transmitter (Fig 2) transmits multiplexed stream (Fig 5a, Fig 5b).
- 25 34. An interface according to claim 33, wherein the data stream is provided to respective buffers (16) and de-multiplexed by a dual or multiphase clock.
- 30 35. An interface according to claim 34, wherein the I/O port (35) is configured / reconfigured to de-multiplex the stream in to two or more single streams (Fig 5a, Fig 5b).
36. According to claim 1, 29 & 31 any embodiment is integrated on to the PC Motherboard.