

COMMUNICATION METHOD, TERMINAL, AND NETWORK DEVICE

5

TECHNICAL FIELD

The disclosure relates to the field of communications, and in particular to a communication method, a terminal and a network device.

10

BACKGROUND

In a New Radio (NR) system such as 5th-Generation (5G), uplink channels or
15 uplink signals with various time lengths may be supported between a terminal and a base station. For example, the terminal may transmit an uplink channel or an uplink signal by using a time domain symbol in a first time slot.

In the NR system, the base station generally reserves resources for
transmitting a certain uplink channel or uplink signal for the terminal, resulting in that
20 a great number of resource fragments exist in the NR system. Moreover, in the reserved resources, it is possible that only a small amount of resources are actually used for transmitting the original uplink channel or the original uplink signal.

If these resource fragments cannot be used by other channels or signals, the resources will be wasted, resulting in a low utilization rate of the resources.

25

SUMMARY

The disclosure provides a communication method, a terminal and a network
30 device, which may flexibly improve the utilization rate of a resource.

According to a first aspect, the disclosure provides a communication method, which may include that, a terminal receives first indication information transmitted by a network device, the first indication information being used to indicate a first resource; and the terminal transmits, according to the first indication information, an
35 uplink channel or an uplink signal to the network device on a third resource within a

second resource, the third resource being a resource within the second resource non-overlapped with the first resource.

In the communication method of the disclosure, the terminal may transmit, according to the first indication information transmitted by the network device, the
5 uplink signal or the uplink channel on the third resource non-overlapped with the first resource indicated by the first indication information in the second resource. Therefore, the terminal may flexibly use a resource within the second resource to transmit the uplink signal or the uplink channel according to the indication information of the network device, thus improving the utilization rate of the resource
10 within the second resource.

In a possible implementation manner, the first indication information is used to indicate at least one of the following: a time domain position of the first resource, or a frequency domain position of the first resource.

In a possible implementation manner, the action that the terminal transmits,
15 according to the first indication information, an uplink channel or an uplink signal to the network device on a third resource within a second resource, the third resource being a resource non-overlapped with the first resource within the second resource may include that, the terminal determines a first number of resource units in the second resource; the terminal performs rate matching for the uplink channel or the
20 uplink signal according to the first number, to obtain an output sequence having a length of a first bit number, the first bit number being determined by the terminal according to the first number; the terminal modulates the output sequence to obtain a first number of modulated symbols; and the terminal maps the first number of modulated symbols to the resource units in the second resource, where the terminal
25 drops modulated symbols mapped to first resource units in the first number of modulated symbols, and the first resource units are resource units in the second resource overlapped with the first resource.

In a possible implementation manner, that the terminal transmits, according to the first indication information, an uplink channel or an uplink signal to the network
30 device on a third resource within a second resource, the third resource being a resource within the second resource non-overlapped with the first resource may include that, the terminal determines a second number of first resource units in the second resource, the first resource units being resource units in the second resource

non-overlapped with the first resource; the terminal performs rate matching for the uplink channel or the uplink signal according to the second number, to obtain an output sequence having a length of a second bit number, the second bit number being determined by the terminal according to the second number; the terminal modulates
5 the output sequence to obtain a second number of modulated symbols; and the terminal maps the second number of modulated symbols to the second number of first resource units.

In a possible implementation manner, the first indication information is used to indicate N time domain symbols included in the first resource, where the N is a
10 nonnegative integer. The action that the terminal transmits, according to the first indication information, an uplink channel or an uplink signal to the network device on a third resource within a second resource, the third resource being a resource within the second resource non-overlapped with the first resource may include that, the terminal transmits, according to the first indication information, the uplink channel or
15 the uplink signal to the network device on the third resource within the second resource, where M time domain symbols included in the third resource exclude the N time domain symbols, M is a positive integer.

In a possible implementation manner, the action that a terminal receives first indication information transmitted by a network device may include that, the terminal
20 receives downlink control information transmitted by the network device, where the downlink control information carries the first indication information, the downlink control information further carries second indication information, and the second indication information is used to instruct the terminal to transmit the uplink channel or the uplink signal.

25 In a possible implementation manner, the first resource is a resource used by the terminal or other terminals to transmit an uplink control channel, an uplink sounding signal, or a random access channel, and the uplink channel includes an uplink shared channel.

According to a second aspect, the disclosure provides a communication
30 method, which may include that, a network device transmits first indication information to a terminal, the first indication information being used to indicate a first resource; and the network device receives an uplink channel or an uplink signal transmitted by the terminal on a third resource within a second resource according to

the first indication information, the third resource being a resource within the second resource non-overlapped with the first resource.

In the communication method of the disclosure, the network device transmits the first indication information to the terminal, so that the terminal may transmit,
5 according to the first indication information, the uplink signal or the uplink channel on the third resource, which is non-overlapped with the first resource and is indicated by the first indication information, within the second resource. Therefore, the terminal may flexibly use a resource within the second resource to transmit the uplink signal or the uplink channel according to the indication information of the network device, thus
10 improving the utilization rate of the resource within the second resource.

In a possible implementation manner, the first indication information is used to indicate at least one of the following: a time domain position of the first resource, or a frequency domain position of the first resource.

In a possible implementation manner, the action that the network device
15 receives an uplink channel or an uplink signal transmitted by the terminal on a third resource within a second resource according to the first indication information may include that, the network device acquires modulated symbols corresponding to the uplink channel or the uplink signal in resource units included in the second resource, where the number of the modulated symbols is equal to the number of the resource
20 units included in the second resource, the network device drops modulated symbols acquired on first resource units, and the first resource units are resource units in the second resource overlapped with those in the first resource.

In a possible implementation manner, the action that the network device receives an uplink channel or an uplink signal transmitted by the terminal on a third
25 resource within a second resource according to the first indication information may include that, the network device acquires modulated symbols corresponding to the uplink channel or the uplink signal on first resource units in resource units included in the second resource, where the number of the modulated symbols is equal to the number of the first resource units included in the second resource, and the first
30 resource units are resource units in the second resource non-overlapped with those in the first resource.

In a possible implementation manner, the first indication information is used to indicate N time domain symbols included in the first resource, where the N is a

nonnegative integer. The action that the network device receives an uplink channel or an uplink signal transmitted by the terminal on a third resource within a second resource according to the first indication information, the third resource being a resource non-overlapped with the first resource within the second resource may
5 include that, the network device receives the uplink channel or the uplink signal transmitted by the terminal on the third resource within the second resource according to the first indication information, where M time domain symbols included in the third resource exclude the N time domain symbols, M is a positive integer.

In a possible implementation manner, the action that a network device
10 transmits first indication information to a terminal may include that, the network device transmits downlink control information to the terminal, where the downlink control information carries the first indication information, the downlink control information further carries second indication information, and the second indication information is used to instruct the terminal to transmit the uplink channel or the uplink
15 signal.

In a possible implementation manner, the first resource is a resource used by the terminal or other terminals to transmit an uplink control channel, an uplink sounding signal, or a random access channel, and the uplink channel includes an uplink shared channel.

20 According to a third aspect, the disclosure provides a terminal, which may include modules configured to execute the communication method in the first aspect or any possible implementation manner of the first aspect.

According to a fourth aspect, the disclosure provides a network device, which may include modules configured to execute the communication method in the second
25 aspect or any possible implementation manner of the second aspect.

According to a fifth aspect, the disclosure provides a communication system, which may include the terminal in the third aspect and the network device in the fourth aspect.

According to a sixth aspect, the disclosure provides a terminal, which may
30 include a receiver, a transmitter, a processor and a memory; the memory is configured to store codes; the processor is configured to execute the codes in the memory; the receiver and the transmitter are configured to communicate with other devices; when the codes are executed, the processor calls the receiver and the transmitter to

implement the communication method in the first aspect or any possible implementation manner of the first aspect.

According to a seventh aspect, the disclosure provides a network device, which may include a receiver, a transmitter, a processor and a memory; the memory is configured to store codes; the processor is configured to execute the codes in the memory; the receiver and the transmitter are configured to communicate with other devices; when the codes are executed, the processor calls the receiver and the transmitter to implement the communication method in the second aspect or any possible implementation manner of the second aspect.

According to an eighth aspect, the disclosure provides a communication system, which may include the terminal in the sixth aspect and the network device in the seventh aspect.

According to a ninth aspect, the disclosure provides a computer readable medium; the computer readable medium stores program codes executed by a terminal; and the program codes include instructions used for executing the communication method in the first aspect or any possible implementation manner of the first aspect.

According to a tenth aspect, the disclosure provides a computer readable medium; the computer readable medium stores program codes executed by a network device; and the program codes include instructions used for executing the communication method in the second aspect or any possible implementation manner of the second aspect.

BRIEF DESCRIPTION OF DRAWINGS

FIG. 1 illustrates a schematic system architecture diagram of a communication method that may be applied to the disclosure.

FIG. 2 illustrates a schematic diagram of resource allocation in a communication method according to an embodiment of the disclosure.

FIG. 3 illustrates a schematic flowchart of a communication method according to an embodiment of the disclosure.

FIG. 4 illustrates a schematic flowchart of a communication method according to an embodiment of the disclosure.

having a wireless communication function, a computing device or other processing devices, vehicle-mounted devices or wearable devices connected to a wireless modulator-demodulator, a terminal device in a future 5G network or the like.

5 In this embodiment of the disclosure, the network device 120 may be a Base Transceiver Station (BTS) in a Global System for Mobile communication (GSM) system or a Code Division Multiple Access (CDMA) system, or may be a NodeB in a Wideband Code Division Multiple Access (WCDMA) system, or may be an Evolutional Node B (eNB or eNodeB) in a Long Term Evolution (LTE) system or a base station device, a small base station device or the like in the future 5G network,
10 all of which are not defined by the disclosure.

The terminal 110 and the network device 120 may transmit an uplink signal or an uplink channel by using one or more time domain symbols in a time slot, e.g., transmit a Physical Uplink Control Channel (PUCCH).

Generally, the network device 120 reserves a resource for transmitting a
15 certain uplink signal or uplink channel for the terminal 110, e.g., reserves the resource for transmitting the PUCCH as illustrated in FIG. 2. As a result, a great number of resource fragments exist in the communication system. If these resource fragments cannot be used by other channels, the resources will be wasted, resulting in a low utilization rate of the resources.

20 In the communication system, resource reservation for a certain uplink signal or the uplink channel may cause all resources in time domain symbols included in the resource reserved for the uplink signal or the uplink channel unavailable to other uplink signals or uplink channels, and thus resource fragments in the time domain symbols included in the reserved resource are wasted, resulting in a low utilization
25 rate of the resources.

Therefore, the disclosure proposes a new communication method, with which the terminal can utilize resource fragments to transmit the uplink channel or the uplink signal adequately and reasonably according to an indication of the network device, to improve the utilization rate of the resources.

30 FIG. 3 illustrates a schematic flowchart of a communication method according to an embodiment of the disclosure. It should be understood that, actions or operations of the communication method illustrated in FIG. 3 are merely examples.

Other operations or variations of each operation in FIG. 3 may also be executed in this embodiment of the disclosure.

At S310, a network device transmits first indication information to a terminal. The first indication information is used to indicate a first resource.

5 At S320, the network device receives an uplink channel or an uplink signal transmitted by the terminal on a third resource within a second resource according to the first indication information. The third resource is a resource within the second resource non-overlapped with the first resource.

10 In the communication method of this embodiment of the disclosure, the network device transmits the first indication information indicating the first resource to the terminal, so that the terminal may transmit, according to the indication of the first indication information, the uplink channel or the uplink signal on the third resource within the second resource non-overlapped with the first resource. Therefore, the terminal may adequately utilize the resource within the second resource while
15 avoiding using the first resource, and thus the utilization rate of the resource is improved.

Correspondingly, FIG. 4 illustrates the schematic flowchart of the communication method executed by the terminal in this embodiment of the disclosure. It should be understood that, actions or operations of the communication method
20 illustrated in FIG. 4 are merely an example. Other operations or variations of each operation in FIG. 4 may also be executed in this embodiment of the disclosure.

At S410, a terminal receives first indication information transmitted by a network device. The first indication information is used to indicate a first resource.

25 At S420, the terminal transmits, according to the first indication information, an uplink channel or an uplink signal to the network device on a third resource within a second resource. The third resource is a resource within the second resource non-overlapped with the first resource.

30 In the communication method of this embodiment of the disclosure, the terminal receives the first indication information transmitted by the network device and indicating the first resource, so that the terminal may transmit, according to the indication of the first indication information, the uplink channel or the uplink signal on the third resource within the second resource non-overlapped with the first resource. Therefore, the terminal may adequately utilize the resource within the

second resource while avoiding using the first resource, and thus the utilization rate of the resource is improved.

In the communication method illustrated in FIG. 3 and FIG. 4, the first resource may be a resource reserved by the network device for the terminal or other terminals to transmit the uplink signal or the uplink channel to the network device.

Specifically, the first resource may be a resource reserved by the network device for the terminal or other terminals to transmit an uplink control channel, an uplink sounding signal, or a random access channel to the network device. In other words, the first resource may be a resource used by the terminal or other terminals to transmit the uplink control channel, the uplink sounding signal, or the random access channel. E.g., the first resource may be a resource used by the terminal or other terminals to transmit the PUCCH, the Sounding Reference Signal (SRS), or Physical Random Access Channel (PRACH).

A specific example of the uplink channel in action S320 and action S420 is a Physical Uplink Shared Channel (PUSCH).

The second resource may be a resource that may be used by the terminal to transmit the uplink channel or the uplink signal, or a resource allocated for the terminal by the network device in advance and used for transmitting the uplink channel or the uplink signal.

The first indication information may be specifically used to indicate time domain symbols included in the first resource, or the first indication information may be specifically used to indicate a time domain position of the first resource and/or a frequency domain position of the first resource.

More specifically, the first indication information may be specifically used to indicate positions of the time domain symbols included in the first resource and/or the number of the time domain symbols included in the first resource.

If the terminal and the network device determine or set the positions of the time domain symbols included in the first resource in advance, e.g., the time domain symbols included in the first resource are last one or more time domain symbols in a time slot, to which the first resource belongs, the first indication information may only indicate the number of the time domain symbols included in the first resource. In this way, the terminal may also determine the positions of the time domain symbols

included in the first resource according to the indication of the first indication information.

If the first indication information is used to indicate N time domain symbols included in the first resource, N is a nonnegative integer, generally, the network device may transmit the first indication information to the terminal in the following manner: the network device transmits downlink control information to the terminal, where the downlink control information carries the first indication information.

Correspondingly, the terminal may receive the first indication information transmitted by the network device in the following manner: the terminal receives the downlink control information transmitted by the network device, where the downlink control information carries the first indication information.

The downlink control information may specifically be Downlink Control Information (DCI).

Alternatively, the downlink control information may further carry second indication information, and the second indication information is used to instruct the terminal to transmit the uplink channel or the uplink signal.

In other words, the network device may transmit the downlink control information to the terminal, where the downlink control information carries the second indication information, and the second indication information is used for scheduling the terminal to transmit the uplink channel or the uplink signal. Meanwhile, the downlink control information further carries the first indication information, and the first indication information is used to indicate N time domain symbols included in the first resource. In this way, when the terminal receives the downlink control information, and transmits the uplink signal or the uplink channel according to the scheduling of the second indication information, the terminal may also determine, according to the indication of the first indication information, a resource that should be used for transmitting the uplink signal or the uplink channel, i.e., the third resource within the second resource non-overlapped with the first resource.

If N is equal to 0, it indicates that the terminal may use all resources within the second resource, i.e., the third resource may be the second resource.

Hereinafter, with the PUCCH and the PUSCH as an example, a schematic diagram of resource utilization in the communication method according to this embodiment of the disclosure is described in combination with FIG. 5 and FIG. 6.

As illustrated in FIG. 5, if the first resource reserved by the network device for the PUCCH is really used by a corresponding terminal to transmit the PUCCH, the network device may transmit the first indication information to this terminal and/or other terminal to indicate N time domain symbols included in the first resource. In this way, after these terminals receive the first indication information, the third resource may be used to transmit the PUSCH, where the third resource includes time domain symbols other than the N time domain symbols.

As illustrated in FIG. 6, if the resource reserved by the network device for the PUCCH is not really used by the corresponding terminal to transmit the PUCCH, although the resource reserved for the PUCCH includes N time domain symbols, the network device may also transmit the first indication information to this terminal and/or other terminals to indicate that the first resource includes no time domain symbol. In this way, after these terminals receive the first indication information, the third resource may be used to transmit the PUSCH, where the third resource may include the N time domain symbols included in the resource reserved for the PUCCH.

As can be seen directly from FIG. 5 and FIG. 6, in the communication method of this embodiment of the disclosure, the network device may transmit the indication information used to indicate the first resource, so that the terminal may utilize the resource reserved by the network device flexibly, reasonably and adequately, to transmit the uplink resource or the uplink channel, thus improving the utilization rate of the resource.

If the first indication information is specifically used to indicate the time domain position and/or the frequency domain position of the first resource, generally, the network device may transmit the first indication information to the terminal in the following manner: the network device transmits high-level signaling to the terminal, where the high-level signaling carries the first indication information.

At this moment, in the action S420, the uplink channel or the uplink signal transmitted by the terminal may be an uplink channel or an uplink signal scheduled by the network device via the downlink control information such as a PUSCH, or may be a semi-static uplink channel or an uplink signal such as a semi-static PUSCH, or may be an uplink channel or an uplink signal not scheduled.

Alternatively, if the first indication information is used to indicate the N time domain symbols included in the first resource, in the action S420 of the

communication method illustrated in FIG. 4, the action that the terminal transmits, according to the first indication information, the uplink channel or the uplink signal to the network device on the third resource within the second resource, the third resource being a resource non-overlapped with the first resource within the second resource may include that, the terminal transmits, according to the first indication information, the uplink channel or the uplink signal to the network device on the third resource within the second resource, where M time domain symbols included in the third resource exclude the N time domain symbols, M is a positive integer.

Correspondingly, in the action S320 of the communication method illustrated in FIG. 3, the action that the network device receives an uplink channel or an uplink signal transmitted by the terminal on a third resource within a second resource according to the first indication information may include that, the network device receives the uplink channel or the uplink signal transmitted by the terminal on the third resource within the second resource according to the first indication information, where M time domain symbols included in the third resource exclude the N time domain symbols, M is a positive integer.

In other words, the network device may indicate the N time domain symbols included in the first resource of the terminal via the first indication information. In this way, the terminal may use, according to the indication of the first indication information, the third resource except for the N time domain symbols, to transmit the uplink signal or the uplink channel. Therefore, the method may avoid the terminal from using the first resource to transmit the uplink signal or the uplink channel, and thus avoid affecting other transmissions of the uplink signal or the uplink channel using the first resource.

Alternatively, if the first indication information is used to indicate the time domain position and/or the frequency domain position of the first resource, in the action S420 of the communication method illustrated in FIG. 4, the action that the terminal transmits, according to the first indication information, an uplink channel or an uplink signal to the network device on a third resource within a second resource, the third resource being a resource non-overlapped with the first resource within the second resource may include that, the terminal determines a first number of resource units in the second resource; the terminal performs rate matching for the uplink channel or the uplink signal according to the first number, to obtain an output

sequence having a length of a first bit number, the first bit number being determined by the terminal according to the first number; the terminal modulates the output sequence, to obtain a first number of modulated symbols; and the terminal maps the first number of modulated symbols to the resource units in the second resource, where
5 the terminal drops modulated symbols mapped to first resource units in the first number of modulated symbols, and the first resource units are resource units in the second resource overlapped with those in the first resource.

Correspondingly, in the action S320 of the communication method illustrated in FIG. 3, the action that the network device receives an uplink channel or an uplink
10 signal transmitted by the terminal on a third resource within a second resource according to the first indication information may include that, the network device acquires modulated symbols corresponding to the uplink channel or the uplink signal in resource units included in the second resource, where the number of the modulated symbols is equal to the number of the resource units included in the second resource,
15 the network device drops modulated symbols acquired on first resource units, and the first resource units are resource units in the second resource overlapped with those in the first resource.

The first number of the resource units in the second resource is the number of the resource units in the second resource.

Specifically, the terminal may firstly determine the number of resource units
20 which are included in the second resource and used for transmitting the uplink signal or the uplink channel. Then, the terminal performs the rate matching for the uplink signal or the uplink channel according to the number of the resource units included in the second resource, to obtain the output sequence. The bit number of the output
25 sequence is relevant to the number of the resource units included in the second resource, or the bit number of the output sequence is determined by the terminal according to the number of the resource units included in the second resource. The terminal modulates the output sequence to obtain a certain number of modulated symbols, where the number of the modulated symbols is equal to the number of the
30 resource units included in the second resource.

In other words, if the number of the resource units included in the second resource is the first number and the bit number of the output sequence is a first bit

number, the first bit number is determined by the terminal according to the first number and the number of the modulated symbols is equal to the first number.

Then, the terminal maps the first number of modulated symbols to the resource units included in the second resource. The specific mapping process is as follows: the terminal maps any one of the first number of modulated symbols to a resource unit in the second resource. If the resource unit, to which the modulated symbol is to be mapped, is a resource unit in a resource within the second resource overlapped with the first resource, the terminal drops the modulated symbol, i.e., the modulated symbol is not mapped to the resource unit. When a resource unit, to which the modulated symbol is to be mapped, is a resource the second resource non-overlapped with the first resource, the modulated symbol is mapped to this corresponding resource unit.

In this way, although the first number of modulated symbols for the uplink signal or the uplink channel are mapped to the first number of resource units in the second resource, as a matter of fact, the modulated symbols for the uplink signal or the uplink channel are not mapped to the resource units that are overlapped in the second resource and the first resource, and the modulated symbols for the uplink signal or the uplink channel are only mapped to the resource units in the second resource that are non-overlapped with the first resource. At this moment, the resource units in the second resource that are non-overlapped with the first resource form the third resource. Such a resource mapping process may also be called punching.

Assuming that the first number of resource units in the second resource is k and the number of the resource units in the second resource that are overlapped with the first resource is s , when the k modulated symbols for the uplink signal or the uplink channel are mapped to the k resource units, the modulated symbols for the uplink signal or the uplink channel are not mapped to the s resource units in the k resource units in fact.

According to the resource mapping process in the method for transmitting the uplink signal or the uplink channel with the first resource indicated by the first indication information, when the terminal transmits the uplink signal or the uplink channel, resource fragments related to the first resource may be adequately utilized, while the first resource is not taken up, thus transmission of other uplink signals or uplink channels would not be affected.

It is to be noted that, the action that the network device drops the modulated symbols acquired on the first resource units includes that, the network device drops, when acquiring modulation sequence numbers carried on resource units of the second resource to obtain corresponding uplink channels or uplink signals, the modulated symbols acquired on the first resource units. However, the modulated symbols actually carried on the first resource units may be used for acquiring other uplink signals or uplink channels.

Alternatively, if the first indication information is used to indicate the time domain position and/or the frequency domain position of the first resource, in the action S420 of the communication method illustrated in FIG. 4, the action that the terminal transmits, according to the first indication information, an uplink channel or an uplink signal to the network device on a third resource within a second resource, the third resource being a resource non-overlapped with the first resource within the second resource may include that the following. The terminal determines a second number of first resource units in the second resource, the first resource units being resource units in the second resource non-overlapped with those in the first resource. The terminal performs rate matching for the uplink channel or the uplink signal according to the second number to obtain an output sequence having a length of a second bit number, the second bit number being determined by the terminal according to the second number. The terminal modulates the output sequence to obtain a second number of modulated symbols. The terminal maps the second number of modulated symbols to the second number of first resource units.

Correspondingly, in the action S320 of the communication method illustrated in FIG. 3, the action that the network device receives an uplink channel or an uplink signal transmitted by the terminal on a third resource within a second resource according to the first indication information may include that, the network device acquires modulated symbols corresponding to the uplink channel or the uplink signal on first resource units in resource units included in the second resource, where the number of the modulated symbols is equal to the number of the first resource units included in the second resource, and the first resource units are resource units in the second resource non-overlapped with those in the first resource.

The second number of first resource units in the second resource is the number of the first resource units in the second resource.

Specifically, the terminal may firstly determine the number (for the convenience of subsequent description, this number is called the second number) of resource units in the second resource, which are non-overlapped with the first resource and used for transmitting the uplink signal or the uplink channel (for the convenience of subsequent description, the non-overlapped resource units are called the first resource units). Then, the terminal performs the rate matching for the uplink signal or the uplink channel according to the second number, to obtain the output sequence. The bit number (for the convenience of subsequent description, this bit number is called a first bit number) of the output sequence is relevant to the second number, or the first bit number is determined by the terminal according to the second number. The terminal modulates the output sequence to obtain a certain number of modulated symbols, where the number of the modulated symbols is equal to the second number.

In other words, if the number of the first resource units in the second resource non-overlapped with the first resource is the second number, the first bit number is a bit number determined by the terminal according to the second number, and the number of the modulated symbols is equal to the second number.

Then, the terminal maps the second number of the modulated symbols to the second number of the first resource units included in the second resource. The specific mapping process is as follows: when the terminal is to map any one of the second number of the modulated symbols to a resource unit included in the second resource, if the resource unit, to which the modulated symbol is to be mapped, is a resource unit in a resource within the second resource overlapped with the first resource, the terminal skips over this resource unit and turns to determine whether the next resource unit is a resource unit in a resource within the second resource overlapped with the first resource. If the resource unit is determined to be a resource unit in the second resource non-overlapped with the first resource, i.e., a first resource unit, the terminal maps the modulated symbol to this corresponding resource unit.

In this way, the modulated symbols of the uplink signal or the uplink channel are only mapped to the first resource units in the second resource non-overlapped with the first resource. The resource units in the second resource that are non-overlapped with the first resource form the third resource.

Assuming the second number of the second resource units in the second resource is k , k modulated symbols of the uplink signal or the uplink channel may be mapped to the k first resource units.

5 Through the resource mapping process in the method for transmitting the uplink signal or the uplink channel with the first resource indicated by the first indication information, when the terminal transmits the uplink signal or the uplink channel, resource fragments related to the first resource may be adequately utilized, while the first resource is not taken up, thus transmission of other uplink signals or uplink channels would not be affected.

10 The communication method in the embodiments of the disclosure has been described above. Hereinafter, the terminal, the network device and the communication system in the embodiments of the disclosure will be described below.

FIG. 7 illustrates a schematic structural diagram of a terminal 700 according to an embodiment of the disclosure. It should be understood that the terminal illustrated in FIG. 7 is merely an example. The terminal in this embodiment of the disclosure may further include other modules or units, or may include modules similar to the respective modules in FIG. 7 in terms of functions, or may not include all modules in FIG. 7.

20 A receiving module 710 is configured to receive first indication information transmitted by a network device. The first indication information is used to indicate a first resource.

A transmitting module 720 is configured to transmit, according to the first indication information, an uplink channel or an uplink signal to the network device on a third resource within a second resource. The third resource is a resource within the second resource non-overlapped with the first resource.

25 In this embodiment of the disclosure, the terminal may transmit, according to the first indication information transmitted by the network device, the uplink signal or the uplink channel on the third resource non-overlapped with the first resource within the second resource indicated by the first indication information, and thus the terminal may flexibly use a resource within the second resource to transmit the uplink signal or the uplink channel according to the indication information of the network device, to improve the utilization rate of the resource within the second resource.

Alternatively, in an embodiment, the first indication information is used to indicate at least one of the following: a time domain position of the first resource, or a frequency domain position of the first resource.

Alternatively, in an embodiment, the transmitting module is specifically
5 configured to: determine a first number of resource units in the second resource; perform rate matching for the uplink channel or the uplink signal according to the first number, to obtain an output sequence having a length of a first bit number, the first bit number being determined by the terminal according to the first number; modulate the
10 output sequence, to obtain a first number of modulated symbols; and map the first number of modulated symbols to the resource units in the second resource, drop modulated symbols mapped to first resource units in the first number of modulated symbols, the first resource units being resource units in the second resource overlapped with those in the first resource.

Alternatively, in an embodiment, the transmitting module is specifically
15 configured to: determine a second number of first resource units in the second resource, the first resource units being resource units in the second resource non-overlapped with those in the first resource; perform rate matching for the uplink channel or the uplink signal according to the second number, to obtain an output sequence having a length of a second bit number, the second bit number being
20 determined by the terminal according to the second number; modulate the output sequence to obtain a second number of modulated symbols; and map the second number of modulated symbols to the second number of first resource units.

Alternatively, in an embodiment, the first indication information is used to indicate N time domain symbols included in the first resource, where the N is a
25 nonnegative integer. The transmitting module is specifically configured to: transmit, according to the first indication information, the uplink channel or the uplink signal to the network device on the third resource within the second resource, where M time domain symbols included in the third resource exclude the N time domain symbols, M is a positive integer.

30 Alternatively, in an embodiment, the receiving module is specifically configured to: receive downlink control information transmitted by the network device, where the downlink control information carries the first indication information, the downlink control information further carries second indication information, and

the second indication information is used to instruct the terminal to transmit the uplink channel or the uplink signal.

Alternatively, in an embodiment, the first resource is a resource used by the terminal or other terminals to transmit an uplink control channel, an uplink sounding
5 signal or a random access channel, and the uplink channel includes an uplink shared channel.

It should be understood that, the above and other operations and/or functions of each unit of the terminal 700 illustrated in FIG. 7 in this embodiment of the disclosure respectively implement corresponding processes of the communication
10 method in FIG. 4, and will not be repeated here for the brief description.

FIG. 8 illustrates a schematic structural diagram of a network device 800 according to an embodiment of the disclosure. It should be understood that, the network device illustrated in FIG. 8 is merely an example. The network device in this embodiment of the disclosure may further include other modules or units, or include
15 modules similar to the respective modules in FIG. 8 in terms of functions, or may not include all modules in FIG. 8.

A transmitting module 810 is configured to transmit first indication information to a terminal, the first indication information being used to indicate a first resource.

20 A receiving module 820 is configured to receive an uplink channel or an uplink signal transmitted by the terminal on a third resource within a second resource according to the first indication information, the third resource being a resource within the second resource non-overlapped with the first resource.

In this embodiment of the disclosure, the network device transmits the first
25 indication information to the terminal, so that the terminal may transmit, according to the first indication information, the uplink signal or the uplink channel on the third resource, which is non-overlapped with the first resource and is indicated by the first indication information, in the second resource. Therefore, the terminal may flexibly use a resource within the second resource to transmit the uplink signal or the uplink
30 channel according to the indication information of the network device, thus improving the utilization rate of the resource within the second resource.

Alternatively, in an embodiment, the first indication information is used to indicate at least one of the following: a time domain position of the first resource, or a frequency domain position of the first resource.

Alternatively, in an embodiment, the receiving module is specifically
5 configured to acquire modulated symbols corresponding to the uplink channel or the uplink signal in resource units included in the second resource, where the number of the modulated symbols is equal to the number of the resource units included in the second resource. The receiving module is further configured to drop modulated symbols acquired on first resource units, where the first resource units are resource
10 units in the second resource overlapped with the first resource.

Alternatively, in an embodiment, the receiving module is specifically configured to acquire modulated symbols corresponding to the uplink channel or the uplink signal in resource units included in the second resource, where the number of the modulated symbols is equal to the number of the resource units included in the
15 second resource, and the first resource units are resource units in the second resource overlapped with the first resource.

Alternatively, in an embodiment, the first indication information is used to indicate N time domain symbols included in the first resource, where the N is a nonnegative integer. The receiving module is specifically configured to receive the
20 uplink channel or the uplink signal transmitted by the terminal on the third resource within the second resource according to the first indication information, where M time domain symbols included in the third resource exclude the N time domain symbols, M is a positive integer.

Alternatively, in an embodiment, the transmitting module is specifically
25 configured to transmit downlink control information to the terminal, where the downlink control information carries the first indication information, the downlink control information further carries second indication information, and the second indication information is used to instruct the terminal to transmit the uplink channel or the uplink signal.

Alternatively, in an embodiment, the first resource is a resource used by the
30 terminal or other terminals to transmit an uplink control channel, an uplink sounding signal, or a random access channel, and the uplink channel includes an uplink shared channel.

It should be understood that, the above and other operations and/or functions of each unit of the network device 800 illustrated in FIG. 8 in this embodiment of the disclosure respectively implement corresponding processes of the communication method in FIG. 3, and will not be repeated here for the brief description.

5 FIG. 9 illustrates a schematic structural diagram of a terminal 900 according to an embodiment of the disclosure. The terminal 900 may include a memory 910, a processor 920, a receiver 930 and a transmitter 940.

 The memory 910 is configured to store a program.

 The processor 920 is configured to execute the program stored by the memory
10 910.

 The receiver 930 is called by the processor to receive first indication information transmitted by a network device, the first indication information being used to indicate a first resource.

 The transmitter 940 is called by the processor 920 to transmit according to the
15 first indication information, an uplink channel or an uplink signal to the network device on a third resource within a second resource, the third resource within the second resource being a resource non-overlapped with the first resource.

 In this embodiment of the disclosure, the terminal may transmit, according to the first indication information transmitted by the network device, the uplink signal or
20 the uplink channel on the third resource within the second resource non-overlapped with the first resource indicated by the first indication information. Therefore, the terminal may flexibly use a resource within the second resource to transmit the uplink signal or the uplink channel according to the indication information of the network device, thus improving the utilization rate of the resource within the second resource.

25 Alternatively, in an embodiment, the first indication information is used to indicate at least one of the following: a time domain position of the first resource, or a frequency domain position of the first resource.

 Alternatively, in an embodiment, the transmitter is specifically configured to:
30 determine a first number of resource units in the second resource; perform rate matching for the uplink channel or the uplink signal according to the first number, to obtain an output sequence having a length of a first bit number, the first bit number being determined by the terminal according to the first number; modulate the output sequence, to obtain a first number of modulated symbols; map the first number of the

modulated symbols to the resource units in the second resource, and drop modulated symbols mapped to first resource units in the first number of the modulated symbols, where the first resource units in the second resource are resource units overlapped with the first resource.

5 Alternatively, in an embodiment, the transmitter is specifically configured to: determine a second number of first resource units in the second resource, the first resource units being resource units in the second resource non-overlapped with the first resource; perform rate matching for the uplink channel or the uplink signal according to the second number, to obtain an output sequence having a length of a
10 second bit number, the second bit number being determined by the terminal according to the second number; modulate the output sequence to obtain a second number of modulated symbols; and map the second number of modulated symbols to the second number of first resource units.

 Alternatively, in an embodiment, the first indication information is used to
15 indicate N time domain symbols included in the first resource, where the N is a nonnegative integer. The transmitter is specifically configured to: transmit, according to the first indication information, the uplink channel or the uplink signal to the network device on the third resource within the second resource, where M time domain symbols included in the third resource exclude the N time domain symbols, M
20 is a positive integer.

 Alternatively, in an embodiment, the receiver is specifically configured to: receive downlink control information transmitted by the network device, where the downlink control information carries the first indication information, the downlink control information further carries second indication information, and the second
25 indication information is used to instruct the terminal to transmit the uplink channel or the uplink signal.

 Alternatively, in an embodiment, the first resource is a resource used by the terminal or other terminals to transmit an uplink control channel, an uplink sounding signal, or a random access channel, and the uplink channel includes an uplink shared
30 channel.

 It should be understood that, the terminal illustrated in FIG. 9 in this embodiment of the disclosure may correspond to the terminal illustrated in FIG. 9; and the above and other operations and/or functions of each unit of the terminal in this

embodiment of the disclosure respectively implement corresponding processes of the communication method in FIG. 4, and will not be repeated here for the brief description.

FIG. 10 illustrates a schematic structural diagram of a network device 1000 according to an embodiment of the disclosure. The network device 1000 may include a memory 1010, a processor 1020, a receiver 1030 and a transmitter 1040.

The memory 1010 is configured to store a program.

The processor 1020 is configured to execute the program stored by the memory 1010.

The transmitter 1040 is called by the processor to transmit first indication information to the terminal, the first indication information being used to indicate a first resource.

The receiver 1030 is called by the processor to receive an uplink channel or an uplink signal transmitted by the terminal on a third resource within a second resource according to the first indication information, the third resource being a resource within the second resource non-overlapped with the first resource.

In this embodiment of the disclosure, the network device transmits the first indication information to the terminal, so that the terminal may transmit, according to the first indication information, the uplink signal or the uplink channel on the third resource, which is non-overlapped with the first resource and is indicated by the first indication information, in the second resource. Therefore, the terminal may flexibly use a resource within the second resource to transmit the uplink signal or the uplink channel according to the indication information of the network device, thus improving the utilization rate of the resource within the second resource.

Alternatively, in an embodiment, the first indication information is used to indicate at least one of the following: a time domain position of the first resource, or a frequency domain position of the first resource.

Alternatively, in an embodiment, the receiver is specifically configured to acquire modulated symbols corresponding to the uplink channel or the uplink signal in resource units included in the second resource, where the number of the modulated symbols is equal to the number of the resource units included in the second resource, drop modulated symbols acquired on first resource units, where the first resource

units are resource units in the second resource overlapped with those in the first resource.

Alternatively, in an embodiment, the receiver is specifically configured to: acquire modulated symbols corresponding to the uplink channel or the uplink signal
5 in resource units included in the second resource, where the number of the modulated symbols is equal to the number of the resource units included in the second resource, and the first resource units are resource units in the second resource overlapped with the first resource.

Alternatively, in an embodiment, the first indication information is used to
10 indicate N time domain symbols included in the first resource, where the N is a nonnegative integer. The receiving module is specifically configured to receive the uplink channel or the uplink signal transmitted by the terminal on the third resource within the second resource according to the first indication information, where M time domain symbols included in the third resource exclude the N time domain symbols, M
15 is a positive integer.

Alternatively, in an embodiment, the transmitter is specifically configured to transmit downlink control information to the terminal, where the downlink control information carries the first indication information, the downlink control information further carries second indication information, and the second indication information is
20 used to instruct the terminal to transmit the uplink channel or the uplink signal.

Alternatively, in an embodiment, the first resource is a resource used by the terminal or other terminals to transmit an uplink control channel, an uplink sounding signal, or a random access channel, and the uplink channel includes an uplink shared channel.

It should be understood that, the network device illustrated in FIG. 10 in this
25 embodiment of the disclosure may correspond to the network device illustrated in FIG. 10; and the above and other operations and/or functions of each unit of the terminal in this embodiment of the disclosure respectively implement corresponding processes of the communication method in FIG. 3, and will not be repeated here for the brief
30 description.

It may be appreciated by a person of ordinary skill in the art that units and actions of algorithms in each example described in combination with embodiments disclosed in the disclosure may be implemented by electronic hardware or a

combination of computer software and electronic hardware. Whether these functions are executed via a hardware manner or a software manner is determined by a specific application and a designed constraint condition of the technical solutions. A person skilled in the art may be implemented the described function by using different methods for each specific application. However, such implementation should not be considered as being beyond the scope of the disclosure.

The person skilled in the art may clearly understand that, for the convenience and briefness of description, the above-described specific working process of the system, the apparatus and the unit may be referred to the corresponding process of the foregoing method embodiment and will not be repeated here.

In some embodiments provided by the application, it should be understood that the disclosed system, apparatus and method may be implemented in other manners. For example, the apparatus embodiment described above is only schematic, and for example, division of the units is only logic function division, and other division manners may be adopted during practical implementation. For example, multiple units or components may be combined or integrated into another system, or some characteristics may be neglected or not executed. In addition, coupling, or direct coupling or communication connection between each displayed or discussed component may be indirect coupling or communication connection, implemented through some interfaces, of the apparatus or the units, and may be electrical and mechanical or adopt other forms.

The units described as separate parts may or may not be physically separated, and parts displayed as units may or may not be physical units, and namely may be located in the same place, or may also be distributed to multiple network units. Part or all of the units may be selected to achieve the purpose of the solutions of the embodiments according to a practical requirement.

In addition, each function unit in each embodiment of the disclosure may be integrated into a processing unit, each unit may also exist independently, and two or more than two unit may also be integrated into a unit. The integrated unit may be implemented in a hardware form, and may also be implemented in form of hardware and software function unit.

When being implemented in form of a software function unit and sold or used as an independent product, the functions may also be stored in a computer-readable

storage medium. Based on such an understanding, the technical solutions of the embodiments of the disclosure substantially or parts making contributions to the conventional art may be embodied in form of software product, and the computer software product is stored in a storage medium, including a plurality of instructions
5 configured to enable a piece of computer equipment (which may be a personal computer, a server, network equipment or the like) to execute all or part of the method in each embodiment of the disclosure. The above-mentioned storage medium includes: various media capable of storing program codes such as a U disk, a mobile hard disk, a ROM, a RAM, a magnetic disk or an optical disk.

10 The above is only the specific implementation mode of the disclosure and not intended to limit the scope of protection of the disclosure. Any variations or replacements apparent to those skilled in the art within the technical scope disclosed by the disclosure shall fall within the scope of protection of the disclosure. Therefore, the scope of protection of the disclosure shall be subject to the scope of protection of
15 the claims.

CLAIMS

1. A communication method, comprising:

5 receiving, by a terminal, first indication information transmitted by a network device, the first indication information being used to indicate a first resource; and

transmitting, by the terminal, according to the first indication information, an uplink channel or an uplink signal to the network device on a third resource within a second resource, the third resource being a resource within the second resource non-overlapped with the first resource.

2. The communication method of claim 1, wherein the first indication information is used to indicate at least one of the following: a time domain position of the first resource, or a frequency domain position of the first resource.

3. The communication method of claim 2, wherein the transmitting, by the terminal, according to the first indication information, the uplink channel or the uplink signal to the network device on the third resource within the second resource, the third resource being the resource within the second resource non-overlapped with the first resource comprises:

determining, by the terminal, a first number of resource units in the second resource;

performing, by the terminal, rate matching for the uplink channel or the uplink signal according to the first number, to obtain an output sequence having a length of a first bit number, the first bit number being determined by the terminal according to the first number;

modulating, by the terminal, the output sequence, to obtain the first number of modulated symbols; and

mapping, by the terminal, the first number of modulated symbols to the resource units in the second resource, wherein the terminal drops modulated symbols, mapped to first resource units, in the first number of modulated symbols, and the first resource units are resource units in the second resource overlapped with the first resource.

4. The communication method of claim 2, wherein the transmitting, by the terminal, according to the first indication information, the uplink channel or the uplink signal to the network device on the third resource within the second resource, the third resource being a resource within the second resource non-overlapped with the first resource

5 comprises:

determining, by the terminal, a second number of first resource units in the second resource, the first resource units being resource units in the second resource non-overlapped with the first resource;

performing, by the terminal, rate matching for the uplink channel or the uplink signal according to the second number, to obtain an output sequence having a length of a second bit number, the second bit number being determined by the terminal according to the second number;

modulating, by the terminal, the output sequence, to obtain the second number of modulated symbols; and

15 mapping, by the terminal, the second number of modulated symbols to the second number of first resource units.

5. The communication method of claim 1, wherein the first indication information is used to indicate N time domain symbols included in the first resource; the N is a nonnegative integer; and

20

wherein the transmitting, by the terminal, according to the first indication information, the uplink channel or the uplink signal to the network device on the third resource within the second resource, the third resource being a resource within the second resource non-overlapped with the first resource comprises:

25 transmitting, by the terminal, according to the first indication information, the uplink channel or the uplink signal to the network device on the third resource within the second resource,

wherein M time domain symbols included in the third resource exclude the N time domain symbols, M is a positive integer.

30

6. The communication method of claim 5, wherein the receiving, by the terminal, first indication information transmitted by the network device comprises:

receiving, by the terminal, downlink control information transmitted by the network device,

wherein the downlink control information carries the first indication information; the downlink control information further carries second indication information; and the second indication information is used to instruct the terminal to transmit the uplink channel or the uplink signal.

7. The communication method of any one of claims 1-6, wherein the first resource is a resource used by the terminal or other terminals to transmit an uplink control channel, an uplink sounding signal, or a random access channel, and the uplink channel comprises an uplink shared channel.

8. A communication method, comprising:

transmitting, by a network device, first indication information to a terminal, the first indication information being used to indicate a first resource; and

receiving, by the network device, an uplink channel or an uplink signal transmitted by the terminal on a third resource within a second resource according to the first indication information, the third resource being a resource within the second resource non-overlapped with the first resource.

9. The communication method of claim 8, wherein the first indication information is used to indicate at least one of the following: a time domain position of the first resource, or a frequency domain position of the first resource.

10. The communication method of claim 9, wherein the receiving, by the network device, the uplink channel or the uplink signal transmitted by the terminal on the third resource within the second resource according to the first indication information comprises:

acquiring, by the network device, modulated symbols corresponding to the uplink channel or the uplink signal from resource units comprised in the second resource, wherein a number of the modulated symbols is equal to a number of the resource units comprised in the second resource;

dropping, by the network device, modulated symbols acquired from first resource units, wherein the first resource units are resource units in the second resource overlapped with the first resource.

5 11. The communication method of claim 9, wherein the receiving, by the network device, the uplink channel or the uplink signal transmitted by the terminal on the third resource within the second resource according to the first indication information comprises:

10 acquiring, by the network device, modulated symbols corresponding to the uplink channel or the uplink signal, on first resource units in resource units comprised in the second resource,

wherein a number of the modulated symbols is equal to the number of the first resource units comprised in the second resource, and the first resource units are resource units in the second resource non-overlapped with those in the first resource.

15

12. The communication method of claim 8, wherein the first indication information is used to indicate N time domain symbols included in the first resource; the N is a nonnegative integer; and

20 wherein the receiving, by the network device, the uplink channel or the uplink signal transmitted by the terminal on the third resource within the second resource according to the first indication information, the third resource being a resource non-overlapped with the first resource within the second resource comprises:

25 receiving, by the network device, the uplink channel or the uplink signal transmitted by the terminal on the third resource within the second resource according to the first indication information, wherein M time domain symbols included in the third resource exclude the N time domain symbols, M is a positive integer.

13. The communication method of claim 12, wherein the transmitting, by the network device, first indication information to the terminal comprises:

30 transmitting, by the network device, downlink control information to the terminal; wherein the downlink control information carries the first indication information; the downlink control information further carries second indication

information; and the second indication information is used to instruct the terminal to transmit the uplink channel or the uplink signal.

14. The communication method of any one of claims 8-13, wherein the first resource
5 is a resource used by the terminal or other terminals to transmit an uplink control channel, an uplink sounding signal, or a random access channel, and the uplink channel comprises an uplink shared channel.

15. A terminal, comprising:

10 a receiving module, configured to receive first indication information transmitted by a network device, the first indication information being used to indicate a first resource; and

a transmitting module, configured to transmit, according to the first indication information, an uplink channel or an uplink signal to the network device on a third
15 resource within a second resource, the third resource being a resource in the second resource non-overlapped with the first resource.

16. The terminal of claim 15, wherein the first indication information is used to indicate at least one of the following: a time domain position of the first resource, or a
20 frequency domain position of the first resource.

17. The terminal of claim 16, wherein the transmitting module is configured to:

determine a first number of resource units in the second resource;

perform rate matching for the uplink channel or the uplink signal according to
25 the first number, to obtain an output sequence having a length of a first bit number, the first bit number being determined by the terminal according to the first number;

modulate the output sequence, to obtain the first number of modulated symbols; and

map the first number of modulated symbols to the resource units in the second
30 resource, wherein modulated symbols, mapped to first resource units, in the first number of modulated symbols are dropped, and the first resource units are resource units in the second resource overlapped with the first resource.

18. The terminal of claim 16, wherein the transmitting module is configured to:
determine a second number of first resource units in the second resource, the first resource units being resource units non-overlapped with those in the first resource within the second resource;

5 perform rate matching for the uplink channel or the uplink signal according to the second number, to obtain an output sequence having a length of a second bit number, the second bit number being determined by the terminal according to the second number;

10 modulate the output sequence, to obtain a second number of modulated symbols; and

map the second number of modulated symbols to the second number of first resource units.

19. The terminal of claim 15, wherein the first indication information is used to indicate N time domain symbols included in the first resource, N is a nonnegative integer; and

the transmitting module is configured to transmit, according to the first indication information, the uplink channel or the uplink signal to the network device on the third resource within the second resource,

20 wherein M time domain symbols included in the third resource exclude the N time domain symbols, M is a positive integer.

20. The terminal of claim 19, wherein the receiving module is configured to receive downlink control information transmitted by the network device,

25 wherein the downlink control information carries the first indication information; the downlink control information further carries second indication information; and the second indication information is used to instruct the terminal to transmit the uplink channel or the uplink signal.

30 21. The terminal of any one of claims 15-20, wherein the first resource is a resource used by the terminal or other terminals to transmit an uplink control channel, an uplink sounding signal, or a random access channel, and the uplink channel comprises an uplink shared channel.

22. A network device, comprising:

a transmitting module, configured to transmit first indication information to a terminal, the first indication information being used to indicate a first resource; and

a receiving module, configured to receive an uplink channel or an uplink signal transmitted by the terminal on a third resource within a second resource according to the first indication information, the third resource being a resource within the second resource non-overlapped with the first resource.

23. The network device of claim 22, wherein the first indication information is used to indicate at least one of the following: a time domain position of the first resource, or a frequency domain position of the first resource.

24. The network device of claim 23, wherein the receiving module is configured to acquire modulated symbols corresponding to the uplink channel or the uplink signal in resource units comprised in the second resource,

wherein the number of the modulated symbols is equal to the number of the resource units comprised in the second resource, modulated symbols acquired on first resource units are abandoned, and the first resource units are resource units overlapped with those in the first resource within the second resource.

25. The network device of claim 23, wherein the receiving module is configured to acquire modulated symbols corresponding to the uplink channel or the uplink signal on first resource units in resource units comprised in the second resource,

wherein the number of the modulated symbols is equal to the number of the first resource units comprised in the second resource, and the first resource units are resource units non-overlapped with those in the first resource within the second resource.

26. The network device of claim 22, wherein the first indication information is used to indicate N time domain symbols included in the first resource, N is a nonnegative integer; and

wherein the receiving module is configured to receive the uplink channel or the uplink signal transmitted by the terminal on the third resource within the second resource according to the first indication information, wherein M time domain symbols included in the third resource exclude the N time domain symbols, M is a positive integer.

27. The network device of claim 26, wherein the transmitting module is configured to transmit downlink control information to the terminal, wherein the downlink control information carries the first indication information; the downlink control information further carries second indication information; and the second indication information is used to instruct the terminal to transmit the uplink channel or the uplink signal.

28. The network device of any one of claims 22-27, wherein the first resource is a resource used by the terminal or other terminals to transmit an uplink control channel, an uplink sounding signal, or a random access channel, and the uplink channel comprises an uplink shared channel.