

[0001] TRANSPORT FORMAT COMBINATION SELECTION
 IN A WIRELESS TRANSMIT/RECEIVE UNIT

[0002] FIELD OF INVENTION

[0003] The present invention is related to a wireless communication system. More particularly, the present invention is related to transport format combination (TFC) selection in wireless transmit/receive units (WTRUs).

[0004] BACKGROUND

[0005] Under the current Third Generation Partnership Project (3GPP) standards, a WTRU is required to estimate a transmission power for each TFC. In the case that a certain TFC would require more transmission power than the maximum allowed WTRU transmission power, the WTRU should limit the usage of that TFC.

[0006] The WTRU continuously evaluates which TFCs can be used for transmission. The evaluation is performed using the estimated WTRU transmit power of a given TFC. When any TFC is restricted for exceeding a transmit power limit, the medium access control (MAC) entity in the WTRU notifies an upper layer to reduce the data rate, if applicable.

[0007] Under the current 3GPP standards, a WTRU has only one coded composite transport channel (CCTrCH) in uplink transmission. Therefore, the WTRU transmit power is the transmit power of the CCTrCH, which is determined by the TFC used for the CCTrCH.

[0008] In order to improve uplink coverage, throughput and transmission latency for uplink transmissions, enhanced uplink (EU) is currently being investigated in 3GPP. With EU implementation, a WTRU may have more than one CCTrCH in uplink transmissions; one for the regular dedicated channel (DCH) and the other for EU enhanced dedicated channel (E-DCH). In this case, the WTRU transmit power will be the sum of the transmit power of two CCTrCHs.

[0009] The WTRU transmit power is determined jointly by the TFCs of the two CCTrCHs. The combination of the TFC used by the dedicated CCTrCH and

the TFC used by the EU CCTrCH is defined as the TFC pair of the WTRU whose transmit power is determined jointly by the TFCs of the two CCTrCHs. This is not an optimal method of determining the TFCs for more than one CCTrCH.

[0010] There is a need for an efficient method for selecting a combination of TFCs for more than one CCTrCHs in uplink transmission.

[0011] SUMMARY

[0012] The present invention is related to a method and apparatus for selecting a TFC in a WTRU. The WTRU is configured to process more than one CCTrCH for uplink transmission. The WTRU estimates a transmit power for each of a plurality of available TFCs and selects a TFC for each CCTrCH such that the sum of the estimated WTRU transmit power for the selected TFCs is within the allowed maximum WTRU transmit power.

[0013] The WTRU may give priority to a particular CCTrCH, whereby the TFC for that particular CCTrCH is selected first and the TFC for the other CCTrCH is selected within the estimated remaining WTRU transmit power after power required for the selected TFC on the prioritized CCTrCH is deducted from the maximum allowed WTRU transmit power. This method allows for transmission of channels mapped to the first CCTrCH to be prioritized over channels mapped to the other CCTrCH.

[0014] Alternatively, the WTRU may reserve a minimum set of TFCs for the other CCTrCH, whereby a TFC for the prioritized CCTrCH is first selected within the maximum allowed WTRU transmit power less the power required to support a minimum set of TFCs on the other CCTrCH. Then the TFC for the other CCTrCH is selected within the remaining WTRU transmit power after power required for the selected TFC on the prioritized CCTrCH is deducted from the maximum allowed WTRU transmit power. This method allows for transmission of channels mapped to the first CCTrCH to be prioritized over channels mapped to the other CCTrCHs while reserving transmit power to allow for a minimum set of TFCs on the other CCTrCH to be transmitted without being effected by the maximum allowed WTRU transmit power limit.

[0015] Alternatively, the WTRU may be configured for individual maximum transmit power for each of the plurality of CCTrCHs, whereby a TFC for each CCTrCH is selected within the individual maximum transmit power designated to each CCTrCH. This method allows each CCTrCH to be given a quality of service (QoS) relative to the other CCTrCH. Activity on one CCTrCH does not take priority or reduce the rate of the other CCTrCH.

[0016] BRIEF DESCRIPTION OF THE DRAWINGS

[0017] Figure 1 is a flow diagram of a general process for selecting TFCs in accordance with a first embodiment of the present invention.

[0018] Figure 2 is a flow diagram of a process for selecting TFCs in accordance with a second embodiment of the present invention.

[0019] Figure 3 is a flow diagram of a process for selecting TFCs in accordance with a third embodiment of the present invention.

[0020] Figure 4 is a flow diagram of a process for selecting TFCs in accordance with a fourth embodiment of the present invention.

[0021] Figure 5 is a block diagram of an apparatus for selecting TFCs in accordance with the present invention.

[0022] DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

[0023] Hereafter, the terminology "WTRU" includes but is not limited to a user equipment, a mobile station, a fixed or mobile subscriber unit, a pager, or any other type of device capable of operating in a wireless environment.

[0024] The features of the present invention may be incorporated into an integrated circuit (IC) or be configured in a circuit comprising a multitude of interconnecting components.

[0025] Hereinafter, the present invention will be described with reference to a system supporting two CCTrCHs, (i.e., a dedicated CCTrCH and an EU CCTrCH). However, it should be noted that the present invention is applicable to a system supporting more than two CCTrCHs.

[0026] Figure 1 is a flow diagram of a process 100 for selecting TFCs in

accordance with a first embodiment of the present invention. The WTRU is configured to process a dedicated CCTrCH and an EU CCTrCH simultaneously in uplink transmission. The transmit power of the WTRU is limited to a maximum allowed WTRU transmit power, which is set by the wireless communication system. In each transmit time interval (TTI), the WTRU estimates the transmit power for each of a plurality of available TFCs (step 102) for each CCTrCH. The WTRU estimates the transmit power of each TFC over a predetermined period taking into account the gain factor of each corresponding TFC. The WTRU then selects TFCs for transmission on each CCTrCH among a plurality of available TFCs, such that the sum of the estimated transmit power of the selected TFCs for the dedicated CCTrCH and the EU CCTrCH does not exceed the maximum allowed WTRU transmit power (step 104).

[0027] Additionally, the dedicated CCTrCH, the EU CCTrCH, or both may be provided with a capability of transmitting a reserved minimum set of TFCs even when the power required for transmission of these TFCs exceeds the maximum allowed WTRU transmit power. TFCs that require power greater than the maximum allowed transmit power are defined to be in an excess power state. The minimum set is for reserving a lowest rate in a CCTrCH, thereby maintaining the basic services for the channel. Since in the EU CCTrCH there is only one TrCH, the minimum set corresponds to a lowest rate per logical channel or MAC-d flow mapped to the EU TrCH. The minimum set of TFCs may be one transport block per TTI for each channel mapped to the CCTrCH or a number of transport blocks per TTI corresponding to a guaranteed bit rate (GBR).

[0028] The reserved minimum set of TFCs may be transmitted in an excess power state. In order to maintain the transmit power within the allowed maximum level, a WTRU scales down power on physical channels mapped to the dedicated CCTrCH, the EU CCTrCH, or all physical channels present.

[0029] Regardless of the TFC selection, the EU CCTrCH may be provided with a minimum reserved set of TFCs that is one or more transport blocks per logical channel or MAC-d flow mapped to the EU CCTrCH. A transport block is one or more radio link control (RLC) protocol data units (PDUs). One or more

transport blocks is equivalent to a data rate. The reserved set of TFCs can be transmitted in an excess power state by scaling down power on either the physical channels mapped to the EU CCH, the dedicated CCH or all present UL channels.

[0030] Figure 2 is a flow diagram of a process 200 for selecting TFCs in accordance with a second embodiment of the present invention. TFC selection of the dedicated CCH is prioritized over TFC selection of the EU CCH. In each TTI of the dedicated CCH, the WTRU estimates the transmit power requirement for each of a plurality of available TFCs configured for the dedicated CCH (step 202). The WTRU selects a TFC for the dedicated CCH first, without considering the power requirement of the EU CCH (step 204). After the TFC for the dedicated CCH is selected, at each TTI of the EU CCH the WTRU selects a TFC for the EU CCH within the remaining WTRU transmit power after the power required for the selected TFC for the dedicated CCH is deducted from the maximum allowed WTRU transmit power (step 206). The TFC selection of the dedicated CCH is not affected by the operation of EU CCH, while the TFC selection of the EU CCH is affected and limited by the operation of the dedicated CCH.

[0031] The remaining power for the EU CCH is estimated either each dedicated CCH TTI or each EU CCH TTI. At each TTI of the EU CCH, the remaining power available for the EU CCH is estimated as the maximum allowed WTRU transmit power minus the power required by transmission of the selected dedicated CCH TFC. Alternatively, at each TTI of the dedicated CCH, the remaining power available for the EU CCH is estimated as the maximum allowed WTRU transmit power minus the power required to support transmission of the selected dedicated CCH TFC.

[0032] In process 200, the EU CCH may allow transmission of a minimum set of TFCs even when these TFCs are in excess power state. An EU TFC is in excess power state when the estimated remaining power is less than the calculated transmission power requirement for the EU CCH TFC. The EU minimum set reserves a lowest or guaranteed rate on channels mapped to the

EU CCTrCH, and thereby maintains the basic services for EU channels. Since in the EU CCTrCH there is only one TrCH, the minimum set corresponds to a lowest rate per logical channel or MAC-d flow mapped to the EU TrCH. The minimum set of TFCs may be one transport block per TTI for each channel mapped to the CCTrCH or a number of transport blocks per TTI corresponding to a guaranteed bit rate (GBR). When transmitting a TFC in excess power state, in order to maintain the transmit power within the allowed maximum level, the WTRU scales down power on physical channels mapped to the EU CCTrCH, the dedicated CCTrCH, or all physical channels present.

[0033] Figure 3 is a flow diagram of a process 300 for selecting TFCs in accordance with a fourth embodiment of the present invention. The WTRU gives priority to dedicated CCTrCH TFC selection while reserving transmit power for a minimum set of EU CCTrCH TFCs (step 302). A minimum set of TFCs for an EU CCTrCH is defined to reserve a lowest or guaranteed rate for channels mapped to the EU CCTrCH. Since in the EU CCTrCH there is only one TrCH, the minimum set corresponds to a lowest rate per logical channel or MAC-d flow mapped to the EU TrCH. The minimum set of TFCs may be one transport block per TTI for each channel mapped to the CCTrCH, or a number of transport blocks per TTI corresponding to a GBR.

[0034] The EU CCTrCH may allow transmission of a minimum set of TFCs even when these TFCs are in excess power state. An EU TFC is in excess power state when the estimated remaining power is less than the calculated transmission power requirement for the EU TFC. When transmitting a TFC in excess power state, in order to maintain the transmit power within the allowed maximum level, the WTRU scales down power on physical channels mapped to the EU CCTrCH, the dedicated CCTrCH, or all physical channels present.

[0035] When a TFC is in an excess power state (with reduced power), the quality of the transmission is reduced, (i.e., lower SIR, higher BLER, etc). This may defeat the purpose of maintaining the minimum set. Therefore, in order to minimize the possibility that the EU CCTrCH TFC has to be transmitted in an excess power state, and to further insure the minimum set is really supported, in

process 300 transmit power is reserved for the EU minimum set when TFC selection is performed on the prioritized dedicated CCTrCH.

[0036] TFC selection of the dedicated CCTrCH is prioritized over TFC selection of the EU CCTrCH. In each TTI of the dedicated CCTrCH, the WTRU estimates the transmit power for each of a plurality of available TFCs configured for the dedicated CCTrCH and TFCs associated with the EU CCTrCH minimum set (step 304). The WTRU selects a TFC for the dedicated CCTrCH that has a power requirement that does not exceed the maximum allowed transmit power minus the power required to support the minimum set of TFCs on the EU CCTrCH (step 306). After the TFC for the dedicated CCTrCH is selected, at each TTI of the EU CCTrCH the WTRU selects a TFC for the EU CCTrCH with the remaining transmit power after power required for the selected the TFC for the dedicated CCTrCH is deducted from the maximum allowed transmit power (step 308).

[0037] The remaining power for the EU CCTrCH is estimated either each dedicated CCTrCH TTI or each EU CCTrCH TTI. At each TTI of the EU CCTrCH, the remaining power available for the EU CCTrCH is estimated as the maximum allowed WTRU transmit power minus the power required by transmission of the selected dedicated CCTrCH TFC. Alternatively, at each TTI of the dedicated CCTrCH, the remaining power available for the EU CCTrCH is estimated as the maximum allowed WTRU transmit power minus the power required to support transmission of the selected dedicated CCTrCH TFC.

[0038] Since the dedicated CCTrCH TFC selection takes precedence over the EU CCTrCH, and the power requirement may change during the dedicated TTI, the minimum set of TFCs of the EU CCTrCH may still be transmitted in an excess power state even though power was reserved when the dedicated TFC was selected. In this situation, in order to maintain the transmit power within the allowed maximum level, the WTRU scales down all physical channels mapped to the EU CCTrCH, the dedicated CCTrCH, or all physical channels present.

[0039] Figure 4 is a flow diagram of a process 400 for selecting TFCs in accordance with a third embodiment of the present invention. The WTRU sets

an individual maximum transmit power, or a ratio relative to the maximum allowed WTRU transmit power, for a dedicated CCTrCH and an EU CCTrCH (step 402). The maximum power level (or the ratio) for each CCTrCH is a configurable parameter. The factors for determining the maximum power level (or the ratio) for each CCTrCH may include, but are not limited to, a data rate of each CCTrCH, quality-of-service (QoS) of each CCTrCH and a relative priority between the CCTrCHs.

[0040] In each TTI of the dedicated CCTrCH and in each TTI of the EU CCTrCH, the WTRU estimates the transmit power for each of a plurality of available TFCs (step 404). The WTRU then selects a TFC for each CCTrCH within the individual maximum transmit power of each CCTrCH (step 406). The TFC selection process for each CCTrCH operates independently. The TFC of each CCTrCH is selected from only those TFCs that can be supported by the individual maximum power level determined for a particular CCTrCH.

[0041] The dedicated CCTrCH, the EU CCTrCH, or both may be provided with a capability of transmitting a minimum set of TFCs. The minimum set is for reserving a lowest rate for each channel mapped to the CCTrCH, thereby maintaining the basic services for each channel. Since in the EU CCTrCH there is only one TrCH, the minimum set corresponds to a lowest rate per logical channel or MAC-d flow mapped to the EU TrCH. The minimum set of TFCs may be one transport block per TTI for each channel mapped to the CCTrCH or a number of transport blocks per TTI corresponding to a GBR.

[0042] The minimum set of TFCs may be transmitted in an excess power state. In this situation, in order to maintain the transmit power within the allowed maximum level, the WTRU scales down all physical channels mapped to the EU CCTrCH, the dedicated CCTrCH, or all physical channels present.

[0043] Figure 5 is a block diagram of an apparatus 500 for selecting TFCs in accordance with the present invention. The apparatus comprises a transmit power estimation unit 502, a TFC selection unit 504, and a measurement unit 506. The transmit power estimation unit 502 calculates an estimate of a transmit power for each of a plurality of available TFCs. The TFC selection unit

504 selects a TFC for each CCTrCH such that the sum of the estimated WTRU transmit power for the selected TFCs is within a maximum WTRU transmit power. The measurement unit 506 performs physical measurements of the WTRU transmit power over a predetermined period, and the transmit power estimation unit 502 calculates the estimate of a transmit power of each TFC using the measurement results and a gain factor of the corresponding TFC.

[0044] Although the features and elements of the present invention are described in the preferred embodiments in particular combinations, each feature or element can be used alone without the other features and elements of the preferred embodiments or in various combinations with or without other features and elements of the present invention.

*

*

*

CLAIMS

What is claimed is:

1. A method for selecting a transport format combination (TFC) in a wireless transmit/receive unit (WTRU), the WTRU being configured to process more than one code composite transport channel (CCTrCH) for uplink transmission, the method comprising:

estimating a transmit power for each of a plurality of available TFCs; and

selecting a TFC for each CCTrCH such that the sum of the estimated WTRU transmit power for the selected TFCs is within a maximum allowed WTRU transmit power.

2. The method of claim 1 wherein selection of a TFC for a particular CCTrCH has a priority over the other CCTrCH, whereby the TFC for the prioritized CCTrCH is selected first independently and a TFC for the other CCTrCH is selected within the remaining WTRU transmit power after the TFC for the prioritized CCTrCH is selected.

3. The method of claim 2 wherein during the period of each transmit time interval (TTI) of the prioritized CCTrCH, one or more TTIs may exist for the other CCTrCH.

4. The method of claim 2 wherein one TFC is selected for each transmit time interval (TTI) of the prioritized CCTrCH and one TFC is selected for each TTI of the other CCTrCH.

5. The method of claim 2 wherein the prioritized CCTrCH is a dedicated channel (DCH) and the other CCTrCH is an enhanced uplink (EU) channel.

6. The method of claim 5 wherein the remaining WTRU transmit power is calculated every transmit time interval (TTI) of the EU channel.

7. The method of claim 5 wherein the remaining WTRU transmit power is calculated every transmit time interval (TTI) of the dedicated channel.

8. The method of claim 2 wherein a minimum set of TFCs is reserved for at least one CCTrCH, whereby the CCTrCH always has a possibility to transmit the minimum set of TFCs even when the minimum set of TFCs are in an excess power state.

9. The method of claim 8 further comprising a step of scaling down physical channels in at least one CCTrCH when a transmit power of at least one CCTrCH is in an excess power state.

10. The method of claim 8 wherein the minimum set of reserved TFCs is one protocol data unit (PDU) per medium access control (MAC)-d flow or logical channel per transmit time interval.

11. The method of claim 8 wherein the minimum set of reserved TFCs is one or more protocol data units corresponding to a guaranteed bit rate per medium access control (MAC)-d flow or logical channel per transmit time interval.

12. The method of claim 1 further comprising the step of:
setting an individual maximum allowed transmit power for each of the plurality of CCTrCHs, whereby a TFC for each CCTrCH is selected within the individual maximum allowed transmit power designated to each CCTrCH.

13. The method of claim 12 wherein the individual maximum transmit power is determined by at least one of a data rate, quality of service and relative priority between CCTrCHs.

14. The method of claim 12 wherein a minimum set of TFCs is reserved for each CCTrCH, whereby each CCTrCH always has a possibility to transmit the minimum set of TFCs, even when the minimum set of TFCs is in an excess power state.

15. The method of claim 14 further comprising a step of scaling down physical channels in each CCTrCH when a transmit power of one CCTrCH is in an excess state.

16. The method of claim 14 wherein the minimum set of reserved TFCs is one protocol data unit per medium access control (MAC)-d flow or logical channel per transmit time interval.

17. The method of claim 14 wherein the minimum set of reserved TFCs is one or more protocol data units corresponding to a guaranteed bit rate per medium access control (MAC)-d flow or logical channel per transmit time interval.

18. The method of claim 1 further comprising the step of:
providing a priority to a particular CCTrCH while reserving a minimum set of TFCs for the other CCTrCH, whereby a TFC for the prioritized CCTrCH is selected first within the maximum allowed WTRU transmit power less the power to support the minimum set of reserved TFCs on the other CCTrCH, and a TFC for the other CCTrCH is selected within the remaining WTRU transmit power after the TFC for the prioritized CCTrCH is selected.

19. The method of claim 18 wherein during the period of each transmit time interval (TTI) of the prioritized CCTrCH, one or more TTIs may exist for the other CCTrCH.

20. The method of claim 18 wherein one TFC is selected for each transmit time interval (TTI) of the prioritized CCTrCH and one TFC is selected for each TTI of the other CCTrCH.

21. The method of claim 18 wherein the prioritized CCTrCH is a dedicated channel (DCH) and the other CCTrCH is an enhanced uplink (EU) channel.

22. The method of claim 21 wherein a minimum set of TFC is also reserved for the dedicated CCTrCH.

23. The method of claim 18 wherein the minimum set of reserved TFCs is one protocol data unit per medium access control (MAC)-d flow or logical channel per transmit time interval.

24. The method of claim 18 wherein the minimum set of reserved TFCs is one or more protocol data units corresponding guaranteed bit rate per medium access control (MAC)-d flow or logical channel per transmit time interval.

25. The method of claim 18 wherein the remaining WTRU transmit power is calculated every transmit time interval of the EU channel.

26. The method of claim 18 wherein the remaining WTRU transmit power is calculated every transmit time interval of the dedicated channel.

27. The method of claim 18 further comprising the step of scaling down physical channels in at least one CCTrCH when a transmit power of at least one CCTrCH is in an excess power state.

28. The method of claim 1 wherein one CCTrCH is a dedicated channel (DCH) and the other CCTrCH is an enhanced uplink (EU) channel, and the EU

channel is provided with a minimum set of reserved TFCs, whereby the EU channel has always a capability of transmitting the minimum set of reserved TFCs.

29. An apparatus for selecting transport format combinations (TFCs) for a plurality of code composite transport channels (CCTrCHs), the apparatus comprising:

a transmit power estimation unit for estimating a transmit power for each of a plurality of available TFCs; and

a TFC selection unit for selecting a TFC for each CCTrCH such that the sum of the estimated wireless transmit/receive unit (WTRU) transmit power for selected TFCs is within a maximum allowed WTRU transmit power.

30. The apparatus of claim 29 wherein selection of a TFC for a particular CCTrCH has a priority over the other CCTrCH, whereby the TFC for the prioritized CCTrCH is selected first independently and a TFC for the other CCTrCH is selected within the remaining WTRU transmit power after the TFC for the prioritized CCTrCH is selected.

31. The apparatus of claim 30 wherein during the period of each transmit time interval (TTI) of the prioritized CCTrCH, one or more TTIs may exist for the other CCTrCH.

32. The apparatus of claim 30 wherein one TFC is selected for each transmit time interval (TTI) of the prioritized CCTrCH and one TFC is selected for each TTI of the other CCTrCH.

33. The apparatus of claim 30 wherein the prioritized CCTrCH is a dedicated channel (DCH) and the other CCTrCH is an enhanced uplink (EU) channel.

34. The apparatus of claim 33 wherein the remaining WTRU transmit power is calculated every transmit time interval of the EU channel.

35. The apparatus of claim 33 wherein the remaining WTRU transmit power is calculated every transmit time interval of the dedicated channel.

36. The apparatus of claim 30 wherein a minimum set of TFCs is reserved for each CCTrCH, whereby each CCTrCH always has a possibility to transmit the minimum set of TFCs even when the minimum set of TFCs are in an excess power state.

37. The apparatus of claim 36 further comprising means for scaling down physical channels in each CCTrCH when a transmit power of at least one CCTrCH is in an excess power state.

38. The apparatus of claim 36 wherein the minimum set of reserved TFCs is one protocol data unit per medium access control (MAC)-d flow or logical channel per transmit time interval.

39. The apparatus of claim 36 wherein the minimum set of reserved TFCs is one or more protocol data units corresponding to a guaranteed bit rate per medium access control (MAC)-d flow or logical channel per transmit time interval.

40. The apparatus of claim 29 wherein the TFC selection unit selects a TFC for each CCTrCH within an individual maximum allowed transmit power designated to each CCTrCH.

41. The apparatus of claim 40 wherein the individual maximum allowed transmit power is determined by at least one of a data rate, quality of service and relative priority between CCTrCHs.

42. The apparatus of claim 40 wherein a minimum set of TFCs is reserved for each CCTrCH, whereby each CCTrCH always has a possibility to transmit the minimum set of TFCs even when the minimum set of TFCs are in an excess power state..

43. The apparatus of claim 42 further comprising means for scaling down physical channels in each CCTrCH when a transmit power of one CCTrCH is in an excess power state.

44. The apparatus of claim 42 wherein the minimum set of reserved TFCs is one protocol data unit per medium access control (MAC)-d flow or logical channel per transmit time interval.

45. The apparatus of claim 42 wherein the minimum set of reserved TFCs is one or more protocol data units corresponding to a guaranteed bit rate per medium access control (MAC)-d flow or logical channel per transmit time interval.

46. The apparatus of claim 29 wherein the TFC selection unit provides a priority to a particular CCTrCH and reserves a minimum set of TFCs for the other CCTrCH, whereby a TFC for the prioritized CCTrCH is selected first within the maximum allowed WTRU transmit power less the power to support the minimum set of TFCs and a TFC for the other CCTrCH is selected within the remaining WTRU transmit power after the TFC for the prioritized CCTrCH is selected.

47. The apparatus of claim 46 wherein the prioritized CCTrCH is a dedicated channel (DCH) and the other CCTrCH is an enhanced uplink (EU) channel.

48. The apparatus of claim 46 wherein during the period of each transmit time interval (TTI) of the prioritized CCTrCH, one or more TTIs may exist for the other CCTrCH.

49. The apparatus of claim 46 wherein one TFC is selected for each transmit time interval (TTI) of the prioritized CCTrCH and one TFC is selected for each TTI of the other CCTrCH.

50. The apparatus of claim 47 wherein a minimum set of TFCs is also reserved for the dedicated CCTrCH.

51. The apparatus of claim 50 further comprising means for scaling down physical channels in each CCTrCH when a transmit power of at least one CCTrCH is in an excess power state.

52. The apparatus of claim 50 wherein the minimum set of reserved TFCs is one protocol data unit per medium access control (MAC)-d flow or logical channel per transmit time interval.

53. The apparatus of claim 50 wherein the minimum set of reserved TFCs is one or more protocol data units corresponding to a guaranteed bit rate per medium access control (MAC)-d flow or logical channel per transmit time interval.

54. An integrated circuit (IC) for selecting transport format combinations (TFCs) for a plurality of code composite transport channels (CCTrCHs), the apparatus comprising:

a transmit power estimation unit for estimating a transmit power for each of a plurality of available TFCs; and

a TFC selection unit for selecting a TFC for each CCTrCH wherein the sum of the estimated wireless transmit/receive unit (WTRU) transmit power for selected TFCs is within a maximum allowed WTRU transmit power.