

METHODS AND APPARATUS FOR SIGNALING PARAMETER DISTRIBUTION FOR NEIGHBORING RADIO FREQUENCIES

CROSS-REFERENCE TO RELATED APPLICATIONS

[0001] The present Application for Patent claims priority to Provisional Application No. 60/951,056 entitled "Method and Apparatus for Supporting System Parameter information for Neighboring Radio Frequencies" filed July 20, 2007, and assigned to the assignee hereof and hereby expressly incorporated by reference herein.

BACKGROUND

[0002] Data networks, such as wireless communication networks, have to trade off between services customized for a single terminal and services provided to a large number of terminals. For example, the distribution of multimedia content to a large number of resource limited portable devices (subscribers) is a complicated problem. Therefore, it is important for network operators, content retailers, and service providers to have a way to distribute content and/or other network services in a fast and efficient manner and in such a way as to increase bandwidth utilization and power efficiency.

[0003] A multi-frequency network (MFN) is a network in which one or more radio frequencies (RFs) (or RF channels) are used to transmit media content. One type of MFN is a horizontal multi-frequency network (HMFN) in which a distribution waveform is transmitted over the same or different RF channels in different local areas. The same or different content may be transmitted as part of the distribution waveform carried over the one or more RF channels in such local areas. Another type of MFN is a vertical MFN in which multiple RF channels are used in a given local area to transmit independent distribution waveforms with an aim to increase the capacity of the network (in terms of the ability to deliver more content to a device/end user). An MFN deployment may comprise a VMFN in certain areas and a HMFN in certain other areas.

[0004] In a typical VMFN, a local operations infrastructure (LOI) comprises transmitting sites that operate to transmit multiple distribution waveforms over multiple RF channels in a selected geographic area. Each distribution

waveform may comprise one or more content flows that can be selected at a receiving device for rendering. Adjacent LOIs may utilize the same or different RF channels.

[0005] Generally, content distribution in an MFN occurs over one or more RF channels that may utilize different signaling parameters (SPs) including physical layer parameters in different LOIs. The SP information describes a variety of transmission characteristics that may be associated with RF channels in the MFN. Thus, the SP information may be different across RF channels carried in the same or different LOIs in an MFN. Therefore, a device attempting to receive content on a particular RF channel would need to utilize the appropriate SP information for that RF channel to receive the content.

[0006] Typically, as a device moves from region to region in an MFN, an RF handoff is performed to allow the device to switch between available RF channels that carry desired content flows. These available RF channels may belong to different LOIs, and may utilize different SP information. A device may also perform an RF handoff to another RF in the current LOI to acquire desired content flows. To facilitate handoff, a device may actively monitor RF channels in the current and neighboring regions to determine whether these RF channels can be received with adequate signal strength to perform a handoff. Note that an RF channel determined to have strong signal strength during RF monitoring may not necessarily carry the desired distribution waveform. The knowledge of SP information may improve the effectiveness of RF monitoring by eliminating those RF channels which have strong signal strength but do not carry the desired distribution waveform. Typically, an initialization mechanism is provided to allow a device to tune to a selected RF channel and obtain the SP information associated with that RF channel. The SP information can then be used to determine transmission characteristics of the RF channel in order to receive desired content flows on that RF channel. This process may add additional latency to the RF handoff process. For example, in an MFN having multiple RF channels, it may be necessary for a device to tune to several RF channels to obtain their associated SP information in order to receive desired content flows. Unfortunately, this process is not efficient from a device power consumption perspective and also not desirable from an end user experience perspective.

[0007] Therefore, it would be desirable to have a system that operates to allow a device to obtain SP information associated with RF channels in a MFN to facilitate RF channel monitoring and handoff.

BRIEF DESCRIPTION OF THE DRAWINGS

[0008] The foregoing aspects described herein will become more readily apparent by reference to the following Description when taken in conjunction with the accompanying drawings wherein:

- [0009] **FIG. 1** shows an exemplary network that illustrates how SP information is provisioned in multiple LOIs of an MFN for use in aspects of a SP distribution system;
- [0010] **FIG. 2** shows a diagram of an exemplary transmission frame for use in aspects of a SP distribution system;
- [0011] **FIG. 3** shows exemplary SP logic for use in aspect of a SP distribution system;
- [0012] **FIG. 4** shows a diagram that illustrates an exemplary neighbor description message for use in aspects of a SP distribution system;
- [0013] **FIG. 5** shows exemplary SP_info for use in aspects of a SP distribution system
- [0014] **FIG. 6** shows an exemplary method for generating neighbor description messages for use in aspects of a SP distribution system;
- [0015] **FIG. 7** shows exemplary SP acquisition logic for use in aspects of a SP distribution system;
- [0016] **FIG. 8** shows an exemplary method for acquiring SP information associated with RF channels in an MFN for use in aspects of a SP distribution system;
- [0017] **FIG. 9** shows exemplary SP logic for use in aspects of a SP distribution system; and
- [0018] **FIG. 10** shows exemplary SP acquisition logic for use in aspects of a SP distribution system.

DETAILED DESCRIPTION OF THE INVENTION

[0019] In one or more aspects, a SP distribution system is provided that operates to distribute SP information associated with one or more RF channels in a multi-frequency network. This SP distribution system enables a device to obtain SP information associated with RF channels in current and neighboring LOIs in a fast and efficient manner. The device can utilize the received SP information to monitor RF channels in current and neighboring LOIs in an effective and efficient manner to determine which RF channels with strong signal strength carry a desired waveform and hence are desirable for RF handoff purposes. The device can also utilize the received SP information to receive desired content flows in an efficient manner after performing a handoff to a new RF channel by eliminating additional delays caused by SP information acquisition. In an aspect, the SP distribution system aggregates SP information associated with RF channels belonging to a particular LOI and its neighboring LOIs. The system generates an NDM that comprises the SP information for RF channels belonging to a particular LOI and its neighboring LOIs (or for another selected group of LOIs and their neighboring LOIs) in the multi-frequency network. The NDMs are then distributed to transmitters in respective LOIs, which in turn transmit the NDMs as part of the distribution waveform to devices in their coverage areas.

[0020] A device receiving an NDM can determine the set of neighboring LOIs of the current LOI and SP information associated with RF channels available in its current LOI and its neighboring LOIs. Because the NDM provides the SP information associated with RF channels in the current and neighboring LOIs, the device does not have to individually tune to each RF channel to obtain the associated SP information. Thus, by obtaining SP information for neighboring RF channels from the NDM, a device is able to effectively monitor RF channels for RF handoff purposes and efficiently acquire desired content flows after performing a handoff to a new RF. The acquired SP information can be used to achieve a faster and more power efficient RF handoff.

[0021] The system is well suited for use in wireless network environments, and may be used in any type of network environment, including but not limited to, communication networks, public networks, such as the Internet, private

networks, such as virtual private networks (VPN), local area networks, wide area networks, long haul networks, or any other type of data network.

[0022] The following definitions are used herein to describe aspects of a SP distribution system.

1. Local Area – Refers to a local geographic area such as a building, group of buildings, community, city, county or other local region in which services may be broadcast.
2. Wide Area – Refers to a wide geographic area such as a county, state, multiple states, country, multiple countries or other wide region in which services may be broadcast.
3. Multiplex – Refers to a grouping of content flows.
4. Wide Area Multiplex – Refers to a grouping of content flows that are broadcasted over at least one wide area.
5. Local Area Multiplex – Refers to grouping of content flows that are broadcasted over at least one local area.
6. Wide Area Operations Infrastructure (WOI) – Refers to a grouping of transmitters and associated systems that operate to transmit content flows over a wide area. A WOI maps to the smallest geographical wide area which can carry a wide area multiplex. A wide area multiplex may be broadcasted over one or more WOIs.
7. Local Area Operations Infrastructure (LOI) – Refers to a grouping of transmitters and associated systems that operate to transmit content flows over a local area. A LOI maps to the smallest geographical local area which can carry a local area multiplex. A local area multiplex may be broadcasted over one or more LOIs.
8. RF Channel – Refers to an RF frequency that is used to convey a content distribution waveform over a selected LOI.

[0023] The following acronyms are used herein to describe aspects of a SP distribution selection system.

LM – Local Area Multiplex

WM – Wide Area Multiplex

NOC – Network Operations Center

LOI – Local Operations Infrastructure

NDM – Neighbor Description Message

SP – Signaling Parameter

FFT – Fast Fourier Transform

OFDM – Orthogonal Frequency Division Multiplexing

WOI – Wide Area Operations Infrastructure

[0024] **FIG. 1** shows an exemplary network **100** that illustrates how SP information is provisioned in multiple LOIs of an MFN for use in aspects of a SP distribution system. For example, the network **100** comprises four WOIs (WOI1, WOI2, WOI3, and WOI4) each comprising one LOI (LOI1, LOI2, LOI3, and LOI4, respectively) of a multi-frequency network. Within each LOI, one or more RF channels are used to transmit content. Each RF channel is associated with SP information that can be used to allow a device to quickly receive a distribution waveform transmitted on that RF channel. LOI1, LOI2, LOI3, and LOI4 are neighboring LOIs as shown in network **100**. The LOI1 has LOI2 as its neighbor, the LOI2 has LOI1, LOI3 and LOI4 as its neighbors, the LOI3 has LOI2 as its neighbor and LOI4 has LOI2 as its neighbor.

[0025] -The network **100** comprises a network operations center (NOC) **102** that operates to receive wide and local content multiplexes for distribution over selected wide and local areas of a multi-frequency network. The NOC **102** also operates to configure the multi-frequency network to distribute that content. To accomplish this, the NOC **102** is aware of the geographic regions of the network that are covered by the LOIs, the RF channels used in each region, and any other network information that may be needed to configure the network and distribute the wide and local area content multiplexes. It should be noted that the network **100** may comprise any number of LOIs.

[0026] In an aspect, the NOC **102** comprises SP logic **104**. The SP logic **104** operates to aggregate SP information associated with RF channels in each LOI and its neighboring LOIs in the MFN. In an aspect, the SP logic **104** operates to generate NDM messages that are configured to provide a list of neighboring LOIs associated with a particular LOI and SP information associated with RF channels of the particular LOI and its neighboring LOIs. In another aspect, the NDM messages are configured to provide a list of neighboring LOIs and SP information associated with RF channels for any

selected group of LOIs. A more detailed description of the NDM messages generated by the SP logic **104** is provided in another section of this document.

[0027] The NOC **102** operates to transmit the wide and local area multiplexes and the generated NDMs to the LOIs in the network **100**. It should be noted that although only four LOIs are shown, the NOC **102** may transmit the multiplexes and associated NDMs to any number of LOIs.

[0028] In an aspect, the LOI1, LOI2, LOI3, and LOI4 comprise one or more transmitter sites. For example, the LOI1 comprises transmitter site **106**. Each transmitter site operates to transmit a distribution waveform on a selected RF channel over its respective LOI. It should be noted that each transmitter site comprises one or more servers as illustrated at **108**.

[0029] In an aspect, the NOC **102** operates to transmit the content multiplexes and the NDMs to the transmitter sites using any suitable transport mechanism. For example, the content multiplexes and the NDMs are transmitted to servers associated with each transmitter site, as illustrated at **110**. In an aspect, the NOC **102** transmits the content multiplexes and the NDM messages to the transmitter sites using an MPEG-2 transport mechanism. In this configuration, the multiplexes and NDM messages are assigned MPEG-2 transport identifiers so that servers at each transmitter site can detect and receive selected content multiplexes and an NDM message which are directed to them, respectively.

[0030] The servers at the transmitter sites use the transport identifiers to determine which multiplexes and NDM message are intended for them to distribute over their respective LOIs. The servers then operate to pack their respective multiplexes and the NDM message into transmission frames for transmission over selected RF channels. The servers utilize any suitable physical layer process to pack the multiplexes and the NDM message into the transmission frames for transmission. By using the transport identifiers to determine the multiplexes and the NDM message intended for transmission over their respective LOIs, the servers at the transmitter sites need not decode any of the multiplexes or NDM messages. The servers simply detect the appropriate transport identifiers and then pack the identified multiplexes and the NDM message into the transmission frames according to the physical layer process.

[0031] The transmission frames comprise content flows associated with the wide and local area multiplexes and the NDM message generated by the SP logic **104**. In an aspect, the transmission frames comprise wide and local area data partitions that are used to convey the wide and local area content flows, respectively. In addition, the wide and local partitions comprise wide and local area control channels. In an aspect, the local area control channel is used to distribute the NDM message generated by the SP logic **104** to the devices in each LOI.

[0032] In an aspect, the transmitter sites transmit transmission frames over their respective LOIs using the designated RF channels. By using multiple RF channels, the network **100** is able to transmit more content flows over such LOIs. It should be noted that the transmitter sites within a LOI may be co-located or separated by any desired distance. It should also be noted that the NDMs distributed over each LOI may be different because each LOI may have a different set of neighbor LOIs and each neighbor may be associated with different RF channels and descrambling sequences with which to descramble the transmitted content.

[0033] A device **112** operating in the LOI2 is tuned to receive a distribution waveform on channel RF2. Details of the device **112** are shown at **114**. The device **112** comprises a receiver **116** that operates to tune to a selected RF channel to receive a distribution waveform that comprises a sequence of transmission frames. The transmission frames that are received comprise a local control channel that conveys an NDM generated by the SP logic **104** for distribution in LOI2. The NDM comprises the list of neighboring LOIs for the current LOI (i.e. LOI2) and SP information associated with RF channels in the current LOI (i.e., LOI2) and its neighboring LOIs (i.e., LOI1, LOI3 and LOI4).

[0034] The receiver **116** passes the received NDM to SP acquisition logic **118**, as illustrated at **120**. The receiver **116** also descrambles the received content associated with RF2 in LOI2 and passes the descrambled content to a decoder **122** that operates to render the content for the device user.

[0035] The SP acquisition logic **118** operates to receive the NDM, which identifies a list of neighboring LOIs for a given LOI (i.e., LOI2) and SP information associated with RF channels in the given LOI and its neighboring LOIs. From this information, the SP acquisition logic **118** operates to store the

mappings between RF channels and SP information used in the current LOI and each neighboring LOI of the current LOI.

[0036] In an aspect, RF channel monitoring logic **124** receives an RF channel indicator that indicates a selected RF channel to be monitored. For example, the signal strength of the selected RF channel is to be determined. The RF channel monitoring logic **124** operates to obtain the appropriate SP information associated with the selected RF channel from the SP acquisition logic **118**, and passes these parameters to the receiver **116** as shown at **126**. The receiver **116** operates to monitor the strength of the selected RF channel using received SP information and passes a signal strength indicator **128** to the RF channel monitoring logic **124**. The RF channel monitoring logic **124** then passes the signal strength indicator for the selected RF channel to other logic at the receiving device **112**. For example, handoff logic **130** at the receiving device **112** may provide several RF channel indicators to the RF channel monitoring logic **124** so that the signal strength of each RF channel can be monitored for handoff purposes.

[0037] The handoff logic **130** receives an RF channel indicator to perform a handoff to a selected RF for receiving desired content. The handoff logic **130** operates to obtain the appropriate SP information associated with the selected RF channel from the SP acquisition logic **118**, and passes these parameters to the receiver **116** as shown at **132**. The receiver **116** operates to acquire the desired content on the selected RF channel using the received SP information.

[0038] Thus, the SP distribution system operates to perform one or more of the following functions to distribute SP information in a multi-frequency network.

1. Determine the configuration of a multi-frequency network.
2. Determine SP information associated with RF channels of the multi-frequency network.
3. Generate NDM messages that are configured to provide a list of neighboring LOIs associated with a particular LOI and SP information associated with RF channels of the particular LOI and its neighboring LOIs.
4. Distribute the NDM messages over the multi-frequency network.

[0039] Additionally, the SP distribution system operates to perform one or more of the following functions to acquire SP information in a multi-frequency network.

1. Obtain (from information in a received NDM) a list of available RF channels in current and neighboring LOIs.
2. Obtain (from information in a received NDM) SP information associated with the list of available RF channels in the current and neighboring LOIs.
3. Receive one or more RF channel identifiers for performing RF monitoring, RF handoff or some other function.
4. Obtain the appropriate SP information for the one or more RF channel identifiers.
5. Output the SP information to the requesting logic.
6. The requesting logic then utilizes the SP information for the one or more RF channel identifiers to perform RF monitoring, RF handoff, or some other function.

[0040] Therefore, in various aspects, the SP distribution system (in the example illustrated in FIG. 1 comprising the SP logic 104 and SP acquisition logic 118) operates to assemble a NDM that comprises a given LOI and its neighboring LOIs and the associated SP information for distribution in a multi-frequency network. Devices receiving the NDM can obtain SP information associated with RF channels in current and neighboring LOIs and use the SP information to effectively monitor selected RF channels and perform RF handoff in an efficient manner.

[0041] **FIG. 2** shows a diagram of an exemplary transmission frame **200** for use in aspects of a SP distribution system. For example, the transmission frame **200** may be packed with wide and local area content multiplexes and an NDM message. The transmission frame **200** may be transmitted by one or more of the transmitter sites shown in **FIG. 1**.

[0042] The transmission frame **200** comprises four sub-frames, shown generally at **202**, that are used to convey wide and local area content multiplexes. For example, each sub-frame **202** comprises a wide area partition **204** that is packed with wide area content multiplexes, and a local area partition **206** that is packed with local area content multiplexes.

[0043] Included in the wide area partition **204** is a wide area control channel **208**. The wide area control channel **208** operates to convey messages pertaining to the wide area content multiplex. Included in the local area partition **206** is a local area control channel **210**. The local area control channel **210** operates to convey messages pertaining to the local area content multiplex. In an aspect, the local area control channel is used to convey an NDM message comprising SP information as described herein.

[0044] At the start of the transmission frame **200** are overhead information symbols (OIS) **212** that provide overhead information that is used to locate the wide area control channel, the local area control channel, and the wide and local area content multiplexes that are packed into the sub-frames **202**. The OIS **212** comprises wide overhead information symbols (WOIS) and local overhead information symbols (LOIS).

[0045] **FIG. 3** shows exemplary SP logic **300** for use in aspect of a SP distribution system. For example, the SP logic **300** is suitable for use as the SP logic **104** shown in **FIG. 1**. The SP logic **300** comprises messaging logic **302**, multiplex input logic **304**, and output logic **306** all coupled to a data bus **308**.

[0046] The multiplex input logic **304** comprises at least one of a CPU, processor, gate array, hardware logic, memory elements, and/or hardware executing software. The multiplex input logic **304** operates to receive one or more wide and/or local area multiplexes **310** that are to be distributed over wide and local regions of a multi-frequency distribution network.

[0047] The messaging logic **302** comprises at least one of a CPU, processor, gate array, hardware logic, memory elements, and/or hardware executing software. The messaging logic **302** operates to generate messages for use in aspects of the SP distribution system. The messaging logic **302** has access to the neighboring relationship information among LOIs in the multi-frequency distribution network. For example, the messaging logic **302** receives network information **314** from the NOC **102**. In an aspect, the messaging logic **302** generates one or more NDM messages that identify one or more neighboring LOIs for a given LOI and SP information associated with RF channels used in the given LOI and its neighboring LOIs. In another aspect, the messaging logic **302** generates an NDM message for any selected group of LOIs. A more

detailed description of the NDM message is provided in another section of this document.

[0048] The output logic **306** comprises at least one of a CPU, processor, gate array, hardware logic, memory elements, and/or hardware executing software. The output logic **306** operates to output content multiplexes and NDM messages (shown at **312**) for distribution to LOIs in a multi-frequency network. For example, the output logic **306** operates to output the received content multiplexes **310** and NDM messages generated by the messaging logic **302** to transmitter sites in a multi-frequency network using any type of transport mechanism.

[0049] In an aspect, the SP distribution system comprises a computer program product having one or more program instructions ("instructions") or sets of "codes" embodied or stored on a machine-readable medium. When the codes are executed by at least one processor, for instance, a processor at the messaging logic **302**, the codes cause the processor to provide the functions described herein. For example, the sets of codes may be embodied on a machine-readable medium, such as a floppy disk, CDROM, memory card, FLASH memory device, RAM, ROM, or any other type of memory device or machine-readable medium that interfaces to the SP logic **300**. In another aspect, the sets of codes may be downloaded into the SP logic **300** from an external device or network resource. The sets of codes, when executed, provide aspects of a SP distribution system as described herein.

[0050] **FIG. 4** shows a diagram that illustrates an exemplary neighbor description message **400** for use in aspects of a SP distribution system. For example, the NDM **400** is generated by the messaging logic **302** shown in **FIG. 3**.

[0051] In an aspect, the NDM **400** is generated separately for each LOI and is configured to provide a list of RF channels associated with a selected LOI and its neighboring LOIs. In another aspect, the NDM **400** is generated for a selected group of LOIs (which may or may not be neighbors), and includes all neighboring LOIs for each of the LOI within the selected group of LOIs. Each of the RF channels described in the NDM **400** is associated with its own SP information. The following is a description of the parameters included in the NDM **400**.

[0052] The NDM **400** comprises a message header **402** which identifies the NDM message **400**. The NDM **400** also comprises a SP information length indicator (SP_Info_Length) **404** that indicates the length (in bits) of a SP information (SP_Info) field provided in the NDM **400**. In an aspect, the SP_Info_Length indicator **404** is a global indicator that specifies length in an integer number of bits for the SP_Info field **420** for every RF included in the NDM **400**. Thus, in this aspect the SP_Info **420** is specified using the same number of bits for all RFs in the NDM.

[0053] The NDM **400** also comprises a LOI count parameter **406** that indicates the number of LOIs for which a set of neighboring LOIs, associated RF channels, and associated SP information is described in the NDM **400**. For each LOI count **406**, a LOI record **422** is included containing the group of parameters as indicated by the bracket. For example, if the LOI count parameter **406** is equal to "2", there will be two sets of LOI records **422**.

[0054] As part of the LOI record **422**, a Reference LOI identifier parameter **408** is provided that identifies a particular reference LOI. A neighbor LOI count parameter **410** is provided that indicates the total number of neighboring LOIs associated with the reference LOI plus the reference LOI itself. For each neighbor LOI count **410**, a Neighbor LOI record **424** is included containing the group of parameters as indicated by the bracket. For example, if the neighbor LOI count parameter **410** is equal to "2", there will be two sets of Neighbor LOI records **424**. The Neighbor LOI record **424** provides RF channels and SP information associated with a given LOI.

[0055] As part of the Neighbor LOI record **424**, a Neighbor LOI Identifier **412** is provided that identifies the particular LOI for which information is being described in the Neighbor LOI Record **424**. A frequency count parameter **414** is provided that indicates how many frequencies (i.e., RF channels) are associated with the identified LOI. For each RF channel in the identified LOI, a Frequency record **426** is included containing the group of parameters as indicated by the bracket. For example, if the Frequency count parameter **414** is equal to "2", there will be two sets of Frequency records **426**.

[0056] As part of the Frequency record **426**, a frequency parameter **416** is provided that indicates a particular transmission frequency. A channel plan parameter **418** is provided that indicates channel bandwidth for the particular

transmission frequency. A SP_info field **420** is provided that describes signaling parameters (including physical layer parameters) associated with a particular transmission frequency.

[0057] As illustrated in **FIG. 4**, the NDM **400** is distributed over the LOI2 using a local control channel **428** that is part of the transmission frames transmitted by the RF channels in LOI2. It should be noted that the NDM **400** may be formatted in any suitable format, encoded or encrypted, and/or reorganized or divided into two or more message components.

[0058] A table **430** is shown that illustrates how parameters provided in the NDM **400** may be organized and stored at SP acquisition logic **118** located at a device **112**. The table **430** comprises a LOI identifier **432** that identifies the device's current LOI (i.e., LOI2). The table **430** also includes a Neighbor LOI List **434** that identifies neighboring LOIs of the device's current LOI plus the current LOI itself.

[0059] The table **430** also comprises RF Frequency identifiers **436** that identify RF frequencies associated with each LOI identified in the Neighbor LOI List **434**. The table **430** also comprises SP information **438** that provides SP_info associated with each RF Frequency **436**. Thus, the table **430** may be generated by SP acquisition logic **118** and stored at a receiving device **112** for use during RF channel monitoring and RF handoff.

[0060] **FIG. 5** shows exemplary SP_info **500** for use in aspects of a SP distribution system. For example, the SP_info **500** may be received in a NDM as illustrated at **420** and stored for each RF channel shown in the table **430**. In an aspect, the SP_info **500** comprises the following information.

1. FFT_Mode (**502**): Specifies a physical layer FFT mode used for OFDM on a RF transmission frequency (3-bits).
2. Pilot_Pattern (**504**): Specifies physical layer pilot pattern used for a RF transmission frequency (2-bits).
3. CP_Length (**506**): Specifies physical layer cyclic prefix length used for a RF transmission frequency (3-bits).

[0061] In an aspect, the SP_info **500** has a size of 8 bits. However, the SP_info can be extended up to 16 bits or larger. In an aspect, the SP_Info_Length field **404** is five bits to support 16 bit SP_info fields. In an

aspect, the SP_Info field **404** is always set to maximum size for each RF channel included in the NDM. In this case, the NDM message does not need to have an SP_Info_Length field **404**. It should be noted that the SP_info **500** is not limited to the signaling parameters shown and that the SP_info **500** may comprise additional signaling parameters or any other type of signaling parameters than those described above.

[0062] In an aspect, only a subset of the SP information may be different for RF channels within a network. For example, the FFT Mode may be the same for all RF channels in the network but the CP Length may be different for these RF channels. In an aspect, only partial SP information can be sent for RF channels in an MFN network. For example, the SP_info can be shortened to three or five bits to send only the following information.

1. 3-Bit SP_info: Includes only CP Length
2. 5-Bit SP_info: Includes only CP Length and Pilot Pattern

[0063] In an aspect, a receiving device should interpret an SP_Info_Length of 3-bits or 5-bits such that the device uses default values for parameter information that is not included in the SP_info. Thus, in an aspect the SP_Info_Length can take one of the following values [0, 3, 5, 8 or larger] depending upon SP_info that is transmitted.

[0064] In an aspect, the SP_Info_Length will be set to zero (0) if no SP_info is being transmitted. This may happen if the entire network is using default SP information that is pre-configured on receiving devices. If the SP_Info_Length set to 0, a receiving device uses a default configured value for SP information associated with all neighboring RFs.

[0065] **FIG. 6** shows an exemplary method **600** for generating neighbor description messages for use in aspects of a SP distribution system. For clarity, the method **600** is described herein with reference to the SP logic **300** shown in **FIG. 3**. For example, in an aspect, the messaging logic **302** executes one or more sets of codes to control the SP logic **300** to perform the functions described below.

[0066] At block **602**, the configuration of a multi-frequency network is determined. For example, the NOC **102** determines the distribution of the wide area and local area multiplexes to selected WOIs and LOIs. In an aspect, the

NOC **102** determines which multiplexes are to be delivered to each LOI and the RF channels that are to be used to deliver the multiplexes within each LOI.

[0067] At block **604**, SP_info is determined for each RF channel. For example, the messaging logic **302** determines SP_info for RF channels in the multi-frequency network from network information received from the NOC **102**.

[0068] At block **606**, NDM messages are generated for each LOI. For example, in an aspect, for each LOI in the distribution network, an NDM is generated that identifies the set of neighboring LOIs for that LOI and provides SP_info for RF channels in that LOI and its neighboring LOIs. In another aspect, an NDM message is generated for any selected group of LOIs. For example, the messaging logic **302** operates to generate the NDM messages, which may be formatted as the NDM **400** illustrated in **FIG. 4**.

[0069] At block **608**, the content multiplexes and NDM messages are distributed to transmitter sites for distribution to devices in each LOI. For example, the content multiplexes and NDM messages are transmitted to the transmitters using any suitable transport mechanism. From the transmitter sites the NDM messages are distributed over each LOI in the local control channel portion of the transmission frames as illustrated in **FIG. 2**.

[0070] Thus, the method **600** operates to generate NDM messages for use in aspects of a SP distribution system. It should be noted that the method **600** represents just one implementation and that other implementations are possible within the scope of the aspects.

[0071] **FIG. 7** shows exemplary SP acquisition logic **700** for use in aspects of a SP distribution system. For example, the SP acquisition logic **700** is suitable for use as the SP acquisition logic **118** shown in **FIG. 1**. The SP acquisition logic **700** comprises processing logic **702**, message decoder **704**, and control channel input logic **706** all coupled to a data bus **708**.

[0072] The control channel input logic **706** comprises at least one of a CPU, processor, gate array, hardware logic, memory elements, and/or hardware executing software. The control channel input logic **706** operates to receive control channel data over an RF channel that a device is currently tuned to and passes this data to the message decoder **704**. For example, an NDM message is received over a local control channel that is part of a transmission frame as illustrated in **FIG. 2**.

[0073] The message decoder **704** comprises at least one of a CPU, processor, gate array, hardware logic, memory elements, and/or hardware executing software. In an aspect, the message decoder **704** operates to decode an NDM message received over the control channel. For example, the message decoder **704** operates to decode the received NDM message to determine SP_info associated with RF channels in the current LOI and its neighboring LOIs. For example, the NDM message is formatted as illustrated in **FIG. 4** and is decoded to determine the SP_info associated with RF channels in the current LOI and its neighbor LOIs. In an aspect, a table of RF channels and associated SP information is maintained and stored as illustrated by table **430**. This information is passed to the processing logic **702**.

[0074] The processing logic **702** comprises at least one of a CPU, processor, gate array, hardware logic, memory elements, and/or hardware executing software. In an aspect, the processing logic **702** operates to receive an RF channel identifier which identifies a selected RF channel. In an aspect, the processing logic **702** is configured to receive the RF channel identifier from the RF channel monitoring logic **124** shown in **FIG. 1** for monitoring signal strength of the selected RF channel. In another aspect, the processing logic **702** is configured to receive the RF channel identifier from the handoff logic **130** shown in **FIG. 1** for performing a handoff to the selected RF channel. The processing logic **702** obtains the SP_info for the selected RF channel from the received NDM. The processing logic **702** then outputs the SP_info to the RF channel monitoring logic **124**, which operates to use the SP_info to effectively monitor the signal strength of the selected RF channel. For example, the signal strength of the selected RF channel may be provided to the handoff logic **130** operating at the device for the purpose of facilitating an RF handoff. The processing logic **702** also outputs the SP_info to the handoff logic **130**, which operates to use the SP_info to acquire desired content on the selected RF channel.

[0075] In an aspect, the SP distribution system comprises a computer program product having one or more program instructions ("instructions") or sets of "codes" stored on a machine-readable medium. When the codes are executed by at least one processor, for instance, a processor at the processing logic **702**, the codes cause the processor to provide the functions described herein. For example, the sets of codes may be loaded into the SP acquisition

logic **700** from a machine-readable medium, such as a floppy disk, CDROM, memory card, FLASH memory device, RAM, ROM, or any other type of memory device or machine-readable medium that interfaces to the SP acquisition logic **700**. In another aspect, the sets of codes may be downloaded into the SP acquisition logic **700** from an external device or network resource. The sets of codes, when executed, cause a processor to provide aspects of a SP distribution system as described herein.

[0076] **FIG. 8** shows an exemplary method **800** for acquiring SP information associated with RF channels in an MFN for use in aspects of a SP distribution system. For clarity, the method **800** is described herein with reference to the SP acquisition logic **700** shown in **FIG. 7**. For example, in an aspect, the processing logic **702** executes one or more sets of codes to control the SP acquisition logic **700** to perform the functions described below.

[0077] At block **802**, a NDM is received over a local control channel. In an aspect, the local control channel data is received by the control channel input logic **706**. For example, local control channel data is received at a device in a sequence of transmission frames that are formatted as illustrated in **FIG. 2**.

[0078] At block **804**, a received NDM message is decoded and SP information is stored. In an aspect, the NDM message is formatted as illustrated in **FIG. 4**. The NDM message identifies the set of neighboring LOIs for the current LOI and associates RF channels with SP information for the current LOI and its neighboring LOIs. In an aspect, the information in the NDM message is decoded by the message decoder **704** and stored at the device in a table as illustrated by table **430**.

[0079] At block **806**, a request is received for SP_info associated with a selected RF channel. In an aspect, the request is received by the processing logic **702**. For example, the request may be received from the RF channel monitoring logic **124** or the handoff logic **130** shown in **FIG. 1**.

[0080] At block **808**, SP_info associated with the selected RF channel is obtained from the information received in the NDM. In an aspect, the processing logic **702** determines the SP_info associated with the selected RF channel from a table that maps RF channels of the current LOI and neighboring LOIs to SP information.

[0081] At block **810**, the SP_info associated with the selected RF channel is output. For example, in an aspect, the SP_info is output by the processing logic **702** to the RF monitoring logic **124** or the RF handoff logic **130** shown in **FIG. 1**.

[0082] At block **812**, the SP_Info is utilized to acquire a distribution waveform on the selected RF. For example, the SP_Info is used by the RF channel monitoring logic **124** to effectively monitor the selected RF channel to facilitate a device handoff. In an aspect, the FFT mode indicator and the cyclic prefix length indicator can be used to determine the OFDM symbol boundaries on the selected RF. The OFDM symbol boundaries can then be used to perform cyclic prefix correlation and determine if the selected RF carries the desired distribution waveform. Alternatively, the SP_Info is used by the handoff logic **130** to acquire desired content on the selected RF channel in an efficient manner.

[0083] Thus, the method **800** operates to acquire and utilize SP information associated with RF channels in an MFN for use in aspects of a SP distribution system. It should be noted that the method **800** represents just one implementation and that other implementations are possible within the scope of the aspects.

[0084] **FIG. 9** shows exemplary SP logic **900** for use in aspects of a SP distribution system. For example, the SP logic **900** is suitable for use as the SP logic **300** shown in **FIG. 3**. In an aspect, the SP logic **900** is implemented by at least one integrated circuit comprising one or more modules configured to provide aspects of a SP distribution system as described herein. For example, in an aspect, each module comprises hardware and/or hardware executing software.

[0085] The SP logic **900** comprises a first module (**902**) for identifying one or more selected local operations infrastructures (LOIs) and one or more neighboring LOIs for each of the one or more selected LOIs in the multi-frequency network, which in an aspect comprises the messaging logic **302**. The SP logic **900** also comprises a second module (**904**) for generating a neighbor description message (NDM) that identifies the one or more selected LOIs and their respective neighboring LOIs and specifies SP information for each radio frequency (RF) channel associated with each of the one or more selected LOIs and their respective neighboring LOIs, which in an aspect comprises the

messaging logic **302**. The SP logic **900** also comprises a third module (**906**) for distributing the NDM over each of the one or more selected LOIs, which in an aspect comprises the output logic **308**.

[0086] **FIG. 10** shows exemplary SP acquisition logic **1000** for use in aspects of a SP distribution system. For example, the SP acquisition logic **1000** is suitable for use as the SP acquisition logic **700** shown in **FIG. 7**. In an aspect, the SP acquisition logic **1000** is implemented by at least one integrated circuit comprising one or more modules configured to provide aspects of a SP distribution system as described herein. For example, in an aspect, each module comprises hardware and/or hardware executing software.

[0087] The SP acquisition logic **1000** comprises a first module (**1002**) for receiving a neighbor description message (NDM) that identifies radio frequency (RF) channels associated with one or more local operations infrastructures (LOIs) and one or more neighboring LOIs of the one or more LOIs, and wherein each RF channel is associated with SP information, which in an aspect comprises the control channel input logic **706**. The SP acquisition logic **1000** also comprises a second module (**1004**) for receiving a request to obtain selected SP information associated with a selected RF channel, which in an aspect comprises the processing logic **702**. The SP acquisition logic **1000** also comprises a third module (**1006**) for determining the selected SP information associated with the selected RF channel based on the NDM, which in an aspect comprises the processing logic **702**. The SP acquisition logic **1000** also comprises a fourth module (**1008**) for outputting the selected SP information, which in an aspect comprises the processing logic **702**.

[0088] The various illustrative logics, logical blocks, modules, and circuits described in connection with the aspects disclosed herein may be implemented or performed with a general purpose processor, a digital signal processor (DSP), an application specific integrated circuit (ASIC), a field programmable gate array (FPGA) or other programmable logic device, discrete gate or transistor logic, discrete hardware components, or any combination thereof designed to perform the functions described herein. A general-purpose processor may be a microprocessor, but, in the alternative, the processor may be any conventional processor, controller, microcontroller, or state machine. A processor may also be implemented as a combination of computing devices,

e.g., a combination of a DSP and a microprocessor, a plurality of microprocessors, one or more microprocessors in conjunction with a DSP core, or any other such configuration.

[0089] The steps of a method or algorithm described in connection with the aspects disclosed herein may be embodied directly in hardware, in a software module executed by a processor, or in a combination of the two. A software module may reside in RAM memory, flash memory, ROM memory, EPROM memory, EEPROM memory, registers, a hard disk, a removable disk, a CD-ROM, or any other form of storage medium known in the art. An exemplary storage medium is coupled to the processor, such that the processor can read information from, and write information to, the storage medium. In the alternative, the storage medium may be integral to the processor. The processor and the storage medium may reside in an ASIC. The ASIC may reside in a user terminal. In the alternative, the processor and the storage medium may reside as discrete components in a user terminal.

[0090] The description of the disclosed aspects is provided to enable any person skilled in the art to make or use the present invention. Various modifications to these aspects may be readily apparent to those skilled in the art, and the generic principles defined herein may be applied to other aspects, e.g., in an instant messaging service or any general wireless data communication applications, without departing from the spirit or scope of the invention. Thus, the present invention is not intended to be limited to the aspects shown herein but is to be accorded the widest scope consistent with the principles and novel features disclosed herein. The word “exemplary” is used exclusively herein to mean “serving as an example, instance, or illustration.” Any aspect described herein as “exemplary” is not necessarily to be construed as preferred or advantageous over other aspects.

[0091] Accordingly, while aspects of SP distribution system have been illustrated and described herein, it will be appreciated that various changes can be made to the aspects without departing from their spirit or essential characteristics. Therefore, the disclosures and descriptions herein are intended to be illustrative, but not limiting, of the scope of the invention, which is set forth in the following claims.

CLAIMS

WHAT IS CLAIMED IS:

1. A method for signaling parameter (SP) distribution in a multi-frequency network, the method comprising:
 - identifying one or more selected local operations infrastructures (LOIs) and one or more neighboring LOIs for each of the one or more selected LOIs in the multi-frequency network;
 - generating a neighbor description message (NDM) that identifies the one or more selected LOIs and their respective neighboring LOIs and specifies SP information for each radio frequency (RF) channel associated with each of the one or more selected LOIs and their respective neighboring LOIs; and
 - distributing the NDM over each of the one or more selected LOIs.
2. The method of claim 1, wherein said generating comprises generating the SP information to comprise at least one of a FFT mode indicator, a pilot pattern indicator, and a cyclic prefix length indicator.
3. The method of claim 1, wherein said generating comprises generating the NDM to specify one instance of SP information for all RF channels associated with a selected LOI
4. The method of claim 1, wherein said generating comprises generating the NDM to specify a separate instance of SP information for each RF channel included in the NDM.
5. The method of claim 1, wherein said generating comprises generating the NDM to specify a size of the SP information for each RF channel included in the NDM.
6. The method of claim 1, wherein said distributing comprises distributing the NDM using a control channel.

7. An apparatus for signaling parameter (SP) distribution in a multi-frequency network, the apparatus comprising:
- messaging logic configured to:
 - identify one or more selected local operations infrastructures (LOIs) and one or more neighboring LOIs for each of the one or more selected LOIs in the multi-frequency network; and
 - generate a neighbor description message (NDM) that identifies the one or more selected LOIs and their respective neighboring LOIs and specifies SP information for each radio frequency (RF) channel associated with each of the one or more selected LOIs and their respective neighboring LOIs; and
 - output logic configured to distribute the NDM over each of the one or more selected LOIs.
8. The apparatus of claim 7, wherein said messaging logic is configured to generate the SP information to comprise at least one of a FFT mode indicator, a pilot pattern indicator, and a cyclic prefix length indicator.
9. The apparatus of claim 7, wherein said messaging logic is configured to generate the NDM to specify one instance of SP information for all RF channels associated with a selected LOI
10. The apparatus of claim 7, wherein said messaging logic is configured to generate the NDM to specify a separate instance of SP information for each RF channel included in the NDM.
11. The apparatus of claim 7, wherein said messaging logic is configured to generate the NDM to specify a size of the SP information for each RF channel included in the NDM.
12. The apparatus of claim 7, wherein said output logic is configured to distribute the NDM using a control channel.
13. An apparatus for signaling parameter (SP) distribution in a multi-frequency network, the apparatus comprising:

means for identifying one or more selected local operations infrastructures (LOIs) and one or more neighboring LOIs for each of the one or more selected LOIs in the multi-frequency network;

means for generating a neighbor description message (NDM) that identifies the one or more selected LOIs and their respective neighboring LOIs and specifies SP information for each radio frequency (RF) channel associated with each of the one or more selected LOIs and their respective neighboring LOIs; and

means for distributing the NDM over each of the one or more selected LOIs.

14. The apparatus of claim 13, wherein said means for generating comprises means for generating the SP information to comprise at least one of a FFT mode indicator, a pilot pattern indicator, and a cyclic prefix length indicator.

15. The apparatus of claim 13, wherein said means for generating comprises means for generating the NDM to specify one instance of SP information for all RF channels associated with a selected LOI

16. The apparatus of claim 13, wherein said means for generating comprises means for generating the NDM to specify a separate instance of SP information for each RF channel included in the NDM.

17. The apparatus of claim 13, wherein said means for generating comprises means for generating the NDM to specify a size of the SP information for each RF channel included in the NDM.

18. The apparatus of claim 13, wherein said means for distributing comprises means for distributing the NDM using a control channel.

19. A computer program product for signaling parameter (SP) distribution in a multi-frequency network, the computer program product comprising:

a machine-readable medium comprising:

a first set of codes for causing a computer to identify one or more selected local operations infrastructures (LOIs) and one or more neighboring LOIs for each of the one or more selected LOIs in the multi-frequency network;

a second set of codes for causing the computer to generate a neighbor description message (NDM) that identifies the one or more selected LOIs and their respective neighboring LOIs and specifies SP information for each radio frequency (RF) channel associated with each of the one or more selected LOIs and their respective neighboring LOIs; and

a third set of codes for causing the computer to distribute the NDM over each of the one or more selected LOIs.

20. The machine-readable medium of claim 19, wherein said second set of codes is configured to cause the computer to generate the SP information to comprise at least one of a FFT mode indicator, a pilot pattern indicator, and a cyclic prefix length indicator.

21. The machine-readable medium of claim 19, wherein said second set of codes is configured to cause the computer to generate the NDM to specify one instance of SP information for all RF channels associated with a selected LOI.

22. The machine-readable medium of claim 19, wherein said second set of codes is configured to cause the computer to generate the NDM to specify a separate instance of SP information for each RF channel included in the NDM.

23. The machine-readable medium of claim 19, wherein said second set of codes is configured to cause the computer to generate the NDM to specify a size of the SP information for each RF channel included in the NDM.

24. The machine-readable medium of claim 19, wherein said third set of codes is configured to cause the computer to distribute the NDM using a control channel.

25. At least one integrated circuit configured for signaling parameter (SP) distribution, the at least one integrated circuit comprising:

a first module configured to identify one or more selected local operations infrastructures (LOIs) and one or more neighboring LOIs for each of the one or more selected LOIs in the multi-frequency network;

a second module configured to generate a neighbor description message (NDM) that identifies the one or more selected LOIs and their respective neighboring LOIs and specifies SP information for each radio frequency (RF) channel associated with each of the one or more selected LOIs and their respective neighboring LOIs; and

a third module configured to distribute the NDM over each of the one or more selected LOIs.

26. The at least one integrated circuit of claim 25, wherein said second module is configured to generate the SP information to comprise at least one of a FFT mode indicator, a pilot pattern indicator, and a cyclic prefix length indicator.

27. The at least one integrated circuit of claim 25, wherein said second module is configured to generate the NDM to specify one instance of SP information for all RF channels associated with a selected LOI

28. The at least one integrated circuit of claim 25, wherein said second module is configured to generate the NDM to specify a separate instance of SP information for each RF channel included in the NDM.

29. The at least one integrated circuit of claim 25, wherein said second module is configured to generate the NDM to specify a size of the SP information for each RF channel included in the NDM.

30. The at least one integrated circuit of claim 25, wherein said third module is configured to distribute the NDM using a control channel.

31. A method for signaling parameter (SP) distribution in a multi-frequency network, the method comprising:

receiving a neighbor description message (NDM) that identifies radio frequency (RF) channels associated with one or more local operations infrastructures (LOIs) and one or more neighboring LOIs of the one or more LOIs, and wherein each RF channel is associated with SP information;

receiving a request to obtain selected SP information associated with a selected RF channel;

determining the selected SP information associated with the selected RF channel based on the NDM; and

outputting the selected SP information.

32. The method of claim 31, wherein said receiving the NDM comprises receiving the NDM over a control channel.

33. The method of claim 31, wherein said receiving the NDM comprises receiving the NDM, wherein the SP information comprises at least one of a FFT mode indicator, a pilot pattern indicator, and a cyclic prefix length indicator.

34. The method of claim 31, wherein said receiving the NDM comprises receiving the NDM, wherein the NDM specifies one instance of SP information for all RF channels associated with a selected LOI.

35. The method of claim 31, wherein said receiving the NDM comprises receiving the NDM, wherein the NDM specifies a separate instance of SP information for each RF channel included in the NDM.

36. The method of claim 31, wherein said receiving the NDM comprises receiving the NDM, wherein the NDM specifies a size of the SP information for each RF channel included in the NDM.

37. The method of claim 31, wherein said receiving the request comprises receiving the request to obtain the selected SP information from RF monitoring logic.

38. The method of claim 31, wherein said receiving the request comprises receiving the request to obtain the selected SP information from RF handoff logic.

39. The method of claim 31, further comprising utilizing the selected SP information to determine if the selected RF channel carries a desired distribution waveform for monitoring the selected RF channel.

40. The method of claim 31, further comprising utilizing the selected SP information to receive a desired distribution waveform for acquiring desired content on the selected RF channel.

41. An apparatus for signaling parameter (SP) distribution in a multi-frequency network, the apparatus comprising:

a message decoder configured to receive a neighbor description message (NDM) that identifies radio frequency (RF) channels associated with one or more local operations infrastructures (LOIs) and one or more neighboring LOIs of the one or more LOIs, and wherein each RF channel is associated with SP information; and

processing logic configured to:

receive a request to obtain selected SP information associated with a selected RF channel;

determine the selected SP information associated with the selected RF channel based on the NDM; and

output the selected SP information.

42. The apparatus of claim 41, wherein said message decoder is configured to receive the NDM over a control channel.

43. The apparatus of claim 41, wherein said SP information comprises at least one of a FFT mode indicator, a pilot pattern indicator, and a cyclic prefix length indicator.

44. The apparatus of claim 41, wherein said NDM specifies one instance of SP information for all RF channels associated with a selected LOI

45. The apparatus of claim 41, wherein said NDM specifies a separate instance of SP information for each RF channel included in the NDM.

46. The apparatus of claim 41, wherein said NDM specifies a size of the SP information for each RF channel included in the NDM.

47. The apparatus of claim 41, wherein said processing logic is configured to receive the request to obtain the selected SP information from RF monitoring logic.

48. The apparatus of claim 41, wherein said processing logic is configured to receive the request to obtain the selected SP information from RF handoff logic.

49. The apparatus of claim 41, wherein said processing logic is configured to utilize the selected SP information to determine if the selected RF channel carries a desired distribution waveform for monitoring the selected RF channel.

50. The apparatus of claim 41, wherein said processing logic is configured to utilize the selected SP information to receive a desired distribution waveform for acquiring desired content on the selected RF channel.

51. An apparatus for signaling parameter (SP) distribution in a multi-frequency network, the apparatus comprising:

means for receiving a neighbor description message (NDM) that identifies radio frequency (RF) channels associated with one or more local

operations infrastructures (LOIs) and one or more neighboring LOIs of the one or more LOIs, and wherein each RF channel is associated with SP information;
means for receiving a request to obtain selected SP information associated with a selected RF channel;
means for determining the selected SP information associated with the selected RF channel based on the NDM; and
means for outputting the selected SP information.

52. The apparatus of claim 51, wherein said means for receiving the NDM comprises means for receiving the NDM over a control channel.

53. The apparatus of claim 51, wherein said SP information comprises at least one of a FFT mode indicator, a pilot pattern indicator, and a cyclic prefix length indicator.

54. The apparatus of claim 51, wherein said NDM specifies one instance of SP information for all RF channels associated with a selected LOI

55. The apparatus of claim 51, wherein said NDM specifies a separate instance of SP information for each RF channel included in the NDM.

56. The apparatus of claim 51, wherein said NDM specifies a size of the SP information for each RF channel included in the NDM.

57. The apparatus of claim 51, wherein said means for receiving the request comprises means for receiving the request to obtain the selected SP information from RF monitoring logic.

58. The apparatus of claim 51, wherein said means for receiving the request comprises means for receiving the request to obtain the selected SP information from RF handoff logic.

59. The apparatus of claim 51, further comprising means for utilizing the selected SP information to determine if the selected RF channel carries a desired distribution waveform for monitoring the selected RF channel.

60. The apparatus of claim 51, further comprising means for utilizing the selected SP information to receive a desired distribution waveform for acquiring desired content on the selected RF channel.

61. A computer program product for signaling parameter (SP) distribution in a multi-frequency network, the computer program product comprising:

- a machine-readable medium comprising:

- a first set of codes for causing a computer to receive a neighbor description message (NDM) that identifies radio frequency (RF) channels associated with one or more local operations infrastructures (LOIs) and one or more neighboring LOIs of the one or more LOIs, and wherein each RF channel is associated with SP information;

- a second set of codes for causing the computer to receive a request to obtain selected SP information associated with a selected RF channel;

- a third set of codes for causing the computer to determine the selected SP information associated with the selected RF channel based on the NDM;
- and

- a fourth set of codes for causing the computer to output the selected SP information.

62. The machine-readable medium of claim 61, wherein said first set of codes is configured to cause the computer to receive the NDM over a control channel.

63. The machine-readable medium of claim 61, wherein said SP information comprises at least one of a FFT mode indicator, a pilot pattern indicator, and a cyclic prefix length indicator.

64. The machine-readable medium of claim 61, wherein said NDM specifies one instance of SP information for all RF channels associated with a selected LOI

65. The machine-readable medium of claim 61, wherein said NDM specifies a separate instance of SP information for each RF channel included in the NDM.

66. The machine-readable medium of claim 61, wherein said NDM specifies a size of the SP information for each RF channel included in the NDM.

67. The machine-readable medium of claim 61, wherein said second set of codes is configured to cause the computer to receive the request to obtain the selected SP information from RF monitoring logic.

68. The machine-readable medium of claim 61, wherein said second set of codes is configured to cause the computer to receive the request to obtain the selected SP information from RF handoff logic.

69. The machine-readable medium of claim 61, further comprising a fifth set of codes for causing the computer to utilize the selected SP information to determine if the selected RF channel carries a desired distribution waveform for monitoring the selected RF channel.

70. The machine-readable medium of claim 61, further comprising a fifth set of codes for causing the computer to utilize the selected SP information to receive a desired distribution waveform for acquiring desired content on the selected RF channel.

71. At least one integrated circuit configured for signaling parameter (SP) distribution in a multi-frequency network, the at least one integrated circuit comprising:

a first module configured to receive a neighbor description message (NDM) that identifies radio frequency (RF) channels associated with one or

more local operations infrastructures (LOIs) and one or more neighboring LOIs of the one or more LOIs, and wherein each RF channel is associated with SP information;

a second module configured to receive a request to obtain selected SP information associated with a selected RF channel;

a third module configured to determine the selected SP information associated with the selected RF channel based on the NDM; and

a fourth module configured to output the selected SP information.

72. The at least one integrated circuit of claim 71, wherein said first module is configured to receive the NDM over a control channel.

73. The at least one integrated circuit of claim 71, wherein said SP information comprises at least one of a FFT mode indicator, a pilot pattern indicator, and a cyclic prefix length indicator.

74. The at least one integrated circuit of claim 71, wherein said NDM specifies one instance of SP information for all RF channels associated with a selected LOI

75. The at least one integrated circuit of claim 71, wherein said NDM specifies a separate instance of SP information for each RF channel included in the NDM.

76. The at least one integrated circuit of claim 71, wherein said NDM specifies a size of the SP information for each RF channel included in the NDM.

77. The at least one integrated circuit of claim 71, wherein said second module is configured to receive the request to obtain the selected SP information from RF monitoring logic.

78. The at least one integrated circuit of claim 71, wherein said second module is configured to receive the request to obtain the selected SP information from RF handoff logic.

79. The at least one integrated circuit of claim 71, further comprising a fifth module configured to utilize the selected SP information to determine if the selected RF channel carries a desired distribution waveform for monitoring the selected RF channel.

80. The at least one integrated circuit of claim 71, further comprising a fifth module configured to utilize the selected SP information to receive a desired distribution waveform for acquiring desired content on the selected RF channel.