

SUPPORT OF MULTIUSER DETECTION IN THE DOWNLINK

This application claims priority from U.S. Provisional Patent Application No. 60/180,402, filed February 4, 2000.

BACKGROUND

The present invention relates generally to wireless time division duplex using code division multiple access (TDD/CDMA) communication systems. In particular, the invention relates to determining channelization codes for use in multiuser detection in the downlink for TDD/CDMA systems.

A TDD/CDMA communication system is illustrated in Figure 1. The system 10 has multiple base stations 12_1 to 12_5 . Each base station 12_i has an associated operating area. User equipments (UEs) 14_1 to 14_3 in a base station's operating area communicate with that base station 12_i . Communications transmitted from a base station 12_i to a UE 14_i are referred to as downlink communications and communications transmitted from a UE 14_i to a base station 12_i are referred to as uplink communications.

In a wireless TDD/CDMA communication system, multiple communications are sent in a shared frequency spectrum. One such system is proposed in a third generation wideband-CDMA (W-CDMA) standard. In CDMA systems, multiple communications are sent in the shared spectrum and are distinguished by channelization codes. In TDD/CDMA systems, the shared spectrum is also time divided using repeating frames having a fixed number of time slots, such as fifteen (15) time slots. Each time slot is used to transmit either only uplink or downlink communications. As a result, the communications are distinguished by both channelization codes and time slots. A single channelization code used in a single time slot is referred to as a resource unit. Based on a communications bandwidth,



communication may require one or multiple resource units. Typical data modulation schemes used in TDD/CDMA systems are quadrature phase shift keying (QPSK), binary phase shift keying (BPSK) and N Quadrature Amplitude Modulation (QAM), such as $N = 8, 16$ or 64 .

Data is transmitted in such systems using communication bursts 16. A communication burst 16 carries data in a single time slot using a single channelization code (a single resource unit). A typical communication burst 16 has a midamble 20, a guard period 18 and two data bursts 22, 24, as shown in Figure 2. The midamble 20 separates the two data bursts 22, 24. The guard period 18 separates the communication bursts 16 to allow for the difference in arrival times of bursts 16 transmitted from different transmitters. The two data bursts 22, 24 contain the communication burst's data. The midamble 20 contains a midamble code for use in estimating the channel response between the receiver and transmitter.

Since multiple communication bursts may be transmitted in a single time slot, a receiver must be able to distinguish data from the multiple bursts. One approach to recover the received data is multiuser detection (MUD).

In MUD, a receiver recovers all communication bursts' data in a time slot, including bursts transmitted to other UEs. To recover all the bursts' data, the MUD receiver needs to know all of the channelization codes used to transmit the bursts. In the proposed TDD mode of W-CDMA, each UE 14₁ to 14₃ only knows which channelization and midamble codes are used for carrying information intended for it. To determine all the channelization and midamble codes, a bank of matched filters is used to detect all possible channelization/midamble combinations. The output power from each matched filter is compared to a threshold to determine whether a particular channelization/midamble combination was used. Due to the number of required matched filters, this approach has a high complexity. Additionally, if there is a high correlation between channelization codes, this approach may have poor performance.

GB2351422 discloses an association of training codes and channelization codes. The training and channelization codes are associated so that for a given spreading factor

each training code is only associated with one channelization code. To facilitate the association, each training sequence is associated with a branch of the DVSF tree.

WO 99/40698 discloses using channel estimates derived from tracking sequences to estimate soft symbols of received communications.

Accordingly, it is desirable to have alternate

approaches for UEs 14_1 to 14_3 to be able to determine the active channelization codes.

SUMMARY

A wireless time division duplex communication system using code division multiple access has a base station and user equipments. The system communicates using communication bursts. Each communication burst has a unique channelization code and a midamble code. Each midamble code is mapped to a set of at least one channelization code. For each communication burst to be transmitted in a time slot from the base station, the midamble code mapped to that burst's channelization code is determined. Communication bursts are generated and transmitted in the time slot. Each burst has the determined midamble code for its channelization code. The user equipment receives the bursts and determines each received midamble code. The user equipment determines the channelization codes of the transmitted communication bursts based on in part a result of the determining of each received midamble code.

BRIEF DESCRIPTION OF THE DRAWINGS

Figure 1 is an illustration of a time division duplex/code division multiple access communication system.

Figure 2 is an illustration of a communication burst.

Figure 3 is an illustration of a simplified base station transmitter and a user equipment receiver.

Figure 4 is a flow chart of downlink channelization code identification.

Figure 5 is an illustration of midamble sequence to channelization code mapping.

Figure 6 is a channelization code detection device.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENT(S)

Figure 3 illustrates a simplified base station transmitter 26 and a UE receiver 28 using multiuser detection (MUD). Data to be communicated to the active UEs 14₁ to 14₃ is produced by data generators 32₁ to 32_K. Each generator 32₁ to 32_K produces data to be sent in a particular communication burst. Each communication burst's generated data is subsequently formatted into a communication burst by a spreading and modulation device 34₁ to 34_K. The spreading and modulation device 34₁ to 34_K adds the midamble and spreads the generated data with a channelization code associated with that communication burst. Additionally, the spread data is time multiplexed into the appropriate time slot. All of the communication bursts are combined by a combiner 52. The combined communication bursts are modulated up to radio frequency, such as by a mixer 36, and the radio frequency signal is radiated by an antenna 38 through a wireless radio channel 30. If transmit diversity is utilized by the base station 14₁, the radio frequency signal will be transmitted by multiple antennas.

At a UE receiver 28, radio frequency signals are received by an antenna 40. The received signals are demodulated to a baseband signal, such as by a mixer 42. A channel estimation device 44 is used to estimate the channel that the communication bursts were transmitted in using the transmitted midamble codes. A multiuser detection (MUD) device 46 processes the baseband signal using the estimated channel information and the active channelization codes to produce hard symbols.

Identifying active channelization codes is shown in the flow chart of Figure 4. One approach to aid in identifying active channelization codes at the UE 14₁ is to provide a mapping between midamble codes (midamble sequences) 54₁ to 54_N and channelization codes 56₁₁ to 56_{NM}, 58. Each midamble sequence 54₁ to 54_N is associated with a set of channelization codes 56₁₁ to 56_{NM}, as illustrated in Figure 5. The sets may contain only a single channelization code, which is a one to one mapping of midambles to channelization codes. A burst transmitted by the base

station 12_i with a channelization code of a midamble's set is formatted with that midamble sequence, 60, 62. To illustrate, if a burst with channelization code 21 was sent, midamble sequence 2 is used for that burst.

At the UE receiver 28, after channel estimation, the transmitted midamble sequences are detected by a midamble sequence detection device 48, 64. Based on the detected midambles, a logic block 45, utilizing the midamble to channelization code mapping 49, determines the set of possible channelization codes. A channelization code detection device 50 determines the received channelization codes based on the determination, 66. If a one midamble code to one channelization code mapping is used, the logic block 45 determines the channelization codes. As a result, for a one to one mapping, the channelization code detection device 50 is not used. The MUD device 46 uses the determined channelization codes and the channel response for the midamble sequences associated with the channelization codes to detect the data from all the bursts, 68.

One channelization code detection device 50 is shown in Figure 6. Matched filters 82_i to 82_M are matched to the possible channelization codes and associated channel responses as determined by the logic block 45. Since only the possible channelization codes need to be checked, the number of matched filters 82_i to 82_M is greatly reduced, reducing the complexity and improving the performance of the receiver 28. The power of the soft symbols produced by each matched filter 82_i to 82_M is measured by corresponding power measurement devices 84_i to 84_M . The comparator 80 determines the received channelization codes based on the power measurement for each channel. If the number of transmitted channelization codes is known, the comparator 80 selects that number of channels with the highest measured power. Otherwise, the comparator 80 compares each channel's power level to a threshold to determine the transmitted channelization codes.

To aid in identifying channelization codes, channelization code information, such as transmitted channelization codes or a number of transmitted channelization codes, may be signaled to the UE 14_i . The signaled information can be used in

conjunction with channelization/midamble code mapping or when mapping is not used. The additional channelization code information will increase the accuracy in determining the active channelization codes at the UE receiver 28. One such signal would be a layer one signal, where the midamble code or midamble code shift is associated with the information. The midamble detection device 48 determines the received midamble code(s) and the logic block 45 recovers the channelization code information using the determined midamble codes. Using the recovered information, the channelization code detection device 50 uses the recovered information to aid in the channelization code determination. Another approach signals channelization code information using a layer 2/3 signal. The signal is generated by the network circuitry. The layer 2/3 signal can be used in conjunction with layer one signals or with the midamble/channelization code mapping.

* * *

CLAIMS

What is claimed is:

1. A method for a time division duplex/code division multiple access user equipment to determine active channelization codes, the user equipment receiving a plurality of communication bursts transmitted in a time slot, the user equipment determining a midamble associated with each received communication burst (64), the method characterized by:

determining possible channelization codes of each received communication burst using a mapping between midambles and channelization codes, each midamble is mapped to at least one channelization code and at least one midamble code is mapped to a plurality of channelization codes (66); and

for each determined midamble mapped to a plurality of possible channelization codes, matching the received communication bursts to the possible channelization codes of that midamble and determining the channelization code of that midamble's communication burst using a result of the matching.

2. The method of claim 1 further characterized by each midamble code is uniquely associated with a shift of a base midamble code.

3. The method of claim 1 further characterized by each midamble code is associated with a plurality of the channelization codes.

4. A method for a time division duplex/code division multiple access user equipment to detect data, the user equipment determining a midamble associated with each received communication burst (64), the method characterized by:

determining possible channelization codes of each received communication burst using a mapping between midambles and channelization codes, each midamble is mapped

to at least one channelization code and at least one midamble code is mapped to a plurality of channelization codes (66); and

for each determined midamble mapped to a plurality of possible channelization codes, matching the received communication bursts to the possible channelization codes of that midamble and determining the channelization code of that midamble's communication burst using a result of the matching; and

detecting data from the received communication bursts using multiuser detection using the determined channelization codes (68).

5. The method of claim 4 further characterized by each midamble code is uniquely associated with a shift of a base midamble code.

6. The method of claim 4 further characterized by each midamble code is associated with a plurality of the channelization codes.

7. A time division duplex/code division multiple access user equipment, the user equipment receiving a plurality of communication bursts transmitted in a time slot and determining a midamble associated with each received communication burst, the user equipment characterized by:

means (45) for determining possible channelization codes of each received communication burst using a mapping (49) between midambles and channelization codes of each received communication burst, each midamble is mapped to at least one channelization code and at least one midamble code is mapped to a plurality of channelization codes; and

means (50) for each determined midamble mapped to a plurality of possible channelization codes, matching the received communication bursts to the possible channelization codes of that midamble and determining the channelization code of that midamble's communication burst using a result of the matching.

8. The user equipment of claim 7 further characterized by each midamble code is uniquely associated with a shift of a base midamble code.

9. The user equipment of claim 7 further characterized by each midamble code is associated with a plurality of the channelization codes.

10. The user equipment of claim 7 further characterized by comprising a multiuser detection device (46) for detecting data of the received communication bursts using the determined channelization codes.

11. A time division duplex/code division multiple access user equipment, the user equipment receiving a plurality of communication bursts transmitted in a time slot and determining a midamble associated with each received communication burst, the user equipment characterized by:

a logic block (45) for determining possible channelization codes of each received communication burst using a mapping (49) between midambles and channelization codes, each midamble is mapped to at least one channelization code and at least one midamble code is mapped to a plurality of channelization codes; and

a channelization code detection device (50) for each midamble mapped to a plurality of possible channelization codes, for matching the received communication bursts to the possible channelization codes of that midamble and determining the channelization code of that midamble's communication burst using a result of the matching.

12. The user equipment of claim 11 wherein the channelization code detection device uses a matched filter (82) matched to each possible channelization code to determine the channelization code of that midamble's communication burst.

13. The user equipment of claim 11 further characterized by each midamble code is uniquely associated with a shift of a base midamble code.

14. The user equipment of claim 11 further characterized by each midamble code is associated with a plurality of the channelization codes.

15. The user equipment of claim 11 further characterized by comprising a multiuser detection device (46) for detecting data of the received communication bursts using the determined channelization codes.

16. A method for a time division duplex/code division multiple access base station to transmit communication bursts, each communication burst having a unique channelization code and a midamble code, the method characterized by:

providing a mapping between channelization codes and midamble codes, each midamble is mapped to at least one channelization code and at least one midamble code is mapped to at least two channelization codes which may be transmitted in communication bursts simultaneously; and

transmitting communication bursts from the base station, each transmitted communication burst having a channelization code and the midamble mapped to that channelization code.

17. The method of claim 16 further characterized by each midamble code is uniquely associated with a shift of a base midamble code.

18. A time division duplex/code division multiple access base station, the base station transmitting communication bursts, each communication burst having a unique channelization code and a midamble code, a mapping exists between channelization codes

and midamble codes, the base station characterized by:

the mapping has each midamble mapped to at least one channelization code and at least one midamble code is mapped to at least two channelization codes which may be transmitted together in communication bursts simultaneously; and

means for transmitting communication bursts, each transmitted communication burst having a channelization code and the midamble mapped to that channelization code.

19. The base station of claim 18 further characterized by each midamble code is uniquely associated with a shift of a base midamble code.