

REPLACED SHEETS		SG
☒ Description	: paged 1 to paged 46	
☒ Claim(s)	: paged 47 to paged 52	
☒ Drawing(s)	: paged 53 to paged 53	
☒ Abstract	: paged 53 to paged 53	

9801061-4
IPDS

TITLE OF THE INVENTION

PACKET SWITCHING SYSTEM, PACKET SWITCHING NETWORK AND
PACKET SWITCHING METHOD

5 BACKGROUND OF THE INVENTION

The present invention relates to a packet switching system and, more particularly, to a packet switching system which, in sending and receiving packets over ATM (Asynchronous Transfer Mode) lines, switches the packets based on the IP (Internet Protocol) routing protocol.

Recent years have seen a surging traffic of packet communications based on the IP thanks in part to the introduction of novel applications such as the WWW (World Wide Web). IP packet switching was carried out conventionally on a packet-by-packet basis with reference to a routing table prepared according to the IP routing protocol. The switching was conducted primarily by software, and it was desired to increase the speed of the processing in the face of an ever-swelling volume of traffic.

One way to address the need for high-speed processing has been proposed in the form of a packet switching system by P. Newman, et al. "Flow Labeled IP: A Connectionless Approach ATM", Proc. IEEE Infocom, March 1996, pp. 1-10 and Japanese Patent Laid-open (Kokai) No. Hei 8-125692. The proposed packet switching system combines two processes: packet-by-packet



processing based on a routing table, and processing of individual ATM cells using ATM switches.

The above packet switching system has a packet processor called IP controller connected to each input/output line of an ATM switch. When IP packets arrive in the form of assembled ATM cells, the cells are sent to the IP controller for a while via the ATM switch. The IP controller reassembles the cells to a IP packet. The destination of each packet to which the cells are reassembled is decided by referring to a routing table as has been done conventionally. The cells are again assembled from the packet and sent via the ATM switch to the output lines bound for their destinations.

If a specific condition is met (e.g., if a predetermined number of packets having the same part of header have arrived); the IP controller allocates a dedicated VC (Virtual Channel) to the packets that were hitherto multiplexed on the same VC as other IP packets. The IP controller then informs the input interface in the ATM switch of a VPI(Virtual Path Identifier) and a VCI(Virtual Channel Identifier) of the input line for the IP packets in question, as well as an output line number and a VPI and a VCI of the output line.

Thereafter, of the IP packets that have arrived at the input interface, those whose headers are partially the same (this group of packets is called a flow hereunder) are switched in the form of ATM cells by the ATM switch without passing through



the IP controller. The switched IP packets are placed onto the output line bound for the destination (this operation is called a cut-through hereunder). This eliminates the need for having to switch each packet by referring to the routing table, whereby
5 high-speed packet switching based on the ATM switch is implemented.

SUMMARY OF THE INVENTION

Conventionally, it has been necessary for a plurality of
10 packet switching systems to allocate dedicated VCs therebetween for each flow of packets when carrying out a cut-through. Therefore, where large quantities of packets need to be processed, the resource allocation becomes a bottleneck. And there are the following problems to be solved in the prior art:

15 (1) Throughput is limited.

(2) The input interface of each ATM switch needs to have connection information set for each flow. Under size constraints of the table permitted for the input interface, only a limited number of flows is handled by cut-through operations.

20 (3) Delays in the dedicated VC resource allocation prevent the cut-through from providing any appreciable improvement in performance for packet transfers of short holding times.

(4) Where packets are transferred through a plurality of packet switching systems connected in a multi-stage structure, no
25 significant improvement in performance is attained if none of



the switching systems performs a cut-through.

On the other hand, a way to provide an idle VC table for retrieving unused VCIs and set a direct channel for transmitting and receiving ATM cells sharing the same destination by setting
5 VCs corresponding to transmission demand has been proposed by U. S. Patent No. 5,452,296. This way brings realizing a cut-through action in the inside of the ATM switching system and lessen a switching delay. However, since the direct channel is not set in each switching system without a setting time, there
10 is still the problem to be solved that there is little effect of lessening a total switching delay in the entire switching network.

It is therefore an object of the present invention to provide a large-capacity packet switching system which has only
15 small delays in cut-through and has limited constraints on the number of flows that may be handled by the cut-through action.

In carrying out the invention and according to one aspect thereof, there is provided a packet switching system comprising: switching means accommodating a plurality of input/output ATM
20 lines; packet destination determining means for determining the destination of a packet on a routing protocol; packet reassembling means for reassembling ATM cells to a packet; cell assembling means for assembling ATM cells from a packet; VPC (Virtual Path Connection) setting means for setting up a VPC
25 among the packet switching systems; and VCC (Virtual Channel



Connection) allocating means for allocating an idle VCC existing in the VPC to packets sharing the same part of header.

The packet switching system may include input and output interfaces, an ATM switch and a control processor. The ATM switch comprises the above-mentioned switching means, and the control processor comprises the remaining means. The input interface is located between the input ATM line connected to the packet switching system and the ATM switch. The output interface is located between the output ATM line connected to the packet switching system and the ATM switch. The input interface changes incoming ATM cells from the input ATM line into internal cells and forwards them to the ATM switch. The output interface turns the internal cells from the ATM switch into ATM cells and sends them to the output ATM line. In the description that follows, packet switching systems located at the input/output parts, namely the peripheral part, of a network will be called edge nodes, and packet switching systems positioned at the transit points, namely the inner part, of the network will be called transit nodes.

Gateways are provided between each of the input and output points of the network and the edge nodes. The gateway located at the input part turns incoming packets from the input point of the network into ATM cells and sends the cells to the edge node located at the input part. In the description that follows, the gateway at the input part will be called a sending-side



gateway, and the edge node at the input part will be called a sending-side edge node. The gateway located at the output part turns the ATM cells received from the edge node located at the output part into packets and forwards the packets to the output point of the network. In the description that follows, the gateway at the output part will be called a receiving-side gateway, and the edge node at the output part will be called a receiving-side edge node.

Since a VPC is assigned up among packet switching systems by the invention, the transit node performs VP (Virtual Path) switching only and does not perform VC switching. This produces that VCCs provided in the VPC are unchanged. Therefore, large capacity switching can be realized in the transit switching system thanks to few constraints on the number of flows.

And, since packets sharing the same part of header are allocated to a VCC and then treated collectively, an easy cut-through can be realized.

It is desired that the packet switching system of the invention has mapping means for mapping correspondence between a packet destination and a VPC. This produces an effect of rapid setting of a VPC.

Moreover, it is desired that the packet switching system of the invention switches the second and subsequent packets of the packets sharing the same part of header without intervention of the packet destination determining means after having



transferred the first packet by use of the packet destination determining means. This produces an actual cut-through.

According to the invention, the control processor of the sending-side edge node manages the VCCs in the VPC established
5 between edge nodes. Each series of IP packets sharing the same part of header and sent from the sending-side gateway is transferred over a different VCC. Therefore, when the first packet of a series of packets is allocated an idle VCC, the need to report this VCC to the receiving-side edge node is eliminated.
10 Hence the ability to perform cut-through at high speed, i.e., rapidly to switch routes at the edge node (to process the first packet followed by transfer of the second and subsequent packets by the switching unit alone).

The inventive constitution permits allocating a VCC to
15 each flow, i.e., a series of packets sharing the same part of header. Unlike conventional arrangements requiring packet switching systems to allocate a dedicated VC to each flow therebetween, the packet switching system of the invention implements the cut-through by simply making necessary internal
20 settings. This significantly reduces delays in cut-through operations.

And, since VCCs set in the direction of an receiving-side edge node are multiplexed collectively in a VPC, there is no need to set up switching information about each VCC as has
25 been the case conventionally. Switching information about the



VPC multiplexing VCCs need only be established, therefore an appreciable increase in the number of VCCs switched by the transit node can be realized.

According to another aspect of the invention, there is provided a packet switching network comprising a first packet switching system (edge node) and a second packet switching system (transit node), the first packet switching system including: switching means accommodating a plurality of input/output ATM lines; packet destination determining means for determining a destination of a packet on a routing protocol; packet reassembling means for reassembling ATM cells to a packet; cell assembling means for assembling ATM cells from a packet; VPC setting means for setting up a VPC among the packet switching systems; mapping means for mapping correspondence between a packet destination address and the VPC; and VCC allocating means for allocating an idle VCC existing in the VPC to packets sharing the same part of header, and the second packet switching system including: switching means accommodating a plurality of input/output ATM lines; and VPC setting means for setting up a VPC among the packet switching systems, wherein at least one transit second packet switching system is furnished between a sending-side first packet switching system and a receiving-side first packet switching system.

Over the inventive packet switching network, the sending-side first packet switching system inputs packets to VPCs, the transit second packet switching system performs VP



(Virtual Path) switching, and the receiving-side first packet switching system switches packets on a flow-by-flow basis. The arrangement allows the transit second packet switching system, in which a large number of packets are concentrated, to switch
5 numerous flows using a single VPC.

These and other objects and many of the attendant advantages of the invention will be readily appreciated as the same becomes better understood by reference to the following detailed description when considered in connection with the
10 accompanying drawings.

BRIEF DESCRIPTION OF THE DRAWINGS

Fig. 1 is a block diagram of a typical edge node;

Fig. 2 is a system block diagram of a network constitution
15 to which the invention is applied;

Fig. 3 is a block diagram of a typical transit node;

Fig. 4 is a block diagram of an input interface included
in the edge node of Fig. 1;

Fig. 5 is a schematic view of a header conversion table
20 included in the interface of Fig. 4;

Fig. 6 is a schematic view of an internal cell format;

Fig. 7 is a flowchart of steps performed by the input
interface of Fig. 4, detailing a cell process thereby;

Fig. 8 is a block diagram of a control processor included
25 in the edge node of Fig. 1;



Fig. 9 is a schematic view of an IP routing table included in the control processor of Fig. 8;

Fig. 10 is a schematic view of a transit flow management table included in the control processor of Fig. 8;

5 Fig. 11 is a schematic view of an IP address/VPC mapping table included in the control processor of Fig. 8;

Fig. 12 is a schematic view of a VPC management table included in the control processor of Fig. 8;

10 Fig. 13 is a schematic view of an input/output VPI/VCI mapping table included in the control processor of Fig. 8;

Fig. 14 is a schematic view of an idle VPI management table included in the control processor of Fig. 8;

Fig. 15 is a schematic view of an ATM routing table included in the control processor of Fig. 8;

15 Fig. 16 is a schematic view of an IP address/ATM address mapping table included in the control processor of Fig. 8;

Fig. 17 is a schematic view of a typical format of an IP packet included in the control processor of Fig. 8;

20 Fig. 18 is a flowchart of steps performed by the control processor of Fig. 8, depicting a packet process thereby;

Fig. 19 is a flowchart of steps performed by the control processor of Fig. 8, detailing an IP packet transfer process thereby;

25 Fig. 20 is a flowchart of steps performed by the control processor of Fig. 8, detailing a VPC setup message transfer



process thereby;

Fig. 21 is a flowchart of steps performed by the control processor of Fig. 8, detailing a VPC setup reply message transfer process thereby;

5 Fig. 22 is a block diagram of a control processor included in the transit node of Fig. 3;

Fig. 23 is a block diagram of a typical gateway;

Fig. 24 is a schematic view of an idle VCI management table included in the gateway of Fig. 23;

10 Fig. 25 is a schematic view of an input flow management table included in the gateway of Fig. 23; and

Fig. 26 is a flowchart of steps performed by the gateway of Fig. 23, detailing a packet processing thereby.

15 DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

Preferred embodiments of this invention will now be described with reference to the accompanying drawings.

20 Fig. 2 shows a typical network constitution to which the invention is applied. In Fig. 2, reference numerals 1a and 1b stand for edge nodes; 2a, 2b and 2c for transit nodes; 3a and 3b for gateways; 4a, 4b and 4c for networks; and 5 for a network management system.

25 Fig. 1 depicts a typical constitution of the edge node 1 (1a, 1b). In Fig. 1, reference numeral 6 (6a, 6b, ..., 6n) stands for an input interface, 7 (7a, 7b, ..., 7m) for an output



interface, 8 for an ATM switch, and 9 for a control processor.

Fig. 3 illustrates a typical constitution of the transit node 2 (2a, 2b, 2c). In Fig. 3, reference numeral 6 (6a, 6b, ..., 6n) stands for an input interface, 7 (7a, 7b, ..., 7m) for an output interface, 8 for an ATM switch, and 10 for a control processor.

Fig. 4 shows a typical constitution of the input interface 6 (6a, 6b, ..., 6n). In Fig. 4, reference numeral 61 stands for a processor, 62 for a header conversion table, and 63 for a cell buffer.

Fig. 5 outlines a typical constitution of the header conversion table 62. In Fig. 5, reference numeral 621 stands for an input VPI, 622 for an input VCI, 623 for a VP switch flag, 624 for an output interface number, 625 for an output VPI, 626 for an output VCI, and 627 for the number of arrival cells.

Fig. 6 depicts a typical format of an internal cell. An internal cell is constructed with an output interface number added to its top.

How each cell is processed by the input interface 6 will now be described with reference to Fig. 7. After receiving an ATM cell (step 500), the input interface 6 stores the received cell in a cell buffer 63 (see Fig. 4) (step 505). The processor 61 retrieves the header conversion table 62 using the VPI in the header as a key (step 510), and checks the VP switch flag 623 (see Fig. 5) (step 520).



If the VP switch flag 623 is found to be 1, the received ATM cell should be switched over VP. In that case, the processor 61 (see Fig. 4) reads out the output interface number 624 and output VPI 625, substituting the output VPI 625 for the VPI in the header of the received ATM cell (step 530). The processor 61 adds the output interface number 624 to the cell (step 540) to create an internal cell, sends the cell to the ATM switch (step 541), and increments by one the number of arrival cells 627 (see Fig. 5) (step 545) in the matching entry of the applicable ATM cell in the header conversion table 62 (see Fig. 4).

If the VP switch flag 623 is found to be 0, the received ATM cell should be switched over VC. In this case, the processor 61 retrieves again the header conversion table 62 using a VPI-VCI pair (step 535). The processor 61 reads out the output interface number 624, output VPI 625 and output VCI 626 to substitute the output VPI 625 and output VCI 626 respectively for the VPI and VCI in the header of the received ATM cell (step 536), and adds the output interface number 624 to the ATM cell (step 540).

The processor 61 creates an internal cell in the manner described above, sends the internal cell to the ATM switch 8 (step 541), and increments by one the number of arrival cells 627 (step 545) in the matching entry of the applicable ATM cell in the header conversion table 62.



The input interface 6 checks periodically the number of arrival cells 627 in each entry of the header conversion table 62. If the number of arrival cells in any entry is found to be 0, the input interface 6 informs the control processor 9 of the applicable input interface number, input VPI, input VCI, and VP switch flag 623. If the number of arrival cells 627 is found to be 1 or larger, the number is reset to 0.

The ATM switch 8 (see Fig. 1) forwards the internal cell to an output interface 7 of the destination on the basis of the output interface number 624 added to the cell by the input interface 6. The output interface 7 deletes the output interface number from the internal cell before transferring the ATM cell to the next node.

Fig. 8 shows a typical constitution of the control processor 9. In Fig. 8, reference numeral 90 stands for an IP routing table, 91 for a processor, 92 for a packet buffer, 93 for an ATM adaptation processing unit, 94 for a transit flow management table, 95 for an IP address/VPC mapping table, 96 for a VPC management table, 97 for an input/output VPI/VCI mapping table, 98 for an idle VPI management table, 99 for an ATM routing table, 100 for an idle VPI memory, 101 for an idle VCI memory, 110 for an IP address/ATM address mapping table, and 120 for an assigned VPI table.

Fig. 9 depicts a typical constitution of the IP routing table 90. In Fig. 9, reference numeral 901 stands for a



destination network IP address, 902 for a mask, 903 for a metric, 904 for a next hop node IP address, and 905 for a next hop node ATM address.

Fig. 10 outlines a typical constitution of the transit flow management table 94. In Fig. 10, reference numeral 941 stands for a destination IP address, 942 for a source IP address, 943 for a port number, 944 for a VPC identifier, 945 for an output interface number, 946 for an output VPI, 947 for an output VCI, and 948 for status.

Further, the port number is given to each packet in TCP/IP (Transmission Control Protocol/IP) protocol or UDP/IP (User Datagram Protocol/IP) protocol so as to identify a higher rank application which uses the carrying service for the each packet. However, the invention is not limited to the port number but can adopt an application identifier to identify an application for general packets including the IP packet. The port number is a kind of the application identifier.

Fig. 11 shows a typical constitution of the IP address/VPC mapping table 95. In Fig. 11, reference numeral 951 stands for a destination IP address, 952 for a port number, 953 for a VPC identifier, 954 for an output interface number, and 955 for an output VPI.

Fig. 12 indicates a typical constitution of the VPC management table 96. In Fig. 12, reference numeral 961 stands for an ATM address, 962 for a VPC identifier, 963 for an output



interface number, 964 for an output VPI, 965 for the number of idle VCIs, 966 for a default VCI, and 967 for an idle VCI pointer.

Fig. 13 gives a typical constitution of the input/output VPI/VCI mapping table 97. In Fig. 13, reference numeral 971 stands for a received VPI, 972 for a received VCI, 973 for an input interface number, 974 for an input VPI, 975 for an input VCI, 976 for status, 977 for a flow pointer.

Fig. 14 sketches a typical constitution of the idle VPI management table 98. In Fig. 14, reference numeral 981 denotes an output interface number and 982 represents an idle VPI pointer.

Fig. 15 depicts a typical constitution of the ATM routing table 99. In Fig. 15, reference numeral 991 stands for a destination ATM address, 992 for a next hop ATM address, 993 for an output interface number, 994 for an output VPI, and 995 for an output VCI.

Fig. 16 shows a typical constitution of the IP address/ATM address mapping table 110. In Fig. 16, reference numeral 111 denotes an IP address and 112 represents an ATM address.

Fig. 17 illustrates a typical format of an IP packet.

At the time of initialization, the network management system 5 establishes an ATM signaling channel between the control processor 9 (see Fig. 1) of a given edge node and the neighbor control processor 9 of its neighbor edge node 1. The control processor 9 receives a destination ATM address, a next



hop ATM address, an output interface number, an output VPI and an output VCI reported through the signaling channel, and sets the reported data to the ATM routing table 99 (see Fig. 8).

The control processor 9 then stores a list of VPIs
5 available over the reported lines in the idle VPI management table 98 as well as to the idle VPI memory 100. Furthermore, the control processor 9 stores in the IP address/ATM address mapping table 110 the correspondence between ATM addresses and the IP addresses assigned to all nodes on the reported network
10 4.

With initialization completed, the control processor 9 processes the received packets in the manner to be described below and transfers the processed packets. The control processor 9 periodically generates IP routing information and
15 transfers the information to the control processor 9 of the neighbor node.

How each packet is processed by the control processor 9 will now be described with reference to Fig. 18. When receiving an internal cell from the ATM switch 8 (step 800), the control
20 processor 9 deletes from the cell the internal interface number added to the cell by the adaptation processing unit 93 so as to reassemble the ATM cells to a packet (step 801). If the received packet is found to be an IP packet (step 810), an IP packet transfer process is carried out (step 820).

25 If the received packet is found to be a VPC setup message



(step 811), a VPC setup message transfer process is conducted (step 840). If the received packet has turned out to be a VPC setup reply message (step 812), a VPC setup reply message transfer process is performed (step 860).

5 If the received packet has proved to be a VPC setup request (step 813), a VPC setup reply message transfer process is carried out (step 880). If the received packet is found to be IP routing information (step 814), an IP routing information process is effected (step 816).

10 If the received packet is found to be a resource allocation request from the gateway 3 (step 815), a resource allocation process is performed (step 817). If the received packet does not fall into any of the above-mentioned categories, the packet is subject to other processes suitable for it (step 818).

15 How the IP packet transfer process is performed (step 820) will now be described with reference to Fig. 19. Upon receipt of the IP packet (step 821), the processor 91 retrieves the transit flow management table 94 using the destination IP address, source IP address and port number (step 822) to check
20 whether the table has a matching content (step 823). If a matching content is detected in the table 94, the processor 91 reads out the output interface number 945, output VPI 946 and output VCI 947 (step 835). The processor 91 assembles cells from the IP packet in question using the adaptation processing
25 unit 93 (step 836), sets the output VPI 946 and output VCI 947



to the ATM header, adds the output interface number 945 to the ATM header, creates internal cells, and sends the created internal cells to the ATM switch 8 (step 837).

5 What follows is a description of how a plurality of VCCs allocated to the IP packets sharing the same header part are multiplexed on the VPC set up between the sending-side edge node 1a and the receiving-side edge node 1b on the packet route.

The processor 91 retrieves the transit flow management table 94 using the destination IP address, source IP address and port number. If the table 94 has no matching content, the processor 91 retrieves the IP address/VPC mapping table 95 using the destination IP address and port number, in order to read the VPC identifier 953, output interface number 954 and output VPI 955 corresponding to the destination IP address and port number (step 824).

The processor 91 then retrieves the VPC management table 96 using the read VPC identifier 953, so as to read the number of idle VCIs 965 and default VCI 966 (step 825). A check is made on the number of idle VCIs 965 (step 826).

20 If the number of idle VCIs is found to be 0, the processor 91 sets the default VCI to the output VCI (step 827). The processor 91 then registers to the transit flow management table 94 the destination IP address, source IP address and port number of the received packet; the VPC identifier 953, output interface number 954 and output VPI 955 read from the IP address/VPC



mapping table 95; and the default VCI 966 read from the VPC management table 96, while the status 948 is set for "default VC being assigned" (step 831).

5 If the number of idle VCIs is found to be at least 1, the processor 91 decrements the number of idle VCIs 965 by one (step 828) and reads out the idle VCI pointer 967 (step 829).

10 The idle VCI memory 101 contains in a list structure the idle VCIs that may be used for this VPC. The starting address of the idle VCIs is written in the idle VCI pointer 967. The processor 91 reads one idle VCI from the idle VCI memory 101 using the idle VCI pointer 967, in order to update the list structure of the idle VCIs in the idle VCI memory 101 (step 830).

15 The processor 91 then registers to the transit flow management table 94 the destination IP address, source IP address and port number of the received packet; the VPC identifier 953, output interface number 954 and output VPI 955 retrieved from the IP address/VPC mapping table 95; and the idle VCI read from the idle VCI memory 101, while the status 948 is set for "dedicated VC being assigned" (step 831).

20 With the above data registered to the transit flow management table 94, the processor 91 reads out the output interface number 945, output VPI 946 and output VCI 947 therefrom (step 835). The processor 91 assembles cells from the IP packet in question using the adaptation processing unit 93 (step 836),
25 sets the output VPI 946 and output VCI 947 to the ATM header,



mapping table 95; and the default VCI 966 read from the VPC management table 96, while the status 948 is set for "default VC being assigned" (step 831).

5 If the number of idle VCIs is found to be at least 1, the processor 91 decrements the number of idle VCIs 965 by one (step 828) and reads out the idle VCI pointer 967 (step 829).

The idle VCI memory 101 contains in a list structure the idle VCIs that may be used for this VPC. The starting address of the idle VCIs is written in the idle VCI pointer 967. The processor 91 reads one idle VCI from the idle VCI memory 101 using the idle VCI pointer 967, in order to update the list structure of the idle VCIs in the idle VCI memory 101 (step 830).

15 The processor 91 then registers to the transit flow management table 94 the destination IP address, source IP address and port number of the received packet; the VPC identifier 953, output interface number 954 and output VPI 955 retrieved from the IP address/VPC mapping table 95; and the idle VCI read from the idle VCI memory 101, while the status 948 is set for "dedicated VC being assigned" (step 831).

20 With the above data registered to the transit flow management table 94, the processor 91 reads out the output interface number 945, output VPI 946 and output VCI 947 therefrom (step 835). The processor 91 assembles cells from the IP packet in question using the adaptation processing unit 93 (step 836), sets the output VPI 946 and output VCI 947 to the ATM header,

25



onward, a cell which is based on the same VPI and VCI and fed to the same input interface as the IP packet in question is forwarded not to the control processor 9 but to the output interface 7 corresponding to the output interface number 945.

5 The edge node 1 carries out its route changing operation in the manner described. That is, a cut-through cell transfer without the intervention of the control processor 9 is accomplished by the switching unit comprising the input interface 6, output interface 7 and ATM switch 8.

10 Below is a description of how any VCC, allocated to a series of IP packets and having become unnecessary, is released. The contents registered in the transit flow management table 94 with regard to a given IP packet are deleted as follows: the input interface 6 first informs the control processor 9 of the input
15 interface number, input VPI, input VCI and VP switch flag 623 (see Fig. 5) in effect when the number of arrival cells is 0. In response, the control processor 9 retrieves the input/output VPI/VCI mapping table 97 (see Figs. 8 and 13) to read the flow pointer 977. The control processor 9 then reads the VPC
20 identifier 944, output VPI 946 and output VCI 947 from the transit flow management table 94 (see Fig. 10) pointed to by the flow pointer 977. Using the VPC identifier 944 thus read, the control processor 9 retrieves the VPC management table 96 (see Fig. 12) and increments by one the number of idle VCIs in
25 the corresponding region. The control processor 9 also adds



onward, a cell which is based on the same VPI and VCI and fed to the same input interface as the IP packet in question is forwarded not to the control processor 9 but to the output interface 7 corresponding to the output interface number 945.

5 The edge node 1 carries out its route changing operation in the manner described. That is, a cut-through cell transfer without the intervention of the control processor 9 is accomplished by the switching unit comprising the input interface 6, output interface 7 and ATM switch 8.

10 Below is a description of how any VCC, allocated to a series of IP packets and having become unnecessary, is released. The contents registered in the transit flow management table 94 with regard to a given IP packet are deleted as follows: the input interface 6 first informs the control processor 9 of the input
15 interface number, input VPI, input VCI and VP switch flag 623 (see Fig. 5) in effect when the number of arrival cells is 0. In response, the control processor 9 retrieves the input/output VPI/VCI mapping table 97 (see Figs. 8 and 13) to read the flow pointer 977. The control processor 9 then reads the VPC
20 identifier 944, output VPI 946 and output VCI 947 from the transit flow management table 94 (see Fig. 10) pointed to by the flow pointer 977. Using the VPC identifier 944 thus read, the control processor 9 retrieves the VPC management table 96 (see Fig. 12) and increments by one the number of idle VCIs in
25 the corresponding region. The control processor 9 also adds



91 (see Fig. 8) first sets the ATM address, the VPC identifier, QOS type and assigned number of VCIs of the node 1, and the ATM address of the own node which are in the VPC setup message, respectively, to the destination ATM address, VPC identifier, QOS type, assigned number of VCIs and source ATM address.

The processor 91 then assigns as many VCIs used for this VPC as the assigned number of VCIs, and sets the value to the assigned VCI region in the setup message. On the basis of the destination ATM address, the processor 91 retrieves the ATM routing table 99 (see Figs. 8 and 15) to read the next hop ATM address 992, output interface number 993, output VPI 994 and output VCI 995. A cell is assembled from the VPC setup message, and the read output VPI 994 and output VCI 995 are set to that cell. The processor 91 further adds the output interface number 993 to the cell before sending the cell to the ATM switch 8. This VPC setup message is transferred to the control processor 9 or 10 of the neighbor node corresponding to the destination ATM address. This completes the processing of the VPC setup request.

How the VPC setup message transfer process (step 840) is carried out will now be described with reference to Fig. 20. Upon receipt of a VPC setup message (step 841), the processor 91 checks to see if the VPC in the message is enable to be assigned (step 842). If it is enable to assign the VPC, the controller 91 retrieves the idle VPI management table 98 to obtain an idle



91 (see Fig. 8) first sets the ATM address, the VPC identifier, QOS type and assigned number of VCIs of the node 1, and the ATM address of the own node which are in the VPC setup message, respectively, to the destination ATM address, VPC identifier, QOS type, assigned number of VCIs and source ATM address.

The processor 91 then assigns as many VCIs used for this VPC as the assigned number of VCIs, and sets the value to the assigned VCI region in the setup message. On the basis of the destination ATM address, the processor 91 retrieves the ATM routing table 99 (see Figs. 8 and 15) to read the next hop ATM address 992, output interface number 993, output VPI 994 and output VCI 995. A cell is assembled from the VPC setup message, and the read output VPI 994 and output VCI 995 are set to that cell. The processor 91 further adds the output interface number 993 to the cell before sending the cell to the ATM switch 8. This VPC setup message is transferred to the control processor 9 or 10 of the neighbor node corresponding to the destination ATM address. This completes the processing of the VPC setup request.

How the VPC setup message transfer process (step 840) is carried out will now be described with reference to Fig. 20. Upon receipt of a VPC setup message (step 841), the processor 91 checks to see if the VPC in the message is enable to be assigned (step 842). If it is enable to assign the VPC, the controller 91 retrieves the idle VPI management table 98 to obtain an idle



is, the setup reply message is made with "enable to setup" and the assigned VPI is put into the VPC setup reply message (step 852). The source address of the VPC setup reply message is set to the ATM address of the own node, and the destination address is set to the source address of the VPC setup message. The VPC identifier and transit node ATM address are copied from their counterparts in the VPC setup message. The VPC setup reply message is then informed to the control processor 9 or 10 of the source neighbor node (step 853).

10 If the ATM address of the own node is found to be other than the destination ATM address in step 845, the processor 91 registers the VPC identifier and assigned VPI of the VPC setup message to the assigned VPI table 120 (step 854). The ATM address of the own node is added to the transit node ATM address of the VPC setup message.

15 The processor 91 then retrieves the ATM routing table 99 on the basis of the destination ATM address so as to read the next hop ATM address 992, output interface number 993, output VPI 994 and output VCI 995 (step 855). The processor 91
20 assembles a cell from the VPC setup message (step 856), sets the read output VPI 994 and output VCI 995 to the cell, adds the output interface number 993 to the cell, and sends the cell thus prepared to the ATM switch 8. Thereafter, the processor 91 transfers the VPC setup message to the control processor 9
25 or 10 of the neighbor node corresponding to the destination ATM



is, the setup reply message is made with "enable to setup" and the assigned VPI is put into the VPC setup reply message (step 852). The source address of the VPC setup reply message is set to the ATM address of the own node, and the destination address is set to the source address of the VPC setup message. The VPC identifier and transit node ATM address are copied from their counterparts in the VPC setup message. The VPC setup reply message is then informed to the control processor 9 or 10 of the source neighbor node (step 853).

10 If the ATM address of the own node is found to be other than the destination ATM address in step 845, the processor 91 registers the VPC identifier and assigned VPI of the VPC setup message to the assigned VPI table 120 (step 854). The ATM address of the own node is added to the transit node ATM address of the VPC setup message.

15 The processor 91 then retrieves the ATM routing table 99 on the basis of the destination ATM address so as to read the next hop ATM address 992, output interface number 993, output VPI 994 and output VCI 995 (step 855). The processor 91
20 assembles a cell from the VPC setup message (step 856), sets the read output VPI 994 and output VCI 995 to the cell, adds the output interface number 993 to the cell, and sends the cell thus prepared to the ATM switch 8. Thereafter, the processor 91 transfers the VPC setup message to the control processor 9
25 or 10 of the neighbor node corresponding to the destination ATM



out as follows:

The processor 91 regards the input VPI 621 in the header conversion table 62 (see Fig. 5) as the assigned VPI, and regards the input VCI 622 as one VCI previously assigned to this VPC.
5 Output VPis 625 and output VCis 626 are assigned so that all values of the VPis and VCis for the VC input from all input interfaces to the control processor 9 differ from one another. The output interface number 624 is set as the output interface number corresponding to the control processor 9 (step 865).

10 The processor 91 carries out the above registration on all VCis assigned to the VPI in question (step 866). The processor 91 proceeds to check whether the VPC is enable to be assigned in the VPC setup reply message (step 863). If the assignment is unable, the network management system 5 is
15 informed thereof.

If the destination ATM address is found to be other than that of the own node in step 862, the processor 91 checks to see if the VPC is enable to be assigned in the VPC setup reply message (step 867). If it is enable to assign the VPC, the
20 controller 91 gets the assigned VPI from the message (step 869). The processor 91 then sets the input VPI 621 in the header conversion table 62 (see Figs. 4 and 5) for the input interface 6 of the VPC in question to the assigned VPI, sets the output VPI 622 to the VPI assigned previously to this VPC, sets the
25 VP switch flag 623 to 1, and sets the output interface number



out as follows:

The processor 91 regards the input VPI 621 in the header conversion table 62 (see Fig. 5) as the assigned VPI, and regards the input VCI 622 as one VCI previously assigned to this VPC. Output VPIs 625 and output VCIs 626 are assigned so that all values of the VPIs and VCIs for the VC input from all input interfaces to the control processor 9 differ from one another. The output interface number 624 is set as the output interface number corresponding to the control processor 9 (step 865).

The processor 91 carries out the above registration on all VCIs assigned to the VPI in question (step 866). The processor 91 proceeds to check whether the VPC is enable to be assigned in the VPC setup reply message (step 863). If the assignment is unable, the network management system 5 is informed thereof.

If the destination ATM address is found to be other than that of the own node in step 862, the processor 91 checks to see if the VPC is enable to be assigned in the VPC setup reply message (step 867). If it is enable to assign the VPC, the controller 91 gets the assigned VPI from the message (step 869). The processor 91 then sets the input VPI 621 in the header conversion table 62 (see Figs. 4 and 5) for the input interface 6 of the VPC in question to the assigned VPI, sets the output VPI 622 to the VPI assigned previously to this VPC, sets the VP switch flag 623 to 1, and sets the output interface number



the output interface number 993 to the cell (step 873). The cell thus prepared is sent to the ATM switch 8, and the VPI setup reply message is transferred to the control processor 9 or 10 of the corresponding neighbor node (step 874). This completes
5 the VPC setup reply message transfer process.

The VPC setup message and the VPC setup reply message can be processed by use of the ATM signaling protocol.

How IP routing information is processed will now be described. If the received packet is found to be IP routing
10 information (see Fig. 18) (step 816), the control processor 9 sets the destination network IP address 901, mask 902, metric 903 and next hop IP address 904 in the IP routing table 90 (see Fig. 8 and 9) on the basis of the IP routing protocol. Then the following process is carried out on each of the registration
15 items in the IP routing table 90.

The control processor 9 first retrieves the IP address/ATM address mapping table 110 (see Fig. 8 and 16) using the next hop node IP address 904 to read the corresponding ATM address 112. The retrieved ATM address 112 is set to the next hop node
20 ATM address 905 (see Fig. 9).

The control processor 9 then retrieves the VPC management table 96 (see Figs. 8 and 12) using the next hop node ATM address 112 to read the corresponding VPC identifier 962, output interface number 963 and output VPI 964. The read VPC
25 identifier 962, output interface number 963 and output VPI 964



the output interface number 993 to the cell (step 873). The cell thus prepared is sent to the ATM switch 8, and the VPI setup reply message is transferred to the control processor 9 or 10 of the corresponding neighbor node (step 874). This completes the VPC setup reply message transfer process.

The VPC setup message and the VPC setup reply message can be processed by use of the ATM signaling protocol.

How IP routing information is processed will now be described. If the received packet is found to be IP routing information (see Fig. 18) (step 816), the control processor 9 sets the destination network IP address 901, mask 902, metric 903 and next hop IP address 904 in the IP routing table 90 (see Fig. 8 and 9) on the basis of the IP routing protocol. Then the following process is carried out on each of the registration items in the IP routing table 90.

The control processor 9 first retrieves the IP address/ATM address mapping table 110 (see Fig. 8 and 16) using the next hop node IP address 904 to read the corresponding ATM address 112. The retrieved ATM address 112 is set to the next hop node ATM address 905 (see Fig. 9).

The control processor 9 then retrieves the VPC management table 96 (see Figs. 8 and 12) using the next hop node ATM address 112 to read the corresponding VPC identifier 962, output interface number 963 and output VPI 964. The read VPC identifier 962, output interface number 963 and output VPI 964



Fig. 22 shows a typical constitution of the control processor 10. In Fig. 22, reference numeral 91 stands for a processor, 92 for a packet buffer, 93 for an adaptation processing unit, 98 for an idle VPI management table, 99 for an ATM routing table, 100 for an idle VPI memory, and 120 for an assigned VPI table. The control processor 10 operates in the same manner as the control processor 9 when the VPC setup message or VPC setup reply message is received. Because the control processor 10 is located in the transit node 2, the processor 10 does not receive any IP packet, VPC setup request or IP routing information.

Fig. 23 depicts a typical constitution of the gateway 3. In Fig. 23, reference numeral 31 stands for a processor, 32 for a packet buffer, 33 for an adaptation processing unit, 34 for an idle VCI management table, 35 for an input flow management table, and 36 for an idle VCI memory.

Fig. 24 illustrates a typical constitution of the idle VCI management table 34. In Fig. 24, reference numeral 341 stands for a VPI, 342 for the number of idle VCIs, 343 for a default VCI, and 344 for an idle VCI pointer.

Fig. 25 indicates a typical constitution of the input flow management table 35. In Fig. 25, reference numeral 351 stands for a destination IP address, 352 for a source IP address, 353 for a port number, 354 for an output VPI, 355 for an output VCI, and 356 for status.



Fig. 22 shows a typical constitution of the control processor 10. In Fig. 22, reference numeral 91 stands for a processor, 92 for a packet buffer, 93 for an adaptation processing unit, 98 for an idle VPI management table, 99 for an ATM routing table, 100 for an idle VPI memory, and 120 for an assigned VPI table. The control processor 10 operates in the same manner as the control processor 9 when the VPC setup message or VPC setup reply message is received. Because the control processor 10 is located in the transit node 2, the processor 10 does not receive any IP packet, VPC setup request or IP routing information.

Fig. 23 depicts a typical constitution of the gateway 3. In Fig. 23, reference numeral 31 stands for a processor, 32 for a packet buffer, 33 for an adaptation processing unit, 34 for an idle VCI management table, 35 for an input flow management table, and 36 for an idle VCI memory.

Fig. 24 illustrates a typical constitution of the idle VCI management table 34. In Fig. 24, reference numeral 341 stands for a VPI, 342 for the number of idle VCIs, 343 for a default VCI, and 344 for an idle VCI pointer.

Fig. 25 indicates a typical constitution of the input flow management table 35. In Fig. 25, reference numeral 351 stands for a destination IP address, 352 for a source IP address, 353 for a port number, 354 for an output VPI, 355 for an output VCI, and 356 for status.



cells from the received IP packet using the adaptation
processing unit 33 (see Fig. 23). The retrieved output VPI 354
and output VCI 355 are set in the ATM header (step 571) of each
of the cells, before the cells are sent to the edge node 1 (step
5 572).

If the input flow management table 35 is not found to have
any item matching the received IP packet in step 555, the
processor 31 retrieves the idle VCI management table 34 (see
Figs. 23 and 24) (step 556), to read the VPI 341, number of idle
10 VCIs 342 and default VCI 343 (step 557).

If the number of idle VCIs 342 is found to be 0, the default
VCI 343 is set as the output VCI (step 561). The gateway 3 sets
to the input flow management table 35 the destination IP address,
source IP address and port number of the received IP packet;
15 and the output VPI 341 and default VCI 343 read from the idle
VCI management table 34, while the status 356 is set for "default
VC being assigned" (step 569).

The gateway 3 proceeds to check the number of idle VCIs
342 (step 560). If the number of idle VCIs is at least 1, the
20 gateway 3 decrements the number of idle VCIs by one (step 565)
and reads the idle VCI pointer 344. Using the read idle VCI
pointer 344, the gateway 3 reads one idle VCI from the idle VCI
memory 36 and updates the list structure of idle VCIs in the
memory 36 (step 566).

25 The gateway 3 then sets the read idle VCI as the output



cells from the received IP packet using the adaptation
processing unit 33 (see Fig. 23). The retrieved output VPI 354
and output VCI 355 are set in the ATM header (step 571) of each
of the cells, before the cells are sent to the edge node 1 (step
5 572).

If the input flow management table 35 is not found to have
any item matching the received IP packet in step 555, the
processor 31 retrieves the idle VCI management table 34 (see
Figs. 23 and 24) (step 556), to read the VPI 341, number of idle
10 VCIs 342 and default VCI 343 (step 557).

If the number of idle VCIs 342 is found to be 0, the default
VCI 343 is set as the output VCI (step 561). The gateway 3 sets
to the input flow management table 35 the destination IP address,
source IP address and port number of the received IP packet;
15 and the output VPI 341 and default VCI 343 read from the idle
VCI management table 34, while the status 356 is set for "default
VC being assigned" (step 569).

The gateway 3 proceeds to check the number of idle VCIs
342 (step 560). If the number of idle VCIs is at least 1, the
20 gateway 3 decrements the number of idle VCIs by one (step 565)
and reads the idle VCI pointer 344. Using the read idle VCI
pointer 344, the gateway 3 reads one idle VCI from the idle VCI
memory 36 and updates the list structure of idle VCIs in the
memory 36 (step 566).

25 The gateway 3 then sets the read idle VCI as the output



edge nodes to the respective ATM routing tables 99 (see Fig. 8).

Thereafter, the network management system 5 informs the control processors 9 in the edge nodes 1a and 1b of a list of VPIs available on the lines, and of the correspondence between ATM addresses and the IP addresses assigned to all nodes on the network 4. Upon initialization or in case of a network status change, the network management system 5 issues a VPC setup request to each of the control processors 9 in the edge nodes 1a and 1b.

What follows is a description of the routing procedure during initialization. When the network 4a is started up, the network management system 5 first establishes ATM signaling channel between the control processor 9 of the edge node 1a and that of the edge node 1b. The network management system 5 then registers the destination ATM address, next hop ATM address, output interface number, output VPI and output VCI corresponding to each of the edge nodes to the respective ATM routing tables 99 (see Fig. 8).

The network management system 5 issues a VPC setup request to each of the control processors 9 in the nodes 1a and 1b. It is assumed here as an example that the VPC setup request has a VPC of a QOS type 1 and a number of an assigned VCI of 16 set therein for the edge nodes 1a and 1b.

Given the VPC setup request from the network management



edge nodes to the respective ATM routing tables 99 (see Fig. 8).

Thereafter, the network management system 5 informs the control processors 9 in the edge nodes 1a and 1b of a list of VPIs available on the lines, and of the correspondence between ATM addresses and the IP addresses assigned to all nodes on the network 4. Upon initialization or in case of a network status change, the network management system 5 issues a VPC setup request to each of the control processors 9 in the edge nodes 1a and 1b.

What follows is a description of the routing procedure during initialization. When the network 4a is started up, the network management system 5 first establishes ATM signaling channel between the control processor 9 of the edge node 1a and that of the edge node 1b. The network management system 5 then registers the destination ATM address, next hop ATM address, output interface number, output VPI and output VCI corresponding to each of the edge nodes to the respective ATM routing tables 99 (see Fig. 8).

The network management system 5 issues a VPC setup request to each of the control processors 9 in the nodes 1a and 1b. It is assumed here as an example that the VPC setup request has a VPC of a QOS type 1 and a number of an assigned VCI of 16 set therein for the edge nodes 1a and 1b.

Given the VPC setup request from the network management



reply message. The VPC setup reply message thus prepared is sent to the transit node 2a that forwarded the VPC setup message.

On receiving the VPC setup reply message from the edge node 1a, the transit node 2a gets the assigned VPI in the message, and sets to the assigned VPI the input VPI of the header conversion table 62 (see Fig. 4) in the interface 6 connected to the edge node 1a. The transit node 2a reads a VPI from the assigned VPI table 120 (see Fig. 22) using the VPC identifier as a key, sets the output VPI to the read VPI, and sets the output interface number to its counterpart in this VPC. The VPI read from the assigned VPI table 120 is placed into the VPC setup reply message before the message is informed to the control processor 9 of the neighbor edge node 1b.

Upon receipt of the VPC setup reply message from the transit node 2a, the edge node 1b gets the assigned VPI in the message to set it up as the input VPI, and regards as the input VCI the VCI previously assigned to this VPC. Output VPIs and output VCIs are assigned so that all values of the VPIs and VCIs for the VC input from all input interfaces to the control processor 9 differ from one another. The VPIs and VCIs, along with the output interface number corresponding to the control processor 9, are registered to the header conversion table 62 (see Fig. 4) for the input interface 6f in each value group. This completes the setup of the VPC between edge nodes.

How initialization takes place at the gateway 3 (see Fig.



reply message. The VPC setup reply message thus prepared is sent to the transit node 2a that forwarded the VPC setup message.

On receiving the VPC setup reply message from the edge node 1a, the transit node 2a gets the assigned VPI in the message, and sets to the assigned VPI the input VPI of the header conversion table 62 (see Fig. 4) in the interface 6 connected to the edge node 1a. The transit node 2a reads a VPI from the assigned VPI table 120 (see Fig. 22) using the VPC identifier as a key, sets the output VPI to the read VPI, and sets the output interface number to its counterpart in this VPC. The VPI read from the assigned VPI table 120 is placed into the VPC setup reply message before the message is informed to the control processor 9 of the neighbor edge node 1b.

Upon receipt of the VPC setup reply message from the transit node 2a, the edge node 1b gets the assigned VPI in the message to set it up as the input VPI, and regards as the input VCI the VCI previously assigned to this VPC. Output VPIs and output VCIs are assigned so that all values of the VPIs and VCIs for the VC input from all input interfaces to the control processor 9 differ from one another. The VPIs and VCIs, along with the output interface number corresponding to the control processor 9, are registered to the header conversion table 62 (see Fig. 4) for the input interface 6f in each value group. This completes the setup of the VPC between edge nodes.

How initialization takes place at the gateway 3 (see Fig.



processor 9 updates the IP routing table 90 (see Fig. 8). In addition, the control processor 9 updates the IP address/VPC mapping table 95 using the address mapping table 110 and VPC management table 96.

5 Described below is what takes place upon arrival of a new IP packet at a gateway 3a on the network 4a. When receiving the packet, the gateway 3a retrieves the input flow management table 35. Because this packet is a new arrival and is not registered in the input flow management table 35 (see Fig. 23),
10 the gateway 3a selects one idle VCI from the idle VCI management table 34, registers the selected VCI to the input flow management table 35, assembles cells from the packet using registered VPIs and VCIs, and sends the cells to the edge node 1a. This completes the assignment of the VCC to the IP packet.

15 The input interface 6 (see Fig. 1) of the edge node 1a retrieves the header conversion table 62 (see Fig. 5) on the basis of the VPI and VCI in the received ATM cell, in order to read the output interface number 624, output VPI 625 and output VCI 626. The input interface 6 sets the output VPI 625 and output
20 VCI 626 to the received ATM cell header, adds the output interface number 624 to the ATM cell, and forwards the ATM cell thus prepared to the ATM switch 8. The ATM switch 8 sends this ATM cell to the output interface corresponding to the output interface number 624 added to the cell.

25 In this packet, the destination output interface number



processor 9 updates the IP routing table 90 (see Fig. 8).. In addition, the control processor 9 updates the IP address/VPC mapping table 95 using the address mapping table 110 and VPC management table 96.

5 Described below is what takes place upon arrival of a new IP packet at a gateway 3a on the network 4a. When receiving the packet, the gateway 3a retrieves the input flow management table 35. Because this packet is a new arrival and is not registered in the input flow management table 35 (see Fig. 23),
10 the gateway 3a selects one idle VCI from the idle VCI management table 34, registers the selected VCI to the input flow management table 35, assembles cells from the packet using registered VPIs and VCIs, and sends the cells to the edge node 1a. This completes the assignment of the VCC to the IP packet.

15 The input interface 6 (see Fig. 1) of the edge node 1a retrieves the header conversion table 62 (see Fig. 5) on the basis of the VPI and VCI in the received ATM cell, in order to read the output interface number 624, output VPI 625 and output VCI 626. The input interface 6 sets the output VPI 625 and output
20 VCI 626 to the received ATM cell header, adds the output interface number 624 to the ATM cell, and forwards the ATM cell thus prepared to the ATM switch 8. The ATM switch 8 sends this ATM cell to the output interface corresponding to the output interface number 624 added to the cell.

25 In this packet, the destination output interface number



If the IP packet meets a predetermined condition, the control processor 9 retrieves the input/output VPI/VCI mapping table 97 for a matching content on the basis of the received VPI and received VCI found earlier in the ATM cell header upon receipt of the IP packet in question. The corresponding input interface 6 is informed of the matching content from the table 97. Then, the input interface 6 stores the output interface number 945 (see Fig. 10), output VPI 946 and output VCI 947 which are received to the corresponding regions in the header conversion table 62 (see Figs. 4 and 5). From this setup onward, a cell fed to the same input interface as the IP packet in question on the basis of the same VPI and VCI is forwarded not to the control processor 9 but to the output interface 7 corresponding to the output interface number 945.

Route changes are carried out by the edge node in the manner described above. That is, the cut-through operation is accomplished in a way that transfers cells not through the control processor 9 but only via the switching unit comprising the input interface 6, output interface 7 and ATM switch 8.

Given the ATM cell from the control processor 9, the ATM switch 8 transfers it to the output interface 7 designated by the output interface number added to the cell. The added output interface number is deleted from the internal cell sent to the output interface 7. The cell is then sent to the transit node

2a.



If the IP packet meets a predetermined condition, the control processor 9 retrieves the input/output VPI/VCI mapping table 97 for a matching content on the basis of the received VPI and received VCI found earlier in the ATM cell header upon receipt of the IP packet in question. The corresponding input interface 6 is informed of the matching content from the table 97. Then, the input interface 6 stores the output interface number 945 (see Fig. 10), output VPI 946 and output VCI 947 which are received to the corresponding regions in the header conversion table 62 (see Figs. 4 and 5). From this setup onward, a cell fed to the same input interface as the IP packet in question on the basis of the same VPI and VCI is forwarded not to the control processor 9 but to the output interface 7 corresponding to the output interface number 945.

Route changes are carried out by the edge node in the manner described above. That is, the cut-through operation is accomplished in a way that transfers cells not through the control processor 9 but only via the switching unit comprising the input interface 6, output interface 7 and ATM switch 8.

Given the ATM cell from the control processor 9, the ATM switch 8 transfers it to the output interface 7 designated by the output interface number added to the cell. The added output interface number is deleted from the internal cell sent to the output interface 7. The cell is then sent to the transit node 2a.



This causes the received ATM cell to be transferred to the control processor 9.

When sent to the control processor 9 (see Fig. 8), the cells are reassembled to an IP packet by the adaptation
5 processing unit 93. The processor 91 retrieves the transit flow management table 94 for a matching content but finds none because this packet is a new arrival. Thus the processor 91 retrieves the IP address/VPC mapping table 95 using the destination IP address, source IP address and port number of the received IP
10 packet, in order to read the destination VPC identifier. One idle VCI defined by the VPC identifier which is read from the VPC management table 96, is assigned to this IP flow, and registered to the transit flow management table 94.

The processor 91 assembles cells from the IP packet using
15 the adaptation processing unit 93, sets to the ATM header of the cell the output VPI 946 and output VCI 947 read from the transit flow management table 94 (see Fig. 10), and adds the output interface number 945 to the cell to turn it into an internal cell. The internal cell thus prepared is sent to the
20 ATM switch 8. This completes the assignment of VCCs set up between the receiving-side edge node 1b and the receiving-side gateway 3b on the packet route.

As with the edge node 1a, if the IP packet meets a predetermined condition, the edge node 1b causes its control
25 processor 9 to instruct the corresponding input interface 6



This causes the received ATM cell to be transferred to the control processor 9.

When sent to the control processor 9 (see Fig. 8), the cells are reassembled to an IP packet by the adaptation
5 processing unit 93. The processor 91 retrieves the transit flow management table 94 for a matching content but finds none because this packet is a new arrival. Thus the processor 91 retrieves the IP address/VPC mapping table 95 using the destination IP address, source IP address and port number of the received IP
10 packet, in order to read the destination VPC identifier. One idle VCI defined by the VPC identifier which is read from the VPC management table 96, is assigned to this IP flow, and registered to the transit flow management table 94.

The processor 91 assembles cells from the IP packet using
15 the adaptation processing unit 93, sets to the ATM header of the cell the output VPI 946 and output VCI 947 read from the transit flow management table 94 (see Fig. 10), and adds the output interface number 945 to the cell to turn it into an internal cell. The internal cell thus prepared is sent to the
20 ATM switch 8. This completes the assignment of VCCs set up between the receiving-side edge node 1b and the receiving-side gateway 3b on the packet route.

As with the edge node 1a, if the IP packet meets a predetermined condition, the edge node 1b causes its control
25 processor 9 to instruct the corresponding input interface 6



from the spirit and scope thereof.





from the spirit and scope thereof.

This Sheet Has Been Replaced





destination determining means, the second and subsequent packets are switched solely by said switching means without intervention of said packet destination determining means.

4. A packet switching system according to claim 3, wherein
5 said plurality of packets assigned to the idle VCC have the same destination.

5. A packet switching system according to claim 3, wherein said plurality of packets assigned to the idle VCC have the same source and the same destination.

10 6. A packet switching system according to claim 3, wherein said plurality of packets assigned to the idle VCC have the same application identifier.

7. A packet switching network for switching packets on a routing protocol and comprising a first and a second packet
15 switching system,

wherein said first packet switching system includes:

switching means accommodating a plurality of input/output
ATM lines;

20 packet destination determining means for determining the destination of a packet on said routing protocol;

packet reassembling means for reassembling ATM cells to a packet;

cell assembling means for assembling ATM cells from a packet;

25 VPC setting means for setting up a VPC among the packet





destination determining means, the second and subsequent packets are switched solely by said switching means without intervention of said packet destination determining means.

4. A packet switching system according to claim 3, wherein
5 said plurality of packets assigned to the idle VCC have the same destination.

5. A packet switching system according to claim 3, wherein said plurality of packets assigned to the idle VCC have the same source and the same destination.

10 6. A packet switching system according to claim 3, wherein said plurality of packets assigned to the idle VCC have the same application identifier.

7. A packet switching network for switching packets on a routing protocol and comprising a first and a second packet
15 switching system,

wherein said first packet switching system includes:

switching means accommodating a plurality of input/output
ATM lines;

packet destination determining means for determining the
20 destination of a packet on said routing protocol;

packet reassembling means for reassembling ATM cells to
a packet;

cell assembling means for assembling ATM cells from a
packet;

25 VPC setting means for setting up a VPC among the packet





packet;

VPC setting means for setting up a VPC among the packet switching systems;

mapping means for mapping correspondence between a packet
5 destination address and said VPC; and

VCC allocating means for allocating an idle VCC existing in said VPC to a plurality of packets sharing the same part of header,

wherein said second packet switching system includes:
10 switching means accommodating a plurality of input/output ATM lines; and

VPC means for setting up a VPC among the packet switching systems, and

wherein said first packet switching system is located in
15 the peripheral part of said packet switching network, and said first and said second packet switching system are located in the inner part of said packet switching network.

9. A packet switching network according to claim 7 or 8, wherein, after the first packet of said plurality of packets
20 sharing the same part of header inputted to said first packet switching system has been transferred by said packet destination determining means, the second and subsequent packets inputted to said first packet switching system as well as the packets input to said second packet switching system are switched solely
25 by said switching means without intervention of said packet





destination determining means.

10. A packet switching system according to claim 7 or 8, wherein said VPC is formed by multiplexing VCCs having the same QOS (Quality Of Service).

5 11. A packet switching method for switching packets using packet switching systems on a routing protocol, the method comprising the steps of:

storing into first storing means correspondence between the destination and the output line of an input ATM cell and
10 a VCC;

storing correspondence between a destination address and a VPC into second storing means on said routing protocol;

storing correspondence between a part of header of packet and a VCC into third storing means;

15 switching ATM cells by use of an ATM switch on the basis of the destination stored in said first storing means upon receipt of the cells which are assembled from a packet;

reassembling ATM cells to a packet;

retrieving said third storing means;

20 assembling ATM cells from a packet if the correspondence of the part of header of packet is stored in said third storing means, the ATM cells being transferred by use of said ATM switch over a first VCC registered for the correspondence; and

retrieving said second storing means if the correspondence
25 of the part of header of packet is not stored in said third storing





means,

wherein the VPC corresponding to said destination address is assigned a second VCC, the correspondence between the part of header of packet and said second VCC is stored into said third
5 storing means, and ATM cells are assembled from the packet in question and are transferred by use of said ATM switch over said second VCC.

12. A packet switching method according to claim 8, further comprising the steps of:

10 setting said VCC that corresponds to the destination and the output line of each of input ATM cells which are assembled from the packet as a VCC for cut-through by updating said first storing means after the correspondence between the part of header of packet and said second VCC has been stored into said
15 third storing means;

retrieving said first storing means upon receipt of ATM cells which are assembled from a packet; and

transferring the ATM cells by use of said ATM switch over said second VCC if the destination and the output line of the
20 received ATM cell corresponds said VCC for cut-through.

This Sheet Has Been Replaced

