

Description

This invention relates generally to the field of optical waveguides and particularly to devices using optical waveguides having a varying refractive index and low loss.

An optical waveguide typically has a region of high refractive index surrounded by a region of low refractive index. The high-low refractive index profile provides the required light guiding effect as the optical radiation is reflected back to the high refractive index region at the interface of the two regions.

Optical waveguides presently find many applications in technology and will undoubtedly be even more widely used in the future. For example, optical waveguides are commonly used to guide light between two optical devices. The waveguide can be an optical fiber guiding light between a light source and a photodetector. Optical fibers typically have a high-index cylindrical core surrounded by a low-index clad. Waveguides are also used in many types of devices including electro-optic devices using LiNbO_3 as well as semiconductor lasers. Waveguides may also be used to connect different optical devices.

For many applications, the waveguides must either be curved or have varying transverse dimensions, i.e., they are tapered. These characteristics are often required, e.g., to connect devices having different dimensions or to switch the optical signals from one waveguide to another waveguide. However, practical implementation of low-loss waveguides having these characteristics is not easy. For example, curved waveguides may have extremely high radiation losses unless very large radii of curvature are used. The currently used optical waveguides are formed by indiffusing Ti into LiNbO_3 , and they may be bent only very slightly to avoid prohibitively high radiation losses. A typical radius of curvature is about 2 cm at a wavelength of approximately $1.3 \mu\text{m}$. Such a relatively large radius of curvature is undesirable for several reasons. For example, optical circuits using such waveguides tend to be long and skinny thereby making an inefficient use of the crystal surface as only relatively thin strips are effectively utilized. Additionally, there are some devices such as, e.g., ring filters and ring lasers which require optical feedback and are not currently feasible because of the large radius of curvature required.

A simple physical argument may be used to show that the conventional curved dielectric waveguide should be lossy because of radiation. Assume that the waveguide is a curved slab having a constant thickness and curvature with a uniform refractive index inside the slab which is larger than the uniform refractive index outside the slab. The phase fronts of the radiation in the waveguide

should move at the same speed, that is, the phase fronts should be rotating planes. It will be readily appreciated that the phase fronts have zero speed at zero radius and approach infinite velocity as the radius becomes large. However, since the velocity of the energy cannot exceed the speed of light, radiation from the waveguide must necessarily occur. Therefore, this curved waveguide is lossy.

Another type of problem also leading to losses often occurs when a waveguide is used to connect devices of different physical dimensions. This problem may arise, e.g., when the waveguide is used to connect a semiconductor laser to an optical fiber or one optical fiber to another when the two have significantly different physical dimensions. The waveguide is typically tapered, i.e., it has a varying transverse dimension, so that the dimensions of the waveguide match those of the devices at the device-waveguide interfaces.

The fact that such a waveguide may be lossy is easily understood from the following physical argument. Assume that the waveguide is a linearly tapered slab with a uniform refractive index outside the slab and a larger and uniform refractive index inside the slab. If the electromagnetic radiation propagates from the wide end to the narrow end, a point is eventually reached at which the waveguide is sufficiently narrow so that at least one mode is no longer guided and radiates.

Attempts have been made to design waveguides having parameters chosen to minimize losses. See, for example, *Applied Optics*, 13, pp. 642-647, March 1974; *Applied Optics*, 16, pp. 711-716, March 1977; *Applied Optics*, 17, pp. 763-768, March 1978; *IEEE Journal of Quantum Electronics*, QE-11, pp. 75-83, February 1975; and *IEEE Journal of Quantum Electronics*, QE-18, pp. 1802-1806, October 1982.

A paper by E.G. Neumann in the Proceedings of the 7th European Conference on Optical Communications, Copenhagen, 8-11 September 1981, pages 9.3-1 to 9.3-4 discloses various modifications of waveguide parameters in the neighbourhood of a bend to reduce radiation loss. These consist of displacement of the core-cladding interface (i.e. changing the shape of the waveguide near the bend) or, alternatively, reducing the refractive index of the cladding at the outside of the bend.

The present invention relates to a device as set out in claim 1. In such a device radiation loss is reduced by one or more refractive elements (e.g. prisms or lenses), constituted by regions having a second profile of refractive index, and arranged to substantially equalise optical path lengths round a bend or through a taper. Such equalization is understood to be relative to optical path length along an optical axis of a waveguide, and equalization

amounts to reducing or minimizing the difference between the optical path lengths along the optical axis and along other significant optical paths. (The latter are optical paths of the waveguide, defined conveniently to carry 75 percent of transmitted power, as well as, preferably, a significant neighborhood of the waveguide). Optical path length can be defined as the integral of refractive index as a function of geometrical path length, and comparison of optical path lengths is understood to involve lengths of paths originating at points on a phase front.

The waveguide has at least one longitudinal section which is curved or whose cross-section varies, and the refractive index varies inside and preferably also in a vicinity of the waveguide so as to locally influence the direction of light propagation. In one embodiment, a waveguide is curved and the refractive index decreases as the distance from the center of the curvature increases. The radius of curvature may be as small as approximately 1 mm with a loss comparable to the loss within a straight waveguide section. In a particular embodiment, a plurality of dielectric prisms provides the varying refractive index which guides the beam around the curve. In yet another embodiment, the waveguides are tapered and have dielectric converging or diverging lenses to shape the wavefront add maintain the desired transverse field configuration. A diverging lens can be interpreted as formed by two prisms touching apex-to-apex, and a converging lens as formed by two prisms touching base-to-base.

FIG. 1 is a schematic representation of a curved waveguide according to this invention;

FIG. 2 is a schematic representation of a tapered waveguide according to this invention;

FIG. 3 is a detailed representation of a curved waveguide according to this invention;

FIG. 4 is a schematic representation of another embodiment of a curved waveguide according to this invention;

FIG. 5 is a schematic representation of a tapered waveguide according to this invention; and

FIG. 6 is a schematic representation of a bent waveguide according to this invention.

For reasons of clarity, the elements depicted are not drawn to scale.

Curved and tapered waveguides according to our invention will be described generally and then more particular design considerations will be discussed.

FIG. 1 illustrates a curved waveguide according to this invention. Depicted are substrate 1, first waveguide 3, second waveguide 5, first electrode 7 to first waveguide 3 and second electrode 9 to second waveguide 5. Optical devices, not shown,

may be connected to the ends of the waveguides. Application of suitable voltages to the electrodes permits optical signals to be transferred from one waveguide to the other. Techniques are well known to those skilled in the art and need not be described in more detail. As can be seen, waveguide 3 curves so as to come closer to waveguide 5 for energy transfer between the waveguides to occur and then curves again to move away from waveguide 5. Waveguide 3 has four curved or curvilinear sections, depicted as 101, 103, 105 and 107 which have radii of curvature indicated as R . Sections 101 and 103 have a combined length L as do sections 105 and 107.

Waveguide 3 has refractive index variations within each curved section which are chosen to permit the radius of curvature of the plurality of bends to be small while allowing the waveguide to guide the mode with little loss. The refractive index variations are such that the refractive index of the waveguide decreases as the distance from the center of curvature increases.

FIG. 2 depicts a tapered waveguide according to this invention. Depicted are substrate 21, first optical device 23, tapered dielectric waveguide 25, and second optical device 27. The first and second devices have different transverse dimensions, i.e., the optical energy is confined within regions of different transverse dimensions. Thus, the tapered dielectric waveguide connects the first and second optical devices 23 and 27 which may be, for example, a light source such as a laser and an optical fiber. The tapers are formed by first polygonal sections 201 and 203 which form a converging section and second polygonal sections 205 and 207 which form a diverging section. The tapered waveguide is desirably used because the active area the laser is typically smaller than the core region of the optical fiber and the taper permits more efficient light coupling between the two devices.

The tapered dielectric waveguide has a varying refractive index which influences the mode configuration within the waveguide as its transverse dimension varies and thus permits mode guidance with little radiative loss.

FIG. 3 is a schematic representation of a portion of a curved waveguide section, for example, 101 and 103 (FIG. 1), according to our invention which is useful in illustrating how the desired refractive index variation is obtained in one exemplary embodiment. For reasons of clarity, the substrate is not depicted. Depicted are waveguide 31 and a plurality 33 of dielectric prisms. The waveguide has a width w_1 while the height of each prism is w_2 . The bases of the prisms are at a distance r_0 from the center of the radius of curvature. The radial direction is indicated by the

arrow designated r . The prisms are positioned so that their widths decrease as the distance from the center of curvature increases. The refractive index of the waveguide decreases, on the average, as the distance from the concave interface increases.

For perfect steering of the beam, the radius of curvature should be equal to r where $r = w_2 n / \Delta n$ where n is the refractive index of the waveguide and Δn is the amount of refractive index increase due to the prisms.

In practice the radius of curvature does not need to be exactly equal to r as the wedges will still reduce the radiation lost due to bending. However, it should be approximately equal to r . For a radius of curvature much larger than r , the prisms are detrimental because of mode mismatch. For a radius of curvature much smaller than r , the prisms are less effective and there will be some loss due to radiation.

The waveguides are expediently fabricated using Ti-diffused LiNbO₃. In principle, the thickness of a Ti sheet deposited on a LiNbO₃ substrate and then diffused may be precisely controlled and the desired refractive index variation obtained by a single diffusion. However, this is not easy to accomplish in practice. It is presently easier in practice to deposit a layer of Ti with a uniform thickness through a mask having a crown-like shape. This layer is then diffused into the underlying LiNbO₃ substrate. A second Ti layer is then deposited and diffused to form the waveguide. While diffusion is considered to be particularly convenient for titanium and lithium niobate, other techniques such as, e.g., ion exchange or ion implantation may be used and indeed may be preferred under different circumstances.

Light within the waveguide travels from notch to notch of the crown parallel to the y axis. The separation between the notches is short as compared to the collimation length of guided beam, and the electromagnetic wave senses the average index and for all practical purposes ignores the discontinuities.

While the embodiment depicted in FIG. 3 is expediently fabricated by using a dual-diffusion process with the prisms being formed by a first diffusion and the waveguide being formed by a second diffusion, embodiments are possible in which there is only a single diffusion. One such embodiment is depicted in FIG. 4 which comprises a plurality of prisms 41 and a plurality of waveguide segments 43. In this embodiment, the guiding of the beam around the turn is provided by the portions of the guides between the prisms.

FIG. 5 depicts a tapered dielectric waveguide 5. The waveguide increases from a width $2a$ to a width $2b$. There is a diverging lens 53 and a converging lens 55 separated by a distance L . The

lenses should overlap the waveguide so that they contain most of the decaying evanescent field. T_1 is a thickness of divergent lens 53 at its center and $T_1 + t$ is the thickness of this lens at the edge of the waveguide. T_0 is a thickness of convergent lens 55 at the edge of the waveguide and $T_0 + h$ is the thickness of lens 55 at the midpoint of the lens. (Typically, the combined widths of index-modifying features is in the range from 1.1 to 4 and preferably from 1.5 to 3 times the width of the waveguide.) Proper choice to t and h insures maximum optical confinement. One skilled in the art can now show that optimum confinement is obtained when $t = n(b-a)a/(2 \Delta n L)$ and

$h = n(b-a)b/(2 \Delta n L)$. A plurality of converging lenses and a plurality of diverging lenses can be used in place of depicted single lenses.

Although the previous descriptions of curved waveguides were in terms of gradual changes in direction, it is contemplated that the change in direction of the curve of the waveguide may be abrupt. One such embodiment is depicted in FIG. 6 which uses only a single prism 71 to deflect the radiation in waveguide 73 through an angle θ . Waveguide 73 has a width $2a$. One skilled in the art may show that optimum steering is obtained when

$$4 \frac{\Delta n}{n} = \theta.$$

It is believed that the desired refractive index and the prism shape and position variations may be more easily understood from the following explanation. To obtain the desired small radius of curvature, w_2 should be small and Δn should be large. The fractional compensating index is limited by the materials available in the fabrication techniques. The choice of w_2 , as well as the location of the crown notches with respect to the guide center, are design variables. Superficially, it seems that the distance between the base of the prism and the edge of the waveguide should be as small as possible. However, more careful consideration indicates that this is not an especially good choice. Due to the symmetry of the index distribution, the field configuration of the guided mode differs from that of the straight section and as a result, the conversion loss occurring at the junction of sections of guides with different curvatures such as an S-shaped guide depicted can become too large. There is a minimization of the total loss that occurs when the mode conversion loss at the junction and the radiation loss due to curvature are identical. Alternatively, loss can be minimized at the juncture of guide sections having different curvature by appropriate lateral displacement of one section relative to the other at the point of juncture.

Still further loss minimization is possible if the teeth of the crown are truncated. The losses are still smaller but problems arising from the high order modes may occur.

The field of applicability of the invention further includes ring lasers, channel dropping filters, frequency tuning, optical feedback circuits, pillbox resonators, and circular resonating cavities in communication, e.g., with a tangential waveguide. Furthermore, the invention is amenable to semiconductor implementation.

Claims

1. An optical waveguiding device comprising an optical waveguide (27,31) having a first cross-sectional profile of raised refractive index being such as to result in guidance of an electromagnetic wave at least in the absence of bends or tapers and having a bend or taper therein and means for reducing radiation loss at the bend or taper

CHARACTERIZED IN THAT said radiation loss reducing means comprises one or more regions (35,33,53,55) having a second profile of raised refractive index, said one or more regions extending across the waveguide bend or taper and being substantially transverse to the longitudinal direction of the waveguide and constituting one or more refractive elements arranged to substantially equalize optical path lengths in the waveguide round the bend or through the taper.

2. A device as claimed in claim 1 wherein the waveguide has a bend and the said one or more regions are arranged so as to constitute one or more prism-shaped features having raised refractive index.
3. A device as claimed in claim 2 including a plurality of said prism-shaped features having raised refractive index.
4. A device as claimed in claim 3 wherein said plurality of features is crown-shaped.
5. A device as claimed in any of the preceding claims wherein said one or more features significantly extend past the waveguide in at least one direction transverse to said path.
6. A device as claimed in claims wherein a width of said one or more features transverse to said path is in the range 1.1 to 4 times a width of said waveguide.

7. A device as claimed in claim 6 wherein said feature width is in the range 1.5 to 3 times said waveguide width.

8. A device as claimed in claim 1 wherein the waveguide has a taper and said one or more regions constitute at least one lens-shaped feature (53,55) having raised refractive index.

Patentansprüche

1. Optische wellenleitende Einrichtung mit einem optischen Wellenleiter (27, 31) mit einem ersten Querschnittsprofil eines erhöhten Brechungsindex, das so ausgebildet ist, daß es zur Führung einer elektromagnetischen Welle wenigstens in der Abwesenheit von Biegungen oder konischen Abschnitten führt, und mit einer Biegung oder einem konischen Abschnitt und eine Einrichtung zur Senkung von Strahlungsverlust an der Biegung oder dem konischen Abschnitt, dadurch gekennzeichnet, daß die den Strahlungsverlust senkende Einrichtung einen oder mehrere Bereiche (35, 33, 53, 55) umfaßt, die ein zweites Profil eines erhöhten Brechungsindex haben, wobei der eine oder die mehreren Bereiche sich über die Wellenleiterbiegung oder den konischen Wellenleiterabschnitt erstrecken und sich im wesentlichen transversal zur Längsrichtung des Wellenleiters erstrecken und eines oder mehrere Brechungsindexelemente bilden, die vorgesehen sind, die optischen Weglängen im Wellenleiter entlang der Biegung oder durch den konischen Abstand im wesentlichen gleichzumachen.
2. Einrichtung nach Anspruch 1, in welcher der Wellenleiter eine Biegung aufweist und der eine oder die mehreren Bereiche so ausgebildet sind, daß eine oder mehrere prismenförmige Strukturen mit erhöhtem Brechungsindex gebildet sind.
3. Einrichtung nach Anspruch 2, mit einer Vielzahl der prismenförmigen Strukturen mit erhöhtem Brechungsindex.
4. Einrichtung nach Anspruch 3, in welcher die Vielzahl von Strukturen kronenförmig ist.
5. Einrichtung nach einem der vorstehenden Ansprüche, in welcher die eine oder mehreren Strukturen sich deutlich wenigstens in einer transversalen Richtung zu dem Ausbreitungsweg über den

Still further loss minimization is possible if the teeth of the crown are truncated. The losses are still smaller but problems arising from the high order modes may occur.

The field of applicability of the invention further includes ring lasers, channel dropping filters, frequency tuning, optical feedback circuits, pillbox resonators, and circular resonating cavities in communication, e.g., with a tangential waveguide. Furthermore, the invention is amenable to semiconductor implementation.

Claims

1. An optical waveguiding device comprising an optical waveguide (27,31) having a first cross-sectional profile of raised refractive index being such as to result in guidance of an electromagnetic wave at least in the absence of bends or tapers and having a bend or taper therein and means for reducing radiation loss at the bend or taper

CHARACTERIZED IN THAT said radiation loss reducing means comprises one or more regions (35,33,53,55) having a second profile of raised refractive index, said one or more regions extending across the waveguide bend or taper and being substantially transverse to the longitudinal direction of the waveguide and constituting one or more refractive elements arranged to substantially equalize optical path lengths in the waveguide round the bend or through the taper.

2. A device as claimed in claim 1 wherein the waveguide has a bend and the said one or more regions are arranged so as to constitute one or more prism-shaped features having raised refractive index.
3. A device as claimed in claim 2 including a plurality of said prism-shaped features having raised refractive index.
4. A device as claimed in claim 3 wherein said plurality of features is crown-shaped.
5. A device as claimed in any of the preceding claims wherein said one or more features significantly extend past the waveguide in at least one direction transverse to said path.
6. A device as claimed in claims wherein a width of said one or more features transverse to said path is in the range 1.1 to 4 times a width of said waveguide.

7. A device as claimed in claim 6 wherein said feature width is in the range 1.5 to 3 times said waveguide width.

8. A device as claimed in claim 1 wherein the waveguide has a taper and said one or more regions constitute at least one lens-shaped feature (53,55) having raised refractive index.

Patentansprüche

1. Optische wellenleitende Einrichtung mit einem optischen Wellenleiter (27, 31) mit einem ersten Querschnittsprofil eines erhöhten Brechungsindex, das so ausgebildet ist, daß es zur Führung einer elektromagnetischen Welle wenigstens in der Abwesenheit von Biegungen oder konischen Abschnitten führt, und mit einer Biegung oder einem konischen Abschnitt und eine Einrichtung zur Senkung von Strahlungsverlust an der Biegung oder dem konischen Abschnitt, dadurch gekennzeichnet, daß die den Strahlungsverlust senkende Einrichtung einen oder mehrere Bereiche (35, 33, 53, 55) umfaßt, die ein zweites Profil eines erhöhten Brechungsindex haben, wobei der eine oder die mehreren Bereiche sich über die Wellenleiterbiegung oder den konischen Wellenleiterabschnitt erstrecken und sich im wesentlichen transversal zur Längsrichtung des Wellenleiters erstrecken und eines oder mehrere Brechungsindexelemente bilden, die vorgesehen sind, die optischen Weglängen im Wellenleiter entlang der Biegung oder durch den konischen Abstand im wesentlichen gleichzumachen.
2. Einrichtung nach Anspruch 1, in welcher der Wellenleiter eine Biegung aufweist und der eine oder die mehreren Bereiche so ausgebildet sind, daß eine oder mehrere prismenförmige Strukturen mit erhöhtem Brechungsindex gebildet sind.
3. Einrichtung nach Anspruch 2, mit einer Vielzahl der prismenförmigen Strukturen mit erhöhtem Brechungsindex.
4. Einrichtung nach Anspruch 3, in welcher die Vielzahl von Strukturen kronenförmig ist.
5. Einrichtung nach einem der vorstehenden Ansprüche, in welcher die eine oder mehreren Strukturen sich deutlich wenigstens in einer transversalen Richtung zu dem Ausbreitungsweg über den



* C L M S *

Wellenleiter hinaus erstrecken.

prisme ayant un indice de réfraction augmenté.

6. Einrichtung nach Anspruch 5,
in welcher eine Breite der einen oder der mehreren Strukturen transversal zum Ausbreitungsweg im Bereich von 1,1- bis 4-mal der Breite des Wellenleiters liegt. 5
7. Einrichtung nach Anspruch 6,
in welcher die Strukturbreite im Bereich von 1,5- bis 3-mal der Wellenleiterbreite liegt. 10
8. Einrichtung nach Anspruch 1,
in welcher der Wellenleiter einen konischen Abschnitt hat und der eine oder die mehreren Bereiche wenigstens eine linsenförmige Struktur (53, 55) mit erhöhtem Brechungsindex bilden. 15

Revendications

1. Un dispositif optique de guidage d'ondes comprenant un guide d'ondes optique (27, 31) ayant un premier profil de section transversale présentant un indice de réfraction augmenté, de façon à assurer un guidage d'une onde électromagnétique, au moins en l'absence de coudes ou de variations de dimension transversale, et comprenant un coude ou une variation de dimension transversale, et des moyens pour réduire les pertes par rayonnement au niveau du coude ou de la variation de section transversale 20
 CARACTERISE EN CE QUE les moyens de réduction de pertes par rayonnement comprennent une ou plusieurs régions (35, 33, 53, 55) ayant un second profil d'indice de réfraction augmenté, cette région ou ces régions s'étendant sur le coude ou la variation de dimension transversale du guide d'ondes, et étant orientées de façon pratiquement transversale par rapport à la direction longitudinale du guide d'ondes, et constituant un ou plusieurs éléments réfringents qui sont conçus pour égaliser pratiquement des longueurs de chemin optique dans le guide d'ondes sur l'étendue du coude ou de la variation de dimension transversale. 35 40 45
2. Un dispositif selon la revendication 1, dans lequel le guide d'ondes comporte un coude et la ou les régions précitées sont conçues de façon à constituer un ou plusieurs éléments en forme de prisme ayant un indice de réfraction augmenté. 50 55
3. Un dispositif selon la revendication 2, comprenant un ensemble des éléments en forme de

4. Un dispositif selon la revendication 3, dans lequel l'ensemble d'éléments a la forme d'une couronne. 5
5. Un dispositif selon l'une quelconque des revendications précédentes, dans lequel le ou les éléments précités s'étendent notablement au-delà du guide d'ondes dans au moins une direction orientée transversalement au chemin précité. 10
6. Un dispositif selon la revendication 5, dans lequel la largeur du ou des éléments, transversalement au chemin précité, est en dans la plage de 1,1 à 4 fois la largeur du guide d'ondes. 15
7. Un dispositif selon la revendication 6, dans lequel la largeur d'élément est dans la plage de 1,5 à 3 fois la largeur du guide d'ondes. 20
8. Un dispositif selon la revendication 1, dans lequel le guide d'ondes présente une variation de dimension transversale, et la ou les régions précitées constituent au moins un élément en forme de lentille (53, 55) ayant un indice de réfraction augmenté. 25 30

