

DESCRIPTION

TRANSMISSION DEVICE AND TRANSMISSION METHOD

5 TECHNICAL FIELD

 The present invention generally relates to a transmission device and a transmission method.

BACKGROUND ART

10 Transmission methods for a downlink data channel include localized transmission and distributed transmission.

 In localized transmission, as shown in FIG. 1A, frequency resources are allocated to the respective
15 users by frequency blocks. For example, in localized transmission, frequency blocks are allocated in such a manner that frequency selective fading is reduced. Generally, transmission data sizes in localized
20 transmission are large, and therefore localized transmission is suitable to achieve the effect of frequency scheduling.

 As shown in FIG. 1B, in distributed transmission, transmission data are distributed across an allocated frequency band regardless of frequency
25 blocks. For example, distributed transmission is employed when frequency scheduling is not usable because users are moving at high speed or when transmission data sizes are small as in VoIP. Generally, transmission data sizes in distributed transmission are small, and
30 therefore distributed transmission is suitable to achieve frequency diversity gain.

DISCLOSURE OF INVENTION

PROBLEMS TO BE SOLVED BY THE INVENTION

However, the above background art technologies have disadvantages as described below.

5 Generally, a system has to support communications of users moving both at low speed and high speed.

Also, a system has to support both packets with large data sizes as in Web browsing and packets
10 with small data sizes as in VoIP.

Embodiments of the present invention make it possible to solve or reduce one or more problems caused by the limitations and disadvantages of the background art, and provide a transmission device and a
15 transmission method that enable a system to support both localized transmission and distributed transmission.

MEANS FOR SOLVING THE PROBLEMS

An embodiment of the present invention
20 provides a transmission device including a frequency scheduling unit configured to allocate, to each user, either frequency blocks that are consecutive frequency subcarrier blocks obtained by dividing a system bandwidth or distributed frequency blocks that are
25 frequency subcarrier blocks discretely distributed in the system bandwidth; and a mapping unit configured to assign transmission data to the frequency blocks or the distributed frequency blocks according to the allocation result. The frequency scheduling unit is configured to
30 allocate the distributed frequency blocks using the frequency blocks as units and to allocate sub-blocks obtained by dividing the respective distributed frequency blocks.

This configuration makes it possible to assign a packet that normally fits in one distributed frequency block to multiple sub-blocks.

Another embodiment of the present inventions
5 provides a transmission method where either frequency blocks that are consecutive frequency subcarrier blocks obtained by dividing a system bandwidth or distributed frequency blocks that are frequency subcarrier blocks discretely distributed in the system bandwidth are
10 allocated to each user. The transmission method includes a sub-block allocating step of allocating sub-blocks obtained by dividing the respective distributed frequency blocks that are allocated using the frequency blocks as units; and a mapping step of assigning
15 transmission data to the frequency blocks or the distributed frequency blocks that are allocated.

This method makes it possible to assign a packet that normally fits in one distributed frequency block to multiple sub-blocks.

20

ADVANTAGEOUS EFFECT OF THE INVENTION

Embodiments of the present invention provide a transmission device and a transmission method that enable a system to support both localized transmission
25 and distributed transmission.

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1A is a drawing illustrating localized transmission;

30 FIG. 1B is a drawing illustrating distributed transmission;

FIG. 2 is a partial block diagram illustrating a transmission device according to an embodiment of the

present invention;

FIG. 3 is a drawing used to describe operations of a transmission device according to an embodiment of the present invention;

5 FIG. 4A is a drawing used to describe operations of a transmission device according to an embodiment of the present invention;

FIG. 4B is a drawing used to describe operations of a transmission device according to an
10 embodiment of the present invention;

FIG. 5 is a drawing illustrating a method of reporting allocation information in localized and distributed multiplexing;

FIG. 6 is a drawing illustrating a method of
15 reporting allocation information in localized and distributed multiplexing;

FIG. 7A is a drawing illustrating a method of reporting allocation information in localized and distributed multiplexing;

20 FIG. 7B is a drawing illustrating a method of reporting allocation information in localized and distributed multiplexing;

FIG. 8 is a drawing illustrating a method of reporting allocation information in localized and
25 distributed multiplexing;

FIG. 9 is a drawing illustrating a method of reporting allocation information in localized and distributed multiplexing;

FIG. 10 is a partial block diagram
30 illustrating a frequency scheduling unit of a transmission device according to an embodiment of the present invention;

FIG. 11 is a drawing used to describe

operations of a frequency scheduling unit of a transmission device according to an embodiment of the present invention;

FIG. 12 is a partial block diagram
5 illustrating a frequency scheduling unit of a transmission device according to an embodiment of the present invention;

FIG. 13 is a drawing used to describe
10 operations of a frequency scheduling unit of a transmission device according to an embodiment of the present invention;

FIG. 14 is a partial block diagram
15 illustrating a frequency scheduling unit of a transmission device according to an embodiment of the present invention;

FIG. 15 is a drawing used to describe
operations of a frequency scheduling unit of a transmission device according to an embodiment of the present invention;

20 FIG. 16 is a flowchart showing a process of allocating radio resources in a transmission device according to an embodiment of the present invention;

FIG. 17A is a drawing illustrating a method of
25 reporting allocation information in localized and distributed multiplexing;

FIG. 17B is a drawing illustrating a method of
reporting allocation information in localized and distributed multiplexing;

FIG. 18A is a drawing illustrating a method of
30 reporting allocation information in localized and distributed multiplexing;

FIG. 18B is a drawing illustrating a method of
reporting allocation information in localized and

distributed multiplexing;

FIG. 19 is a drawing illustrating a method of reporting allocation information in localized and distributed multiplexing;

5 FIG. 20 is a drawing illustrating a method of reporting allocation information in localized and distributed multiplexing;

10 FIG. 21A is a drawing used to describe operations of a frequency scheduling unit of a transmission device according to an embodiment of the present invention;

15 FIG. 21B is a drawing used to describe operations of a frequency scheduling unit of a transmission device according to an embodiment of the present invention;

 FIG. 22A is a drawing used to describe operations of a frequency scheduling unit of a transmission device according to an embodiment of the present invention;

20 FIG. 22B is a drawing used to describe operations of a frequency scheduling unit of a transmission device according to an embodiment of the present invention;

25 FIG. 23A is a drawing used to describe operations of a frequency scheduling unit of a transmission device according to an embodiment of the present invention;

30 FIG. 23B is a drawing used to describe operations of a frequency scheduling unit of a transmission device according to an embodiment of the present invention;

 FIG. 24A is a drawing used to describe operations of a frequency scheduling unit of a

transmission device according to an embodiment of the present invention;

FIG. 24B is a drawing used to describe operations of a frequency scheduling unit of a transmission device according to an embodiment of the present invention;

FIG. 25A is a drawing used to describe operations of a frequency scheduling unit of a transmission device according to an embodiment of the present invention;

FIG. 25B is a drawing used to describe operations of a frequency scheduling unit of a transmission device according to an embodiment of the present invention;

FIG. 26 is a drawing illustrating a method of reporting allocation information in localized and distributed multiplexing;

FIG. 27 is a drawing illustrating a method of reporting allocation information in localized and distributed multiplexing;

FIG. 28 is a drawing illustrating a method of reporting allocation information in localized and distributed multiplexing;

FIG. 29 is a drawing used to describe operations of a frequency scheduling unit of a transmission device according to an embodiment of the present invention;

FIG. 30 is a drawing used to describe operations of a frequency scheduling unit of a transmission device according to an embodiment of the present invention; and

FIG. 31 is a drawing illustrating tree based resource allocation.

EXPLANATION OF REFERENCES

100 Transmission device

5 BEST MODE FOR CARRYING OUT THE INVENTION

The best mode for carrying out the invention is described based on the following embodiments with reference to the accompanying drawings.

Throughout the accompanying drawings, the same
10 reference numbers are used for parts having the same functions, and overlapping descriptions of those parts are omitted.

A transmission device according to an embodiment of the present invention is described below
15 with reference to FIG. 2.

A transmission device 100 of this embodiment performs distributed transmission based on localized transmission. The transmission device 100 is provided, for example, in a base station.

20 The transmission device 100 includes a resource block (RB) allocation ratio switching unit 102 used as an allocation ratio determining unit that receives information on the mobility of mobile stations (UEs) and information, such as sizes and types, on the
25 traffic of the mobile stations; a frequency scheduling unit 104 that receives propagation path information of the mobile stations, priority information of the mobile stations, and an output signal from the resource block allocation ratio changing unit 102; a control
30 information generating unit 106 and a transmission data generating unit 112 each of which receives an output signal from the frequency scheduling unit 104; coding-rate-and-data-modulation determining units 108 and 114

that, respectively, receive output signals from the control information generating unit 106 and the transmission data generating unit 112; a mapping unit 110 that receives an output signal from the coding-rate-and-data-modulation determining unit 108 and outputs control information; and a mapping unit 116 that receives data and an output signal from the coding-rate-and-data-modulation determining unit 114 and outputs data.

The resource block allocation ratio changing unit 102 determines the allocation ratio of resource blocks to be allocated for localized transmission (localized resource blocks) to those to be allocated for distributed transmission (distributed resource blocks) based on the mobility information and traffic information of the mobile stations, and inputs the determined allocation ratio as resource block allocation ratio information to the frequency scheduling unit 104.

For example, when there are many high mobility mobile stations or when the data sizes of packets in the traffic are small as in VoIP, the resource block allocation ratio changing unit 102 allocates a larger share of resource blocks for distributed transmission.

The frequency scheduling unit 104 allocates resource blocks to the mobile stations based on the propagation path information of the mobile stations, the priority information of the mobile stations, and the resource block allocation ratio information. In this embodiment, the priority information of each mobile station is represented by a numerical value obtained based on parameters such as the presence or absence of a retransmission request, time elapsed after a packet is transmitted from a transmitting terminal, a target

transmission rate, actual throughput, and an allowed delay in packet transmission.

For example, the frequency scheduling unit 104 adaptively changes the allocation ratio of localized resource blocks to distributed resource blocks at predetermined intervals, e.g., at each scheduling cycle, according to the resource block allocation ratio information determined based on the conditions, such as channel conditions and traffic, of the mobile stations. This approach makes it possible to increase the throughput of data channels.

Alternatively, the frequency scheduling unit 104 may be configured to change the allocation ratio of localized resource blocks to distributed resource blocks at long intervals according to the resource block allocation ratio information determined based on the conditions, such as traffic, of the mobile stations. Compared with a case where the ratio is changed at each scheduling cycle, this approach makes it easier to control resource block allocation. Also, this approach makes it possible to reduce the number of control bits used to report the number of resource blocks allocated for distributed transmission.

For example, as shown in FIG. 3, the frequency scheduling unit 104 assigns data to be sent by localized transmission and data to be sent by distributed transmission to frequency blocks. In other words, the frequency scheduling unit 104 allocates distributed frequency blocks (resource blocks) that are frequency subcarrier blocks discretely distributed in a system bandwidth to each user using frequency blocks, which are consecutive frequency subcarrier blocks obtained by dividing the system bandwidth, as units. This approach

makes it unnecessary to use signaling information in distributed transmission.

Also, the frequency scheduling unit 104 divides one resource block into multiple sub-blocks, e.g., into N sub-blocks (N represents an integer greater than 0), to perform distributed transmission at resource block level. In this case, the frequency scheduling unit 104 allocates sub-blocks obtained by dividing respective distributed frequency blocks as resource blocks. Here, resource blocks indicate units for mapping users or units for assigning users.

For example, as shown in FIG. 4A, the frequency scheduling unit 104 divides a resource block in the time direction, e.g., into two and allocates the divided resource blocks to multiple users, e.g., to two users. In the example shown in FIG. 4A, the frequency scheduling unit 104 allocates first blocks and second blocks to different users.

Alternatively, the frequency scheduling unit 104 may be configured to divide a resource block in the frequency direction, e.g., into two as shown in FIG. 4B, and to allocate the divided resource blocks to multiple users, e.g., to two users. In the example shown in FIG. 4B, the frequency scheduling unit 104 allocates first blocks and second blocks to different users.

In FIGs. 4A and 4B, the first two symbols represent a pilot and signaling bits, i.e., a pilot channel and an L1/L2 control channel.

In distributed transmission at resource block level, frequency diversity gain cannot be achieved unless multiple resource blocks are allocated. When the data size of a packet is small as in VoIP traffic, all data may fit in one resource block and frequency

diversity gain may not be achieved. In VoIP, the data size of a packet is, for example, 180 bits.

Dividing a resource block into N resource blocks and assigning a packet that normally fits in one resource block to the N resource blocks make it possible to increase frequency diversity gain.

The control information generating unit 106 generates control information for the mobile stations to which resource blocks are allocated by the frequency scheduling unit 104.

The control information generating unit 106 assigns identification codes, for example, numbers, indicating physical locations of resource blocks to the numbers of localized resource blocks. For example, as shown in FIG. 5, when there are 16 resource blocks in a frequency band and all the resource blocks are used as localized resource blocks, the numbers of the localized resource blocks and the numbers indicating physical locations of the resource blocks become identical. In FIG. 5, numbers written in localized RBs represent the numbers assigned to the localized resource blocks and numbers written above the localized RBs represent physical locations of the resource blocks.

When distributed transmission is performed, the control information generating unit 106 converts a subset of the resource blocks into distributed resource blocks. For example, the control information generating unit 106 converts four resource blocks into distributed resource blocks. In this embodiment, localized resource blocks that are to be converted into distributed resource blocks are selected according to a predetermined rule depending on the number of distributed resource blocks.

For example, as shown in FIG. 6, the control information generating unit 106 assigns identification codes or numbers starting from 0 indicating the corresponding physical locations to the resource blocks and converts every $16/N$ -th (N indicates the number of distributed resource blocks to be allocated) resource block to a distributed resource block. This approach makes it possible to uniquely determine resource blocks to be allocated for distributed transmission based on the number of distributed resource blocks and thereby to reduce the amount of control information. In FIG. 6, numbers written in localized RBs and beside distributed RBs, respectively, represent the numbers assigned to localized resource blocks and distributed resource blocks, and numbers written above the RBs represent physical locations of the resource blocks.

The control information generating unit 106 assigns serial numbers to the localized resource blocks and the distributed resource blocks according to a predetermined rule. For example, as shown in FIG. 6, the control information generating unit 106 first assigns numbers to the localized resource blocks in ascending order of the physical location numbers of the resource blocks, and then assigns numbers to the distributed resource blocks. This approach makes it possible to uniquely identify physical locations of the distributed resource blocks and the localized resource blocks based on their assigned numbers and the number of distributed resource blocks. This in turn makes it possible to report allocation information with a small number of bits.

Exemplary resource block allocation to a mobile station 0 (UE0), a mobile station 1 (UE1), a

mobile station 2 (UE2), a mobile station 3 (UE3), and a mobile station 4 (UE4) is described below with reference to FIGs. 7A and 7B.

Here, it is assumed that the mobile stations 0, 1, and 2 are low mobility users and the mobile stations 3 and 4 are high mobility users. In this case, the frequency scheduling unit 104 allocates localized resource blocks to the mobile stations 0, 1, and 2, and allocates distributed resource blocks to the mobile stations 3 and 4.

For example, the frequency scheduling unit 104 allocates resource blocks #0, #1, and #3 to the mobile station 0, resource block #2 to the mobile station 1, resource blocks #4, #5, #6, #7, #8, #9, #10, and #11 to the mobile station 2, resource blocks #12, #13, and #14 to the mobile station 3, and resource block #15 to the mobile station 4.

An exemplary method of reporting allocation information is described below.

As shown in FIG. 8, when encoding and sending allocation information for multiple mobiles stations collectively, the control information generating unit 106 reports the number of distributed resource blocks, IDs of mobile stations to which resource blocks are allocated, and mobile station numbers associated with resource block numbers of allocated resource blocks. In other words, the control information generating unit 106 generates control information including the number of identification codes identifying resource blocks, information indicating all mobile stations to which either frequency blocks or sub-blocks are allocated, and information indicating the correspondence between the mobile stations and the identification codes.

For example, when the number of distributed resource blocks is between 1 and 16, four bits are necessary to express the value.

Fields for the IDs of mobile stations are provided for the maximum number of allocatable users to which resource blocks can be allocated at the same time.

For example, when the maximum number of allocatable users is 4 and each mobile station ID is represented by 12 bits, "abcdefghijkl" (ID of a mobile station to which a user number #0 is assigned) is stored in #0 and similarly, IDs of other mobile stations are stored in #1 through #3. In this case, the total number of bits for mobile station IDs is $4 \times 12 = 48$.

The mobile station numbers used to indicate the correspondence between mobile stations and allocated resource blocks are represented by the user numbers #0 through #3 instead of mobile station IDs.

The resource block numbers are serial numbers assigned to the distributed resource blocks and the localized resource blocks and do not indicate physical locations of resource blocks. When the number of resource blocks is 16 and the maximum number of allocatable users is 4 (2 bits), the required number of bits is $16 \times 2 = 32$. For example, the mobile station #1 is specified for the resource block number #0, the mobile station #3 for the resource block number #1, the mobile station #0 for the resource block number #2, the mobile station #2 for the resource block number #3, and the mobile station #2 for the resource block number #4.

As an alternative method, allocation information may be encoded and sent for each mobile station.

In this case, as shown in FIG. 9, the control

information generating unit 106 reports the number of distributed resource blocks, an ID of a mobile station to which resource blocks are allocated, and resource block numbers of allocated resource blocks. In other words, the control information generating unit 106 generates control information including the number of identification codes identifying resource blocks, information indicating a mobile station to which either frequency blocks or sub-blocks are allocated, and information indicating the correspondence between the mobile station and the identification codes.

For example, when the number of distributed resource blocks is between 1 and 16, four bits are necessary to express the value.

In the mobile station ID field, the ID of the mobile station is stored. The required number of bits for the mobile station ID is, for example, 12 bits.

The resource block numbers are serial numbers assigned to the distributed resource blocks and the localized resource blocks and do not indicate physical locations of resource blocks. For example, allocated resource blocks are flagged with "1" and unallocated resource blocks are flagged with "0". In this case, the required number of bits is, for example, 16 and is the same as the number of resource blocks. For example, 0 is specified for the resource block number #0, 0 for the resource block number #1, 0 for the resource block number #2, 1 for the resource block number #3, and 1 for the resource block number #4.

The coding-rate-and-data-modulation determining unit 108 determines a coding rate and a data modulation level used to transmit control information.

The mapping unit 110 modulates and encodes

control information using the data modulation level and the coding rate determined by the coding-rate-and-data-modulation determining unit 108 and maps the control information to physical channels. As a result, the
5 control information is transmitted.

The transmission data generating unit 112 generates transmission data according to the numbers of resource blocks allocated to the respective mobile stations. For example, the transmission data generating
10 unit 112 determines the amount of transmission data.

The coding-rate-and-data-modulation determining unit 114 determines coding rates and data modulation levels used to transmit the data for the respective mobile stations to which resource blocks are
15 allocated by the frequency scheduling unit 104.

The mapping unit 116 modulates and encodes the data and maps the data to physical channels.

Next, an exemplary process in the frequency scheduling unit 104 of allocating resource blocks to
20 transmission data is described with reference to FIG. 10.

The frequency scheduling unit 104 allocates resource blocks preferentially to data to be sent by localized transmission.

As shown in FIG. 10, the frequency scheduling
25 unit 104 includes a localized allocation unit 1042 and a distributed allocation unit 1044 that receives an output signal from the localized allocation unit 1042.

The localized allocation unit 1042 receives propagation path information of the respective mobile
30 stations, priority information, and resource block allocation ratio information indicating the allocation ratio of localized resource blocks to distributed resource blocks, and allocates resource blocks

preferentially to data to be sent by localized transmission based on the propagation path information and the priority information.

As shown in FIG. 11, the localized allocation unit 1042 first allocates resource blocks to mobile stations to which localized transmission is applied taking into account the reception conditions of the mobile stations in the respective resource blocks. In this step, the localized allocation unit 1042 leaves resource blocks to be allocated to mobile stations to which distributed transmission is applied based on the resource block allocation ratio information. For example, the localized allocation unit 1042 allocates resource blocks to the mobile stations based on the priority information.

The distributed allocation unit 1044 allocates resource blocks, other than those allocated to data to be sent by localized transmission, to data to be sent by distributed transmission.

As shown in FIG. 11, after resource blocks are allocated to mobile stations to which localized transmission is applied, the distributed allocation unit 1044 allocates remaining resource blocks to mobile stations to which distributed transmission is applied. For example, the distributed allocation unit 1044 allocates resource blocks to the mobile stations based on the priority information.

Alternatively, the frequency scheduling unit 104 may be configured to allocate resource blocks preferentially to data to be sent by distributed transmission.

In the example shown in FIG. 12, the frequency scheduling unit 104 includes a distributed allocation

unit 1044 and a localized allocation unit 1042 that receives an output signal from the distributed allocation unit 1044.

The distributed allocation unit 1044 receives
5 propagation path information of the respective mobile stations, priority information, and resource block allocation ratio information indicating the allocation ratio of localized resource blocks to distributed
10 resource blocks, and allocates resource blocks preferentially to data to be sent by distributed transmission based on the propagation path information and the priority information.

As shown in FIG. 13, the distributed allocation unit 1044 preferentially allocates resource
15 blocks to mobile stations to which distributed transmission is applied taking into account the reception conditions of the mobile stations in the respective resource blocks or in such a manner that the frequency diversity gain is increased. In this step, the
20 distributed allocation unit 1044 leaves resource blocks to be allocated to mobile stations to which localized transmission is applied based on the resource block allocation ratio information. For example, the distributed allocation unit 1044 allocates resource
25 blocks to the mobile stations based on the priority information.

As shown in FIG. 13, after resource blocks are allocated to mobile stations to which distributed
transmission is applied, the localized allocation unit
30 1042 allocates remaining resource blocks to mobile stations to which localized transmission is applied. For example, the localized allocation unit 1042 allocates resource blocks to the mobile stations based on the

priority information.

As another example, the frequency scheduling unit 104 may be configured to allocate resource blocks reserved for localized transmission and distributed
5 transmission, respectively.

In this case, the frequency scheduling unit 104 allocates reserved resource blocks to users to which localized transmission is applied and to users to which distributed transmission is applied, respectively. With
10 this approach, because resource blocks are reserved for localized transmission and distributed transmission, respectively, the order of allocation is not relevant to the allocation results.

In the example shown in FIG. 14, the frequency
15 scheduling unit 104 includes a distributed allocation unit 1044 and a localized allocation unit 1042 that receives an output signal from the distributed allocation unit 1044.

The distributed allocation unit 1044 receives
20 propagation path information of the respective mobile stations, priority information, and resource block allocation ratio information indicating the allocation ratio of localized resource blocks to distributed resource blocks.

As shown in FIG. 15, the distributed
25 allocation unit 1044 allocates resource blocks reserved for distributed transmission to mobile stations to which distributed transmission is applied. For example, the distributed allocation unit 1044 allocates the reserved
30 resource blocks to the mobile stations based on the priority information.

As shown in FIG. 15, the localized allocation unit 1042 allocates resource blocks reserved for

localized transmission to mobile stations to which localized transmission is applied. For example, the localized allocation unit 1042 allocates the reserved resource blocks to the mobile stations based on the
5 priority information.

Next, an exemplary process of allocating radio resources by the transmission device 100 is described with reference to FIG. 16.

The frequency scheduling unit 104 determines
10 whether it is time to change the allocation ratio of localized resource blocks to distributed resource blocks (step S1602).

If it is time to change the allocation ratio of localized resource blocks to distributed resource
15 blocks (YES in step S1602), the resource block allocation ratio changing unit 102 changes the resource block allocation ratio (step S1604).

After the resource block allocation ratio is changed in step S1604 or if it is not time to change the
20 resource block allocation ratio (NO in step S1602), the process goes to step S1606. In step S1606, the frequency scheduling unit 104 allocates resource blocks as described above to mobile stations to which localized or distributed transmission is applied (step S1606).

25 Then, the control information generating unit 106 generates control information for reporting resource block allocation information to the mobile stations (step S1608).

Next, the transmission data generating unit
30 112 determines the amounts of data to be transmitted to the respective mobile stations based on the scheduling result of the frequency scheduling unit 104, and generates transmission signal sequences (step S1610).

The coding-rate-and-data-modulation determining units 108 and 114 determine coding rates and data modulation levels, respectively, for the data and the control information (step S1612).

5 Then, the mapping units 110 and 116 map the control information and the data, respectively, to physical channels (step S1614).

A transmission device according to another embodiment of the present invention is described below.

10 The configuration of a transmission device 100 of this embodiment is substantially the same as that shown in FIG. 2, and therefore descriptions of the configuration are omitted here. The transmission device 100 of this embodiment is different from the
15 transmission device of the above embodiment in the operations of the control information generating unit 106.

The control information generating unit 106 generates control information for the mobile stations to
20 which resource blocks are allocated by the frequency scheduling unit 104.

The control information generating unit 106 assigns identification codes, for example, numbers, indicating physical locations of resource blocks to the
25 numbers of localized resource blocks. For example, when there are 16 resource blocks in a frequency band and all the resource blocks are used as localized resource blocks as shown in FIG. 5, the numbers assigned to the localized resource blocks and the numbers indicating
30 physical locations of the resource blocks become identical.

When distributed transmission is performed, the control information generating unit 106 converts a

subset of the resource blocks into distributed resource blocks. For example, the control information generating unit 106 converts four resource blocks into distributed resource blocks.

5 In this embodiment, localized resource blocks that are to be converted into distributed resource blocks are selected according to a predetermined rule depending on the number of distributed resource blocks.

 For example, the control information
10 generating unit 106 allocates frequency blocks and distributed frequency blocks as described below. In this example, one distributed resource block (distributed frequency block) is divided into N_D resource blocks. Sets of the N_D resource blocks are positioned apart from
15 each other by a distance C expressed by formula (1) below.

[Formula 1]

$$C = \lfloor N_{PRB} / N_D \rfloor \quad (1)$$

20

 In formula (1), N_{PRB} represents the number of physical locations of resource blocks. Digits after the decimal point of N_{PRB}/N_D are truncated.

 When the number of distributed resource blocks
25 is N_{DVRB} and $N_{DVRB} = N_{D-PRB} \times N_D$ (N_{D-PRB} is an integer that satisfies $0 \leq N_{D-PRB} \leq C$), N_{D-PRB} "paired physical resource blocks" are allocated for distributed transmission. Location k of each physical resource block is expressed by formula (2) below.

30

[Formula 2]

$$k = i \times C + j \times \left\lfloor C / N_{D-PRB} \right\rfloor \quad (2)$$

In formula (2), i represents values 0 through N_D-1 , and j represents values 0 through $N_{D-PRB}-1$.

FIG. 17A shows an example where N_{PRB} is 12, N_D is 2, and N_{DVRB} is 2. FIG. 17B shows an example where N_{PRB} is 12, N_D is 2, and N_{DVRB} is 4. In FIGs. 17A and 17B, numbers written in localized RBs and beside distributed RBs represent the numbers assigned to localized resource blocks and distributed resource blocks, respectively, and numbers written above the RBs represent physical locations of the resource blocks.

This approach enables the transmission device 100 to report allocation information by just sending the number of distributed resource blocks to receiving devices. For example, a mobile station to which localized transmission is to be applied can identify resource blocks allocated to itself based only on the locations of the resource blocks. Meanwhile, a mobile station to which distributed transmission is to be applied can identify resource blocks allocated to itself based on the number of distributed resource blocks and information indicating the locations of the resource blocks.

Also, this approach makes it possible to uniquely determine resource blocks to be used as distributed resource blocks based on the number of the distributed resource blocks. In other words, this approach makes it possible to uniquely identify physical locations of distributed resource blocks and localized resource blocks based on their assigned numbers and the number of the distributed resource blocks. This in turn

makes it possible to report allocation information with a small number of bits.

Exemplary resource block allocation for a mobile station 0 (UE0), a mobile station 1 (UE1), a
5 mobile station 2 (UE2), a mobile station 3 (UE3), and a mobile station 4 (UE4) is described below with reference to FIGs. 18A and 18B. In FIGs. 18A and 18B, numbers written in localized RBs and beside distributed RBs represent the numbers assigned to localized resource
10 blocks and distributed resource blocks, respectively.

Here, it is assumed that the mobile stations 0, 1, and 2 are low mobility users and the mobile stations 3 and 4 are high mobility users. In this case, the frequency scheduling unit 104 allocates localized
15 resource blocks to the mobile stations 0, 1, and 2, and allocates distributed resource blocks to the mobile stations 3 and 4.

For example, as shown in FIG. 18B, the frequency scheduling unit 104 allocates resource blocks
20 #1, #2, and #5 to the mobile station 0, resource block #3 to the mobile station 1, resource blocks #6, #7, #9, #10, #11, #13, #14, and #15 to the mobile station 2, resource blocks #0, #4, and #8 to the mobile station 3, and resource block #12 to the mobile station 4.

25 An exemplary method of reporting allocation information is described below.

As shown in FIG. 19, when encoding and sending allocation information for multiple mobile stations collectively, the control information generating unit
30 106 reports UE-IDs associated with UE indexes (Replacement of UE-ID by UE index), transmission methods for the respective UEs (Transmission method for each UE), and the UE indexes associated with resource blocks

(Assignment UE index of each RB).

The UE-IDs are identification information of all mobile stations and associated with UE indexes. UE-ID fields are provided for the maximum number of users to which resource blocks can be allocated at the same time. The UE-ID fields store the IDs of UEs to which resource blocks are allocated. For example, when the maximum number of allocatable users is 4 and each UE-ID is represented by 12 bits, #0:abcdefghijkl (UE-ID of a mobile station to which a user number #0 is assigned) is stored in #0 and similarly, UE-IDs of other mobile stations are stored in #1 through #3. In this case, the total number of bits for UE-IDs is $4 \times 12 = 48$.

The user numbers #0 through #3 are used instead of UE-IDs to indicate the correspondence between UEs and allocated resource blocks.

In transmission method fields, information indicating distributed transmission or localized transmission is stored for the respective users to which resource blocks are allocated by the frequency scheduling unit 104. The transmission method fields are provided for the maximum number of users to which resource blocks can be allocated at the same time. For example, "1" indicates distributed transmission and "0" indicates localized transmission. In other words, in the transmission method fields, information indicating whether frequency blocks or sub-blocks are allocated is stored in association with the identification information identifying all the mobile stations.

In UE index fields, user numbers indicating mobile stations are stored in association with the resource block numbers (that are different from those indicating physical locations of resource blocks)

assigned to distributed resource blocks and localized resource blocks. In other words, the UE index fields store identification information of mobile stations in association with identification codes indicating
5 locations of frequency blocks and sub-blocks.

For example, when the number of resource blocks is 16 and the maximum number of allocatable users is 4 (2 bits), the required number of bits is $16 \times 2 = 32$.

As an alternative method, allocation
10 information may be encoded and sent for each mobile station.

In this case, as shown in FIG. 20, the control information generating unit 106 reports a UE-ID associated with a UE index (Assignment UE-ID), a
15 transmission method for the UE (Transmission method for each UE), and resource block allocation information (Assignment information of each RB).

The UE-ID is identification information of a mobile station and associated with a UE index. The UE-ID
20 field stores the ID of a UE to which resource blocks are allocated. For example, the UE-ID may be represented by 12 bits.

In the transmission method field, information indicating distributed transmission or localized
25 transmission is stored for the user to which resource blocks are allocated by the frequency scheduling unit 104. For example, "1" indicates distributed transmission and "0" indicates localized transmission. In other words, in the transmission method field, information indicating
30 whether frequency blocks or sub-blocks are allocated is stored in association with the identification information of the mobile station.

In the resource block allocation information

fields, information indicating whether resource blocks are allocated for the user is stored in association with the corresponding resource block numbers (that are different from those indicating physical locations of resource blocks) assigned to the distributed resource blocks and the localized resource blocks. For example, "1" indicates that the resource block is allocated for the user and "0" indicates that the resource block is not allocated for the user. In other words, the identification information of the mobile station is associated with identification codes indicating locations of frequency blocks and sub-blocks.

Next, a transmission device according to another embodiment of the present invention is described. The configuration of a transmission device 100 of this embodiment is substantially the same as that shown in FIG. 2, and therefore descriptions of the configuration are omitted here. The transmission device 100 of this embodiment is different from the transmission device of the above embodiments in the operations of the control information generating unit 106.

The control information generating unit 106 generates control information for the mobile stations to which resource blocks are allocated by the frequency scheduling unit 104.

In this embodiment, locations of distributed resource blocks and the dividing pattern are predetermined. More specifically, which resource blocks are to be converted into distributed resource blocks and which distributed resource blocks are to be divided into how many sub-blocks are determined by a preset rule depending on the number of the distributed resource

blocks.

FIGs. 21A and 21B show examples where the numbers of distributed resource blocks are two and three, respectively. In the examples shown in FIGs. 21A and 21B, the number of distributed resource blocks is made identical with the division number into which each distributed resource block is divided. In FIGs. 21A and 21B, numbers written in localized RBs and beside distributed RBs represent the numbers assigned to localized resource blocks and distributed resource blocks, respectively, and numbers written above the RBs represent physical locations of the resource blocks.

If the number of distributed resource blocks is made identical with the division number of each distributed resource block, the number of distributed resource blocks becomes equal to the number of allocatable distributed resource blocks. As a result, regardless of the number of distributed resource blocks, all of the distributed resource blocks can be allocated. Compared with the above embodiments, this approach makes it possible to improve radio resource allocation efficiency.

Alternatively, the number of distributed resource blocks may be made different from the division number of each distributed resource block.

FIG. 22A shows an example where the number of distributed resource blocks is 5 and the division number of each distributed resource block is 2 or 3. FIG. 22B shows an example where the number of distributed resource blocks is 5 and the division number of each distributed resource block is 5. In FIGs. 22A and 22B, numbers written in localized RBs and beside distributed RBs represent the numbers assigned to localized resource

blocks and distributed resource blocks, respectively, and numbers written above the RBs represent physical locations of the resource blocks.

Dividing distributed resource blocks by multiple dividing patterns makes it possible to make the number of distributed resource blocks identical with the number of allocatable distributed resource blocks.

Next, an exemplary method of assigning identification codes or serial numbers to localized and distributed resource blocks is described with reference to FIGs. 21A through 22B.

Serial numbers are assigned separately to localized resource blocks and distributed resource blocks. To the localized resource blocks, serial numbers are assigned such that the numbers indicating the physical locations of the resource blocks become identical with the serial numbers. To the distributed resource blocks, serial numbers are assigned separately from those of the localized resource blocks according to the dividing pattern of the distributed resource blocks.

By assigning serial numbers separately to distributed resource blocks and localized resource blocks and by allocating resource blocks such that the serial numbers of the allocated resource blocks become consecutive, it is possible to reduce the number of control bits used to report allocation information. An example of this method is described later.

This method of assigning serial numbers to resource blocks may also be applied to a case as shown in FIG. 6 where serial numbers are first assigned to localized resource blocks and then assigned to distributed resource blocks. Also, this method may be applied to a case where serial numbers are first

assigned to distributed resource blocks and then assigned to localized resource blocks.

Further, this method may be applied regardless of whether the division number of each distributed
5 resource block is predetermined or not predetermined.

Next, an exemplary method of assigning identification codes or serial numbers to localized resource blocks and distributed resource blocks is described with reference to FIGs. 23A through 24B. In
10 FIGs. 23A through 24B, numbers written in localized RBs and beside distributed RBs represent the numbers assigned to localized resource blocks and distributed resource blocks, respectively, and numbers written above the RBs represent physical locations of the resource
15 blocks.

In this method, serial numbers to be assigned to localized resource blocks are predetermined as shown in FIG. 23A. Similarly, serial numbers to be assigned to distributed resource blocks are predetermined as shown
20 in FIG. 23B. FIG. 23B shows an example where the division number of each resource block is 2.

In this case, the physical locations of resource blocks to be used as distributed resource blocks are determined based on the number of the
25 distributed resource blocks. For example, when the number of distributed resource blocks is 2, resource blocks with physical location numbers 0 and 8 are used as the distributed resource blocks, and identification codes 0 and 1 are assigned to the respective distributed
30 resource blocks.

Alternatively, as shown in FIGs. 24A and 24B, the dividing pattern of distributed resource blocks and assignment of serial numbers to the distributed resource

blocks may be changed depending on whether the number of the distributed resource blocks is an even number or an odd number. FIG. 24A shows an example where the number of distributed resource blocks is an even number and the
5 division number of each distributed resource block is 2. FIG. 24B shows an example where the number of distributed resource blocks is an odd number and the division number of each distributed resource block is 1, 2, or 3.

10 The dividing patterns of distributed resource blocks and assignment of serial numbers to the distributed resource blocks shown in FIGs. 24A and 24B are just examples and may be changed as necessary.

 Thus, in the above method, the dividing
15 pattern of distributed resource blocks and assignment of serial numbers to the distributed resource blocks are changed depending on whether the number of the distributed resource blocks is an even number or an odd number. This method makes it possible for a mobile
20 station to determine the dividing pattern of the distributed resource blocks based only on whether the number of the distributed resource blocks is an even number or an odd number.

 For example, when the number of distributed
25 resource blocks is 4 as shown in FIG. 25A, resource blocks with physical location numbers 0, 4, 8, and 12 are used as the distributed resource blocks and numbers 0 through 3 are assigned to the distributed resource blocks according to the serial number assignment scheme
30 shown in FIG. 24A, and other resource blocks are used as localized resource blocks.

 As another example, when the number of distributed resource blocks is 5 as shown in FIG. 25B,

resource blocks with physical location numbers 0, 4, 7, 12, and 15 are used as the distributed resource blocks and numbers 0 through 4 are assigned to the distributed resource blocks according to the serial number
5 assignment scheme shown in FIG. 24B, and other resource blocks are used as localized resource blocks.

Next, an exemplary method of reporting allocation information to mobile stations is described.

Allocating distributed resource blocks with
10 consecutive serial numbers, instead of those with separate serial numbers, to a mobile station makes it possible to reduce the number of control bits used to encode and send allocation information to the mobile station. This approach may also be applied to a case
15 where allocation information for multiple mobile stations is encoded and sent collectively.

Characteristics of all distributed resource blocks are essentially the same. The above method makes it possible to assign resource block numbers to
20 distributed resource blocks such that those numbers do not depend on the characteristics of the distributed resource blocks.

An exemplary method of encoding and sending allocation information for each UE is described below.

25 FIG. 26 shows an example where the division number of each distributed resource block is not predetermined. In this case, allocation information including the division number of each distributed resource block is sent to the mobile station.

30 The base station sends allocation information that includes the ID (Assigned UE-ID) of a mobile station to which resource blocks are allocated, information indicating whether localized transmission or

distributed transmission is applied (Localized or Distributed), the number of distributed resource blocks (Number of Distributed RBs) if distributed transmission is to be applied, and resource block allocation information (Assigned information for each RB). The base station sends control bits representing the allocation information separately to each of the mobile stations to which distributed resource blocks are allocated.

The UE-ID is, for example, represented by 12 bits. In the field for the information indicating whether localized transmission or distributed transmission is applied, "0" is specified for localized transmission and "1" is specified for distributed transmission. Based on the number of distributed resource blocks, the mobile station can determine which localized resource blocks are converted into distributed resource blocks and the division number of each distributed resource block. The "Assigned information for each RB" field stores information indicating distributed resource blocks and information indicating locations of allocated distributed resource blocks.

Using tree based allocation information (see, for example, 3GPP, R1-061308, NEC, "Resource Allocation Signaling for E-UTRA", May 2006) described below makes it possible to reduce the amount of resource block allocation information that indicates allocated distributed resource blocks by a range of consecutive serial numbers assigned to the distributed resource blocks. For example, when the number of resource blocks is 16, the required number of bits is $\log_2(16 \times 17/2) = 7$.

Another exemplary method of encoding and sending allocation information for each UE is described below.

FIG. 27 shows an example where the division number of each distributed resource block is not predetermined. In this case, allocation information including the division number of each distributed resource block is sent to the mobile station.

The base station sends allocation information that includes the ID (Assigned UE-ID) of a mobile station to which resource blocks are allocated, information indicating whether localized transmission or distributed transmission is applied (Localized or Distributed), a division type of distributed resource blocks (Distributed RB division type) if distributed transmission is to be applied, i.e., information indicating whether the number of distributed resource blocks is an odd number or an even number, and resource block allocation information (Assigned information for each RB). The base station sends control bits representing the allocation information separately to each of the mobile stations to which distributed resource blocks are allocated.

The UE-ID is, for example, represented by 12 bits. In the field for the information indicating whether localized transmission or distributed transmission is applied, for example, "0" is specified for localized transmission and "1" is specified for distributed transmission. In the "Distributed RB division type" field, for example, "0" is specified when the number of distributed resource blocks is an even number and "1" is specified when the number of distributed resource blocks is an odd number. With the division type, the mobile station can determine the dividing pattern of distributed resource blocks and serial numbers of the distributed resource blocks.

The "Assigned information for each RB" field stores information indicating distributed resource blocks and information indicating locations of allocated distributed resource blocks.

5 As described above, using the tree based allocation information described below makes it possible to reduce the amount of resource block allocation information that indicates allocated distributed resource blocks by a range of consecutive serial numbers
10 assigned to the distributed resource blocks. For example, when the number of resource blocks is 16, the required number of bits is $\log_2(16 \times 17 / 2) = 7$.

 Another exemplary method of encoding and sending allocation information for each UE is described
15 below.

FIG. 28 shows an example where the division number of each distributed resource block is predetermined.

 In this case, the same predetermined division
20 number may be applied to all distributed resource blocks as shown in FIG. 24A or two or more division numbers may be applied to the distributed resource blocks as shown in FIG. 24B.

 The base station sends allocation information
25 that includes the ID (Assigned UE-ID) of a mobile station to which resource blocks are allocated, information indicating whether localized transmission or distributed transmission is applied (Localized or Distributed), and resource block allocation information
30 (Assigned information for each RB). The base station sends control bits representing the allocation information separately to each of the mobile stations to which distributed resource blocks are allocated.

The UE-ID is, for example, represented by 12 bits. In the field for the information indicating whether localized transmission or distributed transmission is applied, for example, "0" is specified
5 for localized transmission and "1" is specified for distributed transmission. In this example, the division number of each distributed resource block is predetermined, and the resource block allocation information is represented by tree based allocation
10 information obtained based on the serial numbers assigned to distributed resource blocks as described with reference to FIG. 23B. The mobile station can determine the locations of allocated resource blocks based only on the tree based allocation information.

15 For example, as shown in FIG. 29, when the number of resource blocks is 6 and distributed resource blocks with consecutive serial numbers 2, 3, and 4 are allocated to a mobile station, the mobile station can determine the locations of the allocated distributed
20 resource blocks based only on the serial numbers 2, 3, and 4.

Next, an exemplary method of reporting allocation information using the tree based allocation information is described.

25 In the example shown in FIG. 30, it is assumed that the number of resource blocks is 6 and distributed resource blocks with consecutive serial numbers 0, 1, and 2 are allocated to a mobile station.

In a method using the tree based allocation
30 information, a tree chart as shown in FIG. 31 is used. The base station reports the number (in this example, "12") at an intersection of lines, one extending from each of the first and last serial numbers of allocated

resource blocks.

The number of figures necessary to form a tree chart depends on the number of resource blocks (in this example, the number of distributed resource blocks).
5 Specifically, the number of figures necessary to form a tree chart for N resource blocks can be represented by a formula $N \times (N+1) / 2$.

Therefore, the number of bits necessary to express resource block allocation information using the
10 tree based allocation information is $\log_2(N \times (N+1) / 2)$.

Thus, using the tree based allocation information makes it possible to reduce the amount of resource block allocation information that indicates allocated distributed resource blocks by a range of
15 consecutive serial numbers assigned to the distributed resource blocks.

The present international application claims priority from Japanese Patent Application No. 2006-031742 filed on February 8, 2006, Japanese Patent Application No.
20 2006-077820 filed on March 20, 2006, and Japanese Patent Application No. 2006-169449 filed on June 19, 2006, the entire contents of which are hereby incorporated herein by reference.

25 INDUSTRIAL APPLICABILITY

A transmission device and a transmission method according to embodiments of the present invention may be applied to a wireless communication system.

CLAIMS

1. A transmission device, comprising:
 - a frequency scheduling unit configured to
5 allocate, to each user, either frequency blocks that are consecutive frequency subcarrier blocks obtained by dividing a system bandwidth or distributed frequency blocks that are frequency subcarrier blocks discretely distributed in the system bandwidth; and
10 a mapping unit configured to assign transmission data to the frequency blocks or the distributed frequency blocks according to the allocation result;
wherein the frequency scheduling unit is
15 configured to allocate the distributed frequency blocks using the frequency blocks as units and to allocate sub-blocks obtained by dividing the respective distributed frequency blocks.
- 20 2. The transmission device as claimed in claim 1, wherein the frequency scheduling unit is configured to allocate the sub-blocks obtained by dividing the respective distributed frequency blocks in the time
25 direction.
3. The transmission device as claimed in claim 1, wherein the frequency scheduling unit is configured to allocate the sub-blocks obtained by dividing the respective distributed frequency blocks in the frequency
30 direction.
4. The transmission device as claimed in claim 1, further comprising:

an allocation ratio determining unit configured to determine an allocation ratio of the frequency blocks to the distributed frequency blocks based on conditions of mobile stations;

5 wherein the frequency scheduling unit is configured to change the current allocation ratio of the frequency blocks to the distributed frequency blocks at predetermined intervals based on the determined allocation ratio.

10

5. The transmission device as claimed in claim 1, further comprising:

15 a control information generating unit configured to generate identification codes indicating locations of the frequency blocks and the sub-blocks according to the number of the sub-blocks and to generate control information indicating either the frequency blocks or the sub-blocks that are to be allocated to a mobile station based on the
20 identification codes; and

 a reporting unit configured to report the control information.

25 6. The transmission device as claimed in claim 5, wherein the control information generating unit is configured to generate the control information including the number of the identification codes, information identifying all mobile stations to which either the frequency blocks or the sub-blocks are to be allocated,
30 and information indicating the correspondence between the identification codes and the mobile stations.

7. The transmission device as claimed in claim

5, wherein the control information generating unit is configured to generate the control information including the number of the identification codes, information identifying a mobile station to which either the
5 frequency blocks or the sub-blocks are to be allocated, and information indicating the correspondence between the identification codes and the mobile station.

8. The transmission device as claimed in claim
10 5, wherein

the frequency blocks and the distributed frequency blocks are assigned codes indicating their corresponding locations;

the distributed frequency blocks are
15 positioned apart from each other by a number of frequency blocks determined based on a division number; and

the control information generating unit is configured to assign information indicating the corresponding locations as identification information to
20 the frequency blocks and to assign information indicating the corresponding locations to the distributed frequency blocks based on the codes indicating the locations and the division number.

25

9. The transmission device as claimed in claim 8, wherein the control information generating unit is configured to generate the control information including identification information of all mobile stations,
30 information associated with the identification information of the respective mobile stations and indicating whether the frequency blocks or the sub-blocks are to be allocated, and information indicating

the correspondence between the identification codes indicating the locations of the frequency blocks and the sub-blocks and the identification information of the respective mobile stations.

5

10. The transmission device as claimed in claim 8, wherein the control information generating unit is configured to generate the control information including identification information of a mobile station,
10 information associated with the identification information of the mobile station and indicating whether the frequency blocks or the sub-blocks are to be allocated, and information indicating the correspondence between the identification codes indicating the
15 locations of the frequency blocks and the sub-blocks and the identification information of the mobile station.

11. A transmission method where either frequency blocks that are consecutive frequency
20 subcarrier blocks obtained by dividing a system bandwidth or distributed frequency blocks that are frequency subcarrier blocks discretely distributed in the system bandwidth are allocated to a user, the method comprising:

25 a sub-block allocating step of allocating sub-blocks obtained by dividing the respective distributed frequency blocks that are allocated using the frequency blocks as units; and

a mapping step of assigning transmission data
30 to the frequency blocks or the distributed frequency blocks that are allocated.

12. The transmission method as claimed in

claim 11, wherein the sub-blocks allocated in the sub-block allocating step are obtained by dividing the respective distributed frequency blocks in the time direction.

5

13. The transmission method as claimed in claim 11, wherein the sub-blocks allocated in the sub-block allocating step are obtained by dividing the respective distributed frequency blocks in the frequency
10 direction.

14. The transmission method as claimed in claim 11, further comprising:

an allocation ratio determining step of
15 determining an allocation ratio of the frequency blocks to the distributed frequency blocks based on conditions of mobile stations;

wherein in the sub-block allocating step, the current allocation ratio of the frequency blocks to the distributed frequency blocks is changed at predetermined
20 intervals based on the determined allocation ratio.

15. The transmission method as claimed in claim 11, further comprising:

25 an identification code generating step of generating identification codes indicating locations of the frequency blocks and the sub-blocks according to the number of the sub-blocks;

a control information generating step of
30 generating control information indicating either the frequency blocks or the sub-blocks that are to be allocated to a mobile station based on the identification codes; and

a reporting step of reporting the control information.

16. The transmission method as claimed in
5 claim 15, wherein

the frequency blocks and the distributed frequency blocks are assigned codes indicating their corresponding locations;

the distributed frequency blocks are
10 positioned apart from each other by a number of frequency blocks determined based on a division number; and

in the control information generating step, information indicating the corresponding locations is
15 assigned to the frequency blocks as identification information and information indicating the corresponding locations is assigned to the distributed frequency blocks based on the codes indicating the locations and the division number.

20

17. The transmission device as claimed in claim 5, wherein

the frequency blocks and the distributed frequency blocks are assigned codes indicating their
25 corresponding locations;

the identification codes of the sub-blocks are predetermined based on the number of the distributed frequency blocks; and

the control information generating unit is
30 configured to generate the control information including identification information of a mobile station, information associated with the identification information of the mobile station and indicating whether

the frequency blocks or the sub-blocks are to be allocated, the number of the distributed frequency blocks, and the identification codes of the sub-blocks to be allocated to the mobile station.

5

18. The transmission device as claimed in claim 17, wherein

the identification codes of the sub-blocks are predetermined differently according to whether the
10 number of the distributed frequency blocks is an odd number or an even number; and

the control information generating unit is configured to generate the control information including the identification information of the mobile station,
15 the information associated with the identification information of the mobile station and indicating whether the frequency blocks or the sub-blocks are to be allocated, information indicating whether the number of the distributed frequency blocks is an odd number or an
20 even number, and the identification codes of the sub-blocks to be allocated to the mobile station.

19. The transmission device as claimed in claim 5, wherein

25 the frequency blocks and the distributed frequency blocks are assigned codes indicating their corresponding locations;

the identification codes of the sub-blocks are predetermined based on the number of the distributed
30 frequency blocks; and

when the number of the distributed frequency blocks is predetermined, the control information generating unit is configured to generate the control

information including identification information of a mobile station, information associated with the identification information of the mobile station and indicating whether the frequency blocks or the sub-
5 blocks are to be allocated, and the identification codes of the sub-blocks to be allocated to the mobile station.

20. The transmission device as claimed in claim 17, wherein when the sub-blocks with consecutive
10 identification codes are allocated to the mobile station, the control information generating unit is configured to generate a value based on tree based resource allocation.