

FREQUENCY HOPPING CONFIGURATION METHOD AND DEVICE

TECHNICAL FIELD

[0001] The present disclosure relates to the field of communication technologies, and in particular, to a frequency hopping configuration method and device.

BACKGROUND

[0002] Frequency hopping is a technology often used in communication systems. By transmitting on different frequency domain resources, the gain of channel frequency diversity can be obtained. In the related art, User Equipment (UE) in the same cell may use the same system bandwidth and cell configuration information, and select the same frequency hopping method. However, in the new generation of communication system, different user equipment may be configured with different Band Width Part (BWP) by the system. If the uplink frequency hopping design in the related art is used, the complexity of scheduling of the base station may increase, the fragmentation of system resource usage may also increase, and the utilization efficiency of the system resource is reduced.

SUMMARY

[0003] In order to overcome the problems in the related art, the embodiments of the present disclosure provide a frequency hopping configuration method and device.

[0004] According to a first aspect of the embodiments of the present disclosure, a frequency hopping configuration method is provided. The method is applied in a base station. The base station configures at least one BWP for a terminal. The method includes:

[0005] configuring a frequency hopping configuration for each configured BWP;

[0006] in response to instructing the terminal to perform uplink transmission frequency hopping, determining, according to the configured frequency hopping configuration, a frequency hopping configuration corresponding to a BWP with which the terminal being configured currently; and

[0007] sending the corresponding frequency hopping configuration to the terminal, so that the terminal determines, according to the corresponding frequency hopping configuration

and a first frequency domain resource position before the frequency hopping, a second frequency domain resource position after the frequency hopping, and performs uplink transmission at the second frequency domain resource position.

[0008] Alternatively, the configuring a frequency hopping configuration for each configured BWP includes:

[0009] configuring one or more different frequency hopping subband schemes for each configured BWP, each frequency hopping subband scheme comprising at least one frequency hopping subband, and the frequency hopping subbands in the same BWP are a section of continuous frequency resources in the BWP.

[0010] Alternatively, the determining, according to the configured frequency hopping configuration, a frequency hopping configuration corresponding to a BWP with which the terminal being configured currently, includes:

[0011] in response to one frequency hopping subband scheme is configured for the BWP with which the terminal being configured currently, determining the frequency hopping subband scheme as the frequency hopping configuration corresponding to the BWP with which the terminal being configured currently;

[0012] in response to a plurality of frequency hopping subband schemes are configured for the BWP with which the terminal being configured currently, selecting one frequency hopping subband scheme from the plurality of frequency hopping subband schemes, and determining the selected frequency hopping subband scheme as the frequency hopping configuration corresponding to the BWP with which the terminal being configured currently.

[0013] Alternatively, the sending the corresponding frequency hopping configuration to the terminal includes:

[0014] generating first indication information, wherein the first indication information comprises the frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently; and

[0015] sending the first indication information to the terminal, so that the terminal obtains the frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently according to the first indication information.

[0016] Alternatively, the method further includes:

[0017] generating frequency hopping configuration information, wherein the frequency hopping configuration information comprises the one or more different frequency hopping subband schemes configured by the base station for each configured BWP; and

[0018] sending the frequency hopping configuration information to the terminal, so that the terminal obtains, according to the frequency hopping configuration information, the one or more different frequency hopping subband schemes configured by the base station for each configured BWP.

[0019] Alternatively, the sending the corresponding frequency hopping configuration to the terminal includes:

[0020] generating second indication information, wherein the second indication information comprises a frequency hopping subband scheme identifier, and the frequency hopping subband scheme identifier is an identifier of the frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently; and

[0021] sending the second indication information to the terminal, so that the terminal obtains the frequency hopping subband scheme identifier according to the second indication information, and determines, according to the frequency hopping subband scheme identifier, the frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently.

[0022] Alternatively, the configuring a frequency hopping configuration for each configured BWP, includes:

[0023] configuring one or more different specified frequency hopping offsets for each configured BWP.

[0024] Alternatively, the determining, according to the configured frequency hopping configuration, a frequency hopping configuration corresponding to a BWP with which the terminal being configured currently, includes:

[0025] in response to one specified frequency hopping offset is configured for the BWP with which the terminal being configured currently, determining the frequency hopping offset as the frequency hopping configuration corresponding to the BWP with which the terminal being configured currently; and

[0026] in response to a plurality of specified frequency hopping offsets are configured for the BWP with which the terminal being configured currently, selecting one specific frequency hopping offset from the plurality of specified frequency hopping offsets, and determining the selected frequency hopping subband scheme as the frequency hopping configuration corresponding to the BWP with which the terminal being configured currently.

[0027] Alternatively, the sending the corresponding frequency hopping configuration to the terminal includes:

[0028] generating third indication information, wherein the third indication information comprises the specified frequency hopping offset corresponding to the BWP with which the terminal being configured currently; and

[0029] sending the third indication information to the terminal, so that the terminal obtains, according to the third indication information, the specified frequency hopping offset corresponding to the BWP with which the terminal being configured currently.

[0030] According to a second aspect of the embodiments of the present application, a frequency hopping configuration method is provided. The method is applied in a terminal, and the terminal is configured, by a base station, at least one BWP. The method includes:

[0031] receiving a frequency hopping configuration sent by the base station, wherein the frequency hopping configuration is a frequency hopping configuration configured by the base station for a BWP with which the terminal being configured currently;

[0032] in response to performing uplink transmission frequency hopping, determining, according to the frequency hopping configuration and a first frequency domain resource position before the frequency hopping, a second frequency domain resource position after the frequency hopping; and

[0033] performing uplink transmission at the second frequency domain resource position.

[0034] Alternatively, the receiving a frequency hopping configuration sent by the base station includes:

[0035] receiving first indication information sent by the base station, wherein the first indication information comprises a frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently, the frequency hopping subband

scheme comprises at least one frequency hopping subband, and the frequency hopping subbands in the same BWP are a section of continuous frequency resources in the BWP; and

[0036] obtaining the frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently according to the first indication information.

[0037] Alternatively, the method further includes:

[0038] receiving frequency hopping configuration information sent by the base station, wherein the frequency hopping configuration information comprises one or more different frequency hopping subband schemes configured by the base station for each configured BWP, each of the frequency hopping subband schemes comprises at least one frequency hopping subband, and the frequency hopping subbands in the same BWP are a section of continuous frequency resources in the BWP; and

[0039] obtaining, according to the frequency hopping configuration information, the one or more different frequency hopping subband schemes configured by the base station for each configured BWP.

[0040] Alternatively, the receiving a frequency hopping configuration sent by the base station includes:

[0041] receiving second indication information sent by the base station, wherein the second indication information comprises a frequency hopping subband scheme identifier, and the frequency hopping subband scheme identifier is an identifier of the frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently;

[0042] obtaining the frequency hopping subband scheme identifier according to the second indication information; and

[0043] determining, according to the frequency hopping subband scheme identifier, the frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently.

[0044] Alternatively, the determining the second frequency domain resource position after the frequency hopping according to the frequency hopping configuration and the first frequency domain resource position before the frequency hopping, includes:

[0045] determining a first frequency hopping subband corresponding to the first frequency domain resource position according to the frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently; and

[0046] calculating the second frequency domain resource position according to the first frequency hopping subband and the first frequency domain resource position.

[0047] Alternatively, the calculating the second frequency domain resource position according to the first frequency hopping subband and the first frequency domain resource position includes:

[0048] calculating a mirror position of the first frequency domain resource position in the first frequency hopping subband, the mirror position being the second frequency domain resource position; or

[0049] using the first frequency hopping subband as a transmission bandwidth for uplink data transmission, and calculating the second frequency domain resource position according to information in uplink scheduling signaling sent by the base station.

[0050] Alternatively, the receiving a frequency hopping configuration sent by the base station includes:

[0051] receiving third indication information sent by the base station, wherein the third indication information comprises a specified frequency hopping offset corresponding to the BWP with which the terminal being configured currently; and

[0052] obtaining, according to the third indication information, the specified frequency hopping offset corresponding to the BWP with which the terminal being configured currently.

[0053] Alternatively, the determining the second frequency domain resource position after the frequency hopping according to the frequency hopping configuration and the first frequency domain resource position before the frequency hopping includes:

[0054] determining the second frequency domain resource position according to the specified frequency hopping offset corresponding to the BWP with which the terminal being configured currently and the first frequency domain resource position.

[0055] According to a third aspect of the embodiments of the present application, a frequency hopping configuration device is provided. The device is applied in a base station,

and the base station configures at least one BWP for a terminal. The device includes:

[0056] a configuration module configured to configure a frequency hopping configuration for each configured BWP;

[0057] a frequency hopping configuration determining module configured to, in response to instructing the terminal to perform uplink transmission frequency hopping, determine, according to the configured frequency hopping configuration, a frequency hopping configuration corresponding to a BWP with which the terminal being configured currently; and

[0058] a first sending module configured to send the corresponding frequency hopping configuration to the terminal, so that the terminal determines, according to the corresponding frequency hopping configuration and a first frequency domain resource position before the frequency hopping, a second frequency domain resource position after the frequency hopping, and perform uplink transmission at the second frequency domain resource position.

[0059] Alternatively, the configuration module includes:

[0060] a first configuration submodule configured to configure one or more different frequency hopping subband schemes for each configured BWP, each frequency hopping subband scheme comprising at least one frequency hopping subband, and the frequency hopping subbands in the same BWP are a section of continuous frequency resources.

[0061] Alternatively, the frequency hopping configuration determining module includes:

[0062] a first determining submodule configured to, in response to one frequency hopping subband scheme is configured for the BWP with which the terminal being configured currently, determine the frequency hopping subband scheme as the frequency hopping configuration corresponding to the BWP with which the terminal being configured currently; and

[0063] a second determining submodule configured to, in response to a plurality of frequency hopping subband schemes are configured for the BWP with which the terminal being configured currently, select one frequency hopping subband scheme from the plurality of frequency hopping subband schemes, and determine the selected frequency hopping

subband scheme as the frequency hopping configuration corresponding to the BWP the terminal being configured with currently.

[0064] Alternatively, the first sending module includes:

[0065] a first generating submodule configured to generate first indication information, wherein the first indication information comprises the frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently; and

[0066] a first sending submodule configured to send the first indication information to the terminal, so that the terminal obtains the frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently, according to the first indication information.

[0067] Alternatively, the device further includes:

[0068] an information generating module configured to generate frequency hopping configuration information, wherein the frequency hopping configuration information comprises one or more different frequency hopping subband schemes configured by the base station for each configured BWP; and

[0069] a second sending module configured to send the frequency hopping configuration information to the terminal, so that the terminal obtains, according to the frequency hopping configuration information, the one or one different frequency hopping subband schemes configured by the base station for each configured BWP.

[0070] Alternatively, the first sending module includes:

[0071] a second generating submodule configured to generate second indication information, wherein the second indication information comprises a frequency hopping subband scheme identifier, and the frequency hopping subband scheme identifier is an identifier of the frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently; and

[0072] a second sending submodule configured to send the second indication information to the terminal, so that the terminal obtains the frequency hopping subband scheme identifier according to the second indication information, and determine the frequency hopping subband scheme corresponding to the BWP with which the terminal being

configured currently according to the frequency hopping subband scheme identifier.

[0073] Alternatively, the configuration module includes:

[0074] a second configuration submodule configured to configure one or more different specified frequency hopping offsets for each configured BWP.

[0075] Alternatively, the frequency hopping configuration determining module includes:

[0076] a third determining submodule configured to, when one specified frequency hopping offset is configured for the BWP with which the terminal being configured currently, determine this specified frequency hopping offset as the frequency hopping configuration corresponding to the BWP with which the terminal being configured currently; and

[0077] a fourth determining submodule configured to, in response to a plurality of frequency hopping subband schemes are configured for the BWP with which the terminal being configured currently, select one specified frequency hopping offset from the plurality of specified frequency hopping offsets, and determine the selected frequency hopping subband scheme as the frequency hopping configuration corresponding to the BWP with which the terminal being configured currently.

[0078] Alternatively, the first sending module includes:

[0079] a third generating submodule configured to generate third indication information, wherein the third indication information comprises the specified frequency hopping offset corresponding to the BWP with which the terminal being configured currently; and

[0080] a third sending submodule configured to send the third indication information to the terminal, so that the terminal obtains, according to the third indication information, the specified frequency hopping offset corresponding to the BWP with which the terminal being configured currently.

[0081] According to a fourth aspect of the embodiments of the present application, a frequency hopping configuration device is provided. The device is applied in a terminal, and the terminal is configured, by a base station, at least one BWP. The device includes:

[0082] a first receiving module configured to receive a frequency hopping configuration sent by the base station, wherein the frequency hopping configuration is a

frequency hopping configuration configured by the base station for a BWP with which the terminal being configured currently;

[0083] a resource position determining module configured to, in response to performing uplink transmission frequency hopping, determine, according to the frequency hopping configuration and a first frequency domain resource position before the frequency hopping, a second frequency domain resource position after the frequency hopping; and

[0084] an uplink transmission module configured to perform uplink transmission at the second frequency domain resource position.

[0085] Alternatively, the first receiving module includes:

[0086] a first receiving submodule configured to receive first indication information sent by the base station, wherein the first indication information comprises a frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently, the frequency hopping subband scheme comprises at least one frequency hopping subband, and the frequency hopping subbands in the same BWP are a section of continuous frequency resource in the BWP; and

[0087] a first obtaining submodule configured to obtain the frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently according to the first indication information.

[0088] Alternatively, the device further includes:

[0089] a second receiving module configured to receive frequency hopping configuration information sent by the base station, wherein the frequency hopping configuration information comprises one or more different frequency hopping subband schemes configured by the base station for each configured BWP, each of the frequency hopping subband schemes comprises at least one frequency hopping subband, and the frequency hopping subbands in the same BWP are a section of continuous frequency resources in the BWP; and

[0090] an obtaining module configured to obtain one or more different frequency hopping subband schemes configured by the base station for each configured BWP from the frequency hopping configuration information.

[0091] Alternatively, the first receiving module includes:

[0092] a second receiving submodule configured to receive second indication information sent by the base station, wherein the second indication information comprises a frequency hopping subband scheme identifier, and the frequency hopping subband scheme identifier is an identifier of the frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently;

[0093] a second obtaining submodule configured to obtain the frequency hopping subband scheme identifier according to the second indication information; and

[0094] a frequency hopping scheme determining submodule configured to determine, according to the frequency hopping subband scheme identifier, the frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently.

[0095] Alternatively, the resource position determining module includes:

[0096] a frequency hopping subband determining submodule configured to determine a first frequency hopping subband corresponding to the first frequency domain resource position according to the frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently; and

[0097] a first calculation submodule configured to calculate the second frequency domain resource position according to the first frequency hopping subband and the first frequency domain resource position.

[0098] Alternatively, the first calculation submodule includes:

[0099] a second calculation submodule configured to calculate a mirror position of the first frequency domain resource position in the first frequency hopping subband, the mirror position being the second frequency domain resource position; or

[00100] a third calculation submodule configured to use the first frequency hopping subband as a transmission bandwidth for uplink data transmission, and calculate the second frequency domain resource position according to information in uplink scheduling signaling sent by the base station.

[00101] Alternatively, the first receiving module includes:

[00102] a third receiving submodule configured to receive third indication information sent by the base station, wherein the third indication information comprises a specified

frequency hopping offset corresponding to the BWP with which the terminal being configured currently; and

[00103] a third obtaining submodule configured to obtain the specified frequency hopping offset corresponding to the BWP with which the terminal being configured currently according to the third indication information.

[00104] Alternatively, the resource position determining module includes:

[00105] a resource position determining submodule configured to determine the second frequency domain resource position according to the specified frequency hopping offset corresponding to the BWP with which the terminal being configured currently and the first frequency domain resource position.

[00106] According to a fifth aspect of the embodiments of the present disclosure, a non-transitory computer-readable storage medium is provided, a computer program is stored on the storage medium, the computer program is configured to execute the frequency hopping configuration method according to the above first aspect.

[00107] According to a sixth aspect of the embodiments of the present disclosure, a non-transitory computer-readable storage medium is provided, a computer program is stored on the storage medium, and the computer program is configured to execute the frequency hopping configuration method according to the above first aspect.

[00108] According to a seventh aspect of the embodiments of the present disclosure, a frequency hopping configuration device is provided. The device is applied in a base station, and the base station configures at least one BWP for a terminal. the device includes:

[00109] a processor; and

[00110] memory for storing instructions executable by the processor;

[00111] wherein the processor is configured to:

[00112] configure a frequency hopping configuration for each configured BWP;

[00113] in response to instructing the terminal to perform uplink transmission frequency hopping, determine, according to the configured frequency hopping configuration, a frequency hopping configuration corresponding to a BWP with which the terminal being configured currently; and

[00114] send the corresponding frequency hopping configuration to the terminal, so

that the terminal determines, according to the corresponding frequency hopping configuration and a first frequency domain resource position before the frequency hopping, a second frequency domain resource position after the frequency hopping, and performs uplink transmission at the second frequency domain resource position.

[00115] According to an eighth aspect of the embodiments of the present disclosure, a frequency hopping configuration device is provided. The device is applied in a terminal, and a base station configures at least one BWP for the terminal. The device includes:

[00116] a processor; and

[00117] memory for storing instructions executable by the processor;

[00118] wherein the processor is configured to:

[00119] receive a frequency hopping configuration sent by the base station, wherein the frequency hopping configuration is a frequency hopping configuration configured by the base station for a BWP with which the terminal being configured currently;

[00120] in response to performing uplink transmission frequency hopping, determine, according to the frequency hopping configuration and a first frequency domain resource position before the frequency hopping, a second frequency domain resource position after the frequency hopping; and

[00121] perform uplink transmission at the second frequency domain resource position.

[00122] The technical solutions provided by the embodiments of the present disclosure may include the following beneficial effects.

[00123] The base station in the present disclosure can configure the frequency hopping configuration for each configured BWP, determine the frequency hopping configuration corresponding to the BWP with which the terminal being configured currently when instructing the terminal to perform uplink transmission frequency hopping, and send the frequency hopping configuration corresponding to the BWP with which the terminal being configured currently to the terminal, so that the terminal can determine the second frequency domain resource position after frequency hopping according to the frequency hopping configuration indicated by the base station and the first frequency domain resource position before frequency hopping, and perform the uplink transmission at the second frequency

domain resource position, thereby the terminal can complete the uplink transmission frequency hopping under the frequency hopping configuration indicated by the base station, which not only reduces the complexity of uplink scheduling, but also reduces the fragmentation of system resources, thereby improving the utilization efficiency of the system resource.

[00124] The terminal in the present disclosure can receive the frequency hopping configuration sent by the base station. The frequency hopping configuration is the frequency hopping configuration configured by the base station for the BWP with which the terminal being configured currently. When performing uplink transmission frequency hopping, the terminal determines the second frequency domain resource position after the frequency hopping according to the frequency hopping configuration and the first frequency domain resource position before the frequency hopping, and performs uplink transmission at the second frequency domain resource position, thereby achieving the completion of uplink transmission frequency hopping under the frequency hopping configuration indicated by the base station, reducing the complexity of the uplink scheduling, reducing the system resource fragmentation, and improving system resource utilization efficiency.

[00125] It is to be understood that both the foregoing general description and the following detailed description are exemplary and explanatory only and are not restrictive of the present disclosure.

BRIEF DESCRIPTION OF THE DRAWINGS

[00126] The accompanying drawings, which are incorporated in and constitute a part of this specification, illustrate embodiments consistent with the present disclosure and, together with the description, serve to explain the principles of the present disclosure.

[00127] Fig. 1 is a flowchart illustrating a frequency hopping configuration method according to an exemplary embodiment;

[00128] Fig. 2 is a scenario diagram illustrating a frequency hopping configuration method according to an exemplary embodiment;

[00129] Fig. 3 is a flowchart illustrating another frequency hopping configuration method according to an exemplary embodiment;

[00130] Fig. 4 is a schematic diagram of a frequency hopping subband scheme according to an exemplary embodiment;

[00131] Fig. 5 is a schematic diagram of another frequency hopping subband scheme according to an exemplary embodiment;

[00132] Fig. 6 is a schematic diagram of another frequency hopping subband scheme according to an exemplary embodiment;

[00133] Fig. 7 is a flowchart illustrating another frequency hopping configuration method according to an exemplary embodiment;

[00134] Fig. 8 is a flowchart illustrating another frequency hopping configuration method according to an exemplary embodiment;

[00135] Fig. 9 is a flowchart illustrating another frequency hopping configuration method according to an exemplary embodiment;

[00136] Fig. 10 is a flowchart illustrating another frequency hopping configuration method according to an exemplary embodiment;

[00137] Fig. 11 is a flowchart illustrating another frequency hopping configuration method according to an exemplary embodiment;

[00138] Fig. 12 is a flowchart illustrating another frequency hopping configuration method according to an exemplary embodiment;

[00139] Fig. 13 is a flowchart illustrating another frequency hopping configuration method according to an exemplary embodiment;

[00140] Fig. 14 is a flowchart illustrating a frequency hopping configuration method according to an exemplary embodiment;

[00141] Fig. 15 is a flowchart illustrating another frequency hopping configuration method according to an exemplary embodiment;

[00142] Fig. 16 is a flowchart illustrating another frequency hopping configuration method according to an exemplary embodiment;

[00143] Fig. 17 is a flowchart illustrating another frequency hopping configuration method according to an exemplary embodiment;

[00144] Fig. 18 is a flowchart illustrating another frequency hopping configuration method according to an exemplary embodiment;

[00145] Fig. 19 is a flowchart illustrating another frequency hopping configuration method according to an exemplary embodiment;

[00146] Fig. 20 is a flowchart illustrating another frequency hopping configuration method according to an exemplary embodiment;

[00147] Fig. 21 is a flowchart illustrating another frequency hopping configuration method according to an exemplary embodiment;

[00148] Fig. 22 is a block diagram illustrating a frequency hopping configuration device according to an exemplary embodiment;

[00149] Fig. 23 is a block diagram illustrating another frequency hopping configuration device according to an exemplary embodiment;

[00150] Fig. 24 is a block diagram illustrating another frequency hopping configuration device according to an exemplary embodiment;

[00151] Fig. 25 is a block diagram illustrating another frequency hopping configuration device according to an exemplary embodiment;

[00152] Fig. 26 is a block diagram illustrating another frequency hopping configuration device according to an exemplary embodiment;

[00153] Fig. 27 is a block diagram illustrating another frequency hopping configuration device according to an exemplary embodiment;

[00154] Fig. 28 is a block diagram illustrating another frequency hopping configuration device according to an exemplary embodiment;

[00155] Fig. 29 is a block diagram illustrating another frequency hopping configuration device according to an exemplary embodiment;

[00156] Fig. 30 is a block diagram illustrating another frequency hopping configuration device according to an exemplary embodiment;

[00157] Fig. 31 is a block diagram illustrating a frequency hopping configuration device according to an exemplary embodiment;

[00158] Fig. 32 is a block diagram illustrating a frequency hopping configuration device according to an exemplary embodiment;

[00159] Fig. 33 is a block diagram illustrating a frequency hopping configuration device according to an exemplary embodiment;

[00160] Fig. 34 is a block diagram illustrating a frequency hopping configuration device according to an exemplary embodiment;

[00161] Fig. 35 is a block diagram illustrating a frequency hopping configuration device according to an exemplary embodiment;

[00162] Fig. 36 is a block diagram illustrating a frequency hopping configuration device according to an exemplary embodiment;

[00163] Fig. 37 is a block diagram illustrating a frequency hopping configuration device according to an exemplary embodiment;

[00164] Fig. 38 is a block diagram illustrating a frequency hopping configuration device according to an exemplary embodiment;

[00165] Fig. 39 is a schematic structural diagram illustrating a frequency hopping configuration device according to an exemplary embodiment; and

[00166] Fig. 40 is a schematic structural diagram illustrating a frequency hopping configuration device according to an exemplary embodiment.

DETAILED DESCRIPTION

[00167] Reference will now be made in detail to exemplary embodiments, examples of which are illustrated in the accompanying drawings. The following description refers to the accompanying drawings in which the same numbers in different drawings represent the same or similar elements unless otherwise represented. The implementations set forth in the following description of exemplary embodiments do not represent all implementations consistent with the invention. Instead, they are merely examples of apparatuses and methods consistent with aspects related to the invention as recited in the appended claims.

[00168] The terms used in the present disclosure only tend to depict specific embodiments, rather than restricting the present disclosure. Unless the exceptional case in which the context clearly gives supports, the singular forms “a”, “an”, and “the” used in the present disclosure and accompany claims are intended to include the plural forms. It should also be appreciated that the expression "and/or" used herein indicates including any and all possible combinations of one or more of the associated listed items.

[00169] It should be understood, although terms first, second, third and the like are

used in the present disclosure to depict various information, such information is not restricted by these terms. These terms are only used to distinguish information of the same type from each other. For example, without departing from the scope of the present disclosure, the first information may also be referred to as the second information. Similarly, the second information may also be referred to as the first information. Depending on context, the word “if” used herein may be explained to “when” or “upon” or “in response to determining ...”.

[00170] Fig. 1 is a flowchart illustrating a frequency hopping configuration method according to an exemplary embodiment, and Fig. 2 is a scenario diagram of a frequency hopping configuration method according to an exemplary embodiment. The frequency hopping configuration method may be applied in a base station, and the base station configures at least one BWP for the terminal. As shown in Fig. 1, the frequency hopping configuration method may include the following steps 110-130.

[00171] In step 110, a frequency hopping configuration is configured for each configured BWP.

[00172] In the embodiments of the present disclosure, the base station may configure one or more different BWPs for the same terminal according to the actual situation, and the configured BWPs generally do not exceed 4. The base station may also configure a frequency hopping configuration for each configured BWP, and the frequency hopping configurations configured by the base station for different BWPs of the same terminal may be the same or different.

[00173] For example, the base station configures two BWPs for the terminal, namely BWP1 and BWP2, and the frequency hopping configuration configured for BWP1 is one frequency hopping subband scheme, and the frequency hopping configuration configured for BWP2 is two different frequency hopping subband schemes.

[00174] In addition, the base station can also assign different BWPs to different terminals according to capabilities and needs of the terminals. For example: the system bandwidth is 400 MHz, the uplink transmission bandwidth capability of terminal 1 is 100 MHz, and the uplink transmission bandwidth capability of terminal 2 is 200 MHz, then the base station may configure a BWP not greater than 100 MHz for terminal 1 and configure a BWP not greater than 200 MHz for terminal 2.

[00175] In step 120, when instructing the terminal to perform uplink transmission frequency hopping, a frequency hopping configuration corresponding to a BWP with which the terminal being configured currently is determined according to the configured frequency hopping configuration.

[00176] In the embodiments of the present disclosure, the base station may configure a plurality of BWPs for the terminal in advance, but at the same time, the base station can only activate one of the BWPs, that is, the BWP with which the terminal being configured currently. In addition, the base station can also control the terminal to dynamically switch between different BWPs through downlink control signaling.

[00177] In step 130, the frequency hopping configuration corresponding to the BWP with which the terminal being configured currently is sent to the terminal, so that the terminal determines a second frequency domain resource position after frequency hopping according to the frequency hopping configuration and a first frequency domain resource position before frequency hopping, and performs uplink transmission at the second frequency domain resource position.

[00178] In an exemplary scenario, as shown in Fig. 2, a terminal and a base station are included. The base station configures one or more BWPs for the terminal according to the actual situation, and also configures the frequency hopping configuration for each BWP. When the base station instructs the terminal to perform uplink transmission frequency hopping, the frequency hopping configuration corresponding to the BWP with which the terminal being configured currently can be determined according to the frequency hopping configurations that have been configured in advance, and the frequency hopping configuration corresponding to the BWP with which the terminal being configured currently is sent to the terminal, so that the terminal can determine the second frequency domain resource position after frequency hopping according to the frequency hopping configuration indicated by the base station and the first frequency domain resource position before the frequency hopping, and perform uplink transmission at the second frequency domain resource position.

[00179] It can be seen from the foregoing embodiments that by configuring a frequency hopping configuration for each configured BWP, determining the frequency

hopping configuration corresponding to the BWP with which the terminal being configured currently according to the configured frequency hopping configuration when instructing a terminal to perform uplink transmission frequency hopping, and sending the frequency hopping configuration corresponding to the BWP with which the terminal being configured currently to the terminal, the terminal can determine the second frequency domain resource position after frequency hopping according to the frequency hopping configuration indicated by the base station and the first frequency domain resource position before frequency hopping, and perform uplink transmission at the second frequency domain resource position, thereby realizing that the terminal completes uplink transmission frequency hopping under the frequency hopping configuration indicated by the base station, which not only reduces the uplink scheduling complexity, but also reduces the fragmentation of system resources and improves the utilization efficiency of system resource.

[00180] Fig. 3 is a flowchart illustrating another frequency hopping configuration method according to an exemplary embodiment, Fig. 4 is a schematic diagram of a frequency hopping subband solution according to an exemplary embodiment, Fig. 5 is a flowchart according to an exemplary embodiment, and Fig. 6 is a schematic diagram of another frequency hopping subband scheme according to an exemplary embodiment. The frequency hopping configuration method may be used for a base station, and based on the method shown in Fig. 1, the frequency hopping configuration may be a frequency hopping subband scheme. When step 110 is performed, as shown in Fig. 3, it may include the following step 310.

[00181] In step 310, one or more different frequency hopping subband schemes are configured for each configured BWP. Each frequency hopping subband scheme includes at least one frequency hopping subband. The frequency hopping subbands in the same BWP are a section of continuous frequency resources in the BWP.

[00182] In the embodiments of the present disclosure, the base station may configure one or more different frequency hopping subband schemes for each configured BWP in advance, so that when the base station instructs the terminal to perform uplink transmission frequency hopping, the frequency hopping configuration corresponding to the BWP with which the terminal being configured currently can be timely assigned to the terminal.

[00183] In an exemplary schematic diagram, as shown in Fig. 4, it is assumed that there are three terminals in the system: terminal1, terminal2, and terminal3, respectively. The base station configures a frequency hopping subband scheme for terminal1-BWP, terminal2-BWP, and terminal3-BWP. The frequency hopping subband scheme configured for terminal1-BWP includes five non-overlapping frequency hopping subbands, the frequency hopping subband scheme configured for terminal2-BWP includes one frequency hopping subband, and the frequency hopping subband scheme configured for terminal3-BWP includes one frequency hopping subband.

[00184] In an example schematic diagram, the base station configures two types of frequency hopping subband schemes for terminal1-BWP: the first type of the frequency hopping subband scheme includes three non-overlapping frequency hopping subbands, as shown in Fig. 5; and the second type of the frequency hopping subband scheme includes two non-overlapping frequency hopping subbands, as shown in Fig. 6. In addition, the base station configures one type of frequency hopping subband scheme for terminal2-BWP, and the configured frequency hopping subband scheme includes one frequency hopping subband; the base station also configures one type of frequency hopping subband scheme for terminal3-BWP, and the configured frequency hopping subband scheme includes one frequency hopping subband.

[00185] In the first type of frequency-hopping subband scheme of terminal1-BWP, there is one frequency-hopping subband being the same as the frequency-hopping subband of terminal2-BWP; in the second type of frequency-hopping subband scheme, there is one frequency hopping subband being the same as the frequency hopping subband of terminal3-BWP. According to scheduling by the base station, terminal1 and terminal2 may be scheduled for uplink transmission simultaneously in a certain Transmission Timing Interval (TTI). In this TTI, terminal1 may use the first type of frequency hopping subband scheme according to the downlink signaling instruction. terminal1 and terminal3 may also be scheduled by the base station for uplink transmission in another TTI simultaneously. In this TTI, terminal1 may use the second type of frequency hopping subband scheme according to the downlink signaling instruction. Thus, the same terminal1 can flexibly use different frequency hopping subband schemes in different TTIs according to the actual scheduling

situation.

[00186] It can be seen from the above embodiments that one or more different frequency hopping subband schemes can be configured for each configured BWP. Each frequency hopping subband scheme includes at least one frequency hopping subband, and the frequency hopping subbands in the same BWP are a section of continuous frequency resources in the BWP, thus realizing the uplink transmission frequency hopping of the terminal under the frequency hopping subband scheme indicated by the base station, which not only enriches the implementation manners of frequency hopping configuration, but also improves the use efficiency of system resource.

[00187] Fig. 7 is a flowchart illustrating another frequency hopping configuration method according to an exemplary embodiment. The frequency hopping configuration method may be used in a base station, and based on the method shown in Fig. 3, the frequency hopping configuration may be frequency hopping subband scheme. When step 120 is performed, as shown in Fig. 7, the method may include the following steps 710-720.

[00188] In step 710, if one frequency hopping subband scheme is configured for the BWP with which the terminal being configured currently, this frequency hopping subband scheme is determined as the frequency hopping configuration corresponding to the BWP with which the terminal being configured currently.

[00189] In step 720, if a plurality of frequency hopping subband schemes are configured for the BWP with which the terminal being configured currently, one frequency hopping subband scheme is selected from the plurality of frequency hopping subband schemes, and the selected frequency hopping subband scheme is determined as the frequency hopping configuration corresponding to the BWP with which the terminal being configured currently.

[00190] In the embodiments of the present disclosure, the base station may flexibly select the frequency hopping configuration corresponding to the BWP with which the terminal being configured currently according to an actual scheduling situation. For example, as shown in Fig. 5, according to scheduling of the base station, when terminal1 and terminal2 may be scheduled for uplink transmission at the same time in a TTI, in this TTI, the base station may select the first type of frequency hopping subband scheme as the frequency

hopping configuration corresponding to the BWP with which the terminal being configured currently. Similarly, according to scheduling of the base station, terminal1 and terminal3 may also be scheduled by the base station for uplink transmission in another TTI at the same time. In another TTI, the base station may select the second type of frequency hopping subband scheme as the frequency hopping configuration corresponding to the BWP with which the terminal being configured currently.

[00191] It can be seen from the above embodiments that one or more frequency hopping subband schemes may be configured in advance for the BWP with which the terminal being configured currently. When the base station instructs the terminal to perform uplink transmission frequency hopping, it can select an appropriate frequency hopping subband scheme from these frequency hopping subband schemes configured in advance and allocate it to the terminal, which can avoid the problem of the decrease in use efficiency of the system resource caused by different terminals using different BWPs, thereby improving the use efficiency of system resource.

[00192] Fig. 8 is a flow chart showing another frequency hopping configuration method according to an exemplary embodiment. The frequency hopping configuration method may be used in a base station, and based on the method shown in Fig. 7, the frequency hopping configuration may be one or multiple different frequency hopping subband schemes. When step 130 is performed, as shown in Fig. 8, the following steps 810-820 may be included.

[00193] In step 810, first indication information is generated, and the first indication information includes a frequency hopping subband scheme corresponding to a BWP with which the terminal being configured currently.

[00194] In step 820, the first indication information is sent to the terminal, so that the terminal obtains the frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently according to the first indication information.

[00195] It can be seen from the foregoing embodiment that the frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently indicated by the base station can be delivered to the terminal through the first indication information, so that the terminal can accurately obtain the frequency hopping

subband scheme corresponding to the BWP with which the terminal being configured currently from the first indication information, thereby improving the accuracy of frequency hopping configuration.

[00196] Fig. 9 is a flowchart illustrating another frequency hopping configuration method according to an exemplary embodiment. The frequency hopping configuration method may be used in a base station, and based on the method shown in Fig. 3, the frequency hopping configuration may be one or multiple different frequency hopping subband schemes. After step 310 is performed, as shown in Fig. 9, the frequency hopping configuration method may further include the following steps 910-920.

[00197] In step 910, frequency hopping configuration information is generated, and the frequency hopping configuration information includes one or more different frequency hopping subband schemes configured by the base station for each configured BWP.

[00198] In the embodiments of the present disclosure, after the base station configures one or more different frequency hopping subband schemes for each configured BWP of the terminal, it may use the frequency hopping configuration information to deliver one or more different frequency hopping subband schemes corresponding to each configured BWP to the terminal. The purpose is to let the terminal know the specific content of these frequency hopping subband schemes in advance. When the base station instructs the terminal to perform uplink transmission frequency hopping, it only needs to inform the terminal of a frequency hopping subband scheme identifier corresponding to BWP with which the terminal being configured currently, so that the terminal determines the frequency hopping subband scheme corresponding to the BWP that it currently uses according to the frequency hopping subband scheme identifier.

[00199] In step 920, the frequency hopping configuration information is sent to the terminal, so that the terminal obtains one or more different frequency hopping subband schemes configured by the base station for each configured BWP from the frequency hopping configuration information.

[00200] It can be seen from the above embodiments that after configuring the frequency hopping configuration for each configured BWP, the base station may deliver one or more different frequency hopping subband schemes configured for each configured BWP

to the terminal by using the frequency hopping configuration information, so that the terminal can know the specific content of these frequency hopping subband schemes in advance. When the base station instructs the terminal to perform uplink transmission frequency hopping, the frequency hopping subband scheme corresponding to BWP with which the terminal being configured currently can be determined by only the frequency hopping subband scheme identifier indicated by the base station, thereby improving the efficiency of frequency hopping configuration.

[00201] Fig. 10 is a flowchart illustrating another frequency hopping configuration method according to an exemplary embodiment. The frequency hopping configuration method may be used in a base station, and based on the method shown in Fig. 9, the frequency hopping configuration may be one or more different frequency hopping subband schemes. When step 130 is performed, as shown in Fig. 10, the following steps 1010-1020 may be included.

[00202] In step 1010, second indication information is generated, the second indication information includes a frequency hopping subband scheme identifier, and the frequency hopping subband scheme identifier is an identifier of the frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently.

[00203] In step 1020, the second indication information is sent to the terminal, so that the terminal obtains the frequency hopping subband scheme identifier according to the second indication information, and determines the frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently according to the frequency hopping subband scheme identifier.

[00204] It can be seen from the foregoing embodiments that the frequency hopping subband scheme identifier can be sent to the terminal through the second indication information, so that the terminal can determine the frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently according to the frequency hopping subband scheme identifier indicated by the base station and the specific content of the different frequency hopping subband schemes known in advance, thereby ensuring that the terminal accurately determines the frequency hopping subband scheme corresponding to the BWP currently used by itself, and also increasing the instruction

speed of the frequency hopping configuration.

[00205] Fig. 11 is a flowchart illustrating another frequency hopping configuration method according to an exemplary embodiment. The frequency hopping configuration method may be used in a base station, and based on the method shown in Fig. 1, the frequency hopping configuration may be a specified frequency hopping offset. When step 110 is performed, as shown in Fig. 11, the method may include the following step 1110.

[00206] In step 1110, one or more different specified frequency hopping offsets are configured for each configured BWP.

[00207] In the embodiment of the present disclosure, in order to meet the requirement of more flexible frequency hopping offset caused by different BWP configurations, one or more different specified frequency hopping offsets may be configured for different BWPs. When performing dynamic scheduling according to the actual scheduling situation, the base station may select an appropriate specified frequency hopping offset; or, when the uplink transmission resource allocation of the terminal is semi-static allocation, the base station may directly indicate the frequency domain offset needing to be used by the frequency hopping when the uplink resource allocation is performed.

[00208] It can be seen from the above embodiments that, by configuring one or more different specified frequency hopping offsets for each configured BWP, the terminal can complete the uplink transmission frequency hopping at the specified frequency hopping offset indicated by the base station, which enriches the implementation manners of frequency hopping configuration, and also improves the speed of completing the frequency hopping for uplink transmission.

[00209] Fig. 12 is a flowchart illustrating another frequency hopping configuration method according to an exemplary embodiment. The frequency hopping configuration method may be used in a base station, and based on the method shown in Fig. 11, the frequency hopping configuration may be a specified frequency hopping offset. When performing step 120, as shown in Fig. 12, the method may include the following steps 1210-1220.

[00210] In step 1210, if one specified frequency hopping offset is configured for the BWP with which the terminal being configured currently, the specified frequency hopping

offset is determined as the frequency hopping configuration corresponding to the BWP with which the terminal being configured currently.

[00211] In step 1220, if multiple specified frequency hopping offsets are configured for the BWP with which the terminal being configured currently, one specific frequency hopping offset is selected from the multiple specified frequency hopping offsets, and the selected frequency hopping subband scheme is determined as the frequency hopping configuration corresponding to the BWP with which the terminal being configured currently.

[00212] For example, the base station pre-configures 4 specified frequency hopping offsets for terminal1-BWP, namely specified frequency hopping offset 1, specified frequency hopping offset 2, specified frequency hopping offset 3, and specified frequency hopping offset 4. When the base station performs uplink data scheduling, it may indicate in the uplink scheduling information which specified frequency hopping offset is to be used.

[00213] It can be seen from the above embodiments that one or more specified frequency hopping offsets can be configured in advance for the BWP with which the terminal being configured currently. When the base station instructs the terminal to perform uplink transmission frequency hopping, an appropriate specified frequency hopping offset is selected from the specified frequency hopping offsets configured in advance and is allocated to the terminal, so that the problem of the decrease in use efficiency of system resource caused by different terminals using different BWPs can be avoided, thereby improving the use efficiency of system resource.

[00214] Fig. 13 is a flowchart illustrating another frequency hopping configuration method according to an exemplary embodiment. The frequency hopping configuration method may be used in a base station, and based on the method shown in Fig. 12, the frequency hopping configuration may be a specified frequency hopping offset. When performing step 130, as shown in Fig. 13, the method may include the following steps 1310 to 1320.

[00215] In step 1310, third indication information is generated, and the third indication information includes a specified frequency hopping offset corresponding to a BWP with which the terminal being configured currently.

[00216] In step 1320, the third indication information is sent to the terminal, so that the

terminal obtains the specified frequency hopping offset corresponding to the BWP with which the terminal being configured currently according to the third indication information.

[00217] It can be seen from the foregoing embodiment that the specified frequency hopping offset corresponding to the BWP with which the terminal being configured currently indicated by the base station can be sent to the terminal through the third indication information, so that the terminal can accurately obtain the specified frequency hopping offset corresponding to the BWP with which the terminal being configured currently from the third indication information, thereby improving the accuracy of the frequency hopping configuration.

[00218] Fig. 14 is a flowchart illustrating a frequency hopping configuration method according to an exemplary embodiment. The frequency hopping configuration method may be used for a terminal, and the base station configures the terminal with at least one BWP. As shown in Fig. 14, the frequency hopping configuration method may include the following steps 1410-1430.

[00219] In step 1410, a frequency hopping configuration sent by the base station is received, where the frequency hopping configuration is a frequency hopping configuration configured by the base station for a BWP with which the terminal being configured currently.

[00220] In step 1420, when uplink transmission frequency hopping is performed, a second frequency domain resource position after the frequency hopping is determined according to the frequency hopping configuration and a first frequency domain resource position before the frequency hopping.

[00221] In step 1430, uplink transmission is performed at the second frequency domain resource position.

[00222] It can be seen from the above embodiments that by receiving the frequency hopping configuration sent by the base station, the frequency hopping configuration being the frequency hopping configuration configured by the base station for the BWP with which the terminal being configured currently, and when performing uplink transmission frequency hopping, determining the second frequency domain resource position after frequency hopping according to the frequency hopping configuration and the first frequency domain resource position, and performing uplink transmission at the second frequency domain resource

position, uplink transmission frequency hopping under the frequency hopping configuration indicated by the base station can be achieved, which not only reduces uplink scheduling complexity, but also reduces fragmentation of system resources and improves system resource utilization efficiency.

[00223] Fig. 15 is a flowchart illustrating another frequency hopping configuration method according to an exemplary embodiment. The frequency hopping configuration method may be used for a terminal, and based on the method shown in Fig. 14, the frequency hopping configuration may be a frequency hopping subband scheme. When step 1410 is performed, as shown in Fig. 15, the following steps 1510-1520 may be included.

[00224] In step 1510, first indication information sent by the base station is received, where the first indication information includes a frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently, and the frequency hopping subband scheme includes at least one frequency hopping subband, and the frequency hopping subbands in the same BWP are a section of continuous frequency resources in the BWP.

[00225] In step 1520, the frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently is obtained according to the first indication information.

[00226] It can be seen from the foregoing embodiment that the frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently can be accurately obtained from the first indication information, thereby improving the reliability of the terminal obtaining the frequency hopping subband scheme.

[00227] Fig. 16 is a flowchart illustrating another frequency hopping configuration method according to an exemplary embodiment. The frequency hopping configuration method may be used for a terminal, and based on the method shown in Fig. 14, the frequency hopping configuration may be a frequency hopping subband scheme. As shown in Fig. 16, the frequency hopping configuration method may further include the following steps 1610-1620.

[00228] In step 1610, frequency hopping configuration information sent by the base station is received, where the frequency hopping configuration information includes one or

more different frequency hopping subband schemes configured by the base station for each configured BWP, and each frequency hopping subband scheme includes at least one frequency hopping subband, and the frequency hopping subbands in the same BWP are a section of continuous frequency resources in the BWP.

[00229] In step 1620, one or more different frequency hopping subband schemes configured by the base station for each configured BWP are obtained from the frequency hopping configuration information.

[00230] It can be seen from the above embodiments that the specific content of one or more different frequency hopping subband schemes configured by the base station for each configured BWP can be known in advance from the frequency hopping configuration information, and when the base station instructs to perform uplink transmission frequency hopping, the frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently can be determined according to the frequency hopping subband scheme identifier indicated by the base station, thereby enriching the implementation manners of the terminal determining the frequency hopping subband scheme corresponding to the BWP currently used, and improving the efficiency of the terminal obtaining the frequency hopping subband scheme.

[00231] Fig. 17 is a flowchart illustrating another frequency hopping configuration method according to an exemplary embodiment. The frequency hopping configuration method may be used for a terminal, and based on the method shown in Fig. 16, the frequency hopping configuration may be a frequency hopping subband scheme. When step 1410 is performed, as shown in Fig. 17, the following steps 1710 to 1730 may be included.

[00232] In step 1710, the second indication information sent by the base station is received. The second indication information includes a frequency hopping subband scheme identifier, and the frequency hopping subband scheme identifier is an identifier of the frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently.

[00233] In step 1720, the frequency hopping subband scheme identifier is obtained according to the second indication information.

[00234] In step 1730, the frequency hopping subband scheme corresponding to the

BWP with which the terminal being configured currently is determined according to the frequency hopping subband scheme identifier.

[00235] It can be seen from the foregoing embodiment that the frequency hopping subband scheme identifier indicated by the base station can be obtained through the second indication information, and the frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently is determined according to the frequency hopping subband scheme identifier indicated by the base station, thereby ensuring that the frequency hopping subband scheme corresponding to the BWP currently used is determined, and also improving the efficiency of the terminal obtaining the frequency hopping subband scheme.

[00236] Fig. 18 is a flowchart illustrating another frequency hopping configuration method according to an exemplary embodiment. The frequency hopping configuration method may be used for a terminal, and based on the method shown in Fig. 15 or Fig. 17, the frequency hopping configuration may be the frequency hopping subband scheme. When step 1420 is performed, as shown in Fig. 18, the following steps 1810 to 1820 may be included.

[00237] In step 1810, a first frequency hopping subband corresponding to a first frequency domain resource position is determined according to the frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently.

[00238] In step 1820, a second frequency domain resource position is calculated according to the first frequency hopping subband and the first frequency domain resource position.

[00239] It can be seen from the foregoing embodiments that the first frequency hopping subband corresponding to the first frequency domain resource position may be determined according to the frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently, and according to the first frequency hopping subband and the first frequency domain resource position, the second frequency domain resource position is calculated, thereby realizing the determination of the second frequency domain resource position after the frequency hopping under the frequency hopping subband scheme indicated by the base station, and improving the efficiency of completing the

frequency hopping of the uplink transmission.

[00240] Fig. 19 is a flowchart illustrating another frequency hopping configuration method according to an exemplary embodiment. The frequency hopping configuration method may be used for a terminal, and based on the method shown in Fig. 18, the frequency hopping configuration may be a frequency hopping subband solution. When step 1820 is performed, as shown in Fig. 19, the subband solution may include the following step 1910 or step 1920.

[00241] In step 1910, a mirror position of the first frequency domain resource position in the first frequency hopping subband is calculated, and the mirror position is the second frequency domain resource position.

[00242] In step 1920, the first frequency hopping subband is used as a transmission bandwidth for uplink data transmission, and the second frequency domain resource position is calculated according to information in uplink scheduling signaling sent by the base station.

[00243] It can be seen from the above embodiments that the mirror position of the first frequency domain resource position in the first frequency hopping subband can be calculated, the mirror position being the second frequency domain resource position; or the first frequency hopping subband is used as the transmission bandwidth of uplink data transmission, and the second frequency domain resource position is calculated according to the information in the uplink scheduling signaling sent by the base station, thereby enriching the implementation manners of determining the second frequency domain resource position and improving the efficiency of completing uplink transmission frequency hopping.

[00244] Fig. 20 is a flowchart illustrating another frequency hopping configuration method according to an exemplary embodiment. The frequency hopping configuration method may be used for a terminal, and based on the method shown in Fig. 14, the frequency hopping configuration may be a specified frequency hopping offset. When step 1410 is performed, as shown in Fig. 20, the method may include the following steps 2010-2020.

[00245] In step 2010, third indication information sent by the base station is received, and the third indication information includes a specified frequency hopping offset corresponding to a BWP with which the terminal being configured currently.

[00246] In step 2020, the specified frequency hopping offset corresponding to the

BWP with which the terminal being configured currently is obtained according to the third indication information.

[00247] It can be seen from the foregoing embodiment that the specified frequency hopping offset corresponding to the BWP with which the terminal being configured currently can be accurately obtained from the third indication information, thereby improving the reliability of the terminal in obtaining the specified frequency hopping offset.

[00248] Fig. 21 is a flowchart illustrating another frequency hopping configuration method according to an exemplary embodiment. The frequency hopping configuration method may be used for a terminal, and based on the method shown in Fig. 20, the frequency hopping configuration may be a specified frequency hopping offset. When performing step 1420, as shown in Fig. 21, the method may include the following step 2110.

[00249] In step 2110, the second frequency domain resource position is determined according to the specified frequency hopping offset corresponding to the BWP with which the terminal being configured currently and the first frequency domain resource position.

[00250] It can be seen from the above embodiments that the second frequency domain resource position can be determined according to the specified frequency hopping offset corresponding to the BWP with which the terminal being configured currently and the first frequency domain resource position, thereby achieving determination of the second frequency domain resource after frequency hopping under the specified frequency hopping offset indicated by the base station, and improving the efficiency of completing frequency hopping for uplink transmission.

[00251] Corresponding to the foregoing embodiments of the frequency hopping configuration method, the present disclosure also provides an embodiment of a frequency hopping configuration device.

[00252] Fig. 22 is a block diagram of a frequency hopping configuration device according to an exemplary embodiment. The device is used in a base station. The base station configures at least one BWP for a terminal and is used to perform the frequency hopping configuration method shown in Fig. 1. As shown in Fig. 22, the frequency hopping configuration device may include:

[00253] a configuration module 221 configured to configure a frequency hopping

configuration for each configured BWP;

[00254] a frequency hopping configuration determining module 222 configured to, when instructing the terminal to perform uplink transmission frequency hopping, determine a frequency hopping configuration corresponding to a BWP with which the terminal being configured currently according to the configured frequency hopping configuration; and

[00255] a first sending module 223 configured to send the corresponding frequency hopping configuration to a terminal, so that the terminal determines a second frequency domain resource position after frequency hopping according to the corresponding frequency hopping configuration and a first frequency domain resource position before the frequency hopping, and perform uplink transmission at the second frequency domain resource position.

[00256] It can be seen from the foregoing embodiments that by configuring a frequency hopping configuration for each configured BWP, when instructing the terminal to perform uplink transmission frequency hopping, determining the frequency hopping configuration corresponding to the BWP with which the terminal being configured currently according to the configured frequency hopping configuration, and sending the frequency hopping configuration corresponding to the BWP with which the terminal being configured currently to the terminal, the terminal can determine the second frequency domain resource position after frequency hopping according to the frequency hopping configuration indicated by the base station and the first frequency domain resource position before frequency hopping, and perform uplink transmission at the second frequency domain resource position, thereby realizing that the terminal completes uplink transmission frequency hopping under the frequency hopping configuration indicated by the base station, which not only reduces uplink scheduling complexity, but also reduces system resource fragmentation and improves system resource use efficiency.

[00257] In an embodiment, based on the device shown in Fig. 22, as shown in Fig. 23, the configuration module 221 may include:

[00258] a first configuration submodule 231 configured to configure one or more different frequency hopping subband schemes for each configured BWP. Each frequency hopping subband scheme includes at least one frequency hopping subband. In the same BWP, the frequency hopping subbands are a section of continuous frequency resources in the BWP.

[00259] It can be seen from the above embodiments that one or more different frequency hopping subband schemes can be configured for each configured BWP, each frequency hopping subband scheme includes at least one frequency hopping subband, and the frequency hopping subbands in the same BWP are a section of continuous frequency resources in the BWP, thus realizing the uplink transmission frequency hopping of the terminal under the frequency hopping subband scheme indicated by the base station, which not only enriches the implementation manners of frequency hopping configuration, but also improves the efficiency of system resource use .

[00260] In an embodiment, based on the device shown in Fig. 23, as shown in Fig. 24, the frequency hopping configuration determining module 222 may include:

[00261] a first determining submodule 241 configured to, if one frequency hopping subband scheme is configured for the BWP with which the terminal being configured currently, determine the frequency hopping subband scheme as the frequency hopping configuration corresponding to the BWP with which the terminal being configured currently; and

[00262] a second determining submodule 242 configured to, if multiple frequency hopping subband schemes are configured for the BWP with which the terminal being configured currently, select one frequency hopping subband scheme from the multiple frequency hopping subband schemes and determine the selected frequency hopping subband scheme as the frequency hopping configuration corresponding to the BWP with which the terminal being configured currently.

[00263] It can be seen from the above embodiments that one or more frequency hopping subband schemes can be configured in advance for the BWP with which the terminal being configured currently, when the base station instructs the terminal to perform uplink transmission frequency hopping, it can select from these frequency hopping subband schemes configured in advance an appropriate frequency hopping subband scheme and allocate it to the terminal, which can avoid the problem of the decrease in the system resource use efficiency caused by different terminals using different BWPs, thereby improving the system resource use efficiency.

[00264] In an embodiment, based on the device shown in Fig. 24, as shown in Fig. 25,

the first sending module 223 may include:

[00265] a first generating submodule 251 configured to generate first indication information, where the first indication information includes a frequency hopping subband scheme corresponding to a BWP with which the terminal being configured currently; and

[00266] a first sending submodule 252 configured to send the first indication information to the terminal, so that the terminal obtains the frequency hopping subband solution corresponding to the BWP with which the terminal being configured currently according to the first indication information.

[00267] It can be seen from the foregoing embodiment that the frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently indicated by the base station can be delivered to the terminal through the first indication information, so that the terminal can accurately obtain the frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently from the first indication information, thereby improving the accuracy of frequency hopping configuration.

[00268] In an embodiment, based on the device shown in Fig. 23, as shown in Fig. 26, the frequency hopping configuration device may further include:

[00269] an information generating module 261 configured to generate frequency hopping configuration information, where the frequency hopping configuration information includes one or more different frequency hopping subband schemes configured by the base station for each configured BWP;

[00270] a second sending module 262 configured to send the frequency hopping configuration information to the terminal, so that the terminal obtains, from the frequency hopping configuration information, one or multiple different frequency hopping subband schemes configured by the base station for each configured BWP.

[00271] It can be seen from the above embodiments that after the frequency hopping configuration are configured for each configured BWP, the base station may send one or more different frequency hopping subband schemes configured for each configured BWP to the terminal by using the frequency hopping configuration information, so that the terminal can know the specific content of these frequency hopping subband schemes in advance, and

when the base station instructs the terminal to perform uplink translation frequency hopping, the frequency hopping subband scheme corresponding to the currently used BWP can be determined only by using the frequency hopping subband scheme identifier indicated by the base station, thereby improving the efficiency of frequency hopping configuration.

[00272] In an embodiment, based on the device shown in Fig. 26, as shown in Fig. 27, the first sending module 223 may include:

[00273] a second generating submodule 271 configured to generate second indication information, where the second indication information includes a frequency hopping subband scheme identifier, and the frequency hopping subband scheme identifier is an identifier of the frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently;

[00274] a second sending submodule 272 configured to send the second indication information to the terminal, so that the terminal obtains the frequency hopping subband scheme identifier according to the second indication information, and determines the frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently according to the frequency subband scheme identifier.

[00275] It can be seen from the foregoing embodiments that the frequency hopping subband scheme identifier can be sent to the terminal through the second indication information, so that the terminal can determine the frequency hopping subband scheme corresponding to the BWP currently used by itself according to the frequency hopping subband scheme identifier indicated by the base station and the specific content of the different frequency hopping subband schemes obtained in advance, thereby ensuring that the terminal accurately determines the frequency hopping subband scheme corresponding to the BWP currently used, and also increasing the instruction speed of the frequency hopping configuration.

[00276] In an embodiment, based on the device shown in Fig. 22, as shown in Fig. 28, the configuration module 221 may include:

[00277] a second configuration submodule 281 configured to configure one or more different specified frequency hopping offsets for each configured BWP.

[00278] It can be seen from the above embodiments that, by configuring one or more

different specified frequency hopping offsets for each configured BWP, the terminal can complete the uplink transmission frequency hopping at the specified frequency hopping offset indicated by the base station, which not only enriches the implementation manners of the frequency hopping configuration, but also improves the speed of completing the frequency hopping for uplink transmission.

[00279] In an embodiment, based on the device shown in Fig. 28, as shown in Fig. 29, the frequency hopping configuration determining module 222 may include:

[00280] a third determining submodule 291 configured to, if one specified frequency hopping offset is configured for the BWP with which the terminal being configured currently, determine the specified frequency hopping offset as the frequency hopping configuration corresponding to the BWP with which the terminal being configured currently;

[00281] a fourth determining submodule 292 configured to select a specified frequency hopping offset from the plurality of specified frequency hopping offsets if a plurality of specified frequency hopping offsets are configured for the BWP with which the terminal being configured currently. And determine the selected frequency hopping subband scheme as the frequency hopping configuration corresponding to the BWP with which the terminal being configured currently.

[00282] It can be seen from the above embodiments that one or more specified frequency hopping offsets can be configured in advance for the BWP with which the terminal being configured currently. When the base station instructs the terminal to perform uplink transmission frequency hopping, an appropriate specified frequency hopping offset may be selected from the specified frequency hopping offsets configured in advance and allocated to the terminal, so that the problem of the decrease in system resource use efficiency caused by different terminals using different BWPs can be avoided, thereby improving the system resource use efficiency.

[00283] In an embodiment, based on the device shown in Fig. 29, as shown in Fig. 30, the first sending module 223 may include:

[00284] a third generating submodule 301 configured to generate third indication information, where the third indication information includes a specified frequency hopping offset corresponding to the BWP with which the terminal being configured currently;

[00285] a third sending submodule 302 configured to send the third indication information to the terminal, so that the terminal obtains a specified frequency hopping offset corresponding to the BWP with which the terminal being configured currently according to the third indication information.

[00286] It can be seen from the foregoing embodiment that the specified frequency hopping offset corresponding to the BWP with which the terminal being configured currently indicated by the base station can be sent to the terminal through the third indication information, so that the terminal can accurately obtain the specified frequency hopping offset corresponding to the BWP with which the terminal being configured currently from the third indication information, thereby improving the accuracy of the frequency hopping configuration.

[00287] Fig. 31 is a block diagram of a frequency hopping configuration device according to an exemplary embodiment. The device is used for a terminal, and the base station configures the terminal with at least one BWP, and is used to perform the frequency hopping configuration method shown in Fig. 14. As shown in Fig. 31, the frequency hopping configuration device may include:

[00288] a first receiving module 311 configured to receive a frequency hopping configuration sent by the base station, where the frequency hopping configuration is a frequency hopping configuration configured by the base station for a BWP with which the terminal being configured currently;

[00289] a resource position determining module 312 configured to, when performing uplink transmission frequency hopping, determine a second frequency domain resource position after frequency hopping according to the frequency hopping configuration and a first frequency domain resource position before the frequency hopping;

[00290] an uplink transmission module 313 configured to perform uplink transmission at the second frequency domain resource position.

[00291] It can be seen from the above embodiments that by receiving the frequency hopping configuration sent by the base station, the frequency hopping configuration being the frequency hopping configuration configured by the base station for the BWP with which the terminal being configured currently, when performing uplink transmission frequency hopping,

determining the second frequency domain resource position after frequency hopping according to the frequency hopping configuration and the first frequency domain resource position before frequency hopping, and performing uplink transmission at the second frequency domain resource position, uplink transmission frequency hopping can be achieved under the frequency hopping configuration indicated by the base station, which not only reduces uplink scheduling complexity, but also reduces fragmentation of system resources and improves system resource utilization efficiency.

[00292] In an embodiment, based on the device shown in Fig. 31, as shown in Fig. 32, the first receiving module 311 may include:

[00293] a first receiving submodule 321 configured to receive first indication information sent by the base station, where the first indication information includes a frequency hopping subband scheme corresponding to a BWP with which the terminal being configured currently, the frequency hopping subband scheme includes at least one frequency hopping subband, and the frequency hopping subbands in the same BWP are a section of continuous frequency resources in the BWP;

[00294] a first obtaining submodule 322 configured to obtain a frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently according to the first indication information.

[00295] It can be seen from the foregoing embodiment that the frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently can be accurately obtained from the first indication information, thereby improving the reliability of the terminal obtaining the frequency hopping subband scheme.

[00296] In an embodiment, based on the device shown in Fig. 31, as shown in Fig. 33, the frequency hopping configuration device may further include:

[00297] a second receiving module 331 configured to receive frequency hopping configuration information sent by the base station, where the frequency hopping configuration information includes one or more different frequency hopping subband schemes configured by the base station for each configured BWP, each frequency hopping subband scheme includes at least one frequency hopping subband, and the frequency hopping subbands in the same BWP are a section of continuous frequency resources in the BWP;

[00298] an obtaining module 332 configured to obtain, from the frequency hopping configuration information, one or more different frequency hopping subband schemes configured by the base station for each configured BWP.

[00299] It can be seen from the above embodiments that the specific content of one or more different frequency hopping subband schemes configured by the base station for each configured BWP can be known in advance from the frequency hopping configuration information, and when the base station instructs to perform uplink transmission frequency hopping, the frequency hopping subband scheme corresponding to the BWP currently used can be determined according to the frequency hopping subband scheme identifier indicated by the base station, thereby enriching the implementation manners of the terminal determining the frequency hopping subband scheme corresponding to the BWP currently used, and improving the efficiency of obtaining the frequency hopping subband scheme by the terminal.

[00300] In an embodiment, based on the device shown in Fig. 33, as shown in Fig. 34, the first receiving module 311 may include:

[00301] a second receiving submodule 341 configured to receive second indication information sent by the base station, where the second indication information includes a frequency hopping subband scheme identifier, and the frequency hopping subband scheme identifier is a current identifier used by the terminal. Identification of the frequency hopping subband scheme corresponding to the BWP;

[00302] a second obtaining submodule 342 configured to acquire the frequency hopping subband scheme identifier according to the second indication information;

[00303] a frequency hopping scheme determining submodule 343 configured to determine, according to the frequency hopping subband scheme identifier, a frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently.

[00304] It can be seen from the foregoing embodiment that the frequency hopping subband scheme identifier indicated by the base station can be obtained through the second indication information, and the frequency hopping subband scheme corresponding to the BWP currently used by the base station is determined according to the frequency hopping

subband scheme identifier indicated by the base station, thereby ensuring that the frequency hopping subband scheme corresponding to the BWP currently used is determined, and the efficiency of obtaining the frequency hopping subband scheme by the terminal is also improved.

[00305] In an embodiment, based on the device shown in Fig. 32 or Fig. 34, as shown in Fig. 35, the resource position determining module 312 may include:

[00306] a frequency hopping subband determining submodule 351 configured to determine a first frequency hopping subband corresponding to the first frequency domain resource position according to the frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently;

[00307] a first calculation submodule 352 configured to calculate a second frequency domain resource position according to the first frequency hopping subband and the first frequency domain resource position.

[00308] It can be seen from the foregoing embodiments that the first frequency hopping subband corresponding to the first frequency domain resource position may be determined according to the frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently, and according to the first frequency hopping subband and the first frequency domain resource position, the second frequency domain resource position is calculated, thereby realizing the determination of the second frequency domain resource position after the frequency hopping under the frequency hopping subband scheme indicated by the base station, and improving the efficiency of completing the frequency hopping of the uplink transmission.

[00309] In an embodiment, based on the device shown in Fig. 35, as shown in Fig. 36, the first calculation submodule 352 may include:

[00310] a second calculation submodule 361 configured to calculate a mirror position of the first frequency domain resource position in the first frequency hopping subband, the mirror position being the second frequency domain resource position; or

[00311] a third calculation submodule 362 configured to use the first frequency hopping subband as a transmission bandwidth for uplink data transmission, and calculate the second frequency domain resource position according to information in uplink scheduling

signaling sent by the base station.

[00312] It can be seen from the above embodiments that the mirror position of the first frequency domain resource position in the first frequency hopping subband can be calculated, and the mirror position is the second frequency domain resource position; or the first frequency hopping subband is used as the uplink data transmission bandwidth, and the second frequency domain resource position is calculated according to the information in the uplink scheduling signaling sent by the base station, thereby enriching the implementation manners of determining the second frequency domain resource position and improving the efficiency of completing uplink transmission frequency hopping.

[00313] In an embodiment, based on the device shown in Fig. 31, as shown in Fig. 37, the first receiving module 311 may include:

[00314] a third receiving submodule 371 configured to receive third indication information sent by the base station, where the third indication information includes a specified frequency hopping offset corresponding to the BWP with which the terminal being configured currently;

[00315] a third obtaining submodule 372 configured to obtain the specified frequency hopping offset corresponding to the BWP with which the terminal being configured currently according to the third indication information.

[00316] It can be seen from the foregoing embodiment that the specified frequency hopping offset corresponding to the BWP with which the terminal being configured currently can be accurately obtained from the third indication information, thereby improving the reliability of obtaining the specified frequency hopping offset by the terminal.

[00317] In an embodiment, based on the device shown in Fig. 37, as shown in Fig. 38, the resource position determining module 312 may include:

[00318] a resource position determining submodule 381 configured to determine a second frequency domain resource position according to the specified frequency hopping offset corresponding to the BWP with which the terminal being configured currently and the first frequency domain resource position.

[00319] It can be seen from the above embodiments that the second frequency domain resource position can be determined according to the specified frequency hopping offset

corresponding to the BWP with which the terminal being configured currently and the first frequency domain resource position, thereby achieving the determination of the second frequency domain resource position after frequency hopping under the specified frequency hopping offset indicated by the base station, which improves the efficiency of completing frequency hopping for uplink transmission.

[00320] As for the device embodiments, since they basically correspond to the method embodiments, the relevant contents may refer to the description of the method embodiments. The device embodiments described above are only schematic, in which the units described as separate components may or may not be physically separated, and the components shown as units may or may not be physical units, that is, they may be located in one place, or may be distributed in multiple network elements. Some or all of the modules can be selected according to actual needs to achieve the objectives of the solutions of the present disclosure. Those of ordinary skill in the art can understand and implement them without creative efforts.

[00321] The present disclosure also provides a non-transitory computer-readable storage medium. A computer program is stored on the storage medium, and the computer program is configured to execute the frequency hopping configuration method described in any one of Fig. 1 to Fig. 13.

[00322] The present disclosure also provides a non-transitory computer-readable storage medium. A computer program is stored on the storage medium, and the computer program is configured to execute the frequency hopping configuration method described in any one of Fig. 14 to Fig. 21.

[00323] The present disclosure also provides a frequency hopping configuration device. The device is used in a base station. The base station configures at least one BWP for a terminal. The device includes:

[00324] a processor; and

[00325] memory for storing instructions executable by the processor;

[00326] where the processor is configured to:

[00327] configure a frequency hopping configuration for each configured BWP;

[00328] when instructing the terminal to perform uplink transmission frequency hopping, determine a frequency hopping configuration corresponding to a BWP with which

the terminal being configured currently according to the configured frequency hopping configuration; and

[00329] send the corresponding frequency hopping configuration to the terminal, so that the terminal determines a second frequency domain resource position after the frequency hopping according to the corresponding frequency hopping configuration and a first frequency domain resource position before the frequency hopping, and perform uplink transmission at the second frequency domain resource position.

[00330] Fig. 39 is a schematic structural diagram of a frequency hopping configuration device according to an exemplary embodiment. As shown in Fig. 39, the device 3900 may be provided as a base station. Referring to Fig. 39, the device 3900 includes a processing component 3922, a wireless transmitting/receiving component 3924, an antenna component 3926, and a signal processing portion unique to a wireless interface. The processing component 3922 may further include one or more processors.

[00331] One of the processors in the processing component 3922 may be configured to perform any of the frequency hopping configuration methods described above.

[00332] The present disclosure also provides a frequency hopping configuration device. The device is used for a terminal. The base station configures the terminal with at least one BWP. The device includes:

[00333] a processor; and

[00334] memory for storing instructions executable by the processor;

[00335] wherein the processor is configured to:

[00336] receive a frequency hopping configuration sent by the base station, wherein the frequency hopping configuration is a frequency hopping configuration configured by the base station for a BWP with which the terminal being configured currently;

[00337] when performing uplink transmission frequency hopping, determine a second frequency domain resource position after the frequency hopping according to the frequency hopping configuration and a first frequency domain resource position before the frequency hopping; and

[00338] perform uplink transmission at the second frequency domain resource position.

[00339] Fig. 40 is a schematic structural diagram illustrating a frequency hopping configuration device according to an exemplary embodiment. As shown in Fig. 40, the frequency hopping configuration device 4000 according to an exemplary embodiment may be a computer, a mobile phone, a digital broadcast terminal, a messaging device, a gaming console, a tablet, a medical device, exercise equipment, a personal digital assistant, and other terminals.

[00340] Referring to Fig. 40, the device 4000 may include one or more of the following components: a processing component 4001, a memory 4002, a power component 4003, a multimedia component 4004, an audio component 4005, an input/output (I/O) interface 4006, a sensor component 4007, and a communication component 4008.

[00341] The processing component 4001 typically controls overall operations of the device 4000, such as the operations associated with display, telephone calls, data communications, camera operations, and recording operations. The processing component 4001 may include one or more processors 1220 to execute instructions to perform all or part of the steps in the above described methods. Moreover, the processing component 4001 may include one or more modules which facilitate the interaction between the processing component 4001 and other components. For instance, the processing component 4001 may include a multimedia module to facilitate the interaction between the multimedia component 4004 and the processing component 4001.

[00342] The memory 4002 is configured to store various types of data to support the operation of the device 4000. Examples of such data include instructions for any applications or methods operated on the device 4000, contact data, phonebook data, messages, pictures, video, etc. The memory 4002 may be implemented using any type of volatile or non-volatile memory devices, or a combination thereof, such as a static random access memory (SRAM), an electrically erasable programmable read-only memory (EEPROM), an erasable programmable read-only memory (EPROM), a programmable read-only memory (PROM), a read-only memory (ROM), a magnetic memory, a flash memory, a magnetic or optical disk.

[00343] The power component 4003 provides power to various components of the device 4000. The power component 4003 may include a power management system, one or more power sources, and any other components associated with the generation, management,

and distribution of power in the device 4000.

[00344] The multimedia component 4004 includes a screen providing an output interface between the device 4000 and the user. In some embodiments, the screen may include a liquid crystal display (LCD) and a touch panel (TP). If the screen includes the touch panel, the screen may be implemented as a touch screen to receive input signals from the user. The touch panel includes one or more touch sensors to sense touches, swipes, and gestures on the touch panel. The touch sensors may not only sense a boundary of a touch or swipe action, but also sense a period of time and a pressure associated with the touch or swipe action. In some embodiments, the multimedia component 4004 includes a front camera and/or a rear camera. The front camera and the rear camera may receive an external multimedia datum while the device 4000 is in an operation mode, such as a photographing mode or a video mode. Each of the front camera and the rear camera may be a fixed optical lens system or have focus and optical zoom capability.

[00345] The audio component 4005 is configured to output and/or input audio signals. For example, the audio component 4005 includes a microphone (“MIC”) configured to receive an external audio signal when the device 4000 is in an operation mode, such as a call mode, a recording mode, and a voice recognition mode. The received audio signal may be further stored in the memory 4002 or transmitted via the communication component 4008. In some embodiments, the audio component 4005 further includes a speaker to output audio signals.

[00346] The I/O interface 4006 provides an interface between the processing component 4001 and peripheral interface modules, such as a keyboard, a click wheel, buttons, and the like. The buttons may include, but are not limited to, a home button, a volume button, a starting button, and a locking button.

[00347] The sensor component 4007 includes one or more sensors to provide status assessments of various aspects of the device 4000. For instance, the sensor component 4007 may detect an open/closed status of the device 4000, relative positioning of components, e.g., the display and the keypad, of the device 4000, a change in position of the device 4000 or a component of the device 4000, a presence or absence of user contact with the device 4000, an orientation or an acceleration/deceleration of the device 4000, and a change in temperature of

the device 4000. The sensor component 4007 may include a proximity sensor configured to detect the presence of nearby objects without any physical contact. The sensor component 4007 may also include a light sensor, such as a CMOS or CCD image sensor, for use in imaging applications. In some embodiments, the sensor component 4007 may also include an accelerometer sensor, a gyroscope sensor, a magnetic sensor, a pressure sensor, or a temperature sensor.

[00348] The communication component 4008 is configured to facilitate communication, wired or wirelessly, between the device 4000 and other devices. The device 4000 can access a wireless network based on a communication standard, such as WiFi, 2G, or 3G, or a combination thereof. In one exemplary embodiment, the communication component 4008 receives a broadcast signal or broadcast associated information from an external broadcast management system via a broadcast channel. In one exemplary embodiment, the communication component 4008 further includes a near field communication (NFC) module to facilitate short-range communications. For example, the NFC module may be implemented based on a radio frequency identification (RFID) technology, an infrared data association (IrDA) technology, an ultra-wideband (UWB) technology, a Bluetooth (BT) technology, and other technologies.

[00349] In exemplary embodiments, the device 4000 may be implemented with one or more application specific integrated circuits (ASICs), digital signal processors (DSPs), digital signal processing devices (DSPDs), programmable logic devices (PLDs), field programmable gate arrays (FPGAs), controllers, micro-controllers, microprocessors, or other electronic components, for performing the above described methods.

[00350] In exemplary embodiments, there is also provided a non-transitory computer-readable storage medium including instructions, such as included in the memory 4002, executable by the processor 4009 in the device 4000, for performing the above-described methods. For example, the non-transitory computer-readable storage medium may be a ROM, a RAM, a CD-ROM, a magnetic tape, a floppy disc, an optical data storage device, and the like.

WHAT IS CLAIMED IS:

1. A frequency hopping configuration method, wherein the method is applied in a base station, and the base station configures at least one bandwidth part (BWP) for a terminal, the method comprising:

configuring a frequency hopping configuration for each configured BWP;

in response to instructing the terminal to perform uplink transmission frequency hopping, determining, according to the configured frequency hopping configuration, a frequency hopping configuration corresponding to a BWP with which the terminal being configured currently; and

sending the corresponding frequency hopping configuration to the terminal, such that the terminal determines, according to the corresponding frequency hopping configuration and a first frequency domain resource position before the frequency hopping, a second frequency domain resource position after the frequency hopping, and performs uplink transmission at the second frequency domain resource position.

2. The method according to claim 1, wherein the configuring a frequency hopping configuration for each configured BWP comprises:

configuring one or more different frequency hopping subband schemes for each configured BWP, each frequency hopping subband scheme comprising at least one frequency hopping subband, and the frequency hopping subbands in the same BWP are a section of continuous frequency resources in the BWP.

3. The method according to claim 2, wherein the determining, according to the configured frequency hopping configuration, a frequency hopping configuration corresponding to a BWP with which the terminal being configured currently, comprises:

in response to one frequency hopping subband scheme is configured for the BWP with which the terminal being configured currently, determining the frequency hopping subband scheme as the frequency hopping configuration corresponding to the BWP with which the terminal being configured currently;

in response to a plurality of frequency hopping subband schemes are configured for the BWP with which the terminal being configured currently, selecting one frequency hopping subband scheme from the plurality of frequency hopping subband schemes, and determining

the selected frequency hopping subband scheme as the frequency hopping configuration corresponding to the BWP with which the terminal being configured currently.

4. The method according to claim 3, wherein the sending the corresponding frequency hopping configuration to the terminal comprises:

generating first indication information, wherein the first indication information comprises the frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently; and

sending the first indication information to the terminal, such that the terminal obtains the frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently according to the first indication information.

5. The method according to claim 2, further comprising:

generating frequency hopping configuration information, wherein the frequency hopping configuration information comprises the one or more different frequency hopping subband schemes configured by the base station for each configured BWP; and

sending the frequency hopping configuration information to the terminal, such that the terminal obtains, according to the frequency hopping configuration information, the one or more different frequency hopping subband schemes configured by the base station for each configured BWP.

6. The method according to claim 5, wherein the sending the corresponding frequency hopping configuration to the terminal comprises:

generating second indication information, wherein the second indication information comprises a frequency hopping subband scheme identifier, and the frequency hopping subband scheme identifier is an identifier of the frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently; and

sending the second indication information to the terminal, such that the terminal obtains the frequency hopping subband scheme identifier according to the second indication information, and determines, according to the frequency hopping subband scheme identifier, the frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently.

7. The method according to claim 1, wherein the configuring a frequency hopping

configuration for each configured BWP, comprises:

configuring one or more different specified frequency hopping offsets for each configured BWP.

8. The method according to claim 7, wherein the determining, according to the configured frequency hopping configuration, a frequency hopping configuration corresponding to a BWP with which the terminal being configured currently, comprises:

in response to one specified frequency hopping offset is configured for the BWP with which the terminal being configured currently, determining the frequency hopping offset as the frequency hopping configuration corresponding to the BWP with which the terminal being configured currently; and

in response to a plurality of specified frequency hopping offsets are configured for the BWP with which the terminal being configured currently, selecting one specific frequency hopping offset from the plurality of specified frequency hopping offsets, and determining the selected frequency hopping subband scheme as the frequency hopping configuration corresponding to the BWP with which the terminal being configured currently.

9. The method according to claim 8, wherein the sending the corresponding frequency hopping configuration to the terminal, comprises:

generating third indication information, wherein the third indication information comprises the specified frequency hopping offset corresponding to the BWP with which the terminal being configured currently; and

sending the third indication information to the terminal, such that the terminal obtains, according to the third indication information, the specified frequency hopping offset corresponding to the BWP with which the terminal being configured currently.

10. A frequency hopping configuration method, wherein the method is applied in a terminal, and the terminal is configured, by a base station, at least one bandwidth part (BWP), the method comprising:

receiving a frequency hopping configuration sent by the base station, wherein the frequency hopping configuration is a frequency hopping configuration configured by the base station for a BWP with which the terminal being configured currently;

in response to performing uplink transmission frequency hopping, determining,

according to the frequency hopping configuration and a first frequency domain resource position before the frequency hopping, a second frequency domain resource position after the frequency hopping; and

performing uplink transmission at the second frequency domain resource position.

11. The method according to claim 10, wherein the receiving a frequency hopping configuration sent by the base station, comprises:

receiving first indication information sent by the base station, wherein the first indication information comprises a frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently, the frequency hopping subband scheme comprises at least one frequency hopping subband, and the frequency hopping subbands in the same BWP are a section of continuous frequency resources in the BWP; and

obtaining the frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently according to the first indication information.

12. The method according to claim 10, further comprising:

receiving frequency hopping configuration information sent by the base station, wherein the frequency hopping configuration information comprises one or more different frequency hopping subband schemes configured by the base station for each configured BWP, each of the frequency hopping subband schemes comprises at least one frequency hopping subband, and the frequency hopping subbands in the same BWP are a section of continuous frequency resources in the BWP; and

obtaining, according to the frequency hopping configuration information, the one or more different frequency hopping subband schemes configured by the base station for each configured BWP.

13. The method according to claim 12, wherein the receiving a frequency hopping configuration sent by the base station, comprises:

receiving second indication information sent by the base station, wherein the second indication information comprises a frequency hopping subband scheme identifier, and the frequency hopping subband scheme identifier is an identifier of the frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently;

obtaining the frequency hopping subband scheme identifier according to the second indication information; and

determining, according to the frequency hopping subband scheme identifier, the frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently.

14. The method according to claim 11 or 13, wherein the determining the second frequency domain resource position after the frequency hopping according to the frequency hopping configuration and the first frequency domain resource position before the frequency hopping, comprises:

determining a first frequency hopping subband corresponding to the first frequency domain resource position according to the frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently; and

calculating the second frequency domain resource position according to the first frequency hopping subband and the first frequency domain resource position.

15. The method according to claim 14, wherein the calculating the second frequency domain resource position according to the first frequency hopping subband and the first frequency domain resource position, comprises:

calculating a mirror position of the first frequency domain resource position in the first frequency hopping subband, the mirror position being the second frequency domain resource position; or

using the first frequency hopping subband as a transmission bandwidth for uplink data transmission, and calculating the second frequency domain resource position according to information in uplink scheduling signaling sent by the base station.

16. The method according to claim 10, wherein the receiving a frequency hopping configuration sent by the base station, comprises:

receiving third indication information sent by the base station, wherein the third indication information comprises a specified frequency hopping offset corresponding to the BWP with which the terminal being configured currently; and

obtaining, according to the third indication information, the specified frequency hopping offset corresponding to the BWP with which the terminal being configured currently.

17. The method according to claim 16, wherein the determining the second frequency domain resource position after the frequency hopping according to the frequency hopping configuration and the first frequency domain resource position before the frequency hopping, comprises:

determining the second frequency domain resource position according to the specified frequency hopping offset corresponding to the BWP with which the terminal being configured currently and the first frequency domain resource position.

18. A frequency hopping configuration device, wherein the device is applied in a base station, and the base station configures at least one bandwidth part (BWP) for a terminal, the device comprising:

a configuration module configured to configure a frequency hopping configuration for each configured BWP;

a frequency hopping configuration determining module configured to, in response to instructing the terminal to perform uplink transmission frequency hopping, determine, according to the configured frequency hopping configuration, a frequency hopping configuration corresponding to a BWP with which the terminal being configured currently; and

a first sending module configured to send the corresponding frequency hopping configuration to the terminal, such that the terminal determines, according to the corresponding frequency hopping configuration and a first frequency domain resource position before the frequency hopping, a second frequency domain resource position after the frequency hopping, and perform uplink transmission at the second frequency domain resource position.

19. The device according to claim 18, wherein the configuration module comprises:

a first configuration submodule configured to configure one or more different frequency hopping subband schemes for each configured BWP, each frequency hopping subband scheme comprising at least one frequency hopping subband, and the frequency hopping subbands in the same BWP are a section of continuous frequency resources.

20. The device according to claim 19, wherein the frequency hopping configuration determining module comprises:

a first determining submodule configured to, in response to one frequency hopping subband scheme is configured for the BWP with which the terminal being configured currently, determine the frequency hopping subband scheme as the frequency hopping configuration corresponding to the BWP with which the terminal being configured currently; and

a second determining submodule configured to, in response to a plurality of frequency hopping subband schemes are configured for the BWP with which the terminal being configured currently, select one frequency hopping subband scheme from the plurality of frequency hopping subband schemes, and determine the selected frequency hopping subband scheme as the frequency hopping configuration corresponding to the BWP the terminal being configured with currently.

21. The device according to claim 20, wherein the first sending module comprises:

a first generating submodule configured to generate first indication information, wherein the first indication information comprises the frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently; and

a first sending submodule configured to send the first indication information to the terminal, such that the terminal obtains the frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently, according to the first indication information.

22. The device according to claim 19, further comprising:

an information generating module configured to generate frequency hopping configuration information, wherein the frequency hopping configuration information comprises one or more different frequency hopping subband schemes configured by the base station for each configured BWP; and

a second sending module configured to send the frequency hopping configuration information to the terminal, such that the terminal obtains, according to the frequency hopping configuration information, the one or one different frequency hopping subband schemes configured by the base station for each configured BWP.

23. The device according to claim 22, wherein the first sending module comprises:

a second generating submodule configured to generate second indication information,

wherein the second indication information comprises a frequency hopping subband scheme identifier, and the frequency hopping subband scheme identifier is an identifier of the frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently; and

a second sending submodule configured to send the second indication information to the terminal, such that the terminal obtains the frequency hopping subband scheme identifier according to the second indication information, and determine the frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently according to the frequency hopping subband scheme identifier.

24. The device according to claim 18, wherein the configuration module comprises:

a second configuration submodule configured to configure one or more different specified frequency hopping offsets for each configured BWP.

25. The device according to claim 24, wherein the frequency hopping configuration determining module comprises:

a third determining submodule configured to, in response to one specified frequency hopping offset is configured for the BWP with which the terminal being configured currently, determine this specified frequency hopping offset as the frequency hopping configuration corresponding to the BWP with which the terminal being configured currently; and

a fourth determining submodule configured to, in response to a plurality of frequency hopping subband schemes are configured for the BWP with which the terminal being configured currently, select one specified frequency hopping offset from the plurality of specified frequency hopping offsets, and determine the selected frequency hopping subband scheme as the frequency hopping configuration corresponding to the BWP with which the terminal being configured currently.

26. The device according to claim 25, wherein the first sending module comprises:

a third generating submodule configured to generate third indication information, wherein the third indication information comprises the specified frequency hopping offset corresponding to the BWP with which the terminal being configured currently; and

a third sending submodule configured to send the third indication information to the terminal, such that the terminal obtains, according to the third indication information, the

specified frequency hopping offset corresponding to the BWP with which the terminal being configured currently.

27. A frequency hopping configuration device, wherein the device is applied in a terminal, and the terminal is configured, by a base station, at least one bandwidth part (BWP), the device comprising:

a first receiving module configured to receive a frequency hopping configuration sent by the base station, wherein the frequency hopping configuration is a frequency hopping configuration configured by the base station for a BWP with which the terminal being configured currently;

a resource position determining module configured to, in response to performing uplink transmission frequency hopping, determine, according to the frequency hopping configuration and a first frequency domain resource position before the frequency hopping, a second frequency domain resource position after the frequency hopping; and

an uplink transmission module configured to perform uplink transmission at the second frequency domain resource position.

28. The device according to claim 27, wherein the first receiving module comprises:

a first receiving submodule configured to receive first indication information sent by the base station, wherein the first indication information comprises a frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently, the frequency hopping subband scheme comprises at least one frequency hopping subband, and the frequency hopping subbands in the same BWP are a section of continuous frequency resource in the BWP; and

a first obtaining submodule configured to obtain the frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently according to the first indication information.

29. The device according to claim 27, further comprising:

a second receiving module configured to receive frequency hopping configuration information sent by the base station, wherein the frequency hopping configuration information comprises one or more different frequency hopping subband schemes configured by the base station for each configured BWP, each of the frequency hopping subband

schemes comprises at least one frequency hopping subband, and the frequency hopping subbands in the same BWP are a section of continuous frequency resources in the BWP; and

an obtaining module configured to obtain one or more different frequency hopping subband schemes configured by the base station for each configured BWP from the frequency hopping configuration information.

30. The device according to claim 29, wherein the first receiving module comprises:

a second receiving submodule configured to receive second indication information sent by the base station, wherein the second indication information comprises a frequency hopping subband scheme identifier, and the frequency hopping subband scheme identifier is an identifier of the frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently;

a second obtaining submodule configured to obtain the frequency hopping subband scheme identifier according to the second indication information; and

a frequency hopping scheme determining submodule configured to determine, according to the frequency hopping subband scheme identifier, the frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently.

31. The device according to claim 28 or 30, wherein the resource position determining module comprises:

a frequency hopping subband determining submodule configured to determine a first frequency hopping subband corresponding to the first frequency domain resource position according to the frequency hopping subband scheme corresponding to the BWP with which the terminal being configured currently; and

a first calculation submodule configured to calculate the second frequency domain resource position according to the first frequency hopping subband and the first frequency domain resource position.

32. The device according to claim 31, wherein the first calculation submodule comprises:

a second calculation submodule configured to calculate a mirror position of the first frequency domain resource position in the first frequency hopping subband, the mirror position being the second frequency domain resource position; or

a third calculation submodule configured to use the first frequency hopping subband as a transmission bandwidth for uplink data transmission, and calculate the second frequency domain resource position according to information in uplink scheduling signaling sent by the base station.

33. The device according to claim 27, wherein the first receiving module comprises:

a third receiving submodule configured to receive third indication information sent by the base station, wherein the third indication information comprises a specified frequency hopping offset corresponding to the BWP with which the terminal being configured currently; and

a third obtaining submodule configured to obtain the specified frequency hopping offset corresponding to the BWP with which the terminal being configured currently according to the third indication information.

34. The device according to claim 33, wherein the resource position determining module comprises:

a resource position determining submodule configured to determine the second frequency domain resource position according to the specified frequency hopping offset corresponding to the BWP with which the terminal being configured currently and the first frequency domain resource position.

35. A non-transitory computer-readable storage medium, wherein a computer program is stored on the storage medium, and wherein the computer program is configured to execute the frequency hopping configuration method according to any one of claims 1-9.

36. A non-transitory computer-readable storage medium, wherein a computer program is stored on the storage medium, and wherein the computer program is configured to execute the frequency hopping configuration method according to any one of claims 10-17.

37. A frequency hopping configuration device, wherein the device is applied in a base station, the base station configures at least one bandwidth part (BWP) for a terminal, the device comprising:

a processor; and

memory for storing instructions executable by the processor;

wherein the processor is configured to:

configure a frequency hopping configuration for each configured BWP;

in response to instructing the terminal to perform uplink transmission frequency hopping, determine, according to the configured frequency hopping configuration, a frequency hopping configuration corresponding to a BWP with which the terminal being configured currently; and

send the corresponding frequency hopping configuration to the terminal, such that the terminal determines, according to the corresponding frequency hopping configuration and a first frequency domain resource position before the frequency hopping, a second frequency domain resource position after the frequency hopping, and performs uplink transmission at the second frequency domain resource position.

38. A frequency hopping configuration device, wherein the device is applied in a terminal, and the terminal is configured, by a base station, at least one bandwidth part (BWP), the device comprising:

a processor; and

memory for storing instructions executable by the processor;

wherein the processor is configured to:

receive a frequency hopping configuration sent by the base station, wherein the frequency hopping configuration is a frequency hopping configuration configured by the base station for a BWP with which the terminal being configured currently;

in response to performing uplink transmission frequency hopping, determine, according to the frequency hopping configuration and a first frequency domain resource position before the frequency hopping, a second frequency domain resource position after the frequency hopping; and

perform uplink transmission at the second frequency domain resource position.