

PATENT SPECIFICATION

(11)

1 582 456

1 582 456

(21) Application No. 14035/77 (22) Filed 2 April 1977 (19)

(23) Complete Specification filed 15 Sept. 1977

(44) Complete Specification published 7 Jan. 1981

(51) INT. CL.³ H04Q 11/04

(52) Index at acceptance

H4K 1L 1U1 1U7 TH

(72) Inventors ALEXANDER SCHRODER PHILIP,

STEPHEN NIEWIADOMSKI,

FREDERICK HENRY REES

and ANTHONY ERNEST SHUTTLEWORTH



(54) IMPROVEMENTS IN OR RELATING TO DIGITAL TELECOMMUNICATION SWITCHING SYSTEMS

(71) We, THE PLESSEY COMPANY LIMITED, of Vicarage Lane, Ilford, Essex IG1 4AQ, STANDARD TELEPHONES & CABLES LIMITED, of 190 Strand, London, W.C.2 and THE GENERAL ELECTRIC COMPANY LIMITED, of 1 Stanhope Gate, London W1A 1EH, all British Companies, do hereby declare the invention, for which we pray that a patent may be granted to us, and the method by which it is to be performed, to be particularly described in and by the following statement:—

The present invention relates to telecommunications systems employing digital switching and is more particularly concerned with the provision of security arrangements involving cross-office path duplicated connections for use in such systems.

The switching networks used in telecommunication exchanges which handle digital data transmission carrying connections (such as pulse code modulation handling connections) are organised in accordance with so-called time division switching involving both time and space division switching techniques. Security in such switching networks is always a significant problem because of the high traffic carried by the time-shared highways and switching stages constituting the switching network. Schemes have been proposed in the prior art in which "M in N" types of sparing are provided for the various component parts of the switching network. However, such procedures pose severe problems of cabling and timing between main and spare units and add appreciably to the complexity of switch path selection arrangements.

To overcome such problems it has been suggested that the trunking in a digital switching network should be completely duplicated between the exchange receive and transmit transmission interfaces and it is an

aim of the present invention to provide arrangements in the exchange transmission interfaces which exploit the provision of the duplicated switching planes to enhance the information handling security of the exchange.

According to the invention there is provided a digital switching exchange handling digital information samples in time division multiplex form carried by incoming and outgoing exchange junction paths, the exchange comprising a receive interface for each incoming junction path and a transmit interface for each outgoing junction path and first and second time division multiplex switching networks, each network providing selectable connection between any one of the receive interfaces and any one of the transmit interfaces on a time division multiplex basis and each receive interface is arranged to generate an error indicating code for each information sample received and to pass each information sample accompanied by its error indicating code to both the first and second switching networks and each transmit interface is arranged to compare each sample received from the first switching network with that received from the second switching network and when the samples differ to use the error detecting codes of each sample to decide which sample should be used for transmission over the outgoing exchange junction path served by the transmit interface.

Each transmit interface, according to a feature of the invention, includes alarm indicating means arranged to signal to an exchange common control device the detection of each information sample corrupted by its passage through a switching network and when the number of corruptions signalled from one of the switching networks exceeds a predetermined threshold the common control device causes the transmit interfaces to

be biased to accept only information samples from the other switching network.

One embodiment of the invention will now be described with reference to the accompanying drawings which, at fig. 1, shows an abbreviated block diagram of a digital switching exchange having a switchblock of the type shown in fig. 2 which incorporates a digital line termination unit of the type shown in fig. 3.

A digital switching exchange subsystem DSS suitable for use with one embodiment of the invention is shown in fig. 1 and it comprises a combination of hardware and software modules which provide a general purpose switching facility.

The subsystem (DSS) provides full accessibility between any two channels terminating on its switchblock SB and it is arranged to grow smoothly over a range of conversational traffic capacities. Interruptions of service due to exchange extension are avoided by the use of a facility which allows one of a pair of duplicated switchblock planes to be "biased" to carry all calls.

The Digital Switching Subsystem switchblock, (SB) belongs to the Time-Space-Time, or so-called T-S-T, family. Specifically, segmentation of the central space stage results in a T(s)S(s)T format. The (s) component denotes an access mechanism between T stages and the central space switch (S) segments. Quality of service characteristics appropriate to the multiplexed nature of the traffic are satisfied by duplication of switching planes of the switchblock.

The subsystem DSS maintains a record of the busy/free state of each of its internal paths and in addition to selecting, setting up and clearing down connections, it is capable of tracing, busyng and reserving paths.

Switching is performed with reference to a local timebase originated by a Timing Unit located in the Network Synchronisation Subsystem and supplied via the digital switching subsystem waveform generator (WG).

All bit streams terminating on the subsystem DSS are frame aligned external to the basic switching mechanism. Alignment-induced information loss occurs in integral frame units. The subsystem is responsible for insertion of all outgoing synchronisation patterns and additionally transmits idle codes to free lines.

The main switchblock SB also fulfils the role of an access switch, making connections to tone, signalling, maintenance, and other auxiliary units on a semi-permanent or call-by-call basis.

The subsystem DSS as mentioned previously is formed of a number of modules. These modules are shown in fig. 1 and comprise a digital distribution frame (DDF), a switchblock module (SB), a control hard-

ware module (CH), a waveform generator module (WG) and an error rate monitor module (ERM) together with a control software module (CS).

The switchblock SB consists of three modules shown in fig. 1 as a digital line termination module DLT, a time switch TS and a space switch module SS.

Fig. 2 shows the constitution of a typical switchblock SB in more detail. Two planes of T(s)-S(s)-T switching SP1 and SP2 are employed in the switchblock SB, however, only one such plane SP1 is shown in detail fig. 2. The second plane SP2 is arranged to include identical modules to those shown in SP1 of Fig. 2. Each plane comprises a number of receive time switches RTSA1 to RTSXN, a space switching network array involving an (s)-S-(s) configuration together with a number of transmit time switches TTSA1 to TTAXN. The (s) sections are provided by the receive primary switches RPSA-RPSX and the transmit primary switches TPSA to TPSX. The central S section is formed by matrices SMA and SMX.

The time switching module TS is shown in fig. 1 as being fed, from a data point of view, on one side by the digital line termination modules DLT and on the other side by the space switching module SS. The actual sub-sections used to form the time switching module TS comprise the receive time switches (RTSA1-RTSXN in fig. 2), the transmit time switches (TTSA1-TTAXN in fig. 2) and the control stores (CONT STS). The control store arrangement CONT STS is also used to provide the addressing information for the space switch columns allowing the passage of a demultiplexed channel across the switching network into a selected location in a transmit time switch store. The transmit time switch location is selected under the control of information held in the control store arrangement also.

The control store arrangement comprises one control store for each receive time switch. Each control store is formed of 512 locations each location being of 21 bits. Each location is allocated to a cross-office slot and stores a receive time switch address and a transmit time switch address together with a call status code.

Each receive time switch, such as RTSA, comprises a serial-to-parallel conversion logic and a receive speech store RSSA having 512 locations of 9 bits per location and serving the receive paths of a group of up to 16 balanced aligned thirty two channel p.c.m. systems emanating from the corresponding digital line termination module overleads RSGA1 to 16. The information is written a channel at a time as it occurs into the receive speech store and it is extracted in parallel form (i.e. eight bits plus parity) 130

under the control of the receive time switch control store CONT STS. Each receive speech store (such as RSSA) includes an output buffer BOA which provides duplicated outputs to the 2x2 space switching stage RPSA which operates on its input at twice the receive system p.c.m. bit rates.

Each transmit speech store (such as TSSA) comprises a 512 location store having 9 bits for each location and includes an input selector TSELA, forming the 2x2 space switch TPSA.

The input selector TSELA and the "write" store addressing are controlled by address information from the corresponding control store (such as CONT STS).

Each control store (CONT STS) as previously mentioned has one location for each cross-office slot on an exchange highway and the information to select the receive speech store to the transmit speech store for each cross-office slot is programmed into the control store when a connection is set up by way of the input/output logic such as I/O CLA. The cross-office slot address information is computed in the central control units of the hardware control module CH fig. 1.

Each digital line termination unit DLT provides a number of basic line termination activities segregated into four circuit elements in a receive section (RS in Fig. 3) and two circuit elements in a transmit section TS. These activities will be considered briefly below relative to the referenced blocks of fig. 3.

R1.CR/LCD

This circuit provides a clock recovery and line code conversion function. The recovered clock RECL provides a clock drive for the rest of the receive section whereas the link code conversion changes the HDB3 line signal to pure binary code. The line code decoder also includes a line fail alarm (signal LF) generator.

R2.SS&R

This circuit provides for synch. searching and recovery after the loss of a single frame synchronisation pattern is detected (signal ERR) or when a total loss of frame synchronisation is detected (signal LS). The synch. search and recovery circuit is also used to detect an alarm from the remote terminal (signal AFR).

R3.RDSFD

This circuit is used to detect a remote digital section failure which is the detection of no information being received (i.e. a good line signal carrying a frame synchronisation pattern but no information in any time slot).

R4.ALG

This circuit provides frame alignment between the local and remote clocks and alignment induced information loss is arranged to occur in integral frame units.

T1.S.I.

This circuit is used to insert remote alarm signals into time slots when instructed by the common control over lead ATRPU or from the alarm encoder AE over lead ATRE.

T2.LCE

This circuit is used to encode the binary samples passed from the transmit time switch stores into the HDB3 line transmission code.

In addition to the basic line termination activities the DLT plays an important role in the switch assembly mechanism.

Following frame alignment, the DLT inserts parity on the received speech samples using a parity bit generator PI before feeding switch planes at RTSP1 and RTSP2. The transmit part of the DLT function refers to the outgoing parity state at parity check circuits PCP1 and PCP2 to decide which security plane TTSP1 or TTSP2 of the switch should provide an output through the plane selectors PS to the transmit line system via LCE.

The security plane selection will be performed in a channel conscious manner for each 32-channel transmit multiplex. Where the choice to be made on a permultiplex basis, the broadcasting of a fault from the receive side of the trunking could rapidly affect many or all the transmit selectors putting one complete transmit plane out of service. There would then be a significant probability of an unacceptable fault incidence in the remaining plane.

The selector on a transmit 32-channel multiplex will only adopt a continuous preference under the control of the security plane changeover signal SPCO for one plane if the error rate monitor indicates a regular fault incidence on a significant proportion of channels from the other plane. This fault threshold will be presettable to a level which will be determined by experience of prototype equipments.

Locking of the selector to one plane can also be used as an aid to maintenance and extension operations.

Also included in the Digital Line Termination Function is data comparison of the samples emerging from the two security planes TTSP1 and TTSP2 using comparator COMP. This detects the convergence of two different (but parity-correct) paths on one outlet channel.

The various alarm conditions detected by the parity check circuits PCP1 and PCP2 and the comparator COMP are passed to

the alarm encoder AE. This encoder produces encoded alarm signals on leads EAS and these signals may be priority encoded according to the significance of the fault to the performance of the switchblock.

Typically the parity generator and parity check circuits use integrated circuit devices of the type produced by Texas Instruments Ltd. under the trade name SN74180 whereas the comparator use devices having the trade name SN7485. Obviously alternative devices providing the same function could be employed. Further embodiment of the invention has been described with reference to a digital switching arrangement using a time-space-time switching network having a particular space switch configuration. It will be apparent to those skilled in the art that alternative switching networks handling time division multiplex channels could readily be employed.

WHAT WE CLAIM IS:—

1. A digital-switching telecommunications exchange handling digital information samples in time division multiplex form carried by incoming and outgoing junction paths, the exchange comprising a receive interface for each incoming junction path and a transmit interface for each outgoing junction path and first and second time division multiplex-switching networks, each network providing selectable connection between any one of the receive interfaces and any one of the transmit interfaces on a time division multiplex basis and each receive interface includes error code generating means arranged to generate an error indicating code for each information sample received and to pass each information sample accompanied by its error indicating code to both the first and second switching networks and each transmit interface includes comparison means arranged to compare each sample received from the first and second switching network and when the samples differ, the error detect-

ing codes of each sample are tested to decide which sample should be used for transmission over the outgoing exchange junction path served by the transmit interface.

2. A digital-switching telecommunications exchange according to claim 1 in which each transmit interface includes alarm indicating means arranged to send signals to an exchange common control device indicative of the detection of a corrupted information sample and each transmit interface includes means for biasing the transmit interface to accept only information samples from one of the switching networks.

3. A digital-switching telecommunications exchange according to claim 1 or 2 in which the error code generating means is a parity generator and each sample is accompanied by a parity bit.

4. A digital-switching telecommunications exchange according to claim 3 in which each transmit interface includes first and second parity checking arrangements to which each sample and parity bit from the first and second switching network respectively is applied.

5. A digital-switching telecommunications exchange according to any one of the preceding claims in which each receive interface includes means for generating line fault condition and synchronisation failure alarm signals for communication to the common control device.

6. A digital-switching telecommunications exchange according to any one of the preceding claims in which each transmit interface includes means for inserting alarm signals into selected outgoing time division multiplex channels.

7. A digital-switching telecommunications exchange substantially as described with reference to and as shown in the accompanying drawings.

For the Applicants:

R. J. HART,

Chartered Patent Agent.

Printed for Her Majesty's Stationery Office by Burgess & Son (Abingdon), Ltd.—1981.
Published at The Patent Office, 25 Southampton Buildings, London, WC2A 1AY,
from which copies may be obtained.

the alarm encoder AE. This encoder produces encoded alarm signals on leads EAS and these signals may be priority encoded according to the significance of the fault to the performance of the switchblock.

Typically the parity generatory and parity check circuits use integrated circuit devices of the type produced by Texas Instruments Ltd. under the trade name SN74180 whereas the comparator use devices having the trade name SN7485. Obviously alternative devices providing the same function could be employed. Further embodiment of the invention has been described with reference to a digital switching arrangement using a time-space-time switching network having a particular space switch configuration. It will be apparent to those skilled in the art that alternative switching networks handling time division multiplex channels could readily be employed.

WHAT WE CLAIM IS:—

1. A digital-switching telecommunications exchange handling digital information samples in time division multiplex form carried by incoming and outgoing junction paths, the exchange comprising a receive interface for each incoming junction path and a transmit interface for each outgoing junction path and first and second time division multiplex switching networks, each network providing selectable connection between any one of the receive interfaces and any one of the transmit interfaces on a time division multiplex basis and each receive interface includes error code generating means arranged to generate an error indicating code for each information sample received and to pass each information sample accompanied by its error indicating code to both the first and second switching networks and each transmit interface includes comparison means arranged to compare each sample received from the first and second switching network and when the samples differ, the error detect-

ing codes of each sample are tested to decide which sample should be used for transmission over the outgoing exchange junction path served by the transmit interface.

2. A digital-switching telecommunications exchange according to claim 1 in which each transmit interface includes alarm indicating means arranged to send signals to an exchange common control device indicative of the detection of a corrupted information sample and each transmit interface includes means for biasing the transmit interface to accept only information samples from one of the switching networks.

3. A digital-switching telecommunications exchange according to claim 1 or 2 in which the error code generating means is a parity generator and each sample is accompanied by a parity bit.

4. A digital-switching telecommunications exchange according to claim 3 in which each transmit interface includes first and second parity checking arrangements to which each sample and parity bit from the first and second switching network respectively is applied.

5. A digital-switching telecommunications exchange according to any one of the preceding claims in which each receive interface includes means for generating line fault condition and synchronisation failure alarm signals for communication to the common control device.

6. A digital-switching telecommunications exchange according to any one of the preceding claims in which each transmit interface includes means for inserting alarm signals into selected outgoing time division multiplex channels.

7. A digital-switching telecommunications exchange substantially as described with reference to and as shown in the accompanying drawings.

For the Applicants:

R. J. HART,
Chartered Patent Agent.

