

DATA TRANSFER METHODBACKGROUND OF THE INVENTION1. Field of the Invention

This invention relates the field of communications media for transferring data between a source and a plurality of peripheral devices coupled to the source. More particularly, the present invention relates to data transfer along a peripheral device bus between a plurality of peripheral devices and a host computer.

2. Art Background

In the computing industry, it is quite common to transfer data and commands between a plurality of data processing devices, such as for example, computers, printers, memories and the like. The interconnection of computers and other peripheral devices principally developed in the early 1970's with the advent of computer networking systems, which permitted the distribution of access to computing resources beyond the immediate proximity of a main frame computer.

Networks, such as the ARPA network, were developed to provide access by various users to large time-sharing systems and the transfer of data between such systems. In the case of geographically local networks, so-called "local area networks" (LANs) were developed to connect together a collection of computers, terminals and peripherals located, typically in the same building or adjacent buildings, and permitted each of these devices to communicate among themselves or with devices attached to other networks. Local area networks permit the implementation of distributed computing. In other words, some of the devices coupled to the local area network may be dedicated to perform specific functions, such as file storage, data base management,

terminal handling, and so on. By having different machines perform different tasks, distributed computing can make the implementation of the system simpler and more efficient.

Presently, networking has only been applied to provide communications between data processing devices, which are machine input devices. However, it would also be useful to provide a networking means to provide communication between a single computer and a plurality of peripheral devices such as human input devices, listen only devices, appliances, etc. Human input devices include keyboards, cursor control devices (such as a "mouse"), and sketch pads, etc. Listen only devices include transaction logs, etc. In the prior art, such devices are attached to a host computer through a port dedicated to each device. Often, additional "cards" are required to allow a peripheral input device to be added. Further, the addition of cards requires that the host computer be powered down, with no mechanism for adding peripheral devices to a live system. Such prior art systems are inefficient since peripheral devices are not generally operated simultaneously. (for example, someone using a mouse is generally not using the keyboard or sketchpad at the same time). Thus, the devices could share a common line to the host computer without creating data traffic problems, eliminating the need for cards.

Prior art networking schemes also include elaborate methods for establishing control of the network to allow a device to transmit. Such systems are not needed for networking of peripheral devices, since only one is generally used at a time. In addition, prior art networking schemes provide for means for attached devices to identify themselves to each other through

elaborate "handshaking" schemes. Again, such complexity is not required to connect peripheral devices since there is no need for these devices to identify themselves to other devices, only to the host computer.

5

According to the present invention there is provided a method for transferring signals and data, wherein the signals and data are transferred under the control of a host computer between the host computer and first and second peripheral devices, wherein the signals and data are transferred over a bus coupling the first and second peripheral devices to the host computer, and wherein the first and second peripheral devices have a same first address, comprising the steps of:

the host computer initially activating the first peripheral device by transmitting over the bus (1) the first address of the first peripheral device and (2) a signal that matches a first number stored as an extended address of the first peripheral device;

after the first peripheral device is activated, the host computer sending a command over the bus to the first address of the first peripheral device, wherein the first peripheral device executes the command without the host computer sending the extended address of the first peripheral device;

the host computer both activating the second peripheral device and deactivating the first peripheral device by transmitting over the bus a second number as an extended address, wherein the second number is the extended

30

35

address of the second peripheral device, and wherein the second number is different from the first number:

after the second peripheral device is activated, the host computer sending a command over the bus to the first address of the second peripheral device, wherein the second peripheral device executes the command without the host computer sending the extended address of the second peripheral device.

5

10

15

20

25

30

35

BRIEF DESCRIPTION OF THE DRAWINGS

Figure 1 is block diagram illustrating the networking system of the present invention.

Figure 2 is a timing diagram illustrating the present
5 invention's use of return to zero encoding.

Figure 3 illustrates a register of a peripheral device of the present invention.

Figure 4 is a flow chart illustrating the sequence of operations utilized by a peripheral device to request service by
10 the host computer.

Figure 5 is a flow chart illustrating the sequence the operations utilized to provide new addresses to devices sharing the same hard-wired address.

Figure 6 is a timing diagram illustrating a command
15 transaction of the present invention.

DETAILED DESCRIPTION OF THE INVENTION

A peripheral device bus including apparatus and methods for transferring data between a plurality of peripheral devices coupled to a host computer is disclosed. In the following
5 description numerous specific details are set forth, such as specific numbers, registers, addresses, times, signals, and formats, etc., in order to provide a thorough understanding of the present invention. However, it will be apparent to one skilled in the art that the present invention may be practiced
10 without these specific details. In other instances, well-known circuits and devices are shown in block diagram form in order not to unnecessarily obscure the present invention.

Referring to Figure 1, the preferred embodiment of the present invention may be seen. A plurality of peripheral
15 devices, generally identified by numbers 11 through 16 are coupled through a single cable 17 to a host computer 10. In the preferred embodiment, all devices communicate with the host computer by a mini-phono jack with the following connector assignments; tip-power, ring-data, sleeve-power return. A "high"
20 signal (1) is 2.4 volts minimum. A "low" signal (0) is .8 volts maximum. Although a single cable is contemplated in the preferred embodiment of the present invention, other communications media, such as broad band methods, fiber optic systems, and infrared signals, are contemplated.

25 The bus of the present invention supports coded devices, (for which a keystroke represents a symbol or a function, such as a keyboard 14), relative devices, (in which movement of a display cursor in response to a control device, such as a mouse 11 or 12, may be from any starting point), and absolute devices

(for which there is a constant and direct relationship between display position and device position, such as sketch pad 13).

The system also permits the networking of extended address devices. Extended address devices share a common hard wired address 35, but further include an address unique to the individual device which the host computer must recognize before the device can be accessed. For example, it is contemplated that appliances may be coupled to the host computer and controlled by the host computer. In such a situation, all appliances would have an identical hardwired fixed address. The host computer, on a first level, would simply address the hard wired address for appliances. At this time, all appliances coupled to that address are inactive. An individual appliance may be activated by the host computer if the host computer sends a signal to that appliance which matches the extended address of the appliance. An extended address is an individual identification number, which, in the preferred embodiment, may be up to 64 bytes long. Once the host computer has provided the extended address, the device having that address is active. Subsequent commands to the appliance address location will be executed by that device without the need for providing the extended address each time. An activated appliance will respond to all commands to the appliance address, while unactivated devices remain passive. To deactivate an active extended address device, the host computer provides the extended address of another extended address device, activating it and deactivating the previously active device. It is contemplated that any device which could be controlled by the host computer is suitable for the present networking scheme, such as lights, ovens, sprinkler systems, phone answering machines,

etc. It is contemplated that at least one other hardwired address for extended address devices be provided in the present system. Such an address would be used for system protection schemes or user identification schemes. For example, a device at
5 this location could contain an extended address which must be provided by the system user before the system could be enabled. In other instances, individual operations could require that the extended address of other security devices be provided by the host computer prior to performance. Such security devices could
10 function as "keys" to lock the entire system or certain operations performed on the system.

Also reserved for use on the network of the present invention are soft address locations 16. Soft address locations are reserved for duplicates of peripheral devices coupled to the
15 bus. When more than one mouse is coupled to the bus, for example, the host computer assigns new addresses to each mouse, those addresses being at the soft address locations.

Although specific examples have been given for each type of device coupled to the bus, there may be more than one kind of
20 each type of device with that address. For example, a sketch pad has been given as an absolute device but a touch screen would also be considered an absolute device and be assigned the same fixed command address as the sketch pad. In those situations, the host computer will assign new addresses from the soft address
25 locations to each device.

In the preferred embodiment of the present invention, the various peripheral devices have been assigned addresses as shown below:

	<u>Address</u>	<u>Device Types</u>	<u>Example</u>
5	0000 (zero)	extended address device	security systems, user ID
	0001 (one)	extended address device	appliances
	0010 (two)	coded devices	keyboard
10	0011 (three)	relative devices	mouse, track ball
	0100 (four)	absolute devices	sketchpad, touch screen
	0101 (five)	reserved	none
15	0110 (six)	reserved	none
	0111 (seven)	reserved	none
	1000 (eight)	soft addressed	duplicate peripheral devices
20			
			
	1111 (15)	soft addressed	duplicate peripheral devices

It will be appreciated by one skilled in the art that other addresses may be assigned to these devices containing more or less bits than in the preferred embodiment. Fixed hard-wired addresses 31, 32, 33 and 34 are shown in Fig. 1 for mouse 11, mouse 12, sketch pad 13 and keyboard 14 respectively.

All peripheral devices have four registers in the preferred embodiment to receive data and send data. For each device, register 3 talk and register 3 listen have status information such as device address and handler information. The remaining registers are data registers which are device specific except

register 2 listen which contains the extended addresses for extended address devices or device specific contents for soft addressed devices.

5 In the preferred embodiment of the present invention, there are three types of communication on the peripheral bus: commands, data and global signals. Commands are sent from the host computer to the peripheral devices, data is sent from the host computer to the devices or from the devices to the host computer, and global signals are special messages sent to the entire system.

10 In the preferred embodiment data is encoded as the ratio of low time to high time of each bit cell. A bit cell boundary is defined by a falling edge on the bus. A "zero" is encoded as a bit cell in which the low time is greater than the high time. This is shown in Figure 2 by bit cell 20. Therefore, a "1" is defined as a bit cell in which the low time is less than the high time as shown by cell 21 of Figure 2. In the present preferred embodiment, a start bit is defined as a "1". A stop bit is a "0" which does not have an additional falling edge to define the bit cell time. The stop bit is used to synchronize the stopping of transactions on the bus.

20 The period for each bit cell of command signals and low speed data transmission is approximately 100 microseconds plus or minus 30%. For high speed data transmission, the bit cell is 50 microseconds plus or minus 1%. The format of a data transaction is a start bit (1), followed by up to 256 bits of data and ending with a stop bit. It will be appreciated that when other communications media are utilized, other signaling methods may be utilized.

Commands are sent only by the host. In the preferred embodiment of the present invention, there are three commands; talk, listen, and flush. As shown in Figure 6, to signal the start of a command, an attention pulse is sent out. An attention pulse is generated by the host computer by transmitting a bus low for a period of "T-attn". In the preferred embodiment, T-attn is approximately 560-1040 microseconds. The attention pulse is followed by a synch pulse to give the initial bus timing. The following edge of the synch pulse is used as a timing reference for the first bit of the command. The command is followed by a stop bit, (in the preferred embodiment a "0"). After the stop bit, the bus returns to its normally high state unless a device requests service.

The command is an 8 bit value in the preferred embodiment. The command includes a 4 bit device address field which specifies the fixed hardwired address of the desired peripheral device (e.g., 0011 for a mouse). The next 2 bits form the command and the final 2 bits form a registered address field which allows a specific register, R0-R3 within an addressed peripheral device to be specified. In the preferred embodiment, the commands have the following bit code:

	<u>Command</u>	<u>Code</u>
	Flush	01
	Listen	10
25	Talk	11

The talk command orders the addressed device to provide its data to the host computer. The listen command orders the addressed device to accept data from the host computer and place it in one of its registers. The flush command has an effect on

each device which is defined by the individual device. It can be used for such functions as clearing a register or resetting all keys on a keyboard so that they will be sent again.

When a peripheral devices is addressed to talk, it must
5 respond within a certain period, called the "time out" period. The time out, "Tlt", is approximately 140 to 260 microseconds (2 bit cells). The selected device, if it does not time out, becomes active on the bus and performs its data transaction, and then "untalks" itself and goes inactive on the bus.

10 Global signals are used for transactions which are neither commands nor data transactions. Global signals include: attention and synch, which is used to signal the start of a command and to give initial bus timing; service request, a transaction that devices use to signal the host that they require
15 service; and reset, used to issue a break on the bus by holding the bus low for a minimum of "Tres", which is approximately 2.8 to 5.2 milliseconds, (40 bit cells). Global signals will be described in more detail in conjunction with other transactions.

Since a peripheral device can only send data when it has
20 been commanded to talk by the host computer, the present system provides a means for a device to notify the host computer that it needs servicing. This is accomplished by having the device send a service request signal to the host computer. In the present invention, a service request is sent by holding the
25 bus low after the stop bit of any command transaction. Each of the peripheral devices coupled to the bus include a number of registers (in the preferred embodiment four registers). Figure 3 shows one of the registers for a peripheral device. Bit A13 has been identified as the service request enable bit. When this bit

is set high by the host computer, the device is enabled to hold the bus low after the stop bit of a command transaction, as shown in Figure 6, if the device needs service. A device will keep requesting service until it receives a talk command from the host. The flow chart in Figure 4 shows the steps followed by a device requiring service.

Initially the device determines if it requires servicing, that is, if it has data to send to the host. If it does, it sets an internal flag bit. When the next command is sent out from the host, the device checks to see if the command is addressed to the device. If the command was not addressed to the device, the device checks to see if its service request enable bit, (bit A13 of register 3), is set high. If so, it holds the bus low after the command stop bit. (See Fig. 6) The device then waits until the next command is received from the host to see if it will be addressed to talk. If the command is addressed to the device, the device determines if it is a command to talk. If it is not a command to talk the device sends a service request, performs whatever command is instructed and awaits the next command. If the command is to talk, the device sends its data and considers its service request to be satisfied. The device continues to monitor itself to determine when it needs service. By allowing the host computer to control the service request enable bit, more efficient operation of the bus is realized. When a service request is received, the host computer need only ask those devices whose service request bit was enabled whether they need servicing. Additionally, the host computer can disable certain devices that are not required for particular applications.

When sending data, the device is able to detect collisions. If a peripheral device tries to output a 1 and the data line is or goes to a 0, the device assumes it has lost a collision to another device. This means that another device is also sending
5 on the bus. When this happens the losing device untalks itself from the bus and preserves the data which was being sent for retransmission. The device sets an internal flag bit if it loses a collision. Prior art peripheral devices were unable to detect collisions. This novel feature of the present invention permits
10 more efficient operation of the communications medium. By having the device sense a collision, it can preserve the data that is transmitted and indicate to the host computer that it requires serving. Additionally, the collision detection scheme of the present invention does not require a waiting period before a
15 collision is assumed. A device will end its transmission if the line is modulated by another device or simply not begin its transmission if the line is already in use. Further, this collision detection scheme is useful in locating multiple devices at a single hardwired address location, such as mouse 11 and
20 mouse 12 of Figure 1.

In such a situation, the host will change the address of the devices by forcing a collision of devices sharing the same address. The host achieves this by issuing a talk R3 command addressed to those devices. R3 (one of the registers of the
25 device) contains the information shown in Figure 3. Bits A0 through A7 contain a device handler which tells the host computer the function of a device and the use of data provided by the device. Bits A8 through A11 are an address field which can be changed when more than one device having the same command address

is coupled to the bus. In that situation, one of the soft address locations are assigned to bits A8 through A11 which then serve as the command address for that device. Until that time, those bit locations contain a random number which aids in the
5 detection of collisions. For example, if two mice received a talk R3 command and both began talking at the same, neither would detect a collision. However, by having random numbers in the address field of register 3, the output of the two devices will eventually differ. When that occurs, one of the devices will
10 detect a collision and stop talking. Bit A12 is a high speed enable bit which if set, provides for data transmission at the higher modulation rate (50 microseconds per bit frame). The high speed enable bit is set by the host computer. If the host computer is unable to receive data at the higher modulation rate,
15 it sets the high speed enable bit low in each of the devices. If the host computer is able to accept data at the higher modulation rate, and the device is able to transmit at the higher rate, (that information being contained in the handler bits of register 3), the host computer sets the high speed enable bit high for
20 the device. As previously mentioned, bit A13 is service request enable which is set by the host to enable the device to perform a service request transaction. Bits A14 and A15 are reserved for future use and are set to 0.

When a device receives a talk R3 command the device provides
25 its status (handler and address) to the host computer. If there are two devices of the same type coupled to the bus, only one can respond since the other will detect a collision. Figure 5 shows the method of assigning new addresses on the bus.

After receiving a talk R3 signal the device sends its status from Register 3. If the line goes low, the device determines that there has been a collision, it stops sending (untalks itself) and sets an internal flag bit to indicate a collision.

- 5 The host sends a listen R3 to the mouse address. Each talk command resets the internal collision flag of the device. The device checks to see if its collision bit is set. If the collision bit is not set the device changes A8 through A11 to the soft address provided by the listen R3 command. In this manner the address of
- 10 the winning device is changed with the host computer keeping track of the new address of the device. If a collision bit is detected by the device after a listen R3 command, the device does not change the soft address bits, but may change other fields in R3. The host computer sends out another talk R3 command to see
- 15 if any devices remain at the mouse address. In this situation the remaining mouse will send its start bit, not detect a collision, and send its status from register 3. The host computer will send back a listen R3 command to the mouse address. The remaining mouse will not detect a collision bit being set in
- 20 this instance so it will change bits A8 through A11 of register 3 to the soft address received from the host computer. The host computer then sends out another talk R3 command to the mouse address. This time, since no mouse remains at that address, the bus is timed out and the host computer knows that it has assigned
- 25 new addresses to each of the mice sharing the mouse address.

In one embodiment of the present invention, peripheral devices have a device on them to indicate activity called the activator. The activator can be a special key on a keyboard or a button on a mouse. When more than one of a device is coupled to

the bus, the host computer can display a message requesting one of the devices to use the activator. The host can then issue a listen R3 command which will change the address of the device which is activated. In this manner individual devices can be
5 located and assigned new addresses in multiuser applications.

Thus, a peripheral device bus has been described which allows a plurality of peripheral devices to be coupled to a host computer through a single port.

10 The present application has been divided-out-of our co-pending U.K. patent application No. 8607632 in which there is described and claimed an apparatus for transferring signals and data, wherein the signals and data are transferred under the control of a host computer from the host computer to the first and second
15 peripheral devices and from the first and second peripheral devices to the host computer, wherein the signals and data are transferred over a bus coupling the first and second peripheral devices to the host computer, and wherein the bus is normally in a logical first state.

20 Reference is also directed to co-pending divisional applications Nos. 8912530.6 and 8912531.4, which respectively relate to a method for transferring signals and data, wherein the signals and data are transferred under the control of a host computer between the host computer and first and second peripheral devices, wherein
25 the signals and data are transferred over a bus coupling the first and second peripheral devices to the host computer, wherein the bus is normally in a logical first state, and wherein the first and second peripheral devices each initially contain the same first number as a command address for both the first and second
30 peripheral devices, and a method for requesting service by a device coupled to a host computer through a communication medium.



CLAIMS

1. A method for transferring signals and data, wherein the signals and data are transferred under the control of a host computer between the host computer and first and second peripheral devices, wherein the signals and data are
5 transferred over a bus coupling the first and second peripheral devices to the host computer, and wherein the first and second peripheral devices have a same first address, comprising the steps of:

the host computer initially activating the first
10 peripheral device by transmitting over the bus (1) the first address of the first peripheral device and (2) a signal that matches a first number stored as an extended address of the first peripheral device;

after the first peripheral device is activated, the
15 host computer sending a command over the bus to the first address of the first peripheral device, wherein the first peripheral device executes the command without the host computer sending the extended address of the first peripheral device;

the host computer both activating the second peripheral
20 device and deactivating the first peripheral device by transmitting over the bus a second number as an extended address, wherein the second number is the extended address of the second peripheral device, and wherein
25 the second number is different from the first number:

after the second peripheral device is activated, the
host computer sending a command over the bus to the first
address of the second peripheral device, wherein the
second peripheral device executes the command without the
30 host computer sending the extended address of the second peripheral device.

2. The method of claim 1 for transferring signals and data,



- 19 -

wherein at least one of the first and second peripheral devices comprises an appliance.

5 3. The method of claim 1 for transferring signals and data, wherein at least one of the first and second peripheral devices comprises a system protection device.

10
