

DESCRIPTION

Title of Invention

TRANSMISSION EQUIPMENT AND METHOD FOR SENDING
CONTROL MESSAGES

5

Technical Field

[0001] The present invention relates to a
transmission apparatus and control information
transmission method for transmitting control
10 information for resource assignment in a
multiple access wireless communication system.

Background Art

[0002] Currently, wireless mobile communication
15 systems are evolving towards the fourth
generation (i.e. 4G networks). The evolution to
4G promises substantial increase in system
requirements (e.g. an increase in the number of
users, user bandwidths, and mobility).

20 [0003] Several new technologies are planning to
be used to make possible this increase in system
requirements. One of these technologies is
orthogonal frequency division multiple access
(OFDMA), which is a wireless technique proposed
25 for WiMAX (IEEE 802.16e) and 3GPP LTE (Long Term
Evolution).

[0004] The orthogonal frequency division

multiplexing (OFDM) is a technique of multiplexing and transmitting transmission data using a plurality of subcarriers. In an OFDM system, first, a data stream is divided into several parallel sub-streams. The data rate then is lowered. That is to say, with these parallel substreams, the symbol duration increases compared to the original data stream. The plurality of parallel substreams are then modulated and later mapped on separate subcarriers.

[0005] The increased symbol duration improves the robustness of OFDM to channel delay spread. Furthermore, the introduction of cyclic prefixes (CPs) can completely eliminate inter-symbol interference as long as the CP duration is longer than the channel delay spread. In addition, OFDM modulation can be realized using the efficient inverse Fast Fourier transform (IFFT), which enables a large number of subcarriers to be provided with lower complexity.

[0006] In an OFDM communication system, resources are defined by means of OFDM symbols in the time domain or by means of subcarriers in the frequency domain. That is, OFDMA is a multiple-access scheme that makes possible multiplexing transmission by mapping data

streams from a plurality of users upon time resources and frequency resources.

[0007] For example, non-patent literature 1 discloses a conventional wireless communication apparatus that communicates using an OFDM communication scheme.

[0008] FIG.1 illustrates an example of an OFDMA frame structure. FIG.1 is an illustration of a downlink (DL) frame structure. Note that, although not shown in FIG.1, normally, there also is an uplink (UL) part as well.

[0009] With reference to FIG.1, the frame includes MAC control information 22 which carries control signal. The control signal includes, for example, scheduling information for DL data transmission, scheduling grants for UL transmission, and ACK/NACK indications in response to UL transmission. Generally, control signal is valid for the current frame only. There may, however, be additional modes of operation in which control signal is valid for multiple frames.

[0010] Control information 22 is broadcasted from a base station (BS) to all the mobile stations (MSs) connected to that BS. Each MS needs to receive and decode MAC control information 22 and then search for its own

scheduling information unit in MAC control information 22. Typically, control information 22 is broadcasted with fixed timing with respect to the frame boundaries, usually near the beginning of frame.

[0011] With reference to FIG.1, control information 22 has a plurality of scheduling information units. Each scheduling information unit is formed with an information element (IE) including an MS-ID. Each IE corresponds to a specific MS or a group of a plurality of MSs (hereinafter simply "group"). The information included in an IE is essential to determine the data transmission format. The specification of the data transmission format by an MS (or group) is essential to identify the system resources scheduled for that MS (or group) and correctly demodulate in the identified system resources. For example, referring to FIG.1, the contents of IEs 24, 26, 28 and 30 are essential to correctly demodulate in resources 32, 34, 36 and 38, respectively.

[0012] Depending on the number of target MSs, IEs categorise into three types: unicast, multicast and broadcast. A unicast IE corresponds to a single MS, a multicast IE corresponds to a predetermined number of MSs (or

group), and a broadcast IE corresponds to all MSs.

[0013] For example, like unicast IE 24 including MS-ID1, each unicast IE includes an MS-ID that uniquely identifies an MS. Some of unicast IEs may correspond to one MS in control information 22. For example, in FIG.1, two IEs 24 and 30 both correspond to the MS having MS-ID1.

[0014] Also, like multicast IE 26 including MS-ID2 and broadcast IE 28 including MS-ID3, each broadcast or multicast IE also includes an MS-ID that uniquely identifies a broadcast or multicast connection. Note that an MS has preliminarily knowledge of the group of MS-IDs for broadcast/multicast.

[0015] Each IE corresponds to a separate assignment resource area. That is, if the unit scale of assignment resource areas is determined, even when the first assignment resource area and a second assignment resource area are addressed to the same mobile station, separate IEs are provided for the first assignment resource area and the second assignment resource area, respectively. Also, this occurs at other times as well, including, for example, when the first assignment resource

area and a second assignment resource area are not consecutive, when different services are applied to the first assignment resource area and a second assignment resource area, when
5 different configuration conditions (for example, different modulation and coding schemes (MCSs)) are applied to the first assignment resource area and a second assignment resource area, and when the number of times of data retransmissions
10 is different between the first assignment resource area and a second assignment resource area.

[0016] FIG.2 illustrates an exemplary IE structure on a DL. This DL IE includes a DL
15 scheduling information unit to be used to notify an MS how to process data. In FIG.2, the IE includes MS-ID 42 which identifies the MS or group to which resource is assigned in the frame. Furthermore, the IE includes, as
20 resource-related information, an indication (that is, resource assignment information 44) of specific resource that is assigned (e.g. time resource, frequency resource, space resource, or any combination of these), and time duration 46
25 in which this assignment of specific resource is valid. The IE also includes, as information related to the data transmission format, MIMO

data 48 to indicate that the content depends on a particular MIMO scheme that is specified, modulation scheme information 50 to be applied to the assigned resource, payload size information 52, and HARQ information 54 to indicate the hybrid ARQ process of the current transmission.

[0017] In the above-described fashion, each MS or group is able to decode an IE included in MAC control information and identify the resource assigned to that MS or group according to the decoding result.

Citation List

15 Non-Patent Literature

[0018]

NPL 1

IEEE Std 802.16e-2005

20 Summary of Invention

Technical Problem

[0019] Now, IEs in MAC control information are arranged in an arbitrary order, and there may be a plurality of IEs carrying the same MS-ID. Consequently, to find out the resource corresponding to its own MS-ID, an MS has to check all the IEs in MAC control information 22.

This would result in the problems of increasing the processing time and power consumption in the MS.

[0020] Embodiments of the present invention provide a transmission apparatus and control information transmission method to reduce the processing time and power consumption at the reception side by making the reception processing at the reception side efficient.

Solution to Problem

[0020a] According to a first aspect of the present invention, there is provided a communication apparatus comprising: a generator that generates assignment information; and a transmitter that transmits the generated assignment information in a region of the assignment information, wherein the assignment information is categorized into at least multicast assignment information intended for a group of a plurality of the reception apparatuses and unicast assignment information intended for one reception apparatus, the region of the assignment information includes a first region and a second region, and a plurality of the unicast assignment information intended for one reception apparatus are present in the first

region following the second region, in which a plurality of the multicast assignment information intended for a group of a plurality of the reception apparatuses are present.

[0020b] According to a second aspect of the present invention, there is provided a communication method performed by a communication apparatus comprising: generating assignment information; and transmitting the generated assignment information in a region of the assignment information, wherein the assignment information is categorized into at least multicast assignment information intended for a group of a plurality of the reception apparatuses and unicast assignment information intended for one reception apparatus, the region of the assignment information includes a first region and a second region, and a plurality of the unicast assignment information intended for one reception apparatus are present in the first region following the second region, in which a plurality of the multicast assignment information intended for a group of a plurality of the reception apparatuses are present.

[0021] Disclosed herein is a transmission apparatus to transmit control information for resource assignment in a multiple access wireless communication system, and has: a structuring section that structures the control information; and a transmitting section that transmits the frame including the structured control information, and, in this transmission apparatus: the control information comprises a unicast area where a unicast scheduling information unit addressing one mobile station is placed, and a non-unicast area where a non-unicast scheduling information unit addressing two or more mobile stations is placed; and a scheduling information unit group to be placed in the unicast area comprises a

scheduling information unit formed with one mobile station identifier, which is identification information of a mobile station, a plurality of information elements to be transmitted to the mobile station associated with the mobile station identifier, and information about the number of the plurality of information elements.

[0022] Disclosed herein is a transmission method to transmit control information for resource assignment in a multiple access wireless communication system, and includes: a structuring step of structuring the control information; and a transmitting step of transmitting the frame including the structured control information, and, in this transmission method: the control information comprises a unicast area where a unicast scheduling information unit addressing one mobile station is placed, and a non-unicast area where a non-unicast scheduling information unit addressing two or more mobile stations is placed; and a scheduling information unit group to be placed in the unicast area comprises a scheduling information unit formed with one mobile station identifier, which is identification information of a mobile station, a plurality of information

elements to be transmitted to the mobile station associated with the mobile station identifier, and information about the number of the plurality of information elements.

Advantageous Effects of Invention

[0023] With the embodiments of the present invention, it is possible to reduce the processing time and power consumption at the reception side by making the reception processing at the reception side efficient.

Brief Description of Drawings

[0024]

FIG.1 shows an example of an OFDM frame structure;

FIG.2 shows a typical structure of a downlink information element (IE);

FIG.3 is a block diagram showing a configuration of a base station according to embodiment 1 of the present invention;

FIG.4 is a block diagram showing a configuration of a mobile station according to embodiment 1 of the present invention;

FIG.5 shows a control information structure according to embodiment 1 of the present invention;

FIG.6 shows a control information structure according to embodiment 2 of the present invention;

FIG.7 shows a control information structure according to embodiment 3 of the present invention;

FIG.8 shows a control information structure according to embodiment 4 of the present invention;

FIG.9 illustrates the system on which embodiment 5 of the present invention is based;

FIG.10 shows a control information structure according to embodiment 5 of the present invention;

FIG.11 shows a control information structure according to embodiment 6 of the present invention;

FIG.12 illustrates the system on which embodiment 7 of the present invention is based;

FIG.13 illustrates the system on which embodiment 7 of the present invention is based;

FIG.14 illustrates the system on which embodiment 7 of the present invention is based;

FIG.15 shows a control information structure according to embodiment 7 of the present invention;

FIG.16 illustrates processing in an

information processing section;

FIG.17 shows a control information structure according to embodiment 8 of the present invention; and

5 FIG.18 illustrates processing in an information processing section.

Description of Embodiments

[0025] Now, embodiments of the present invention will be described in detail below with reference to the accompanying drawings. Parts that are the same between embodiments will be assigned the same reference numerals and their descriptions will not be repeated.

15 [0026] (Embodiment 1)

[Configuration of base station]

FIG.3 is a block diagram showing a configuration of base station 100 according to embodiment 1 of the present invention. In FIG.3, base station 100 has control section 101, scheduler 102, information generating section 103, OFDM communication section 104, and information processing section 105. In this context, control section 101, scheduler 102, information generating section 103 and information processing section 105 perform MAC layer processing, and OFDM communication section

104 performs physical layer processing.

[0027] Control section 101 performs processing related to the MAC protocol.

[0028] Scheduler 102 assigns resources to a
5 communicating party, which is mobile station 200
or a group comprised of a plurality of mobile
stations 200, based on control by control
section 101. Scheduler 102 outputs the MS-ID,
which is identification information assigned to
10 mobile station 200 or group, resource assignment
information and cast identification information
(information to identify between unicast,
multicast and broadcast), to information
generating section 103.

15 [0029] Information generating section 103
generates control information to be transmitted
in a downlink using the information received
from scheduler 102. The control information
includes control signal. The control signal is,
20 for example, scheduling information related to
downlink data communication and scheduling
information related to uplink data
communication. Also, information generating
section 103 assigns, to resource corresponding
25 to a scheduling information, transmission data
addressing the MS-ID associated with that
scheduling information. To be more specific, a

scheduling information unit includes an MS-ID and resource assignment information, so that transmission data addressing this MS-ID is mapped to a resource corresponding to this resource allocation information. In this way, a scheduling information unit included in control information and transmission data are associated with each other, so that, at the reception side, it is possible to receive and process the data addressing the receiving party based on information in the control information. The structure of control information to be generated in information generating section 103 will be later described in detail.

[0030] OFDM communication section 104 performs OFDM modulation and OFDM demodulation. OFDM communication section 104 transmits a frame including control information generated in information generating section 103.

[0031] Information processing section 105 analyzes uplink information transmitted from mobile station 200, and outputs the analysis result to control section 101.

[0032] [Configuration of mobile station]

FIG. 4 is a block diagram showing a configuration of mobile station 200 according to embodiment 1 of the present invention.

Referring to FIG.4, mobile station 200 has control section 201, information generating section 202, OFDM communication section 203 and information processing section 204. In this context, control section 201, information generating section 202 and information processing section 204 perform processes related to the MAC layer, and OFDM communication section 203 performs processes related to the physical layer.

[0033] Control section 201 performs processes related to the MAC protocol.

[0034] Information generating section 202 generates information to be transmitted in an uplink based on control by control section 201. This information includes at least one of control information and transmission data.

[0035] OFDM communication section 203 performs OFDM modulation and OFDM demodulation.

[0036] Information processing section 204 analyzes downlink information transmitted from a communication party (base station 100) based on control by control section 201, and outputs the analysis result to control section 201. That is to say, information processing section 204 extracts, for example, a scheduling information unit related to downlink data communication and

a scheduling information unit related to uplink data communication, and outputs these to control section 201.

[0037] [Structure of control information]

5 As described above, information generation section 103 generates control information to be transmitted in a downlink. FIG.5 shows a control information structure according to embodiment 1 of the present invention.

10 [0038] In FIG.5, control information 300 is divided into multicast/broadcast zone 310 and unicast zone 320. Multicast/broadcast zone 310 and unicast zone 320 are formed with consecutive areas.

15 [0039] Multicast/broadcast zone 310 includes all of multicast scheduling information and broadcast scheduling information in the frame in which this control information is transmitted. In other words, multicast/broadcast zone 310
20 includes all multicast IEs and broadcast IEs in control information 300.

[0040] On the other hand, unicast zone 320 includes all the unicast scheduling information in the frame in which this control information
25 is transmitted.

[0041] Unicast zone 320 has scheduling information unit 330 for each mobile station

200. Each scheduling information unit 330 includes area 332 for one MS-ID, area 334 for an indicator of the number of IEs, and areas 336 for IEs. The indicator of the number of IEs shows the number of IEs included in that scheduling information unit 330.

[0042] As for multicast IE and broadcast IE, every IE contains an MS-ID. This IE format will also be referred to as "first format" hereinafter. On the other hand, an MS-ID is not included in a unicast IE, and only one MS-ID is placed at the beginning of each mobile station assignment area 330. This IE format will also be referred to as "second format" hereinafter.

[0043] In this way, in unicast zone 320, scheduling information unit 330 is formed by placing, for one MS-ID, a plurality of unicast IEs together in one IE area 336. Consequently, once scheduling information unit 330 for mobile station 200 is found out, the unicast IEs for mobile station 200 are not present in other areas, so that mobile station 200 at the reception side is able to finish the process of searching for the areas assigned to mobile station 200 at the time of finding out scheduling information unit 330 for mobile station 200. As a result, compared to the prior

art which has heretofore necessitated a search of whole control information, it is possible to reduce the time for the scheduling information unit search process, and, in accordance with this, reduce the power consumption of mobile station 200.

[0044] Also, an MS-ID is not included in a unicast IE but is situated in the beginning area of each scheduling information unit 330. By this means, even when a plurality of IEs are included in scheduling information unit 330, unlike the prior art which has heretofore included an MS-ID in each unicast IE, it is possible to reduce the signaling overhead.

15 [0045] (Embodiment 2)

With embodiment 2, a unicast zone is divided into a plurality of partial zones depending on the number of IEs. The configurations of the base station and mobile station according to embodiment 2 are the same as base station 100 and mobile station 200 according to embodiment 1.

[0046] Information generation section 103 generates control information to be transmitted in a downlink. FIG.6 shows a control information structure according to embodiment 2.

[0047] In FIG.6, control information 400 is

divided into multicast/broadcast zone 410 and unicast zones 420.

[0048] Also, in FIG.6, unicast zones 420 are divided into two partial zones -- first unicast zone 420a and second unicast zone 420b.

[0049] In the frame in which control information 400 is transmitted, first unicast zone 420a includes a scheduling information unit for mobile station 200, which one unicast IE addresses. The unicast IEs to be mapped in first unicast zone 420a include MS-IDs respectively (see unicast IEs 422 and 424 in FIG.6). That is to say, first unicast zone 420a employs the first format.

[0050] On the other hand, in the frame in which control information 400 is transmitted, second unicast zone 420b includes a scheduling information unit for mobile station 200, which a plurality of unicast IEs address. Similar to embodiment 1, the unicast IEs to be mapped in second unicast zone 420b do not include MS-IDs, and only one MS-ID is situated in the beginning area of each scheduling information unit 330. That is to say, second unicast zone 420b employs the second format.

[0051] As described above, by thus providing first unicast zone 420a for mapping only a

scheduling information unit which obviously has only one IE, an indicator of the number of IEs is not necessary in this area. By this means, it is possible to reduce signaling overhead.

5 [0052] Also, multicast/broadcast zone 410 is
provided between first unicast zone 420a and
second unicast zone 420b. That is to say,
multicast/broadcast zone 410 forms the border
between first unicast zone 420a and second
10 unicast zone 420b. By this means, mobile
station 200 at the reception side is able to
readily identify the end of first unicast zone
420a and the beginning of second unicast zone
420b using multicast/broadcast zone 410 as a
15 landmark.

[0053] Note that, in addition to multicast/broadcast zone 410, it is also possible to provide a zone to include an IE for special use (e.g. ranging IE) with a predetermined MS-ID, and use this zone as a unicast zone terminal signal.

[0054] Also, the order of first unicast zone 420a and second unicast zone 420b may be reversed to place second unicast zone 420b in the front and first unicast zone 420a in the back. However, such order needs to be determined in advance.

[0055] (Embodiment 3)

Similar to embodiment 2, embodiment 3 also divides a unicast zone into a plurality of partial zones depending on the number of IEs. The configurations of the base station and mobile station according to embodiment 3 are the same as base station 100 and mobile station 200 according to embodiment 1.

[0056] Information generation section 103 generates control information to be transmitted in a downlink. FIG.7 shows a control information structure according to embodiment 3.

[0057] In FIG.7, control information 500 is divided into multicast/broadcast zones 510 and unicast zones 520.

[0058] Also, in FIG.7, unicast zones 520 are divided into three partial zones -- first unicast zone 520a, second unicast zone 520b and third unicast zone 520c.

[0059] Similar to first unicast zone 420a described with embodiment 2, in the frame in which control information 500 is transmitted, first unicast zone 520a includes a scheduling information unit for mobile station 200, which one unicast IE addresses.

[0060] Also, in the frame in which control information 500 is transmitted, second unicast

zone 520b includes a scheduling information unit for mobile station 200, which two unicast IEs address. Second unicast zone 520b includes scheduling information unit 530 for each mobile station 200. Similar to scheduling information unit 330, scheduling information unit 530 includes area 532 for one MS-ID and area 534 for IE. However, unlike scheduling information unit 330, scheduling information unit 530 does not include an indicator of the number of IEs. Similar to first unicast zone 520a, information about the number of IEs is associated with second unicast zone 520b itself, and so it is not even necessary to include an indicator of the number of IEs. By this means, it is possible to reduce signaling overhead.

[0061] Also, in the frame in which control information 500 is transmitted, third unicast zone 520c includes a scheduling information unit for mobile station 200, which equal to or more than three unicast IEs address.

[0062] By thus providing three unicast zones, mobile station 200 at the reception side is able to further narrow the areas in which mobile station 200 has to search for its own MS-ID, so that, as a result, it is possible to further reduce the processing time and power consumption

of mobile station 200.

[0063] Also, multicast/broadcast zones 510 are divided into first multicast/broadcast zone 510a and second multicast/broadcast zone 510b. First
5 multicast/broadcast zone 510a and second multicast/broadcast zone 510b are provided between first unicast zone 520a and second unicast zone 520b and between second unicast zone 520b and third unicast zone 520c,
10 respectively.

[0064] By this means, mobile station 200 at the reception side is able to readily identify the beginning and end of unicast zones 520 using multicast/broadcast zone 510 as a landmark.

15 [0065] Note that, in addition to first multicast/broadcast zone 510a and second multicast/broadcast zone 510b, it is also possible to provide a zone to include an IE for special use (e.g. ranging IE) with a
20 predetermined MS-ID, and use this zone as a unicast zone terminal signal.

[0066] Also, the order of first unicast zone 520a, second unicast zone 520b and third unicast zone 520c may be reordered. However, the order
25 needs to be determined in advance.

[0067] (Embodiment 4)

With embodiment 4, unlike embodiment 2 and

embodiment 3, a multicast/broadcast zone is divided into multicast zones and broadcast zones. Information generation section 103 generates control information to be transmitted in a downlink. FIG.8 shows a control information structure according to embodiment 4.

[0069] Referring to FIG.8, control information 600 is divided into broadcast zone 610, multicast zone 620 and unicast zones 420.

[0070] Broadcast zone 610 is present at the beginning of control information 600. By this means, it is possible to provide an information structure that complies with a protocol that requires placing broadcast scheduling information in the beginning area of control information (e.g. IEEE 802.16e).

[0071] Also, multicast zone 620 is present between first unicast zone 420a and second unicast zone 420b. By this means, mobile station 200 at the reception side is able to readily identify the end of first unicast zone 420a and the beginning of second unicast zone 420b using multicast zone 620 as a landmark.

[0072] Also, no area where broadcast zone and multicast zone are present together is provided, broadcast zone 610 and multicast zone 620 are each provided as an independent zone. By this

means, the load of the process of zone search in mobile station 200 at the reception side is reduced. That is to say, if, for example, an address notation complies with IPv4, the last
5 eight bits in a broadcast IP address becomes all 1's and the first 4 bits in a multicast IP address become 1110. Consequently, when broadcast zone and multicast zone are present together in the same area, mobile station 200
10 might be able to identify between broadcast and multicast only upon looking at the first four bits or the last eight bits. Meanwhile, if a broadcast zone and a multicast zone are separated and their order is determined as with
15 the present embodiment, it is possible to reduce the load of the process of zone search in mobile station 200 by first carrying out a search by focusing on a characteristic point of an IP address of the zone to show up first and then
20 switching that characteristic point to search for to that of the other zone.

[0073] (Embodiment 5)

With embodiments 2 to 4, a non-unicast zone is arranged between the first unicast zone and
25 the second unicast zone. By this means, a mobile station at the reception side is able to readily identify the end of the first unicast zone and

the beginning of the second unicast zone using the non-unicast zone as a landmark.

[0074] The present embodiment presumes using control information having a different structure
5 from those of embodiments 2 to 4.

[0075] [Conventional system as precondition]

Unlike the system explained in the background art part, with this system, there are cases where an MS-ID is not reported expressly
10 and a CRC (Cyclic Redundancy Check) part is masked by multiplying the CRC part included in each IE by an MS-ID. A mobile station at the reception side decodes an IE and calculates an exclusive OR of the CRC part using its own MS-
15 ID. If the CRC check result is "OK," the mobile station determines that the IE addresses itself, and receives data using that IE. The mobile station then has to try decoding all the IEs to look for an IE addressing itself.

20 [0076] Furthermore, in this system, a plurality of resource sizes and MCSs (Modulation and Coding Schemes) are prepared each, to report an IE to a mobile station. For example, two resource sizes (1 MLRU (MAP Logical Resource
25 Unit) and 2 MLRU) and two MCSs (QPSK 1/2 and QPSK 1/8) are prepared. Then, the combination of resource size and MCS to be applied to an IE

may be changed per destination mobile station,
based on propagation path conditions.

[0077] Also, there are four kinds of
combinations of resource size and MCS in the
5 above-described example, so that, in control
information, IEs are sorted in four groups and
included and furthermore the number of IEs is
included per group (see FIG.9, which illustrates
a case where there are N types of groups). By
10 this means, a mobile station to receive control
information is able to reduce the number of
times the mobile station has to try performing
decoding in order to look for an IE addressing
the mobile station.

15 [0078] However, as shown in FIG.9, IEs are
placed in the area referred to as "user specific
MAP" and the numbers of IEs per group are placed
in the area referred to as "non-user specific
MAP." Consequently, by providing this non-user
20 specific MAP, compared to the system described
in the background part, this system has the
problems of increasing the overhead and
decreasing the total throughput.

[0079] [Configurations of base station and
25 mobile station according to embodiment 5]

The base station and mobile station
according to embodiment 5 have the same basic

configurations as base station 100 and mobile station 200 according to embodiment 1.

[0080] Information generating section 103 generates control information to be transmitted
5 in a downlink. To be more specific, information generating section 103 first groups IEs based on the IE type. The IE type refers to, for example, the combination of resource size and MCS. Information generating section 103
10 separates an assignment area per group and places IEs in control information. Furthermore, in an assignment area for an arbitrary group, information generating section 103 separates a unicast IE assignment area and a non-unicast IE
15 assignment area and places IEs.

[0081] [Structure of control information]

FIG.10 shows a structure of control information according to embodiment 5. In FIG.10, the IEs are arranged in the order of
20 group 1(G_1), ..., group N(G_N), and included in control information. Also, in an assignment area for an arbitrary group, IEs are placed in the order of a unicast IE and then a broadcast IE (which is a kind of a non-unicast IE). That
25 is to say, in an arbitrary group, a unicast IE forms one subgroup (SG) and a non-unicast IE forms the other subgroup.

[0082] As described above, according to the present embodiment, control information has an IE assignment area per group corresponding to the IE type. In each group's IE assignment area, a unicast IE assignment area and a non-unicast IE assignment area are separated and arranged in a given order.

[0083] By this means, a non-unicast IE assignment area of the first group or a second group is provided between a unicast IE assignment area of the first group and a unicast IE assignment area of the second group. Consequently, a mobile station at the reception side is able to readily identify the end of a unicast IE assignment area of the first group and the beginning of a unicast IE assignment area of a second group using a non-unicast IE assignment area as a landmark. That is to say, by adopting this control information structure, unlike the conventional system such as described earlier, it is not necessary to provide a non-user specific MAP and therefore is possible to reduce overhead.

[0084] (Embodiment 6)

A case has been assumed with embodiment 5 where a non-unicast IE is included in each group. By contrast with this, embodiment 6 is

directed to a control information structure in the event there is a group not containing a non-unicast IE. The basic configuration of the base station and mobile station according to embodiment 6 are the same as in embodiment 5.

[0085] Similar to embodiment 5, information generating section 103 generates control information to be transmitted in a downlink. To be more specific, information generating section 103 first groups IEs based on the IE type. Then, information generating section 103 separates an assignment area per group and places IEs in control information. Furthermore, in an assignment area for an arbitrary group, information generating section 103 separates a unicast IE assignment area and a non-unicast IE assignment area and places IEs.

[0086] Furthermore, information generating section 103 places information about the number of unicast IEs of groups not including non-unicast IEs, in a non-user specific MAP. Also, information generating section 103 places information about groups not including non-unicast IEs in a non-user specific MAP. This group-related information is provided in, for example, bitmap format.

[0087] FIG.11 shows a control information

structure according to embodiment 6. FIG.11 shows a control information structure in the event N is 4. In FIG.11, G_2 and G_4 do not include non-unicast IEs. Consequently,

5 information related to groups not including non-unicast IEs is placed in the non-user specific MAP. In this context, whether or not a non-unicast IE is present in an arbitrary group is represented by the bit value 1 or 0. There are
10 four groups in this context, so a bit map is comprised of four constituent bits. When the k -th constituent bit in the bit map is associated with group k , if G_2 and G_4 do not include non-unicast IEs, the bit map is formed with a bit
15 sequence of 0101.

[0088] By this means, even when there is a group not including a non-unicast IE, a mobile station at the reception side is able to readily identify the beginning and end of each group's
20 assignment area. Also, given that only information about the number of IEs for groups not including non-unicast IEs is placed in the non-user specific MAP, it is possible to reduce the overhead compared to the conventional system
25 described in embodiment 5. Also, compared to the conventional system described above with embodiment 5, although information about groups

not including non-unicast IEs needs to be provided additionally, the number of bits is just the same as the number of groups, and this has little impact on the increase of overhead.

5 [0091] (Embodiment 7)

The present embodiment presumes that a base station transmits a signal using a plurality of carriers.

[0090] [Conventional system of precondition]

10 In this system, for example, as shown in FIG.12, a base station transmits a signal using a plurality of carriers. The plurality of carriers include a primary carrier and secondary carriers. All control information is
15 transmitted using the primary carrier. Then, control information for the primary carrier is reported as a basic assignment IE, while control information for the secondary carriers is reported as an MC assignment IE. Basic
20 assignment IE and MC assignment IE are transmitted as one set by a primary carrier.

[0091] By this means, the primary carrier transmits all the single carrier IEs and multicarrier IEs. In this case, as shown in
25 FIG.13, single carrier IEs and multicarrier IEs are transmitted randomly. Consequently, when this information structure is adopted, even when

a signal for a given mobile station is transmitted by single carrier, it is still necessary to decode all the IEs.

[0092] To reduce the load of a mobile station at the reception side, for example, it is possible to adopt the control information structure shown in FIG.14. That is to say, in the area called "user specific MAP," which is different from the area called "non-user specific MAP," a single carrier IE arrangement area and a non-single carrier IE arrangement area are placed apart. The number of IEs and the like are placed in the non-user specific MAP.

[0093] By this means, when a signal addressing a given mobile station is transmitted by single carrier, that mobile station has only to decode single carrier IEs and therefore is able to reduce the number of attempts to search for IEs addressing that mobile terminal.

[0094] However, by providing this non-user specific MAP, compared to the system described in the background part, this system has the problems of increasing the overhead and decreasing the total throughput.

[0095] [Configuration of base station and mobile station according to embodiment 7]

The base station and mobile station according to embodiment 7 have the same basic configurations as base station 100 and mobile station 200 according to embodiment 1.

5 [0096] Information generating section 103 generates control information to be transmitted in a downlink. To be more specific, information generating section 103 first groups IEs based on the IE type. In this context, the IE type
10 refers to, for example, the combination of the type of single carrier or multicarrier and the type of unicast IE or non-unicast IE. Information generating section 103 separates an assignment area per group and places IEs in
15 control information. Furthermore, in an assignment area of a group of the single carrier type, information generating section 103 separates a unicast IE assignment area and a non-unicast IE assignment area and places IEs.

20 [0097] [Structure of control information]

FIG.15 shows a control information structure according to embodiment 7. In FIG.15, the IEs are arranged in the order of a single carrier group and then a multicarrier group, and
25 included in control information. Also, in an assignment area for a single carrier group, IEs are placed in the order of a unicast IE and then

a broadcast IE (which is a kind of a non-unicast IE). That is to say, in a single carrier group, a unicast IE forms one subgroup (SG) and a non-unicast IE forms the other subgroup. The IEs here include both a basic assignment IE and a non-basic assignment IE. A basic assignment IE is an information element for a regular data channel. A non-basic assignment IE is, for example, a group-specific information element, an IE for reporting a group-specific information element component, and an IE for a channel other than a regular data channel such as persistent allocation.

[0098] [Receiving processing in mobile station]

Control information structured as described above is transmitted from base station and received in mobile station 200.

[0099] FIG.16 illustrates processing in information processing section 204.

[0100] In step S1001, information processing section 204 performs a CRC check per control information IE.

[0101] In step S1002, when a CRC check result is determined to be "OK" ("YES") as a result of demasking the CRC part using broadcast identification information, this IE is detected as the beginning of an area where a single

carrier and broadcast IE group is placed (that is, SG₂ in FIG.15) (step S1003). If the CRC check result is determined to be "NG" ("NO"), the process of step S1001 is repeated.

5 [0102] In step S1004, a CRC check for a subsequent IE is performed.

[0103] In step S1005, when a CRC check result is determined to be "NG" ("NO") as a result of demasking the CRC part using broadcast
10 identification information, this IE is detected as the beginning of an area where a multicarrier IE group is placed (step S1007).

[0104] In step S1005, when a CRC check result is determined to be "OK" ("YES") as a result of
15 demasking the CRC part using broadcast identification information, whether or not this IE is a multicarrier assignment IE is decided (step S1006).

[0105] When a multicarrier assignment IE is
20 identified (step S1006: "YES"), this IE is identified as the beginning of the area where a multicarrier IE group is placed (step S1007). If an IE is identified not to be a multicarrier assignment IE (step S1006: "NO"), the process of
25 step S1004 is repeated.

[0106] As described above, according to the present embodiment, control information has an

IE assignment area per group corresponding to the IE type. In an assignment area for a single carrier group, a unicast IE assignment area and a non-unicast IE assignment area are separated
5 and arranged in a given order.

[0107] By this means, a non-unicast IE assignment area of a single carrier group is provided between a unicast IE assignment area of a single carrier group and an IE assignment area
10 of a multicarrier group. Consequently, a mobile station at the reception side is able to readily identify the end of a unicast IE assignment area of a single carrier group and the beginning of an IE assignment area of a multicarrier group
15 using a non-unicast IE assignment area of a single carrier group as a landmark. That is to say, by adopting this control information structure, unlike the conventional system such as described earlier, it is not necessary to
20 provide a non-user specific MAP and therefore is possible to reduce overhead.

[0108] (Embodiment 8)

With embodiment 7, a mobile station detects the first "basic assignment IE" in a
25 multicarrier group and by this means identifies the border between a single carrier group and a multicarrier group. The criterion for detecting

the first "basic assignment IE" in a multicarrier group is, for example, whether or not an IE subject to detection is a broadcast IE or a multicarrier assignment IE. Whether or not
5 an IE that is subject to detection is a multicarrier assignment IE is useful when the basic assignment IE placed at the beginning of a multicarrier group is a broadcast IE.

[0109] By contrast with this, with the present
10 embodiment, in a single carrier group assignment area, an IE that is a non-basic assignment IE and that is also a broadcast IE is assigned immediately before a multicarrier group allocation area. By this means, switch from a
15 non-basic assignment IE to a basic assignment IE can be used as the criterion for detecting the first "basic assignment IE" in a multicarrier group.

[0110] [Configuration of base station and
20 mobile station according to embodiment 8]

The base station and mobile station according to embodiment 8 have the same basic configurations as base station 100 and mobile station 200 according to embodiment 1.

25 [0111] Information generating section 103 generates control information to be transmitted in a downlink. To be more specific, information

generating section 103 first groups IEs based on the IE type. In this context, the IE type refers to, for example, the combination of the type of single carrier or multicarrier, the type of unicast IE or non-unicast IE, and the type of basic assignment or non-basic assignment. Information generating section 103 separates an assignment area per group and places IEs in control information. Furthermore, in an assignment area of a group of the single carrier type, information generating section 103 separates an IE that is non-basic assignment and that is a non-unicast IE assignment area, and other assignment areas, and places IEs.

[0112] [Structure of control information]

FIG.17 shows a structure of control information according to embodiment 8. In FIG.17, the IEs are arranged in the order of a single carrier group and then a multicarrier group, and included in control information. Also, in an assignment area for a single carrier group, IEs are placed in the order of a basic assignment IE (both a unicast IE and a non-unicast IE), a non-basic assignment and unicast IE, and then a non-basic assignment and broadcast IE. That is to say, in a single carrier group, a non-basic assignment, non-

unicast IE forms the subgroup to be placed immediately before a multicarrier group. Furthermore, in an arbitrary set as described above, IEs are placed in the order of a basic assignment IE and then a non-basic assignment IE. That is to say, at the beginning of an assignment area of the multicarrier group type, information generating section 103 places a basic assignment IE.

10 [0113] [Receiving processing at mobile station]

Control information structured as described above is transmitted from base station 100 to mobile station 200.

[0114] FIG.18 illustrates processing in information processing section 204.

[0115] In step S2001, information processing section 204 performs a CRC check per control information IE.

[0116] In step S2002, when a CRC check result is determined to be "OK" as a result of demasking the CRC part of a check target IE using broadcast identification information and the check target IE is identified to be a non-basic assignment IE ("YES"), the check target IE is detected as the beginning of an area where a non-basic assignment and non-unicast IE group is placed (that is, SG₂ in FIG.17) (step S2003). If

the CRC check result is determined to be "NG" ("NO"), the process of step S2001 is repeated.

[0117] In step S2004, a CRC check for a subsequent IE is performed.

5 [0118] In step S2005, when a CRC check result is determined to be "NG" ("NO") as a result of demasking the CRC part of a check target IE using broadcast identification information, the check target IE is detected as the beginning of
10 an area where a multicarrier IE group is placed (step S2007).

[0119] When the CRC check result is determined to be "OK" (step S2005: "YES"), whether or not the check target IE is a non-basic assignment IE
15 is decided (step S2006).

[0120] If the check target IE is identified not to be a non-basic assignment IE (step S2006: "NO"), this check target IE is detected as the beginning of an area where a multicarrier IE
20 group is placed (step S2007). If the check target IE is identified to be a non-basic assignment IE (step S2006: "YES"), the process of step S2004 is repeated.

[0121] (Other embodiments)

25 (1) In embodiment 1 through 3, multicast/broadcast zone 310, multicast/broadcast zone 410 and

multicast/broadcast zone 510 are areas where multicast and broadcast IEs are present together. However, the present invention is by no means limited to this, and it is equally possible to divide multicast/broadcast zone 310, multicast/broadcast zone 410, and multicast/broadcast zone 510 each into a multicast zone and a broadcast zone. By this means, similar to embodiment 4, it is possible to reduce the load of zone search process in mobile station 200 at the reception side.

[0122] In particular, in the event a broadcast zone is placed at the beginning of multicast/broadcast zone 310 as with the case with embodiment 1, by placing a broadcast zone at the beginning in multicast/broadcast zone 310, it is possible, like embodiment 4, to provide a information structure that complies with a protocol that requires placing broadcast scheduling information in the beginning area of control information (e.g. IEEE 802.16e).

[0123] (2) With embodiment 3, multicast/broadcast zone 510, which is an area where multicast and broadcast IEs are present together, is placed between unicast zones. However, the present invention is by no means limited to this, and it is equally possible to

provide a broadcast zone in the place of
multicast/broadcast zone 510a and place a
multicast zone in the place of
multicast/broadcast zone 510b. By this means,
5 too, it is possible, like embodiment 4, to
reduce the load of zone search process in mobile
station 200 at the reception side.

[0124] Also, although cases have been described
with the above embodiment as examples where the
10 present invention is configured by hardware, the
present invention can also be realized by
software.

[0125] Each function block employed in the
description of each of the aforementioned
15 embodiments may typically be implemented as an
LSI constituted by an integrated circuit. These
may be individual chips or partially or totally
contained on a single chip. "LSI" is adopted
here but this may also be referred to as "IC,"
20 "system LSI," "super LSI," or "ultra LSI"
depending on differing extents of integration.

[0126] Further, the method of circuit
integration is not limited to LSI's, and
implementation using dedicated circuitry or
25 general purpose processors is also possible.
After LSI manufacture, utilization of a
programmable FPGA (Field Programmable Gate

Array) or a reconfigurable processor where connections and settings of circuit cells within an LSI can be reconfigured is also possible.

[0127] Further, if integrated circuit technology comes out to replace LSI's as a result of the advancement of semiconductor technology or a derivative other technology, it is naturally also possible to carry out function block integration using this technology.

Application of biotechnology is also possible.

[0128] The disclosures of Japanese Patent Application No.2008-328294, filed on December 24, 2008, Japanese Patent Application No.2009-135324, filed on June 4, 2009, and Japanese Patent Application No.2009-162071, filed on July 8, 2009, including the specifications, drawings and abstracts, are incorporated herein by reference in their entirety.

Industrial Applicability

[0129] The transmission apparatus and control information transmission method of the present invention are suitable for use to reduce processing time and power consumption at the reception side by making the receiving processes at the reception side more efficient.

CLAIMS

1. A communication apparatus comprising:

a generator that generates assignment information; and

a transmitter that transmits the generated assignment information in a region of the assignment information, wherein

the assignment information is categorized into at least multicast assignment information intended for a group of a plurality of the reception apparatuses and unicast assignment information intended for one reception apparatus,

the region of the assignment information includes a first region and a second region, and

a plurality of the unicast assignment information intended for one reception apparatus are present in the first region following the second region, in which a plurality of the multicast assignment information intended for a group of a plurality of the reception apparatuses are present.

2. The communication apparatus according to claim 1, wherein

the region of the assignment information further includes a third region, in which unicast assignment information intended for one reception apparatus is present, and the second region is present between the first region and the third region.

3. The communication apparatus according to claim 2, wherein

the plurality of the unicast assignment information are grouped together based on a size of the unicast assignment information, such that a first group with a first size of the unicast assignment information is present in the first region and a second group with a second size of the unicast assignment information is present in the third region.

4. The communication apparatus according to claim 1, wherein the region of the assignment information further includes a fourth region, in which broadcast assignment information intended for all of reception apparatuses, is present, and the fourth region is present at the beginning of the region of the assignment information.

5. The communication apparatus according to claim 1, wherein the unicast assignment information, the multicast assignment information are present in a frequency domain.

6. A communication method performed by a communication apparatus comprising:

generating assignment information; and

transmitting the generated assignment information in a region of the assignment information, wherein

the assignment information is categorized into at least multicast assignment information intended for a group of a plurality of the reception apparatuses and unicast assignment information intended for one reception apparatus,

the region of the assignment information includes a first region and a second region, and

a plurality of the unicast assignment information intended for one reception apparatus are present in the first region following the second region, in which a plurality of the multicast assignment information intended for a group of a plurality of the reception apparatuses are present.