

DESCRIPTION

FLOATING BODY FIELD-EFFECT TRANSISTORS, AND METHODS OF FORMING FLOATING BODY FIELD-EFFECT TRANSISTORS

5 TECHNICAL FIELD

Embodiments disclosed herein pertain to floating body field-effect transistors, and to methods of forming floating body field-effect transistors.

BACKGROUND

10 One type of dynamic random access memory (DRAM) includes individual memory cells that include a field-effect transistor and a storage capacitor. As the size of integrated circuitry shrinks, the size of the capacitor also shrinks. Generally as the storage capacitor shrinks, the quantity of charge and the time which the charge can be retained decreases as well. Consequently, maintaining
15 an acceptable level of performance of this type of DRAM structure becomes more difficult as the capacitor size decreases. Using capacitor dielectrics having high dielectric constants and increasing capacitor plate surface area through surface roughening, greater vertical dimensions, and other various capacitor shapes have been the conventional approaches to maintaining
20 sufficiently high capacitance.

Another type of DRAM cell uses a structure which is void of a discrete storage capacitor. An example of a capacitor-less DRAM consists essentially of only a single transistor (1T) memory cell. Such DRAM cells use a semiconductor-on-insulator (SOI) structure for storing positive electrical charge
25 in the form of "holes". The stored positive charge reduces the transistor threshold voltage (V_t), which is the voltage applied to the gate at which the channel region between the pair of source/drain regions becomes conductive. Accordingly, binary data states are represented in a 1T memory cell based on whether the transistor is switched "on" or remains "off" in response to a voltage
30 applied to its gate during a memory read operation.

Various SOI 1T DRAM cell structures have been developed based on metal-oxide-semiconductor (MOS) field-effect transistor (FET) devices using a floating SOI channel body in which the holes accumulate. Accordingly, the source/drain regions are n-type, and the channel region is lightly doped p-type.

These types of 1T DRAM cells are generally referred to as floating body cells (FBCs) due to the use of a floating SOI body. As accumulated holes lower the voltage at which the channel becomes conductive, a conductive channel is formed in the same floating SOI body in which the holes accumulate upon appropriate voltage application to the gate of the FET device. A data "1" is written by creating holes (for example, by impact ionization) and push up the body potential to a high level. Conversely, data "0" is written by extracting holes from the body which pulls the body potential down to a low level. By grounding the bit line and by applying negative voltage to the word line, body potential level which is either high or low is held for a certain time. The data can be distinguished using MOSFET current modulated by body potential.

The floating SOI channel body can be designed for use as partially depleted semiconductor-on-insulator (PDSOI) or fully depleted semiconductor-on-insulator (FDSOI), which refers to the extent of the formation of the conductive channel within thickness of the floating SOI body. In the case of FDSOI operation, negative substrate (plate) bias is applied so that the back surface of the semiconductor film accumulates holes. In the case of a partially depleted floating body cell (PDFBC), a neutral volume region exists. Accordingly, the neutral volume region is used in the case of PDFBC, and a bottom "plane" is used in the case of fully depleted floating body cell (FDFBC) for respective hole storage regions representing data states by potential level.

Regardless, writing a "1" to a floating body cell is achieved by voltage application in which excessive holes are stored in the floating body channel region of the FET. Conversely, application of different voltage potentials to the various FET components removes holes of the floating body channel region, thereby writing a "0". A mostly non-destructive read or data determination state of the FET is conducted typically utilizing a different set of voltage parameters particularly in which the voltage of one of the source/drain regions functioning as a drain is provided at lower voltage than at which such is provided during either a writing "1" operation or a writing "0" operation. There is a need for refresh of a written "1" due to hole loss due to injection into the source/drain because of the forward biased junction. Accordingly, any structure which facilitates quantity of hole storage and minimizes hole loss by any mechanism would be an improvement in the context of floating body field-effect transistors.

Floating body field-effect transistors might also be used in other than DRAM or in other than memory circuitry.

BRIEF DESCRIPTION OF THE DRAWINGS

Fig. 1 is a diagrammatic sectional view of a semiconductor substrate in process in accordance with an embodiment of the invention.

Fig. 2 is a view of the Fig. 1 substrate at a processing step subsequent to that shown in Fig. 1.

Fig. 3 is a view of the Fig. 2 substrate at a processing step subsequent to that shown in Fig. 2.

Fig. 4 is a view of the Fig. 3 substrate at a processing step subsequent to that shown in Fig. 3.

Fig. 5 is a view of the Fig. 4 substrate at a processing step subsequent to that shown in Fig. 4.

Fig. 6 is a diagrammatic sectional view of another semiconductor substrate in process in accordance with an embodiment of the invention.

Fig. 7 is a view of the Fig. 6 substrate at a processing step subsequent to that shown in Fig. 6.

Fig. 8 is a diagrammatic sectional view of another semiconductor substrate in process in accordance with an embodiment of the invention.

Fig. 9 is a view of the Fig. 8 substrate at a processing step subsequent to that shown in Fig. 8.

Fig. 10 is a view of the Fig. 9 substrate at a processing step subsequent to that shown in Fig. 9.

Fig. 11 is a diagrammatic sectional view of another semiconductor substrate in process in accordance with an embodiment of the invention.

Fig. 12 is a view of the Fig. 11 substrate at a processing step subsequent to that shown in Fig. 11.

Fig. 13 is a view of the Fig. 12 substrate at a processing step subsequent to that shown in Fig. 12.

Fig. 14 is a view of the Fig. 13 substrate at a processing step subsequent to that shown in Fig. 13.

Fig. 15 is a view of the Fig. 14 substrate at a processing step subsequent to that shown in Fig. 14.

Fig. 16 is a view of the Fig. 15 substrate at a processing step subsequent to that shown in Fig. 15.

Fig. 17 is a diagrammatic sectional view of another semiconductor substrate in process in accordance with an embodiment of the invention.

Fig. 18 is a diagrammatic sectional view of another semiconductor substrate in process in accordance with an embodiment of the invention.

5 Fig. 19 is a view of the Fig. 18 substrate at a processing step subsequent to that shown in Fig. 18.

Fig. 20 is a view of the Fig. 19 substrate at a processing step subsequent to that shown in Fig. 19.

10 Fig. 21 is a diagrammatic sectional view of another semiconductor substrate in process in accordance with an embodiment of the invention.

Fig. 22 is a view of the Fig. 21 substrate at a processing step subsequent to that shown in Fig. 21.

Fig. 23 is a view of the Fig. 22 substrate at a processing step subsequent to that shown in Fig. 22.

15 Fig. 24 is a view of the Fig. 23 substrate at a processing step subsequent to that shown in Fig. 23.

Fig. 25 is a diagrammatic sectional view of another semiconductor substrate in process in accordance with an embodiment of the invention.

20 Fig. 26 is a view of the Fig. 25 substrate at a processing step subsequent to that shown in Fig. 25.

Fig. 27 is a view of the Fig. 26 substrate at a processing step subsequent to that shown in Fig. 26.

Fig. 28 is a view of the Fig. 27 substrate at a processing step subsequent to that shown in Fig. 27.

25 Fig. 29 is a diagrammatic sectional view of another semiconductor substrate in process in accordance with an embodiment of the invention.

Fig. 30 is a view of the Fig. 29 substrate at a processing step subsequent to that shown in Fig. 29.

30 Fig. 31 is a view of the Fig. 30 substrate at a processing step subsequent to that shown in Fig. 30.

Fig. 32 is a view of the Fig. 31 substrate at a processing step subsequent to that shown in Fig. 31.

Fig. 33 is a view of the Fig. 32 substrate at a processing step subsequent to that shown in Fig. 32.

Fig. 34 is a view of the Fig. 33 substrate at a processing step subsequent to that shown in Fig. 33.

Fig. 35 is a view of the Fig. 34 substrate at a processing step subsequent to that shown in Fig. 34.

5 Fig. 36 is a view of the Fig. 35 substrate at a processing step subsequent to that shown in Fig. 35.

Fig. 37 is a diagrammatic sectional view of another semiconductor substrate in process in accordance with an embodiment of the invention.

10 Fig. 38 is a view of the Fig. 37 substrate at a processing step subsequent to that shown in Fig. 37.

Fig. 39 is a view of the Fig. 38 substrate at a processing step subsequent to that shown in Fig. 38.

Fig. 40 is a view of the Fig. 39 substrate at a processing step subsequent to that shown in Fig. 39.

15 Fig. 41 is a view of the Fig. 40 substrate at a processing step subsequent to that shown in Fig. 40.

Fig. 42 is a view of the Fig. 41 substrate at a processing step subsequent to that shown in Fig. 41.

20 Fig. 43 is a view of the Fig. 42 substrate at a processing step subsequent to that shown in Fig. 42.

DETAILED DESCRIPTION OF EXAMPLE EMBODIMENTS

Embodiments encompass methods of forming floating body field-effect transistors, for example for use as memory cells or in other circuitry, and floating body field-effect transistors independent of method of fabrication, also for example for use as memory cells or in other circuitry. Initial embodiments are described with reference to Figs. 1-5.

Referring to Fig. 1, a semiconductor substrate is indicated generally with reference numeral 10. In the context of this document, the term "semiconductor substrate" or "semiconductive substrate" is defined to mean any construction comprising semiconductive material, including, but not limited to, bulk semiconductive materials such as a semiconductive wafer (either alone or in assemblies comprising other materials thereon), and semiconductive material layers (either alone or in assemblies comprising other materials). The term "substrate" refers to any supporting structure, including, but not limited to, the semiconductive substrates described above. Substrate 10 is depicted as comprising a semiconductor region 12 having an insulator 14 formed thereover. An example semiconductor material 12 is doped or undoped monocrystalline silicon (including for example bulk monocrystalline silicon), and an example insulator 14 is silicon dioxide. By way of example only, a thickness range for insulator 14 is from about 30 Angstroms to about 5,000 Angstroms.

Referring to Fig. 2, a semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer 16 has been formed over insulator 14. Such might be provided by any existing or yet-to-be developed manner. Existing examples may include physical vapor deposition, chemical vapor deposition, atomic layer deposition, and/or epitaxial deposition or lateral overgrowth, and by way of examples only. One specific manner of depositing a $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer 16 includes epitaxial growth wherein a suitable seed layer is provided over insulator 14, with $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer 16 being epitaxially grown therefrom by using a silane and a germane as feed gases with the relative portions thereof determining silicon and germanium concentration within $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer 16. By way of example only, embodiments of the invention include where x is at least 0.5, at least 0.7, no greater than 0.85, no greater than 0.8, and from 0.7 to 0.85. Regardless, Fig. 2 depicts an embodiment wherein semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer 16 is formed to be received directly physically

contacting against insulator 14. Additional embodiments are contemplated wherein semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer 16 is not received directly physically contacting against insulator 14, and including where some of the base of semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer 16 contacts insulator 14 and some
5 does not. Further by way of example only, semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer 16 might be formed to be homogenous at least regarding Ge concentration, or formed to not be homogenous at least regarding Ge concentration. Further by way of example only, semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer 16 might be formed to be entirely homogenous as respects all its components.

10 Referring to Fig. 3, a semiconductor silicon-comprising layer 18 has been formed over and in direct physical contact with semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer 16. Semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer 16 has a greater quantity of Ge than any quantity of Ge within semiconductor silicon-comprising layer 18. Accordingly, semiconductor silicon-comprising
15 layer 18 may contain some quantity of Ge or may be void of Ge. In the context of this document, "void of Ge" defines no detectable Ge being present within a silicon-comprising layer such as layer 18. In one embodiment, semiconductor silicon-comprising layer 18 is void of Ge. In one embodiment, semiconductor silicon-comprising layer 18 comprises Ge, but ideally in considerably lower
20 concentration than present in $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer 16. Example embodiments include Ge quantity in semiconductor silicon-comprising layer 18 being less than about 10 atomic percent, less than about 1 atomic percent, less than 0.1 atomic percent, and being void of Ge.

Referring to Fig. 4, a gate construction 20 has been formed over
25 semiconductor silicon-comprising layer 18. Such is depicted as comprising a gate dielectric 22 having a conductive gate electrode 24 formed thereover. Gate electrode 24 might comprise one or a combination of conductively doped semiconductive material, elemental metal, alloys of elemental metals, and/or conductive metal compounds. Further by way of example only, an insulative
30 cap over gate electrode 24 (not shown) might be associated with gate construction 20. Gate construction 20 is also depicted as comprising anisotropically etched insulative sidewall spacers 26 formed about sidewalls of gate electrode 24 and gate dielectric 22. By way of example only, LDD, halo, and/or other implants into one or both of semiconductor silicon-comprising

layer 18 and $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer 16 might be conducted prior to or after formation of example anisotropically etched insulative sidewall spacers 26.

Referring to Fig. 5, a pair of source/drain regions 28 and a floating body channel region 30 therebetween have been formed using gate dielectric 22 and gate electrode 24 at least in part as a mask. In the context of this document, a source/drain region is any source region and/or drain region of a field-effect transistor which will function as one or both of a source and drain during current flow through the channel region of the FET. Accordingly, a source/drain region in operation might always function as either a source or a drain of a field-effect transistor, or circuitry construction and operation might be provided wherein in some operational regimes a source becomes a drain and a drain becomes a source. In the context of this document, a floating body channel region is that portion of the FET capable of operating as a conductive channel upon suitable application of gate voltage and which includes some portion thereof operable for a hole storage in a hole storage region whether operating in a fully depleted or partially depleted mode.

Fig. 5 depicts an embodiment wherein ion implanting of n-type conductivity enhancing impurity has been conducted into unmasked portions of semiconductor silicon-comprising layer 18 and semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer 16 to form a pair of highest dopant concentration n-type source/drain regions 28 using gate dielectric 22 and gate electrode 24 at least in part as a mask during such ion implanting. In the depicted embodiment, insulative sidewall spacers 26 have also effectively been used at least in part as a mask during such implanting. Additional masking might also be used.

Regardless, in the Figs. 1-5 embodiments, a pair of highest dopant concentration n-type source/drain regions 28 comprises both semiconductor silicon-comprising layer 18 and $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer 16 which have been suitably highly conductively doped to be capable of functioning as source/drain regions.

Floating body channel region 30 comprises semiconductor silicon-comprising layer 18 and $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer 16.

Accordingly and by way of example only, Fig. 5 depicts one embodiment floating body field-effect transistor 32. Such comprises a pair of source/drain regions 28 having a floating body channel region 30 received therebetween. Source/drain regions 28 and floating body channel region 30 are received over

an insulator 14. A gate electrode 24 is received proximate floating body channel region 30, with “proximate” in the context of this document requiring being in operable closeness to a floating body channel region to enable operation of the field-effect transistor to selectively cause current flow through some portion of the channel region. A gate dielectric 22 is received between gate electrode 24 and floating body channel region 30.

Floating body channel region 30 comprises a semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising region 16 and a semiconductor silicon-comprising region 18 received between semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising region 16 and gate dielectric 22. Semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising region 16 has greater quantity of Ge than any quantity of Ge within semiconductor silicon-comprising region 18 as explained fully above.

In one embodiment, $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising region 16 has a thickness of at least 20 Angstroms, and in one embodiment has a thickness of from about 100 Angstroms to about 600 Angstroms. In one embodiment wherein the transistor is partially depleted in operation, semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising region 16 has a thickness of from about 300 Angstroms to about 600 Angstroms. In one embodiment wherein the transistor is fully depleted in operation, semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising region 16 has a thickness of from about 100 Angstroms to about 300 Angstroms. In one embodiment where semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising region 16 has a thickness of from about 20 Angstroms to about 50 Angstroms, x is from 0.5 to 0.6.

In one embodiment, $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising region 16 has a thickness which is from about 25% to about 75% of total thickness of floating body channel region 30. Semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising region 16 may have a thickness which is about equal to, less than, or greater than (as shown) that of semiconductor silicon-comprising region 18. Semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising region 16 and semiconductor silicon-comprising region 18 might be provided to have the same maximum widths, or different maximum widths. For example and by way of example only, Fig. 5 depicts semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising region 16 having a greater maximum width 34 than a maximum width 36 of semiconductor silicon-comprising region 18. This size relationship might of course be reversed, or the maximum widths made equal.

Without being limited to any advantages or theory of operation, constructions as provided above and in certain embodiments below might enhance floating body field-effect transistor operation. For example, the band gap offset between $\text{Si}_x\text{Ge}_{(1-x)}$ and silicon (that has low or no Ge content) lies in the valence band with type II alignment, thereby forming a SiGe potential well for excessive holes which as a result of channel hot electron impact ionization are stored in the bottom $\text{Si}_x\text{Ge}_{(1-x)}$ potential well. Further, a smaller source/drain junction in a thin $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising floating body channel might be provided and result in less hole dissipation and longer refresh time than in a floating body channel region the entirety of which is homogenous and predominantly comprises silicon, or in a floating body channel region which is homogenous and predominantly comprises $\text{Si}_x\text{Ge}_{(1-x)}$. Further, the above attributes are applicable in both partially depleted SOI and fully depleted SOI floating body cells.

Further embodiments are next described with reference to Figs. 6 and 7. Like numerals from the above first described embodiments are utilized where appropriate, with differences being indicated with the suffix "a" or with different numerals. Fig. 6 depicts a semiconductor substrate 10a at a processing step subsequent to that depicted by Fig. 4 and alternate to that depicted by Fig. 5. Fig. 6 depicts etching into unmasked portions of semiconductor silicon-comprising layer 18 and semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer 16 using gate dielectric 22 and gate electrode 24 at least in part as a mask for such etching. Such also depicts using anisotropically etched insulative sidewall spacers 26 as masking for such etching, and the forming of floating body channel region 30a which comprises semiconductor silicon-comprising layer 18 and semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer 16. In Fig. 6 and for purposes of the continuing discussion, such can be considered as comprising respective laterally outermost sidewalls 37.

After the etching, semiconductive silicon-comprising material is epitaxially grown from laterally outermost sidewalls of at least the silicon-comprising layer to form a pair of source/drain regions. Fig. 7 depicts one example wherein semiconductive silicon-comprising material 39 has been epitaxially grown from laterally outermost sidewalls 37 of both silicon-comprising layer 18 and $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer 16 to form a pair of

source/drain regions 38. Semiconductive silicon-comprising material 39 might comprise any of the materials described above with respect to layers 18 and 16, and ideally includes low Ge quantity or is void of Ge as described above.

Regardless and further in the depicted example Fig. 7 embodiment, pair of

5 source/drain regions 38 can be considered as respectively comprising an elevated source/drain portion 40 and a non-elevated source/drain portion 42.

Further embodiments are next described with reference to Figs. 8-10 with respect to a semiconductor substrate 10b. Like numerals from the first

described embodiment have been utilized where appropriate, with differences

10 being indicated with a suffix "b" or with different numerals. Fig. 8 depicts alternate processing to that depicted at least in Fig. 4. In Fig. 8, another

semiconductor silicon-comprising layer 44 has been provided to be received between semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer 16 and insulator 14.

Semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer 16 is provided to have greater

15 quantity of Ge than any quantity of Ge within such another semiconductor silicon-comprising layer 44. Accordingly, example attributes as respects Ge

quantity in layer 44 are the same as that described above with respect to semiconductor silicon-comprising layer 18, although layer 18 and 44 may have

different respective Ge quantities, if any. By way of example only, a thickness

20 range for layer 44 is from about 20 Angstroms to about 100 Angstroms. Further and regardless, Fig. 8 depicts an example embodiment wherein semiconductor

$\text{Si}_x\text{Ge}_{(1-x)}$ -comprising region 16 is not received directly physically contacting against insulator 14.

Processing may occur subsequent to Fig. 8 in accordance with Fig. 5

25 and/or Figs. 6-7, or otherwise, in fabrication of a floating body channel region. By way of example only, Fig. 9 depicts processing corresponding to that of Fig.

6 in formation of a floating body channel region 30b. Fig. 10 depicts processing corresponding to that of Fig. 7 in the fabrication of a pair of source/drain

regions 38.

30 Further embodiments of the invention are next described with reference to Figs. 11-16. Fig. 11 depicts processing of the Fig. 4 substrate to produce an

alternate construction to that depicted by Fig. 6 in conjunction with a semiconductor substrate 10c. Like numerals from the first described

embodiments have been utilized where appropriate, with differences being

indicated with the suffix “c” or with different numerals. In the context of Fig. 11, anisotropically etched sidewall spacers 26 might be considered as first sidewall spacers formed over sidewalls of gate electrode 24. Figs. 11-16 depict an embodiment wherein etching occurs into unmasked portions of the

5 semiconductor silicon-comprising layer and the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer to form a floating body channel region comprising such layers using the gate dielectric and the gate electrode at least in part as a mask. Fig. 11 illustrates first etching having been conducted through semiconductor silicon-comprising layer 18 at least to semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer 16
10 using gate dielectric 22, gate electrode 24, and first sidewall spacers 26 at least in part as masking during such etching. Such might, by way of example only, be conducted as a timed etch, or an etching chemistry selected to selectively etch silicon-comprising layer 18 selectively relative to $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer 16. Example selective etching chemistries for doing so include plasma using
15 either a SF_6 , H_2 , and CF_4 mixture or a CF_4 , CH_2F_2 , N_2 , and O_2 mixture.

Referring to Fig. 12, second sidewall spacers 48 have been formed over first sidewall spacers 26 and over sidewalls of etched-through semiconductor silicon-comprising layer 18. An example technique for doing so includes deposition and maskless anisotropic etch. In one embodiment, second sidewall
20 spacers 48 are ideally selectively etchable relative to first sidewall spacers 26.

Referring to Fig. 13, a second etching has been conducted, this time through at least some of semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer 16 using gate dielectric 22, gate electrode 24, first sidewall spacers 26, and second sidewall spacers 48 at least in part as masking during such etching. Fig. 13 depicts one
25 example embodiment wherein $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer 16 is completely etched through to insulator 14, and forms a floating body channel region 30c.

Referring to Fig. 14, insulative material 50 has been formed over sidewalls of semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer 16. An example technique for doing so includes exposure to oxidizing conditions effective to
30 thermally oxidize such sidewalls, thereby forming an insulative silicon-germanium oxide material. An example lateral thickness range for insulative material 50 is from about 30 Angstroms to about 300 Angstroms.

Referring to Fig. 15, second sidewall spacers 48 (not shown) have been etched to expose sidewalls of semiconductor silicon-comprising layer 18.

Where, for example, insulative material 50 comprises a silicon-germanium oxide, first spacers 26 comprise silicon dioxide, and second spacers 48 comprise silicon nitride, an example etching to produce the Fig. 15 construction includes a mixture of H_3PO_4 and H_2O heated to from about 150°C to about 180°C .

Referring to Fig. 16, semiconductive silicon-comprising material 39 has been epitaxially grown from laterally outermost sidewalls of only silicon-comprising layer 18 (since sidewalls of semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer 16 are covered with insulator 50) to form a pair of source/drain regions 38c.

Accordingly and by way of example only, Figs. 5, 7, and 10 depict example embodiments wherein semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising region 16 of a respective floating body channel region comprises laterally outermost sidewalls which directly physically contact against the respective source/drain regions. On the other hand, Fig. 16 depicts an example embodiment wherein semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising region 16 of a floating body channel region comprises laterally outermost sidewalls which do not directly physically contact against the source/drain regions. For example and by way of example only, the Fig. 16 embodiment depicts insulative material 50 being received between at least some of the laterally outermost sidewalls of the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising region 16 and the source/drain regions 38c, with Fig. 16 more specifically illustrating insulative material 50 being received between all of the laterally outermost sidewalls of the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising region 16 and the source/drain regions 38c.

Further example embodiments are next described with reference to Fig. 17 with respect to a semiconductor substrate 10d. Like numerals from the above-described embodiments are utilized where appropriate, with differences being indicated with the suffix "d" or with different numerals. Fig. 17 depicts processing subsequent to that depicted by Fig. 5, although such Fig. 17 processing could be conducted subsequent to any of that depicted by Figs. 7, 10, or 16, by way of examples only. In Fig. 17, a semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising material 54 has been epitaxially grown outwardly from silicon-comprising pair of highest dopant concentration n-type source/drain regions 28 to form elevated source/drain portions 55 comprising semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising material. $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising material 54 might be the same or

different in composition from that of $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer 16 described above. In one embodiment, Ge quantity in elevated source/drain portions 55 is greater than any quantity of Ge within non-elevated source/drain portions 28. In one embodiment, non-elevated source/drain portions 28 are void of Ge.

5 Regardless in one embodiment, non-elevated source/drain portions 28 comprise silicon.

Without being limited by any theory of invention or operation, elevated source/drain portions comprising the stated $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising material as part of the source/drain regions may help increase probability of programming
10 by impact ionization in excessive hole accumulation in a $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising region of a floating body channel region. Band bending can increase in the overlap region as to increase tunneling from the valence band via gate induced drain leakage, and also possibly help excessive hole generation during programming.

15 Further embodiments of the invention are next described in connection with Figs. 18-20. Like numerals from the above-described embodiments have been utilized where appropriate, with differences being indicated with the suffix "e" or with different numerals. Fig. 18 depicts a semiconductor substrate 10e largely in accordance with the example Fig. 17 processing. However as with
20 Fig. 17, processing in connection with source/drain fabrication in production of the embodiments of Figs. 7, 10 and/or 16, or otherwise, is also contemplated in the context of Fig. 18.

In Fig. 18, a semiconductor silicon-comprising layer 60 has been formed over insulator 14. Composition of layer 60 in certain embodiments is in
25 accordance with composition of layer 18 as described above. Accordingly, such may comprise Ge, or may be void of Ge. Regardless, example gate construction 20 is depicted as being formed thereover.

Referring to Fig. 19, n-type conductivity enhancing impurity has been ion implanted into unmasked portions of semiconductor silicon-comprising layer 60
30 to form a pair of highest dopant concentration n-type source/drain regions 28e comprising semiconductor silicon-comprising layer 60 using gate dielectric 22 and gate electrode 24 at least in part as a mask during such ion implanting. A floating body channel region 30e is formed between pair of source/drain regions 28e, and comprises semiconductor silicon-comprising layer 60.

Referring to Fig. 20, semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising material 54 has been epitaxially grown outwardly from pair of highest dopant concentration n-type silicon-comprising source/drain regions 28e to form elevated source/drain portions 55 which comprise semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising material. Accordingly by way of example only, and further independent of method, Fig. 20 depicts an example floating body field-effect transistor 32e comprising a pair of source/drain regions 28e/55 having a floating body channel region 30e received therebetween. Source/drain regions 28e/55 and floating body channel region 30e are received over an insulator 14. A gate electrode 24 is received proximate floating body channel region 30e, with a gate dielectric 22 being received between gate electrode 24 and floating body channel region 30e. Each of the pair of source/drain regions 28e/55 comprises an elevated source/drain portion 55 and a non-elevated source/drain portion 28e. The elevated source/drain portions comprise $\text{Si}_x\text{Ge}_{(1-x)}$. Non-elevated source/drain portions 28e comprise highest dopant concentration portions comprising silicon. Ge quantity in elevated source/drain portions 55 is greater than any quantity of Ge within the highest dopant concentration portions of non-elevated silicon-comprising source/drain portion 28e.

Further example embodiments are next described in connection with Figs. 21-24 in connection with a semiconductor substrate 10f. Like numerals from the above-described embodiments are utilized where appropriate, with differences being indicated with the suffix "f" or with different numerals. Fig. 21 is similar to the in-process embodiment of Fig. 3, however with a $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer 16f not being homogenous at least regarding Ge concentration. For example, Fig. 21 depicts one portion 62 intended to designate a different Ge concentration from that of another portion 64 of $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer 16f. For example, portion 62 might have higher Ge concentration than portion 64, or portion 64 might have higher concentration Ge than portion 62. Further, a gradual or other different gradient in Ge concentration across the thickness of $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer 16f may be used.

Figs. 22 and 23 illustrate subsequent processing occurring which corresponds to that of Figs. 4 and 5, respectively. Alternately by way of example only, processing in accordance with any of the other above-described embodiments might also be conducted. Fig. 24 depicts processing subsequent to

that of Fig. 23 corresponding in accordance with processing depicted by Fig. 17. Alternately by way of example only, processing in accordance with any of the other above-described embodiments might also be conducted.

Without being limited by any theory of invention or operation, in one example embodiment, germanium concentration in portion 64 is provided to be higher than germanium concentration in portion 62. Such might facilitate displacing hole quantity slightly away from insulator 14 to separate such holes from defects inherently occurring at an interface of a semiconductive material such as silicon with insulator 14. Further, a germanium concentration gradient may help control carrier lifetime within the floating body channel for retention improvement.

Further example embodiments are next described with reference to Figs. 25-28 in connection with a semiconductor substrate 10g. Like numerals from the above-described embodiments are utilized where appropriate, with differences being indicated with the suffix "g" or with different numerals. Fig. 25 depicts processing of the Fig. 22 substrate alternate to that depicted by Fig. 23. For example and by way of example only, Fig. 25 depicts previous formation of a semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer 64 over and in direct physical contact with a semiconductor silicon-comprising material 62 that is received over an insulator 14. Semiconductor silicon-comprising material 62 in one embodiment comprises Ge, and might be considered as a first $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer. In one embodiment, Ge concentration in semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer 64 is of greater concentration than any Ge concentration in silicon-comprising layer 62, and in one embodiment semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer 64 might be considered as a second $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer 64. A semiconductor silicon-comprising layer 18 has been formed over and in direct physical contact with semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer 64. The semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer 64 has greater quantity of Ge than any quantity of Ge within semiconductor silicon-comprising layer 18. Example gate construction 20 has been formed over semiconductor silicon-comprising layer 18.

Fig. 25 also depicts etching having been conducted into unmasked portions of semiconductor silicon-comprising layer 18, second $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer 64, and first $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer 62 to form a

floating body channel region 30g comprising at least semiconductor silicon-comprising layer 18 and first $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer 62.

Referring to Fig. 26, at least some of second $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer 64 has been etched selectively relative to first $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer 62, thereby leaving the depicted gap. The depicted structure would be supported at opposite ends on portions received into and out of the plane of the page upon which Fig. 26 appears. Example etching a higher concentration Ge-comprising silicon-germanium material relative to lower germanium or no germanium concentration silicon-comprising material includes using an HF, HNO_3 , H_2O solution or a CH_3COOH , H_2O_2 , HF, H_2O solution, or using CF_4 , CF_2Cl_2 , and HBr plasmas.

Referring to Fig. 27, insulative material 68 has been provided to replace at least some of second $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer 64 (not shown) which was removed. An example technique for doing so comprises thermal oxidation of one or both of materials 18 and 62. An example thickness range for insulative material 68 is from about 20 Angstroms to about 250 Angstroms. Regardless, outer sidewalls of material 18 and 62 are ultimately outwardly exposed as shown in Fig. 27, with Fig. 28 depicting subsequent epitaxial growth of a semiconductive silicon-comprising material 70 from laterally outermost sidewalls of at least the silicon-comprising layer 18 and first $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer 62 to form a pair of source/drain regions 71. Not being limited by any theory of invention or operation, a thin insulative layer 68 provided as described in the Fig. 28 embodiment might further isolate excessive holes which are stored in a bottom silicon-germanium-comprising buried channel region and reduce dissipation and thereby perhaps enhance charge retention.

Further embodiments are next described in connection with Figs. 29-36 with respect to a semiconductor substrate 10h. Like numerals from the above-described embodiments are utilized where appropriate, with differences being indicated with a suffix "h" or with different numerals. Referring to Fig. 29, a semiconductor first silicon-comprising layer 72 has been formed over insulator 14. Composition and dimensional parameters of first silicon-comprising layer 72 can, by way of example only, be the same as those described above with respect to layer 18 of the first-described embodiment. A semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer 74 has been formed over first silicon-

comprising layer 72. Composition can, by way of example only, be the same as that described above in connection with $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer 16. An example thickness range for semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer 74 is from about 20 Angstroms to about 250 Angstroms. A semiconductor second silicon-comprising layer 76 is formed over semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer 74. By way of example only, composition for second silicon-comprising layer 76 may be the same as that described above with respect to layer 18, although layers 72 and 76 of course need not be, but may be, of the same composition. An example thickness range for layer 76 is from 20 Angstroms to 250 Angstroms.

Referring to Fig. 30, an example gate construction 20 has been formed over second silicon-comprising layer 76.

Referring to Fig. 31, etching has been conducted into unmasked portions of second silicon-comprising layer 76 and semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer 74 at least to an outer surface of first silicon-comprising layer 72. Such might be conducted by a timed etch, or an etch at least through semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer 74 which is substantially selective to semiconductor first silicon-comprising layer 72.

Referring to Fig. 32, second spacers 48h have been formed over first spacers 26 and laterally outermost sidewalls of first silicon-comprising layer 76 and $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer 74.

Referring to Fig. 33, etching is continued this time into first silicon-comprising layer 72 at least using semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer 74, second silicon-comprising layer 76, second sidewall spacers 48h, first sidewall spacers 26, gate dielectric 22, and gate electrode 24 as a mask during such etching. As depicted, such etching is in one embodiment completely through first silicon-comprising layer 72 to insulator 14. In one embodiment, such thereby forms a floating body channel region 30h.

Referring to Fig. 34, insulative material 50h has been formed over outermost lateral sidewalls of first silicon-comprising layer 72.

Referring to Fig. 35, second sidewall spacers 48h (not shown) have been removed to expose outer lateral sidewalls of second silicon-comprising layer 76 and semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer 74 of floating body channel region 30h.

Referring to Fig. 36, semiconductive silicon-comprising material 39 has been epitaxially grown from outermost lateral sidewalls of second silicon-comprising layer 76 and semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer 74 of floating body channel region 30h to form a pair of source/drain regions 38h.

5 Without being limited by any theory of invention or operation, such might facilitate excess hole storage within the floating body channel region, and reduce excessive hole dissipation to the source/drains, thereby lengthening required refresh time.

10 Regardless, and by way of example only, Fig. 36 depicts an example embodiment floating body field-effect transistor 32h comprising a pair of source/drain regions 38h having a floating body channel region 30h received therebetween. The source/drain regions 38h and floating body channel region 30h are received over an insulator 14. A gate electrode 24 is provided proximate floating body channel region 30h, with a gate dielectric 22 being received
15 between gate electrode 24 and floating body channel region 30h. Floating body channel region 30h comprises a semiconductor first silicon-comprising region 72, a semiconductor second silicon-comprising region 76, and a semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising region 74 received between region 76 and 72. Semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising region 74 has greater quantity of Ge than
20 any quantity of Ge within each of semiconductor first and second silicon-comprising regions 72, 76, respectively.

Semiconductor first silicon-comprising region 72 is received directly physically contacting against insulator 14, and comprises laterally outermost sidewalls. An insulative material 50h is received between at least some of such
25 laterally outermost sidewalls and source/drain regions 38h. In one embodiment, first and second silicon-comprising regions 72, 76, respectively, are void of Ge. In one embodiment, semiconductor first and second silicon-comprising region 72, 76, respectively, consists essentially of p-doped silicon. In one embodiment, second silicon-comprising region 76 and semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising
30 region 74 comprise laterally outermost sidewalls which directly physically contact against source/drain regions 38h.

In one embodiment, a method of forming a floating body field-effect transistor includes forming a semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer and a semiconductor silicon-comprising layer over an insulator. Either might be

formed before the other. Regardless, a gate dielectric and a gate electrode are formed over the semiconductor silicon-comprising layer. Using the gate dielectric and the gate electrode at least in part as a mask, etching is conducted into unmasked portions of the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer and the semiconductor silicon-comprising layer to form a floating body channel region comprising the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer and the semiconductor silicon-comprising layer. By way of example only, Figs. 13 and 32/33 depict exemplary such processings.

Insulative material is formed over outermost lateral sidewalls of only one of the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer and the semiconductor silicon-comprising layer of the floating body channel region and not over the other of the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer and the semiconductor silicon-comprising layer of the floating body channel region. By way of example only, Figs. 14 and 34 depict such processing. After such formation of insulative material, semiconductive silicon-comprising material is epitaxially grown from outermost lateral sidewalls of the other of the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer and the semiconductor silicon-comprising layer of the floating body channel region to form a pair of source/drain regions. Again by way of example only, Figs. 16 and 36 depict exemplary such processing.

Further embodiments are next described in conjunction with Figs. 37-43 with respect to a semiconductor substrate 10m. Like numerals from the above-described embodiments are utilized where appropriate, with differences being indicated with the suffix "m" or with different numerals. Referring to Fig. 37, a semiconductive material first region 80 has been formed over insulator 14. By way of examples only, composition for the same might be either of that described above in connection with layers 16 and 18 in the first-described embodiments. Accordingly and in but one embodiment, first region 80 comprises a silicon-comprising material which has been deposited over insulator 14, and in one embodiment in direct physical contact therewith.

Referring to Fig. 38, trenches 81 and 82 have been etched into silicon-comprising material 80 to insulator 14.

Referring to Fig. 39, trenches 81 and 82 have been filled with insulative material 84. Example materials 84 include doped or undoped silicon dioxide, and/or silicon nitride. An example manner of forming the construction of Fig.

39 is by deposition of material 84 effective to overfill trenches 81 and 82, followed by chemical mechanical polishing thereof at least to an outer surface of semiconductive material first region 80. For purposes of the continuing discussion, first region 80 can be considered as comprising laterally outermost
5 sidewalls 85 having insulative material 84 received contacting directly physically there-against. Such provides but one example method of forming a semiconductive material first region 80 over an insulator 14, where insulative material 84 is received contacting directly physically against laterally outermost sidewalls 85 of first region 80. Any alternate example manner of forming the
10 same might also be utilized, and whether existing or yet-to-be developed.

Referring to Fig. 40, a semiconductive material second region 86 has been formed over and in direct physical contact with semiconductive material first region 80 and over insulative material 84. Again, example materials for semiconductive second material second region 86 are either of those as
15 described above in connections with layers 16 and 18 of the first-described embodiment. Alternate materials are, of course, contemplated. Regardless, materials 80 and 86 might be of the same composition, or of different composition. Further, respective materials 80 and 86 might be homogenous or non-homogenous. One manner of forming semiconductive material second
20 region 86 is by epitaxial growth. For example, a seed layer can be deposited at least over insulative material 84, with material 86 being epitaxially grown therefrom and from semiconductive material first region 80. In one embodiment and after such growth, semiconductive material second region 86 might be polished, for example by chemical mechanical polishing. Regardless, Fig. 40
25 depicts a gate dielectric 88 as having been formed over semiconductive material second region 86. An example material is thermally grown silicon dioxide.

Referring to Fig. 41, a gate construction 89 has been formed. Such is depicted as comprising a gate electrode 90 comprised of conductive layers 91 and 92. By way of example only, conductive layer 92 might comprise
30 conductively doped polysilicon, while conductive layer 91 might comprise one or a combination of a refractory metal and/or a refractory metal silicide. Gate construction 89 is also depicted as comprising anisotropically etched insulative sidewall spacers 93 which have been formed over laterally outermost sidewalls

of gate electrode 90. An insulative cap (not shown) might also of course be formed.

Referring to Fig. 42, etching has been conducted into unmasked portions of semiconductive material second region 86 to insulative material 84 to form a floating body channel region 30m comprising semiconductive material first region 80 and semiconductive material second region 86. Such etching has been conducted using gate dielectric 88 and gate electrode 90 at least in part as a mask for such etching. In the depicted embodiment, anisotropically etched sidewall spacers 93 have also been used as a mask during such etching, with semiconductive material second region 86 being unmasked first by the etching of gate dielectric 88. For purposes of the continuing discussion, semiconductive material second region 86 can be considered as comprising laterally outermost sidewalls 94.

Referring to Fig. 43, semiconductive material has been epitaxially grown from laterally outermost sidewalls 94 of at least semiconductive material second region 86 to form a pair of source/drain regions 96. In one embodiment and as shown, pair of source/drain regions 96 are epitaxially grown over insulative material 84 and in one embodiment in direct physical contact therewith. Each source/drain region 96 in one embodiment, and as shown, is formed to comprise an elevated source/drain portion 97 and a non-elevated source/drain portion 98. In one embodiment, source/drain regions comprise silicon, with example materials being as described above in connection with source/drain regions 38 of the example Fig. 7 embodiment.

Fig. 43 also depicts an example floating body field-effect transistor 100 independent of method of fabrication. In one such embodiment, such comprises a pair of source/drain regions 96 having a floating body channel region 30m received therebetween. Source/drain regions 96 and floating body channel region 30m are received over an insulator 14. A gate electrode 90 is received proximate floating body channel region 30m, with a gate dielectric 88 being received between gate electrode 90 and floating body channel region 30m. Such floating body channel region comprises first and second regions 80 and 86, respectively, with second region 86 being received elevationally between gate dielectric 88 and first region 80. First region 80 comprises laterally outermost sidewalls 85, with insulative material 84 being received contacting directly

physically against laterally outermost sidewalls 85 of first region 80. In one embodiment, first region 80 has a thickness which is greater than that of second region 86. In one embodiment, each of first and second regions 80 and 86 is void of Ge. Yet in one embodiment, at least one of first and second regions 80 and 86, respectively, comprises Ge. One or both of regions 80 and 86 might form hole storage volume. In one embodiment, region 80 comprises hole storage volume and in one embodiment an elevationally inward portion thereof. Region 80 may comprise $\text{Si}_x\text{Ge}_{(1-x)}$ for example in any of the orientations, positions, and/or concentrations as described above and with or without other silicon-comprising material as also described above.

CLAIMS:

1. A floating body field-effect transistor comprising:
a pair of source/drain regions having a floating body channel region
received therebetween, the source/drain regions and the floating body channel
5 region being received over an insulator;
a gate electrode proximate the floating body channel region;
a gate dielectric received between the gate electrode and the floating body
channel region;
the floating body channel region comprising a semiconductor
10 $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising region; and
the floating body channel region comprising a semiconductor
silicon-comprising region received between the semiconductor
 $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising region and the gate dielectric, the semiconductor
 $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising region having greater quantity of Ge than any quantity of
15 Ge within the semiconductor silicon-comprising region.
2. The floating body field-effect transistor of claim 1 wherein the
semiconductor silicon-comprising region is void of Ge.
3. The floating body field-effect transistor of claim 1 wherein the
semiconductor silicon-comprising region comprises Ge.
- 20 4. The floating body field-effect transistor of claim 3 wherein Ge
quantity in the semiconductor silicon-comprising region is less than about
10 atomic per cent.
5. The floating body field-effect transistor of claim 4 wherein Ge
quantity in the semiconductor silicon-comprising region is less than about
25 1 atomic per cent.
6. The floating body field-effect transistor of claim 4 wherein Ge
quantity in the semiconductor silicon-comprising region is less than
about 0.1 atomic per cent.

7. The floating body field-effect transistor of claim 1 wherein x is at least 0.5.

8. The floating body field-effect transistor of claim 7 wherein x is at least 0.7.

5 9. The floating body field-effect transistor of claim 7 wherein x is no greater than 0.85.

10. The floating body field-effect transistor of claim 7 wherein x is no greater than 0.8.

10 11. The floating body field-effect transistor of claim 7 wherein x is from 0.7 to 0.85.

12. The floating body field-effect transistor of claim 1 wherein x is from 0.5 to 0.6, and the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising region has a thickness of from about 20 Angstroms to about 50 Angstroms.

15 13. The floating body field-effect transistor of claim 1 wherein the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising region has a thickness of at least 20 Angstroms.

14. The floating body field-effect transistor of claim 13 the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising region has a thickness of from about 100 Angstroms to about 600 Angstroms.

20 15. The floating body field-effect transistor of claim 14 wherein the transistor is partially depleted in operation, and the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising region has a thickness of from about 300 Angstroms to about 600 Angstroms.

25 16. The floating body field-effect transistor of claim 14 wherein the transistor is fully depleted in operation, and the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising region has a thickness of from about 100 Angstroms to about 300 Angstroms.

17. The floating body field-effect transistor of claim 1 wherein the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising region has a thickness which is from about 25% to about 75% of total thickness of the floating body channel region.

18. The floating body field-effect transistor of claim 17 wherein the
5 semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising region has a thickness which is about equal to that of the semiconductor silicon-comprising region.

19. The floating body field-effect transistor of claim 1 wherein the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising region has a thickness which is less than that of the semiconductor silicon-comprising region.

10 20. The floating body field-effect transistor of claim 1 wherein the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising region has a thickness which is greater than that of the semiconductor silicon-comprising region.

21. The floating body field-effect transistor of claim 1 wherein the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising region has a maximum width which is
15 greater than that of the semiconductor silicon-comprising region.

22. The floating body field-effect transistor of claim 1 wherein the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising region and the semiconductor silicon-comprising region have the same maximum widths.

23. The floating body field-effect transistor of claim 1 wherein each of
20 the pair of source/drain regions comprises an elevated source/drain portion and a non-elevated source/drain portion.

24. The floating body field-effect transistor of claim 23 wherein the elevated source/drain portion comprises $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising material.

25 25. The floating body field-effect transistor of claim 24 wherein Ge quantity in the elevated source/drain portion is greater than any quantity of Ge within the non-elevated source/drain portion.

26. The floating body field-effect transistor of claim 25 wherein the non-elevated source/drain portion comprises a highest dopant concentration region, at least the highest dopant concentration region of the non-elevated source/drain portion being void of Ge.

5 27. The floating body field-effect transistor of claim 26 wherein at least the highest dopant concentration region of the non-elevated source/drain portion comprises silicon.

10 28. The floating body field-effect transistor of claim 1 wherein the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising region is received directly physically contacting against the insulator.

29. The floating body field-effect transistor of claim 1 wherein the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising region is not received directly physically contacting against the insulator.

15 30. The floating body field-effect transistor of claim 1 comprising another semiconductor silicon-comprising region received between the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising region and the insulator, the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising region having greater quantity of Ge than any quantity of Ge within the another semiconductor silicon-comprising region.

20 31. The floating body field-effect transistor of claim 1 wherein the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising region comprises laterally outermost sidewalls which directly physically contact against the source/drain regions.

25 32. The floating body field-effect transistor of claim 1 wherein the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising region comprises laterally outermost sidewalls which do not directly physically contact against the source/drain regions.

33. The floating body field-effect transistor of claim 1 wherein the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising region comprises laterally outermost sidewalls, insulative material being received between at least some of the laterally outermost sidewalls and the source/drain regions.

34. The floating body field-effect transistor of claim 33 wherein the insulative material is received between all of the laterally outermost sidewalls and the source/drain regions.

5 35. The floating body field-effect transistor of claim 1 wherein the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising region is homogenous at least regarding Ge concentration.

36. The floating body field-effect transistor of claim 1 wherein the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising region is not homogenous at least regarding Ge concentration.

10 37. The floating body field-effect transistor of claim 36 wherein one portion of the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising region has a higher concentration of Ge than does another portion of the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising region, the another portion being received between the one portion and the insulator.

15 38. The floating body field-effect transistor of claim 36 wherein one portion of the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising region has a higher concentration of Ge than does another portion of the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising region, the one portion being received between the another portion and the insulator.

39. A floating body field-effect transistor comprising:

a pair of source/drain regions having a floating body channel region received therebetween, the source/drain regions and the floating body channel region being received over an insulator;

5 a gate electrode proximate the floating body channel region;

a gate dielectric received between the gate electrode and the floating body channel region; and

each of the pair of source/drain regions comprising an elevated source/drain portion and a non-elevated source/drain portion, the elevated source/drain portion comprising $\text{Si}_x\text{Ge}_{(1-x)}$, the non-elevated source/drain portion comprising a highest dopant concentration portion comprising silicon, Ge quantity in the elevated source/drain portion being greater than any quantity of Ge within the highest dopant concentration portion of the non-elevated silicon-comprising source/drain portion.

15 40. The floating body field-effect transistor of claim 39 wherein the highest dopant concentration portion of the non-elevated source/drain portion is void of Ge.

41. The floating body field-effect transistor of claim 39 wherein the highest dopant concentration portion of the non-elevated source/drain portion
20 comprises Ge.

42. The floating body field-effect transistor of claim 41 wherein Ge quantity in the highest dopant concentration portion of the non-elevated source/drain portion is less than about 10 atomic per cent.

43. The floating body field-effect transistor of claim 42 wherein Ge
25 quantity in the highest dopant concentration portion of the non-elevated source/drain portion is less than about 1 atomic per cent.

44. A floating body field-effect transistor comprising:
a pair of source/drain regions having a floating body channel region
received therebetween, the source/drain regions and the floating body channel
region being received over an insulator;

5 a gate electrode proximate the floating body channel region;
a gate dielectric received between the gate electrode and the floating body
channel region; and

the floating body channel region comprising a semiconductor
 $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising region, a semiconductor silicon-comprising region, and an
10 insulating material region received between the semiconductor
 $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising region and the semiconductor silicon-comprising region,
the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising region having greater quantity of Ge
than any quantity of Ge within the semiconductor silicon-comprising region.

45. The floating body field-effect transistor of claim 44 wherein the
15 semiconductor silicon-comprising region is void of Ge.

46. The floating body field-effect transistor of claim 44 wherein the
semiconductor silicon-comprising region comprises Ge.

47. The floating body field-effect transistor of claim 46 wherein Ge
quantity in the semiconductor silicon-comprising region is less than
20 about 10 atomic per cent.

48. The floating body field-effect transistor of claim 47 wherein Ge
quantity in the semiconductor silicon-comprising region is less than about
1 atomic per cent.

49. A floating body field-effect transistor comprising:
a pair of source/drain regions having a floating body channel region
received therebetween, the source/drain regions and the floating body channel
region being received over an insulator;

- 5 a gate electrode proximate the floating body channel region;
a gate dielectric received between the gate electrode and the floating body
channel region;
the floating body channel region comprising a semiconductor first
silicon-comprising region, a semiconductor second silicon-comprising region,
10 and a semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising region; the semiconductor
 $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising region being received between the semiconductor first and
second silicon-comprising regions; the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising
region having greater quantity of Ge than any quantity of Ge within each of the
semiconductor first and second silicon-comprising regions; and
15 the semiconductor first silicon-comprising region being received directly
physically contacting against the insulator and comprising laterally outermost
sidewalls, an insulative material being received between at least some of the
laterally outermost sidewalls and the source/drain regions.

50. The floating body field-effect transistor of claim 49 wherein the
20 semiconductor first and second silicon-comprising regions are void of Ge.

51. The floating body field-effect transistor of claim 49 wherein the
semiconductor first and second silicon-comprising regions consist essentially of
p-doped silicon.

52. The floating body field-effect transistor of claim 49 wherein the
25 semiconductor second silicon-comprising region and the semiconductor
 $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising region comprise laterally outermost sidewalls which
directly physically contact against the source/drain regions.

53. A floating body field-effect transistor comprising:
a pair of source/drain regions having a floating body channel region
received therebetween, the source/drain regions and the floating body channel
region being received over an insulator;

5 a gate electrode proximate the floating body channel region;
a gate dielectric received between the gate electrode and the floating body
channel region; and

10 the floating body channel region comprising first and second regions, the
second region being received elevationally between the gate dielectric and the
first region, the first region comprising laterally outermost sidewalls, insulative
material being received contacting directly physically against the laterally
outermost sidewalls of the first region.

54. The floating body field-effect transistor of claim 53 wherein each
of the pair of source/drain regions is formed over the insulative material.

15 55. The floating body field-effect transistor of claim 53 wherein each
of the pair of source/drain regions comprises an elevated source/drain portion
and a non-elevated source/drain portion.

56. The floating body field-effect transistor of claim 53 wherein the
first region has a thickness which is greater than that of the second.

20 57. The floating body field-effect transistor of claim 53 wherein each
of the first and second regions is void of Ge.

58. The floating body field-effect transistor of claim 53 wherein at
least one of the first and second regions comprises Ge.

59. A method of forming a floating body field-effect transistor, comprising:

forming a semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer over an insulator;

forming a semiconductor silicon-comprising layer over and in direct
5 physical contact with the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer, the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer having greater quantity of Ge than any quantity of Ge within the semiconductor silicon-comprising layer;

forming a gate dielectric and a gate electrode over the semiconductor silicon-comprising layer; and

10 using the gate dielectric and the gate electrode at least in part as a mask, ion implanting n-type conductivity enhancing impurity into unmasked portions of the semiconductor silicon-comprising layer and the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer to form a pair of highest dopant concentration n-type source/drain regions comprising the semiconductor silicon-comprising layer and
15 the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer, and forming a floating body channel region between the pair, the floating body channel region comprising the semiconductor silicon-comprising layer and the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer.

60. The method of claim 59 comprising epitaxially growing a
20 semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising material outwardly from the silicon-comprising pair of highest dopant concentration n-type source/drain regions to form elevated source/drain portions comprising the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising material.

61. The method of claim 59 wherein forming the semiconductor
25 $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer forms the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer to be received directly physically contacting against the insulator.

62. The method of claim 59 wherein forming the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer forms the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer to not be received directly physically contacting against the insulator.

63. The method of claim 59 wherein forming the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer to be homogenous at least regarding Ge concentration.

5 64. The method of claim 59 wherein forming the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer to not be homogenous at least regarding Ge concentration.

10 65. The method of claim 64 wherein forming the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer comprising forming one portion of the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer to have a higher concentration of Ge than does another portion of the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer, the another portion being received between the one portion and the insulator.

15 66. The method of claim 64 wherein forming the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer comprising forming one portion of the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer to have a higher concentration of Ge than does another portion of the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer, the one portion being received between the another portion and the insulator.

67. A method of forming a floating body field-effect transistor, comprising:

forming a semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer over an insulator;

forming a semiconductor silicon-comprising layer over and in direct physical contact with the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer, the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer having greater quantity of Ge than any quantity of Ge within the semiconductor silicon-comprising layer;

forming a gate dielectric and a gate electrode over the semiconductor silicon-comprising layer;

using the gate dielectric and the gate electrode at least in part as a mask, etching into unmasked portions of the semiconductor silicon-comprising layer and the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer to form a floating body channel region comprising the semiconductor silicon-comprising layer and the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer; and

after the etching, epitaxially growing semiconductive silicon-comprising material from laterally outermost sidewalls of at least the silicon-comprising layer to form a pair of source/drain regions.

68. The method of claim 67 comprising epitaxially growing semiconductive silicon-comprising material from laterally outermost sidewalls of both the silicon-comprising layer and the $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer to form the a pair of source/drain regions.

69. The method of claim 67 comprising epitaxially growing semiconductive silicon-comprising material from laterally outermost sidewalls of only the silicon-comprising layer to form the pair of source/drain regions.

70. The method of claim 67 wherein forming the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer forms the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer to be received directly physically contacting against the insulator.

71. The method of claim 67 wherein forming the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer forms the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer to not be received directly physically contacting against the insulator.

72. The method of claim 71 comprising forming the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer over another semiconductor silicon-comprising layer, the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising region having greater quantity of Ge than any quantity of Ge within the another semiconductor silicon-comprising region.

73. The method of claim 72 comprising epitaxially growing semiconductive silicon-comprising material from laterally outermost sidewalls of the another silicon-comprising layer and from the $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer to form the pair of source/drain regions.

74. The method of claim 67 wherein,

prior to the etching, forming first sidewall spacers over sidewalls of the gate electrode;

the etching comprises first etching through the semiconductor silicon-comprising layer at least to the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer using the gate dielectric, the gate electrode and the first sidewall spacers at least in part as masking;

the etching comprises after the first etching, forming second sidewall spacers over the first sidewall spacers and over sidewalls of the etched through semiconductor silicon-comprising layer;

the etching comprises after forming the second sidewall spacers, second etching through at least some of the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer using the gate dielectric, the gate electrode, the first sidewall spacers, and the second sidewall spacers at least in part as masking;

after the second etching, forming insulative material over sidewalls of the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer;

after forming the insulative material, etching the second sidewall spacers to expose sidewalls of the semiconductor silicon-comprising layer; and

after etching the second sidewall spacers to expose sidewalls of the semiconductor silicon-comprising layer, conducting said epitaxially growing.

75. The method of claim 67 comprising:
after the etching, selectively etching a portion of the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer relative to the semiconductor silicon-comprising layer;

5 forming insulative material in place of the etched portion; and
after forming the insulative material, conducting said epitaxially growing.

76. A method of forming a floating body field-effect transistor, comprising:

10 forming a semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer over and in direct physical contact with a semiconductor silicon-comprising material that is received over an insulator;

forming a semiconductor silicon-comprising layer over and in direct physical contact with the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer, the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer having greater quantity of Ge than
15 any quantity of Ge within the semiconductor silicon-comprising layer;

forming a gate dielectric and a gate electrode over the semiconductor silicon-comprising layer; and

using the gate dielectric and the gate electrode at least in part as a mask, forming a pair of source/drain regions and forming a floating body channel
20 region between the pair or source/drain regions; the floating body channel region comprising the semiconductor silicon-comprising layer, the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer, and the semiconductor silicon-comprising material.

77. The method of claim 76 wherein forming the pair of source/drain
25 regions comprises etching the semiconductor silicon-comprising layer, the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer, and the semiconductor silicon-comprising material, and thereafter epitaxially growing silicon-containing material from sidewalls of the floating body channel region.

78. A method of forming a floating body field-effect transistor, comprising:

forming a semiconductor silicon-comprising layer over an insulator;

forming a gate dielectric and a gate electrode over the semiconductor

5 silicon-comprising layer;

using the gate dielectric and the gate electrode at least in part as a mask, ion implanting n-type conductivity enhancing impurity into unmasked portions of the semiconductor silicon-comprising layer to form a pair of highest dopant concentration n-type source/drain regions comprising the semiconductor

10 silicon-comprising layer, and forming a floating body channel region between the pair comprising the semiconductor silicon-comprising layer; and

epitaxially growing a semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising material outwardly from the pair of highest dopant concentration n-type silicon-comprising source/drain regions to form elevated source/drain portions

15 comprising the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising material.

79. A method of forming a floating body field-effect transistor, comprising:

forming a semiconductor first $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer over an insulator; forming a semiconductor second $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer over
5 the semiconductor first $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer, the second $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer having greater Ge quantity than the first $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer;

forming a semiconductor silicon-comprising layer over the second $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer, the second $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer having
10 greater quantity of Ge than any quantity of Ge within the semiconductor silicon-comprising layer;

forming a gate dielectric and a gate electrode over the semiconductor silicon-comprising layer;

using the gate dielectric and the gate electrode at least in part as a mask,
15 etching into unmasked portions of the semiconductor silicon-comprising layer, the second $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer, and the first $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer to form a floating body channel region comprising at least the semiconductor silicon-comprising layer and the first $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer;

replacing at least some of the second $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer with
20 insulative material; and

after the replacing, epitaxially growing semiconductive silicon-comprising material from laterally outermost sidewalls of at least the silicon-comprising layer and the first $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer to form a pair of source/drain regions.

80. A method of forming a floating body field-effect transistor, comprising:

forming a semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer and a semiconductor silicon-comprising layer over an insulator;

5 forming a gate dielectric and a gate electrode over the semiconductor silicon-comprising layer;

using the gate dielectric and the gate electrode at least in part as a mask, etching into unmasked portions of the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer and the semiconductor silicon-comprising layer to form a floating body channel
10 region comprising the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer and the semiconductor silicon-comprising layer;

after the etching, forming insulative material over outermost lateral sidewalls of only one of the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer and the semiconductor silicon-comprising layer of the floating body channel region and
15 not over the other of the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer and the semiconductor silicon-comprising layer of the floating body channel region; and

after forming the insulative material, epitaxially growing semiconductive silicon-comprising material from outermost lateral sidewalls of the other of the semiconductor $\text{Si}_x\text{Ge}_{(1-x)}$ -comprising layer and the semiconductor
20 silicon-comprising layer of the floating body channel region to form a pair of source/drain regions.

81. A method of forming a floating body field-effect transistor, comprising:

forming a semiconductive material first region over an insulator, insulative material being received contacting directly physically against laterally
5 outermost sidewalls of the first region;

forming a semiconductive material second region over and in direct physical contact with the semiconductive material first region and over the insulative material;

10 forming a gate dielectric and a gate electrode over the semiconductive material second region;

using the gate dielectric and the gate electrode at least in part as a mask, etching into unmasked portions of the semiconductive material second region to the insulative material to form a floating body channel region comprising the semiconductive material first region and the semiconductive material second
15 region; and

after the etching, epitaxially growing semiconductive material from laterally outermost sidewalls of at least the semiconductive material second region to form a pair of source/drain regions.

82. The method of claim 81 forming the semiconductive first region
20 comprises:

depositing a silicon-comprising material over the insulator;

etching trenches into the silicon-comprising material to the insulator; and filling the trenches with the insulative material.

83. The method of claim 81 wherein forming the semiconductive
25 material second region comprises epitaxial growth.

84. The method of claim 83 comprising polishing the epitaxial grown semiconductive material second region prior to forming the gate dielectric thereover.

85. The method of claim 81 comprising forming anisotropically etched
30 sidewall spacers over laterally outermost sidewalls of the gate electrode, and using said spacers at least in part as said mask during said etching.

86. The method of claim 81 wherein the pair of source/drain regions is epitaxially grown over the insulative material.

87. The method of claim 86 wherein the pair of source/drain regions is formed in direct physical contact with the insulative material.

5 88. The method of claim 81 wherein the pair of source/drain regions is formed to comprise an elevated source/drain portion and a non-elevated source/drain portion.

89. The method of claim 81 comprising forming the first region to have a thickness which is greater than that of the second region.

10 90. The method of claim 81 wherein each of the first and second regions are formed to be void of Ge.

91. The method of claim 81 wherein at least one of the first and second regions is formed to comprise Ge.