

INTER-CELL INTERFERENCE CANCELLATION FRAMEWORK

CLAIM OF PRIORITY UNDER 35 U.S.C. §119

[0001] The present Application for Patent claims priority to Provisional Application Number 61/080,051 entitled "Systems and Methods for Uplink Inter-cell Interference Cancellation Using Hybrid Automatic Repeat (HARQ) Retransmissions," filed July 11, 2008, assigned to the assignee hereof and hereby expressly incorporated by reference herein in their entirety.

BACKGROUND

Field

[0002] The present disclosure relates generally to wireless communications, and more specifically but not exclusively to various electronic circuitry or algorithms for interference management in a wireless network.

Background

[0003] Wireless networks are widely deployed to provide various services to consumers, such as telephony, data, video, audio, messaging, broadcasts, etc. Wireless networks enable broadband communications over a regional, nationwide, or even global region. Such networks are sometimes referred as Wireless Wide Area Networks (WWANs). One common example of a WWAN is a cellular network that supports CDMA2000, a telecommunications standard that uses Code Division Multiple Access (CDMA) to send voice, data, and signaling between mobile subscribers. Another example of a WWAN is a cellular network that provides broadband Internet access to mobile subscribers, such as Evolution-Data Optimized (EV-DO) or Ultra Mobile Broadband (UMB), both of which are part of the CDMA2000 family of air interface standards. Other examples include WCDMA, HSPA, LTE (Long Term Evolution) and LTE-Advanced. These cellular networks generally provide coverage over multiple cellular regions, with a fixed-site base station located in each cell to serve mobile subscribers.

[0004] In one particular exemplary use in a network, a terminal may communicate with a serving base station on the forward and/or reverse link. On the forward link, the terminal may observe high interference from an interfering base station. On the reverse

link, the serving base station may observe high interference from an interfering terminal. The interference on each link may degrade performance of data transmission sent on that link. In future revisions of wireless standards such as LTE, there is a need to support base stations of different powers (e.g., high-powered macrocells and lower-powered picocells). Additionally, there may be some cells (henceforth referred to as femtocells) that operate under “restricted association,” or Closed Subscriber Group (CSG) i.e., they only allow some user terminals (UEs) to connect to them. For example, these UEs may belong to users who subscribe to a special access plan offered by the operator.

[0005] In a traditional homogeneous deployment, an UE typically connects to the cell with the highest geometry (i.e., signal to noise ratio). However, in some cases such as disjoint links, it could connect to a weaker cell as the strongest forward link geometry cell may not be the same as the strongest reverse link cell (or vice versa). Moreover, in a heterogeneous deployment, there are benefits in allowing the UE to connect to a weaker base station. For example, an UE may connect to the cell with the lowest path loss to minimize interference caused to the network, even though its geometry is lower. Similarly, in the case of restricted association, an UE may be forced to connect to a weaker geometry base station as it may not have permission to access the strongest geometry base station.

SUMMARY

[0006] The following presents a simplified summary in order to provide a basic understanding of some aspects of the disclosed aspects. This summary is not an extensive overview and is intended to neither identify key or critical elements nor delineate the scope of such aspects. Its purpose is to present some concepts of the described features in a simplified form as a prelude to the more detailed description that is presented later.

[0007] In accordance with one or more aspects and corresponding disclosure thereof, various aspects are described in connection with canceling an interfering channel by use of an identifier that was used to encode the interfering channel. A network entity (e.g., serving base station and/or interfering base station) makes transmission adjustments that affect a signal to interfering noise ratio (SINR) of one of the channels to enhance cancellation of interference.

[0008] In one aspect, a method is provided for network facilitating wireless inter-cell interference cancellation at a served user equipment (UE) by transmitting a first link encoded with a first identifier to a served UE that also receives an interfering second link from an interfering base station encoded with a second identifier; transmitting the second identifier to the UE, receiving feedback from the served UE indicative of the ability to cancel one of the first and second links from a received signal at the served UE; and causing an adjustment in transmission for a relative change in signal to the interfering noise ratio (SINR) of one of the first and second links responsive to the feedback, wherein the served UE performs cancellation of the second link when received at a higher SINR by decoding the second link with the second identifier, re-encoding the second link with the second identifier, canceling the second link from the received signal, and decoding the first link from the received signal by channel estimation.

[0009] In another aspect, at least one processor is provided for network facilitating wireless inter-cell interference cancellation at a served UE. A first module transmits a first link encoded with a first identifier to a served UE that also receives an interfering second link from an interfering base station encoded with a second identifier. A second module transmits the second identifier to the UE and receives feedback from the served UE indicative of the ability to cancel one of the first and second links from a received signal at the served UE. A third module causes an adjustment in transmission for a relative change in signal to interfering noise ratio (SINR) of one of the first and second links responsive to the feedback. The served UE performs cancellation of the second link when received at a higher SINR by decoding the second link with the second identifier, re-encoding the second link with the second identifier, canceling the second link from the received signal, and decoding the first link from the received signal by channel estimation.

[0010] In an additional aspect, a computer program product is provided for network facilitating wireless inter-cell interference cancellation at a served UE. A computer-readable storage medium comprises a first set of codes for causing a computer to transmit a first link encoded with a first identifier to a served UE that also receives an interfering second link from an interfering base station encoded with a second identifier. A second set of codes causes the computer to transmit the second identifier to the UE and to receive feedback from the served UE indicative of ability to cancel one of the

first and second links from a received signal at the served UE. A third set of codes causes the computer to cause an adjustment in transmission for a relative change in signal to interfering noise ratio (SINR) of one of the first and second links responsive to the feedback. The served UE performs cancellation of the second link when received at a higher SINR by decoding the second link with the second identifier, re-encoding the second link with the second identifier, canceling the second link from the received signal, and decoding the first link from the received signal by channel estimation.

[0011] In another additional aspect, an apparatus is provided for network facilitating wireless inter-cell interference cancellation at a served UE. Means are provided for transmitting a first link encoded with a first identifier to a served UE that also receives an interfering second link from an interfering base station encoded with a second identifier. Means are provided for transmitting the second identifier to the UE and for receiving feedback from the served UE indicative of ability to cancel one of the first and second links from a received signal at the served UE. Means are provided for causing an adjustment in transmission for a relative change in signal to interfering noise ratio (SINR) of one of the first and second links responsive to the feedback. The served UE performs cancellation of the second link when received at a higher SINR by decoding the second link with the second identifier, re-encoding the second link with the second identifier, canceling the second link from the received signal, and decoding the first link from the received signal by channel estimation.

[0012] In a further aspect, an apparatus is provided for network facilitating wireless inter-cell interference cancellation at a served UE. A transmitter transmits a first link encoded with a first identifier to a served UE that also receives an interfering second link from an interfering base station encoded with a second identifier. The transmitter also transmits the second identifier to the served UE. A receiver at either the transmitter of the first link or the interfering base station receives feedback from the served UE indicative of ability to cancel one of the first and second links from a received signal at the served UE. A computing platform causes an adjustment in transmission for a relative change in signal to interfering noise ratio (SINR) of one of the first and second links responsive to the feedback. The served UE performs cancellation of the second link when received at a higher SINR by decoding the second link with the second identifier, re-encoding the second link with the second identifier, canceling the second

link from the received signal, and decoding the first link from the received signal by channel estimation.

[0013] In yet one aspect, a method is provided for facilitating wireless inter-cell interference cancellation by a non-served UE. While a serving base station transmits a first link encoded with a first identifier to a non-served UE, an interfering second link encoded with a second identifier is transmitted. Communication is received from the serving base station indicating that the interfering second link requires interference cancellation by the non-served UE. Transmission is adjusted of the interfering second link to facilitate interference cancellation by the non-served UE.

[0014] In yet another aspect, a computer program product is provided for facilitating wireless inter-cell interference cancellation by a non-served UE. A computer-readable storage medium comprises a set of codes for causing a computer, while a serving base station transmits a first link encoded with a first identifier to a non-served UE, to transmit an interfering second link encoded with a second identifier. A set of codes causes the computer to receive communication from the serving base station indicating that the interfering second link requires interference cancellation by the non-served UE. A set of codes causes the computer to transmit the second identifier directly or indirectly to the non-served UE. A set of codes causes the computer to adjust transmission of the interfering second link to facilitate interference cancellation by the non-served UE.

[0015] In yet an additional aspect, an apparatus is provided for facilitating wireless inter-cell interference cancellation by a non-served UE. Means are provided for, while a serving base station transmits a first link encoded with a first identifier to a non-served UE, transmitting an interfering second link encoded with a second identifier. Means are provided for receiving communication from the serving base station indicating that the interfering second link requires interference cancellation by the non-served UE. Means are provided for transmitting the second identifier directly or indirectly to the non-served UE. Means are provided for adjusting transmission of the interfering second link to facilitate interference cancellation by the non-served UE.

[0016] In yet a further aspect, an apparatus is provided for facilitating wireless inter-cell interference cancellation by a non-served UE. A transmitter, while a serving base station transmits a first link encoded with a first identifier to a non-served UE, transmits an interfering second link encoded with a second identifier. A receiver receives

communication from the serving base station indicating that the interfering second link requires interference cancellation by the non-served UE. The transmitter is further for transmitting the second identifier directly or indirectly to the non-served UE. A computing platform adjusts transmission of the interfering second link to facilitate interference cancellation by the non-served UE.

[0017] To the accomplishment of the foregoing and related ends, one or more aspects comprise the features hereinafter fully described and particularly pointed out in the claims. The following description and the annexed drawings set forth in detail certain illustrative aspects and are indicative of but a few of the various ways in which the principles of the aspects may be employed. Other advantages and novel features will become apparent from the following detailed description when considered in conjunction with the drawings and the disclosed aspects are intended to include all such aspects and their equivalents.

BRIEF DESCRIPTION OF THE DRAWINGS

[0018] The features, nature, and advantages of the present disclosure will become more apparent from the detailed description set forth below when taken in conjunction with the drawings in which like reference characters identify correspondingly throughout and wherein:

[0019] FIG. 1 depicts a block diagram of a wireless communication system with user equipment (UE) communicating with a base station in the presence of an interfering base station.

[0020] FIGS. 2-3 depict a timing diagram of a methodology or sequence of operations for performing pilot, control and traffic integration cancellation.

[0021] FIG. 4 depicts a block diagram of a communication system of user equipment (UE) communicating with respective base stations and subject to interference from the other respective base station.

[0022] FIG. 5 depicts a block diagram of a base station and served user equipment (UE) each having a computing platform for performing methods for performing wireless interference cancellation.

[0023] FIG. 6 depicts a block diagram of a system having a logical grouping of electrical components for performing wireless interference cancellation.

[0024] FIG. 7 depicts a block diagram of a system having a logical grouping of electrical components for enhancing performance of wireless interference cancellation.

[0025] FIG. 8 depicts a block diagram of an apparatus having means for wireless inter-cell interference cancellation.

[0026] FIG. 9 depicts a block diagram of an apparatus having means for network facilitation of inter-cell interference cancellation.

[0027] FIG. 10 depicts a block diagram of an apparatus having means for network facilitation of inter-cell interference cancellation at a non-served UE.

[0028] FIG. 11 depicts a block diagram of a system having a logical grouping of electrical components for enhancing performance of wireless interference cancellation at a non-served UE.

DETAILED DESCRIPTION

[0029] Communication techniques enable efficient communication to an UE (User Equipment) that is subject to a dominant interference signal that is transmitted by a different base station. It is helpful to assume a synchronous system, meaning that the femtocells and picocells have access to a synchronizing source such as the Global Positioning System (GPS). Disclosed interference cancellation techniques, both UE-centric and network-centric, are suitable to this situation. These techniques are particularly advantageous when it is undesirable or difficult to introduce changes in the physical (PHY) and medium access control (MAC) layers at the existing base stations. UE-centric (“backward-compatible”) framework refers to an approach largely implemented by UEs to include pico or femto cells. Network-centric framework closed-loop coordination between base stations and UEs achieves interference mitigation thereby improving network performance. In particular, an interfering base-station can help a “victim” UE by adjusting downlink pilot and control power and adjusting traffic data rates responsive to information that the “victim” UEs provide, including information about the interfering link and the performance of the cancellation itself (e.g., pre-cancellation CQI (channel quality indication) and ACK (acknowledgement)). This feedback information can be sent over the air or using the backhaul.

[0030] The word “exemplary” is used herein to mean “serving as an example, instance, or illustration.” Any embodiment described herein as “exemplary” is not necessarily to be construed as preferred or advantageous over other embodiments. The

disclosed embodiments may be applied to any one or combinations of the following technologies: Code Division Multiple Access (CDMA) systems, Multiple-Carrier CDMA (MC-CDMA), Wideband CDMA (W-CDMA), High-Speed Packet Access (HSPA, HSPA+), Time Division Multiple Access (TDMA) systems, Frequency Division Multiple Access (FDMA) systems, Orthogonal Frequency Division Multiple Access (OFDMA) systems, or other multiple access techniques. A wireless communication system may be designed to implement one or more standards, such as IS-95, cdma2000, IS-856, W-CDMA, TD-SCDMA, and other standards.

[0031] The detailed description set forth below in connection with the appended drawings is intended as a description of various configurations of the invention and is not intended to represent the only configurations in which the invention may be practiced. The detailed description includes specific details for the purpose of providing a thorough understanding of the invention. However, it will be apparent to those skilled in the art that the invention may be practiced without these specific details. In some instances, well-known structures and components are shown in block diagram form in order to avoid obscuring the concepts of the invention.

[0032] Referring now to the drawings, in **FIG. 1**, a wireless communication system **100** facilitates an inter-cell interference cancellation framework **101** performed by an interference mitigating UE (UE_B) **102** in order to effectively communicate with an interference mitigating evolved base station (eNB_B) **104** in the presence of a stronger interfering eNB_A **106** that communicates with a second UE_A **108**.

[0033] In one aspect of the present innovation, interference cancellation by a computing platform **110** at the UE_B **102** is used to allow the decoding of a signal that is subject to strong interference. In one aspect, the interference cancellation can be applied to a pilot channel ("pilots") **112**, control channel **114** and traffic channel **116**. Because the interference is created by a different base station eNB_A **106**, some extra information can be used in this cancellation process. For example, estimating of the interference can be done by decoding the interference and its identifier and re-encoding the interference with the corresponding identifier. It may also done by estimating the transmitted modulation symbols via soft estimation, iterative estimation or some other techniques.

[0034] In one aspect, Pilot Interference Cancellation (PIC) component **118** of the computing platform **110** of the UE_B **102** cancels the pilots **112** from the stronger eNB_A

106 from a received signal (i.e., combined downlink 120 from eNB_B 104 and downlink 122 from eNB_A 106) and then attempts to retrieve the downlink 120 transmitted by the weaker eNB_B 104. PIC component 118 may be advantageous even if traffic interference cancellation is not used. In some interference avoidance schemes, eNB_A 106 yields downlink resources for eNB_B 104. Even in this case, the eNB_A 106 might transmit RS (i.e., reference signals, an alternate name for pilots) for legacy reasons. If the RS of eNB_A 106 and the RS of eNB_B 104 overlap, then PIC is necessary or advantageous to enable a better estimation of the channel of eNB_B 104. If the RS of eNB_A 106 overlap with the traffic channel of eNB_B 104, then the UE_B 102 can either zero out the LLRs or try to cancel the pilots of eNB_A 106 from its signal. The interference cancellation on the pilots 112 requires the UE_B 102 to know the identifier (ID) of each cell 104, 106 as depicted at 124.

[0035] In another aspect, a Control Interference Cancellation (CIC) component 126 of the computing platform 110 of the UE_B 102 performs interference cancellation on the control channels 114 which requires the UE_B 102 to know MAC_IDs 127 of users (e.g., UE_A 108) to which the interfering control channel is transmitted.

[0036] In an additional aspect, a Traffic interference Cancellation (TIC) component 128 of the computing platform 110 of the UE_B 102 performs interference cancellation on the traffic channels 116 without extra actions from the interfering base station eNB_A 106. The traffic interference cancellation requires the UE_B 102 to know control information (i.e., assignments and ACKs) 130 that is relevant to the interfering traffic 116. Communication from the base station eNB_B 104 to UE_B 102 that performs interference cancellation is more efficient if some extra information about the interfering link (downlink 122) and the performance of the cancellation itself is provided to the base station eNB_B 104 as pre-cancellation feedback 132 (CQI and ACK).

[0037] Alternatively or in addition, network entities such as the eNB_B 104 and/or the eNB_A 106 can be part of the part of inter-cell interference cancellation framework 101, enhancing the ability of the UE_B 102. In one aspect, a computing platform 134 of the eNB_B 104 can comprise a PIC component 136, a CIC component 138, and a TIC component 140 that can operate as described below. Further, the interfering eNB_A 106 can cooperate with interference mitigation by use of a pilot power adjustment component 142, a control channel power adjustment component 144, and a traffic data

rate adjustment component **146**. This cooperation is responsive to relevant information (e.g., CQI_A , CQI_B , ACK_A , ACK_B) **148** sent over a backhaul network or radio link (RL) control channel **150**.

[0038] In **FIG. 2**, a methodology or sequence of operations **200** are provided for UE-centric inter-cell interference cancellation performed by an interference mitigating UE (UE_B) **202** in order to effectively communicate with an interference mitigating evolved base station (eNB_B) **204** in the presence of a stronger interfering eNB_A **206** that communicates with a second UE_A **208**.

[0039] In one aspect, Pilot Interference Cancellation (PIC) is performed by a communication **200** as depicted at **210** wherein the pilots sent by the two eNB s **204**, **206** overlap as depicted respectively at **212**, **214**. The pilots sent by each eNB **204**, **206** are cell-specific and they are determined by an eNB_ID (e.g., cellID, sectorID). For PIC **210**, UE_B **202** retrieves the eNB_IDs of both eNB s, depicted respectively at **216**, **218**. UE_B **202** uses the received pilots to estimate the channel of the stronger eNB and cancels the contribution of this eNB from the received pilot sequence (block **220**). Then in block **222**, UE_B **202** uses the second eNB_ID to estimate the channel for the second eNB_A **206**.

[0040] Alternatively or in addition as depicted at **222**, a network-centric Pilot Interference Cancellation (PIC) enhances efforts by the UE_B **202** to cancel the pilots from the stronger eNB_A **208** from the received signal and then attempts to retrieve the signal transmitted by the weaker eNB_B **204**. In particular, the network-centric PIC scheme **222** enables eNB_A **206** to control the power of the pilots such that the UE-centric PIC **210** in the UE_B **202** (e.g., femto-cells) is more efficient (block **223**). In general, this can be particularly suitable to scenarios where dedicated pilots are used and thus an eventual power boost has a limited effect on the whole system.

[0041] In another aspect, Control Interference Cancellation (CIC) is performed as depicted at **224**. In block **225**, the retrieval of the control information sent by the interfering eNB_A **206** is necessary. UE_B **202** decodes the control channel of one eNB_A **206** (block **226**), re-encodes it (block **227**), and cancels it out of the received signal (block **228**).

[0042] In an illustrative implementation for LTE, the control channel_A is scrambled with the MAC_ID of the intended user UE_A **208** as depicted at block **230** and sent unicast from the eNB_A **206** (block **232**). In the case of LTE, the MAC_ID may be

referred to as Cell Radio Network Temporary Identifier (c-RNTI). Thus, it is advantageous for the UE to know the MAC_IDs that are used to scramble the control channel that: (a) occupies the same PHY resources as the control channel from eNB_B 204 to UE_B 202; (b) carries assignments for the traffic channel (traffic from eNB_A 206) that interferes with the traffic from eNB_B 204. It should be appreciated that the cases (a) and (b) are not necessary mutually exclusive. The MAC_IDs that are used to scramble the control_A can be revealed to the UE_B 202: (i) over the air, using PDCCH_A (physical downlink control channel), as depicted at 234, possibly using a special coding scheme; or (b) over the backhaul as depicted at 236.

[0043] Upon knowledge of the MAC_IDs, the UE can choose the PDCCH decoding method that allows the decoding of both PDCCH_B and PDCCH_A (as needed) (block 238). If CIC 224 is performed, the UE_B 202 decodes first the PDCCH that is received at higher SINR (Signal to Interference-plus-Noise Ratio) (block 239).

[0044] In another additional aspect depicted at 240, network-centric Control Interference Cancellation (CIC) procedure enhances the ability of UE_B 202 to decode the control channel (PDCCH) of one eNB_A 206, re-encodes it and cancels it out of the received signal. In particular, the CIC can be performed more efficiently if the transmission of PDCCH_B is adapted to this situation. Assume that the transmission rate on PDCCH_B is much lower than the one on PDCCH_A (block 242). In this situation, eNB_B 204 might choose an encoding scheme for PDCCH_B that maximizes the SINR at which the PDCCH_A is received, thus enabling better decoding of this channel and better CIC (block 244).

[0045] Alternatively or in addition, the CIC can be performed more efficiently if the transmissions of PDCCH_A are adapted to this situation. Assume that cell A is larger and cell B is inside cell A (block 245). In this situation eNB_A 206 might want to boost the power of PDCCH_A such that this channel can be decoded correctly by the UEs close to eNB_B 204. Also, eNB_A 206 might want to do this selectively; in this case, eNB_B 204 can convey some relevant information (cell size and position, the traffic assignments of its users) to eNB_A 206 on the backhaul (block 246) that eNB_A 206 uses to boost the power of the PDCCH_A (block 248). As an alternative or in addition to CIC, control orthogonalization may be used. In such a case, the control channels of the serving and interfering cells use different resources.

[0046] Continuing in FIG. 3, in an additional aspect, UE-centric (“backward-compatible”) Traffic Interference Cancellation (TIC) is depicted at 249 wherein the traffic sent by eNB_A 206 (the interfering traffic) as depicted at 250 can be decoded by the UE_B 202 without any action (power control, rate adjustment) from eNB_A 206 or eNB_B 204. In this instance traffic power A is greater than traffic power B. The decoding of the traffic from eNB_A 206 as depicted at is done by treating the traffic from eNB_B 204 as noise (block 251). This might be possible, if, for example, the traffic sent by eNB_A 206 is intended for a user that is at the cell edge, and thus is received by the UE_B 202 of interest at high power. The UE_B 202 decodes the control information relevant to the traffic sent by eNB_A 206 (block 252).

[0047] The post-cancellation of SINR (Signal to Interference Noise Ratio) of the traffic from eNB_B 204 can be substantially higher than the SINR that considers the traffic from eNB_A 206 as interference as depicted 254. In this situation, it is useful for the UE_B 202 to report to eNB_B 204: (1) the (pre-TIC) CQI (channel quality indication) for link A, denoted as CQI_A at 256; (1a) the ACK for the traffic on link A, denoted as DL ACK_A at 260; and (2) the (post TIC) CQI for link B, denoted as CQI_B as depicted at 264. The UE_B 202 uses the CQI_A and ACK_A to adjust the rate on the link B (block 266). This adjustment can be done in two illustrative ways: (1) assure that the UE_B 202 can perform UE-centric TIC (block 268) or (2) adjust the transmission on the traffic of link B such that the UE_B 202 decodes it without doing UE-centric TIC first (block 270).

[0048] In an additional aspect depicted at 272, network-centric Traffic Interference Cancellation (TIC) can provide the additional SINR required for the UE_B 202 in some instances to decode the interfering traffic (the traffic from eNB_A 206) without extra help from eNB_A 204. In the UE-centric TIC procedure 272, the extra actions required to enable correct decoding of the traffic channel on link B 273 were performed (mainly) by the UE_B 202 and eNB_B 204. In an illustrative implementation, the UE_B 202 sends CQI_A, ACK_A, ACK_B and CQI_B to eNB_B 204 as depicted at 274. The UE_B 202 sends the same information (CQI_A, CQI_B, ACK_A, ACK_B) to eNB_A 206 (e.g. over the backhaul or using the radio link (RL) control channel) (block 276). In one aspect, eNB_B 204 and eNB_A 206 negotiate the rates using the backhaul/RL control channel (block 278). The eNB_A 206 adjusts the rate of the data that is transmitted on the link A 256 such that the UE_B 202 can perform interference cancellation (block 280). The rate adjustment can be done in different ways. For example, if cell B is inside cell A, then eNB_A 206 might

schedule on link A users that (i) are at cell edge (have lower geometries) thus their signal is received at higher power inside the cell, which creates the situation of UE-centric TIC (block 282); (ii) have low data rate (e.g., VoIP users) (block 284). UE-centric TIC can be performed then as described above 249. As depicted at 285, the serving eNB changes its power to improve the SNR for the interfering eNB. This in turn enables the UE to estimate the interfering link better, which it can then cancel. It then gets better SINR from the serving cell.

[0049] In information theory, a scenario in which a pair of users communicates with a pair of base stations is referred to as the interference channel. In the previous scenarios, the presence of the UE_A 208 that is supposed to receive the traffic on link A is not considered explicitly when the traffic on link B does not really affect the reception at UE_A 208. However, in some instances there is a non-dominant interferer situation in which link B is also causing interference for UE_A (block 286). In this situation, the rate adjustment (in fact, rate reduction) on the interfering link that is mentioned before comes at the expense of UE_A 208. The eNB_A 206 and eNB_B 204 might negotiate a rate pair (R_A, R_B) that is suitable for both links A and B (block 288). One illustrative method to achieve a wide range of rate pairs is by resource sharing between two different interference cancellation schemes (block 290). In one exemplary scheme, UE_A 208 cancels the signal received on link B (i.e., the signal intended for UE_B 202) (block 292) while UE_B 202 is decoding its signal treating the signal of link A as noise (block 294). In the other exemplary scheme, UE_B 202 is doing the interference cancellation (block 296) while UE_A 208 treats the signal from eNB_B 204 as noise (block appar

[0050] FIG. 4 is an illustration of a wireless multiple-access communication system 400 in accordance with various aspects. In one example, the wireless multiple-access communication system 400 includes multiple base stations 410 and multiple terminals 420. Further, one or more base stations 410 can communicate with one or more terminals 420. By way of non-limiting example, a base station 410 can be an access point, a Node B, and/or another appropriate network entity. Each base station 410 provides communication coverage for a particular geographic area 402a-c. As used herein and generally in the art, the term "cell" can refer to a base station 410 and/or its coverage area 402a-c depending on the context in which the term is used.

[0051] To improve system capacity, the coverage area **402a**, **402b**, or **402c** corresponding to a base station **410** can be partitioned into multiple smaller areas (e.g., areas **404a**, **404b**, and **404c**). Each of the smaller areas **404a**, **404b**, and **404c** can be served by a respective base transceiver subsystem (BTS, not shown). As used herein and generally in the art, the term "sector" can refer to a BTS and/or its coverage area depending on the context in which the term is used. In one example, sectors **404a**, **404b**, **404c** in a cell **402a**, **402b**, **402c** can be formed by groups of antennas (not shown) at base station **410**, where each group of antennas is responsible for communication with terminals **420** in a portion of the cell **402a**, **402b**, or **402c**. For example, a base station **410** serving cell **402a** can have a first antenna group corresponding to sector **404a**, a second antenna group corresponding to sector **404b**, and a third antenna group corresponding to sector **404c**. However, it should be appreciated that the various aspects disclosed herein can be used in a system having sectorized and/or unsectorized cells. Further, it should be appreciated that all suitable wireless communication networks having any number of sectorized and/or unsectorized cells are intended to fall within the scope of the hereto appended claims. For simplicity, the term "base station" as used herein can refer both to a station that serves a sector as well as a station that serves a cell. It should be appreciated that as used herein, a downlink sector in a disjoint link scenario is a neighbor sector. While the following description generally relates to a system in which each terminal communicates with one serving access point for simplicity, it should be appreciated that terminals can communicate with any number of serving access points.

[0052] In accordance with one aspect, terminals **420** can be dispersed throughout the system **400**. Each terminal **420** can be stationary or mobile. By way of non-limiting example, a terminal **420** can be an access terminal (AT), a mobile station, user equipment, a subscriber station, and/or another appropriate network entity. A terminal **420** can be a wireless device, a cellular phone, a personal digital assistant (PDA), a wireless modem, a handheld device, or another appropriate device. Further, a terminal **420** can communicate with any number of base stations **410** or no base stations **410** at any given moment.

[0053] In another example, the system **400** can utilize a centralized architecture by employing a system controller **430** that can be coupled to one or more base stations **410** and provide coordination and control for the base stations **410**. In accordance with

alternative aspects, system controller **430** can be a single network entity or a collection of network entities. Additionally, the system **400** can utilize a distributed architecture to allow the base stations **410** to communicate with each other as needed. Backhaul network communication **434** can facilitate point-to-point communication between base stations employing such a distributed architecture. In one example, system controller **430** can additionally contain one or more connections to multiple networks. These networks can include the Internet, other packet based networks, and/or circuit switched voice networks that can provide information to and/or from terminals **420** in communication with one or more base stations **410** in system **400**. In another example, system controller **430** can include or be coupled with a scheduler (not shown) that can schedule transmissions to and/or from terminals **420**. Alternatively, the scheduler can reside in each individual cell **402**, each sector **404**, or a combination thereof.

[0054] In an example, system **400** can utilize one or more multiple-access schemes, such as CDMA, TDMA, FDMA, OFDMA, Single-Carrier FDMA (SC-FDMA), and/or other suitable multiple-access schemes. TDMA utilizes time division multiplexing (TDM), wherein transmissions for different terminals **420** are orthogonalized by transmitting in different time intervals. FDMA utilizes frequency division multiplexing (FDM), wherein transmissions for different terminals **420** are orthogonalized by transmitting in different frequency subcarriers. In one example, TDMA and FDMA systems can also use code division multiplexing (CDM), wherein transmissions for multiple terminals can be orthogonalized using different orthogonal codes (e.g., Walsh codes) even though they are sent in the same time interval or frequency sub-carrier. OFDMA utilizes Orthogonal Frequency Division Multiplexing (OFDM), and SC-FDMA utilizes Single-Carrier Frequency Division Multiplexing (SC-FDM). OFDM and SC-FDM can partition the system bandwidth into multiple orthogonal subcarriers (e.g., tones, bins, ...), each of which can be modulated with data. Typically, modulation symbols are sent in the frequency domain with OFDM and in the time domain with SC-FDM. Additionally and/or alternatively, the system bandwidth can be divided into one or more frequency carriers, each of which can contain one or more subcarriers. System **400** can also utilize a combination of multiple-access schemes, such as OFDMA and CDMA. While the power control techniques provided herein are generally described for an OFDMA system, it should be appreciated that the techniques described herein can similarly be applied to any wireless communication system.

[0055] In another example, base stations 410 and terminals 420 in system 400 can communicate data using one or more data channels and signaling using one or more control channels. Data channels utilized by system 400 can be assigned to active terminals 420 such that each data channel is used by only one terminal at any given time. Alternatively, data channels can be assigned to multiple terminals 420, which can be superimposed or orthogonally scheduled on a data channel. To conserve system resources, control channels utilized by system 400 can also be shared among multiple terminals 420 using, for example, code division multiplexing. In one example, data channels orthogonally multiplexed only in frequency and time (e.g., data channels not multiplexed using CDM) can be less susceptible to loss in orthogonality due to channel conditions and receiver imperfections than corresponding control channels.

[0056] In FIG. 5, a serving radio access network (RAN), depicted as an evolved base node (eNB) 500, has a computing platform 502 that provides means such as sets of codes for causing a computer to facilitate wireless inter-cell interference cancellation as either the serving base station or interfering base station. In particular, the computing platform 502 includes a computer readable storage medium (e.g., memory) 504 that stores a plurality of modules 506-510 executed by a processor(s) 520. A modulator 522 controlled by the processor 520 prepares a downlink signal for modulation by a transmitter 524, radiated by antenna(s) 526. A receiver 528 receives uplink signals from the antenna(s) 526 that are demodulated by a demodulator 530 and provided to the processor 520 for decoding. In particular, means (e.g., module, set of codes) 506 are provided for transmitting a first link encoded with a first identifier to a served UE that also receives an interfering second link from an interfering base station encoded with a second identifier. Means (e.g., module, set of codes) 508 are provided for transmitting the second identifier to the UE and for receiving feedback from the UE indicative of ability to cancel one of the first and second links from a received signal at the UE. Means (e.g., module, set of codes) 510 are provided for causing an adjustment in transmission for a relative change in signal to interfering noise ratio (SINR) of one of the first and second links responsive to the feedback. Thereby, the UE is enhanced in performing cancellation of the second link when received at a higher SINR by decoding the second link with the second identifier, re-encoding the second link with the second identifier, canceling the second link from the received signal, and decoding the first link from the received signal by channel estimation. Advantageously a transmit (Tx) power

component **532** can adjust transmission power. A received signal indicator (RSI) **534** can measure signal strength.

[0057] With continued reference to **FIG. 5**, the mobile station or user equipment (UE) **550** has a computing platform **552** that provides means such as sets of codes for causing a computer to perform wireless inter-cell interference cancellation. In particular, the computing platform **552** includes a computer readable storage medium (e.g., memory) **554** that stores a plurality of modules **556-560** executed by a processor(s) **570**. A modulator **572** controlled by the processor **570** prepares an uplink signal for modulation by a transmitter **574**, radiated by antenna(s) **576** as depicted at **577** to the eNB **500**. A receiver **576** receives downlink signals from the eNB **500** from the antenna(s) **576** that are demodulated by a demodulator **560** and provided to the processor **570** for decoding. In particular, means (e.g., module, set of codes) **556** are for accessing a first identifier used by the serving base station to encode a first link. Means (e.g., module, set of codes) **557** are for accessing a second identifier used by the interfering base station to encode a second link. Means (e.g., module, set of codes) **558** are for receiving a signal containing the first and second links. Means (e.g., module, set of codes) **559** are for canceling the second link by estimating the second link with the corresponding identifier and canceling the second link from the received signal. Means (e.g., module, set of codes) **560** are for decoding the first link from the received signal by channel estimation.

[0058] With reference to **FIG. 6**, illustrated is a system **600** that performs wireless inter-cell interference cancellation. For example, system **600** can reside at least partially within user equipment (UE). It is to be appreciated that system **600** is represented as including functional blocks, which can be functional blocks that represent functions implemented by a computing platform, processor, software, or combination thereof (e.g., firmware). System **600** includes a logical grouping **602** of electrical components that can act in conjunction. For instance, logical grouping **602** can include an electrical component for accessing a first identifier used by the serving base station to encode a first link **604**. Moreover, logical grouping **602** can include an electrical component for accessing a second identifier used by the interfering base station to encode a second link **606**. Further, logical grouping **602** can include an electrical component for receiving a signal containing the first and second links **608**. Logical grouping **602** can include an electrical component for canceling the second link by estimating the second link with

the corresponding identifier and canceling the second link from the received signal **610**. Logical grouping **602** can include an electrical component for decoding the first link from the received signal by channel estimation **612**. Additionally, system **600** can include a memory **614** that retains instructions for executing functions associated with electrical components **604** - **612**. While shown as being external to memory **614**, it is to be understood that one or more of electrical components **604** - **612** can exist within memory **614**.

[0059] With reference to **FIG. 7**, illustrated is a system **700** that enhances wireless inter-cell interference cancellation. For example, system **700** can reside at least partially within a base station. It is to be appreciated that system **700** is represented as including functional blocks, which can be functional blocks that represent functions implemented by a computing platform, processor, software, or combination thereof (*e.g.*, firmware). System **700** includes a logical grouping **702** of electrical components that can act in conjunction. For instance, logical grouping **702** can include an electrical component for transmitting a first link encoded with a first identifier to a UE that also receives an interfering second link from an interfering base station encoded with a second identifier **704**. Moreover, logical grouping **702** can include an electrical component for transmitting the second identifier to the UE and for receiving feedback from the UE indicative of ability to cancel one of the first and second links from a received signal at the UE **706**. Further, logical grouping **702** can include an electrical component for causing an adjustment in transmission for a relative change in signal to interfering noise ratio (SINR) of one of the first and second links responsive to the feedback, wherein the UE performs cancellation of the second link when received at a higher SINR by decoding the second link with the second identifier, re-encoding the second link with the second identifier, canceling the second link from the received signal, and decoding the first link from the received signal by channel estimation **708**. Additionally, system **700** can include a memory **714** that retains instructions for executing functions associated with electrical components **704** - **708**. While shown as being external to memory **714**, it is to be understood that one or more of electrical components **704** - **708** can exist within memory **714**.

[0060] In **FIG. 8**, an apparatus **802** is provided for wireless inter-cell interference cancellation. A means **804** is provided for accessing a first identifier used by the serving base station to encode a first link. A means **806** is provided for accessing a

second identifier used by the interfering base station to encode a second link. A means 808 is provided for receiving a signal containing the first and second links. A means 810 is provided for canceling the second link by estimating the second link with the corresponding identifier, and canceling the second link from the received signal. A means 812 is provided for decoding the first link from the received signal by channel estimation.

[0061] In FIG. 9, an apparatus 902 is provided for network facilitated wireless inter-cell interference cancellation. A means 904 is provided for transmitting a first link encoded with a first identifier to a node that also receives an interfering second link from an interfering base station encoded with a second identifier. A means 906 is provided for receiving feedback from the node indicative of ability to cancel one of the first and second links from a received signal at the node. A means 908 is provided for causing an adjustment in transmission for a relative change in signal to interfering noise ratio (SINR) of one of the first and second links responsive to the feedback, wherein the node performs cancellation of the second link when received at a higher SINR by decoding the second link with the second identifier, re-encoding the second link with the second identifier, canceling the second link from the received signal, and decoding the first link from the received signal by channel estimation.

[0062] In FIG. 10, an apparatus 1002 is provided for facilitating wireless inter-cell interference cancellation by a non-served UE. Means 1004 are provided for transmitting an interfering second link encoded with a second identifier while a serving base station transmits a first link encoded with a first identifier to a non-served node. Means 1006 are provided for receiving communication from the serving base station indicating that the interfering second link requires interference cancellation by the non-served node. Means 1008 are provided for transmitting the second identifier directly or indirectly to the non-served UE. Means 1010 are provided for adjusting transmission of the interfering second link to facilitate interference cancellation by the non-served node.

[0063] While the specification describes particular examples of the present invention, those of ordinary skill can devise variations of the present invention without departing from the inventive concept. For example, the teachings herein refer to circuit-switched network elements but are equally applicable to packet-switched domain network elements.

[0064] With reference to FIG. 11, illustrated is a system 1100 that enhances wireless inter-cell interference cancellation. For example, system 1100 can reside at least partially within a base station. It is to be appreciated that system 1100 is represented as including functional blocks, which can be functional blocks that represent functions implemented by a computing platform, processor, software, or combination thereof (*e.g.*, firmware). System 1100 includes a logical grouping 1102 of electrical components that can act in conjunction. For instance, logical grouping 1102 can include an electrical component for transmitting an interfering second link encoded with a second identifier while a serving base station transmits a first link encoded with a first identifier to a non-served UE 1104. Moreover, logical grouping 1102 can include an electrical component for receiving communication from the serving base station indicating that the interfering second link requires interference cancellation by the non-served UE 1106. In addition, logical grouping 1102 can include an electrical component for transmitting the second identifier directly or indirectly to the non-served UE 1108. Further, logical grouping 1102 can include an electrical component for adjusting transmission of the interfering second link to facilitate interference cancellation by the non-served UE 1110. Additionally, system 1100 can include a memory 1114 that retains instructions for executing functions associated with electrical components 1104 - 1110. While shown as being external to memory 1114, it is to be understood that one or more of electrical components 1104 - 1110 can exist within memory 1114.

[0065] By virtue of the foregoing, it should be appreciated that in one aspect, a UE that is receiving interference can benefit from receiving the identifier that encoded the interference. Receipt of the identifier, such as a MAC ID or c-RNTI can advantageously be tunneled from an interfering base station to the serving base station to the UE. This transmission can be prompted by a request initiated by the UE or serving base station.

[0066] In another aspect, Pilot Interference Cancellation for OFDMA systems can be supported. For example, the UE can cancel the reference signal or can use a different interference estimate for resource elements containing the cancelled Reference Signal (RS).

[0067] In an additional aspect, Control Interference Cancellation can be supported. For example, the UE can decode the PDCCH of interfering sector, which can be based on received c-RNTI. Further, the UE can cancel the PDCCH after decoding it.

[0068] In another additional aspect, Inter-Cell Interference Coordination (ICIC) can be performed based on decoded PDCCH assignment.

[0069] In a further aspect, Traffic Interference Cancellation can be supported in situations such as (1) restricted association, (2) range expansion (lower geometry cell, and (3) disjoint links. For example, the UE performs ICIC in each situation. As another example, the serving base station can determine post-cancellation SINR, either directly or by receiving information from the UE, and that the UE could handover to the interfering base station.

[0070] In yet another aspect, CQI based on post-cancellation SINR can be supported. UE feeds back CQI based on post-cancellation SINR. In some instances, the UE also feeds pre-cancellation CQI. The serving eNB schedules can be based on post-cancellation ICIC. In another instance, pre-cancellation CQI is provided when HARQ fails.

[0071] In yet an additional aspect, feedback of control channels is supported. The UE feeds back CQI / ACK corresponding to interfering sectors. The serving base station tunnels the CQI / ACK to the interfering base station. The interfering base station receives the CQI / ACK feedback either directly or over a backhaul connection. In one example, the CQI/ACK can pertain to data. In another example, the CQI/ACK can pertain to PDCCH. In an additional example, the CQI/ACK can pertain to Reference Signal (RS). The serving base station can change (e.g., reduce) its power to aid its UE in ICIC (e.g., based on feedback). The interfering base station can change (e.g., increase) its power to aid a non-served neighbor UE (e.g., based on feedback).

[0072] In yet another additional aspect, an interfering base station can control the rate to enable ICIC. In one instance, this rate control can pertain to PDCCH. In another aspect, the rate control can pertain to PDSCH. The UE can provide feedback and then perform ICIC. The interfering base station provides a rate which enables a non-served UE to decode. (e.g., based on feedback).

[0073] For example, the exemplary aspects discussed above can be implemented with nodes that can reciprocate in playing the role of a transmitting node in one instance and then playing the role of an interfering node in another. Further, fairness can be

meted out in relation to receptivity of a node to favorably respond to a reduced transmit power request. Alternatively, a node can only be provisioned to act as a selected one of a transmitting node and an interfering node.

[0074] Those skilled in the art will understand that information and signals may be represented using any of a variety of different technologies and techniques. For example, data, instructions, commands, information, signals, bits, symbols, and chips that may be referenced throughout the above description may be represented by voltages, currents, electromagnetic waves, magnetic fields or particles, optical fields or particles, or any combination thereof.

[0075] Those skilled in the art will further appreciate that the various illustrative logical blocks, modules, circuits, methods and algorithms described in connection with the examples disclosed herein may be implemented as electronic hardware, computer software, or combinations of both. To clearly illustrate this interchangeability of hardware and software, various illustrative components, blocks, modules, circuits, methods and algorithms have been described above generally in terms of their functionality. Whether such functionality is implemented as hardware or software depends upon the particular application and design constraints imposed on the overall system. Skilled artisans may implement the described functionality in varying ways for each particular application, but such implementation decisions should not be interpreted as causing a departure from the scope of the present invention.

[0076] As used in this application, the terms “component,” “module,” “system” and the like are intended to include a computer-related entity, such as but not limited to hardware, firmware, a combination of hardware and software, software, or software in execution. For example, a component may be, but is not limited to being, a process running on a processor, a processor, an object, an executable, a thread of execution, a program, and/or a computer. By way of illustration, both an application running on a computing device and the computing device can be a component. One or more components can reside within a process and/or thread of execution and a component may be localized on one computer and/or distributed between two or more computers. In addition, these components can execute from various computer readable media having various data structures stored thereon. The components may communicate by way of local and/or remote processes such as in accordance with a signal having one or more data packets, such as data from one component interacting with another

component in a local system, distributed system, and/or across a network such as the Internet with other systems by way of the signal.

[0077] Furthermore, various aspects are described herein in connection with a terminal, which can be a wired terminal or a wireless terminal. A terminal can also be called a system, device, subscriber unit, subscriber station, mobile station, mobile, mobile device, remote station, remote terminal, access terminal, user terminal, terminal, communication device, user agent, user device, or user equipment (UE). A wireless terminal may be a cellular telephone, a satellite phone, a cordless telephone, a Session Initiation Protocol (SIP) phone, a wireless local loop (WLL) station, a personal digital assistant (PDA), a handheld device having wireless connection capability, a computing device, or other processing devices connected to a wireless modem. Moreover, various aspects are described herein in connection with a base station. A base station may be utilized for communicating with wireless terminal(s) and may also be referred to as an access point, a Node B, or some other terminology.

[0078] Moreover, the term “or” is intended to mean an inclusive “or” rather than an exclusive “or.” That is, unless specified otherwise, or clear from the context, the phrase “X employs A or B” is intended to mean any of the natural inclusive permutations. That is, the phrase “X employs A or B” is satisfied by any of the following instances: X employs A; X employs B; or X employs both A and B. In addition, the articles “a” and “an” as used in this application and the appended claims should generally be construed to mean “one or more” unless specified otherwise or clear from the context to be directed to a singular form.

[0079] The techniques described herein may be used for various wireless communication systems such as CDMA, TDMA, FDMA, OFDMA, SC-FDMA and other systems. The terms “system” and “network” are often used interchangeably. A CDMA system may implement a radio technology such as Universal Terrestrial Radio Access (UTRA), cdma2000, etc. UTRA includes Wideband-CDMA (W-CDMA) and other variants of CDMA. Further, cdma2000 covers IS-2000, IS-95 and IS-856 standards. A TDMA system may implement a radio technology such as Global System for Mobile Communications (GSM). An OFDMA system may implement a radio technology such as Evolved UTRA (E-UTRA), Ultra Mobile Broadband (UMB), IEEE 802.11 (Wi-Fi), IEEE 802.16 (WiMAX), IEEE 802.20, Flash-OFDM, etc. UTRA and E-UTRA are part of Universal Mobile Telecommunication System (UMTS). 3GPP

Long Term Evolution (LTE) is a release of UMTS that uses E-UTRA, which employs OFDMA on the downlink and SC-FDMA on the uplink. UTRA, E-UTRA, UMTS, LTE and GSM are described in documents from an organization named "3rd Generation Partnership Project" (3GPP). Additionally, cdma2000 and UMB are described in documents from an organization named "3rd Generation Partnership Project 2" (3GPP2). Further, such wireless communication systems may additionally include peer-to-peer (*e.g.*, mobile-to-mobile) *ad hoc* network systems often using unpaired unlicensed spectrums, 802.xx wireless LAN, BLUETOOTH and any other short- or long- range, wireless communication techniques.

[0080] Various aspects or features will be presented in terms of systems that may include a number of devices, components, modules, and the like. It is to be understood and appreciated that the various systems may include additional devices, components, modules, etc. and/or may not include all of the devices, components, modules etc. discussed in connection with the figures. A combination of these approaches may also be used.

[0081] The various illustrative logics, logical blocks, modules, and circuits described in connection with the embodiments disclosed herein may be implemented or performed with a general purpose processor, a digital signal processor (DSP), an application specific integrated circuit (ASIC), a field programmable gate array (FPGA) or other programmable logic device, discrete gate or transistor logic, discrete hardware components, or any combination thereof designed to perform the functions described herein. A general-purpose processor may be a microprocessor, but, in the alternative, the processor may be any conventional processor, controller, microcontroller, or state machine. A processor may also be implemented as a combination of computing devices, *e.g.*, a combination of a DSP and a microprocessor, a plurality of microprocessors, one or more microprocessors in conjunction with a DSP core, or any other such configuration. Additionally, at least one processor may comprise one or more modules operable to perform one or more of the steps and/or actions described above.

[0082] Further, the steps and/or actions of a method or algorithm described in connection with the aspects disclosed herein may be embodied directly in hardware, in a software module executed by a processor, or in a combination of the two. A software module may reside in RAM memory, flash memory, ROM memory, EPROM memory,

EEPROM memory, registers, a hard disk, a removable disk, a CD-ROM, or any other form of storage medium known in the art. An exemplary storage medium may be coupled to the processor, such that the processor can read information from, and write information to, the storage medium. In the alternative, the storage medium may be integral to the processor. Further, in some aspects, the processor and the storage medium may reside in an ASIC. Additionally, the ASIC may reside in a user terminal. In the alternative, the processor and the storage medium may reside as discrete components in a user terminal. Additionally, in some aspects, the steps and/or actions of a method or algorithm may reside as one or any combination or set of codes and/or instructions on a machine readable medium and/or computer readable medium, which may be incorporated into a computer program product.

[0083] In one or more aspects, the functions described may be implemented in hardware, software, firmware, or any combination thereof. If implemented in software, the functions may be stored or transmitted as one or more instructions or code on a computer-readable medium. Computer-readable media includes both computer storage media and communication media including any medium that facilitates transfer of a computer program from one place to another. A storage medium may be any available media that can be accessed by a computer. By way of example, and not limitation, such computer-readable media can comprise RAM, ROM, EEPROM, CD-ROM or other optical disk storage, magnetic disk storage or other magnetic storage devices, or any other medium that can be used to carry or store desired program code in the form of instructions or data structures and that can be accessed by a computer. Also, any connection may be termed a computer-readable medium. For example, if software is transmitted from a website, server, or other remote source using a coaxial cable, fiber optic cable, twisted pair, digital subscriber line (DSL), or wireless technologies such as infrared, radio, and microwave, then the coaxial cable, fiber optic cable, twisted pair, DSL, or wireless technologies such as infrared, radio, and microwave are included in the definition of medium. Disk and disc, as used herein, includes compact disc (CD), laser disc, optical disc, digital versatile disc (DVD), floppy disk and blu-ray disc where disks usually reproduce data magnetically, while discs usually reproduce data optically with lasers. Combinations of the above should also be included within the scope of computer-readable media.

[0084] While the foregoing disclosure discusses illustrative aspects and/or embodiments, it should be noted that various changes and modifications could be made herein without departing from the scope of the described aspects and/or embodiments as defined by the appended claims. Furthermore, although elements of the described aspects and/or embodiments may be described or claimed in the singular, the plural is contemplated unless limitation to the singular is explicitly stated. Additionally, all or a portion of any aspect and/or embodiment may be utilized with all or a portion of any other aspect and/or embodiment, unless stated otherwise.

CLAIMS

1. A method for network facilitating wireless inter-cell interference cancellation at a served UE, comprising:
 - transmitting a first link signal encoded with a first identifier to a served user equipment (UE) that also receives an interfering second link signal from an interfering base station encoded with a second identifier;
 - transmitting the second identifier to the served UE;
 - receiving feedback from the served UE indicative of ability to cancel one of the first and second link signals from a received signal at the served UE; and
 - causing an adjustment in transmission for a change in signal to interfering noise ratio (SINR) of one of the first and second link signals responsive to the feedback,
 - wherein the served UE performs cancellation of the second link signal when the served UE receives the second link signal at higher SINR than the first link signal, by decoding the second link signal with the second identifier, re-encoding the second link signal with the second identifier, canceling the second link signal from the received signal, and decoding the first link signal from the received signal by channel estimation.
2. The method of claim 1, further comprising adjusting a transmission rate for pilots to enhance an ability of the served UE to cancel pilot interference.
3. The method of claim 1, further comprising relaying pilot feedback from the served UE to the interfering base station to cause a change in transmission power in the pilot interference.
4. The method of claim 3, further comprising transmitting dedicated pilots in the first and second link signals.
5. The method of claim 1, further comprising transmitting a unicast control channel signal scrambled with a medium access control (MAC) identifier.
6. The method of claim 5, wherein transmitting a control channel signal using physical layer resources is occupied by the interfering base station.
7. The method of claim 5, further comprising transmitting a physical downlink control channel (PDCCH) signal at a lower transmission rate encoded for increased signal to interfering noise ratio than a PDCCH from the interfering base station.
8. The method of claim 5, further comprising adjusting transmission power for a physical downlink control channel (PDCCH) signal responsive to feedback from the served UE regarding interference by the interfering base station.
9. The method of claim 5, further comprising communicating with the interfering base station to cause a transmission power adjustment for an interfering downlink control channel (PDCCH) signal responsive to feedback from the served UE regarding interference by the interfering base station.

10. The method of claim 1, wherein traffic interference cancellation is performed in a selected one of a group consisting of restricted association by the interfering base station, range expansion of a lower geometry cell, and disjoint links.
11. The method of claim 1, further comprising transmitting a unicast control channel signal scrambled with a medium access control (MAC) identifier.
12. The method of claim 1, further comprising:
 - receiving channel quality for a first link and reporting channel quality and downlink acknowledgement assignment decoded for a second link; and
 - transmitting a traffic channel signal on the first link at a transmission rate adjusted for increase signal to interfering noise ratio enabling decoding without prior cancellation of a traffic channel interference.
13. The method of claim 1, further comprising:
 - receiving channel quality for a first link to the serving base station and channel quality and downlink acknowledgement assignment decoded for a second link;
 - communicating with the interfering base station to cause adjustment of at least one of the traffic channel signal on the first link and the traffic channel interference on the second link at an adjusted transmission rate,
 - wherein the served UE decodes first the link signal having the higher signal to interfering noise ratio subsequent to the transmission rate adjustment.
14. The method of claim 1, further comprising receiving a request for the second identifier from the served UE.
15. The method of claim 1, further comprising receiving the second identifier from the interfering base station via a backhaul connection.
16. The method of claim 1, further comprising receiving the second identifier comprising a medium access control identifier (MACID).
17. The method of claim 1, further comprising receiving the second identifier comprising a Cell Radio Network Temporary Identifier (c-RNTI).
18. The method of claim 1, further comprising:
 - determining post-cancellation SINR; and
 - determining that the served UE can handover to the interfering base station.
19. The method of claim 1, further comprising:
 - receiving channel quality indicator (CQI) from the served UE based on post cancellation SINR;
 - scheduling the served UE based upon the post cancellation SINR.
20. The method of claim 19, further comprising receiving pre-cancellation CQI in response to Hybrid Automatic Repeat Request (HARQ) failure.
21. The method of claim 1, further comprising:
 - receiving channel quality indicator (CQI) and acknowledgement (ACK) from the served UE corresponding to an interfering sector; and

transmitting the CQI and ACK to the interfering base station.

22. The method of claim 1, further comprising controlling the power level for a selected one of a group consisting of a data channel, a Reference Signal (RS) channel, and a physical downlink control channel (PDCCH).

23. A computer-readable medium for network facilitating wireless inter-cell interference cancellation at a served user equipment (UE), comprising:

a first set of codes for causing a computer to transmit a first link signal encoded with a first identifier to a served UE that also receives an interfering second link signal from an interfering base station encoded with a second identifier;

a second set of codes for causing the computer to receive feedback from the served UE indicative of ability to cancel one of the first and second link signals from a received signal at the served UE; and

a third set of codes for causing the computer to cause an adjustment in transmission for a change in signal to interfering noise ratio (SINR) of one of the first and second link signals responsive to the feedback,

wherein the served UE performs cancellation of the second link signal when the served UE receives the second link signal at higher SINR than the first link signal, by decoding the second link signal with the second identifier, re-encoding the second link signal with the second identifier, canceling the second link signal from the received signal, and decoding the first link signal from the received signal by channel estimation.

24. An apparatus for network facilitating wireless inter-cell interference cancellation at a served user equipment (UE), comprising:

means for transmitting a first link signal encoded with a first identifier to a served UE that also receives an interfering second link signal from an interfering base station encoded with a second identifier;

means for receiving feedback from the served UE indicative of ability to cancel one of the first and second link signals from a received signal at the served UE; and

means for causing an adjustment in transmission for a change in signal to interfering noise ratio (SINR) of one of the first and second link signals responsive to the feedback,

wherein the served node performs cancellation of the second link signal when the served node receives the second link signal at higher SINR than the first link signal, by decoding the second link signal with the second identifier, re-encoding the second link signal with the second identifier, canceling the second link signal from the received signal, and decoding the first link signal from the received signal by channel estimation.

25. An apparatus for network facilitating wireless inter-cell interference cancellation at a served user equipment (UE), comprising:

a transmitter for transmitting a first link signal encoded with a first identifier to a served UE that also receives an interfering second link signal from an interfering base station encoded with a second identifier;

a receiver for receiving feedback from the served UE indicative of ability to cancel one of the first and second link signals from a received signal at the served UE; and

a computing platform for causing an adjustment in transmission for a change in signal to interfering noise ratio (SINR) of one of the first and second link signals responsive to the feedback,

wherein the served UE performs cancellation of the second link signal when the served UE receives the second link signal at higher SINR than the first link signal, by decoding the second link signal with the second identifier, re-encoding the second link signal with the second identifier, canceling the second link signal from the received signal, and decoding the first link signal from the received signal by channel estimation.

26. The apparatus of claim 25, wherein the computing platform is further for adjusting a transmission rate for pilots to enhance an ability of the served UE to cancel pilot interference.

27. The apparatus of claim 25, wherein the computing platform is further for relaying pilot feedback from the served UE to the interfering base station to cause a change in transmission power in the pilot interference.

28. The apparatus of claim 27, wherein the transmitter is further for transmitting dedicated pilots in the first and second link signals.

29. The apparatus of claim 25, wherein the transmitter is further for transmitting a unicast control channel signal scrambled with a medium access control (MAC) identifier.

30. The apparatus of claim 29, wherein the transmitter is further for transmitting a control channel signal using physical layer resources occupied by the interfering base station.

31. The apparatus of claim 25, wherein the transmitter is further for transmitting a physical downlink control channel (PDCCH) signal at a lower transmission rate encoded for increased signal to interfering noise ratio than a PDCCH from the interfering base station.

32. The apparatus of claim 25, wherein the transmitter is further for adjusting transmission power for a physical downlink control channel (PDCCH) signal responsive to feedback from the served UE regarding interference by the interfering base station.

33. The apparatus of claim 25, wherein the computing platform is further for communicating with the interfering base station to cause a transmission power adjustment for an interfering downlink control channel (PDCCH) signal responsive to feedback from the served UE regarding interference by the interfering base station.

34. The apparatus of claim 25, wherein the transmitter is further for transmitting a unicast control channel signal scrambled with a medium access control (MAC) identifier.

35. The apparatus of claim 25, wherein
the receiver is further for receiving channel quality for a first link and reporting channel quality and downlink acknowledgement assignment decoded for a second link;
and
the transmitter is further for transmitting a traffic channel signal on the first link at a transmission rate adjusted for increase signal to interfering noise ratio enabling decoding without prior cancellation of a traffic channel interference.
36. The apparatus of claim 25, wherein
the receiver is further for receiving channel quality for a first link to the serving base station and channel quality and downlink acknowledgement assignment decoded for a second link;
the computing platform is further for communicating with the interfering base station to cause adjustment of at least one of the traffic channel signal on the first link and the traffic channel interference on the second link at an adjusted transmission rate,
wherein the served UE decodes first the link having the higher signal to interfering noise ratio subsequent to the transmission rate adjustment.