

DESCRIPTION
COMMUNICATION DEVICE, COMMUNICATION METHOD, PROGRAM, AND
COMMUNICATION SYSTEM

5 TECHNICAL FIELD

[0001]

The present disclosure relates to a communication device, a communication method, a program, and a communication system, and specifically, to a
10 communication device, a communication method, a program, and a communication system through which it is possible to perform communication more reliably.

BACKGROUND ART

15 [0002]

In the related art, as a bus interface (IF) used for communication between devices through a bus in a board in which a plurality of devices are installed, for example, I2C (Inter-Integrated Circuit) is broadly used.
20 In addition, in recent years, it is necessary to implement I2C at high speeds, and the standardization of I3C (Improved Inter Integrated Circuit) as a next generation standard is in progress.

[0003]

25 For example, Patent Document 1 discloses a digital data processing system in which a host processor and a sub-system controller are connected to each other according to I2C. In addition, Patent Document 2 discloses a method of implementing a communication
30 protocol arranged in a layer above a standard I2C protocol.

CITATION LIST

PATENT DOCUMENT

[0004]

5 Patent Document 1: Japanese Patent Application Laid-Open
No. 2000-99448

Patent Document 2: Japanese Patent Application Laid-Open
No. 2002-175269

10 SUMMARY OF THE INVENTION

PROBLEMS TO BE SOLVED BY THE INVENTION

[0005]

When an error has occurred in a signal that is transmitted and received between devices configured to perform communication through a bus, if there is a device that is unable to detect occurrence of the error and continues to perform communication, the device is assumed to erroneously detect communication start and stop. In this case, the device has a possibility of communication failure and has difficulty performing communication reliably.

[0006]

In view of such problems, an embodiment of the present disclosure makes it possible to perform communication more reliably.

[0007]

According to an embodiment of the present disclosure, there is provided a communication device that performs communication through a bus, including: a transmitting and receiving unit configured to transmit and receive a signal to and from at least one other

communication device; and an error detection unit configured to, when the transmitting and receiving unit transmits and receives the signal, detect whether an error has occurred in the signal using a specific error
5 detection method according to transmission and reception of the signal. The signal is transmitted and received between a first communication device, which is the communication device having a communication initiative through the bus, and a second communication device, which
10 is the communication device configured to perform communication under control of the first communication device. When one bit indicating a data read or write request, which is transmitted together with a broadcast command for notifying of simultaneous transmission of a
15 command to all of a plurality of the second communication devices as a target, indicates data read in a first word of a head in a frame transmitted after the first communication device starts communication, the error detection unit of the second communication device detects
20 that an error has occurred in the first word.

SOLUTIONS TO PROBLEMS

[0008]

According to an embodiment of the present
25 disclosure, there is provided a communication method performed by a communication device configured to perform communication through a bus, or a program causing a computer of a communication device configured to perform communication through a bus to execute operations. The
30 communication device includes a transmitting and receiving unit configured to transmit and receive a

signal to and from at least one other communication device, and an error detection unit configured to, when the transmitting and receiving unit transmits and receives the signal, detect whether an error has occurred
5 in the signal using a specific error detection method according to transmission and reception of the signal. The communication method or the operations include transmitting and receiving the signal between a first communication device, which is the communication device
10 having a communication initiative through the bus, and a second communication device, which is the communication device configured to perform communication under control of the first communication device; and when one bit indicating a data read or write request, which is
15 transmitted together with a broadcast command for notifying of simultaneous transmission of a command to all of a plurality of the second communication devices as a target, indicates data read in a first word of a head in a frame transmitted after the first communication
20 device starts communication, detecting by the error detection unit of the second communication device that an error has occurred in the first word.

[0009]

According to an embodiment of the present
25 disclosure, there is provided a communication system in which a plurality of communication devices perform communication through a bus. The communication devices each include a transmitting and receiving unit configured to transmit and receive a signal to and from at least one
30 other communication device, and an error detection unit configured to, when the transmitting and receiving unit

transmits and receives the signal, detect whether an error has occurred in the signal using a specific error detection method according to transmission and reception of the signal. The signal is transmitted and received
5 between a first communication device, which is the communication device having a communication initiative through the bus, and a second communication device, which is the communication device configured to perform communication under control of the first communication
10 device. When one bit indicating a data read or write request, which is transmitted together with a broadcast command for notifying of simultaneous transmission of a command to all of a plurality of the second communication devices as a target, indicates data read in a first word
15 of a head in a frame transmitted after the first communication device starts communication, the error detection unit of the second communication device detects that an error has occurred in the first word.

[0010]

20 In an embodiment of the present disclosure, a communication device includes: a transmitting and receiving unit configured to transmit and receive a signal to and from at least one other communication device; and an error detection unit configured to, when
25 the transmitting and receiving unit transmits and receives the signal, detect whether an error has occurred in the signal using a specific error detection method according to transmission and reception of the signal. The signal is transmitted and received between a first
30 communication device, which is the communication device having a communication initiative through the bus, and a

second communication device, which is the communication device configured to perform communication under control of the first communication device. When one bit indicating a data read or write request, which is
5 transmitted together with a broadcast command for notifying of simultaneous transmission of a command to all of a plurality of the second communication devices as a target, indicates data read in a first word of a head in a frame transmitted after the first communication
10 device starts communication, the error detection unit of the second communication device detects that an error has occurred in the first word.

EFFECTS OF THE INVENTION

15 [0011]

According to an embodiment of the present disclosure, it is possible to perform communication more reliably.

20 BRIEF DESCRIPTION OF DRAWINGS

[0012]

FIG. 1 is a block diagram illustrating an exemplary configuration of an embodiment of a bus IF to which the present technology is applied.

25 FIG. 2 is a diagram illustrating an example in which a transmission scheme is switched from an SDR to an HDR and data is transmitted.

FIG. 3 is a diagram illustrating an error detection method when data write CCC communication is
30 simultaneously performed for a plurality of slaves.

FIG. 4 is a diagram illustrating an error detection

method when data write CCC communication is performed by designating an address for each slave.

FIG. 5 is a diagram illustrating an error detection method when data read CCC communication is performed by designating an address for each slave.

FIG. 6 is a diagram illustrating an error detection method when communication is performed using CCC (ENTDAA).

FIG. 7 is a diagram illustrating an error detection method when private write transfer communication initiated with a start condition is performed.

FIG. 8 is a diagram illustrating an error detection method when private write transfer communication is performed.

FIG. 9 is a diagram illustrating an error detection method when private read transfer communication initiated with a start condition is performed.

FIG. 10 is a diagram illustrating an error detection method when private read transfer communication is performed.

FIG. 11 is a diagram illustrating an error detection method when data write communication is performed in an HDR-DDR mode.

FIG. 12 is a diagram illustrating an error detection method when data read communication is performed in the HDR-DDR mode.

FIG. 13 is a diagram illustrating an error detection method when data write communication is performed in an HDR-TSL/TSP.

FIG. 14 is a diagram illustrating an error detection method when data read communication is performed in the HDR-TSL/TSP.

FIG. 15 is a diagram describing a collision detection circuit.

FIG. 16 is a diagram illustrating an example in which a current is changed under general circumstances
5 and at the time of collision.

FIG. 17 is a diagram describing transmission of an HDR exit command and a stop condition.

FIG. 18 is a flowchart describing an error detection process performed in the slave.

10 FIG. 19 is a block diagram illustrating an exemplary configuration of an embodiment of a computer to which the present technology is applied.

MODE FOR CARRYING OUT THE INVENTION

15 [0013]

Hereinafter, specific embodiments to which the present technology is applied will be described in detail with reference to the drawings.

[0014]

20 <Exemplary configuration of bus IF>

[0015]

FIG. 1 is a block diagram illustrating an exemplary configuration of an embodiment of a bus IF to which the present technology is applied.

25 [0016]

In a bus IF 11 illustrated in FIG. 1, a master 12 and three slaves 13-1 to 13-3 are connected through two signal lines 14-1 and 14-2. In addition, a plurality of transmission schemes having different communication rates
30 are defined in the bus IF 11. The master 12 can switch such transmission schemes. For example, in the bus IF 11,

depending on a transfer rate of data, a standard data rate (SDR) at which data is transmitted at a general transfer rate and a high data rate (HDR) at which data is transmitted at a transfer rate higher than the SDR are defined.

[0017]

The master 12 has a control initiative in the bus IF 11, and performs communication with the slaves 13-1 to 13-3 through the signal lines 14-1 and 14-2.

[0018]

As illustrated, the master 12 includes a transmitting and receiving unit 21, an error detection unit 22, and an error countermeasure unit 23.

[0019]

The transmitting and receiving unit 21 transmits and receives a signal to and from the slaves 13-1 to 13-3 through the bus IF 11.

[0020]

When the transmitting and receiving unit 21 transmits and receives a signal, the error detection unit 22 detects whether an error has occurred in the transmitted and received signal using a specific error detection method according to transmission and reception of the signal. For example, the error detection unit 22 detects an error that has occurred in a predetermined part of the signal received by the transmitting and receiving unit 21 using an error detection method for each predetermined part. In addition, the error detection unit 22 detects an error that has occurred due to collision of the signal transmitted by the transmitting and receiving unit 21 using an error

detection method in which the signal line 14-1 is monitored.

[0021]

The error countermeasure unit 23 performs an error countermeasure for enabling detection of an error in the slave 13. That is, as will be described below, in the error countermeasure unit 23, for example, predetermined address is prohibited from being used in a first word of a frame transmitted after communication starts, and a range in which a parity check is performed by a one-bit parity is set to include two words from the frame transmitted after communication starts.

[0022]

The slaves 13-1 to 13-3 can perform communication with the master 12 through the signal lines 14-1 and 14-2 under control of the master 12. Also, the slaves 13-1 to 13-3 have the same configuration. Hereinafter, when it is unnecessary to distinguish the slaves, these are simply called the slave 13, and this is similarly applied to blocks of the slave 13.

[0023]

As illustrated, the slave 13 includes a transmitting and receiving unit 31 and an error detection unit 32.

[0024]

The transmitting and receiving unit 31 transmits and receives a signal to and from the transmitting and receiving unit 21 of the master 12 through the bus IF 11.

[0025]

When the transmitting and receiving unit 31 transmits and receives a signal, the error detection unit

32 detects whether an error has occurred in the transmitted and received signal using a specific error detection method according to transmission and reception of the signal. For example, the error detection unit 32
5 detects an error that has occurred in a predetermined part of the signal received by the transmitting and receiving unit 31 using an error detection method for each predetermined part. In addition, the error detection unit 32 detects an error that has occurred due
10 to collision of the signal transmitted by the transmitting and receiving unit 31 using an error detection method in which the signal line 14-1 is monitored.

[0026]

15 The signal lines 14-1 and 14-2 are used to transmit a signal between the master 12 and the slave 13. For example, serial data (SDA) is sequentially transmitted bit by bit through the signal line 14-1, and a serial clock (SCL) of a predetermined frequency is transmitted
20 through the signal line 14-2.

[0027]

In the bus IF 11 having such a configuration, the master 12 can simultaneously transmit data to all of the slaves 13-1 to 13-3 as targets and can individually
25 transmit data by designating an address of the slaves 13-1 to 13-3.

[0028]

Therefore, as described above, the master 12 and the slave 13 can switch the transmission scheme to the SDR or the HDR, and transmit and receive data.
30

[0029]

For example, FIG. 2 illustrates an example in which, in the bus IF 11, the transmission scheme is switched from the SDR to the HDR and data is transmitted.

[0030]

5 First, the master 12 outputs a start condition S or Sr to the slaves 13-1 to 13-3 through the bus IF 11 and declares communication start. For example, both of the SDA and the SCL are at an H level in a waiting state in which no communication is performed in the bus IF 11, and
10 the master 12 changes the SDA from the H level to an L level while the SCL is at the H level, and thus outputs the start condition. Note that the transmission scheme when communication starts is set as the SDR.

[0031]

15 Therefore, the master 12 transmits a broadcast command (I3C Reserved byte) for notifying of simultaneous transmission of a command to all of the slaves 13-1 to 13-3 as targets in a first word of a frame head, and subsequently confirms whether reception is successful
20 using an acknowledge (ACK). For example, when the broadcast command is completely received, each of the slaves 13-1 to 13-3 returns the ACK (for example, 0 of one bit) as a reception completion notification. Therefore, when the ACK is returned, the master 12
25 confirms that the broadcast command is successfully received.

[0032]

Then, the master 12 transmits a common command code (I3C Modal Broadcast CCC (ENTHDR)) for indicating switch
30 of the transmission scheme to the HDR in a second word from the frame head to the slaves 13-1 to 13-3, and

subsequently transmits a one-bit parity T. The one-bit parity is used to detect an error of the common command code in the slaves 13-1 to 13-3.

[0033]

5 In this manner, after the common command code for indicating switch of the transmission scheme to the HDR is transmitted, the master 12 starts data transmission at the HDR, and transmits an HDR command or HDR data. Then, in order to terminate transmission using the HDR, the
10 master 12 transmits an HDR exit command (HDR Exit) for indicating release from the HDR.

[0034]

 Then, the master 12 outputs a stop condition P to the slaves 13-1 to 13-3 through the bus IF 11, and
15 declares communication termination. For example, the master 12 changes the SDA from the L level to the H level while the SCL is at the H level and thus sets the bus IF 11 to the stop condition. Note that, in the bus IF 11, when the SDR is used, the SDA is defined not to be
20 changed when the SCL is at the H level, except that communication start or termination is declared.

[0035]

 When any of the slaves 13-1 to 13-3 is unable to normally receive the common command code, the slave 13 is
25 unable to recognize that the transmission scheme is transited to the HDR. Therefore, when the slave 13 that has failed to recognize the transition of the transmission scheme to the HDR incorrectly interprets data to be transmitted at the HDR, a negative influence
30 is caused in the bus IF 11 and a state in which secure communication is not possible is assumed.

[0036]

That is, when a one-bit error has occurred in two words (0x7E+R/W+CCC [ENTHDR]) of the frame head in the specific slave 13, only the slave 13 continues to

5 maintain the SDR. Therefore, the slave 13 is assumed to erroneously detect the start condition S or Sr or the stop condition P, and it is difficult to perform communication reliably.

[0037]

10 Hereinafter, a method in which, when an error has occurred in the particularly important two words of the frame head, the error is detected will be proposed, and a new method for performing restoration safely when the master 12 or the slave 13 detects the error in the two
15 words of the frame head will be proposed. Further, an error detection method in which an error that has occurred in parts other than the two words of the frame head is detected will be proposed. In addition, when the slave 13 shows no reaction, a method of delivering the
20 HDR exit command (HDR Exit) and the stop condition P is proposed as a method of the master 12 restoring the slave 13. Also, in the present embodiment, occurrence of only a one-bit error is assumed for description.

[0038]

25 Note that, hereinafter, an error detection method in which the slave 13 detects an error using only a parity check of the second word without detecting an error in the first word will be appropriately referred to as an error detection method S0 of the slave 13.

30 [0039]

<First error detection method on slave side>

[0040]

A first error detection method performed by the slave 13 is a method of detecting an error that has occurred in two words (9 bits×2) of the frame head in a mode in which a signal is transmitted at the SDR.

[0041]

For example, as described above with reference to FIG. 2, when the transmission scheme is switched from the SDR to the HDR and data is transmitted, the master 12 sets the bus IF 11 to the start condition and then transmits the broadcast command. In this case, in the bus IF 11, as illustrated in FIG. 2, in a bit stream transmitted in the first word of the frame head, 7 bits (0x7E) indicating the broadcast command and R/W=0 indicating write in one bit indicating a data read or write request are defined.

[0042]

Therefore, the error detection unit 32 of the slave 13 confirms whether a bit stream in which any one bit among the bit stream (0x7E+R/W=0:111_1110_0) to be transmitted in the first word of the frame head is reversed is arranged in the first word. Then, when it is confirmed that such a bit stream is arranged in the first word, the error detection unit 32 can detect that an error has occurred in the first word of the frame head.

[0043]

In addition, the error detection unit 32 of the slave 13 performs a parity check using the one-bit parity T transmitted following the common command code (I3C Modal Broadcast CCC) in the second word of the frame head, and thus can detect that an error has occurred.

[0044]

In this manner, the first error detection method performed by the slave 13 is a method of detecting occurrence of an error. The error is detected in the

5 first word of the frame head when a bit stream
 (0x3E+R/W=0:011_1110_0), a bit stream
 (0x5E+R/W=0:101_1110_0), a bit stream
 (0x6E+R/W=0:110_1110_0), a bit stream
 (0x76+R/W=0:111_0110_0), a bit stream
 10 (0x7A+R/W=0:111_1010_0), a bit stream
 (0x7C+R/W=0:111_1100_0), a bit stream
 (0x7F+R/W=0:111_1111_0), and a bit stream
 (0x7E+R/W=1:011_1110_1), which are 8 possible
 combinations of a one-bit error of the bit stream

15 (0x7E+R/W=0:111_1110_0), are received. The error is
 detected in the second word of the frame head according
 to a parity check result.

[0045]

Note that, hereinafter, among the first error

20 detection methods by the slave 13, a method in which 7
 bit streams (0x3E, 0x5E, 0x6E, 0x76, 0x7A, 0x7C, and
 0x7F) in which any one bit of 7 bits (0x7E) indicating
 the broadcast command to be transmitted in the first word
 of the frame head is reversed are received and thus an

25 error is detected will be appropriately referred to as an
 error detection method S0a of the slave 13.

[0046]

In this case, in order to implement the error
 detection method S0a of the slave 13, the error

30 countermeasure unit 23 of the master 12 prohibits these 7
 bit streams (0x3E, 0x5E, 0x6E, 0x76, 0x7A, 0x7C, and

0x7F) from being used as an address to be dynamically assigned.

[0047]

In addition, hereinafter, among the first error
 5 detection methods by the slave 13, a method in which the
 bit stream (0x7E+R/W=1:011_1110_1) in which one bit
 (R/W=0) to be finally transmitted in the first word of
 the frame head is reversed is received and thus an error
 is detected will be appropriately referred to as an error
 10 detection method S0b of the slave 13.

[0048]

Here, as will be described below with reference to
 FIG. 6, the bit stream (0x7E+R/W=1:011_1110_1) is defined
 to be used only when an address to be dynamically
 15 assigned (dynamic address assignment (DAA)) is set.
 Therefore, when the bit stream (0x7E+R/W=1:011_1110_1) is
 detected before the dynamically assigned address is fixed,
 it is considered as an error.

[0049]

20 As described above, compared to the above error
 detection method S0, in the first error detection method
 performed by the slave 13, it is also possible to detect
 an error that has occurred in one bit indicating a data
 read or write request.

25 [0050]

<Second error detection method on slave side>

[0051]

A second error detection method performed by the
 slave 13 is a method in which an error that has occurred
 30 in two words (9 bit×2) of the frame head is detected in a
 mode in which a signal is transmitted at the SDR,

similarly to the first error detection method.

[0052]

For example, as described above with reference to FIG. 2, the one-bit parity T is transmitted following the common command code (I3C Modal Broadcast CCC) transmitted in the second word of the frame head. In the related art, a range in which a parity check is performed by the one-bit parity T is set to include only the common command code (I3C Modal Broadcast CCC).

10 [0053]

Here, the error countermeasure unit 23 of the master 12 sets a bit stream of the two words including the broadcast command and the common command code to be included in a range in which a parity check is performed by the one-bit parity transmitted following the common command code transmitted in the second word of the frame head.

[0054]

Accordingly, the error detection unit 32 of the slave 13 can detect an error that has occurred in the broadcast command and the common command code using the second error detection method in which the one-bit parity transmitted following the common command code of the second word from the frame head is used to perform a parity check on the bit stream of two words from the frame head.

[0055]

As described above, compared to the above first error detection method, in the second error detection method performed by the slave 13, it is possible to prevent available addresses (for example, 0x3E, 0x5E,

0x6E, and 0x76) from being limited.

[0056]

Note that, hereinafter, the second error detection method performed by the slave 13 will be appropriately referred to as an error detection method S0c of the slave 13.

[0057]

<Third error detection method on slave side>

[0058]

10 A third error detection method performed by the slave 13 is a method in which an error that has occurred in one word (0x7E+R/W=1) immediately after communication is continuously re-started (Sr) without terminating communication is detected until communication termination is detected after the dynamically assigned address is fixed in a mode in which a signal is transmitted in DAA within the SDR (CCC).

[0059]

20 For example, as will be described below with reference to FIG. 6, in communication through the bus IF 11, one word (0x7E+R/W=1) immediately after communication is continuously re-started without terminating communication after dynamic address assignment is detected until communication termination is detected appears only in this part.

[0060]

30 Therefore, the error detection unit 32 of the slave 13 confirms whether the bit stream (0x7E+R/W=1) that is predefined to be transmitted as one word is arranged in the one word transmitted immediately after communication is continuously re-started without terminating

communication after dynamic address assignment is detected until communication termination is detected. Therefore, when it is confirmed that the bit stream (0x7E+R/W=1) is arranged in the one word immediately after communication is re-started, the error detection unit 32 can determine that no error occurred. On the other hand, when it is confirmed that the bit stream (0x7E+R/W=1) is not arranged in the one word, that is, a bit stream other than the bit stream is arranged, it can be considered that an error has occurred in the one word immediately after communication is re-started.

[0061]

As described above, in the third error detection method performed by the slave 13, it is possible to detect an error that has occurred in the one word, which is not detected using methods in the related art, immediately after communication is continuously re-started without terminating communication after dynamic address assignment is detected until communication termination is detected.

[0062]

Note that, hereinafter, the third error detection method performed by the slave 13 will be appropriately referred to as an error detection method S3a of the slave 13.

[0063]

<Fourth error detection method on slave side>

[0064]

A fourth error detection method performed by the slave 13 is a method in which, in a mode in which a signal is transmitted at the SDR (CCC), after a

transaction of transmitting the common command code (CCC) to the plurality of slaves 13 is fixed, an error that has occurred in data transmitted from the master 12 is detected.

5 [0065]

That is, after the transaction of transmitting the common command code is fixed, transmission and reception of data having a format predefined by a standard are determined. Therefore, the error detection unit 32 of
10 the slave 13 confirms whether a format of data transmitted after the transaction of transmitting the common command code is fixed is different from the predefined format. When data having a different format is received by the transmitting and receiving unit 31, it
15 can be determined that an error has occurred.

[0066]

For example, after the transaction of the common command code is fixed, when read/write is 1 that indicates read regardless of a data write-related
20 instruction (refer to FIG. 4 to be described below), the error detection unit 32 determines that data having a format different from the predefined format is received and can detect that an error has occurred.

[0067]

25 Similarly, when read/write is 0 that indicates write regardless of a data read-related instruction, the error detection unit 32 can detect that an error has occurred when data having a format different from the predefined format is received. In addition, the error
30 detection unit 32 can detect that an error has occurred when third words are received against an instruction to

receive two words.

[0068]

Note that, hereinafter, the fourth error detection method performed by the slave 13 will be appropriately referred to as an error detection method S5a of the slave 13.

[0069]

<Fifth error detection method on slave side>

[0070]

10 A fifth error detection method performed by the slave 13 is a method in which, at a timing at which a signal is delivered from the slave 13, it is constantly monitored whether the delivered signal matches a signal in the signal line 14-1, and thus an error is detected.

15 [0071]

For example, the bus IF 11 allows an interrupt process according to the standard. Therefore, when the interrupt process is performed, if a transmission signal from the master 12 and an interrupt request from the slave 13 are generated at the same time, the signal encounters collision in the signal line 14-1. In order to manage such signal collision, arbitration is defined. That is, in such an interval, it is necessary to compare a signal transmitted by itself with a signal flowing on the bus and monitor advantages and disadvantages of bus rights.

[0072]

Here, for example, the master 12 transfers private write, but the slave 13 erroneously recognizes it as private read due to a reception error. In this case, there is signal collision in the signal line 14-1 between

write data transmitted by the master 12 and read data transmitted by the slave 13. Accordingly, it is difficult to perform communication accurately.

[0073]

5 Therefore, in the fifth error detection method performed by the slave 13, at a timing at which a signal is delivered from the slave 13, the error detection unit 32 constantly monitors (that is, including the above arbitration part, and the other parts) whether the
10 delivered signal matches a signal in the signal line 14-1. Accordingly, the error detection unit 32 can detect occurrence of an error due to data collision.

[0074]

<Sixth error detection method on slave side>

15 [0075]

 A sixth error detection method performed by the slave 13 is a method in which, at a timing at which a signal is delivered from the slave 13, it is determined whether the delivered signal matches a signal in the
20 signal line 14-1 by constantly monitoring a current flowing in the signal line 14-1 and thus an error is detected.

[0076]

 Here, in order to monitor the current, a collision
25 detection circuit 74 illustrated in FIG. 15 to be described below is used. Therefore, at a timing at which a signal is delivered from the slave 13, the error detection unit 32 constantly monitors (that is, including the above arbitration part, and the other parts) whether
30 the delivered signal matches a signal in the signal line 14-1 based on a current value. Accordingly, the error

detection unit 32 can detect occurrence of an error due to data collision.

[0077]

For example, in the fifth error detection method performed by the slave 13, between the master 12 and the slave 13 that transmit a signal, only one can detect collision, and it is difficult for both to detect collision. For example, when the signal line 14-1 has an intermediate potential, both of the master 12 and the slave 13 are assumed to fail detection.

[0078]

Therefore, like the collision detection circuit 74 illustrated in FIG. 15 to be described below, by constantly monitoring whether a current exceeding assumption in an analog manner flows, both of the master 12 and the slave 13 can detect collision.

[0079]

Note that, hereinafter, the fifth and sixth error detection methods by the slave 13 will be appropriately referred to as the error detection method S0a of the slave 13.

[0080]

<First error detection method on master side>

[0081]

Similarly to the above fourth error detection method performed by the slave 13, the first error detection method performed by the master 12 is a method in which, in a mode in which a signal is transmitted at the SDR (CCC), after the transaction of transmitting the common command code (CCC) to the plurality of slaves 13 is fixed, the error detection unit 22 of the master 12

detects an error that has occurred in data transmitted from the slave 13.

[0082]

That is, the error detection unit 22 of the master 12 confirms whether a format of data transmitted after the transaction of transmitting the common command code is fixed is different from the predefined format. When data having a different format is received by the transmitting and receiving unit 21, it can be determined that an error has occurred.

[0083]

Note that, hereinafter, the first error detection method performed by the master 12 will be appropriately referred to as an error detection method M0a of the master 12.

[0084]

<Second and third error detection methods on master side>

[0085]

Similarly to the above fifth and sixth error detection methods by the slave 13, second and third error detection methods by the master 12 are methods in which an error is detected by constantly monitoring a signal in the signal line 14-1.

[0086]

That is, the error detection unit 22 of the master 12 detects an error by, at a timing at which a signal is delivered from the master 12, constantly monitoring (that is, including the above arbitration part, and the other parts) whether the delivered signal matches a signal in the signal line 14-1. In addition, the collision detection circuit 74 illustrated in FIG. 15 to be

described below is used to constantly monitor a current flowing in the signal line 14-1 and thus an error is detected.

[0087]

5 Note that, hereinafter, the second and third error detection methods by the master 12 will be appropriately referred to as an error detection method M30a of the master 12.

[0088]

10 When the master 12 and the slave 13 detect an error using the error detection methods described above, in the bus IF 11, for example, it is possible to reliably switch the transmission scheme and perform communication more reliably. Accordingly, it is possible to perform
15 communication more securely.

[0089]

<Restoration method after error detection>

[0090]

 Hereinafter, a method in which the master 12 and
20 the slave 13 perform restoration after the error is detected as described above will be described.

[0091]

 The master 12 and the slave 13 adaptively perform operations thereafter according to an error state, and
25 can restore communication reliably.

[0092]

 For example, when an error is detected using the error detection method S0 of the slave 13, the error detection method S0b of the slave 13, and the error
30 detection method S0c of the slave 13 described above, in consideration of communication failure, the slave 13 that

has detected an error completely ignores communication until the HDR exit command (HDR Exit) is detected.

Accordingly, when the transmission scheme is the HDR, it is possible to prevent the stop condition P from being
5 erroneously detected. Then, it is possible to resume communication.

[0093]

In addition, within the error detection method S0b of the slave 13, a process of the second word is not
10 performed. That is, when no 0x7E is transmitted and the dynamically assigned address is transmitted, it is possible to perform error detection to a certain degree although an error detection rate is limited. In this case, since the transmission scheme is the SDR, the slave
15 13 that has detected an error completely ignores communication until the stop condition P is detected. Accordingly, only a frame in which an error has occurred is ignored and it is possible to resume communication.

[0094]

In addition, when an error is detected using the error detection method S3a of the slave 13 and the error detection method S5a of the slave 13 described above, since the transmission scheme is the SDR, the slave 13 that has detected an error completely ignores
20 communication until the stop condition P is detected. Accordingly, only a frame in which an error has occurred is ignored and it is possible to resume communication.

[0095]

Also, if the transmission scheme is the SDR, when
30 an error is detected using an error detection method S1 of the slave 13 in which an error that has occurred in

write data is detected by a parity check and an error detection method S2 of the slave 13 in which an error that has occurred in the assigned address is detected by a parity check after the dynamically assigned address is fixed, similarly, the slave 13 that has detected an error completely ignores communication until the stop condition P is detected.

[0096]

In addition, in a mode in which a signal is transmitted in an HDR-DDR, when an error is detected using an error detection method S10 of the slave 13 in which an error that has occurred in a command word is detected by a parity check and an error detection method S11 of the slave 13 in which an error that has occurred in a data word is detected by a parity check or a cyclic redundancy check (CRC), since it is in an HDR state, the slave 13 that has detected an error completely ignores communication until the HDR exit command (HDR Exit) is detected. Accordingly, only a frame in which an error has occurred is ignored and it is possible to resume communication.

[0097]

In addition, in a mode in which a signal is transmitted in an HDR-TSL/TSP, when an error is detected using an error detection method S20 of the slave 13 in which an error that has occurred in a command word is detected by a symbol of "2" that is shown two consecutive times (other than HDR Restart or HDR Exit) and an error detection method S21 of the slave 13 in which an error that has occurred in a data word is detected by a parity check or a symbol of "2" that is shown two consecutive

times (other than HDR Restart or HDR Exit), similarly, since it is in an HDR state, the slave 13 that has detected an error completely ignores communication until the HDR exit command (HDR Exit) is detected. Accordingly,
5 only a frame in which an error has occurred is ignored and it is possible to resume communication.

[0098]

In addition, when an error is detected using an error detection method S30a of the slave 13 described
10 above, since a high current is consumed due to signal collision, the slave 13 that has detected an error immediately stops signal transmission, and completely ignores communication until the stop condition P is detected (HDR Exit is detected in HDR). Accordingly,
15 only a frame in which an error has occurred is ignored and it is possible to resume communication.

[0099]

In addition, when an error is detected using the error detection method M0a of the master 12 described
20 above, since the transmission scheme is the SDR, the master 12 that has detected an error stops transmission and restarts communication from the beginning after the stop condition P is transmitted. Accordingly, only a frame in which an error has occurred is ignored and it is
25 possible to resume communication.

[0100]

In addition, when an error is detected using the error detection method M30a of the master 12 described
above, since a high current is consumed due to signal
30 collision, the master 12 that has detected an error immediately stops signal transmission, and after the stop

condition P is transmitted (HDR Exit is transmitted in HDR), restarts communication from the beginning. Accordingly, only a frame in which an error has occurred is ignored and it is possible to resume communication.

5 [0101]

<Error detection method for each of various types of communication>

[0102]

An error detection method applied for each of
10 various types of communication illustrated in FIGS. 3 to 14 will be described below.

[0103]

FIG. 3 illustrates an error detection method when data write communication (I3C Broadcast CCC Write) is
15 simultaneously performed for the plurality of slaves 13.

[0104]

In such communication, an error that has occurred in two words of the frame transmitted following the start condition can be detected by the error detection method
20 S0b of the slave 13 and the error detection method S0c of the slave 13 described above.

[0105]

In addition, an error that has occurred in data (Optional Write Data) transmitted after the one-bit
25 parity can be detected by the error detection method S1 of the slave 13 and the error detection method S5a of the slave 13 described above.

[0106]

FIG. 4 illustrates an error detection method when
30 data write communication (I3C Directed CCC Write) is performed by designating an address for each slave 13.

[0107]

In such communication, an error that has occurred in two words of the frame transmitted following the start condition can be detected by the error detection method S0b of the slave 13 and the error detection method S0c of the slave 13 described above.

[0108]

In addition, an error that has occurred in all parts surrounded by a dashed line can be detected by the error detection method S5a of the slave 13 described above. Further, an error that has occurred in one word immediately after the restart Sr can be detected by the process corresponding to the first word of the error detection method S0b of the slave 13 described above. In addition, an error that has occurred in the data (Optional Write Data) can be detected by a parity check using the error detection method S1 of the slave 13 described above.

[0109]

FIG. 5 illustrates an error detection method when data read communication (I3C Directed CCC Read) is performed by designating an address for each slave 13.

[0110]

In such communication, an error that has occurred in two words of the frame transmitted following the start condition can be detected by the error detection method S0b of the slave 13 and the error detection method S0c of the slave 13 described above.

[0111]

In addition, an error that has occurred in all parts surrounded by a dashed line can be detected by the

error detection method S5a of the slave 13 and the error detection method M0a of the master 12 described above.

Further, an error that has occurred in one word immediately after the restart Sr can be detected by the process corresponding to the first word of the error detection method S0b of the slave 13 described above.

[0112]

FIG. 6 illustrates an error detection method when communication is performed using CCC (ENTDAA).

10 [0113]

In such communication, an error that has occurred in two words of the frame transmitted following the start condition can be detected by the error detection method S0b of the slave 13 and the error detection method S0c of the slave 13 described above.

15 [0114]

In addition, an error that has occurred in all parts surrounded by a dashed line can be detected by the error detection method S5a of the slave 13 and the error detection method M0a of the master 12 described above.

20

Further, an error that has occurred in one word immediately after the restart Sr can be detected by the error detection method S3a of the slave 13 described above. An error that has occurred in the assigned address can be detected by the error detection method S2 of the slave 13 described above.

25

[0115]

FIG. 7 illustrates an error detection method when private write transfer communication (I3C Private Write Transfer Initiated with START Condition) initiated with a start condition is performed.

30

[0116]

In such communication, an error that has occurred in one word of the frame transmitted following the start condition can be detected by the process corresponding to
5 the first word of the error detection method S0b of the slave 13 described above.

[0117]

In addition, an error that has occurred in two words of the frame transmitted following the restart Sr
10 can be detected by the error detection method S0b of the slave 13 and the error detection method S0c of the slave 13 described above. Further, an error that has occurred in data (Write Data - N) can be detected by a parity check using the error detection method S1 of the slave 13
15 described above.

[0118]

FIG. 8 illustrates an error detection method when private write transfer communication (I3C Private Write Transfer) is performed.

20 [0119]

In such communication, an error that has occurred in one word of the frame transmitted following the start condition can be detected by the error detection method S0b of the slave 13 and the error detection method S0c of
25 the slave 13 described above. Further, an error that has occurred in data (Write Data - N) can be detected by a parity check using the error detection method S1 of the slave 13 described above.

[0120]

30 FIG. 9 illustrates an error detection method when private read transfer communication (I3C Private Read

Transfer Initiated with START Condition) initiated with a start condition is performed.

[0121]

In such communication, an error that has occurred
5 in one word of the frame transmitted following the start condition can be detected by the process corresponding to the first word of the error detection method S0b of the slave 13 described above. In addition, an error that has occurred in one word immediately after the restart Sr can
10 be detected by the process corresponding to the first word of the error detection method S0b of the slave 13 described above.

[0122]

FIG. 10 illustrates an error detection method when
15 private read transfer communication (I3C Private Read Transfer) is performed.

[0123]

In such communication, an error that has occurred
in one word of the frame transmitted following the start
20 condition can be detected by the process corresponding to the first word of the error detection method S0b of the slave 13 described above.

[0124]

FIG. 11 illustrates an error detection method when
25 data write communication is performed in an HDR-DDR mode.

[0125]

In such communication, an error that has occurred
in two words of the frame transmitted following the start condition can be detected by the error detection method
30 S0b of the slave 13 and the error detection method S0c of the slave 13 described above.

[0126]

In addition, an error that has occurred in a command word can be detected by a parity check using the error detection method S10 of the slave 13. In addition,
5 an error that has occurred in a data word can be detected by a parity check or a cyclic redundancy check (CRC) using the error detection method S11 of the slave 13.

[0127]

FIG. 12 illustrates an error detection method when
10 data read communication is performed in the HDR-DDR mode.

[0128]

In such communication, an error that has occurred in two words of the frame transmitted following the start condition can be detected by the error detection method
15 S0b of the slave 13 and the error detection method S0c of the slave 13 described above.

[0129]

In addition, an error that has occurred in a command word can be detected by a parity check using the error detection method S10 of the slave 13. Therefore,
20 an error that has occurred in a data word can be detected by a parity check or a cyclic redundancy check (CRC) using an error detection method M11 of the master 12.

[0130]

FIG. 13 illustrates an error detection method when
25 data write communication is performed in the HDR-TSL/TSP.

[0131]

In such communication, an error that has occurred in two words of the frame transmitted following the start
30 condition can be detected by the error detection method S0b of the slave 13 and the error detection method S0c of

the slave 13 described above.

[0132]

In addition, by the error detection method S20 of the slave 13, an error that has occurred in a command word can be detected by a symbol of "2" that is shown two consecutive times. That is, in Ternary Encoding used in the HDR-TSL and HDR-TSP, a case in which a symbol of "2" is shown two consecutive times is only found in HDR Restart and HDR Exit, and thus it can be considered as an error. In addition, by the error detection method S21 of the slave 13, an error that has occurred in a data word can be detected by a parity check or a symbol of "2" that is shown two consecutive times (other than HDR Restart or HDR Exit).

15 [0133]

FIG. 14 illustrates an error detection method when data read communication is performed in the HDR-TSL/TSP.

[0134]

In such communication, an error that has occurred in two words of the frame transmitted following the start condition can be detected by the error detection method S0b of the slave 13 and the error detection method S0c of the slave 13 described above.

[0135]

25 In addition, by the error detection method S20 of the slave 13, it is possible to detect an error that has occurred in a command word by a symbol of "2" that is shown two consecutive times. In addition, by an error detection method M21 of the master 12, an error that has occurred in a data word can be detected by a parity check or a symbol of "2" that is shown two consecutive times

30

(other than HDR Restart or HDR Exit).

[0136]

Next, FIG. 15 is a diagram describing a collision detection circuit used in the sixth error detection method performed by the slave 13 and the third error detection method performed by the master 12.

[0137]

For example, the transmitting and receiving unit 21 of the master 12 and the transmitting and receiving unit 31 of the slave 13 illustrated in FIG. 1 each include a reception circuit 51 and a transmission circuit 52. That is, FIG. 15 illustrates the transmission circuit 52 when one of the transmitting and receiving unit 21 and the transmitting and receiving unit 31 is set as a side from which to transmit a signal and the reception circuit 51 in which the other is set as a side at which to receive a signal.

[0138]

The reception circuit 51 includes a current source circuit 61. The current source circuit 61 includes a combination of a PMOS transistor 62, an NMOS transistor 63, and a resistor 64. In the current source circuit 61, according to a current I flowing in the resistor 64 from a drain power source V_{DD} through the PMOS transistor 62, serial data (SDA) is transmitted to the signal line 14-1 connected to a terminal 65.

[0139]

In the transmission circuit 52, the signal line 14-1 through which serial data (SDA) is transmitted is connected to a terminal 71. The signal line 14-2 through which a serial clock (SCL) is transmitted is connected to

a terminal 72. In addition, the transmission circuit 52 includes an electrostatic discharge (ESD) element 73, the collision detection circuit 74, an inverter circuit 75, and an amplification unit 76. The inverter circuit 75
5 includes a combination of a PMOS transistor 77 and an NMOS transistor 78.

[0140]

For example, the current I input to the transmission circuit 52 through the terminal 71 is
10 supplied to the collision detection circuit 74 through the electrostatic discharge element 73 configured to protect a circuit from a high voltage due to static electricity. In addition, the serial clock (SCL) input to the transmission circuit 52 through the terminal 72 is
15 amplified to a predetermined voltage by the amplification unit 76 and supplied to the collision detection circuit 74. In addition, the current I output from the collision detection circuit 74 flows at a ground level through the NMOS transistor 78 of the inverter circuit 75.

20 [0141]

The collision detection circuit 74 includes a combination of comparators 81 and 82, flip flop circuits 83 and 84, and a resistor 85.

[0142]

25 As illustrated in FIG. 15, the electrostatic discharge element 73 is connected to a point at which an input terminal on a plus side of the comparator 81 and an input terminal on a minus side of the comparator 82 are connected. One end of the resistor 85 is connected to
30 the connection point. In addition, the other end of the resistor 85 is connected to the inverter circuit 75.

[0143]

A reference signal Vref1 is supplied to an input terminal on a minus side of the comparator 81, and an output terminal of the comparator 81 is connected to the flip flop circuit 83. In addition, the serial clock (SCL) is supplied to the flip flop circuit 83, and a signal output from the flip flop circuit 83 is set as an output signal Out1.

[0144]

Similarly, a reference signal Vref2 is supplied to an input terminal on a plus side of the comparator 82, and an output terminal of the comparator 81 is connected to the flip flop circuit 84. In addition, the serial clock (SCL) is supplied to the flip flop circuit 84, and a signal output from the flip flop circuit 84 is set as an output signal Out2.

[0145]

When the collision detection circuit 74 is configured in this manner and the error detection unit 22 and the error detection unit 32 monitor the output signal Out1, it is possible to detect collision with high accuracy.

[0146]

Also, while it is necessary to confirm a detection result of the master 12 and the slave 13 in the collision detection method using a digital scheme described above, the master 12 and the slave 13 can independently detect collision in a collision detection method using the collision detection circuit 74.

[0147]

Operations of the collision detection circuit 74

will be described with reference to an example in which a current is changed under general circumstances and at the time of collision illustrated in FIG. 16.

[0148]

5 For example, in general, a 4 mA driver is assumed to be used, and a resistor value R_d of the resistor 64 and the resistor 85 is set to about 20 Ω . In this case, when collision occurs, a voltage of 80 mV or higher is generated in the signal line 14-1 through which the
10 serial data (SDA) is transmitted.

[0149]

 On the other hand, since a voltage of the signal line 14-1 is about 0 V when there is no collision, the reference signal V_{ref1} is set to about 40 mV, and the
15 comparator 81 performs comparison. Therefore, the flip flop circuit 83 latches a comparison result of the comparator 81 with the serial clock (SCL), and the output signal Out1 becomes a Hi level.

[0150]

20 Here, since an expected value is known to be its own output (in this case, a low level), when the output signal Out1 is not the expected value, it is possible to detect collision.

[0151]

25 Next, FIG. 17 illustrates the serial data (SDA) and the serial clock (SCL) when the HDR exit command (HDR Exit) and the stop condition P are output.

[0152]

 For example, if there is no reaction when the
30 master 12 performs read access on the slave 13, and there is no reaction when retransmission is performed several

times, it can be determined that the slave 13 is in a state in which detection of the HDR exit command (HDR Exit) or detection of the stop condition P is awaited due to some errors. In this case, the master 12 transmits a
 5 signal including the HDR exit command (HDR Exit) and the stop condition P as illustrated in FIG. 17 to the slave 13.

[0153]

Here, the HDR exit command (HDR Exit) and the stop
 10 condition P are generally defined to be transmitted at the end of the HDR signal. If transmission is performed when the slave 13 has no reaction, even if it is not at the end of such an HDR signal, it is possible to operate the slave 13 normally.

15 [0154]

Note that the master 12 may transmit the signal including the HDR exit command (HDR Exit) and the stop condition P, and may transmit, for example, the start condition S, the HDR exit command (HDR Exit), and the
 20 stop condition P. In addition, the master 12 may transmit the start condition S, a broadcast command (0x7E+R/W(=0)), the ACK, the HDR exit command (HDR Exit), and the stop condition P. Accordingly, the slave 13 can be reliably restored.

25 [0155]

Next, FIG. 18 is a flowchart describing the error detection method S0b among error detection processes performed in the slave 13.

[0156]

30 For example, when the slave 13 is activated, the process starts. In Step S11, the transmitting and

receiving unit 31 waits until the master 12 outputs the start condition S or Sr and the output is detected.

Therefore, when the transmitting and receiving unit 31 detects the start condition S or Sr, the process advances
5 to Step S12.

[0157]

In Step S12, the error detection unit 32 confirms a first word of a frame head received by the transmitting and receiving unit 31.

10 [0158]

In Step S13, the error detection unit 32 determines whether one bit (R/W) indicating a data read or write request included in the first word has a value of 1 or 0 based on the confirmation result in Step S12.

15 [0159]

In Step S13, when the error detection unit 32 determines that the value of one bit (R/W) indicating a data read or write request is 1 that indicates data read, the process advances to Step S14. That is, in this case,
20 as described above, an error in the first word of the frame head is detected.

[0160]

In Step S14, the slave 13 performs a general process until the transmitting and receiving unit 31
25 detects the stop condition P. Also, in this case, Private Read (without 0x7E) is set.

[0161]

On the other hand, in Step S13, when the error detection unit 32 determines that the value of one bit
30 (R/W) indicating a data read or write request is 0 that indicates data write, the process advances to Step S15.

[0162]

In Step S15, the error detection unit 32 determines whether the transmitting and receiving unit 31 has received repeat start Sr following the ACK of the first
5 word.

[0163]

In Step S15, when the error detection unit 32 determines that the transmitting and receiving unit 31 did not receive the repeat start Sr following the ACK of
10 the first word, the process advances to Step S16.

[0164]

In Step S16, the error detection unit 32 confirms a second word from the frame head. In Step S17, it is determined whether the second word is a common command
15 code (CCC).

[0165]

In Step S17, when the error detection unit 32 determines that the second word is not the common command code, the process advances to Step S18, and the slave 13
20 performs a general process until the transmitting and receiving unit 31 detects the stop condition P. Also, in this case, Private Write (without 0x7E) is set.

[0166]

On the other hand, in Step S17, when the error
25 detection unit 32 determines that the second word is the common command code, the process advances to Step S19. In Step S19, the error detection unit 32 repeats confirmation of the first word following the repeat start Sr and performs a general process until the transmitting
30 and receiving unit 31 detects the stop condition P.

[0167]

On the other hand, in Step S15, when the error detection unit 32 determines that the transmitting and receiving unit 31 has received the repeat start Sr following the ACK of the first word, the process advances to Step S20.

[0168]

In Step S20, the error detection unit 32 confirms the first word following the repeat start Sr received by the transmitting and receiving unit 31.

10 [0169]

In Step S21, the error detection unit 32 determines whether one bit (R/W) indicating a data read or write request included in the first word has a value of 1 or 0 based on the confirmation result in Step S12.

15 [0170]

In Step S21, when the error detection unit 32 determines that the value of one bit (R/W) indicating a data read or write request is 0 that indicates data write, the process advances to Step S22.

20 [0171]

In Step S22, the error detection unit 32 confirms a second word and performs a general process until the transmitting and receiving unit 31 detects the stop condition P. Also, in this case, Private Write (with 0x7E) is set.

[0172]

On the other hand, in Step S21, when the error detection unit 32 determines that the value of one bit (R/W) indicating a data read or write request is 1 that indicates data read, the process advances to Step S23.

30

[0173]

In Step S23, the slave 13 performs a general process until the transmitting and receiving unit 31 detects the stop condition P. Also, in this case, Private Read (with 0x7E) is set.

5 [0174]

Also, an embodiment of the present technology is not limited to the bus IF 11 according to a standard I2C, but can be applied to the bus IF 11 according to the other standards. In addition, in the bus IF 11
10 illustrated in FIG. 1, an exemplary configuration in which the slaves 13-1 to 13-3 are connected is illustrated. However, for example, one, two, three or more slaves 13 may be connected. Further, for example, the bus IF 11 may use both transmission of an error
15 correction code for correcting an error that has occurred in a common command code and confirmation of whether reception is successful using a parity check result in combination.

[0175]

20 Note that the processes described with reference to the above flowcharts are not necessarily performed in time series according to sequences described in the flowchart, but include processes (for example, parallel processes or processes by an object) that are performed
25 in parallel or individually. In addition, a program may be processed by one CPU or may be processed by a plurality of CPUs in a distributed manner.

[0176]

In addition, the series of processes described
30 above can be performed by hardware or software. When the series of processes are performed by the software, a

program of the software is installed in a computer embedded in dedicated hardware or installed in, for example, a general-purpose personal computer in which various programs can be installed to perform various functions from a program recording medium in which a program is recorded.

[0177]

<Exemplary configuration of hardware>

[0178]

FIG. 19 is a block diagram illustrating an exemplary configuration of hardware of a computer causing a program to execute the series of processes described above.

[0179]

In the computer, a central processing unit (CPU) 101, a read only memory (ROM) 102, a random access memory (RAM) 103, and an electronically erasable and programmable read only memory (EEPROM) 104 are connected to one another through a bus 105. To the bus 105, an input and output interface 106 is further connected, and the input and output interface 106 is connected to the outside (for example, the signal lines 14-1 and 14-2 of FIG. 1).

[0180]

In the computer configured as described above, the CPU 101 loads and executes the program stored in, for example, the ROM 102 and the EEPROM 104, in the RAM 103 through the bus 105, and thus the series of processes described above are performed. In addition, the program executed by the computer (the CPU 101) may be written in advance in the ROM 102, or installed and updated in the

EEPROM 104 from the outside through the input and output interface 106.

[0181]

Additionally, the present technology may also be
5 configured as below.

(1) A communication device that performs
communication through a bus, including:

a transmitting and receiving unit configured to
transmit and receive a signal to and from at least one
10 other communication device; and

an error detection unit configured to, when the
transmitting and receiving unit transmits and receives
the signal, detect whether an error has occurred in the
signal using a specific error detection method according
15 to transmission and reception of the signal,

wherein the signal is transmitted and received
between a first communication device, which is the
communication device having a communication initiative
through the bus, and a second communication device, which
20 is the communication device configured to perform
communication under control of the first communication
device, and

wherein, when one bit indicating a data read or
write request, which is transmitted together with a
25 broadcast command for notifying of simultaneous
transmission of a command to all of a plurality of the
second communication devices as a target, indicates data
read in a first word of a head in a frame transmitted
after the first communication device starts communication,
30 the error detection unit of the second communication
device detects that an error has occurred in the first

word.

(2) The communication device according to (1),
wherein the first communication device sets a
parity bit transmitted following a second word of the
5 frame so that two words from the head of the frame are
included in an error detection target using the parity
bit.

(3) The communication device according to (2),
wherein the error detection unit of the second
10 communication device uses an error detection method in
which a parity bit transmitted following a second word
from the head of the frame is used to perform a parity
check on a bit stream of two words from the head of the
frame and detects an error that has occurred in the two
15 words.

(4) The communication device according to any of
(1) to (3),
wherein the error detection unit of the second
communication device uses an error detection method in
20 which it is confirmed whether, in one word transmitted
immediately after communication is continuously re-
started without terminating communication, a bit stream
predefined to be transmitted as the one word is arranged
after dynamic address assignment is fixed until
25 communication termination is detected and detects an
error that has occurred in the one word.

(5) The communication device according to any of
(1) to (4),
wherein the error detection unit uses an error
30 detection method in which it is confirmed whether a
format of data transmitted after a transaction of

transmitting a common command code to a plurality of the other communication devices is fixed is different from a predefined format and detects an error that has occurred in the data.

5 (6) The communication device according to any of (1) to (5),

 wherein the error detection unit of the second communication device uses an error detection method in which, at a timing at which a signal is delivered from
10 the second communication device, it is constantly monitored whether the delivered signal matches a signal on the bus and detects an error that has occurred in the signal.

 (7) The communication device according to any of
15 (1) to (6), further including

 a current monitoring circuit configured to monitor a current flowing in a signal line configured to output a signal from the communication device,

 wherein the error detection unit uses an error
20 detection method in which, at a timing at which a signal from the communication device itself is delivered, it is confirmed whether the delivered signal matches a signal on the bus based on a current that is constantly monitored by the current monitoring circuit and detects
25 an error that has occurred in the signal.

 (8) A communication method performed by a communication device configured to perform communication through a bus,

 wherein the communication device includes
30 a transmitting and receiving unit configured to transmit and receive a signal to and from at least one

other communication device, and

an error detection unit configured to, when the transmitting and receiving unit transmits and receives the signal, detect whether an error has occurred in the
5 signal using a specific error detection method according to transmission and reception of the signal

the communication method including:

transmitting and receiving the signal between a first communication device, which is the communication
10 device having a communication initiative through the bus, and a second communication device, which is the communication device configured to perform communication under control of the first communication device; and

when one bit indicating a data read or write
15 request, which is transmitted together with a broadcast command for notifying of simultaneous transmission of a command to all of a plurality of the second communication devices as a target, indicates data read in a first word of a head in a frame transmitted after the first
20 communication device starts communication, detecting by the error detection unit of the second communication device that an error has occurred in the first word.

(9) A program causing a computer of a communication device configured to perform communication through a bus
25 to execute operations,

wherein the communication device includes

a transmitting and receiving unit configured to transmit and receive a signal to and from at least one other communication device, and

30 an error detection unit configured to, when the transmitting and receiving unit transmits and receives

the signal, detect whether an error has occurred in the signal using a specific error detection method according to transmission and reception of the signal, and

wherein the operations include

5 transmitting and receiving the signal between a first communication device, which is the communication device having a communication initiative through the bus, and a second communication device, which is the communication device configured to perform communication
10 under control of the first communication device, and

 when one bit indicating a data read or write request, which is transmitted together with a broadcast command for notifying of simultaneous transmission of a command to all of a plurality of the second communication
15 devices as a target, indicates data read in a first word of a head in a frame transmitted after the first communication device starts communication, detecting by the error detection unit of the second communication device that an error has occurred in the first word.

20 (10) A communication system in which a plurality of communication devices perform communication through a bus,

 wherein the communication devices each include a transmitting and receiving unit configured to transmit and receive a signal to and from at least one
25 other communication device, and

 an error detection unit configured to, when the transmitting and receiving unit transmits and receives the signal, detect whether an error has occurred in the signal using a specific error detection method according
30 to transmission and reception of the signal,

 wherein the signal is transmitted and received

between a first communication device, which is the communication device having a communication initiative through the bus, and a second communication device, which is the communication device configured to perform
 5 communication under control of the first communication device, and

wherein, when one bit indicating a data read or write request, which is transmitted together with a broadcast command for notifying of simultaneous
 10 transmission of a command to all of a plurality of the second communication devices as a target, indicates data read in a first word of a head in a frame transmitted after the first communication device starts communication, the error detection unit of the second communication
 15 device detects that an error has occurred in the first word.

[0182]

Note that the present embodiment is not limited to the embodiments described above, and various
 20 modifications without departing from the spirit and scope of the present disclosure can be implemented.

REFERENCE SIGNS LIST

[0183]

25 11 bus IF
 12 master
 13-1 to 13-3 slave
 14-1 to 14-2 signal lines
 21 receiving unit
 30 22 error detection unit
 23 error countermeasure unit

	31-1 to 31-3	transmitting and receiving unit
	32-1 to 32-3	error detection unit
	51	reception circuit
	52	transmission circuit
5	61	current source circuit
	62	PMOS transistor
	63	NMOS transistor
	64	resistor
	65	terminal
10	71 and 72	terminal
	73	electrostatic discharge element
	74	collision detection circuit
	75	inverter circuit
	76	amplification unit
15	77	PMOS transistor
	78	NMOS transistor
	81 and 82	comparator
	83 and 84	flip flop circuit
	85	resistor

CLAIMS

1. A communication device that performs communication through a bus, comprising:

5 a transmitting and receiving unit configured to transmit and receive a signal to and from at least one other communication device; and

an error detection unit configured to detect, when the transmitting and receiving unit transmits and
10 receives the signal, whether an error has occurred in the signal by using a specific error detection method according to transmission and reception of the signal,

wherein the signal is transmitted and received between a first communication device that is the
15 communication device having a communication initiative through the bus, and a second communication device that is the communication device configured to perform communication under control of the first communication device, and

20 the error detection unit of the second communication device detects, in a case where one bit indicating a data read or write request and transmitted together with a broadcast command for notifying of simultaneous transmission of a command to all of a
25 plurality of the second communication devices as a target indicates data read in a first word of a head in a frame transmitted after the first communication device starts communication, that an error has occurred in the first word.

30

2. A communication method of a communication device

that performs communication through a bus,
the communication device including
a transmitting and receiving unit configured to
transmit and receive a signal to and from at least one
5 other communication device, and
an error detection unit configured to detect, when
the transmitting and receiving unit transmits and
receives the signal, whether an error has occurred in the
signal by using a specific error detection method
10 according to transmission and reception of the signal,
the communication method comprising the steps of:
transmitting and receiving the signal between a
first communication device that is the communication
device having a communication initiative through the bus,
15 and a second communication device that is the
communication device configured to perform communication
under control of the first communication device; and
detecting by the error detection unit of the second
communication device, in a case where one bit indicating
20 a data read or write request and transmitted together
with a broadcast command for notifying of simultaneous
transmission of a command to all of a plurality of the
second communication devices as a target indicates data
read in a first word of a head in a frame transmitted
25 after the first communication device starts communication,
that an error has occurred in the first word.

3. A program executed by a computer of a communication
device that performs communication through a bus,
30 the communication device including
a transmitting and receiving unit configured to

transmit and receive a signal to and from at least one other communication device, and

an error detection unit configured to detect, when the transmitting and receiving unit transmits and

5 receives the signal, whether an error has occurred in the signal by using a specific error detection method according to transmission and reception of the signal,

the program comprising the steps of:

transmitting and receiving the signal between a
10 first communication device that is the communication device having a communication initiative through the bus, and a second communication device that is the communication device configured to perform communication under control of the first communication device; and

15 detecting by the error detection unit of the second communication device, in a case where one bit indicating a data read or write request and transmitted together with a broadcast command for notifying of simultaneous transmission of a command to all of a plurality of the
20 second communication devices as a target indicates data read in a first word of a head in a frame transmitted after the first communication device starts communication, that an error has occurred in the first word.

25 4. A communication system in which a plurality of communication devices performs communication through a bus,

wherein each of the communication devices includes
a transmitting and receiving unit configured to
30 transmit and receive a signal to and from at least one other communication device, and

an error detection unit configured to detect, when the transmitting and receiving unit transmits and receives the signal, whether an error has occurred in the signal by using a specific error detection method
5 according to transmission and reception of the signal,
the signal is transmitted and received between a first communication device that is the communication device having a communication initiative through the bus, and a second communication device that is the
10 communication device configured to perform communication under control of the first communication device, and
the error detection unit of the second communication device detects, in a case where one bit indicating a data read or write request and transmitted
15 together with a broadcast command for notifying of simultaneous transmission of a command to all of a plurality of the second communication devices as a target indicates data read in a first word of a head in a frame transmitted after the first communication device starts
20 communication, that an error has occurred in the first word.

5. A first communication device that performs communication through a bus, comprising:
25 a transmitting and receiving unit configured to transmit and receive a signal to and from at least one second communication device,
wherein the signal is transmitted and received between the first communication device that has a
30 communication initiative through the bus, and the at least one second communication device that performs

communication under control of the first communication device, and

in a case where one bit, which indicates a data read or write request and is transmitted together with a broadcast command for notifying of simultaneous transmission of a command to all of a plurality of the second communication devices as a target, indicates data read in a first word of a head in a frame transmitted after the first communication device starts communication, an error detection unit of each of the second communication devices detects that an error has occurred in the first word.

6. The communication device according to claim 5, further comprising an error detection unit that is set to detect, when the transmitting and receiving unit transmits and receives the signal, that an error has occurred in the signal.

7. The communication device according to claim 5, wherein the first communication device is a master, and each of the second communication devices is a slave.

8. A second communication device that performs communication through a bus, comprising:
a transmitting and receiving unit configured to transmit and receive a signal to and from a first communication device under control of the first communication device; and

an error detection unit configured to detect, when the transmitting and receiving unit transmits and

receives the signal, that an error has occurred in the signal,

wherein in a case where one bit indicating a data read or write request and transmitted together with a broadcast command indicates data read in a first word of a head in a frame transmitted by the first communication device after the first communication device starts communication, the error detection unit detects that an error has occurred in the first word.

10

9. The communication device according to claim 8, wherein the broadcast command notifies, from the first communication device, of simultaneous transmission of a command to all of a plurality of the second communication devices as a target.

15

10. The communication device according to claim 9, wherein one bit indicating a data read or write request is included, in the first word, following the broadcast command.

20

11. The communication device according to claim 10, wherein a word length of the frame is nine bits.

12. The communication device according to claim 11, wherein an acknowledge (ACK) bit is included in the first bit.

25

13. The communication device according to claim 8, wherein a start condition bit is not included in the first bit.

30

14. The communication device according to claim 8,
wherein the broadcast command has seven bits.

5 15. The communication device according to claim 8,
wherein the broadcast command is 0x7E.

16. A communication device that performs communication
through a bus, comprising:

10 a transmitting and receiving unit configured to
transmit and receive a signal to and from at least one
other communication device; and

an error detection unit configured to detect, when
the transmitting and receiving unit transmits and
15 receives the signal, whether an error has occurred in the
signal by using a specific error detection method
according to transmission and reception of the signal,

wherein the signal is transmitted and received
between a first communication device that is the
20 communication device having a communication initiative
through the bus, and a second communication device that
is the communication device configured to perform
communication under control of the first communication
device, and

25 by using an error detection method of confirming,
in a period after dynamic address assignment is started
until termination of communication is detected, whether a
bit stream predefined to be transmitted as one word
transmitted immediately after communication is re-started
30 continuously without termination of the communication is
arranged in the one word, the error detection unit of the

second communication device detects an error that has occurred in the one word.

17. A communication method of a communication device
5 that performs communication through a bus,
the communication device including
a transmitting and receiving unit configured to
transmit and receive a signal to and from at least one
other communication device, and
10 an error detection unit configured to detect, when
the transmitting and receiving unit transmits and
receives the signal, whether an error has occurred in the
signal by using a specific error detection method
according to transmission and reception of the signal,
15 the communication method comprising the steps of:
transmitting and receiving the signal between a
first communication device that is the communication
device having a communication initiative through the bus,
and a second communication device that is the
20 communication device configured to perform communication
under control of the first communication device; and
by using an error detection method of confirming,
in a period after dynamic address assignment is started
until termination of communication is detected, whether a
25 bit stream predefined to be transmitted as one word
transmitted immediately after communication is re-started
continuously without termination of the communication is
arranged in the one word, detecting an error that has
occurred in the one word by the error detection unit of
30 the second communication device.

18. A program executed by a computer of a communication device that performs communication through a bus,
the communication device including
a transmitting and receiving unit configured to
5 transmit and receive a signal to and from at least one other communication device, and
an error detection unit configured to detect, when the transmitting and receiving unit transmits and receives the signal, whether an error has occurred in the
10 signal by using a specific error detection method according to transmission and reception of the signal,
the program comprising the steps of:
transmitting and receiving the signal between a first communication device that is the communication
15 device having a communication initiative through the bus, and a second communication device that is the communication device configured to perform communication under control of the first communication device; and
by using an error detection method of confirming,
20 in a period after dynamic address assignment is started until termination of communication is detected, whether a bit stream predefined to be transmitted as one word transmitted immediately after communication is re-started continuously without termination of the communication is
25 arranged in the one word, detecting an error that has occurred in the one word by the error detection unit of the second communication device.
19. A communication system in which a plurality of
30 communication devices performs communication through a bus,

wherein each of the communication devices includes
a transmitting and receiving unit configured to
transmit and receive a signal to and from at least one
other communication device, and

5 an error detection unit configured to detect, when
the transmitting and receiving unit transmits and
receives the signal, whether an error has occurred in the
signal by using a specific error detection method
according to transmission and reception of the signal,
10 the signal is transmitted and received between a
first communication device that is the communication
device having a communication initiative through the bus,
and a second communication device that is the
communication device configured to perform communication
15 under control of the first communication device, and
by using an error detection method of confirming,
in a period after dynamic address assignment is started
until termination of communication is detected, whether a
bit stream predefined to be transmitted as one word
20 transmitted immediately after communication is re-started
continuously without termination of the communication is
arranged in the one word, the error detection unit of the
second communication device detects an error that has
occurred in the one word.

25

20. A first communication device that performs
communication through a bus, comprising:

a transmitting and receiving unit configured to
transmit and receive a signal to and from at least one
30 second communication device,

wherein the signal is transmitted and received

between the first communication device having a communication initiative through the bus, and the at least one second communication device that performs communication under control of the first communication device, and

by using an error detection method of confirming, in a period after dynamic address assignment is started until termination of communication is detected, whether a bit stream predefined to be transmitted as one word transmitted immediately after communication is re-started continuously without termination of the communication is arranged in the one word, an error detection unit of the second communication device detects an error that has occurred in the one word.

21. The communication device according to claim 20, further comprising an error detection unit that is set to detect, when the transmitting and receiving unit transmits and receives the signal, that an error has occurred in the signal.

22. The communication device according to claim 20, wherein the first communication device is a master, and the second communication device is a slave.

23. A second communication device that performs communication through a bus, comprising:

a transmitting and receiving unit configured to transmit and receive a signal to and from a first communication device under control of the first communication device; and

an error detection unit configured to detect, when the transmitting and receiving unit transmits and receives the signal, that an error has occurred in the signal,

5 wherein by using an error detection method of confirming, in a period after dynamic address assignment is started until termination of communication is detected, whether a bit stream predefined to be transmitted as one word transmitted immediately after communication is re-
10 started continuously without termination of the communication is arranged in the one word, the error detection unit detects an error that has occurred in the one word.

15 24. A communication device that performs communication through a bus, comprising:

 a transmitting and receiving unit configured to transmit and receive a signal to and from at least one other communication device; and

20 an error detection unit configured to detect, when the transmitting and receiving unit transmits and receives the signal, whether an error has occurred in the signal by using a specific error detection method according to transmission and reception of the signal,

25 wherein the signal is transmitted and received between a first communication device that is the communication device having a communication initiative through the bus, and a second communication device that is the communication device configured to perform
30 communication under control of the first communication device, and

the error detection unit detects, by using an error detection method of confirming whether a format of data transmitted after a transaction of transmitting a common command code to a plurality of the other communication devices is fixed is different from a predefined format, an error that has occurred in the data.

25. A communication method of a communication device that performs communication through a bus,
10 the communication device including
a transmitting and receiving unit configured to transmit and receive a signal to and from at least one other communication device, and
an error detection unit configured to detect, when
15 the transmitting and receiving unit transmits and receives the signal, whether an error has occurred in the signal by using a specific error detection method according to transmission and reception of the signal,
the communication method comprising the steps of:
20 transmitting and receiving the signal between a first communication device that is the communication device having a communication initiative through the bus, and a second communication device that is the communication device configured to perform communication
25 under control of the first communication device; and
by using an error detection method of confirming whether a format of data transmitted after a transaction of transmitting a common command code to a plurality of the other communication devices is fixed is different
30 from a predefined format, detecting an error that has occurred in the data by the error detection unit.

26. A program executed by a computer of a communication device that performs communication through a bus,

the communication device including

5 a transmitting and receiving unit configured to transmit and receive a signal to and from at least one other communication device, and

an error detection unit configured to detect, when the transmitting and receiving unit transmits and
10 receives the signal, whether an error has occurred in the signal by using a specific error detection method according to transmission and reception of the signal,

the program comprising the steps of:

transmitting and receiving the signal between a
15 first communication device that is the communication device having a communication initiative through the bus, and a second communication device that is the communication device configured to perform communication under control of the first communication device, and

20 by using an error detection method of confirming whether a format of data transmitted after a transaction of transmitting a common command code to a plurality of the other communication devices is fixed is different from a predefined format, detecting an error that has
25 occurred in the data by the error detection unit.

27. A communication system in which a plurality of communication devices performs communication through a bus,

30 wherein each of the communication devices includes a transmitting and receiving unit configured to

transmit and receive a signal to and from at least one other communication device, and

an error detection unit configured to detect, when the transmitting and receiving unit transmits and

5 receives the signal, whether an error has occurred in the signal by using a specific error detection method according to transmission and reception of the signal,

the signal is transmitted and received between a first communication device that is the communication
10 device having a communication initiative through the bus, and a second communication device that is the communication device configured to perform communication under control of the first communication device, and

the error detection unit detects, by using an error
15 detection method of confirming whether a format of data transmitted after a transaction of transmitting a common command code to a plurality of the other communication devices is fixed is different from a predefined format, an error that has occurred in the data.

20

28. A first communication device that performs communication through a bus, comprising:

a transmitting and receiving unit configured to transmit and receive a signal to and from at least one
25 second communication device,

wherein the signal is transmitted and received between the first communication device having a communication initiative through the bus, and the at least one second communication device that performs
30 communication under control of the first communication device, and

an error detection unit of the second communication device detects, by using an error detection method of confirming whether a format of data transmitted after a transaction of transmitting a common command code to a plurality of the second communication devices is fixed is different from a predefined format, an error that has occurred in the data.

29. The communication device according to claim 28, further comprising an error detection unit that is set to detect, when the transmitting and receiving unit transmits and receives the signal, that an error has occurred in the signal.

30. The communication device according to claim 28, wherein the first communication device is a master, and each of the second communication devices is a slave.

31. A second communication device that performs communication through a bus, comprising:

a transmitting and receiving unit configured to transmit and receive a signal to and from a first communication device under control of the first communication device; and

an error detection unit configured to detect, when the transmitting and receiving unit transmits and receives the signal, that an error has occurred in the signal,

wherein the error detection unit detects, by using an error detection method of confirming whether a format of data transmitted after a transaction of transmitting a

common command code to a plurality of the second communication devices is fixed is different from a predefined format, an error that has occurred in the data.

5 32. The communication device according to claim 1, wherein the first communication device sets a parity bit, which is transmitted following a second word of the frame, in such a manner that two words from the head of the frame are included in a target of error detection using
10 the parity bit.

33. The communication device according to claim 32, wherein by using an error detection method of performing parity check with respect to a bit stream of the two
15 words from the head of the frame by using the parity bit transmitted following the second word from the head of the frame, the error detection unit of the second communication device detects an error that has occurred in the two words.

20

34. The communication device according to claim 1, wherein by using an error detection method of confirming, in a period after dynamic address assignment is started until termination of communication is detected, whether a
25 bit stream predefined to be transmitted as one word transmitted immediately after communication is re-started continuously without termination of the communication is arranged in the one word, the error detection unit of the second communication device detects an error that has
30 occurred in the one word.

35. The communication device according to claim 1,
wherein the error detection unit detects, by using an
error detection method of confirming whether a format of
data transmitted after a transaction of transmitting a
5 common command code to a plurality of the other
communication devices is fixed is different from a
predefined format, an error that has occurred in the data.

36. The communication device according to claim 1,
10 wherein the error detection unit of the second
communication device detects, by using an error detection
method of constantly monitoring at timing at which a
signal is delivered from the second communication device
whether the delivered signal matches a signal on the bus,
15 an error that has occurred in the signal.

37. The communication device according to claim 1,
further comprising a current monitoring circuit
configured to monitor a current flowing in a signal line
20 that outputs a signal from the communication device,
wherein the error detection unit detects, by using
an error detection method of confirming at timing at
which a signal is delivered from the communication device
itself whether the delivered signal matches a signal on
25 the bus on the basis of the current constantly monitored
by the current monitoring circuit, an error that has
occurred in the signal.