

Method and device for capturing an image of a target object

5

TECHNICAL AREA

The present invention relates to a method for capturing an image of a target object illuminated by an illumination laser. It relates further to a device for capturing the
10 image which operates according to the inventive method.

BACKGROUND OF THE INVENTION

Methods and devices are used to capture distant moving objects, such as flying
15 objects, and to track their flight paths. In the course of this target tracking, the entire device, or at least an aiming system of said device is moved to follow the flight path of the target object so that said target object can be reproduced as constantly as possible at a location of the image capturing device. Tracking errors are associated with this following method, manifesting themselves as "juddering" of the image, for
20 example. Moreover, imaging errors can also be caused by atmospheric turbulence. Higher order imaging aberrations can also occur, thereby limiting the achievable optical resolution of the image displayed on the image capturing device.

PRIOR ART

25

In order to correct these deficiencies, it is already known to analyse the angular offset of the object displayed on the image capturing device, and to shift at least one first optical correcting element in the receiving optics units as a function of the result of this analysis. This shift of the first optical correcting element takes place in a closed
30 control circuit with the analysis of the angular offset. Such image stabilisation is thus performed using the light of the illumination laser which is reflected by the target object.

In addition, a second laser is typically provided, which emits laser light of a different wavelength from the wavelength of the illumination laser, and the laser light of which is also aimed at the target object. The light from this second laser which is reflected by the target object is used to compensate for the image resolution limitation caused by the higher order imaging aberrations by providing a wave front sensor to receive said reflected light of the second laser and generate a correction signal, which acts on at least one second optical correcting element in the closed control circuit.

10 SUMMARY OF THE INVENTION

The object of the present invention is to describe a species-related method and a species-related device, with which it is possible to stabilise the image and correct higher order imaging aberrations while at the same time reducing equipment requirement and thus also lowering costs.

With respect to the method, the object is solved with a method having the features of claim 1.

20 This method according to the invention for capturing the image of a target object illuminated by an illumination laser has the following steps:

- a) Illuminating the target object by means of a pulsed laser beam emitted by an illumination laser, which beam is aimed at the target object in the form of an illumination beam by an illumination optics unit;
- 25 b) Receiving the illumination beam laser light reflected from the target object by means of a receiving optics unit;
- c) Directing the received reflected illumination beam laser light to an image capturing device to generate an image of the target object on the image capturing device;
- 30 d) Detecting the angular offset of the image of the target object with respect to a reference axis of the receiving optics unit;

- e) Stabilising the visual axis of the image capturing device detected by imaging of the target object device by means of a first optical correcting element of the receiving optics unit that compensates for the angular offset.

In this context, the following steps are also carried out to stabilise the imaging of the target object:

- a'1) Decoupling a partial beam from the laser beam emitted by the illumination laser;
- a'2) Delaying the decoupled partial beam in an optical delay device;
- a'3) Illuminating the target object by means of the partial beam that is directed at the target object by the receiving optics unit;
- b'1) Receiving the partial beam laser light which is reflected by the target object and which defines a reference wavefront, by the receiving optics unit;
- b'2) Decoupling the received reflected partial beam laser light from the light that is received by the receiving optics unit;
- c') Directing the decoupled reflected partial beam laser light to a wavefront sensor;
- d') Detecting a wavefront error in the received reflected partial beam laser light, and
- e') Fine tuning the receiving optics unit to compensate for the detected wavefront error by means of a second optical correcting element of the receiving optics unit.

ADVANTAGES

- By splitting off the partial beam from the pulsed laser beam of the illumination laser and by delaying the partial beam laser light is delayed, it becomes possible to distinguish between the laser light that is aimed at the target object through the illumination beam by means of the illumination optics unit and reflected therefrom, and the laser light that is reflected from the target object due to the partial beam laser light that is guided "backwards" through the receiving optics unit, so that the light from both that is reflected by the target object can be distinguished from the pulsed light beams that have been temporally offset by the optical delay device, so that it is

thus possible not only to stabilise the image but also to compensate for the higher order imaging aberrations by means of a single illumination source.

It is preferably provided in the method according to the invention that step b'₂) of
 5 decoupling the received reflected partial beam laser light from the light that is received by the receiving optics unit is carried out by means of Pockels cells, which are actuated synchronously to assure clocking of the pulsed laser beam emitted by the illumination laser.

10 The part of the object that relates to the device is solved by the device having the features of claim 3.

Said inventive device is characterised by

- an illumination laser which is designed to emit a pulsed laser beam;
- 15 — an illumination optics unit provided in the beam path of the laser beam emitted by the illumination laser;
- a receiving optics unit for the laser light reflected from the target object;
- an image capturing device, to which the receiving optics unit directs the reflected laser light it receives;
- 20 — a first beam splitter provided between the illumination laser and the illumination optics unit, which diverts a partial beam out of the pulsed laser beam generated by the illumination laser;
- an optical delay device, into which the partial beam is guided by the first beam splitter;
- 25 — a first polarisation beam splitter arranged in the path of the beam exiting the optical delay device and in the beam path between the receiving optics unit and the image capturing device;
- a second polarisation beam splitter provided in the beam path between the first polarisation beam splitter and the receiving optics unit;
- 30 — a first Pockels cell provided between the first polarisation beam splitter and the second polarisation beam splitter;

- a second Pockels cell provided parallel to the first Pockels cell, which is arranged in a bypass beam path formed between the first polarisation beam splitter and the second polarisation beam splitter;
- a wavefront sensor, which is arranged in a beam path split off from the beam path between the first polarisation beam splitter and the delay device by a second beam splitter;

wherein the receiving optics unit has one rapidly adjustable mirror and one adaptive mirror in its inner beam path, wherein the image capturing device has an image analyser that sends an adjustment signal to an adjustment device for the rapidly adjustable mirror, and wherein the wavefront sensor has a wavefront error analyser which generates a correction signal and forwards it to an adjustment device of the adaptive mirror.

By combining the first beam splitter provided in the pulsed laser beam emitted by the illumination laser, the optical delay device, and the beam path which is switchable by mean of the Pockels cells, it is possible to arrive at the method according to the invention, such that in contrast to the prior art only a single laser is required to carry out image stabilisation and also correct the higher order imaging aberrations.

Further preferred, advantageous design features of the device according to the invention are the subject matter of dependent claims 4 to 7.

The illumination optical device preferably has a beam diverging optics unit. This ensures that the laser beam reliably reaches the target object and illuminates it effectively.

It is particularly advantageous if the wavefront sensor is in the form of a Hartmann-Shack sensor.

Advantageously, the transmission direction of the first polarisation beam splitter is aligned perpendicularly to the transmission direction of the second polarisation beam splitter.

Also preferably, the image capturing device is equipped with a fine tracking camera or is in the form of a fine tracking camera that is designed to operate in the range gating mode.

5

Preferred embodiments of the invention with additional configuration details and further advantages are described and explained in greater detail in the following, with reference to the accompanying drawings.

10 BRIEF DESCRIPTION OF THE DRAWINGS

In the drawing:

Fig. 1 shows a schematic construction of a device according to the invention;

15

Fig. 2A is a time-related representation of the two pulsed laser light beams aimed at the target object, and

Fig. 2B is a time-related representation of the two pulsed laser light beams received after being reflected from the target object.

20

PRESENTATION OF PREFERRED EMBODIMENTS

Fig. 1 shows an example of a device according to the invention for capturing the image of a target object. With this device it is possible to obtain high resolution optical images of moving target objects, for example flying objects, by laser illumination. It includes an adaptive optics system and operates according to the method according to the invention, which will be described subsequently.

25

Typical components of the device are an illumination laser 1, an illumination optics unit 2, a receiving optics unit 3, an image capturing device 4 and a wavefront sensor

30

device 5. The particular feature of this inventive device is a partial radiation guide device 6, which will be described in detail below.

5 Illumination laser 1 is designed to emit a pulsed laser beam L. Said laser beam L emitted by illumination laser 1 toward illumination optics unit 2 constitutes a first beam path S_1 between illumination laser 1 and illumination optics unit 2. Illumination laser 1 preferably generates a polarised laser radiation (e.g., pp) in the wavelength range of visible light to near infrared, pulsed for example with a typical pulse length in the range of ten nanoseconds and with a pulse repetition rate greater than 100
10 pulses per second.

A first beam splitter 60 of partial radiation guide device 6 is provided in the first beam path S_1 between illumination laser 1 and illumination optics unit 2, and separates a partial beam L_1 from the pulsed laser beam L generated by illumination laser 1 and
15 diverts it into a second beam path S_2 . In this way, a small proportion (approx. 10%) of the radiation of laser beam L is transferred to partial beam L_1 . The remaining radiation component of laser beam L is forwarded as illumination beam L_2 to illumination optics unit 2, in which it is caused to diverge slightly by means of a beam diverging optics unit 20 and directed at target object Z. The radiation angle of
20 illumination lasers 2 is set via the beam diverging optics unit 20 to 1 mrad beam divergence, for example. Illumination beam L_2 is directed at and follows target object Z, for example a flying object, by means of an aiming system - not shown in Fig. 1 - with a Coudé beam guide, in such manner that the surface of target object Z is illuminated over a large area.

25 Receiving optics unit 3 receives the laser light R reflected from target object Z and guides it along an inner beam path S_3 , in which a rapidly adjustable mirror 30 is arranged as a first optical correcting element, and an adaptive mirror 32 is provided as a second optical correcting element. Receiving optics unit 3 guides the received
30 laser light R that has passed through it farther along a fourth beam path S_4 to image capturing device 4. The laser light R that is backscattered from illuminated target object Z is received by a receiving optics unit 3 which has the form of a telescopic

optical unit arranged on an aiming system used to track a target, and is guided along beam path S_4 via a Coudé beam guide to rapidly adjustable mirror 30 and farther along the beam path to image capturing device 4, which includes a fine tracking camera 40, for example, which displays the target object.

5

Image capturing device 4 further includes an image analyser 42, which actuates an adjustment device 31 of the rapidly adjustable mirror 30 with an adjustment signal.

The image information obtained with fine tracking camera 40 is analysed using known image processing methods to detect the angular offsets of the displayed

10

target object relative to the reference axis. These angular offsets are then used to actuate the rapidly adjustable mirror 30, which stabilises the visual axis of the fine tracking camera 40 in the closed control circuit. This stabilisation of the visual axis effectively minimises the harmful effect of temporally variable image motion on the quality of the imaging delivered by fine tracking camera 40. Such image motion is

15

caused by tracking errors of the aiming system and the effects of atmospheric turbulence on the beam propagation path to the target object and back.

Besides image motion, atmospheric turbulence also causes higher order imaging aberrations, which limit the optical resolution that is achievable with the fine tracking camera 40. Adaptive mirror 32 is used to correct these imaging errors, as will be described subsequently.

20

The partial beam L_2 that is separated by first beam splitter 60 is guided along the second beam path S_2 to an optical delay device 62. An inner beam path S_{2v} is formed inside optical delay device 62, representing an optical delay path 61, which is preferably longer than 3 m.

25

The delayed partial beam L_{1v} exiting from delay device 62 is guided along a further beam path S_5 to a first polarisation beam splitter 64 in fourth beam path S_4 arranged between receiving optics unit 3 and image capturing device 4.

30

In the fourth beam path S_4 , a second polarisation beam splitter 66 is provided between first polarisation beam splitter 64 and receiving optics unit 3, and a first Pockels cell 65 is arranged between the first polarisation beam splitter 64 and the second polarisation beam splitter 66. Parallel to the first Pockels cell 65, a second
 5 Pockels cell 67 is arranged in a bypass beam path S_{4B} created between first polarisation beam splitter 64 and second polarisation beam splitter 66.

Wavefront sensor device 5 includes a wavefront sensor 50 arranged in a wavefront sensor beam path S_6 that is separated from the further beam path S_5 by a second
 10 beam splitter 63 between delay device 62 and first polarisation beam splitter 64. Wavefront sensor device 5 includes a wavefront error analyser 52, which is designed to generate a correction signal and forward said signal to an adjustment device 33 of adaptive mirror 32. The adaptive mirror 32 is adjusted in the closed control circuit according to usual processes of the adaptive optics unit by means of the correction
 15 signal generated by the wavefront error analyser 52 associated with wavefront sensor 50. For this purpose, wavefront sensor 50 measures the wavefront errors caused by turbulence on the optical propagation path, and the wavefront error analyser 52 in the form of an electronic assembly arranged downstream therefrom 52 determines the correction signals from the result of the measurement. A "Hartmann-
 20 Shack sensor" for example may be used as the wavefront sensor.

A single point light source is needed on target object Z so that the wavefront errors can be measured with wavefront sensor 50. This light source generates the reference wavefront, which passes along the imaging path of fine tracking camera 40
 25 (S_3 , S_4) until it reaches wavefront sensor 50. This radiation is decoupled before fine tracking camera 40 and diverted along the further beam path S_5 via first polarisation beam splitter 64, and then diverted along wavefront sensor beam path S_6 to wavefront sensor 50 via the second beam splitter 63.

30 Illumination laser 1 is also used to generate the single point light source on target object Z, specifically by directing the delayed partial radiation L_{1V} toward target object Z over the same optical path used for the imaging by fine tracking camera 40 and

wavefront measurement via wavefront sensor 50. Partial radiation L_{1V} is thus guided "backwards" to target object Z via receiving optics unit 3. Thus, the stabilisation of the beam axis described earlier serves to keep the generation of the single point light source in a fixed position on target object Z, wherein the position can be chosen
 5 freely using the image from fine tracking camera 40.

The partial radiation guide device 6 provided according to the invention is used to couple the delayed partial radiation L_{1V} into the optical path of fine tracking camera 40 and to decouple the radiation reflected by the target object Z from the single point
 10 light source generated thereon from the optical path of the fine tracking camera 40. It consists of the optical delay device 62, the first Pockels cell 65 and the second Pockels cell 67. The purpose of this arrangement is to couple the delayed partial radiation L_{1V} into the optical path (fourth beam path S_4) between the fine tracking camera 40 and the receiving optics unit 3, and to decouple the radiation reflected by
 15 the target object Z from the single point light source generated on the target object from the optical path between receiving optics unit 3 and fine tracking camera 40 as efficiently as possible so that the laser power required to illuminate target object Z is kept as low as possible.

20 To achieve this, the generation and the receiving of radiation components L_1 and L_2 of the laser radiation L generated by illumination laser 1, or the receiving of their reflections from target object Z, which serve as illumination for fine tracking camera 40 and wavefront sensor 50, are offset temporally. The temporal offset of said components is created with the aid of optical delay path 61 in delay device 62, which
 25 path is preferably longer than 3 m such that the laser pulses are offset temporally due to their different transit times.

Since partial radiation L_1 is less intense than the radiation of illumination beam L_2 , the more intense pulses P_2 of the emitted illumination beam L_2 and the pulses P_1 of the
 30 delayed partial radiation L_{1V} emitted with a temporal offset thereto are readily distinguishable, as is evident in Fig. 2A. Consequently, pulses P_{1R} of the received reflected partial radiation L_{1V} and pulses P_{2R} of the received reflected illumination

radiation L_2' are also readily distinguishable, as is shown in Fig. 2B. The use of a separate laser to generate the single point light source is therefore not necessary in the inventive device described here.

5 The pp-polarised, delayed partial radiation L_{1V} is coupled into the optical path of fine tracking camera 40 via first polarisation beam splitter 64 before Pockels cells 65, 67, as is shown in Fig. 1. Second polarisation beam splitter 66 with a transmission direction perpendicular to that of first polarisation beam splitter 64 is mounted after the two Pockels cells 65, 67 in the direction of radiation.

10

In order to enable the radiation reflected from target object Z to be received by fine tracking camera 40 and wavefront sensor 50, the first Pockels cell 65 and the second Pockels cell 67 are actuated by suitable voltage pulses to emit laser pulses synchronously. As a result, the polarisation plane of the transmitted light that
 15 originates from illumination laser 1, that is to say from the reflected illumination radiation L_2' , is rotated through 90° . The transmission positions of the first Pockels cell 65 and the second Pockels cell 67 are arranged perpendicularly to one another (polarisation direction pp and sp, respectively).

20 The construction of the optical switching arrangement of the two Pockels cells 65, 67, of the first polarisation beam splitters 34 arranged at the intersection point of the fourth beam path S_4 with the further beam path S_5 and of the second polarisation beam splitter 36 dividing beam path S_4 on the side facing the receiving optics unit means that this optical switching arrangement is always passable for partial radiation
 25 L_1 "backwards", that is to say towards receiving optics unit 3, because when the laser pulses are emitted to illuminate target object Z for imaging by fine tracking camera 40 (illumination beam L_2) and, with a time delay relative thereto, to generate the single point light source on target object Z for wavefront measurement by wavefront sensor 50 (partial beam L_1), Pockels cells 65, 67 are not actuated. When first polarisation
 30 beam splitter 34 diverts the pp-polarised partial beam L_1 , first Pockels cell 65 is open in the pp direction, meaning that it transmits the emitted laser pulse of partial radiation L_1 , which then also passes through second polarisation beam splitter 36.

Alternatively, the polarisation directions of polarisation beam splitters 34, 36 and of the Pockels cells 35, 37 may each be rotated through 90° as well.

After a period that is identical with twice the transit time of the laser light to target
 5 object Z, the polarisation directions of the Pockels cells 35, 37 are switched in synchronisation with the pulse clock of the radiation of illumination beam L_2 for the duration of the laser pulse, for example 10 nanoseconds; in the example illustrated, the first Pockels cell 65 is switched to transmission in sp polarisation direction and the second Pockels cell 67 is switched to transmission in pp polarisation direction.

10 The reflected illumination radiation L_2' (pp-polarised) passes through the second polarisation beam splitter 36 and is rotated into the sp polarisation plane in first Pockels cell 35. In this way, this polarisation-rotated, reflected illumination radiation L_2' is also able to pass through first polarisation beam splitter 34 and is guided to the image capturing device 4. The optical path to receiving of the laser light that is
 15 backscattered from target object Z by fine tracking camera 40 is thus rendered clear. Consequently, the illumination radiation L_2' reflected from target object Z is guided always and essentially without loss to image capturing device 4 by first polarisation beam splitter 34.

20 After the actuation voltage for the two Pockels cells 65, 67 is switched off, the polarisation planes of the received light are no longer rotated through 90° . The delayed laser light of the reflected partial beam L_{1V} (pp-polarised) reflected from the single point light source on the target object therefore passes unaltered through the second polarisation beam splitter 36 and the first Pockels cell 35, and is decoupled
 25 by first polarisation beam splitter 64, which is arranged before fine tracking camera 40. 50% of the intensity thereof is then diverted to wavefront sensor 50 by means of second beam splitter 63.

The provision of two Pockels cells 65, 67, which are arranged parallel to one another
 30 by means of polarisation beam splitters 34, 36 and bypass radiation path S_{4B} and are designed for polarisation planes that are rotated through 90° relative to each other, increases intensity of the radiation that is incident on image capturing device 4,

particularly in the case in which the incoming, reflected radiation has been depolarised with respect to the emitted radiation, by reflection on target object Z, for example.

- 5 The device according to the invention described above is used to obtain image information with high optical resolution about distant moving targets with little optical radiation of their own. Harmful influences on the optical resolution of the images due to incorrect target tracking as well as atmospheric turbulence in the observation path are minimised by adaptive optics methods. One possible application for this device is
- 10 fine tracking of flying targets in conjunction with a wide angle aiming system, in a laser weapon for example.

The method used may offer a further benefit in that fine tracking camera 40 is preferably operated in "range gating mode". This is advantageous for minimising

15 background-induced noise in the image information.

Reference signs in the claims, the description and the drawings are intended purely to provide a better understanding of the invention and are not intended to limit the scope of protection.

20

List of reference signs

Elements are designated as follows:

5	1	Illumination laser
	2	Illumination optics unit
	3	Receiving optics unit
	4	Image capturing device
	5	Wavefront sensor device
10	6	Partial radiation guide device
	20	Beam diverging optics unit
	30	First optical correcting element (adjustable mirror)
	31	Adjustment device
	32	Second optical correcting element (adaptive mirror)
15	33	Adjustment device
	34	Polarisation beam splitter
	35	Pockels cell
	36	Polarisation beam splitter
	37	Pockels cell
20	40	Fine tracking camera
	42	Image analyser
	50	Wavefront sensor
	52	Wavefront error analyser
	60	Beam splitter
25	61	Delay path
	62	Delay device
	63	Beam splitter
	64	Polarisation beam splitter
	65	Pockels cell
30	66	Polarisation beam splitter
	67	Pockels cell

	L	Laser beam
	L ₁	Partial beam
	L _{1V}	Partial radiation
	L ₂	Illumination beam
5	L _{2'}	Reflected illumination radiation
	P ₁	Pulse
	P _{1R}	Pulse
	P _{2R}	Pulse
	R	Laser light
10	S ₁	Beam path
	S ₂	Beam path
	S _{2V}	Beam path
	S ₃	Beam path
	S ₄	Beam path
15	S _{4A}	Bypass beam path
	S _{4B}	Bypass beam path
	S ₅	Beam path
	S ₆	Beam path
	Z	Target object
20		

Claims

1. A method for capturing the image of a target object (Z) illuminated by an illumination laser (1) including the steps of:
 - 5 a) Illuminating the target object (Z) by means of a pulsed laser beam (L) emitted by the illumination laser (1), which beam is aimed at the target object (Z) in the form of an illumination (L_2) beam by an illumination optics unit (2);
 - b) Receiving the illumination beam laser light reflected from the target object (Z) by means of a receiving optics unit (3);
 - 10 c) Directing the received reflected illumination beam laser light to an image capturing device (4) to generate an image of the target object on the image capturing device (4);
 - d) Detecting the angular offset of the image of the target object with respect to a reference axis of the receiving optics unit (3);
 - 15 e) Stabilising the visual axis of the image capturing device (4) detected by imaging of the target object device by means of a first optical correcting element (30) of the receiving optics unit (3) that compensates for the angular offset;
- 20 wherein the following additional steps are carried out to stabilise the imaging of the target object:
 - a'₁) Decoupling a partial beam (L_1) from the laser beam (L) emitted by the illumination laser (1);
 - a'₂) Delaying the decoupled partial beam (L_1) in an optical delay device (62);
 - 25 a'₃) Illuminating the target object (Z) by means of the partial beam (L_1) that is directed at the target object (Z) by the receiving optics unit (3);
 - b'₁) Receiving the partial beam laser light which is reflected by the target object (Z) and which defines a reference wavefront by the receiving optics unit (3);
 - 30 b'₂) Decoupling the received reflected partial beam laser light from the light that is received by the receiving optics unit (3);

- c') Directing the decoupled reflected partial beam laser light to a wavefront sensor (50);
 - d') Detecting a wavefront error in the received reflected partial beam laser light, and
 - 5 e') Fine tuning the receiving optics unit to compensate for the detected wavefront error by means of a second optical correcting element (32) of the receiving optics unit (3).
2. The method for capturing the image of a target object illuminated by an illumination laser (1) according to claim 1,
- 10 **characterised in that**
- step b'2) of decoupling the received reflected partial beam laser light from the light that is received by the receiving optics unit (3) is carried out by means of Pockels cells (65, 67), which are actuated synchronously to assure clocking of
- 15 the pulsed laser beam (L) emitted by the illumination laser (1).
3. A device for capturing the image of a target object (Z) according to the method of claim 1,
- characterised by**
- 20 — an illumination laser (1) which is designed to emit a pulsed laser beam (L);
 - an illumination optics unit (2) provided in the beam path (S_1) of the laser beam (L) emitted by the illumination laser(1);
 - a receiving optics unit (3) for the laser light reflected from the target
 - 25 object (Z);
 - an image capturing device (4) to which the receiving optics unit (3) directs the reflected laser light it receives;
 - a first beam splitter (60) provided between the illumination laser (1) and the illumination optics unit (2), which diverts a partial beam (L_1) out of
 - 30 the pulsed laser beam (L) generated by the illumination laser (1);
 - an optical delay device (62), into which the partial beam (L_1) is guided by the first beam splitter (60);

- a first polarisation beam splitter (64) arranged in the path (S_5) of the beam exiting the optical delay device (62) and in the beam path (S_4) between the receiving optics unit (3) and the image capturing device (4);
 - 5 — a second polarisation beam splitter (66) provided in the beam path (S_4) between the first polarisation beam splitter (64) and the receiving optics unit (3);
 - a Pockels cell (65) provided between the first polarisation beam splitter (64) and the second polarisation beam splitter (66);
 - 10 — a second Pockels cell (67) provided parallel the first Pockels cell (65), which is arranged in a bypass beam path (S_{4A}) formed between the first polarisation beam splitter (64) and the second polarisation beam splitter (66);
 - a wavefront sensor (50), which is arranged in a beam path (S_6) split off from the beam path (S_5) between the first polarisation beam splitter (64) and the delay device (62) by a second beam splitter (63);
 - 15 wherein the receiving optics unit (3) has one rapidly adjustable mirror (30) and one adaptive mirror (32) in its inner beam path (S_3), wherein the image capturing device (4) has an image analyser (42) that sends an adjustment
 - 20 signal to an adjustment device (31) for the rapidly adjustable mirror (30), and wherein the wavefront sensor (50) has a wavefront error analyser (52) which generates a correction signal and forwards it to an adjustment device (33) of the adaptive mirror (32).
- 25 4. The device according to claim 3,
characterised in that
the illumination optics unit (2) has a beam diverging optics unit (20).
5. The device according to claim 3 or 4,
30 **characterised in that**
the wavefront sensor (50) is formed by a Hartmann-Shack sensor.

6. The device according to any one of claims 3 to 5,
characterised in that
the transmission direction of the first polarisation beam splitter (64) is
perpendicular to that of the second polarisation beam splitter (66).

5

7. The device according to any one of claims 3 to 6,
characterised in that
the image capturing device (4) includes a fine tracking camera (40) that is
designed to operate in range gating mode.

10