

Method and system for calibration of a radio direction finder

FIELD OF THE INVENTION

The present invention relates to a technique for direction finding and more particularly to a method and a system for calibrating a radio direction finder.

5 BACKGROUND OF THE INVENTION

Radio direction finders (RDF) are well known in the art as tools for finding the direction to a source of electromagnetic radiation. A direction finder may, for example, be a ground-based, an airborne or seaborne system that provides a possibility to locate or monitor various radio signal sources, stationary or movable,
10 by determining the direction of the bearing line to the source. RDFs have many applications which may require the ability to determine the coordinates of radio source over a broad range of broadband frequencies. For instance, wideband RDFs may scan a frequency range of a few MHz to several thousand MHz.

A radio direction finder utilizes an array of antennas (usually two or more)
15 dispersed along the surface of the measurement platform. For ground-based systems, the antennas are typically stationary and the directional information obtained is used to locate the signal source. In aerial or nautical applications, the antennas are carried by a mobile platform, such an aircraft or ship, to receive an electromagnetic signal and process it for obtaining the bearing line from this
20 platform to a source of electromagnetic radiation. In that regard, if the position of the signal source is fixed and known, RDF can be used to determine the platform's position relative to the fixed signal source and, hence, the platform's location. Alternatively, if the platform's position is known, RDF can be used to locate the

– 2 –

signal source. For instance, this source can be originated from transmitters used by enemy troops, transmission sources associated with weapons and ordinance, or can be radiation from any type of communications device.

The determination of direction employs amplitude and/or phase
 5 comparisons of the signals received by the different antennas from the source of the electromagnetic radiation. Since the antenna's patterns are affected by the platform on which they are mounted a calibration process is required to account for uncalculable effects.

Referring to **Fig. 1**, the conventional calibration of an airborne radio
 10 direction finder can involve the flying of a surveillance aircraft **11** in a horizontal plane in a circular manner so that the aircraft turned 360^0 in azimuth. The calibration system includes a calibration transmitter **12** arranged at a ground calibration station in the known location on the ground, and a calibration receiver **13** arranged at the aircraft **11**. The calibration transmitter **12** is capable of
 15 transmitting electromagnetic signals in a predetermined frequency range while the aircraft moves in the manner that all required azimuth angles φ and depression angles Θ are covered. For instance, the depression angle can be close to 0^0 when the aircraft is distant from the calibration transmitter **12**, while be close to 90^0 when the aircraft flies directly over the calibration transmitter **12**.

Referring to **Fig. 2**, an exemplary diagram of a conventional calibration
 20 electromagnetic signal transmitted by the calibration transmitter is illustrated. For the predetermined frequency range, the calibration signal is sampled over time so that a set of required frequencies $f_1, f_2, \dots, f_n$ is transmitted cyclically to the aircraft from the ground calibration station. As a result of the calibration process, a set of
 25 calibration tables is formed establishing a relationship between amplitude and/or phase differences between signals received by the antennas, frequencies $f_1, f_2, \dots, f_n$, azimuth angles $\varphi_1, \varphi_2, \dots, \varphi_m$ and depression angles $\Theta_1, \Theta_2, \dots, \Theta_k$; where n is the number of the measurement frequencies, m and k are the numbers of the selected azimuth and depression angles, respectively, at which the measurements are carried
 30 out. The quality of the calibration is dictated by the number n of the frequencies

- 3 -

and angle increments (resolution) at which the measurements are carried out, and the purity of the environmental spectrum.

In the conventional calibration technique, each frequency is transmitted/received for a relatively long time period, e.g., 250-500 milliseconds, that results into a rather slow calibration process. Typically, the data, which can be collected during each collection circle of the vehicle, do not exceed the data corresponding to about 10 frequencies. Another drawback of the conventional calibration technique is in the fact that the long transmission time period also increases the probability of being exposed to the interference with the signals originated from external transmitters. Conventionally, if such interference is noticed, the operator usually rejects the collected data, and then resumes another collection of the data with a frequency offset corresponding to the interfered frequency. However, in most cases the operator cannot distinguish between appropriate signals and interfered signals, and therefore cannot eliminate the interference data from the corrupted data in order to use it for generation of a calibration table.

Moreover, in the conventional techniques, synchronization between the ground transmitter and the onboard calibration receiver is based on a detection process. More specifically, in the beginning, the onboard calibration receiver is set to the measurements at the first frequency f_1 from the set $f_1, f_2, \dots, f_n$, as soon as the successful interception of the first signal of the corresponding frequency is performed. Then, the system steps to the next entries of the frequency set. Hence, the conventional synchronization is based on the detection of the first frequency of the set in each retransmission cycle. Any time that this frequency is interfered with the environment electromagnetic signals, it can cause lose of the synchronization. Thus, in order to avoid the interference with the environment electromagnetic signals, the calibration flight, preferably, is carried out at only certain hours of day or at certain distances from the sources of the environment electromagnetic signals. Because of these reasons, the conventional calibration process requires intensive

– 4 –

interaction between the ground transmission station and the onboard operators, which by itself increases the interference and demands a skilled ground operator.

SUMMARY OF THE INVENTION

5 Thus, there is still a need in the art for, and it would be useful to have, novel calibration system and method for direction finding techniques.

The present invention partially eliminates disadvantages of the conventional calibration technique and provides a new implementation scheme which enables to enhance the calibration process.

10 According to one embodiment of the invention the present invention, a dwell time range of the communication frequency signals used for transmitting/receiving each frequency is set to a predetermined value. Preferably, this predetermined value is selected to be as short as possible, e.g., 0.2–100 milliseconds. The limitation on the duration of the dwell time is associated with a
15 magnitude of the signal-to-noise ratio required by the on-board calibration receiver. The decrease of the dwell time decreases the probability of interference with the electromagnetic signals of the environment.

Moreover, according to another embodiment of the invention, the receiver and the calibration transmitter are synchronized in time by using a common
20 synchronization source. An example of the synchronization source includes, but is not limited to, GPS (Global Positioning System). In other words, contrary to the prior art technique, where the synchronization is based on a detection process and no time synchronization is utilized, the present invention employs common clock signals for synchronization communication frequency signals at the calibration
25 transmitter and receiver ends.

Furthermore, in accordance with yet another embodiment of the invention, a certain time interval (“hop” duration) is selected within the dwell time range for transmitting each desired frequency. In other words, contrary to the prior art techniques, where the time interval used for transmitting each desired frequency

- 5 -

coincided with the dwell time range, in the present invention, only a part of the dwell time range is used for the transmission. The utilization of a transmitting pulse with a predetermined known duration used as a coding of the frequency signals enables the system to identify it and ignore the other signals providing environment
5 interference. According to a further embodiment of the invention, the hop duration interval is located at the middle of the dwell time range. All other signals that do not meet these requirements are rejected.

The present invention also satisfies the aforementioned need by providing a calibration system for providing calibration data for use with a direction finder. The
10 calibration system includes a calibration transmitter, a calibration receiver (herein also referred to as "target platform"), and a synchronization clock source coupled to the calibration transmitter and receiver.

It should be understood that generally, the calibration system can be an airborne calibration system, a satellite calibration system, a seaborne calibration
15 system, and/or ground calibration system. Accordingly, the calibration transmitter and the calibration receiver, each can be arranged either at terrestrial or non-terrestrial calibration stations. The terrestrial station and non-terrestrial calibration station, each can be either mobile or stationary.

According to an embodiment of the present invention the calibration
20 transmitter includes a transmitting antenna, a transmitter synchronization module, a frequency signal generator coupled to the transmitting antenna, and a controller unit coupled to the transmitter synchronization module and the frequency signal generator.

The transmitting antenna is configured for radiating electromagnetic
25 radiation in a predetermined wide frequency range in a required direction. The transmitter synchronization module is configured for providing transmitter synchronization clock signals. The frequency signal generator is configured for generating communication frequency signals corresponding to a list of predetermined frequencies. The controller unit is configured for receiving the
30 transmitter synchronization clock signals and producing controller signals required

- 6 -

for triggering operation of the frequency signal generator to generate the frequency signals sequentially from the list of predetermined frequencies during hop duration intervals located within dwell time ranges of the communication frequency signals.

The calibration receiver includes an array of antennas, a receiver
5 synchronization module, and an onboard direction finder sensor associated with the array of antennas and coupled to the receiver synchronization module.

Examples of the direction finder sensor include, but are not limited to, COMINT system ELINT system, and radar direction finding systems employing an interferometer technique.

10 The array of antennas is configured to receive radio frequency electromagnetic transmissions from the calibration transmitter. The receiver synchronization module is configured to provide synchronization clock signals equal to the clock signals of the transmitter synchronization module. The onboard direction finder sensor is configured for scanning the same list of predetermined
15 frequencies as in the ground station, intercepting frequency signals transmitted during hop duration time intervals located within the dwell time ranges, and rejecting all other frequency signals received within the dwell time ranges having duration different than the hop duration time intervals.

The calibration method and system of the present invention has many of the
20 advantages of the technique mentioned theretofore, while simultaneously overcoming some of the disadvantages normally associated therewith.

For example, the known duration of the transmitting pulses corresponding to transmitted calibration frequencies is used to filter out undesired signals received by the calibration receiver.

25 Moreover, the signals having short duration pulses cause minimal interference with other neighbor systems. Thus, it makes easier to obtain permission to operate the calibration system.

In accordance with the calibration scheme of the present invention, the number of transmitted frequencies and the number of retransmission cycles (per
30 flight) can be increased, thus better resolution in frequency and angles can be

- 7 -

achieved. Hence, a complete set of calibration data can be obtained in one flight/sailing path.

Likewise, due to the high amount of the collected number of frequency signals, there is no need to update the frequency list. In particular, the data of the
5 measurements obtained at the interfering frequencies could be neglected, because of redundancy of the number of the frequencies.

The calibration system utilizing the calibration scheme of the present invention does not require skilled operators of the calibration station, due to the fact that updating of the frequency list according to the environmental interference
10 (which in conventional system had to be done online simultaneously in the target platform and the calibration transmitter end) is not required anymore.

By using the method and system of the present invention, it is not necessary to perform calibration flight at only certain hours of day or at certain locations to avoid interference.

15 The time synchronization technique employed by the present invention increases the time efficiency of the measurements. Moreover, contrary to the prior art technique, it does not dependent on the detection process.

Thus, according to one broad aspect of the invention, there is provided in a method for providing calibration data for use with a direction finder, the
20 improvement comprising the following method steps all carried out at a calibration transmitter end adaptive for communication with a remote calibration receiver:

- (a) setting a value of at least one dwell time range of a communication frequency signal employed for transmitting a frequency from a list of predetermined frequencies to a predetermined value;
- 25 (b) synchronizing in time said at least one dwell time range between a calibration transmitter and a calibration receiver by using clock signals of a common synchronization source;
- (c) providing a hop duration time interval within said at least one dwell time range for transmitting said frequency;

- 8 -

(d) generating and transmitting said communication frequency signal corresponding to said frequency during said hop duration interval.

According to another broad aspect of the invention, there is provided in a method for providing calibration data for use with a direction finder, the improvement comprising the following method steps all carried out at a calibration receiver end adaptive for communication with a calibration transmitter:

- (a) providing synchronization in time between a calibration transmitter and the calibration receiver by using clock signals of a synchronization source for at least one dwell time range of a communication frequency signal employed for transmitting a frequency from a list of predetermined frequencies;
- (b) scanning the list of predetermined frequencies;
- (c) intercepting a frequency signal transmitted during a hop duration time interval within said at least one dwell time range; and
- (d) rejecting all other frequency signals received within said at least one dwell time range having duration different than said hop duration time interval.

According to a further broad aspect of the invention, there is provided a calibration system for providing calibration data for use with a direction finder, the calibration system utilizing a calibration transmitter including a transmitting antenna, a signal generator operable for transmitting communication frequency signals corresponding to a list of predetermined frequencies, and a calibration receiver including an array of antennas for receiving radio frequency transmissions from the calibration transmitter, the calibration system comprising:

- (i) transmitter and receiver synchronization modules configured for providing, respectively, transmitter and receiver clock signals,

(ii) a controller unit coupled to the transmitter synchronization module and the frequency signal generator, and configured for receiving said transmitter synchronization clock signals and producing controller signals required for triggering operation of the frequency signal generator to generate the frequency

- 9 -

signals sequentially from said list of predetermined frequencies during hop duration intervals located within dwell time ranges of said communication frequency signals;

(iii) an onboard direction finder sensor associated with said array of antennas
5 and coupled to the receiver synchronization module, the direction finder sensor being configured for scanning the list of predetermined frequencies, intercepting frequency signals transmitted during hop duration time intervals located within the dwell time ranges, and rejecting all other frequency signals received within the dwell time ranges having duration different than said hop duration time intervals;
10 and

(iv) a synchronization clock source coupled to the transmitter synchronization module and the receiver synchronization module, and being configured for synchronizing clock signals provided by the transmitter and receiver synchronization modules.

15 According to yet a broad aspect of the invention, there is provided a method for providing calibration data for use with a direction finder, comprising:

(A) providing a relative motion of a calibration receiver in a circle manner with respect to calibration transmitter at a predetermined distance from each other,

(B) preparing a communication frequency signal employed for transmitting
20 a frequency from a list of predetermined frequencies, said preparing comprises:

- (a) setting a value of at least one dwell time range of said communication frequency signal to a predetermined value;
- (b) synchronizing in time said at least one dwell time range between the calibration transmitter and the calibration receiver by using clock signals
25 of a common synchronization source;
- (c) providing a hop duration time interval within said at least one dwell time range for transmitting said frequency;
- (d) generating said communication frequency signal corresponding to said frequency during said hop duration interval.

– 10 –

(C) transmitting said communication frequency signal towards said calibration receiver;

(D) scanning the list of predetermined frequencies the calibration receiver;

(E) intercepting a frequency signal transmitted during the hop duration
5 time interval within said at least one dwell time range by the calibration receiver; and

(G) rejecting all other frequency signals received within said at least one dwell time range having duration different than said hop duration time interval by the receiver;

10 (H) producing a Signal Descriptor based on the frequency signal intercepted in step (E).

There has thus been outlined, rather broadly, the more important features of the invention in order that the detailed description thereof that follows hereinafter may be better understood. Additional details and advantages of the invention will
15 be set forth in the detailed description, and in part will be appreciated from the description, or may be learned by practice of the invention.

BRIEF DESCRIPTION OF THE DRAWINGS

In order to understand the invention and to see how it may be carried out in
20 practice, preferred embodiments will now be described, by way of non-limiting examples only, with reference to the accompanying drawings, in which:

Fig. 1 illustrates an exemplary scheme of in-flight calibration process;

Fig. 2 is a pulse diagram of the electromagnetic signal used in a conventional calibration technique;

25 **Fig. 3** illustrates a schematic block diagram of a calibration system for providing calibration data, in accordance with an embodiment of the present invention; and

Fig. 4 illustrates an exemplary scheme of synchronization of the calibration system of the present invention.

DETAILED DESCRIPTION OF THE INVENTION

The principles and operation of the calibration process and system according to the present invention may be better understood with reference to the drawings and the accompanying description, wherein like reference numerals have been used
5 throughout to designate identical elements, where it is convenient for description. It is understood that these drawings are given for illustrative purposes only and are not meant to be limiting.

Referring to **Fig. 3**, a schematic block diagram of a calibration system **30** for
10 providing calibration data is illustrated, in accordance with an embodiment of the present invention. It should be noted that the blocks in **Fig. 3** are intended as functional entities only, such that the functional relationships between the entities are shown, rather than any physical connections and/or physical relationships.

The calibration system **30** includes a calibration transmitter **31**, a calibration
15 receiver **32**, and a synchronization source **33** common for the calibration transmitter **31** and the calibration receiver **32**.

It should be understood that generally, the calibration system **30** can be an airborne calibration system, a satellite calibration system, a seaborne calibration system, and/or ground calibration system. Accordingly, the calibration transmitter
20 **31** and the calibration receiver **32**, each can be arranged either at terrestrial or non-terrestrial calibration stations which, in turn, can be either mobile or stationary.

According to one example, the calibration transmitter and the calibration receiver, each can be arranged at the corresponding terrestrial calibration station (not shown). The terrestrial calibration stations can be either stationary or mounted
25 on a mobile platform, e.g., an automobile.

According to another example, the calibration transmitter and the calibration receiver, each can be arranged at the corresponding non-terrestrial calibration stations (not shown) mounted on mobile platforms selected from an aircraft, ship and satellite.

– 12 –

The synchronization source **33** is configured for generating a clock signal required for time synchronization of the calibration transmitter **31** and the calibration receiver **32**. An example of the synchronization source **33** suitable for the purpose of the present invention includes, but is not limited to, GPS (Global
5 Positioning System).

The calibration transmitter **31** includes a transmitting antenna **311**, a signal generator **312** coupled to the transmitting antenna **311**, a transmitter synchronization module **313**, and a controller unit (system) **314** coupled to the transmitter synchronization module **313** and the frequency signal generator **312**.
10 The transmitting antenna **311** is configured for radiating electromagnetic radiation in a predetermined wide frequency range towards the calibration receiver **32**. The transmitter synchronization module **313** is coupled to the synchronization source **33**. The frequency signal generator **312** is configured for generating frequency signals corresponding to a list of predetermined frequencies $f_1, f_2, \dots, f_n$. The
15 controller unit **314** is configured to receive the clock signal from the transmitter synchronization module **313** and produce controller signals required for triggering operation of the frequency signal generator **312** for generating frequency signals sequentially from the list of the predetermined frequencies. When required, the calibration transmitter **31** can further include an RF amplifier **315** coupled to the
20 transmitting antenna **311** and the frequency signal generator **312**, and configured for amplifying the frequency signals produced by the signal generator **312**, and relaying the amplified frequency signals to the transmitting antenna **311**.

According to an embodiment of the invention, the calibration receiver **32** (target platform) includes an onboard direction finder sensor (DFS) **321**, a receiver
25 synchronization module **322**, and an array of antennas **323** associated with the DFS **321**.

Examples of the direction finder sensor **321** include, but are not limited to, COMINT (communication intercept) system and ELINT (electronic intelligence)

– 13 –

system produced, for example, by the Applicant of the present application, and radar direction finding systems employing an interferometer technique.

The receiver synchronization module 322 is configured to provide synchronization clock signals equal to the synchronization clock signals used at the calibration transmitter 31. The antennas 323 are dispersed along the surface of the measurement target platform, and configured to receive radio frequency electromagnetic transmission from the calibration transmitter 31 and provide it to the DFS 321 in the form of communication signals representing a sequence of frequency signals.

10 In operation, at the calibration transmitter end, the controller unit 314 loads into the frequency signal generator 312 a list of predetermined frequencies $f_1, f_2, \dots, f_n$ selected for the calibration process. Moreover, the controller unit 314 generates the controller signal and provides this signal to the frequency signal generator 312 for triggering thereof to produce the frequency signals sequentially from the list of the predetermined frequencies. The controller signal is indicative of the desired dwell time range, a “hop” duration time interval (i.e., a certain time interval during which each frequency is transmitted), and a time delay defining a position of the hop duration interval within the dwell time range, as will be described hereinbelow in detail.

20 Referring to **Fig. 3** and **Fig. 4** together, the dwell time range of the pulses of the communication signals used for transmitting/receiving each frequency is set to a predetermined value (see **Diagram A**). Preferably, this predetermined value is selected to be as short as possible, e.g., 0.2–100 milliseconds. The decrease of the dwell time reduces the probability of interference with the electromagnetic signals of the environment. The limitation on the duration of the dwell time is associated, *inter alia*, with a magnitude of the signal-to-noise ratio required by the on-board calibration receiver.

30 According to one example, magnitudes of the dwell time ranges of the communication frequency signals employed for transmitting/receiving the frequencies $f_1, f_2, \dots, f_n$ are all equal. According to another example, magnitudes of

– 14 –

the dwell time ranges of some or all of the communication frequency signals corresponding to different frequencies can be different.

In accordance with an embodiment of the invention, the operation of the calibration transmitter **31** and the calibration receiver **32** are synchronized in time by using the GPS. It should be appreciated by a person skilled in the art that contrary to the prior art technique, where the synchronization is based on a detection process and no time synchronization is utilized, the present invention employs a common clock signal for synchronization dwell time ranges at the calibration transmitter and receiver ends.

For example, when the dwell time ranges are all set to 5 milliseconds and a synchronization period of the clock signals (generated by the GPS) is set to 1 PPS the number of frequencies that can be handled by the calibration system in one second equals 200. In other words, calibration data corresponding to 200 frequencies can be collected in one flight/sailing calibration path.

It should be appreciated that if more than 200 frequencies are required for completing the calibration process, the synchronization period can be extended from one second to two (or more) seconds, thereby to achieve the capability to collect data from 400 (or more) frequencies in one calibration path.

In particular, the two-second-synchronization regime can be implemented by filtering out all the odd 1 PPS signals. In this case, resynchronization takes place in the calibration transmitter **31** and the calibration receiver **32** only for the even PPS signals.

In accordance with an embodiment of the invention, the controller unit **314** sets certain time intervals (i.e., “hop” duration time interval) during which each desired frequencies are transmitted. The hop duration intervals are selected within the dwell time ranges (see **Diagram B**). For example, when the dwell time ranges are equal for all the frequency signals and set to 5 milliseconds, the hop duration time intervals can be set to 3 milliseconds for all the frequency signals.

It should be appreciated by a person versed in the art that contrary to the prior art techniques, where the time interval used for transmitting each desired

- 15 -

frequency coincided with the dwell time range, in the present invention, only a part of the dwell time range is used for the transmission. The utilization of a transmitting pulse with a predetermined known duration enables the system to identify it and ignore the other signals providing environment interference.

5 In accordance with a further embodiment of the invention, the controller unit **314** sets values of time delay defining a position of the hop duration interval within the corresponding dwell time range. Preferably, but is not mandatory that each hop duration time interval for transmitting the corresponding frequency is located in the middle of the corresponding dwell time range (as shown in diagram
10 **B**). In order that the hop duration interval was in the middle of the dwell time range when the signal arrives at the receiver, the time required for the traveling of the communication signals between the calibration transmitter **31** and the calibration receiver **32** should be taken into account in the synchronization process. In this case, for the transmitting frequency signal the value of the time delay for
15 positioning the hop duration interval within the dwell time regions can be calculated in accordance with the following equation:

$$t_D = (t_{DW} - t_h)/2 - S/c ,$$

where t_D is the time delay; t_{DW} is the corresponding dwell time range; t_h is the hop duration time interval; S is the distance between the calibration transmitter **31** and
20 the calibration receiver **32**; and c is the light velocity.

For example, when the dwell time ranges are all set to 5 milliseconds and the hop duration intervals are set to 3 milliseconds, a value of the time delay for all the hop duration intervals can be calculated as 1 millisecond minus the signal propagation time between the calibration transmitter **31** and the calibration receiver
25 **32**.

In operation for each synchronization clock signal, the controller unit **314** generates a controller signal (indicative of the desired dwell time ranges, the hop duration time intervals, and the time delays) and relays it to the signal generator **312**. The signal generator **312**, triggered by controller signal, sweeps the frequency
30 list table once at the dwell time rate, and then transmits each frequency over the

– 16 –

required hop duration time interval which position within the dwell time range is determined by the required time delay, as described above.

In operation, the calibration transmitter **31** transmits continuously the communication frequency signals corresponding to the predetermined frequency list, prepared as described above. A relative motion in a circle manner (clockwise or counterclockwise) of the calibration receiver **32** is provided with respect to the calibration transmitter **31** at a predetermined distance from each other, but within the operational range of the calibration receiver **32**. The communication signals intercepted by the calibration receiver **32** should have such magnitude in order to meet the required signal-to-noise condition.

It should be understood that the relative motion of the calibration receiver **32** with respect to the calibration transmitter **31** includes the case when, for example, the calibration receiver **32** moves with respect to the ground, while the calibration transmitter **31** is motionless. According to another example, the calibration receiver **31** can be motionless, while the calibration transmitter **32** moves with respect to the ground. According to yet an example, the calibration receiver **31** and the calibration transmitter **32** can be in the relative motion, as described above, when they both move with respect to the ground.

At the calibration receiver end, the list of the predetermined frequencies is loaded in the DFS **321**. Then, for each clock signal of the receiver synchronization module, the DFS **321** starts scanning sequentially the list of the predetermined frequencies. For example, 1 PPS timing strobe obtainable from the common GPS (Global Positioning System) source can be used as a clock signal. The DFS **321** is set for intercepting each frequency signal from the predetermined frequency list over the dwell time range (see **Diagram C**).

According to one embodiment of the invention, the DFS **321** is configured to intercept a signal only within a defined duration, such as a predetermined hop duration time interval; all other signals (that do not meet this requirement) are rejected. For example, as described above, when the dwell time ranges are set to 5 milliseconds, and the hop duration intervals are set to 3 milliseconds, the

- 17 -

calibration transmitter **31** transmits communication signals for each frequency over 3 milliseconds every 5 milliseconds. According to this example, the DFS **321** takes into account only 3 milliseconds signals intercepted within 5 milliseconds dwell time ranges.

5 According to a further embodiment of the invention, the DFS **321** is configured to accept only those frequency signals which are not only have predetermined hop duration intervals, but also located at the middle of the dwell time range. According to this embodiment, all other signals that do not meet these requirements are rejected.

10 In operation, for each dwell time range that includes a valid intercepted signal, the DFS **321** produces a Signal Descriptor (SD). Examples of data in the Signal Descriptor can include, but are not limited to the following parameters:

- Signal "Rxx" array that contains the information about phase and amplitudes of the intercepted signals for each antenna from the antenna array **323** of the calibration receiver **32**;
- 15 - Detection parameters of the signal, such as signal duration, phase quality, *etc*;
- Direction of Arrival (DOA) of the signal, when exist;
- Navigation data as reported by a navigation system of the target platform at the time of the intercepting the frequency signal, such as: 20 Latitude, Longitude, Altitude, Pitch, Roll and heading;
- Time of interception of the reported frequency signal.

The DFS **321** can relay the SD to a host computer (not shown) for on-line monitoring, analyzing and building calibration tables. When required, the data can 25 be stored in a memory device (not shown) for a further off-line analyzing and generating the calibration tables.

As such, those skilled in the art to which the present invention pertains, can appreciate that while the present invention has been described in terms of preferred embodiments, the concept upon which this disclosure is based may readily be

– 18 –

utilized as a basis for the designing of other structures, systems and processes for carrying out the several purposes of the present invention.

It should be understood that although the transmitter synchronization module **313** and the receiver synchronization module **322** described above were
5 described as receiving the synchronization clock signal from GPS, any other very accurate synchronization source, e.g., atomic clocks, can be also implemented at the calibration transmitter **31** end and the calibration receiver **32** end (target platform) for the synchronization purpose.

Also, it is to be understood that the phraseology and terminology employed
10 herein are for the purpose of description and should not be regarded as limiting.

In the method claims that follow, alphabetic characters used to designate claim steps are provided for convenience only and do not imply any particular order of performing the steps.

It is important, therefore, that the scope of the invention is not construed as
15 being limited by the illustrative embodiments and examples set forth herein. Other variations are possible within the scope of the present invention as defined in the appended claims and their equivalents.

– 19 –

CLAIMS:

1. In a method for providing calibration data for use with a direction finder, the improvement comprising the following method steps all carried out at a calibration transmitter side adaptive for communication with a remote calibration receiver:

- 5 (a) setting a predetermined value of at least one dwell time range of a communication frequency signal employed for transmitting a frequency from a list of predetermined frequencies;
- (b) synchronizing in time said at least one dwell time range between the calibration transmitter and the calibration receiver by using clock signals
- 10 of a common synchronization source;
- (c) providing a hop duration time interval within said at least one dwell time range for transmitting said frequency;
- (d) generating and transmitting said communication frequency signal corresponding to said frequency during said hop duration interval.

15

2. In a method for providing calibration data according to claim 1, the improvement wherein the value of said at least one dwell time range is selected to be so short that a magnitude of a signal-to-noise ratio was in the limits of the magnitude required by the calibration receiver.

20

3. In a method for providing calibration data according to claim 1, the improvement wherein the value of said at least one dwell time range is between 0.2 milliseconds and 100 milliseconds.

25 4. In a method for providing calibration data according to claim 1, the improvement wherein said hop duration time interval is located in the middle of the dwell time range.

- 20 -

5. In a method for providing calibration data according to claim 1, the improvement wherein said providing of the hop duration time interval within the dwell time range includes:

defining a predetermined location of said hop duration interval within the
5 dwell time range;

calculating a time delay required for locating said hop duration interval at said predetermined location.

6. In a method for providing calibration data according to claim 5, the
10 improvement wherein a value of said time delay is calculated in accordance with an equation $t_D = (t_{DW} - t_h)/2 - S/c$, where t_D is the time delay; t_{DW} is the dwell time range; t_h is the hop duration interval; S is the distance between the calibration transmitter and the calibration receiver; and c is the light velocity.

15 7. In a method for providing calibration data for use with a direction finder, the improvement comprising the following method steps all carried out at a calibration receiver end adaptive for communication with a calibration transmitter:

- 20 (a) providing synchronization in time between the calibration transmitter and the calibration receiver by using clock signals of a synchronization source for at least one dwell time range of a communication frequency signal employed for transmitting a frequency from a list of predetermined frequencies;
- s (b) scanning the list of predetermined frequencies;
- (c) intercepting a frequency signal transmitted during a hop duration time
25 interval within said at least one dwell time range; and
- (d) rejecting all other frequency signals received within said at least one dwell time range having duration different than said hop duration time interval.

- 21 -

8. In a method for providing calibration data according to claim 7, the improvement wherein the value of said at least one dwell time range is selected to be so short that a magnitude of a signal-to-noise ratio was in the limits of the magnitude required by the calibration receiver.

5

9. In a method for providing calibration data according to claim 7, the improvement wherein the value of said at least one dwell time range is between 0.2 milliseconds and 100 milliseconds.

10 10. In a method for providing calibration data according to claim 7, the improvement wherein said hop duration time interval is located in the middle of the dwell time range.

11. In a method for providing calibration data according to claim 10, the
15 improvement further comprising rejecting all other frequency signals received within said at least one dwell time range having location different than said hop duration time interval.

12. A calibration system (30) for providing calibration data for use with a direction
20 finder, the calibration system utilizing a calibration transmitter (31) including a transmitting antenna (311), a frequency signal generator (312) operable for transmitting communication frequency signals corresponding to a list of predetermined frequencies, and a remote calibration receiver (32) including an array of antennas (323) for receiving radio frequency transmissions from the
25 calibration transmitter, the calibration system comprising:

(i) a transmitter synchronization module (313) and a receiver synchronization modules (322) configured for providing, respectively, transmitter and receiver clock signals,

(ii) a controller unit (314) coupled to the transmitter synchronization
30 module (313) and the frequency signal generator (312), and configured for

- 22 -

receiving said transmitter synchronization clock signals and producing controller signals required for triggering operation of the frequency signal generator (312) to generate the frequency signals sequentially from said list of predetermined frequencies during hop duration intervals located within dwell
5 time ranges of said communication frequency signals;

(iii) an onboard direction finder sensor (321) associated with said array of antennas (323) and coupled to the receiver synchronization module (322), the direction finder sensor (321) being configured for scanning the list of predetermined frequencies, intercepting frequency signals transmitted during
10 hop duration time intervals located within the dwell time ranges, and rejecting all other frequency signals received within the dwell time ranges having duration different than said hop duration time intervals; and

(iv) at least one clock synchronization source (33) coupled to the transmitter synchronization module (313) and the receiver synchronization module (322),
15 and being configured for synchronizing clock signals provided by the transmitter synchronization module (313) and the receiver synchronization module (322).

13. The calibration system of claim 12 wherein said synchronization source is GPS
20 or atomic clock.

14. The calibration system of claim 12 or 13 wherein said hop duration time intervals are located in the middle of the dwell time ranges.

25 15. The calibration system of any one of claims 12 to 14 wherein the direction finder sensor further configured for rejecting all other frequency signals received within the dwell time ranges having location different than said hop duration time intervals.

– 23 –

16. The calibration system of any one of claims 12 to 15 wherein the direction finder sensor is selected from COMINT system, ELINT system and radar direction finding systems employing an interferometer technique.

5 17. A method for providing calibration data for use with a direction finder, comprising:

(A) providing a relative motion of a calibration receiver in a circle manner with respect to calibration transmitter at a predetermined distance from each other,

(B) preparing a communication frequency signal employed for transmitting
10 a certain frequency from a list of predetermined frequencies, said preparing comprises:

(a) setting a value of at least one dwell time range of said communication frequency signal to a predetermined value;

(b) synchronizing in time said at least one dwell time range between the
15 calibration transmitter and the calibration receiver by using clock signals of a common synchronization source;

(c) providing a hop duration time interval within said at least one dwell time range for transmitting said certain frequency;

(d) generating said communication frequency signal corresponding to
20 said certain frequency during said hop duration interval.

(C) transmitting said communication frequency signal towards said calibration receiver;

(D) scanning the list of predetermined frequencies by the calibration receiver;

(E) intercepting a frequency signal transmitted during the hop duration time interval within said at least one dwell time range by the calibration receiver; and
25

(G) rejecting all other frequency signals received within said at least one dwell time range having duration different than said hop duration time interval by
30 the receiver;

– 24 –

(H) producing a Signal Descriptor based on the frequency signal intercepted in step (E).

18. The method of claim 17 wherein said hop duration time interval is located in
5 the middle of the dwell time range.

19. The method of claim 17 or 18 wherein said providing of the hop duration time interval within the dwell time range includes:

defining a predetermined location of said hop duration interval within the
10 dwell time range;

calculating a time delay required for locating said hop duration interval at said predetermined location.

20. The method of any one of claims 17 to 19 wherein a value of said time delay is
15 calculated in accordance with an equation $t_D = (t_{DW} - t_h)/2 - S/c$, where t_D is the time delay; t_{DW} is the dwell time range; t_h is the hop duration interval; S is the distance between the calibration transmitter and the calibration receiver; and c is the light velocity.

20 21. The method of any one of claims 17 to 20 further comprising rejecting all other frequency signals received within said at least one dwell time range having location different than said hop duration time interval.

25

30