

Horn, Elementary Antenna, Antenna Structure and Telecommunication Method Associated Therewith

The present invention relates to a horn for an antenna structure for
5 telecommunications, in particular by satellite in the Ka band. The invention also relates to an
elementary antenna comprising such a horn, an antenna structure comprising such an
elementary antenna and a method for telecommunication between two stations using the
antenna structure.

10 In the field of satellite communications, obtaining a high quality of communication
entails achieving performance enhancements for the electromagnetic waves generated by
the antenna structure used in the communication in terms of gain and level of side lobes
(ratio between the intensity of the side lobes and the intensity of the main lobe).

15 In the specific case of the Ka band of the electromagnetic spectrum, two distinct
bands of frequencies are involved. Indeed, in emission, the electromagnetic waves of the Ka
band have a frequency within the range of 27.5 GigaHertz (GHz) to 31 GHz whereas in
reception, the electromagnetic waves of the Ka band have a frequency within the range of
17.3 GHz to 21.2 GHz. In addition, the polarisations of the waves in emission and in
reflection are generally of circular type, either opposing or not.

20 These frequencies and the circular polarisations in reception and emission impose
constraints on the antenna structure. In addition, in the context of satellite linking, it is
necessary to orient the antenna in order to point the satellite that is being used to establish
the link. In addition, in order to reduce the visual signature (physical footprint), solutions of
the parabolic antenna type are generally not preferred.

25 Among the antenna structures that provide the ability to compliantly accommodate
these various constraints, a known technique is to use an electronic scanning phased array
antenna comprising two disjoint antenna panels respectively for the emission of a wave at a
frequency of 30 GHz, and for the reception of a wave at a frequency of 20 GHz. However,
the electronic scanning phased array antenna obtained presents a significant dimensional
30 footprint corresponding to the radiating surfaces for each of the modes of operation (emit /
receive). Besides, such types of antenna offer a level of efficiency that is often inadequate
because most often patch type unit antennas are used. In addition, the implementation of a
circular polarisation in a right orientation for emission panel and a circular polarisation in a
second direction opposite to previous one for the reception portion turn out to be difficult. In
particular, the use of a polariser reduces the flexibility of use of the electronic scanning
35 antenna considered.

In order to limit the losses of the electronic scanning phased array antenna, it is also a known practice to use horn type structures so as to obtain improved efficiency levels.

However, in this case also, the antenna obtained presents a significant overall dimensional footprint on account of the use of a polariser and especially two panels used for the emission and reception.

There exists therefore a need for an antenna structure that is capable of receiving waves at a frequency that is distinct and separate from those of the emitted waves while also being compact.

To this end, the invention provides a horn for elementary antennas for telecommunications, in particular satellite telecommunications. The horn includes a first emitting - receiving portion capable of emitting and receiving an electromagnetic wave at a first frequency, and a second emitting - receiving portion capable of emitting and receiving an electromagnetic wave at a second frequency, the second emitting - receiving portion being distinct and separate from the first emitting - receiving portion, and the ratio between the second frequency and the first frequency being greater than 1.2, preferably greater than 1.5.

According to the particular embodiments, the horn includes one or more of the following characteristic features, taken into consideration individually or in accordance with any technically possible combinations :

- the waves at the first frequency and at the second frequency are included in the Ka band of the electromagnetic spectrum ;
- the horn has a cylindrical or cubic shaped form.

In addition, the invention also relates to an elementary antenna comprising at least one horn as previously described above.

According to the particular embodiments, the elementary antenna includes one or more of the following characteristic features, taken into consideration individually or in accordance with any technically possible combinations :

- the elementary antenna comprises dielectric elements ;
- the elementary antenna comprises a polariser arranged in a manner so as to polarise the waves that the first emitting - receiving portion and the second emitting - receiving portion are capable of emitting ;
- the polariser comprises of two parts arranged in a manner so as to circularly polarise in a first direction the electromagnetic waves that the first emitting - receiving portion is capable of emitting and to circularly polarise the electromagnetic waves that the second emitting - receiving portion is capable of emitting in a direction opposite to the first direction.

The invention also relates to an antenna structure comprising at least one elementary antenna as previously described above.

In addition, the invention also relates to a platform, in particular an aerial platform, comprising at least one elementary antenna such as previously described above or an antenna structure such as previously described above.

The present invention also relates to a method for telecommunication, in particular via satellite, between two stations, the method including the use of at least one elementary antenna such as previously described above or an antenna structure such as previously described above.

Other characteristic features and advantages of the invention will become apparent upon reading the detailed description that follows, of embodiments of the invention, being provided purely by way of example only and with reference made to the drawings which include the following :

- Figure 1, is a schematic top view of an antenna structure according to a first embodiment,
- Figure 2, is a schematic perspective view of the antenna structure represented in Figure 1,
- Figure 3, is a schematic perspective view of an elementary antenna of the antenna structure represented in Figure 1 ;
- Figure 4, is a block diagram of an antenna structure according to a second embodiment ;
- Figure 5, is a block diagram of an antenna structure according to a third embodiment;
- Figure 6, is a schematic perspective view of another example of elementary antenna;
- Figure 7, is a schematic top view of an antenna structure comprising elementary antennas according to Figure 6, and
- Figure 8, is a schematic view of a power splitter circuitry adapted to feed a row of elementary antennas in the antenna structure of Figure 7.

An antenna structure 10 according to a first embodiment is represented in Figures 1 and 2.

The antenna structure 10 is an assembly of elementary antennas 11 assembled in a manner so as to obtain twenty rows grouping together twenty adjoining elementary antennas 11. This description would be valid for any number of rows and for any other arrangement of elementary antennas 11.

As illustrated in Figure 3, each elementary antenna 11 includes a horn 12, a polariser 14, dielectric elements 16 and 18 two access ports 20 for the waves emitted or received by the elementary antenna 11.

The horn 12 comprises a first emitting - receiving portion 22 capable of emitting and receiving an electromagnetic wave at a first frequency f_1 and a second emitting - receiving portion 24 capable of emitting and receiving a wave at a second frequency f_2 .

The second emitting - receiving portion 24 is distinct and separate from the first emitting - receiving portion 22. The emitting - receiving portions 22 and 24 may in one embodiment be combined into one single block.

The ratio between the second frequency f_2 and the first frequency f_1 is greater than 1.2.

Preferably, the ratio between the second frequency f_2 and the first frequency f_1 is greater than 1.5.

Advantageously, the waves whereof the frequency is the first frequency f_1 or the second frequency f_2 are included in the Ka band of the electromagnetic spectrum.

By way of a variant, the waves whereof the frequency is the first frequency f_1 or the second frequency f_2 are included in the X band of the electromagnetic spectrum.

By definition, an electromagnetic wave belongs in the X band when the wave has a frequency within the range of 7.2 GHz to 8.4 GHz.

According to another variant embodiment, the waves whereof the frequency is the first frequency f_1 or the second frequency f_2 are included in the Ku band of the electromagnetic spectrum.

By definition, an electromagnetic wave belongs in the Ku band when the wave has a frequency within the range of 10.7 GHz to 14.25 GHz.

The horn 12 has a cylindrical or cubic shaped form. Owing to this form the emission of the elementary antenna 11 takes on a broad band character. The band covered by a horn typically extends to 40% on either side of the operating frequency.

The horn 12 has a cylindrical shaped form which corresponds to the joining of the first emitting - receiving portion 22 and the second emitting - receiving portion 24. The basis of each emitting - receiving portion 22, 24 is respectively called 22B and 24B.

Thus, in this embodiment, the first basis 22B of the first emitting - receiving portion 22 and the basis 22B of the second emitting - receiving portion 24 each has the shape of a half-disk, the joining of the two emitting - receiving portions thus forming the horn 12.

According to another embodiment illustrated by figure 6, the first basis 22B of the first emitting - receiving portion 22 and the basis 22B of the second emitting - receiving portion 24

each has the same rectangular shape, the joining of the two emitting - receiving portions thus forming the horn 12.

More generally, the first emitting - receiving portion 22 and the second emitting - receiving portion 24 each are each cylinder such that the joining of the two emitting - receiving portions forms the horn 12.

According to a specific embodiment, the basis 22A of first basis 22B of the first emitting - receiving portion 22 and the basis 22B of the second emitting - receiving portion 24 have the same shape. As shown on Figure 6, the first emitting - receiving portion 22 and the second emitting - receiving portion 24 have a basis 22B, 24B sharing the same rectangular shape, so that the joining of the two basis 22B, 24B forms a square.

In such case, as illustrated schematically by Figure 7, the antenna structure 10 is an assembly of elementary antennas 11 assembled in a manner so as to obtain four rows grouping together eight adjoining elementary antennas 11.

This description would be valid for any number of rows and for any other arrangement of elementary antennas 11. Preferably, there are twice the number of rows of elementary antennas 11 in each row.

In addition, the rows are staggered rows, which means that the elementary antennas 11 of the first row are aligned with the elementary antennas 11 of the third row whereas the elementary antennas 11 of the second row are aligned with the elementary antennas 11 of the fourth row.

Figure 8 illustrates an example of the circuitry adapted to command a row of the antenna structure 10. It can notably be noticed that there are four excitation access for the four involved states of polarisation, which are the polarisation Tx, the polarisation Rx and the polarisation LHCP (for Left Hand Circular Polarisation) and the polarisation RHCP (for Right Hand Circular Polarisation).

In a conventional manner, a horn that is suitably dimensioned in order to operate over a broad frequency band has exterior dimensions which are constrained by the wavelength of operation corresponding to the lowest of the frequencies to be emitted or received. In addition, the interior of the latter is empty.

In the example shown, identical to the dielectric elements 16, the interior of the horn 12 is filled with a dielectric material in order to reduce the physical dimensions of the horn 12. In effect, the wavelength in a dielectric material is smaller than the corresponding wavelength in air. Thus, for a given horn structure, a widening up to the frequency of operation is achieved. This dielectric material is a substrate having a permittivity in the range from 2 to 5 depending on design and fabrication constraints.

The polariser 14 is arranged in a manner so as to polarise the waves that the first emitting - receiving portion 22 and the second emitting- reception portion 24 are capable of emitting.

The polariser 14 comprises of two parts arranged in a manner so as to circularly polarise in a first direction the waves that the first –emitting - receiving portion 22 is capable of emitting and to circularly polarise the waves that the second emitting - receiving portion is capable of emitting 24 in a direction opposite to the first direction.

For the remainder of the description, the first direction is the right polarisation.

Thus, the elementary antenna 11 is capable of emitting and / or receiving waves having a right circular polarisation at the first frequency f_1 . The elementary antenna 11 is also capable of emitting and / or receiving waves having a left circular polarisation at the second frequency f_2 .

According to one variant embodiment, the polariser 14 is part of the horn 12.

In the elementary antenna 11, the dielectric elements 16 are inserted so as to reduce the electrical dimension in relation to the wavelength and thus to have a basic antenna with dimensions that make it possible to get sufficiently close to the radiating elements at the time of establishing networking in order to facilitate angular scanning over a range that is sufficiently wide while ensuring maintenance of the compatible radiation performance of the satellite link type application considered. The dielectric elements 16 are preferably only located at the access ports 18, 20 as well as in the polariser 14. By way of a variant, the dielectric elements 16 are extended in the parts 22 and 24.

Each access port 18, 20 is arranged to be opposite a emitting - receiving portion of the horn 12. In the example shown in Figure 1, an access port 18 for a left circularly polarised wave is provided opposite the first emitting - receiving portion 22 of the horn 12 while an access port 20 for the right circularly polarised wave is provided opposite the second emitting - receiving portion 24.

According to a variant embodiment, the antenna structure 10 includes a radome.

In operation, the first emitting - receiving portion 22 receives the electromagnetic waves at a first frequency f_1 when the horn 12 is electrically excited. This wave is left circularly polarised by the polariser 14. This wave then passes through the access port 18 provided for a left circularly polarised wave.

A right circularly polarised wave at the second frequency f_2 passes through the access port 20 provided for a right circularly polarised wave. This wave then passes through the polariser 14 before being emitted by the second emitting - receiving portion 24. This emitting - receiving operation can be reversed between the access ports 18 and 20.

It thus appears that a single element provides the ability to ensure both the emission and reception functions, for two frequencies where the ratio there between is greater than 1.2. This is a compact dual band horn 12 with circular polarisation which thereby makes the elementary antenna 11 dual band.

5 In addition, each elementary antenna 11 is capable of emitting and / or receiving waves in two different states of polarisation, in the present case for example as shown in Figure 1, the left and right circular polarisations. In the case where a wave with linear polarisation is desired, the two access ports 18, 20 are used simultaneously by applying a certain phase shift depending on the orientation of the polarisation desired.

10 In addition, it is easy to dissociate the portion dedicated to the radiation in the antenna structure 10 from other elements of the antenna structure 10 and in particular, the portion dedicated to the switching, the filtering and to the distribution circuit. This dissociation makes it possible to minimise the overall losses of the antenna structure 10.

15 The antenna structure 10 is more compact. This effect is enhanced by the presence of the dielectric elements 16. The antenna structure 10 may have dimensions measuring less than 30 mm.

20 In this first embodiment, each of the access ports 18 and 20 of the different elementary antennas 11 are connected to a duplexer not shown with a view to ensuring adequate isolation between the first and second emitting - receiving portions 22, 24. A duplexer is a device that enables the use of a same given antenna for the emitting and receiving of a signal. The switches and power splitter inserted between the duplexer and the access ports 18, 20 can make possible to correctly feed each elementary antenna and to easily select of the access port 18, 20 and the operation desired for the antenna structure 10.

25 In addition, each elementary antenna 11 is associated with a phase control circuit. Thus, it is possible to orient the beam of the antenna structure 10 in any desired directions in a hemisphere, based on the phase control circuits associated with each of the elements 11. As per the terminology used by the specialist in the field of antennas, this is known as implementing a two dimensional scanning or bidirectional scanning.

30 By way of a variant, the antenna structure 10 operates based on three distinct modes: a fixed mode, a unidirectional scanning mode and a bidirectional scanning mode. Switching between the three modes is executed by making use of a circuit for distribution and control of the appropriate phases.

35 According to the invention, the object is also to provide an antenna structure 10 according to a second embodiment represented in Figure 4. In this second embodiment, each of the access ports 18 and 20 of the elements 11 of a same given row (or of a same

given column) of the antenna structure 10 are grouped together. Thus, all of the access ports 18, 20 of the elementary antennas 11 of the same given row (or of the same given column) are connected to a duplexer 52 in order to ensure proper isolation between the first and second emitting - receiving portions 22, 24 of the elementary antennas 11 considered. For the purposes of simplification, in Figure 4, only the links between some of the elementary antennas 11 of the same row are represented and all of the rows are not represented.

The antenna structure 10 thus includes as many duplexers 52 as there are rows (or columns). As is the case for Figure 4, the switches 54 inserted between the duplexer 52 and the access ports 18, 20 can make possible the easy selection of the access port 18, 20 and the operation desired for the antenna structure 10.

In addition, each elementary antenna 11 is associated with a phase control circuit. Thus, it is possible to orient the beam of the antenna structure 10 in any one single direction in a hemisphere, based on the phase control circuits associated with each of the elementary antennas 11. As per the terminology used by the specialist in the field of antennas, this is known as implementing a one dimensional scanning or unidirectional scanning. In this configuration, in order to obtain bidirectional scanning, the antenna structure 10 is coupled to a motor driven system with one axis.

In a third embodiment (the one shown in Figure 5), all the access ports 18 and 20 of the elementary antennas 11 are grouped together. Thus, for the entire antenna structure 10, only two unique access ports are available. Each of these access ports is associated with a duplexer in order to ensure proper isolation between the emitting - receiving portions. For the purposes of simplification, in Figure 5, only the links between some of the elementary antennas 11 of the same row are represented and all of the rows are not represented.

In this third embodiment, the orientation of the radiation pattern of the antenna structure 10 is unique and cannot be controlled. As per the terminology used by the specialist in the field of antennas, this is known as creating a fixed radiating panel.

Thus, the proposed antenna structure 10 may be used as a substitute for an electronic scanning antenna for telecommunications applications between two stations, in particular via satellite. It is to be noted that in this case, the radiation pattern of the antenna structure 10 thus produced is in conformity with the dimensional specifications stipulated for being used with certain satellites.

Such an antenna structure 10 may advantageously be used in a platform, in particular an aerial platform. In the context of such use, the compactness of the antenna structure 10 makes it possible to reduce the constraints at the level of the equipment installations on the platform.

CLAIMS

1. - A horn (12) for elementary antennas for telecommunications, in particular satellite telecommunications, wherein the horn (12) includes :

- a first emitting - receiving portion (22) adapted to emit and receive an electromagnetic wave at a first frequency (f1), and

- a second emitting - receiving portion (24) adapted to emit and receive an electromagnetic wave at a second frequency (f2), the second emitting - receiving portion (24) being distinct and separate from the first emitting - receiving portion (22) and the ratio between the second frequency (f2) and the first frequency (f1) being greater than 1.2.

2. - A horn according to claim 1, wherein the waves at the first frequency (f1) and the second frequency (f2) are included in the Ka band of the electromagnetic spectrum.

3. - A horn according to claim 1 or 2, wherein the horn (12) has a cylindrical shaped form.

4.- A horn according to any one of claims 1 to 3, wherein the ratio between the second frequency (f2) and the first frequency (f1) is greater than 1.5.

5.- A horn according to any one of claims 1 to 4, wherein the joining of the first emitting - receiving portion (22) and of the second emitting - receiving portion (24) forms the horn (12).

6.- A horn according to any one of claims 1 to 5, wherein the first emitting - receiving portion (22) and the second emitting - receiving portion (24) have a cylindric shape.

7.- A horn according to claim 6, wherein the first emitting - receiving portion (22) and the second emitting - receiving portion (24) have a basis (22B, 24B) sharing the same shape.

8.- A horn according to claim 6 or 7, wherein the shapes of the basis (22B, 24B) the first emitting - receiving portion (22) and the second emitting - receiving portion (24) are chosen among a disk and a rectangle.

9. -An elementary antenna (11) comprising at least one horn (12) according to any one of claims 1 to 8.

10. -An elementary antenna according to claim 9 comprising dielectric elements (16).

5

11. -An elementary antenna according to any one of claim 9 or 10, comprising a polariser (14) arranged in a manner so as to polarise the waves that the first emitting - receiving portion (22) and the second emitting - receiving portion (24) are adapted to emit.

10

12. -An elementary antenna according to claim 11, wherein the polariser (14) comprises of two parts arranged in a manner so as to circularly polarise in a first direction the electromagnetic waves that the first emitting - receiving portion (22) is adapted to emit and to circularly polarise the electromagnetic waves that the second emitting - receiving portion (24) is adapted to emit in a direction opposite to the first direction.

15

13. -An antenna structure (10) comprising at least one elementary antenna (10) according to any one of claims 9 to 12.

20

14. -A platform, in particular an aerial platform, comprising at least one elementary antenna (11) according to any one of claims 9 to 12 or an antenna structure (10) according to claim 13.

25

15. -A method for telecommunication, in particular via satellite, between two stations, the method including the use of at least one elementary antenna (11) according to any one of claims 9 to 12 or an antenna structure (10) according to claim 13.