
Use of dissolved hafnium alkoxides or zirconium alkoxides as starting materials for hafnium oxide layers and hafnium oxynitride layers or zirconium oxide layers and zirconium oxynitride layers

5 The present invention relates to the use of a solution of one or more hafnium or zirconium alkoxides as precursors for hafnium oxide and hafnium oxynitride layers or zirconium oxide and zirconium oxynitride
10 layers. The present invention relates in particular to the use of a 30 to 90% strength by weight solution of one or more hafnium alkoxides or zirconium alkoxides for producing hafnium oxide and hafnium oxynitride layers or zirconium oxide and zirconium oxynitride
15 layers by CVD or ALD methods. In addition, the invention relates to a process for the production of a hafnium oxide and hafnium oxynitride layer or zirconium oxide and zirconium oxynitride layers on an article to be coated, and a hafnium alkoxide solution or zirconium
20 alkoxide solution which contains 30 to 90% by weight of one or more hafnium alkoxides or zirconium alkoxides.

Hafnium oxide and hafnium oxynitride layers are the first choice for future generations of semiconductor
25 components as a dielectric both for MOS transistors in logic modules and for capacitors in memory modules, in particular the good temperature stability of the layers in combination with a high dielectric constant distinguishing the material compared with other metal
30 oxides.

A further important application of hafnium oxide or oxynitride as a dielectric is that for integrated capacitors, so-called MIM (metal-insulator-metal)
35 capacitors in the wiring plane of logic modules, the metal planes being used as electrodes. In this application, the high chemical stability of hafnium

oxide to the nonnoble electrode material, such as titanium nitride and tantalum nitride, in addition to the high dielectric constant compared with silicon nitride or aluminum oxide is advantageous.

5

Proposed solutions to date for depositing hafnium oxide or oxynitride layers are based on the use of hafnium chloride, liquid long-chain undiluted hafnium alkoxides and hafnium-aminoalkyl precursors.

10

Hafnium chloride is a solid having a very low vapor pressure, chlorine also being incorporated in the electrical during the deposition of the layers and the electrical properties thus being adversely affected.

15

Moreover, the edge covering is insufficient.

Although liquid long-chain hafnium alkoxides have a sufficiently high vapor pressure for CVD and ALD methods, the thermal stability of the substances is not sufficient for achieving good edge covering on difficult topographies.

20

Hafniumaminoalkyl precursors have good properties with respect to incorporated carbon in the layer and also very good edge covering, but the material costs are so high that their use for capacitors in memory modules and MIM capacitors appears questionable.

25


A list of the most well known precursors and the manner in which they are used according to the prior art in the production of HfO_2 layers are listed below.

30

The general problem with the use of the precursors is that transition metals of groups IVB and VB have a strong tendency to reach six-fold coordination with ligands. Dimers and oligomers which have low volatility and make it difficult or even impossible to carry out the CVD or ALD methods therefore form.

35

1. HF halides: HfX_4 ; $\text{X} = \text{Cl}, \text{I}$



5 Hf halides are highly reactive ALCVD and CVD precursors. Problems exist with regard to low volatility and - as mentioned above - undesired incorporation of halides in the Hf oxide layer.

10 2. HF nitrate: $\text{Hf}(\text{NO}_3)_4$

The main problem with Hf nitrates is their explosiveness.

15 3. HF alkylamides: $\text{Hf}(\text{NR}'\text{R}'')_4$; R' and $\text{R}'' = \text{CH}_3, \text{C}_2\text{H}_5$

Hf alkylamides are reacted in a reaction with H_2O , O_3 , O radicals, NH_3 or NO_x radicals. They are highly reactive ALCVD precursors. The main problems of their use are
20 the very complicated preparation process and hence their extremely high price.

4. HF complexes: $\text{Hf}(\text{mpp})_4$, $\text{Hf}(\text{acac})_4$


25 Marked features are a high C content and low growth rates. Examples are Hf alkoxides: $\text{Hf}(\text{OR})_4$ $\text{R} = \text{CH}_3, \text{C}_2\text{H}_5$, (iso-) C_3H_7 , (tert-) C_4H_9 . A reaction is effected with H_2O , O_3 , O radicals and O_2 . The Hf complexes can be used as MOCVD precursors and partially as ALCVD precursors.
30 Problems arise through their properties as solids having low volatility (except for $\text{Hf}(\text{tert-C}_4\text{H}_9)_4$; however, there is the problem of poor film quality here; $\text{Hf}(\text{tert-C}_4\text{H}_9)_4$ can therefore be used only as an MOCVD precursor).

35

The following specific examples may be mentioned as known hafnium precursors:

HF alkoxides:

Hafnium methoxide $\text{Hf}(\text{OMe})_4$




Molecular Weight = 302.63

Molecular Formula = $\text{C}_4\text{H}_{12}\text{HfO}_4$

Molecular Composition = C 15.88% H 4.00% Hf 58.98% O 21.15%

- 5 Properties: white solid at room temperature;
melting point 50°C ;
remarks: highest Hf content of all alkoxides.

10 Hafnium ethoxide: $\text{Hf}(\text{OEt})_4$



Molecular Weight = 358.74


Molecular Formula = $\text{C}_8\text{H}_{20}\text{HfO}_4$

Molecular Composition = C 26.79% H 5.62% Hf 49.76% O 17.84%

CAS Reg. No. 13428-80-3

Properties: white solid at room temperature

Hafnium n-propoxide: $\text{Hf}(\text{n-Pr})_4$



Molecular Weight = 414.84

Molecular Formula = $\text{C}_{12}\text{H}_{28}\text{HfO}_4$

Molecular Composition = C 34.74% H 6.80% Hf 43.03% O 15.43%

CAS Reg. No. 25491-66-1

5 Properties: white solid at room temperature; $\Delta H_{\text{sub } 0} = 83.7 \pm 8.4 \text{ kJ/mol}$ (Lappert, M.F. et al.; J. Chem. Soc. Chem. Commun., 830 (1975))

Problem: low thermal stability

10


Hafnium tert-butoxide: $\text{Hf}(\text{t-Bu})_4$

CAS Reg. No. 2172-02-3

Properties: liquid at room temperature; vapor pressure 2 mmHg at 75°C ;

15

remarks: thermally unstable (cf. decomposition route); high volatility owing to steric hindrance by bulky tert-butoxide groups




Molecular Weight = 470.95


Molecular Formula = $\text{C}_{16}\text{H}_{36}\text{HfO}_4$

Molecular Composition = C 40.81% H 7.70% Hf 37.90% O 13.59%

thermal decomposition



Hafnium 1-methoxy-2-methyl-2-propanolate: $\text{Hf}(\text{mmp})_4$



Molecular Weight = 591.06

Molecular Formula = $\text{C}_{20}\text{H}_{44}\text{HfO}_8$

Molecular Composition = C 40.64% H 7.50% Hf 30.20% O 21.66%

5

CAS Reg. No. 309915-48-8

Properties: liquid at room temperature (melting point 15°C); vapor pressure 0.1 mmHg at 100°C; 7.6 mmHg at 135°C


Remarks: low growth rate owing to bulky ligands.

5

Hf alkylamides

Tetrakis(dimethylamino)hafnium: TDMAH $\text{Hf}(\text{NMe}_2)_4$

10



Molecular Weight = 354.80

Molecular Formula = $\text{C}_8\text{H}_{24}\text{HfN}_4$


Molecular Composition = C 27.08% H 6.82% Hf 50.31% N 15.79%

CAS Reg. No. 19782-68-4, 19962-11-9

Properties: solid at room temperature; melting point 26-29°C; vapor pressure 0.1 mmHg at 48°C; thermal decomposition > 90°C

15

Tetrakis(ethylmethylamino)hafnium: TEMAH $\text{Hf}(\text{NEtMe})_4$



Molecular Weight = 410.91

Molecular Formula = $\text{C}_{12}\text{H}_{32}\text{HfN}_4$


Molecular Composition = C 35.08% H 7.85% Hf 43.44% N 13.63%

CAS Reg. No. 352535-01-4

Properties: liquid at room temperature; vapor pressure
0.1 mmHg at 79°C

5

Tetrakis(diethylamino)hafnium TDEAH: $\text{Hf}(\text{NEt}_2)_4$



Molecular Weight = 467.01

Molecular Formula = $\text{C}_{16}\text{H}_{40}\text{HfN}_4$

Molecular Composition = C 41.15% H 8.63% Hf 38.22% N 12.00%

CAS Reg. No. 19824-55-6, 19962-12-0

10 Properties: vapor pressure 0.01 mmHg at 130°C; 0.1 mmHg
at 96°C

Remarks: low vapor pressure

15 Hafnium hydroxylamine: $\text{Hf}(\text{ONR}_2)_4$ R = Me, Et

Remarks: Poor film morphology, narrow ALD temperature
range at 300°C.

20

Process for the production of HfO_2 layers

In principle, various processes for the deposition of
hafnium oxide or hafnium oxynitride layers are known in
25 the prior art. These can be divided into ALCVD and CVD
processes.

The CVD process (chemical vapor deposition = CVD) is the chemical conversion of a reaction gas consisting of one or more volatile compounds into a solid substance and volatile byproducts. For deposition of the layer, the reaction gas is passed over the substrate to be coated.

Usually, processes for chemical gas-phase deposition are categorized according to the operating gas pressure, the determining activation method and deposition temperature and reactor wall temperature. A distinction is made here between atmospheric pressure CVD (APCVD = atmospheric pressure CVD), low pressure CVD (LPCVD = low pressure CVD) and plasma CVD (PCVD or PECVD = plasma enhanced CVD).

When organometallic compounds are used, the MOCVD (metal organic CVD or organometallic CVD) variant is referred to. Finally, so-called RPE-ALCVD or RPE-MOCVD can also be used (remote plasma enhanced CVD process). These processes are described below:

RPE-MOCVD (remote plasma enhanced metal organic CVD):
RPE-ALCVD (remote plasma enhanced atomic layer CVD):
The thermal decomposition of the organometallic compound is promoted by the introduction of excited and ionized gases into the reactor. The excitation of the gases is effected in an external plasma chamber (remote plasma) and the gases are then introduced into the reactor, the gases being present as neutral species (so-called radicals) or still partly as ions.

Radicals (e.g. O, N, H) can be passed in simultaneously with the layer deposition (RPE-MOCVD, or preferably sequentially in RPE-ALCVD). The precursor feed is interrupted at certain time intervals and the layer already deposited is treated with radicals. As a

result, the following improvements of the layer are achieved:

- achievement of exact stoichiometries (e.g. incorporation of O into oxide layers)
- 5 - removal of organic residues - reduction of the C content
- incorporation of N into oxide layers (oxynitrides through N radicals)
- 10 - improved electrical properties (leakage current, dielectric strength, capacitance)

For a further explanation of deposition processes which can be used in the context of the present invention, reference may be made to several papers in the technical
15 literature, for example *Mikroelektronik-Technologie*, edited by Prof. Dr sc. techn. K. Schade, Verlag Technik GmbH, Berlin - Munich, 1991, and *Nanoelectronics and Information Technology*, Reiner Waser (editor), Wiley-VCH, Weinheim, 2003.

20 General problems with the use of these technologies occur in the provision of sufficient amounts of precursors, in particular for batch reactors; otherwise, a diffusion-controlled CVD with poor uniformity or
25 extremely long cycle times (e.g. in the case of ALCVD) is effected.

It is therefore the object of the present invention to overcome the problems occurring in the case of the
30 hafnium oxide precursors of the prior art, for example formation of residues and the high cost factor and the frequently occurring poor edge covering on difficult topography. It is also the object of the present invention to provide precursors for the hafnium oxide
35 or hafnium oxynitride deposition which can be used in a sufficient amount and also concentration for batch reactors. It was furthermore the object of the present invention to provide precursors for the abovementioned

purpose which can be used for a very wide range of deposition methods with sufficiently high deposition rates.

- 5 These objects are achieved by the subject of the independent claims. Preferred embodiments are described in the dependent claims.

10 The abovementioned problems are solved by using a solution of one or more hafnium alkoxides or zirconium alkoxides as a precursor for hafnium oxide and hafnium oxynitride layers or zirconium oxide and zirconium oxynitride layers. It has surprisingly been found that, by using a solution instead of the undiluted starting material, the problems occurring in the prior art and relating to poor volatility arising through complex formation (see above) can be overcome.

20 The present invention relates to the preparation of economical, highly concentrated solutions of short-chain Hf alkoxides or zirconium alkoxides, which are usually present as a solid, and the use of these solutions as economical precursors for the production of hafnium or zirconium oxide or oxynitride layers with the aid of, preferably, MOCVD and/or ALCVD processes for the mass production of integrated circuits.

25 The precursor costs of these dissolved Hf alkoxides are only about 10% compared with the Hf alkylamides currently preferred in the prior art.

30 In a first aspect, the present invention relates to the use of a solution of one or more hafnium alkoxides as a precursor for hafnium oxide and hafnium oxynitride layers.

According to the invention, it is also possible to use a further element of group IVb, namely zirconium,

instead of hafnium. Zirconium has properties similar to those of hafnium, although it is somewhat less advantageous in some respects (higher leakage currents).

5 The present invention therefore also relates to the use of a solution of one or more zirconium alkoxides as a precursor for zirconium oxide and zirconium oxynitride layers. All embodiments carried out above and below with regard to hafnium therefore also apply correspondingly to zirconium.
10

According to a preferred embodiment, the solution according to the invention is highly concentrated. In particular, the use of a 30-90% strength by weight
15 solution of one or more hafnium alkoxides as a precursor for hafnium oxide and hafnium oxynitride layers is suitable. A preferred range is 50-80% by weight of hafnium alkoxide in solution. For example, a ratio of hafnium alkoxide : solvent of 2-3 : 1 is suitable.
20

These ranges have arisen for the following reasons: at a concentration above 90%, the solutions are difficult to process owing to the excessively high viscosity. Below a concentration of 30%, on the other hand, there
25 is a clear tendency to form inhomogeneities (cf. figs 1 and 2). For most producers, inhomogeneities of < 5% are tolerable in practice, so that a concentration above 50% is to be particularly preferred.

30 For example, fig. 1 shows that the inhomogeneities are below the critical limit of 5% from a concentration of about > 50%. Fig. 2 shows that this critical limit is not reached even from a range of a concentration of about 30%.

35 In all cases, the deposition rate of the solutions according to the invention increases with increasing concentration.

According to a further embodiment, the solutions defined above are used for the production of hafnium oxide and hafnium oxynitride layers by CVD or ALD processes. The deposition of the hafnium oxide or hafnium oxynitride layer on capacitors or transistors or as an optical layer on laser mirrors is particularly suitable here. Owing to its high refractive index, the hafnium oxide layer can be used as an optical layer of laser mirrors (the refractive index of hafnium oxide is about 2.1).

According to the invention, hafnium methoxide, hafnium n-propoxide, hafnium isopropoxide and/or hafnium ethoxide are preferably used as hafnium alkoxides. Among these, hafnium methoxide and hafnium ethoxide in a range of 30-90% by weight are particularly preferred. Relatively high growth rates in the ALCVD process are achieved in particular by small ligands (methoxide, ethoxide).

According to the invention, suitable zirconium alkoxides are consequently zirconium methoxide, zirconium ethoxide, etc.

The solvent for the preparation of the solution according to the invention preferably has a polar group.

Solvents having a polar group or free electron pairs which, by coordination to the hafnium (or zirconium), increase its coordination number to 6 (e.g. $\text{Hf}(\text{OR})_4 \cdot 2 \text{ROH}$; $\text{R}=\text{Me}, \text{Et}, \text{etc.}$) and thus break coordinate bonds between a plurality of hafnium alkoxide molecules (oligomerization) are particularly preferred. The complexing of the hafnium by solvent molecules also explains the very good solubility.

For example, the preferred solution of $\text{Hf}(\text{OEt})_4$ in EtOH with 80% by weight is $\text{Hf}(\text{OEt})_4 \cdot 2 \text{ EtOH}$.

Preferred classes of substances are: alcohols, amines,
5 ethers or esters.

According to the invention, it has proven particularly advantageous to use an alcoholic solvent as the solvent. An alcoholic solvent preferably comprises one
10 or more straight-chain or branched C_2 - C_8 -alcohols, e.g. ethanol, propanol, butanol, isopropyl alcohol, etc. As discussed above, the alcohol may be straight-chain or branched and may be formed from a primary, secondary or tertiary alcohol.

15 According to the invention, the alcoholic solvent can furthermore also be used in combination with a cosolvent. Suitable cosolvents are all customary substances, but in particular high-boiling solvents.
20 The advantageous high-boiling (b.p. 100-250°C) cosolvent optionally serves for further dilution of the solution. This may be necessary, inter alia, in order to prevent condensation of the precursor in the injection apparatus.

25 In principle, all classes of solvents (see above) are suitable. Relatively long-chain alcohols are suitable only if no exchange with the alcoholates bonded to the Hf occurs.

30 The solvent which is most advantageous in the present invention comprises or consists of EtOH. In particular, a solution containing hafnium ethoxide has given the best results here.

35 According to a second aspect, the present invention provides a process for the production of a hafnium or

zirconium oxide layer on an article to be coated, which comprises the following steps:

- a) provision of a solution as defined above and of an article to be coated;
- 5 b) introduction of the solution into a reactor and vaporization of the solution in the reactor, or
- c) vaporization of the solution and introduction of the vapor into a reactor; and
- d) deposition of the vapor on the article for the
10 formation of a hafnium or zirconium oxide layer.

Regarding the introduction of the solution, reference is made to the publication: "Developments in CVD Delivery Systems: A Chemist's Perspective on the
15 Chemical and Physical Interactions Between Precursors" by Paul O'Brien et al., Chem. Vap. Deposition 2002, 8, No. 6, in its entirety.

According to an embodiment, step c) is effected by
20 liquid injection into the heated antechamber of the reactor, by pulsed liquid injection or aerosol vaporization.

Deposition processes which may be used are all
25 deposition processes which are known and can be used in the prior art. The MOCVD, RPE-MOCVD, ALCVD or RPE-ALCVD process is preferably used.

According to a further embodiment, the hafnium oxide
30 layer can be further reacted by nitriding by means of a nitrogen-containing gas for the production of a hafnium oxynitride layer. N_2 , NH_3 , N_2O or mixtures thereof are preferably used as nitrogen-containing gases.

35 The inventors have found that NH_3 as a nitrogen-containing gas or coprecursor gives the best results. It is therefore most preferred.

A further improvement in the electrical properties of the layers can be achieved by sequential ozone or remote plasma treatment in the MOCVD and ALD mode by so-called RPE-MOCVD and RPE-ALD processes. By burning
5 out the carbon by means of ozone or oxygen radicals and by incorporation of nitrogen by means of nitrogen radicals, the thermal and chemical properties of the layer are improved.

10 The hafnium oxide layer produced by the process according to the invention is therefore optionally aftertreated with ozone or oxygen radicals.

Furthermore, the hafnium oxides or oxynitrides deposited
15 according to the invention preferably by MOCVD, RPE-MOCVD, ALCVD or RPE-ALCVD from dissolved alkoxides can be used for the preparation of hafnium silicon oxide or hafnium silicon oxynitride by sequential deposition with the silicon alkoxide TEOS.

20

In addition, mixed oxides or oxynitrides, such as, for example, hafnium-aluminum, hafnium-tantalum, hafnium-titanium, hafnium-lanthanum, etc., or even ternary mixed hafnium oxides, such as, for example, hafnium
25 aluminum tantalum, can be produced by sequential deposition with other precursors.

As already discussed above, for example, an MOS transistor, a capacitor or a laser mirror can be coated
30 by the process according to the invention.

According to a third aspect, the present invention provides a hafnium alkoxide solution which contains 30-90% by weight of one or more hafnium alkoxides, the
35 hafnium alkoxide being selected from hafnium methoxide, hafnium n-propoxide, hafnium isopropoxide and/or hafnium ethoxide.

According to a preferred embodiment, the hafnium alkoxide solution is a 30-90% strength by weight solution of hafnium ethoxide in ethanol.

- 5 The present invention is now described with reference to embodiments and figures.

The figures show the following:

- 10 Figure 1: deposition of hafnium oxide in the CVD mode in an A400 reactor from ASM. A sufficient homogeneity over the wafers is achieved only at high concentration of Hf ethoxide in ethanol. The deposition rate shows a linear dependence on the concentration.

15

- Figure 2: deposition of hafnium oxide in the ALD mode in an A400 reactor from ASM. A sufficient homogeneity over the wafers is achieved in the ALD mode too only at high concentration of Hf ethoxide in ethanol. The
20 deposition rate shows less dependence on the Hf ethoxide concentration in ethanol.

Embodiments:

- 25 1.1. MOCVD or RPE-MOCVD of hafnium oxide or oxynitride

1.1.1 Hafnium oxide

Precursor: $\text{Hf}(\text{OC}_2\text{H}_5)_4$ dissolved in $\text{C}_2\text{H}_5\text{OH}$

- 30 Process temperature: 250 - 450°C

Pressure: 5 - 200 Pa

Deposition rate: 0.1 - 5 nm/min

35

Deposition of HfO_2 in the CVD mode in an A400 reactor from ASM with 125 wafers in the boat. Wafer diameter 200 mm.

Process temperature: 390°C
Pressure: 35 Pa
Deposition rate: cf. figure 1
5 Precursor: Hf ethoxide dissolved in ethanol
Gas flow: 1 slm nitrogen as carrier gas
Precursor flow: 0.75 g/min

Figure 1 shows in this context the deposition of
10 hafnium oxide in the CVD mode in an A400 reactor from
ASM. A sufficient homogeneity over the wafers is
achieved only at high concentration of Hf ethoxide in
ethanol. The deposition rate shows a linear dependence
on the concentration.

15

1.1.2 Hafnium oxynitride

Precursor: $\text{Hf}(\text{OC}_2\text{H}_5)_4$ dissolved in $\text{C}_2\text{H}_5\text{OH}$
Coprecursor: ammonia

20 Process temperature: 250 - 450°C

Pressure: 5 - 200 Pa

Deposition rate: 0.1 - 5 nm/min

25

1.2. Sequential aftertreatment by oxidation or nitriding of the layer

Oxidation by ozone or oxygen radicals from remote
30 plasma

Process temperature: 250 - 450°C

Ozone concentration: 10% by volume in oxygen

35

Oxygen radicals from remote plasma:

Gases: oxygen, nitrous oxide

Pressure: 5 - 200 Pa

Microwave power: 2 - 6 kW

5

By sequential oxidation with ozone or oxygen radicals at intervals of 3 nm at a temperature of 390°C, it was possible to reduce the leakage current at a field strength of 2 MV/cm from $5 \cdot 10^{-7}$ to $1 \cdot 10^{-8}$ cm².

10

Nitriding by nitrogen radicals from remote plasma:

Gases: nitrogen, ammonia

15 Microwave power: 2 - 6 kW

By sequential nitriding with nitrogen radicals at intervals of 3 nm at a temperature of 390°C, it was possible to reduce the leakage current at a field strength of 2 MV/cm from $5 \cdot 10^{-7}$ to $5 \cdot 10^{-9}$ cm².

20

2. ALD or RPE-ALD of hafnium oxide or oxynitride

2.1 Hafnium oxide

25 First precursor: $\text{Hf}(\text{OC}_2\text{H}_5)_4$ dissolved in $\text{C}_2\text{H}_5\text{OH}$

Process temperature: 200 - 400°C

Pressure: 5 - 200 Pa

30

Deposition rate: 0.05 - 0.5 nm/min

Second precursor: H_2O , ozone, oxygen radicals

35 2.2 Hafnium oxynitride

First precursor: $\text{Hf}(\text{OC}_2\text{H}_5)_4$ dissolved in $\text{C}_2\text{H}_5\text{OH}$

Coprecursor: ammonia

Process temperature: 200 - 400°C

Pressure: 5 - 200 Pa

5 Deposition rate: 0.05 - 0.5 nm/min

Second precursor: H₂O, ozone, ammonia, oxygen radicals, nitrogen radicals, mixtures of nitrogen, ammonia and oxygen in the excited state

10

Microwave power: 2 - 6 kW

Deposition of HfO₂ in the ALD mode in an A400 reactor from ASM with 125 wafers in the boat. Wafer diameter
15 200 mm.

Process temperature: 240°C

Pressure: 50 Pa

Deposition rate: cf. figure 2

20 Precursor: Hf ethoxide dissolved in ethanol

Gas flow: 1.5 slm nitrogen as carrier gas

Precursor flow: 0.75 g/min

Figure 2 shows the relevant deposition of hafnium oxide
25 in the ALD mode in an A400 reactor from ASM. A sufficient homogeneity over the wafers is achieved in the ALD mode too only at high concentration of Hf ethoxide in ethanol. The deposition rate shows only a slight dependence on the Hf ethoxide concentration in
30 ethanol.

On deposition in the RPE-ALD mode it is possible to reduce the leakage current at a field strength of 2 MV/cm from 8 10E-8 to 3 10E-9/cm² by using nitrogen
35 radicals as the second precursor at a deposition temperature of 240°C.

The deposition of the layers was effected both on single wafer lines and on batch lines having a loading up to 160 product wafers.

- 5 The hafnium oxide or oxynitride layer deposited by MOCVD or RPE-MOCVD and ALCVD or RPE-ALCVD are distinguished by very good edge covering on difficult topographies with aspect ratios of 50 (depth/height of a structure) in combination with very good electrical
- 10 properties, low contamination level of carbon or chlorine and low precursor costs compared with all other hafnium precursors.

Claims:

1. The use of a solution of one or more hafnium alkoxides or zirconium alkoxides as a precursor for
5 hafnium oxide and hafnium oxynitride layers or for zirconium oxide and zirconium oxynitride layers, a 30-90% strength by weight solution of one or more hafnium alkoxides being used as precursor for hafnium oxide and hafnium oxynitride layers or a 30-90% strength by
10 weight solution of one or more zirconium alkoxides being used as a precursor for zirconium oxide and zirconium oxynitride layers,
the hafnium oxide and hafnium oxynitride layers being produced by CVD or ALD processes, and
15 a solvent being one or more selected from the group consisting of alcohols, amines, ethers and esters.
2. The use as claimed in claim 1, a 50-80% strength
20 by weight solution being used.
3. The use as claimed in one or more of the preceding claims, the hafnium oxide or hafnium oxynitride layer
25 being produced on capacitors or transistors or as an optical layer on laser mirrors.
4. The use as claimed in one or more of the preceding claims, the hafnium alkoxides used being hafnium meth-
30 oxide, hafnium n-propoxide, hafnium isopropoxide and/or hafnium ethoxide.
5. The use as claimed in one or more of the preceding claims, the solution comprising 30-90% of hafnium meth-
35 oxide.

6. The use as claimed in one or more of claims 1-4, the solution comprising 30-90% by weight of hafnium ethoxide.
- 5 7. The use as claimed in one or more of the preceding claims, the solution comprising, in addition to hafnium alkoxide, a solvent having a polar group.
- 10 8. The use as claimed in claim 7, the solvent being an alcoholic solvent.
9. The use as claimed in claim 8, the solvent comprising one or more straight-chain or branched C₂-C₈-
15 alcohols.
10. The use as claimed in one or more of the preceding claims 8-9, the solvent comprising EtOH and/or the solution comprising hafnium ethoxide.
- 20 11. The use as claimed in one or more of the preceding claims, hafnium being replaced by zirconium in said compounds.
- 25 12. A process for the production of a hafnium oxide layer or zirconium oxide layer on an article to be coated, which comprises the following steps:
- a) provision of a solution as defined in one or more of claims 1-11 and of an article to be coated;
- 30 b) introduction of the solution into a reactor and vaporization of the solution in the reactor, or
- c) vaporization of the solution and introduction of the vapor into a reactor;
- d) deposition of the vapor on the article for the
35 formation of a hafnium oxide layer or zirconium oxide layer.

13. The process as claimed in claim 12, step c) being effected by liquid injection into the heated antechamber of the reactor, by pulsed liquid injection or aerosol vaporization.

5

14. The process as claimed in claim 12 or 13, the deposition process used being the MOCVD, RPE-MOCVD, ALCVD or RPE-ALCVD process.

10

15. The process as claimed in one or more of claims 12-14, nitriding by means of a nitrogen-containing gas for the production of a hafnium oxynitride layer additionally being effected.

15

16. The process as claimed in claim 15, the gas used being N_2 , NH_3 , N_2O or a mixture thereof.

17. The process as claimed in one or more of the preceding claims, in which NH_3 is used as the nitrogen-containing gas or coprecursor.

20

18. The process as claimed in one or more of the preceding claims, hafnium being replaced by zirconium in said compounds.

25

19. The process as claimed in one or more of claims 13-18, the article being an MOS transistor, a capacitor or a laser mirror.