

1 0 MAR 2006

SPECIFICATION



166166

**DEVICE AND METHOD FOR MICROWAVE PLASMA PROCESSING,
AND MICROWAVE POWER SUPPLY DEVICE**

5

TECHNICAL FIELD

The present invention relates to plasma processing apparatuses and more particularly to a microwave plasma processing apparatus that generates plasma by a microwave and conducts plasma processing on a semiconductor wafer, and the like.

BACKGROUND ART

Plasma processing apparatuses are used in these days in the fabrication process of semiconductor devices, in view of increase of integration density and increased degree of device miniaturization, for film formation, etching, ashing, and the like. Particularly, a microwave plasma processing apparatus that induces plasma by using microwave has an advantage of generating stable plasma even in a high vacuum state of relatively low pressure, such as 0.1 - several 10mTorr. Because of this, a microwave plasma processing apparatus that uses a microwave such as 2.45GHz now draws attention.

In the microwave plasma-processing apparatus, there is provided a dielectric plate transparent to microwave on a ceiling part of a processing vessel, while the processing vessel is connected to a general evacuation system. Further, a flat, disk-like antenna member (microwave-emitting member) is provided on the dielectric plate.



G00002

10 MAR 2006

Further, a retardation plate is provided on the antenna member. The retardation plate is formed of a dielectric film having a predetermined dielectric constant and compresses the wavelength of the microwave supplied thereto from a microwave generator with a predetermined ratio. The antenna member is formed with a number of penetrating holes (slots) and the microwave supplied to the central part of the antenna member is introduced into the processing vessel through the slots after propagating inside the antenna member in the radial direction thereof. As a result of the compression of the wavelength of the microwave supplied to the antenna member by the retardation plate, the size of the slots formed in the antenna member is reduced, and as a result, the uniformity of plasma density is improved by providing a large number of slots on the antenna member.

In the microwave plasma processing apparatus of such a construction, the microwave introduced into the processing vessel from the antenna member via the dielectric plate induces plasma of a processing gas, and the semiconductor wafer disposed in the processing vessel is subjected to plasma processing.

The microwave introduced into the processing vessel via the retardation plate and the antenna member is supplied from a microwave generator such as a magnetron, or the like. The microwave generated by the microwave generator is supplied to the retardation plate or to the antenna member via a waveguide. The microwave thus guided through the waveguide is emitted as it is propagated through the

1 0 MAR 2006

antenna member in the radial direction thereof from the central part. Ultimately, the microwave is emitted uniformly into a process space inside the processing vessel.

5 A coaxial waveguide has been used generally for supplying the microwave to the central part of the retardation plate or the antenna member. Thus, the microwave generated by the microwave generator is supplied to a waveguide having a rectangular cross
10 section and is propagated therethrough to the part generally at the center of the retardation plate or the antenna member. There, the microwave is supplied into the central part of the retardation plate or the antenna member via the coaxial waveguide formed of an
15 inner conductor and an outer conductor.

 The coaxial waveguide that supplies the microwave to the central part of the retardation plate or the antenna member is formed for example of an inner conductor and an outer conductor, wherein
20 the inner conductor is formed of a thin tube having a diameter of about 17mm.

 Thus, in the case large electric power is to be supplied to the antenna member via the coaxial waveguide, there is induced a very strong electric
25 field in the vicinity of the inner conductor of the coaxial waveguide, and the temperature of the inner conductor is raised as a result of heating. There, a part of the microwave energy is converted to heat, while such conversion of microwave energy to heat
30 increases the loss (conductor loss) of the supplied microwave. Thereby, the efficiency of electric power feeding is deteriorated. Further, there arises the need of cooling the coaxial waveguide by covering the

10 MAR 2006

same by a cooling device, while such a construction increases the size and cost of the apparatus.

Further, because of the existence of very strong electric field in the vicinity of the inner conductor, there is a possibility that abnormal electric discharge may be caused in the vicinity of the inner conductor. When such abnormal electric discharge is caused, the retardation plate may be damaged in the part thereof near the inner conductor.

For example, there is a need of connecting the inner conductor of the coaxial waveguide to the antenna member in the state that the coaxial waveguide makes an intimate contact with the central part of the antenna member, and because of this, it is practiced to connect the inner conductor to the antenna member by screwing a screw into a threaded hole provided inside the inner conductor through the retardation plate in the state the end surface makes a contact with the antenna member. With such a connection that uses a screw, however, it is difficult to achieve complete and intimate contact of the inner conductor end surface to the surface of the antenna member. When there is a minute gap, on the other hand, there tends to occur abnormal electric discharge in such a part.

Further, in the screwed connection explained above, there exists a screw head at the junction part where the dielectric plate and the antenna member (slot antenna) are joined. Thus, there is a need of forming a depression in the dielectric plate at the central part thereof for accommodating therein the screw head projecting from the surface of the slot antenna. Thus, it is difficult to achieve an

10 MAR 2006

intimate connection between the retardation plate and the antenna member at the central part, and there arises the problem that abnormal electric discharge takes place in the vicinity of such a depression.

5 Further, there can be a case in which it is desired to confine a helium (He) gas between the antenna member or the retardation plate and the top plate formed of a dielectric material, for facilitating thermal conduction. In such a case,
10 there is provided a seal ring at the outer periphery of the inner conductor constituting the coaxial waveguide for achieving sealing with respect to the dielectric top plate. In such a case, however, there arises a problem in that the seal ring may be damaged
15 as a result of degradation caused by the exposure to the strong microwave.

 Thus, there is a proposal to provide a cavity resonator between the waveguide and the antenna member and introduce the microwave into the
20 processing vessel from the cavity resonator. The Patent 2569019 discloses the technology of providing such a cavity resonator in the waveguide for amplifying the microwave. In this technology, the microwave thus amplified is introduced into the
25 processing vessel through a number of slots formed on the bottom surface of the cavity resonator. Thus, the cavity resonator disclosed in this patent publication is formed with a number of slots on the entire bottom surface thereof so that there occurs emission of the
30 microwave from the entire bottom surface facing the processing vessel. Therefore, the foregoing prior art does not have the construction of causing radial propagation of the microwave from the central part

10 MAR 2006

when emitting the microwave into the processing space of the processing vessel. Further, it should be noted that the length of each slot is determined by the wavelength of the microwave. In the case of using the microwave of 2.45GHz, the slot desirably has the length of 60mm or more in correspondence to the half wavelength of the microwave. This means that the construction of the reference does not provide the desirable effect of the microwave propagated in the radial direction from the central part is emitted uniformly into the processing vessel from a number of minute slots. Thus, it is not possible to apply the microwave supplying mechanism (feeding mechanism) having a cavity resonator as is disclosed in the foregoing Patent 2569019 to the antenna member (slot antenna) that supplied the microwave uniformly to the processing vessel from a number of minute slots.

DISCLOSURE OF THE INVENTION

Accordingly, it is a general object of the present invention to provide a novel and useful microwave plasma processing apparatus and processing method wherein the foregoing problems are eliminated.

Another and more specific object of the present invention is to provide a microwave plasma processing apparatus and microwave plasma processing method as well as a microwave feeding mechanism wherein the microwave supplied from a microwave generator is supplied efficiently to an antenna member from a waveguide.

Another object of the present invention is to provide a microwave plasma processing apparatus for applying plasma processing on a substrate,

10 MAR 2006

characterized by:

a processing vessel accommodating therein a stage for supporting the substrate;

a microwave generator;

5 a waveguide connected to said microwave generator, said waveguide guiding a microwave generated by the microwave generator; and

a microwave emitting member emitting the microwave into a space in the processing vessel after
10 wavelength compression by a retardation plate,

the waveguide has a single microwave outlet opening in a location corresponding to a center of the microwave emitting member.

Another object of the present invention is
15 to provide a microwave plasma processing method for applying plasma processing on a substrate, comprising the steps of:

placing the substrate to be processed on a stage inside a processing vessel;

20 generating a microwave by a microwave generator;

guiding the microwave generated by the microwave generator by a waveguide connected to the microwave generator;

25 outputting the microwave supplied from the waveguide connected to the microwave generator, from a single microwave outlet opening;

emitting the microwave outputted from the waveguide connected to the microwave generator into a
30 space inside the processing vessel by a microwave-emitting member; and

applying plasma processing on the substrate by forming plasma by the emitted microwave.

10 MAR 2006

Another object of the present invention is to provide a microwave feeding apparatus for supplying a microwave to a processing chamber, comprising:

5 a waveguide connected to a microwave generator, the waveguide guiding a microwave generated by the microwave generator, the waveguide having a microwave outlet opening for outputting the microwave; and

10 a microwave-emitting member causing the microwave supplied to a central part thereof to propagate in a direction perpendicular to a direction in which the microwave is supplied, the microwave-emitting member introducing the microwave into the
15 processing chamber via a number of slots.

 According to the present invention, the microwave is supplied to the central part of the microwave-emitting member via the single microwave output opening provided in the waveguide, which is
20 connected to the microwave generator, and the microwave thus supplied is caused to propagate through the microwave-emitting member in the radial direction thereof from the central part. As a result, the microwave is emitted efficiently and uniformly
25 into the processing vessel from the number of slots formed in the microwave-emitting member, and there occurs uniform plasma formation. Thus, according to the present invention, it becomes possible to supply the microwave to the microwave-emitting member
30 without using a coaxial waveguide, and the problem of electric power loss caused in the coaxial waveguide by the inner conductor is eliminated. Thereby, the efficiency of power feeding is improved. Further, the

10 MAR 2006

number of the sites where there is caused
concentration of the microwave is reduced, and
occurrence of unnecessary electric discharge at the
feeding part is suppressed. As a result, it becomes
5 possible to supply a large electric power to the
microwave-emitting member. Further, the screw
connection part for connecting the inner conductor of
the coaxial waveguide is no longer used, and the
shape of the microwave emission part is simplified.
10 With this, it becomes possible to confine a heat
conducting gas such as helium, and the like, easily.

Further, by constructing a cavity resonator
by providing another waveguide between the waveguide
connected to the microwave generator and the
15 microwave-emitting member, reflection of the
microwave supplied to the cavity resonator is
prevented, and substantially the entirety of the
microwave energy is introduced into the microwave-
emitting member from the microwave outlet opening
20 formed in the foregoing another waveguide. As a
result, the risk of electric discharge at the
connection part, as in the case of feeding electric
power by a coaxial waveguide, is eliminated, and it
becomes possible to supply a large electric power
25 efficiently, without causing electric power loss by
heating.

BRIEF DESCRIPTION OF THE DRAWINGS

FIG.1 is a cross sectional diagram showing
30 the general construction of a microwave plasma
processing apparatus according to a first embodiment
of the present invention;

FIG.2 is an oblique view showing the cross

10 MAR 2006

section of a microwave feeding apparatus constituting a part of the microwave plasma processing apparatus of FIG.1 for introducing microwave into a processing vessel;

5 FIG.3 is a plan view showing an example of an antenna member shown in FIG.2;

 FIG.4 is a diagram showing the construction of a slot pair shown in FIG.3;

 FIG.5 is a diagram showing the propagation
10 mode of microwave in the microwave-emitting member;

 FIGS.6A - 6C are diagrams showing the propagation mode of microwave in a rectangular waveguide;

 FIG.7 is a diagram showing the magnetic
15 field caused by the microwave propagating in the rectangular waveguide;

 FIGS.8A and 8B are diagrams showing the result of calculation of optimum size for each of the rectangular waveguide and the microwave outlet
20 opening;

 FIG.9 is a graph showing the result of simulation of microwave reflectance at the microwave outlet opening;

 FIG.10 is a graph showing the electric
25 field strength of the microwave outlet opening in the circumferential direction thereof;

 FIG.11 is an oblique view showing the cross section of a microwave feeding apparatus of a microwave plasma processing apparatus according to a
30 second embodiment;

 FIG.12 is an oblique view showing the cross section of a microwave feeding apparatus of a microwave plasma processing apparatus according to a

third embodiment of the present invention;

FIGS.13A and 13B are diagrams explaining the propagation mode of the microwave in a circular waveguide;

5 FIGS.14A and 14B are diagrams showing the result of calculation of optimum size for various parts of the microwave feeding apparatus of FIG.12 for the case a circular waveguide is used for the cavity resonator; and

10 FIG.15 is a graph showing the electric field strength distribution at the microwave outlet opening of the third embodiment of the present invention in the circumferential direction.

15 BEST MODE FOR IMPLEMENTING THE INVENTION

Next, various mode of implementing the present invention will be explained with reference to the drawings.

20 (FIRST EMBODIMENT)

FIG.1 is a cross sectional view showing the general construction of a microwave plasma processing apparatus according to a first embodiment of the present invention.

25 As represented in FIG.1, the microwave plasma processing apparatus according to the first embodiment of the present invention is a plasma CVD apparatus 10 that applies plasma CVD processing on a semiconductor wafer W in a processing vessel 12. It
30 should be noted that the present invention is not limited to such a plasma processing apparatus but is applicable also to the apparatus that applies a plasma process such as plasma ashing, plasma etching,

1 0 MAR 2006

plasma oxidation or oxynitridation or nitridation.

The semiconductor wafer W to be processed is placed on a stage 14 inside the processing vessel 12, and a plasma processing gas is supplied to the processing vessel 12 from a gas source (not shown) via a supply tube 16. On the other hand, there is provided an evacuation port 12a at the bottom part of the processing vessel 12 in connection to a vacuum pump (not shown), and the pressure inside the processing vessel is maintained at a predetermined evacuated pressure.

Next, the construction of a microwave feeding apparatus used for introducing a microwave into the processing vessel 12 will be explained with reference to FIG.1 and also FIG.2.

FIG.2 is an oblique view showing the cross section of a microwave feeding apparatus 20 used in the plasma CVD apparatus 10 of FIG.1 for introducing the microwave into the processing vessel 12.

It should be noted that the ceiling part of the processing vessel 12 is opened, and a microwave emitting member 19, formed of an antenna member (slot plate) 17 functioning as the microwave-emitting member and a retardation plate 18, is mounted on the foregoing opening via a dielectric plate 15 in an air tight state. The retardation plate 18 is the member for compressing the wavelength of the microwave supplied to the antenna member 17 and is provided for reducing the length and also the interval of the slots formed on the antenna member 17.

Above the retardation plate 18, there is provided a rectangular waveguide (first waveguide) 22 having a rectangular cross section, and a microwave

10 MAR 2006

generator 24 such as a magnetron, or the like, is provided at an end of the rectangular waveguide 22. Thus, the microwave of 2.45GHz for example, generated by the microwave generator 24, is propagated through
5 the rectangular waveguide 22 and is supplied to the microwave-emitting member 19 from a microwave outlet opening 22a provided at the other end of the rectangular waveguide 22. In the present embodiment, it should be noted that the microwave outlet opening
10 22a is a circular opening provided in a wall 22b of the rectangular waveguide 22 constituting a longer edge in the cross section and is disposed at the central part of the antenna member 18 located underneath thereof.

15 FIG.3 is a plan view showing an example of the antenna member 17. The antenna member 17 of FIG.3 is formed with a number of slot pairs 30 formed of a slot 30A and a slot 30B. In the example illustrated in FIG.3, the slot pairs 30 are disposed along a
20 plurality of concentric circles, while it is possible that the slot pairs are arranged in a spiral pattern or non-concentric pattern.

FIG.4 shows the construction of a slot pair shown in FIG.3. Each of the slots 30A and 30B has an
25 elongated elliptical shape having a bulging central part, wherein the slot 30B is arranged such that the longitudinal direction thereof form a 90 degree angle with regard to the elongating direction of the slot 30A and the slots 30A and 30B are disposed in a T-
30 shaped form such that an end of the slot 30B is located close to the central part of the slot 30A. The line connecting the center of the slot 30B and the center O of the antenna member 17 forms an angle

10 MAR 2006

of 45 degrees with regard to the elongating direction of the slot 30B. Further, the distance LA from the center of the slot 30A to the center O of the antenna member 17 and the distance LB from the center of the slot 30B to the center of the antenna member 17 are determined such that a difference (LA-LB) is equal to one-quarter of the microwave wavelength λ compressed by the retardation plate 20 ($(LA-LB)=\lambda/4$).

In the case a microwave is caused to propagate through the antenna member 17 having the slot pairs 30 explained above in the radial direction from the central part, there is caused an electric field of circular polarization by the slot pairs 30 and the microwave is emitted efficiently into the process space inside the processing vessel 12 uniformly.

It should be noted that the slots forming the antenna member 17 are not limited to the one that forms the slot pairs. Further, each of the slots is not limited to have the elongated elliptical shape. For example, the slots may have a circular form, triangular form, square form, rectangular form, or any other polygonal form. It is desirable, however, to provide a rounded smooth corner, in the case the slots are formed in a polygonal shape, for avoiding occurrence of abnormal discharge caused by concentration of electric field.

As noted above, the microwave is propagated in TEM mode in the antenna member 17, in which the microwave propagates in the radial direction, wherein TEM mode has a concentric magnetic field distribution within a radial line as represented in FIG.5. Thus, it is preferable that the microwave supplied from the

10 MAR 2006

rectangular waveguide 22 to the antenna member 17 (retardation plate 18) has a magnetic field distribution close to the concentric distribution as much as possible.

5 Thus, in the present embodiment, various dimensions of the rectangular waveguide 22 are adjusted such that the microwave propagating through the rectangular waveguide has a magnetic field distribution as close to a circle as possible.

10 FIGS.6A - 6C are diagrams showing the propagation mode of the microwave in the rectangular waveguide 22. Here, it should be noted that FIG.6A shows the electric flux lines in the cross section perpendicular to the propagating direction of the
15 microwave in the rectangular waveguide 22, while FIG.6B shows the electric flux lines in the cross section parallel to the propagating direction of the microwave in the rectangular waveguide 22. Further, FIG.6C shows the magnetic lines occurring in the
20 plane perpendicular to the electric flux line. In the cross section of FIG.6A, it should be noted that the longer edge has a length a while the shorter edge has a length b .

 It should be noted that the propagation
25 mode of the microwave in the rectangular waveguide is TE₁₀ mode, in which the magnetic field formed in the region defined by the longer edge a in the cross section of the rectangular waveguide and $1/2$ of the wavelength λ_g inside the waveguide propagates in the
30 propagating direction (x direction) of the microwave. In order to modify the magnetic field distribution shown in FIG.6C to be close to the magnetic field distribution of FIG.5, it will be noted that

10 MAR 2006

formation of the magnetic field in a square region as shown in FIG.7 would be effective, by setting the length $\lambda_g/2$ to be equal to the longer edge a ($\lambda_g=2a$).

5 The wavelength λ_g inside the waveguide can be represented by

$$\lambda_g = \lambda / [1 - (\lambda/2a)^2]^{1/2}.$$

10 Thus, by substituting the relationship $\lambda_g=2a$, it becomes possible to obtain the optimum length of the longer edge a . For the case of the microwave of 2.45GHz wavelength, the optimum length of the edge a is calculated as $a=86.6\text{mm}$.

15 FIGS.8A and 8B are diagrams showing the result of calculation of various optimum values of the rectangular waveguide 22 and the microwave outlet opening 22a. Here, it is assumed that the longer edge a of the cross section of the waveguide 22 has the
20 length of 86.6mm as noted above, while the length of the shorter edge b is set to 40mm. Further, the diameter D of the microwave outlet opening 22a is set to 64mm.

 Further, it was assumed that the distance h
25 between the retardation plate 18 and the waveguide 22 is 6mm and a part of the retardation plate 18 projects into the microwave outlet opening 22a. The diameter of the retardation plate 18 is set to 180mm and the thickness is set to 4mm. Further, it should
30 be noted that the results shown below does not change even when the diameter of the retardation plate 18 is 180mm or more. Further, the dielectric constant ϵ_r of the retardation plate 18 is set to 10.1. Here, the

reflection of the microwave feed from the microwave outlet opening 22a is evaluated while changing the distance l from the center of the microwave outlet opening 22a and the edge of the rectangular waveguide 22.

FIG.9 shows the graph showing the result of simulation conducted on the reflectance of the microwave for the case the distance l is changed. From the graph of FIG.9, it can be seen that the reflectance becomes minimum in the case the distance l is 49mm when the microwave has the frequency of 2.45GHz.

As explained above, the reflectance of the feeding part becomes -20dB or less in the case the frequency of the microwave is set to 2.45GHz and various parts of the waveguide 22 are set such that the longer edge of the cross section is 86.6mm, the shorter edge b is 40mm, the diameter D of the microwave outlet opening 22a is 64mm and the thickness (length) h of the microwave outlet opening 22a is 6mm. In this case, the reflection of the microwave at the feeding part is suppressed to 1% or less, and efficient introduction of the microwave becomes possible from the rectangular waveguide 22 to the microwave emission part 19.

In the plasma CVD apparatus 10 of the construction noted above, the microwave generated by the microwave generator 24 propagates through the waveguide 22 and is introduced into the retardation plate 18 via the microwave outlet opening 22a. The microwave thus introduced to the central part of the retardation plate 18 propagates in the radial direction while experiencing wavelength compression

1 0 MAR 2006

and is emitted into the process space inside the processing vessel 12 via the slot pairs 30 provided in the antenna member 17 with a large number. Thereby, uniform plasma is formed in the process space and a
5 uniform plasma processing is conducted on the semiconductor wafer W.

As noted heretofore, the plasma CVD apparatus 10 of the present embodiment can feed a large electric power to the microwave-emitting member
10 19 directly from the rectangular waveguide 22 via the microwave outlet opening 22a, without using a coaxial waveguide. In such a construction, there occurs no microwave loss (conductor loss) caused by the inner conductor of the coaxial waveguide, and deterioration
15 of efficiency of electric power feeding does not take place. Thereby, it becomes possible to reduce the manufacturing cost of the apparatus without increasing the size of the apparatus.

Further, because of the elimination of the
20 inner conductor of the coaxial waveguide, the present invention can eliminate the abnormal electric discharge, which tends to take place in the vicinity of the inner conductor. Thus, the problem of damaging of the retardation plate caused by the shock of
25 abnormal electric discharge, which tends to occur when the microwave is supplied to the antenna member via the retardation plate, is prevented.

Further, because the screw connection used for connecting the inner conductor of the coaxial
30 waveguide is no longer necessary, it becomes possible to eliminate the gap formed between the inner conductor and the antenna member. Thereby, the problem of electric discharge, which takes place in

10 MAR 2006

such a gap, is successfully eliminated.

Further, in the case a conventional coaxial waveguide is used, it is no longer necessary in the screw connection approach explained above to form the
5 depression in the central part of the antenna member at the junction part of the retardation plate and the antenna member for accommodating the screw head. Thus, the retardation plate and the antenna member are intimately contacted for the entire part thereof, and
10 the problem of occurrence of abnormal electric discharge between the retardation plate and the antenna member is eliminated.

Further, there are cases in which it is desirable to confine a helium (He) gas between the
15 antenna member or the retardation plate and the top plate formed of a dielectric material for enhancing thermal conduction. In this case, it is no longer necessary to achieve sealing by providing a seal ring around the periphery of the inner conductor, and the
20 problem of deterioration of the seal ring by the microwave no longer occurs.

(SECOND EMBODIMENT)

Next, a second embodiment of the present
25 invention will be described. The microwave plasma processing apparatus according to the second embodiment of the present invention has a fundamental structure identical with that of the plasma CVD apparatus shown in FIG.1. Thus, only the microwave
30 feeding apparatus will be explained hereinafter.

First, explanation will be made on the symmetry of the microwave introduced into the microwave emitting member from the microwave feeding

10 MAR 2006

apparatus 20 of the plasma CVD apparatus according to the first embodiment will be explained.

In the microwave feeding apparatus 20, the microwave propagating from one side of the microwave outlet opening 22a undergoes a change of propagation direction at the microwave outlet opening 22a to the perpendicular direction and is emitted toward the retardation plate 18. Thereby, it should be noted that the electric field strength of the microwave becomes stronger in the microwave outlet opening 22a at the side of the propagating direction of the microwave as compared with the electric field strength at the opposite side, and there appears non-uniform distribution of the microwave power.

FIG.10 is a graph showing the electric field strength distribution at the microwave outlet opening 22a in the circumferential direction thereof, wherein the vertical axis represents the electric field strength while the horizontal axis represents the azimuth angle. In the graph of FIG.10, it should be noted that the edge part (incident side) of the microwave outlet opening 22a at the azimuth angle of 0.5π coincides with the microwave propagating direction and is located closest to the microwave generator 24. Further, the edge part (terminal side) of the microwave outlet opening 22a at the azimuth angle 1.5π coincides with the microwave propagating direction and is located farthest from the microwave generator 24. As can be seen from FIG.10, the electric field strength becomes larger at the incident side edge part of the microwave outlet opening 22a corresponding to the azimuth angle of 0.5π , while the electric field strength becomes smaller

at the terminal side edge part of the microwave outlet opening 22a corresponding to the azimuth angle of 1.5π .

When there is caused such deviation
5 (asymmetry) in the electric field strength at the microwave outlet opening 22a, there is also caused a similar deviation in the microwave propagating in the antenna member 17 in the radial direction. Thereby, the intensity of the microwave emitted into the
10 processing chamber becomes no longer uniform.

Thus, in the present embodiment, in order to eliminate such asymmetry of the microwave, the rectangular waveguide is formed in a symmetric shape with respect to the microwave outlet opening. Further,
15 the present embodiment supplies the microwave from both sides of the microwave outlet opening.

FIG.11 is an oblique view showing the cross section of the microwave feeding apparatus 40 of the plasma CVD apparatus according to the second
20 embodiment.

As represented in FIG.11, the rectangular waveguide 42 of the microwave feeding apparatus 40 is formed with a single microwave outlet opening 42a on a wall 42b thereof, and the microwave is supplied to
25 the microwave-emitting member 19 from the microwave outlet opening 42a. Thereby, it should be noted that the rectangular waveguide 42 extends in the both directions of the microwave outlet opening 42a and there is formed a symmetrical structure with respect
30 to the microwave outlet opening 42a.

In the microwave feeding apparatus 40 of such a construction, the microwave is supplied from both sides of the rectangular waveguide 42 and is

outputted from the microwave outlet opening 42a. Thus,
the microwave reaches the microwave outlet opening
42a from both sides of the microwave outlet opening
42a. Thereby, the phase of the microwave is
5 controlled such that the microwaves propagating from
both sides have the same phase at the microwave
outlet opening 42a. For example, it is possible to
supply the microwaves of the same phase to the
microwave outlet opening 42a from both lateral sides
10 by constructing the waveguide such that the microwave
emitted from the same microwave generator is divided
by a branched waveguide and reach the microwave
outlet opening 42a with symmetrical paths.

Thus, in FIG.11, the electric field
15 strength of the microwave propagated from the right
side at the incident side of the microwave outlet
opening 42a and the electric field strength of the
microwave propagated from the left side at the
terminal side of the microwave outlet opening 42a
20 cancel out with each other. Similarly, the electric
field strength of the microwave propagated from the
right side at the terminal side of the microwave
outlet opening 42a and the electric field strength of
the microwave propagated from the left side at the
25 incident side of the microwave outlet opening 42a
cancel out with each other. With this, the electric
field strength of the microwave emitted from the
microwave outlet opening 42a becomes uniform
irrespective of the azimuth angle, and it becomes
30 possible to emit a microwave of symmetric electric
field to the microwave-emitting member 19.

In the foregoing embodiment, the
rectangular waveguide 42 extends straight in right

1 0 MAR 2006

and left directions of the microwave outlet opening 42a. On the other hand, it is also possible to construct a cross-shaped rectangular waveguide in which the waveguide extends in four mutually perpendicular directions from the microwave outlet opening 42a. Further, it is possible to modify the microwave intensity distribution intentionally by supplying microwaves to the microwave outlet opening 42a from plural directions.

10 In the present embodiment, the asymmetry of the microwave electric field emitted from the microwave outlet opening is compensated for, by supplying the microwaves from plural directions to the microwave outlet opening. On the other hand, the deviation of the microwave is eliminated also in the construction in which the microwave is supplied only from one direction as in the case of the microwave feeding apparatus 20 of the first embodiment explained before, by modifying the shape of the microwave outlet opening from the circular shape to elliptical shape such as ellipse shape or oval shape.

(THIRD EMBODIMENT)

25 Next, a third embodiment of the present invention will be explained. The microwave plasma processing apparatus according to the third embodiment has a fundamental construction identical with that of the plasma CVD apparatus of FIG.1 except for the microwave feeding apparatus. Thus, only the microwave feeding apparatus will be explained hereinafter.

 In the foregoing second embodiment, the deviation of microwave intensity distribution is

10 MAR 2006

eliminated by supplying the microwave from right and left directions. In the present invention, on the other hand, a microwave substantially free from deviation of electric field distribution to the
5 microwave-emitting member, by providing a circular waveguide having a circular cross section between the rectangular waveguide connected to the microwave generator and the microwave emitting member.

FIG.12 is an oblique view showing the cross
10 section of a microwave feeding apparatus 50 of a microwave plasma processing apparatus according to a third embodiment of the present invention.

As represented in FIG.12, the microwave feeding apparatus 50 includes a circular waveguide 54
15 provided between the rectangular waveguide 52 and the microwave-emitting member 19. Further, there is provided a microwave outlet opening 52a on a wall 52 of the rectangular waveguide 52, and the microwave propagated through the rectangular waveguide 52
20 enters into the circular waveguide 54 through the microwave outlet opening 52a. The microwave thus introduced is emitted into the microwave-emitting member 19 from a microwave outlet opening 54a formed on a bottom part 54b of the circular waveguide. Thus,
25 in the present embodiment, the axial direction (propagating direction of the microwave) of the rectangular waveguide 52 is perpendicular to the axial direction (propagating direction of the microwave) of the circular waveguide 54.

30 Here, it should be noted that the microwave propagation mode in the circular waveguide is a TM01 mode in which the shape of the magnetic flux lines is similar to the one in the rectangular waveguide as

shown in FIGS.13A and 13B. Thus, in FIG.13A, the magnetic flux lines are concentric and close to the TEM mode, which is the microwave propagation mode in a circular waveguide. Thereby, it can be seen that
5 there is formed a uniform distribution in the circular cross section of the circular waveguide. Thus, by supplying a microwave from the circular waveguide 54 to the microwave-emitting member 19 via the circular microwave outlet opening 54a, it becomes
10 possible to supply the microwave with uniform electric field distribution, and it becomes possible to emit the microwave to the processing chamber uniformly from the microwave-emitting member 19.

Here, it should be noted that the circular
15 waveguide 54 functions as a cavity resonator by setting the length of the circular waveguide 54, in other words the distance from the outlet part of the microwave outlet opening 52a to the microwave outlet opening 54a, to be equal to $n/2$ times the microwave
20 wavelength λ_g in the waveguide. Considering the effect of the size of the plasma processing apparatus or propagation loss, it is preferable to set the distance from the outlet part of the microwave outlet opening 52a to the microwave outlet opening 54a to be
25 $1/2$ times the microwave wavelength λ_g in the waveguide. In this case, the reflection from the circular waveguide 54 is reduced, and efficient supplying of the microwave to the antenna member 19 becomes possible.

30 FIGS.14A and 14B are diagrams showing the result of calculation of optimum size for various parts of the microwave feeding apparatus 50 of FIG.12 for the case the circular waveguide 52 forms a cavity

1 0 MAR 2006

resonator, wherein it should be noted that FIG.14A shows the rectangular waveguide 52 in a plan view while FIG.14B shows the microwave feeding apparatus 50 in a side view.

5 In the present embodiment, the longer edge of the rectangular cross section of the rectangular waveguide 52 is set to 86.6mm similarly to the first embodiment noted before, while the size of the shorter edge is set to 25mm. Further, the diameter D0
10 of the microwave outlet opening 52a is set to 84mm. Further, the size of the retardation plate 18 is set similarly to the size of the retardation plate 18 of the first embodiment such that the retardation plate 18 has a thickness of 4mm and an outer size of 180mm.
15 It should be noted that the results shown below does not change even when the outer size is set to 180mm or more. Further, the size of the connection part between the circular waveguide 54 and the retardation plate 18 is set similarly to the case of the
20 connection part of the rectangular waveguide 22 and the retardation plate 18 in the first embodiment. Thus, the diameter D1 of the microwave outlet opening 54a of the circular waveguide 54 is set to 64mm and the height (length) h1 of the microwave outlet
25 opening 54a is set to 6mm.

 From the calculation based on the foregoing dimensions, it became possible to achieve efficient microwave feeding with low reflectance for the case the diameter of the circular waveguide 54 is set to
30 150mm, the length of the circular waveguide is set to 78.4mm and the length l from the center of the microwave outlet opening 52a of the rectangular waveguide 52 is set to 57mm.

1 0 MAR 2006

FIG.15 is a graph showing the result of calculation of the microwave electric field distribution for the case the various parts of the microwave feeding apparatus are set to the foregoing
5 dimensions.

From the graph of FIG.15, it can be seen that the microwave electric field strength is generally uniform in all the azimuth directions.

Thus, according to the microwave feeding
10 apparatus of the present invention, it becomes possible to supply a microwave of uniform electric field strength to the microwave-emitting member 19, and as a result, a microwave of uniform intensity is emitted into the processing vessel 12. With this, a
15 uniform plasma processing becomes possible over the entire surface of the wafer W in the processing vessel, and a high-quality plasma processing is achieved.

Further, because the use of coaxial
20 waveguide is eliminated at the time of supplying the microwave to the microwave-emitting member 19, it becomes possible to achieve efficient microwave supplying with small electric power loss, similarly to the first and second embodiments.

25 It should be noted that there is provided a compartment plate 56 inside the rectangular waveguide 52 shown in FIG.12. It should be noted that this compartment plate 56 is provided for reflecting back the reflection wave returned from the microwave
30 outlet opening 52a again to the microwave outlet opening 52a.

Further, it is possible to use any known converter or construction for introducing a microwave

10 MAR 2006

from the rectangular waveguide to the circular waveguide, and the present invention is not limited to those embodiments explained above.

5 INDUSTRIAL APPLICABILITY

Thus, according to the present invention, it becomes possible to supply a microwave to a microwave-emitting member without using a coaxial waveguide. Thus, the problem of electric power loss
10 caused by the inner conductor of a coaxial waveguide is eliminated and the efficiency of electric power feeding is improved. Further, the number of locations that tend to invite concentration of microwave is reduced, and unwanted electric discharge in the power
15 feeding part is reduced. Thereby, it becomes possible to supply a large electric power to the microwave-emitting member. Further, the screw connection part for connecting the inner conductor of a coaxial waveguide is no longer used. Thereby, the shape of
20 the microwave-emitting member is simplified, and manufacturing thereof is facilitated. Further, as a result of simplification of shape of the microwave-emitting member, it becomes possible to provide a construction that confines helium conducting gas
25 easily.

10 MAR 2006

CLAIMS

5

1. A microwave plasma processing apparatus
for applying plasma processing to a substrate,
characterized by:

10 a processing vessel accommodating therein a
stage for supporting said substrate;

a microwave generator;

a waveguide connected to said microwave
generator, said waveguide guiding a microwave
generated by said microwave generator; and

15 a microwave emitting member emitting said
microwave into a space in said processing vessel
after wavelength compression by a retardation plate,

said waveguide has a single microwave
outlet opening in a location corresponding to a
20 center of said microwave emitting member.

25 2. A microwave plasma processing apparatus
as claimed in claim 1, characterized in that said
waveguide is a rectangular waveguide having a
rectangular cross section.

30

3. A microwave plasma processing apparatus

1 0 MAR 2006

as claimed in claim 2, characterized in that said rectangular waveguide has a cross section such that a longer edge of said cross section has a length of $1/2$ a wavelength of said microwave in said rectangular
5 waveguide.

10 4. A microwave plasma processing apparatus as claimed in claim 2, characterized in that said microwave outlet opening of said rectangular waveguide is provided on a surface corresponding to a longer edge in a cross section of said rectangular
15 waveguide.

20 5. A microwave plasma processing apparatus as claimed in claim 1, characterized in that said waveguide extends in plural directions about said microwave outlet opening.

25

6. A microwave plasma processing apparatus as claimed in claim 5, characterized in that said
30 waveguides have a straight shape are arranged symmetrically about said microwave outlet opening.

1 0 MAR 2006

7. A microwave plasma processing apparatus
as claimed in claim 1, characterized further by
another waveguide provided between said waveguide and
said microwave emitting member with an axial
5 direction perpendicular to an axial direction of said
waveguide connected to said microwave generator,
said microwave is supplied from said
waveguide connected to said microwave generator to
said another waveguide via said microwave outlet
10 opening, said microwave being introduced into said
microwave emitting member via another single
microwave outlet opening provided on a bottom part of
said another waveguide.

15

8. A microwave plasma processing apparatus
as claimed in claim 7, characterized in that said
20 another waveguide is a circular waveguide having a
circular cross section.

25

9. A microwave plasma processing apparatus
as claimed in claim 8, characterized in that said
circular waveguide has a length equal to $n/2$ times (n
being an integer) a wavelength of said microwave in
30 said waveguide connected to said microwave generator,
said circular waveguide forming a cylindrical cavity
resonator.

10. A microwave plasma processing apparatus
as claimed in claim 1, characterized in that said
microwave emitting member includes said retardation
plate.

5

11. A microwave plasma processing apparatus
10 as claimed in claim 1, characterized in that said
microwave emitting member includes a number of slots
penetrating therethrough in a thickness direction.

15

12. A microwave plasma processing apparatus
as claimed in claim 11, characterized in that said
slots of said microwave emitting member are arranged
20 in a spiral form or multiple circumferential form.

25 13. A microwave plasma processing apparatus
as claimed in claim 12, characterized in that said
slots of said microwave emitting member form slot
pairs each formed of two slots arranged to in a T-
shaped form.

30

1 0 MAR 2006

14. A plasma processing method for applying plasma processing on a substrate, characterized by the steps of:

placing a substrate on a stage in a
5 processing vessel;
generating a microwave by a microwave generator;
guiding said microwave generated by said microwave generator by a waveguide connected to said
10 microwave generator;
outputting said microwave supplied from said waveguide connected to said microwave generator, via a single microwave outlet opening;
emitting said microwave outputted from said
15 waveguide connected to said microwave generator into a space in said processing vessel by a microwave emitting member; and
applying a plasma processing on said substrate by forming plasma by said emitted microwave,
20 wherein said waveguide connected to said microwave generator extends in plural directions about said microwave outlet opening, and wherein said microwave is guided to said microwave outlet opening from said plural directions with an identical phase.

25

30

10 MAR 2006

15 . A microwave plasma processing method as
claimed in claim 14, characterized in that said
waveguide connected to said microwave generator has a
straight shape, and wherein said waveguide connected
5 to said microwave generator supplies said microwave
to said microwave outlet opening from both sides of
said microwave outlet opening with an identical same
phase.

10

16 . A microwave plasma processing method as
claimed in claim 14, characterized in that another
15 waveguide is provided between said waveguide
connected to said microwave generator and said
microwave emitting member with an axial direction
perpendicular to an axial direction of said waveguide
connected to said microwave generator,

20

wherein said microwave is supplied from
said waveguide connected to said microwave generator
to said another waveguide via said microwave outlet
opening, said microwave being introduced into said
microwave emitting member via another single
25 microwave outlet opening provided on a bottom part of
said another waveguide.

30

17 . A microwave plasma processing method as
claimed in claim 14, characterized in that said
another waveguide is used for a cavity resonator, and

10 MAR 2006

wherein entirety of said microwave supplied from said microwave outlet opening of said waveguide connected to said microwave generator is introduced into said microwave emitting member from said another microwave outlet opening.

10 18 . A microwave feeding apparatus for feeding a microwave into a processing chamber, characterized by:

a waveguide connected to a microwave generator, said waveguide guiding a microwave generated by said microwave generator, said waveguide having a microwave outlet opening for outputting said microwave; and

a microwave emitting member causing to propagate said microwave supplied at a central part thereof in a direction perpendicular to a direction in which said microwave is supplied, said microwave emitting member further introducing said microwave into said processing chamber via a plurality of slots.

25

19 . A microwave feeding apparatus as claimed in claim 18 , wherein said waveguide connected to said microwave generator is a rectangular waveguide having a rectangular cross section.

30

10 MAR 2006

20 . A microwave feeding apparatus as
claimed in claim 19, wherein said rectangular
waveguide has a cross section such that a longer edge
of said cross section has a length of $1/2$ of a
5 wavelength of said microwave in said rectangular
waveguide.

10

21 . A microwave feeding apparatus as
claimed in claim 19, characterized in that said
microwave outlet opening of said rectangular
waveguide is provided on a surface that forms a
15 longer edge in a cross section of said rectangular
waveguide.

20

22 . The microwave feeding apparatus as
claimed in claim 18, characterized in that said
waveguide connected to said microwave generator
extends in plural directions about said microwave
25 outlet opening.

30

23 . The microwave feeding apparatus as
claimed in claim 22, characterized in that said
waveguide connected to said microwave generator has a
straight shape and extends symmetrically with respect

10 MAR 2006

to said microwave outlet opening.

5

24 . The microwave feeding apparatus as claimed in claim 18, characterized in that another waveguide is provided between said waveguide connected to said microwave generator and said
10 microwave emitting member with an axial direction perpendicular to an axial direction of said waveguide connected to said microwave generator,

wherein said microwave is supplied from said waveguide connected to said microwave generator
15 to said another waveguide via said microwave outlet opening, said microwave being introduced into said microwave emitting member via another single microwave outlet opening provided on a bottom part of said another waveguide.

20

25 . A microwave feeding apparatus as
25 claimed in claim 24, characterized in that said another waveguide is a circular waveguide having a circular cross section.

30

26 . A microwave feeding apparatus as claimed in claim 25, characterized in that said

10 MAR 2006

circular waveguide has a length equal to $n/2$ times (n being an integer) a wavelength of said microwave in said waveguide connected to said microwave generator, said circular waveguide forming a cylindrical cavity
5 resonator.

10 27 . A microwave feeding apparatus as claimed in claim 18, characterized in that said microwave emitting member includes said retardation plate.

15 28 . A microwave feeding apparatus as claimed in claim 18, characterized in that said
20 microwave emitting member includes a number of slots penetrating therethrough in a thickness direction.

25 29 . A microwave feeding apparatus as claimed in claim 28, characterized in that said slots of said microwave emitting member are arranged in a spiral form or multiple circumferential form.

30

10 MAR 2006

30 . A microwave feeding apparatus as
claimed in claim 28, characterized in that said slots
of said microwave emitting member form slot pairs
each formed of two slots arranged to in a T-shaped
5 form.