

IMPLANTABLE MEDICAL DEVICE FOR MINIMALLY-INVASIVE INSERTION

5 CROSS-REFERENCE TO RELATED APPLICATION

[0001] This application claims priority to and the benefit of U.S. Application No. 61/770,486, filed February 28, 2013, which is hereby incorporated by reference in its entirety.

10 FIELD

[0002] The present disclosure relates generally to multi-reservoir containment devices, including but not limited to medical devices, such as implantable medical devices, having containment reservoirs for confining substance or subcomponents for controlled release or exposure thereof. In aspects, the present disclosure relates to improved designs of such
15 devices for minimally invasive implantation and operation.

BACKGROUND

[0003] Implantable medical devices based on microchips that include reservoir arrays containing biosensors or drugs, for example, are known in the art. **FIG. 1** shows a
20 possible conventional approach for assembly of components in an implantable medical device **10**, which includes a microchip assembly **12**. The microchip assembly **12**, which is also referred to as a microchip element, includes microreservoirs, each of which may contain a drug for controlled delivery *in vivo* or a sensor for controlled exposure *in vivo*. The microchip assembly **12** is attached to a feedthrough **16** that is welded to the housing
25 **14**. Such microchip assemblies or elements are described, for example, in U.S. Patent 7,510,551 to Uhland et al. and U.S. Patent 7,604,628 to Santini Jr. et al. The feedthrough **16** contains electrically conductive pins that are metallurgically brazed to metallized surfaces on and through an alumina disc. A typical pin count exceeds 100, and in more complex designs, can be over 400. The consequence of such designs is that each pin
30 connection can be a leak point.

[0004] In addition, each feedthrough pin is electrically connected to an electronic component inside the housing. Some designs utilize a wire from the pin to the circuit, while the illustrated design attaches the feedthrough **16** directly to a conventional plastic circuit board **18**. These electrical connections require testing to ensure continuity. As a

result, the pin count impacts the cost of the feedthrough, and that cost increases as the number of feedthrough pins increases in the implantable device. Consequently, due to this complex design requirement, the resulting manufacturing, and the required acceptance tests, the feedthrough is an expensive component.

[0005] Moreover, conventional implantable device designs based on a feedthrough or header attached to housing components disadvantageously have an overall volume of the resulting device that is larger than desired, because several discrete components make up the assembly.

[0006] The devices shown in FIG. 1 contains control electronics, a power source, and wireless communication capabilities. The benefit of these internal functions is that the device can be programmed to automatically release discrete doses at specific time points, and the dosing schedule can be updated or modified wirelessly at any time. The patient therefore can automatically receive his or her medication without having to take any action. A disadvantage to this automatic drug delivery implant is that all of these functions require a finite volume. There is a clear desire, however, to reduce the volume of the device in order to i) reduce the incision required to implant the device under the skin, ii) increase the possible locations in the body that the device can be implanted, and iii) make the device less intrusive for the patient. In particular, it would be desirable to provide a smaller overall device volume without sacrificing functionality, simplicity, and/or hermeticity.

SUMMARY

[0006a] According to a first aspect of the present invention, there is provided a containment device, comprising: a microchip element comprising one or more containment reservoirs that are configured to be electrically activated to open; an electronic printed circuit board (PCB) fixed to the microchip element, wherein the PCB comprises an alumina or other biocompatible ceramic substrate; one or more electronic components associated with the microchip element or the PCB; and a first inductive coupling device incorporated into the microchip element or the ceramic PCB, wherein the first inductive coupling device is in communication with the one or more electronic components, wherein the containment device does not include a header or feedthrough for connecting the microchip element to the PCB.

[0006b] According to a second aspect of the present invention, there is provided a medical implant system comprising: the above containment device, which is configured for implantation in a patient; and an external communicator comprising a second inductive coupling device configured to form an inductive coupling circuit with the first inductive coupling device when brought within proximity of the containment device.

[0006c] According to a third aspect of the present invention, there is provided a method of assembling a containment device, comprising: providing an elongated microchip element comprising one or more containment reservoirs that are configured to be electrically activated to open; fixing the elongated microchip element to an electronic printed circuit board (PCB) which comprises a biocompatible substrate, without using a feedthrough to connect the elongated microchip element to the PCB; electrically connecting the elongated microchip element to one or more electronic components; and incorporating a first inductive coupling device into the microchip element or the PCB, wherein the first inductive coupling device is in communication with the one or more electronic components.

[0006d] According to a fourth aspect of the present invention, there is provided a system for drug delivery, biosensing, or both drug delivery and biosensing, comprising: an implantable component which comprises: a microchip element comprising one or more containment reservoirs that are configured to be electrically activated to open, the one or more containment reservoirs containing at least one of a drug, a biosensor, or a combination thereof, an electronic printed circuit board (PCB) fixed to the microchip element, wherein the implantable component does not include a header or feedthrough for connecting the microchip element to the PCB, one or more electronic components associated with the microchip element or the PCB, and a first inductive coupling device incorporated into the microchip element or the PCB, wherein the first inductive coupling device is in communication with the one or more electronic components ; and an external component which comprises a second inductive coupling device configured to form an inductive coupling circuit with the first inductive coupling device when brought within proximity of the implantable component.

[0006e] According to a fifth aspect of the present invention, there is provided a containment device, comprising: a microchip element comprising one or more containment reservoirs that are configured to be electrically activated to open; a silicon substrate positioned adjacent to the microchip element; one or more electronic components disposed within the silicon substrate, wherein the one or more electronic components are in communication with the microchip element; and a first inductive coupling device

associated with incorporated into the microchip element or the silicon substrate, wherein the first inductive coupling device is in communication with the one or more electronic components, wherein the containment device does not include a header or feedthrough for connecting the microchip element to the silicon substrate.

[0006f] According to a sixth aspect of the present invention, there is provided a medical implant system comprising: the above containment device, which is configured for implantation in a patient; and an external communicator comprising a second inductive coupling device configured to form an inductive coupling circuit with the first inductive coupling device when brought within proximity of the containment device.

[0006g] According to a seventh aspect of the present invention, there is provided a system for drug delivery, biosensing, or both drug delivery and biosensing, comprising: an implantable component which comprises: a microchip element comprising one or more containment reservoirs that are configured to be electrically activated to open, the one or more containment reservoirs containing at least one of a drug, a biosensor, or a combination thereof, a silicon substrate positioned adjacent to the microchip element, one or more electronic components disposed within the silicon substrate, wherein the one or more electronic components are in communication with the microchip element, and a first inductive coupling device incorporated into the microchip element or the silicon substrate, wherein the first inductive coupling device is in communication with the one or more electronic components, wherein the implantable component does not include a header or feedthrough for connecting the microchip element to the silicon substrate; and an external component which comprises a second inductive coupling device configured to form an inductive coupling circuit with the first inductive coupling device when brought within proximity of the implantable component.

[0006h] According to an eighth aspect of the present invention, there is provided a method of assembling a containment device, comprising: providing an elongated microchip element comprising one or more containment reservoirs that are configured to be electrically activated to open; connecting the elongated microchip element adjacent to a silicon substrate without using a header or feedthrough; electrically connecting the elongated microchip element to one or more electronic components; and incorporating a first inductive coupling device into the microchip element or the silicon substrate, wherein the first inductive coupling device is in communication with the one or more electronic components.

[0006i] According to a ninth aspect of the present invention, there is provided a method of operating a containment device, comprising: determining a location of the containment device, wherein the containment device comprises: a microchip element comprising one or more containment reservoirs that are configured to be electrically activated to open; an electronic printed circuit board (PCB) fixed to the microchip element; one or more electronic components associated with the microchip element or the PCB; and a first inductive coupling device incorporated into the microchip element or the PCB, wherein the first inductive coupling device is in communication with the one or more electronic components, wherein the containment device does not include a header or feedthrough for connecting the microchip element to the PCB; positioning an external communicator comprising a second inductive coupling device configured to form an inductive coupling circuit with the first inductive coupling device within proximity of the containment device; and activating the one or more containment reservoirs to open.

[0007] Some or all of the above needs and/or problems may be addressed by certain embodiments of the disclosure. In one embodiment, a containment device is provided that includes an elongated microchip element comprising one or more containment reservoirs that are configured to be electrically activated to open. The containment device may also include an elongated electronic printed circuit board (PCB) comprising a biocompatible substrate. The elongated PCB also may include a first side on which one or more electronic components are fixed and an opposed second side on which the elongated microchip element is fixed in electrical connection to the one or more electronic components. Further, the containment device may include an elongated housing fixed to the elongated PCB. The elongated housing is configured to hermetically seal the one or more electronic components of the elongated PCB within the elongated housing.

[0008] Other embodiments, aspects, and features of the invention will become apparent to those skilled in the art from the following detailed description, the accompanying drawings, and the appended claims.

5

BRIEF DESCRIPTION OF THE DRAWINGS

[0009] Reference will now be made to the accompanying drawings, which are not necessarily drawn to scale.

[0010] **FIG. 1** schematically depicts an exploded perspective view of a prior art containment device including a microchip assembly.

10 [0011] **FIG. 2A** schematically depicts a cross-sectional view of an assembled containment device including a microchip assembly according to an embodiment.

[0012] **FIG. 2B** schematically depicts an exploded cross-sectional view of the containment device shown in **FIG. 2A**.

15 [0013] **FIG. 2C** schematically depicts a top view of the containment device shown in **FIGS. 2A and 2B**.

[0014] **FIG. 3** schematically depicts a perspective view of the containment device illustrated in **FIGS. 2A-2C**.

[0015] **FIG. 4** schematically depicts a close-up, cross-sectional view of a portion of a containment device according to an embodiment.

20 [0016] **FIG. 5A** schematically depicts a cross-sectional view of a microchip element assembly according to an embodiment.

[0017] **FIG. 5B** schematically depicts an exploded cross-sectional view of the microchip element assembly shown in **FIG. 5A**.

25 [0018] **FIG. 6** schematically depicts a cross-sectional close-up view of a portion of an assembled containment device including a microchip assembly according to an embodiment.

[0019] **FIG. 7** schematically depicts a cross-sectional close-up view of a portion of an assembled containment device including a microchip assembly according to an embodiment.

30 [0020] **FIG. 8** schematically depicts a cross-sectional close-up view of a portion of an assembled containment device including a microchip assembly according to an embodiment.

[0021] FIG. 9 schematically depicts an external communicator that may be configured to wirelessly communicate with a containment device according to an embodiment.

[0022] FIG. 10 schematically depicts an external communicator positioned adjacent to an implanted containment device according to an embodiment.

5

DETAILED DESCRIPTION

[0023] Illustrative embodiments will now be described more fully hereinafter with reference to the accompanying drawings, in which some, but not all embodiments are shown. The representative embodiments described in the disclosure may be embodied in
10 many different forms and should not be construed as limited to the embodiments set forth herein. Like numbers refer to like elements throughout.

[0024] The containment devices and assemblies described herein provide, among other advantages, significantly improved space efficiency of the assembled devices. In certain embodiments, the devices and methods advantageously eliminate the need for a
15 costly and complex feedthrough, provide a thinner, sleek implant due to the elimination of the feedthrough, provide improved reliability by eliminating numerous feedthrough pins and electrical connections, provide improved reliability by reducing the number of hermetic interfaces, simplify tests to confirm functionality, and provide a simpler assembly. This can be particularly important in embodiments in which the containment
20 device is an implantable medical device intended for long-term implantation in a human or animal subject via minimally-invasive insertion means, such as through a small incision, trocar, cannula, injector, or similar like medical instrument.

[0025] The present invention advantageously provides a drug delivery implant with a higher ratio of drug volume to total device volume than previously available for an
25 actively controlled implant device. For example, a theoretical, perfect drug delivery device, with zero device volume could have a ratio of 1000 $\mu\text{L/cc}$. In practice, conventional drug delivery devices may range from less than 1 $\mu\text{L/cc}$ to about 65 $\mu\text{L/cc}$. Advantageously, by providing the containment devices described herein and relocating power source and control functions to an external communicator as described herein, a
30 drug delivery implant having a ratio of drug volume to total device volume from about 80 $\mu\text{L/cc}$ to about 120 $\mu\text{L/cc}$, or higher, is readily achievable. In one embodiment, the implantable drug delivery device has a body housing a drug payload for actively controlled release, which device has a ratio of volume of the drug payload to total volume

of the device from about 75 $\mu\text{L/cc}$ to about 150 $\mu\text{L/cc}$. In one case, for example, the ratio is from about 85 $\mu\text{L/cc}$ to about 120 $\mu\text{L/cc}$. In one embodiment, the body of the implantable drug delivery device includes a microchip element that has one or more containment reservoirs that are configured to be electrically activated to open; a PCB fixed to the microchip element; and a first inductive coupled device associated with the microchip element or the PCB, wherein the first inductive coupling device is in communication with the one or more electronic components. Nevertheless, essentially any ratio of drug volume to total device volume may be used with the devices and systems described herein.

10 [0026] The containment devices provided herein may be further understood with reference to the following exemplary embodiments, including the containment device **110** illustrated in **FIGS. 2A-3**. The containment device **110** includes an elongated microchip element **112** which comprises one or more containment reservoirs **114** that can be electrically activated to open. The containment device **110** also includes an elongated electronic printed circuit board (PCB) **116**. The elongated PCB **116** comprises a biocompatible substrate and has a first side **118** on which one or more electronic components **120** are fixed and an opposed second side **122** on which the microchip element **112** is fixed in electrical connection to the one or more electronic components **120**. As will be explained below with reference to **FIG. 4**, the electronic components **120** on the first side **118** of the PCB **116** are in electrical (i.e., operable) communication with the microchip element **112**.

20 [0027] It is understood that the containment device **110** may include any suitable number of microchip elements **112** (e.g., from 1 to 6) and that each microchip element **112** may include a plurality of discrete containment reservoirs **114** (e.g., from 10 to 750 reservoirs). More microchip elements **112**, and fewer or more containment reservoirs **114**, per containment device **110** are also envisioned. Moreover, it is understood that the containment device **110** may include any suitable number of PCBs **116**.

30 [0028] As shown in **FIGS. 2A-2C**, embodiments particularly suitable for minimally invasive insertion into a patient may have long, narrow microchip elements **112** with elongated arrays of closely spaced containment reservoirs. **FIG. 2C** shows a 2 x 28 reservoirs array. In one embodiment, the elongated array has from 1 to 4 rows of 20 to 40 reservoirs. In other embodiments, other numbers of rows and reservoirs are envisioned.

[0029] The “electronic printed circuit board” (PCB) refers to a substrate that mechanically supports and electrically connects electronic components using conductive pathways, tracks, or signal traces as known in the art. In certain embodiments, the PCB includes a biocompatible and hermetic substrate material. Suitable such materials include ceramics, such as alumina and silicon nitride. Multi-layer alumina PCBs have been successfully designed and manufactured. See, for example, U.S. Patent Application Publication No. 2003/0034564. These laminations may be the result of combining conductive layers, dielectric layers, and aluminum oxide (Al₂O₃, alumina) in a low temperature co-fired process. The alumina is referred to as low temperature co-fired ceramic (LTCC). These biocompatible ceramics also function as a hermetic barrier, eliminating the need, in some instances, for conventional metallic housing elements. Other materials or combinations of materials capable of performing all or some of the described function may also be used.

[0030] The term “biocompatible” as used herein generally refers to materials of construction that are suitable for long-term or short-term implantation into a human or animal subject, e.g., a patient. Such materials of constructions are known in the art of implantable medical devices.

[0031] As used herein, the term “hermetic seal” refers to preventing undesirable ingress or egress of chemicals (e.g., water vapor, water, oxygen, etc.) into or from one or more compartments of the device, such as the device reservoirs or housings, over the useful life of the device. For purposes herein, a material/seal that transmits helium (He) at a rate less than 1×10^{-9} atm*cc/sec is termed hermetic.

[0032] In some instances, the containment device **110** may include an elongated housing **124**. The elongated housing **124** is configured to hermetically seal the one or more electronic components **120** of the elongated PCB **116** within the elongated housing **124**. That is, the elongated housing **124** is configured to surround the first side **118** of the elongated PCB **116**. In this manner, the elongated housing **124** and the elongated PCB **116** collectively form a hermetic enclosure around the one or more electronic components **120**. Desirably, the elongated housing **124** and at least a portion of the outward facing second side **122** of the elongated PCB **114** are formed of a biocompatible material. For example, in some instances, the elongated housing **124** may be made of a biocompatible metal or alloy, such as titanium or stainless steel. In other instances, the elongated housing **124** may be made of a biocompatible polymer. In certain embodiments, at least a

portion of the elongated housing **124** may comprise a generally cylindrical body.

Moreover, a distal end **136** of the elongated housing **124** may be rounded.

[0033] The elongated housing **124** may comprises a battery chamber **126** configured to house one or more batteries **128** therein. In some instances, the battery chamber **126** may
5 be a separate area within the elongated housing **124**. In other instances, the battery chamber **126** may be part of a single enclosure formed by the elongated housing **124**. In one embodiment, the battery chamber **126** may be positioned about a proximal end **130** of the elongated housing **124**. However, the battery chamber **126** may be located at any position within the elongated housing **124**. Moreover, in some instances, the battery
10 chamber **126** may be omitted. For example, the device power may be provided by inductive charging.

[0034] In certain embodiments, the battery chamber **126** may include a cover **132**. The cover **132** may be removable or permanent. The cover **132** may be configured to provide access to the batteries **128** and/or hermetically seal the one or more batteries **128**
15 within the battery chamber **126**. That is, in a preferred embodiment, the cover **132** and the elongated housing **124** form a hermetic seal when affixed to each other. In one example, the cover **132** may be located about the proximal end **130** of the elongated housing **124**.

[0035] The interface of the elongated housing **124** with the elongated PCB **116**, in a preferred embodiment, forms a hermetic seal to isolate the one or more electronic
20 components **120** within the elongated housing **124**. In some instances, the elongated housing **124** may be welded to the elongated PCB **116**. In other instances, a biocompatible substance **134**, such as a biocompatible epoxy coating (e.g., an epoxy resin) or other biocompatible coating material, may be disposed over at least a portion of the elongated microchip element **112**, the elongated PCB **116**, and the elongated housing **124**.
25 This coating may be multilayered, and it may include a hermetic material so long the material does not interfere with the operation of any of the components, such as the electronic components **120** or the batteries **128**.

[0036] In certain embodiments, the containment device **110** may include a sleek, tubular profile. For example, some or all of the components associated with the
30 containment device **110** may be elongated. That is, some or all of the components of the containment device **110**, such as the elongated microchip element **112**, the elongated PCB **116**, and the elongated housing **124**, may have a greater length than width. Furthermore, the biocompatible coating substance **134**, the elongated microchip element **112**, and the

elongated housing **124** may collectively form a generally circular cross-section and rounded distal end **136** of the containment device **110**. The components may collectively fit together to form a sleek, tube-like structure or assembly that may be inserted in a human or animal subject in a minimally invasive manner. In other instances, some or all of the components associated with the containment device **110** may not be elongated.

[0037] The biocompatible coating substance **134** may create an atraumatic surface about the containment device **110**. In embodiments, the surface of the containment device is formed of or coated with a lubricious substance to facilitate passage of the device to the intended tissue site.

[0038] The containment device **110** may be implanted in a human or animal subject, such as a patient in need of treatment, diagnosis, or prophylaxis, by a variety of techniques known in the art. In a preferred embodiment, the device is inserted into the patient at a subcutaneous tissue site. A variety of insertion tools and systems may be used depending on the particular size of the implant and the particular site of implantation desired for a particular medical purpose. The containment device **110** may be inserted, injected, or otherwise placed into the human or animal subject via one or a combination of minimally invasive medical instruments, including a cannula, trocar, subcutaneous insert, or a gun-like injector device or assembly. In one embodiment, a small (few millimeter) incision is made in the patient's skin, and the containment device is passed through the incision and into the patient just under the skin using a long, narrow inserter tool that can grasp an end of the containment device in a linear low profile arrangement. The containment device would be released from the inserter tool, the end of the inserter tool would be removed from the incision, and then the incision would be closed, for example with one or a few stitches. In some instances, one or more suture loops may be provided with the housing **124** and/or the cap **132**. The suture loops may be configured to anchor the containment device **110** in a subcutaneous space.

[0039] The electronic components **120** provide any of a number of functions for the containment device **110**. Examples include, but are not limited to, a controller (e.g., microprocessor) and power source (e.g., a battery or capacitor) for electrically activating the reservoir **114** to cause it to become opened and/to communicate with a sensor, for example, located within the reservoir **114** or with another device remotely located from the containment device **110**. Other electronic components may include, for example, telemetry hardware, capacitors, transistors, and diodes, as well as the control means for

actuating the reservoir caps. The control means may include an input source, a microprocessor, a timer, a demultiplexer (or multiplexer). In an embodiment, the electronic components include components for wirelessly receiving energy for charging an on-board storage capacitor, which may further reduce the space requirements for the electronic components on-board the containment device. In some instances, the electronic components may include an antenna.

[0040] The containment reservoir **114** of the microchip element **112** may be configured to open/activate in a variety of ways, which may be known in the art. In one embodiment, the containment reservoir **114** is structured and configured to be electrically activated to open as described in U.S. Patent No. 7, 510,551 and U.S. Patent No. 7,604,628, which are incorporated herein by reference.

[0041] One embodiment of the electrical connection between a PCB/electronic components and a microchip element is illustrated in **FIG. 4**. The figure shows part of the microchip element **312** including two containment reservoirs **344**. Each containment reservoir **344** has an opening closed off by a reservoir cap **348**. The containment reservoir **344**, which is formed at least in part in a substrate **343**, has a closed end opposed to the opening and a sidewall therebetween. The microchip element **312** is secured to a side of a PCB **314**, and electronic component **318** is secured on the opposed side of the PCB **314**. The PCB **314** includes a via **330** which electrically connects electronic component **318** to the microchip element **312**. Via **330** is mechanically and electrically connected to metallized conductive surfaces **332A**, **332B** on the PCB **314**, and the microchip element **312** is wirebonded **334** to the metallized conductive surface **332A**. A biocompatible coating substance **336** is applied over the wire bond to secure and protect the connection, and typically will coat part of the surface of the PCB **314**, part of the microchip element **312**, and part of the housing **320** but not the reservoir caps **348**. The coating substance **336** may be a polymer, such as an epoxy or other resin.

[0042] In one embodiment, the reservoir caps **348** are structured and configured to be electrically activated to open as described in U.S. Patent No. 7, 510,551 and U.S. Patent No. 7,604,628, which are incorporated herein by reference. The reservoir caps **348** may be formed of a metal film, which may comprise a single layer or a laminate structure. For example, the reservoir cap **348** may comprise gold, platinum, titanium, or a combination thereof. In other embodiments, the reservoir cap **348** can be configured to be activated or opened by a mechanical or electrochemical mechanism.

- [0043] The containment reservoir of the microchip element may be a “microreservoir” which generally refers to a reservoir having a volume equal to or less than 500 μL (e.g., less than 250 μL , less than 100 μL , less than 50 μL , less than 25 μL , less than 10 μL , etc.). In another embodiment, the containment reservoirs may be a “macroreservoir” which
- 5 generally refers to a reservoir having a volume greater than 500 μL (e.g., greater than 600 μL , greater than 750 μL , greater than 900 μL , greater than 1 mL, etc.) and less than 5 mL (e.g., less than 4 mL, less than 3 mL, less than 2 mL, less than 1 mL, etc.). The terms “reservoir” and “containment reservoir” are intended to encompass both microreservoirs and macroreservoirs unless explicitly indicated to be limited to either one or the other.
- 10 [0044] In a second aspect, improved microchip elements and methods for their manufacture are provided. In a preferred embodiment, the microchip device element includes a relatively thin silicon substrate bonded to a relatively thicker primary substrate formed of a polymer or a glass or other ceramic material. Advantageously, by defining the reservoirs in the primary substrate rather than the silicon substrate, the reservoirs may be
- 15 formed using processes other than dry reactive ion etching (DRIE). This is important, not just because DRIE processes are expensive, but also because under the conventional process, the DRIE processes occurred after deposition of the reservoir cap film, unnecessarily exposing the reservoir cap film to subsequent processing, which can negatively impact the yield of acceptable (e.g., hermetic) reservoir caps.
- 20 [0045] In addition, by adding the positive sealing features (e.g., gold sealing rings) to the silicon substrate, this keeps all of the high tolerance microfeatures to only the silicon substrate, which in turn frees up the primary substrate to be made by other, potentially lower tolerance, manufacturing processes. In this way, the reservoir can be made much deeper and thereby increase the unit reservoir payload. In one embodiment, the primary
- 25 substrate is made by a casting or molding process using ceramic or polymeric materials that allows for formation of reservoirs that are deeper than conventional reservoirs and have smoother side walls than would be readily possible using DRIE. This cast or molded substrate then may be gold plated in and about sealing grooves formed therein for bonding with the positive sealing features on the silicon substrate.
- 30 [0046] An exemplary embodiment of the elongated microchip element is illustrated in FIG. 5A and FIG. 5B. The elongated microchip element 412 includes a primary substrate 440 and a silicon substrate 442, which are bonded together. The silicon substrate 442 has a first side, an opposed second side, and apertures 446 extending therethrough. Three

apertures **446** are shown for each reservoir **444**. The first side of the silicon substrate **442** includes reservoir caps **448** which close off the apertures until the reservoir needs to be opened. In a preferred embodiment, the reservoir caps **448** are electrically conductive. For example, the reservoir caps **448** may be in the form of a metal film. The silicon
5 substrate **442**, apertures **446**, and reservoir caps **448** can be made using microfabrication techniques known in the art. For example, the photolithography, etching, and deposition techniques described in U.S. Patent No. 7,604,628 may be used to form the apertures **446** in a polysilicon substrate closed off by metal reservoir caps **448**.

[0047] The primary substrate **440** includes two reservoirs **444** in this illustration,
10 although more or less reservoirs may be included. Each reservoir **444** is defined by a closed end wall, an open end, and at least one sidewall extending between the closed end wall and the open end. As mentioned above, the primary substrate **440** may be formed of silicon. In other embodiments, the substrate may be formed of a metalloid, polymer, glass, or other ceramic material. The substrate and reservoirs may be made by any suitable
15 process, including but not limited to molding, casting, micromachining, and build-up or lamination techniques known in the art. In one embodiment, the primary substrate **440** is made of/by low temperature co-fired ceramics (LTCC). It may further include a coating layer on all or a portion of the substrate, for example to provide or improve hermeticity, biocompatibility, bonding, and/or reservoir content compatibility, stability, or release.
20 Depending on the purpose of the coating layer, it may be applied inside the reservoirs **444**, outside of the reservoirs **444**, or both. Examples of possible coating materials include biocompatible metals, such as gold, and polymers, such as parylene.

[0048] The primary substrate **440** and the silicon substrate **442** are bonded together using any suitable method, to hermetically seal the reservoirs **444**. In this way, the open
25 end of the reservoir **444** is in fluid communication with the apertures **446** for controlled release or exposure of reservoir contents. In a preferred embodiment, the substrates are hermetically sealed together using a compression cold welding process, such as described in U.S. Patent No. 8,191,756, which is incorporated herein by reference.

[0049] As shown in **FIGS. 5A** and **5B**, the second side of the silicon substrate **442**
30 includes ring structures **452** formed thereon, and the first side of the primary substrate **440** includes grooves **450**. These bonding features are compressed together to form a cold weld bond hermetic seal surrounding the individual reservoirs **444**. The ring structures **452** may be formed by a depositing gold or another metal layer on the silicon substrate

442. The grooves **450** may be etched in the silicon and then coated with a metallized layer of the same material as the metal ring. Variations of this embodiment are envisioned, for example, where other positive and negative bonding features are provided in/on either or both interfacing surfaces of the silicon substrate **442** and the primary substrate **440**.

[0050] The primary substrate **440** is generally relatively thicker than the silicon substrate **442**, and all or at least a majority (greater than 50%) of the reservoir sidewall height (or depth) is defined by the primary substrate **440**. In an embodiment, the silicon substrate **442** has thickness that is between 5% and 50% of the thickness of the primary substrate **440** at the bonded interfaces of the substrates.

[0051] Although not shown in **FIG. 4** or **FIG. 5A**, the reservoirs **344** and **444**, respectively, include reservoir contents positioned therewithin. The reservoirs can be configured to store essentially any substance or device component in need of hermetic containment and subsequent release or exposure at a selected time. The reservoir content may be, for example, a chemical reagent, a drug formulation, or sensor or component thereof, such as an electrode. In an embodiment, a single device includes at least one containment reservoir containing a biosensor and at least one reservoir containing a drug formulation. Examples of various reservoir contents are described for example in U.S. Patent No. 7,510,551; U.S. Patent No. 7,497,855; U.S. Patent No. 7,604,628; U.S. Patent No. 7,488,316; and PCT WO 2012/027137.

[0052] An exemplary embodiment of a containment device **600** including a microchip element **612** is illustrated in **FIG. 6**. The containment device **600** includes a ceramic PCB **614** which has via **630** electrically connecting electronic component **618** to the microchip element **612**. The electronic component **618** is secured on a first side of the ceramic PCB **614**, and the microchip element **612** is secured on the opposing second side of the PCB **614**. The via **630** electrically connects to a metallized conductive surface **632** on the first side of the PCB **614**. The electrical circuitry **635** of the microchip element **612** is electrically connected to the metallized surface **632** by a wirebond **634**. An epoxy **633** coats the wirebond **634** and at least a portion of the microchip element **612**, the ceramic PCB **614**, and a housing **620**. In this manner, the epoxy **633** ensures that the containment device **600** is void of any atramatic surfaces. The second side of the ceramic PCB **614** also includes a metallized conductive surface **637**, which is electrically connected to the electronic component **618**. Although not shown in this illustration, the containment device **600** may include multiple microchip elements, as well as multiple vias, electronic

components, and wirebonds. Moreover, the containment device **600** may be completely or partially coated by the epoxy **633**.

[0053] The microchip element **612** includes a primary substrate **640** and a silicon substrate **642**. The primary substrate **640** and silicon substrate **642** are bonded together by compression cold welding at/adjacent the interface of a ring structure and groove structure tongue **650/652**. Reservoirs **644** are defined in the primary substrate **640** with the open end in fluid communication with apertures **646** defined through the silicon substrate **642**. Electrically conductive reservoir caps **648** sealingly cover the apertures **646** and reservoirs **644**.

[0054] An exemplary embodiment of a containment device **700** is illustrated in **FIG. 7**. The containment device **700** includes a microchip element **712** and a ceramic PCB **714**, which is fixed to the microchip element **712**. Electrical circuitry **735** of the microchip element **712** is electrically connected to the metallized surface **732** by a wirebond **734**. An epoxy **733** coats the wirebond **734** and at least a portion of the microchip element **712**, the ceramic PCB **714**, and/or the metallized surface **732**. In this manner, the epoxy **733** ensures that the containment device **700** is void of any atramatic surfaces. Although not shown in this illustration, the containment device **700** may include multiple microchip elements, as well as multiple vias, electronic components, and wirebonds. Moreover, the containment device **700** may be completely or partially coated by the epoxy **733**. In some instances, the containment device **700** may be relatively thin and the epoxy coating may be omitted. The containment device **700** may include any length, to width, to thickness ratio. That is, the containment device **700** may be any suitable size.

[0055] In some instances, the PCB **714** may comprise a silicon material that is manufactured using a MEMS manufacturing process. In other instances, the PCB **714** may comprise a multilayer low temperature co-fired ceramic (LTCC). In yet other instances, the PCB **714** may comprise a substrate other than a printed circuit board that is capable of performing the functionality described herein. For example, element **714** may comprise a silicon substrate or the like that is configured to house one or more electric components **718** therein. In turn, the electrical components **718** may be in communication with the microchip element **712**.

[0056] The microchip element **712** includes a primary substrate **740** and a silicon substrate **742**. The primary substrate **740** and silicon substrate **742** are bonded together by compression cold welding at/adjacent the interface of a ring structure and groove structure

tongue 750/752. The reservoirs 744 are defined in the primary substrate 740 with the open end in fluid communication with the apertures 746 defined through the silicon substrate 742. Electrically conductive reservoir caps 748 sealingly cover the apertures 746 and reservoirs 744. In some instances, the PCB 714 and the primary substrate 740 may
5 comprise a single silicon substrate or separate silicon substrates. In this manner, the PCB 714 and the primary substrate 740 may be manufactured together as part of a MEMS process or manufactured separately and assembled together.

[0057] In certain embodiments, in order to provide a smaller and less intrusive containment device 700, the housing is omitted. In this manner, the electronic
10 components 718 are integrated into the microchip element 712 and/or the ceramic PCB 714. That is, the electronic components 718 may be disposed within or about the microchip element 712 and/or the ceramic PCB 714. In some instances, the electronic components 718 include components and/or functionality for wirelessly receiving energy for charging an on-board storage capacitor, which may further reduce the space
15 requirements for the electronic components on-board the containment device 700. In some instances, the electronic components 718 may include an antenna or the like. In addition, an inductive coupling device 760, such as a coil or the like, may be incorporated into the microchip element 712 and/or the ceramic PCB 714. In certain embodiments, the electronic components 718 and the inductive coupling device 760 may be integrated. In
20 other embodiments, the electronic components 718 and the inductive coupling device 760 may be separate components in electrical (i.e., operable) communication with one another. The inductive coupling device 760 may form an inductive coupling circuit between the implanted containment device 700 and an external communicator, such as a power source and/or computing device or the like. The electronic components 718 and/or the inductive
25 coupling device 760 provide, for example, functionality to receive wireless power transmission from the external communicator, capacitors to store the required energy to open the caps 748, and/or other electronics and circuitry to manage the flow of current to the appropriate reservoirs 744. Other functionality also may be provided by the electronic components 718 and/or the inductive coupling device 760.

30 [0058] An exemplary embodiment of a containment device 800 is illustrated in FIG. 8. The containment device 800 includes a microchip element 812 and a ceramic PCB 814, similar to those described above. That is, the ceramic PCB 814 is fixed to the microchip element 812. A via 830 electrically connects electronic components 818 to portions of the

microchip element **812**. For example, the electrical circuitry **835** of the microchip element **812** is electrically connected to the electronic components **818** by way of the via **830**.

Although not shown in this illustration, the containment device **800** may include multiple microchip elements, as well as multiple vias, electronic components, wirebonds, and/or epoxy coatings that ensure the containment device **800** is void of any atramatic surfaces (i.e., the containment device **800** may be completely or partially coated by an epoxy). In some instances, the containment device is relatively thin and the epoxy coating may be omitted. The containment device **800** may include any length, to width, to thickness ratio. That is, the containment device **800** may be any suitable size.

10 **[0059]** In certain embodiments, the PCB **814** may comprise a silicon material that is manufactured using a MEMS manufacturing process. In other instances, the PCB **814** may include a multilayer low temperature co-fired ceramic (LTCC). In yet other instances, the PCB **814** may include a substrate other than a printed circuit board that is capable of performing the functionality described herein. For example, element **814** may
15 include a silicon substrate or the like that is configured to house one or more electric components **818** therein. In turn, the electrical components **818** may be in communication with the microchip element **812**.

[0060] The microchip element **812** includes a primary substrate **840** and a silicon substrate **842**. The primary substrate **840** and silicon substrate **842** are bonded together by
20 compression cold welding at/adjacent the interface of a ring structure and groove structure tongue **850/852**. The reservoirs **844** are defined in the primary substrate **840** with the open end in fluid communication with the apertures **846** defined through the silicon substrate **842**. Electrically conductive reservoir caps **848** sealingly cover the apertures **846** and reservoirs **844**. In some instances, the PCB **814** and the primary substrate **840** may
25 comprise a single silicon substrate or separate silicon substrates. In this manner, the PCB **814** and the primary substrate **840** may be manufactured together as part of a MEMS process or manufactured separately and assembled together.

[0061] Similar to the embodiments described in **FIG. 7**, in order to provide a smaller and less intrusive containment device **800**, the housing is omitted. As a result, the
30 electronic components **818** are integrated into the microchip element **812** and/or the ceramic PCB **814**. That is, the electronic components **818** may be disposed within or about the microchip element **812** and/or the ceramic PCB **814**. In some instances, the electronic components **818** include components and/or functionality for wirelessly

receiving energy for charging an on-board storage capacitor, which may further reduce the space requirements for the electronic components on-board the containment device **800**. In some instances, the electronic components **818** may include an antenna or the like. In addition, an inductive coupling device **860**, such as a coil or the like, may be incorporated

5 into the microchip element **812** and/or the ceramic PCB **814**. In certain embodiments, the electronic components **818** and the inductive coupling device **860** may be integrated. In other embodiments, the electronic components **818** and the inductive coupling device **860** may be separate components in electrical (i.e., operable) communication with one another. The inductive coupling device **860** may form an inductive coupling circuit between the

10 implanted containment device **800** and an external communicator, such as a power source and/or computing device or the like. The electronic components **818** and/or the inductive coupling device **860** provide, for example, functionality to receive wireless power transmission from the external communicator, capacitors to store the required energy to open the caps **848**, and/or other electronics and circuitry to manage the flow of current to

15 the appropriate reservoirs **844**. Other functionality also may be provided by the electronic components **818** and/or the inductive coupling device **860**.

[0062] An exemplary embodiment of an external communicator **900** (or controller) is illustrated in **FIG. 9**. In certain embodiments, the external communicator **900** includes a display **902**, a battery **904** (or other power supply), a power management module **906**, a

20 multiplexer **908**, a microcontroller **910**, an input/output module **912**, and/or an electromagnetic modulation module **914**. In addition, the external communicator **900** includes one or more processors coupled to at least one memory. In this manner, various instructions, methods, and techniques described herein may be considered in the general context of computer-executable instructions, such as program modules, executed by one or

25 more computers or other devices. Additional components and/or modules may be included. Moreover, the external communicator **900** includes an inductive coupling device **916**. The inductive coupling device **916** forms an inductive coupling circuit between the implanted containment device and the external communicator **900** when brought within proximity of one another.

30 [0063] In some instances, the external communicator **900** may be a hand held device. In other instances, the external communicator **900** may be associated with a computer or the like. In yet other instances, the external communicator **900** may be wireless. The external communicator **900** may include any number of interfaces so that a user may

interact therewith. Moreover, the external communicator **900** may include any number of interfaces and/or functionality so that the external communicator **900** may wirelessly interact with a containment device.

[0064] As depicted in **FIG. 10**, in some instances, an external communicator **1000** may be positioned on or about the surface of the skin **1004** adjacent to a containment device **1002** that is implanted within a patient. For example, in one embodiment the site of implantation is subcutaneous and near to the skin of the patient. The external communicator **1000** includes an inductive coupling device **1006** or the like, and the containment device **1002** includes an inductive coupling device **1008** or the like. In this manner, the external communicator **1000** may be configured to transmit both control instructions and the necessary power to release the required dose or doses by way of an inductive coupling between the inductive coupling device **1006** and the inductive coupling device **1008**. In certain embodiments, the external communicator **1000** may query the implanted containment device **1002** to obtain diagnostic information or confirmation information, such as specific doses released and doses remaining.

[0065] The use of the external communicator **1000** advantageously significantly reduces the overall size of the containment device **1002** by relocating the power source and several of the control functions from the containment device **1002** to the external communicator **1000**. For example, both power and control signals can be transferred across the skin **1004** via electromagnetic coupling, such as inductive charging or the like. Other wireless communications and connections may also be incorporated between the external communicator **1000** and the containment device **1002**. In this manner, the external communicator **1000** may control one or more aspects of the containment device **1002** remotely.

[0066] The reduction in the size (i.e., volume) of the containment device **1002** beneficially leads to reductions in the incision required to implant the containment device **1002** under the skin **1004**. The reduction in the size of the containment device **1002** also beneficially increases the possible locations in the body that the containment device **1002** can be implanted, which may be important for local or regional delivery of therapeutic agents and/or may reduce the amount of drug required to be delivered for a particular therapy. Moreover, the reduction in the size of the containment device **1002** makes the containment device **1002** less intrusive for the patient. As a result, the containment device

1002 may comprise a drug delivery implant with a higher ratio of drug volume to total device volume.

[0067] Modifications and variations of the methods and devices described herein will be obvious to those skilled in the art from the foregoing detailed description. Such
5 modifications and variations are intended to come within the scope of the appended claims.

CLAIMS

1. A containment device, comprising:
 - a microchip element comprising one or more containment reservoirs that are configured to be electrically activated to open;
 - an electronic printed circuit board (PCB) fixed to the microchip element, wherein the PCB comprises an alumina or other biocompatible ceramic substrate;
 - one or more electronic components associated with the microchip element or the PCB; and
 - a first inductive coupling device incorporated into the microchip element or the PCB, wherein the first inductive coupling device is in communication with the one or more electronic components,
 - wherein the containment device does not include a header or feedthrough for connecting the microchip element to the PCB.
2. A medical implant system comprising:
 - the containment device of claim 1, which is configured for implantation in a patient; and
 - an external communicator comprising a second inductive coupling device configured to form an inductive coupling circuit with the first inductive coupling device when brought within proximity of the containment device.
3. The containment device of claim 1, wherein the PCB comprises at least one via configured to electrically connect at least one of the one or more electronic components to the microchip element.
4. The containment device of claim 1, wherein the microchip element is connected via a wire bond to a metallized conductive surface on the PCB.
5. The containment device of claim 4, wherein a biocompatible coating substance is positioned over the wire bond to secure and protect the connection of the wire bond and to create an atraumatic surface about the containment device.

6. The containment device of claim 1, wherein the one or more containment reservoirs comprise microreservoirs containing a drug formulation or a sensor element.
7. The containment device of claim 1, wherein the microchip element comprises:
 - a silicon substrate having a first side, an opposed second side, and at least one aperture extending therethrough, wherein the first side of the silicon substrate comprises an electrically conductive reservoir cap which closes off the at least one aperture;
 - a primary substrate which is formed of silicon or other metalloid, a polymer, or a glass or other ceramic material, wherein the primary substrate has at least one of the one or more reservoirs which is defined by a closed end wall, an open end, and at least one sidewall extending between the closed end wall and the open end; and
 - reservoir contents positioned within the at least one reservoir,
 - wherein the second side of the silicon substrate is hermetically bonded to the primary substrate such that the open end of the reservoir is in fluid communication with the at least one aperture for controlled release or exposure of reservoir contents.
8. The containment device of claim 7, wherein the primary substrate comprises a metal coating over at least a part of the polymer, glass or other ceramic material of the primary substrate.
9. The containment device of claim 8, wherein the metal coating coats the at least one sidewall and/or the closed end wall of the at least one reservoir.
10. The containment device of claim 7, wherein the second side of the silicon substrate comprises at least one ring structure formed thereon.
11. The containment device of claim 10, wherein the at least one ring structure comprises gold or another metal.

12. The containment device of claim 10, wherein the primary substrate comprises at least one groove structure, wherein the at least one ring structure and the at least one groove structure are configured to form a hermetic bond.
13. The containment device of claim 12, wherein the surface of the primary substrate in and/or adjacent to the at least one groove structure comprises a metal coating.
14. The containment device of claim 13, wherein the metal coating comprises gold.
15. The containment device of any one of claims 1 to 14, further comprising at least one drug payload disposed in the one or more containment reservoirs for actively controlled release.
16. The containment device of claim 15, wherein a ratio of a volume of the at least one drug payload to a total volume of the containment device is from about 75 $\mu\text{L}/\text{cc}$ to about 150 $\mu\text{L}/\text{cc}$.
17. The containment device of claim 15, wherein a ratio of a volume of the at least one drug payload to a total volume of the containment device is from about 85 $\mu\text{L}/\text{cc}$ to about 120 $\mu\text{L}/\text{cc}$.
18. A method of assembling a containment device, comprising:
 - providing an elongated microchip element comprising one or more containment reservoirs that are configured to be electrically activated to open;
 - fixing the elongated microchip element to an electronic printed circuit board (PCB) which comprises a biocompatible substrate, without using a feedthrough to connect the elongated microchip element to the PCB;
 - electrically connecting the elongated microchip element to one or more electronic components; and

incorporating a first inductive coupling device into the microchip element or the PCB, wherein the first inductive coupling device is in communication with the one or more electronic components.

19. The method of claim 18, wherein providing the elongated microchip element further comprises:

microfabricating a silicon substrate having a first side, an opposed second side, and at least one aperture extending therethrough, wherein the first side comprises an electrically conductive reservoir cap which closes off the at least one aperture;

casting or molding a polymer or a glass or other ceramic material to form a primary substrate having at least one of the one or more reservoirs which is defined by a closed end wall, an open end, and at least one sidewall extending between the closed end wall and the open end;

providing reservoir contents within the at least one reservoir; and

bonding the silicon substrate to the primary substrate such that the open end of the reservoir is in fluid communication with the at least one aperture.

20. The method of claim 19, wherein the microfabricating step further comprises forming at least one ring structure on the second side of the silicon substrate.

21. A system for drug delivery, biosensing, or both drug delivery and biosensing, comprising:

an implantable component which comprises:

a microchip element comprising one or more containment reservoirs that are configured to be electrically activated to open, the one or more containment reservoirs containing at least one of a drug, a biosensor, or a combination thereof,

an electronic printed circuit board (PCB) fixed to the microchip element, wherein the implantable component does not include a header or feedthrough for connecting the microchip element to the PCB,

one or more electronic components associated with the microchip element or the PCB, and

a first inductive coupling device incorporated into the microchip element or the PCB, wherein the first inductive coupling device is in communication with the one or more electronic components; and
an external component which comprises a second inductive coupling device configured to form an inductive coupling circuit with the first inductive coupling device when brought within proximity of the implantable component.

22. The system of claim 21, wherein the implantable component is configured for subcutaneous insertion into a patient in need thereof.
23. A containment device, comprising:
a microchip element comprising one or more containment reservoirs that are configured to be electrically activated to open;
a silicon substrate positioned adjacent to the microchip element;
one or more electronic components disposed within the silicon substrate, wherein the one or more electronic components are in communication with the microchip element; and
a first inductive coupling device incorporated into the microchip element or the silicon substrate, wherein the first inductive coupling device is in communication with the one or more electronic components,
wherein the containment device does not include a header or feedthrough for connecting the microchip element to the silicon substrate.
24. A medical implant system comprising:
the containment device of claim 23, which is configured for implantation in a patient; and
an external communicator comprising a second inductive coupling device configured to form an inductive coupling circuit with the first inductive coupling device when brought within proximity of the containment device.

25. A system for drug delivery, biosensing, or both drug delivery and biosensing, comprising:
- an implantable component which comprises:
 - a microchip element comprising one or more containment reservoirs that are configured to be electrically activated to open, the one or more containment reservoirs containing at least one of a drug, a biosensor, or a combination thereof,
 - a silicon substrate positioned adjacent to the microchip element,
 - one or more electronic components disposed within the silicon substrate, wherein the one or more electronic components are in communication with the microchip element, and
 - a first inductive coupling device incorporated into the microchip element or the silicon substrate, wherein the first inductive coupling device is in communication with the one or more electronic components,
 - wherein the implantable component does not include a header or feedthrough for connecting the microchip element to the silicon substrate; and
 - an external component which comprises a second inductive coupling device configured to form an inductive coupling circuit with the first inductive coupling device when brought within proximity of the implantable component.
26. The system of claims 21, 22, or 25, wherein the external component comprises a power source and the implantable component does not contain a power source.
27. A method of assembling a containment device, comprising:
- providing an elongated microchip element comprising one or more containment reservoirs that are configured to be electrically activated to open;
 - connecting the elongated microchip element adjacent to a silicon substrate without using a header or feedthrough;
 - electrically connecting the elongated microchip element to one or more electronic components ; and

incorporating a first inductive coupling device into the microchip element or the silicon substrate, wherein the first inductive coupling device is in communication with the one or more electronic components.

28. A method of operating a containment device, comprising:
- determining a location of the containment device, wherein the containment device comprises:
 - a microchip element comprising one or more containment reservoirs that are configured to be electrically activated to open;
 - an electronic printed circuit board (PCB) fixed to the microchip element;
 - one or more electronic components associated with the microchip element or the PCB; and
 - a first inductive coupling device incorporated into the microchip element or the PCB, wherein the first inductive coupling device is in communication with the one or more electronic components,
 - wherein the containment device does not include a header or feedthrough for connecting the microchip element to the PCB;
 - positioning an external communicator comprising a second inductive coupling device configured to form an inductive coupling circuit with the first inductive coupling device within proximity of the containment device; and
 - activating the one or more containment reservoirs to open.