DESCRIPTION

OPTICAL DATA RECORDING METHOD, AND DATA RECORDING MEDIUM

Technical Field

The present invention relates to a recording method for recording optical data to a writable data recording medium, and to the structure of a data recording medium used by this method.

Background Art

Devices for recording and reproducing optical data, particularly digital data, to data recording media have been the subject of much development due to the ability of such devices to store large volumes of data using media of a given physical size.

The phase change optical disk is one type of recordable optical data recording medium. To record to a phase change optical disk, the beam from a semiconductor laser is focused on the rotating disk to heat and melt, that is, change the phase of, a recording film. The temperature of the recording film and the rate at which the film cools vary, for example, according to the intensity of the optical beam.

When the intensity of the optical beam is high, the film cools rapidly from a high temperature state, and the recording film is changed to an amorphous phase. When the optical beam is relatively weak, the recording film cools gradually from a medium-high temperature state, and the recording film thus crystallizes. The resulting amorphous areas of the recording film are normally referred to as a "mark;" the crystallized part between consecutive marks is normally referred to as a "space." These marks and spaces can be

used to record two-value data, that is, 0s and 1s.

It is also to be noted that laser power when the optical beam intensity is high is referred to as "peak power," and laser power when the optical beam intensity is low is referred to as "bias power."

When reproducing data, a low power optical beam, that is, a light beam not strong enough to produce a phase change in the recording film, is emitted to the disk, and the light reflected back from the disk is then detected. In general, the reflectance of the amorphous phase marks is low, and the reflectance of crystal phase spaces is high. A reproduction signal can therefore be obtained by detecting the difference in the amount of light reflected from the marks and spaces.

Mark position recording (or PPM recording) whereby information is recorded using the location of marks of a constant length, and mark edge recording (or PWM recording) whereby information is recorded using the length of the marks and the length of spaces between marks, are two methods of recording data to a phase change optical disk. The data recording density of mark edge recording is generally the higher of these two methods.

The mark edge recording method also generally records longer marks compared with the constant mark length in mark position recording. When a peak power laser beam is emitted to a phase change disk to record a long mark, heat accumulation in the recording film produces marks that are wider in the latter half of the mark as seen in the radial direction, something like a teardrop shape. Such marks significantly degrade signal quality, causing, for example, degraded signal linearity in the recorded signal, increased jitter during reproduction, mark remnants that are left when the marks are overwritten by direct overwrite recording, and signal crosstalk between tracks during reproduction.

Recording shorter marks and spaces is one means of increasing

recording density. A short space length, however, can result in therm interference. For example, heat at the trailing end of a recorded mark is transferred through the following space, which can then contribute to a temperature increase at the beginning of the following mark. Heat at the beginning end of one recorded mark can also transfer through the preceding space and affect the cooling process at the end of the preceding mark. A problem with thermal interference in conventional recording methods is that mark edge positions will vary, causing a higher error rate during reproduction.

To address the above-noted problems, Japanese Unexamined Patent Application Publication (*kokai*) 7-129959 (U.S. Patent numbers 5,490,126 and 5,636,194) teach a method for recording marks by segmenting that part of the recording signal corresponding to a mark in mark edge recording into start, middle, and end parts, the start and end parts each having a constant pulse width and the middle containing pulses of a constant period. This recording signal is then used to rapidly switch the output of a two-value laser.

With this method, the width of the middle part of a long mark is substantially constant and does not spread because laser output is driven with a constant period pulse current producing the minimum power required for mark formation. An increase in jitter at the leading and trailing edges of the mark can also be suppressed during direct overwrite recording because the laser beam is emitted with a constant pulse width at the leading and trailing ends of the mark.

It is also possible to detect whether marks, or spaces before and after a mark, are long or short, and change the position at which the start and end parts of a mark are recorded according to the length of the mark and the leading and trailing spaces. This makes it possible to compensate during recording for peak shifts caused by thermal interference whereby heat at the end of a recorded mark transfers through the following space and affects the

heating process at the beginning of the next mark, and heat at the beginning of a next recorded mark conversely travels back through the preceding space and affects the cooling process at the end of the preceding mark.

Kokai 7-129959 does not, however, teach a method for determining the optimum positions of the start and end parts of a mark, nor does it teach a specific structure and basis for changing or adjusting the start and end edge positions.

If such an optimum method and structure are not defined, the reliability of optimized recording will be low. Furthermore, even if optimized recording is achieved, it will be at the expense of excessive time spent searching for the optimum position and excessive circuit cost.

A method for changing the start and end edge positions of a mark based on the data being recorded has been invented as a means of achieving high density data recording. A problem with this method, however, is that the edge of a recorded mark can move due to thermal interference as described above. This edge movement phenomenon is also highly dependent upon the disk structure and the composition of the recording film, and if either of these change even slightly, optimized recording cannot be achieved.

Disclosure Of Invention

With consideration for the above described problems, an object of the present invention is therefore to provide a method for determining the optimum position of mark start and mark end parts.

A further object of the present invention is to provide a data recording medium wherewith optimized recording is possible even with disks of different types, including disk structure and recording film composition.

To achieve the above objects, a data recording medium according to the present invention has a plurality of tracks to which data is recorded by

controlling the lengths of marks and spaces remaining between consecuti marks. The marks are formed by changing the optical characteristics of th recording film in the track recording surface. More specifically, a mark start position Tu and mark end position Td are varied according to an input signal so that playback signal jitter is a predetermined constant value or less, and one or both of these adjusted start position Tu and end position Td values, or a typical value therefor, and the method for using these Tu and Td values, are prerecorded to a predetermined location on the data recording medium.

In a data recording medium according to the present invention, the mark start position Tu can be determined based on the length of the mark part of a recording signal and the space part immediately preceding the mark part. The mark end position Td can be similarly determined from the length of a mark part and the immediately following space part of a recording signal.

A data recording medium according to a first aspect of the present invention having a plurality of tracks for recording information represented as marks and spaces between the marks, the marks being formed by emitting to a track in the data recording medium an optical beam modulated by one or a plurality of drive pulses where a number of the drive pulses is adjusted according to a length of a mark part in the original signal to be recorded to the track, comprises: a data recording area for recording data, and a control information recording area for storing at least one of a first pulse position Tu value for determining a start position of a mark to be recorded, and a last pulse position Td value for determining an end position of a mark to be recorded.

It is therefore possible to achieve recording optimized for specific differences in disk structure and/or recording film composition by reproducing these adjustment values Tu and Td and using them to generate an optimized recording signal from which the marks and spaces are formed.

A data recording medium according to a second aspect of the

present invention more specifically determines the first pulse position Tu from the length of a mark part and the immediately preceding space part in the original signal, and determines the last pulse position Td from the length of a mark part and the immediately following space part in the original signal.

It is therefore possible to compensate during recording for the effects of heat accumulation and thermal interference during recording, and for equalizer distortion during reproduction, to achieve recording with little jitter.

A data recording medium according to a third aspect of the present invention yet further expresses the first pulse position Tu as a time difference TF between a first reference point R1, which is a leading edge of a mark part in the original signal to be recorded, and a first edge of the first pulse in a plurality of drive pulses, and expresses the last pulse position Td as a time difference TL between a second reference point R2, which has a specific known position relative to a trailing edge of a mark part in the original signal to be recorded, and a trailing edge of the last pulse in a plurality of drive pulses.

It is therefore possible to obtain mark start position Tu and mark end position Td more accurately.

In a data recording medium according to a fourth aspect of the present invention, the length of mark parts in the original signal and the length of space parts between the mark parts are further specifically expressed as a value NT where T is a reference period, and N is a positive integer from n1 to n2. Mark and space parts are further separated into a plurality of groups used for mark start and end position adjustment according to mark and space length; and specific first pulse position Tu and last pulse position Td values are set for each adjustment group.

Circuit scale can therefore be reduced by combining a plurality of mark lengths and space lengths into a single group. Recording with even less jitter can also be achieved by reducing the number of mark lengths and space

lengths in the group as the mark and space length decreases, and t increasing the number of groups as mark and space length decreases.

A data recording medium according to a fifth aspect of the presen invention further specifically separates mark parts by length into three groups, and separates space parts by length into three groups.

A data recording medium according to a sixth aspect of the present invention yet further separates mark parts by length into four groups, and separates space parts by length into four groups.

Recording with less jitter can thus be achieved by even more precisely separating mark and space lengths and further increasing the number of adjustment groups.

A data recording medium according to a seventh aspect of the present invention increases the number of adjustment groups as a length of the mark part and a length of the space part decreases.

Shorter marks and spaces occur more frequently, and by using a signal with a high frequency of occurrence as the reference signal for adjusting mark position, it is possible to record with less jitter compared with using a signal with a low frequency of occurrence as the reference signal.

In a data recording medium according to an eighth aspect of the present invention n1 is 3 and n2 is 11.

In a data recording medium according to a ninth aspect of the present invention, mark parts are separated by length into three groups of 3T, 4T, and 5T or longer marks, and space parts are separated by length into three groups of 3T, 4T, and 5T or longer spaces.

In a data recording medium according to a tenth aspect of the present invention, mark parts are separated by length into four groups of 3T, 4T, 5T, and 6T or longer marks, and space parts are separated by length into three groups of 3T, 4T, 5T, and 6T or longer spaces.

In a data recording medium according to an eleventh aspect of the present invention, there are two or more methods of using Tu and Td with a plurality of pulses, and information indicative of the method of use is prerecorded to the control information recording area.

In a data recording medium according to a twelfth aspect of the present invention, the method of Tu use uses Tu to change the rising edge position of a first drive pulse without changing the width thereof, and the method of Td use uses Td to change the falling edge position of a last drive pulse without changing the width thereof.

In a data recording medium according to a thirteenth aspect of the present invention, the method of Tu use uses Tu to change the width of a first drive pulse without changing the falling edge position thereof, and the method of Td use uses Td to change the width of a last drive pulse without changing the rising edge position thereof.

In a data recording medium according to a fourteenth aspect of the present invention, the information indicative of the method of Tu and Td use is recorded to a position before the position where the Tu and Td values are recorded referenced to the direction in which information is recorded.

A fifteenth aspect of the present invention relates to a method for obtaining a first pulse position Tu for a data recording medium having a plurality of tracks, marks formed by emitting to a track in the data recording medium an optical beam modulated by one or a plurality of drive pulses where a number of the drive pulses is determined according to a length of a mark part in the original signal to be recorded to the track, a data recording area for recording information using the marks and spaces between the marks, and a control information recording area having recorded thereto at least a first pulse position Tu value and a last pulse position Td value whereby at least a first pulse position Tu and a last pulse position Td of the drive pulse is changed so as to

make a reproduction jitter a specific value or less. This method comprises generating a pattern signal containing a pattern of consecutive mark parts with a specific length of PT and space parts with a specific length of QT where T is a reference period, P is a positive integer from n1 to n2, and Q is a positive integer from n1 to n2; storing the pattern signal; generating a plurality of drive pulses from the pattern signal; forming spaces and marks on the data recording medium by generating and emitting thereto an optical beam modulated according to the plurality of drive pulses; reproducing the marks and spaces recorded to the data recording medium; comparing and obtaining a difference between a combination of mark and space parts in the reproduced reproduction signal, and a combination of mark and space parts in the stored pattern signal; and obtaining from this difference a first pulse position Tu for application to an original signal containing a sequence of space parts of length QT and mark parts of length PT.

More specifically according to a sixteenth aspect of the present invention, first pulse position Tu is obtained for a plurality of combinations of mark lengths and space lengths by changing the values of P and Q.

More specifically according to a seventeenth aspect of the present invention, the pattern signal contains an adjustment signal for obtaining a DSV of 0.

An eighteenth aspect of the present invention relates to a method for obtaining a last pulse position Td for a data recording medium having a plurality of tracks, marks formed by emitting to a track in the data recording medium an optical beam modulated by one or a plurality of drive pulses where a number of the drive pulses is determined according to a length of a mark part in the original signal to be recorded to the track, and a control information recording area for recording information using the marks and spaces between the marks, and having recorded thereto at least a first pulse position Tu value

and a last pulse position Td value whereby at least a first pulse position Tu and a last pulse position Td of the drive pulse is changed so as to make a reproduction jitter a specific value or less. This method comprises: generating a pattern signal containing a pattern of consecutive mark parts with a specific length of PT and space parts with a specific length of QT where T is a reference period, P is a positive integer from n1 to n2, and Q is a positive integer from n1 to n2; storing the pattern signal; generating a plurality of drive pulses from the pattern signal; forming spaces and marks on the data recording medium by generating and emitting thereto an optical beam modulated according to the plurality of drive pulses; reproducing the marks and spaces recorded to the data recording medium; comparing and obtaining a difference between a combination of mark and space parts in the reproduced reproduction signal, and a combination of mark and space parts in the stored pattern signal; and obtaining from this difference a last pulse position Td for application to an original signal containing a sequence of space parts of length QT and mark parts of length PT.

It is therefore possible to accurately obtain mark start position Tu and mark end position Td using simple specific patterns with a short pattern length.

Yet further preferably according to a nineteenth aspect of the present invention, this method obtains last pulse position Td for a plurality of combinations of mark lengths and space lengths by changing P and Q.

Yet further preferably according to a twentieth aspect of the present invention, this method uses a pattern signal containing an adjustment signal for obtaining a DSV of 0.

A twenty-first aspect of the present invention relates to an apparatus for obtaining a first pulse position Tu for a data recording medium having a plurality of tracks, marks formed by emitting to a track in the data

recording medium an optical beam modulated by one or a plurality of driv pulses where a number of the drive pulses is determined according to a length of a mark part in the original signal to be recorded to the track, and a control information recording area for recording information using the marks and spaces between the marks, and having recorded thereto at least a first pulse position Tu value and a last pulse position Td value whereby at least a first pulse position Tu and a last pulse position Td of the drive pulse is changed so as to make a reproduction jitter a specific value or less. This apparatus comprises: means (125) for generating a pattern signal containing a pattern of consecutive mark parts with a specific length of PT and space parts with a specific length of QT where T is a reference period, P is a positive integer from n1 to n2, and Q is a positive integer from n1 to n2; means (120) for storing the pattern signal; means (111) for generating a plurality of drive pulses from the pattern signal; means (109, 103 — 106) for forming spaces and marks on the data recording medium by generating and emitting thereto an optical beam modulated according to the plurality of drive pulses; means (105 — 108, 112 — 115) for reproducing the marks and spaces recorded to the data recording medium; means (120) for comparing and obtaining a difference between a combination of mark and space parts in the reproduced reproduction signal, and a combination of mark and space parts in the stored pattern signal; and means (127) for obtaining from this difference a first pulse position Tu for an original signal containing a sequence of space parts of length QT and mark parts of length PT, and storing first pulse position Tu.

Further preferably according to a twenty-second aspect of the present invention, first pulse position Tu is obtained for a plurality of combinations of mark lengths and space lengths by changing P and Q.

Further preferably according to a twenty-third aspect of the present invention, the combinations are classified, and the reproducing means

comprises an equalizer (114), and the ratio between the output amplitude of the equalizer at the frequency of the longest mark and the output amplitude of the equalizer at the frequency of the shortest mark is 3 dB or less, provided that the longest mark and the shortest mark are from the same classification.

Distortion error by the equalizer during reproduction can therefore be reduced, and recording with less jitter can be achieved.

Yet further preferably according to a twenty-fourth aspect of the present invention, the pattern signal contains an adjustment signal for obtaining a DSV of 0.

A twenty-fifth aspect of the present invention relates to an apparatus for obtaining a last pulse position Td for a data recording medium having a plurality of tracks, marks formed by emitting to a track in the data recording medium an optical beam modulated by one or a plurality of drive pulses where a number of the drive pulses is determined according to a length of a mark part in the original signal to be recorded to the track, and a control information recording area for recording information using the marks and spaces between the marks, and having recorded thereto at least a first pulse position Tu value and a last pulse position Td value whereby at least a first pulse position Tu and a last pulse position Td of the drive pulse is changed so as to make a reproduction jitter a specific value or less. This apparatus comprises: means (125) for generating a pattern signal containing a pattern of consecutive mark parts with a specific length of PT and space parts with a specific length of QT where T is a reference period, P is a positive integer from n1 to n2, and Q is a positive integer from n1 to n2; means (120) for storing the pattern signal; means (110) for generating a plurality of drive pulses from the pattern signal; means (109, 103 — 106) for forming spaces and marks on the data recording medium by generating and emitting thereto an optical beam modulated according to the plurality of drive pulses; means (105 — 108, 112 —

115) for reproducing the marks and spaces recorded to the data recording medium; means (120) for comparing and obtaining a difference between a combination of mark and space parts in the reproduced reproduction signal, and a combination of mark and space parts in the stored pattern signal; and means (127) for obtaining from this difference a last pulse position Td for an original signal containing a sequence of space parts of length QT and mark parts of length PT, and storing last pulse position Td.

Further preferably according to a twenty-sixth aspect of the present invention, first pulse position Tu is obtained for a plurality of combinations of mark lengths and space lengths by changing P and Q.

Further preferably according to a twenty-seventh aspect of the present invention, the combinations are classified, and the reproducing means comprises an equalizer (114), and the ratio between the output amplitude of the equalizer at the frequency of the longest mark and the output amplitude of the equalizer at the frequency of the shortest mark is 3 dB or less, provided that the longest mark and the shortest mark are from the same classification.

Further preferably according to a twenty-eighth aspect of the present invention, the pattern signal contains an adjustment signal for obtaining a DSV of 0.

A twenty-ninth aspect of the present invention relates to a recording and reproducing apparatus for recording and reproducing a data recording medium having a plurality of tracks, marks formed by emitting to a track in the data recording medium an optical beam modulated by one or a plurality of drive pulses where a number of the drive pulses is determined according to a length of a mark part in the original signal to be recorded to the track, and a control information recording area for recording information using the marks and spaces between the marks, and having recorded thereto at least a first pulse position Tu value and a last pulse position Td value whereby at

least a first pulse position Tu and a last pulse position Td of the drive pulse is changed so as to make a reproduction jitter a specific value or less. This recording and reproducing apparatus comprises: means (1505 — 1508, 1512 — 1517) for reproducing a first pulse position Tu and a last pulse position Td prerecorded to the data recording medium; means (1520) for storing the reproduced first pulse position Tu and last pulse position Td; means (1510) for generating a drive pulse based on a data recording signal, and correcting the generated drive pulse based on the first pulse position Tu and last pulse position Td; means (109, 103 — 106) for emitting an optical beam based on the corrected drive pulses to form spaces and marks on the data recording medium.

Further preferably according to a thirtieth aspect of the present invention, the reproducing means comprises an equalizer (1514), and the ratio between the output amplitude of the equalizer at the frequency of the longest mark and the output amplitude of the equalizer at the frequency of the shortest mark is 3 dB or less.

A thirty-first aspect of the present invention relates to a manufacturing apparatus for manufacturing a data recording medium having a plurality of tracks, marks formed by emitting to a track in the data recording medium an optical beam modulated by one or a plurality of drive pulses where a number of the drive pulses is determined according to a length of a mark part in the original signal to be recorded to the track, and a control information recording area for recording information using the marks and spaces between the marks, and having recorded thereto at least one of a first pulse position Tu value and a last pulse position Td value whereby at least one of a first pulse position Tu and a last pulse position Td of the drive pulse is changed so as to make a reproduction jitter a specific value or less. This apparatus comprises: means (2701) for storing previously obtained first pulse position Tu and last pulse position Td values for a drive pulse sequence; adjustment method

information storage (2702) for storing information indicative of a pulse position adjustment method; means (2703) for converting the adjustment method information, first drive pulse position Tu, and last drive pulse position Td to a signal for recording, and generating a recording signal; and laser generating means (2704, 2705, 2706) for generating a laser beam based on the recording signal.

Other objects and attainments together with a fuller understanding of the invention will become apparent and appreciated by referring to the following description and claims taken in conjunction with the accompanying drawings.

Brief Description Of Drawings

Fig. 1 is a block diagram of an optical data recording device according to a first embodiment of the present invention;

Fig. 2 illustrates signals used in the first embodiment shown in Fig. 1;

Fig. 3 illustrates recording pulse sequences in the first embodiment shown in Fig. 1;

Figs. 4A and 4B show exemplary pulse movement tables in the first embodiment shown in Fig. 1;

Fig. 5 is used to describe a grouping method in the first embodiment shown in Fig. 1;

Fig. 6 is used to describe a grouping method in the first embodiment shown in Fig. 1;

Fig. 7 is used to describe a grouping method in the first embodiment shown in Fig. 1;

Fig. 8 is used to describe a grouping method in the first embodiment shown in Fig. 1;

Fig. 9 is used to describe a grouping method in the first embodiment shown in Fig. 1;

Fig. 10 is a frequency characteristic diagram for a reproduction equalizer in the first embodiment shown in Fig. 1;

Fig. 11 illustrates signals used in the first embodiment shown in Fig. 1;

Fig. 12 illustrates signals used in the first embodiment shown in Fig. 1;

Fig. 13 illustrates signals used in the first embodiment shown in Fig. 1;

Fig. 14 illustrates signals used in the first embodiment shown in Fig. 1;

Fig. 15 is a block diagram of an optical data recording device according to a second embodiment of the present invention;

Fig. 16 is a plan view of a data recording medium in the second embodiment shown in Fig. 15;

Fig. 17 illustrates signals used in the second embodiment shown in Fig. 15;

Fig. 18 illustrates recording pulse sequences in the second embodiment shown in Fig. 15;

Fig. 19 shows exemplary pulse movement tables in the second embodiment shown in Fig. 15;

Fig. 20 is a waveform diagram for describing first pulse movement according to the present invention;

Fig. 21 is a waveform diagram for describing last pulse movement according to the present invention;

Fig. 22 is a waveform diagram for describing first pulse width adjustment according to the present invention;

Fig. 23 is a waveform diagram for describing last pulse width adjustment according to the present invention;

Fig. 24 shows alternative pulse movement tables according to the present invention;

Fig. 25 is a plan view of a data recording medium according to the present invention;

Fig. 26 is a plan view of a further data recording medium according to the present invention;

Fig. 27 is a block diagram of a system for cutting an optical disk master according to the present invention; and

Fig. 28 illustrates signals used in the first embodiment shown in Fig. 1.

Best Mode for Carrying Out the Invention

The preferred embodiments of the present invention are described below with reference to the accompanying figures.

An optical data recording method according to a preferred embodiment of the present invention is described next below with reference to the accompanying figures. Fig. 1 is a block diagram of an optical data recorder according to a first preferred embodiment of the present invention. It is to be noted that this optical data recorder is used primarily by manufacturers and other commercial users for manufacturing optical disks.

Shown in Fig. 1 are: an optical disk 101 having a plurality of concentric or spiral tracks, spindle motor 102, semiconductor laser 103, collimator lens 104, beam splitter 105, objective lens 106, collective lens 107, photodetector 108, laser drive circuit 109, pulse moving circuit 110, delay circuits 128 and 129 each having the same delay time, pulse generator 111, preamp 112, low pass filter 113, reproduction equalizer 114, digitizing circuit

115, PLL 116, demodulation and error correction circuit 117, reproduction data signal 118, power setting circuit 119, pulse position offset measuring circuit 120, switch 121, switch contacts 122, 123, and 124, pattern signal generator 125, bus 126 connecting pulse position offset measuring circuit 120 and pulse moving circuit 110, and memory 127 for storing a table recording pulse movement information.

Memory 127 stores the two tables shown in Fig. 4B. These two tables are modified by the method of the present invention, and are then rewritten as the two tables shown in Fig. 4A.

The optical data recorder shown in Fig. 1 is for generating a table such as shown in Fig. 4A. The table shown in Fig. 4A and generated by the recorder shown in Fig. 1 is then transferred to memory in another recording device such as shown in Fig. 27, and is recorded to a predetermined recording area on all manufactured optical disks.

It is to be noted that the optical head of the optical data recorder shown in Fig. 1 comprises the semiconductor laser 103, collimator lens 104, beam splitter 105, objective lens 106, collective lens 107, and photodetector 108. When an optical disk 101 is loaded to the optical data recorder, the optical head moves to an area used for determining the optimum positions for the start position and end position of each mark.

This area for determining the optimum start and end positions is an area at the inside circumference area or outside circumference area of the disk, and is outside of the user data recording area. An exemplary area is the drive test zone of the disk. Switch 121 switches contact 122 to contact 123 at this time.

It is to be noted that if limited specifically to recording devices used by a manufacturer of optical disks, this area for determining the optimum start and end positions can be the user data area.

The power setting circuit 119 sets the laser drive circuit 109 to either peak power or bias power. At this time the output signal from pattern signal generator 125 is passed by switch 121 to the pulse generator 111. Signal flow from the pulse generator 111 is described further below with reference to Fig. 2.

Shown in Fig. 2 are a first pattern signal 201, which is the output signal from the pattern signal generator 125; output signal 202 from the pulse generator 111; output signal 203 from the pulse moving circuit 110; and mark pattern 204 formed in the recording track of the optical disk 101 as a result of modulating laser power output between peak power and bias power levels according to output signal 203. It is to be noted that while signals 201, 202, and 203 are not generated on the same time base, for convenience they are shown with corresponding parts in each signal aligned vertically.

In first pattern signal 201, mark parts 209, 211, 213, 215, 217, and 219 are the parts of the signal whereby a mark is to be formed on the disk, and space parts 210, 212, 214, 216, 218, and 220 are the parts of the signal that appear as a space on disk. It is further assumed below that mark part 209 follows space part 220 such that first pattern signal 201 comprises a repeating pattern of parts 209 to 220.

For example, when data generated by (2,10) run-length limited modulation is recorded using a mark edge recording method, the marks and spaces have a shortest length of 3T and a longest length of 11T where T is the reference period. Mark part 209 is a 6T signal (a 6T mark part below), space part 210 is a 6T space, 211 is a 3T mark, 212 is a 6T space, 213 is a 6T mark, 214 is a 6T space, 215 is a 6T mark, 216 is a 4T space, 217 is a 6T mark, 218 is a 6T space, 219 is a 7T mark, and 220 is a 6T space.

Note that if DSV is the difference of the sum of mark and space lengths in a specific period, a reproduction signal with a small dc component or

low frequency component can be obtained when the marks and spaces are reproduced by inserting signals 219 and 220 whereby a DSV of substantially zero can be obtained. Reproducing a signal with many dc components or low frequency components can result in the digitizing circuit 115 erroneously generating a signal with the wrong sequence of 0s and 1s.

To prevent this, a 7T mark part 219 and 6T space part 220 are inserted to the first pattern signal 201 as a compensation signal assuring that the DSV is substantially 0. More specifically, first pattern signal 201 is generated so that the sum (34T) of the periods of mark parts 209, 211, 213, 215, 217, and 219 is equal to the sum (34T) of the space parts 210, 212, 214, 216, 218, and 220. DSV is calculated by adding the periods of the mark parts as positive values and the periods of the space parts as negative values. As a result, the DSV of first pattern signal 201 is 0.

This first pattern signal 201 is converted to a pulse sequence by the pulse generator 111, resulting in pulse generator output signal 202. Pulse output from the pulse generator 111 corresponding to marks of lengths from 3T to 11T is shown in Fig. 3.

Referring by way of example to a 6T signal in Fig. 3, the pulse at the start of the signal is referred to as the first pulse 301, and the pulse at the end of the signal is the last pulse 304. The pulses between the first pulse 301 and last pulse 304 are referred to as multiple pulses 302 and have a constant period.

In a 6T mark there are two multiple pulses 302, in a 7T mark there are three, and in a 5T mark there is one. It will thus be obvious that the number of multiple pulses 302 between the first and last pulses increases by one with each 1T increase in signal length, and decreases one with each 1T decrease in signal length. A 4T mark, therefore comprises only the first and last pulses, and has no multiple pulses 302 therebetween. In addition, a 3T mark comprises just

one pulse.

It is to be noted that in this preferred embodiment the time-base length of the first pulse is 1.5T, the last pulse is 0.5T, and the length of the multiple pulses is also 0.5T. The invention shall not be so limited, however, and the length, count, or period of these pulses can be varied as necessary according to the structure of the optical disk 101.

As noted above, first pattern signal 201 and pulse generator output signal 202 are not on the same time base. However, the difference between the leading edge of first pattern signal 201 and the leading edge of the first pulse of the pulse generator output signal 202 is the same for any particular mark parts, and the difference between the trailing edge of the first pattern signal 201 and the trailing edge of the last pulse of pulse generator output signal 202 is also the same for any particular mark parts.

The pulse generator output signal 202 is input to the pulse moving circuit 110, which generates and outputs a signal 203 in which the positions of the first pulse and last pulse are moved. Figs. 4A and 4B shows the combinations of marks and spaces used for shifting the first pulse and last pulse positions.

Fig. 4A shows the pulse movement tables after correction by the method of this present invention, and Fig. 4B shows the tables before correction. Symbols 3S3M, 4S3M, and so forth in the tables in Fig. 4B are a type of address, and are indicative of the signal type as well as the value written to that address. When read as an address, the value 3S3M, for example, represents a signal in which a 3T mark follows a 3T space. As will be described more fully below, the value of the first pulse movement TF stored at the place indicated by 3S3M is the movement required when a 3T mark follows a 3T space.

These first pulse movement TF values are obtained by, for

example, a trial and error process using a particular optical test disk, and the resulting values are compiled in the tables in Fig. 4A. The content of the completed table is stored for all optical disks having the same structure as the optical test disk. Predetermined initial values are stored in the table on the left in Fig. 4A for the first pulse. The table on the right in Fig. 4B stores the initial values before correcting the last pulse movement.

The position of the first pulse changes according to the length of the mark and the immediately preceding space. In this preferred embodiment, the marks and spaces are separated into three groups, that is, 3T, 4T, and 5T or longer. A total of nine different last pulse positions are therefore defined.

Fig. 20 is an enlarged view of the 6T mark 217 in the first pattern signal 201 shown in Fig. 2, and the corresponding part in the pulse generator output signal 202. As shown in the figure, a 4T space 212 is immediately before the 6T mark 217. A 4T space followed by a 6T mark belongs to the 4S5M group in the left table in Fig. 4A. Correcting the initial first pulse movement TF stored for this group is described below.

The pattern signal generator 125 in the optical data recorder shown in Fig. 1 generates a first pattern signal 201. This first pattern signal 201 is sent to the pulse generator 111, delay circuit 129, pulse position offset measuring circuit 120, and memory 127. As noted above, the two tables shown in Fig. 4B are prestored to memory 127. The pulse position offset measuring circuit 120 also stores the first pattern signal 201, which is used for comparison with the reproduction signal during data reproduction. The pulse generator 111 generates the output signal 202 required for recording the pattern signal. Referring to the signals shown on the top two rows in Fig. 3, for example, the pulse generator 111 generates a first pulse 301 corresponding to the rising edge of the mark in the first pattern signal 201, then outputs multiple pulses 302, and last pulse 304.

The pulse generator output signal 202 is delayed a predetermined period by the delay circuit 128, and then passed to the pulse moving circuit 110. This predetermined delay period is 13T in this exemplary embodiment. The first pattern signal 201 is analyzed in memory 127 to determine to which of the 18 signal groups, that is, 3S3M, 3S4M, 3S5M, 4S3M, 4S4M, 4S5M, 5S3M, 5S4M, 5S5M, 3M3S, 4M3S, 5M3S, 3M4S, 4M4S, 5M4S, 3M5S, 4M5S, and 5M5S, the signal in the preceding 10T or longer period belongs. For example, if a 4T space 216 is followed by a 6T mark 217 in the first pattern signal 201 from the pattern signal generator 125, memory 127 detects that the signal belongs to the 4S5M group. In response to this determination, memory 127 then reads and outputs to the pulse moving circuit 110 the amount of movement stored in the table at 4S5M0. The initial 4S5M0 movement value is read from the table the first time a movement value is read. The pulse moving circuit 110 then moves the first pulse of the pulse generator output signal 202 supplied thereto after a predetermined delay based on the initial movement value read from 4S5M0.

Movement of the first pulse is described in further detail below with reference to Fig. 1 and Fig. 20. When the pulse moving circuit 110 is notified by memory 127 that a pattern belonging to a specific group will soon arrive from the delay circuit 129, it also receives the first pulse movement TF for that pattern from the memory 127. For example, when the memory 127 informs the pulse moving circuit 110 that a pattern belonging to the 4S5M group, that is, a 4T space 216 following by a 6T mark 217, will arrive from the delay circuit 129, it also sends the first pulse movement TF read for the 4S5M0 group. The pulse moving circuit 110 then begins counting first pulse movement TF at the rising pulse edge of the 6T mark 217 received from the delay circuit 129, that is, at time R1 in Fig. 20. Output of the first pulse from the delay circuit 128 is delayed for the period counted by the pulse moving circuit 110, that is, for pulse movement TF1.

When pulse movement is referenced to the rising edge R1 of the first pattern signal 201, for example, first pulse movement TF1 is expressed as the time difference from reference time R1 as shown in Fig. 20. In this exemplary embodiment, pulse movement TF is approximately 3 ns. It is to be noted that the first pulse is moved without changing the pulse width.

The pattern signal shown in Fig. 2 contains signal components belonging to four of the 18 groups in the table shown in Fig. 4A: type 3M5S in period 221, type 5S3M in period 222, type 4S5M in period 223, and type 5M4S in period 224. Each of the pulse signal components corresponding to these four types in first pattern signal 201 are therefore moved.

The laser is therefore driven according to these moved pulses to record the actual marks. The resulting marks 204 are shown in Fig. 2. In a preferred embodiment of the present invention, the first pattern signal 201 comprising elements 209 to 220 as shown in Fig. 2 is output repeatedly and recorded around one track. When recording one complete track is thus completed, the track is reproduced. As will be described more fully below, reproduction includes converting an optical signal from the photodetector 108 to an electrical signal, and then processing this electrical signal with preamp 112, low pass filter 113, reproduction equalizer 114, and digitizing circuit 115 to obtain reproduction signal 205. The reproduction signal 205 is input to pulse position offset measuring circuit 120. The reproduction signal 205 from a single track is thus input repeatedly to the pulse position offset measuring circuit 120. The pulse position offset measuring circuit 120 thus reads each of the periods 221, 222, 223, and 224 associated with different signal types multiple times, and calculates the average for each period.

The pulse position offset measuring circuit 120 compares the periods 221, 222, 223, 224 corresponding to the types obtained in the recorded first pattern signal 201 during recording, and the averages for the same periods

obtained from the reproduction signal 205 to detect whether any shifting in pulse position has occurred. Using by way of example the signals recorded and reproduced as described above, the combined time of the 4T space 216 and 6T mark 217 in the first pattern signal 201 is compared with the average obtained for the corresponding period 224 in the reproduction signal 205, and the difference therebetween is obtained. If there is a difference, the pulse position offset measuring circuit 120 determines that the pulse position shifted, and the calculated difference is therefore sent to memory 127. Because this difference is the result of the initial movement value 4S5M0, this initial movement value 4S5M0 is increased or decreased in memory 127 according to the difference, thereby correcting the stored movement value. This corrected value is then overwritten to type 4S5M.

It is to be noted that the stored movement value is corrected and overwritten to 4S5M using a single feedback loop (through 110, 109, 108, 112, 115, 120, 126) in the above exemplary embodiment. It will be obvious, however, that a plurality of feedback loops can be alternatively used to correct the value of the first pulse movement TF as shown in Fig. 20.

Movement of the last pulse position is similarly corrected. That is, last pulse position movement changes according to the mark length and the length of the following space. In this exemplary embodiment marks and spaces are separated into three groups based on length, 3T, 4T, and 5T or longer, and pulse position movement is defined for each of the nine possible mark/space combinations. The last pulse movement TL is then calculated using the same method used to calculate first pulse movement TF.

Fig. 21 is an enlarged view of the part of the pulse generator output signal 202 corresponding to the 6T mark 215 in the first pattern signal 201 shown in Fig. 2. The last pulse movement TL is corrected in the same manner as the first pulse movement TF described above. In the case of the last

pulse movement TL, however, the period from time reference R2 offset 2T forward of the trailing edge of the mark to the trailing edge of the last pulse is called the time interval, and this time interval is corrected by means of the loop described above with reference to the first pulse. The last pulse movement TL is approximately 13 ns in this exemplary embodiment. It is to be also noted that the width of the last pulse does not change even though the amount of last pulse movement TL changes, and in this exemplary embodiment the pulse width remains the same with the pulse simply shifted on the time axis.

The output signal 206 from the pulse moving circuit 110 obtained using the corrected pulse movement tables shown in Fig. 4A, the marks 207 recorded as a result of this output signal 206, and the reproduction signal 208 reproduced from these marks 207, are also shown in Fig. 2. While the reproduction signal 205 obtained using the original, uncorrected pulse movement table (Fig. 4B) is not identical to the original pattern signal 201, there is substantially no difference between the reproduction signal 208 obtained using the corrected pulse movement table (Fig. 4A) and the original pattern signal 201.

It is to be noted that four of the eighteen pulse movement values are corrected as described above using the first pattern signal 201 shown in Fig. 2. The other values are similarly corrected using other pattern signals. More specifically, types 4M5S, 5S4M, 3S5M, and 5M3S are corrected using a pattern signal 1101 as shown in Fig. 11; types 4M4S, 3M3S, 4S4M, 3S3M are corrected using a pattern signal 1201 as shown in Fig. 12; types 4M3S, 4S3M are corrected using a pattern signal 1301 as shown in Fig. 13; types 3M4S, 3S4M are corrected using a pattern signal 1401 as shown in Fig. 14.

It is to be noted that types 5M5S and 5S5M can be corrected using a pattern signal 2801 as shown in Fig. 28, or a default value therefor can be simply defined. It is to be noted that types 5M5S and 5S5M are preferably

corrected before the other types. This is because these marks and spaces have the longest period and are therefore least affected by thermal interference. The delay period is therefore small, and can be used as a reference value for determining the other delay periods.

The signal types used for changing the movement of the first pulse and last pulse are determined based on the three major factors described below.

The first factor is the effect of heat accumulation in the recording film when marks are recorded, the amount of thermal interference, and the difference in the amount of thermal interference resulting from the specific mark/space combination. Note that as described above thermal interference refers to the process whereby heat at the end of a recorded mark transfers through the following space and affects the heating process at the beginning of the next mark, and heat at the beginning of a next recorded mark conversely travels back through the preceding space and affects the cooling process at the end of the preceding mark.

The affects of heat accumulation in the recording film can be reduced by inserting a plurality of multiple pulses between the first and last pulses, and emitting a laser beam of the lowest power level required for mark formation. These heat accumulation effects cannot be completely eliminated, however, because the multiple pulses are formed with a constant period in order to simplify the pulse generator 111.

The extent of the effect of heat accumulation and thermal interference is also dependent upon numerous factors, including the structure of the optical disk 101, properties of the recording film, recording pulse, the linear speed used for recording to optical disk 101, and the length of the shortest mark. The effect of heat accumulation and thermal interference can also be attenuated to a certain degree by optimizing each of these influencing

factors. To more fully understand this, let us focus on how the effects of heat accumulation and thermal interference vary with different combinations of marks and spaces.

As will be known from Fig. 4A, each first pulse is classified as one of nine types or groups, which are used for determining the movement of the first and last pulses. A method for determining which of these nine types to use based on the above-noted first factor is described next below with reference to Fig. 5 to Fig. 9. Fig. 5 shows a method for determining the dependency of the elongation of the starting position of an 11T mark on the space preceding the 11T mark.

Shown in Fig. 5 are the original signal 500, that is, the two-value waveform of the signal used for recording; marks 501 recorded to the data recording medium; and reproduction signal 502, that is, the two-value waveform of the signal reproduced from the marks 501 recorded to the disk. Original signal 500, marks 501, and reproduction signal 502 are the result of recording marks with a space (S x T) sufficiently long for an 11T mark recorded between the marks. Intersymbol interference is thus minimized as a result of this sufficiently long space.

It is to be noted that space ts1 in the original signal 500 is ideally equal to the time interval of space tm11 in the reproduction signal 502. The positions of the first and last pulses are moved to more closely approach this ideal. If the position of the mark start position only is considered when determining how much to move the marks, the first and last pulses can be categorized into approximately three groups. A method for determining the mark start position group is described more fully below with reference to original signal 520, marks 521, and reproduction signal 522 below.

The original signal 520 is the two-value waveform used for recording. In this case, however, the space ts21 between the two 11T marks is

shorter than that shown in the above original signal 500. As a result, heat at the trailing end of 11T mark 524 transfers through space 525 to the next 11T mark 526, thus accelerating the start of 11T mark 526. The nominal length of 11T mark 526 is thus increased by length a2.

As a result, the time interval of space ts31 in reproduction signal 522 corresponding to space ts21 in the original signal 520 is shortened, and the correct reproduction signal cannot be obtained. A correct reproduction signal can be obtained, however, by predicting the elongation at the start of 11T mark 526, and delaying the rising edge of the mark part tm22 in the original signal 520. The specific delay depends on the length of the space ts21. The length of the space ts21 is therefore varied for each time T from 3T to 11T, an 11T mark is recorded for each space ts21, and edge distance 527 is measured for each case.

The results of these measurements are graphed in Fig. 6. The horizontal axis shows the length 3T to 11T of each space ts21 in original signal 520, and the vertical axis shows the difference of the combined length of mark part tm20 and space part ts21 in the original signal 520 minus the edge distance r 527. As space length decreases, the point at which 11T mark 526 starts moves forward, that is, closer to the preceding pulse, due to thermal interference when the space is short, such as 3T or 4T.

Fig. 7 shows one way of combining spaces of substantially the same length into common groups based on the values shown on the vertical axis in Fig. 6. Spaces of substantially different length are placed in separate groups. This method produces three groups: 3T spaces, 4T spaces, and spaces of 5T or longer.

These results and groups are further mapped in Fig. 8. Shaded cells indicate space/mark combinations for which measurements have been obtained. Bold lines indicate the groups.

As described with reference to Fig. 5, elongation at the start of an 11T mark varies according to the length of the immediately preceding space, and can be separated into the above three groups, 3T, 4T, and 5T or longer.

Fig. 9 shows the results of the evaluation described above with reference to Fig. 5 to Fig. 8 performed for all rows and columns. It will be known from Fig. 9 that both marks and spaces are preferably separated into the above three or more groups, 3T, 4T, and 5T or longer, for determining first pulse movement.

Last pulse movement varies according to the mark length and immediately following space. For the same reasons that apply to the first pulse, last pulse movement is preferably determined based on the same three or more groupings, that is, 3T, 4T, and 5T or longer, of marks and spaces described above.

It is to be noted that when measurement results are substantially equal, such as from 5T to 11T, in adjacent cells in the maps shown in Fig. 9, those cells are grouped together. This makes it possible to reduce the scale of the pulse moving circuit 110.

As will be known from the above description, by focusing on the difference in size resulting from specific mark/space combinations, and placing combinations where the space length is 3T or 4T into a group separate from combinations where the space length is 5T or longer, this preferred embodiment of the invention can control first pulse movement and last pulse movement according to the mark/space pattern, and can thereby achieve recording with little jitter.

In addition, by focusing on the difference in size resulting from specific mark/space combinations, and placing combinations having a space length of 3T and combinations having a space length of 4T into separate groups, this preferred embodiment of the invention can control first pulse

movement and last pulse movement according to the mark/space pattern.

The properties of the reproduction equalizer 114 are a second factor. Reproduction equalizer 114 properties depend on such factors as the beam spot size and shortest mark length. The beam spot size is determined by the wavelength of the semiconductor laser 103 and the aperture of the objective lens 106.

A method of grouping marks and spaces in order to change first pulse movement and last pulse movement due to this second factor is described next below with reference to Fig. 10.

Fig. 10 is a typical graph of the frequency characteristic of the reproduction equalizer 114. This shows the amplitude ratio of the equalizer output signal to the input signal; signal frequency is shown on the horizontal axis, and output amplitude is shown on a logarithmic scale on the vertical axis. The frequency of 3T, 4T, 5T, and 11T signals is shown along the horizontal axis. Note that the frequency of a 3T signal is high, the marks recorded and reproduced for a 3T signal are therefore small, and the amplitude of the reproduced optical signal is therefore low. Equalizer characteristics are therefore set to increase the output amplitude to compensate for this attenuation of the optical frequency characteristic. This can be accomplished by using a high pass filter or a bandpass filter with a peak at a frequency slightly higher than 3T, with or without an amplifier used in combination.

The slope of the curve, that is, the difference in the output amplitude of a high frequency signal in which mark or space length is 3T, and the output amplitude of a low frequency signal in which mark or space length is 11T, increases as the shortest mark length decreases. As a result, the difference between, for example, the output amplitude at a frequency of 5T and the output amplitude at a frequency of 11T, also increases.

If marks for which the difference in output amplitude is great are

included in the same group when separating the marks for changing first and last pulse movement, reproduction equalizer 114 properties prevent correct edge position reproduction even if the first and last pulses are recorded to specifically eliminate the effects of heat accumulation in the recording film and thermal interference.

It is therefore preferable for the difference in the output amplitude characteristic of the reproduction equalizer 114 to be as small as possible for all marks in the same group.

It is further preferable for the ratio between the output amplitude of the reproduction equalizer 114 at the frequency of the longest mark to the output amplitude of the reproduction equalizer 114 at the frequency of the shortest mark in the plurality of marks in the same group to be 3 dB or less. This value, 3 dB or the square root of 2, is relatively commonly used when working with frequency characteristics. In other words, when signals of any frequency but with the same amplitude the amplitude difference between the input signal and output signal of the equalizer is

In other words, regardless of frequency, when signals of the same amplitude are input, the amplitude ratio of the input signal and output signal from the equalizer will always be a difference equal to the square root of 2. By controlling the output amplitude ratio to 3 dB or less as a threshold value for grouping signals together as in this preferred embodiment of the invention, distortion error introduced by the equalizer during reproduction is reduced, and recording and reproducing with less jitter can be achieved.

It is to be noted that in mark edge recording using a semiconductor laser 103 with a 650 nm wavelength, an objective lens 106 with an aperture of 0.6, a shortest mark length of 0.595 μm, and (2,10) run-length limited modulation, marks shorter than 5T, that is, 3T and 4T marks, are preferably not included in the same group as 11T marks. Further considering

the size of the pulse moving circuit 110, 5T and longer marks, or 6T and longer marks, are preferably included in the same group. In this exemplary embodiment, T is approximately 30 ns, 3T is approximately 90 ns, and 11T is approximately 330 ns.

A third factor is the scale of the pulse moving circuit 110 and the desired precision with which pulse movement is determined, and the limited scale of the pattern signal generator 125 and memory 127.

Based on the above described first and second factors, marks or spaces with a great difference in heat accumulation or thermal interference are placed into different groups, and marks resulting in a significantly different output amplitude from the reproduction equalizer are also placed in different groups. However, the number of storage registers increases as the number of groups increases, and this increases the scale of the pulse moving circuit 110. In addition, if the number of registers is increased, the number of patterns used for determining the values stored to the registers also increases, and the scale of the pattern signal generator 125 therefore also increases. Yet further, the time required to set the registers increases whether the register values are set at the factory or by the end user, and the recording track space required for setting the registers also increases.

It is therefore desirable to minimize the number of groups used for determining first and last pulse movement.

By grouping marks of 5T and longer in the same group as described according to this preferred embodiment, the scale of the pulse moving circuit 110, and the scale of the pattern signal generator 125, can both be minimized.

Although determining the optimum grouping of marks and spaces is affected by several factors, the three factors described above are considered in particular to determine the group types shown in Fig. 4A in the present

embodiment.

It is to be noted that a predetermined initial value is set as shown in Fig. 4B before pattern signal recording. These initial values can be separately determined from experience, or they can be all set to the same value. If the same initial value is used for all, the value, for example, 1 ns, stored for the first pulse movement in a 5S5M pattern in the left table in Fig. 4B, for example, is preferably stored for all patterns. In the case of the right table in Fig. 4B, the value stored for 5M5S is used. Note, further, that in this case the value set for the 5S5M pattern is determined so that the time between first pulse 301 and multiple pulses 302 is 0.5T as shown in Fig. 3, and the value set for 5M5S is determined so that the time between multiple pulses 302 and last pulse 304 is 0.5T.

It will also be obvious that the values set for 5S5M and 5M5S can also be determined using other methods. An example is shown in Fig. 28.

As shown in Fig. 28, the pattern signal 2801 of the pattern signal generator 125 in this example has a single period of 6T. Also shown are output signal 2802 from the pulse generator 111; output signal 2803 from the pulse moving circuit 110; and marks 2804 formed in the recording track of the optical disk 101 as a result of modulating laser power output between peak power and bias power levels according to output signal 2803. It is to be noted that while signals 2801, 2802, and 2803 are not generated on the same time base, for convenience they are shown with corresponding parts in each signal aligned vertically.

The pattern signal 2801 in this case represents marks and spaces with a simply repeating 6T period, and thus contains typs 5S5M and 5M5S of the eighteen pattern types shown in Fig. 4A. The laser is then driven based on drive signal 2803 in Fig. 28 to record the marks 2804. In this exemplary embodiment, pattern signal 2801 in Fig. 28 is repeatedly recorded around one

complete circumference of the recording track. When this track is recorded, it is then reproduced. Reproduction includes converting an optical signal from the photodetector 108 to an electrical signal, and then processing this electrical signal with preamp 112, low pass filter 113, and reproduction equalizer 114. The reproduction signal 2805 from the reproduction equalizer 114 is applied to asymmetry measuring circuit 130 and digitizing circuit 115. The digitizing circuit 115 adjusts the slice level signal 2809 so that the output level corresponding to a mark and the output level corresponding to a space in the output signal of the digitizing circuit are at equal intervals, and applies this slice level signal 2809 to the asymmetry measuring circuit 130.

The asymmetry measuring circuit 130 compares the average of the high 2811 and low 2810 peak values of the reproduction signal 2805 with the slice level signal 2809. When the difference therebetween is a predefined level or greater, the lengths of the marks 2804 and spaces are not equal. This difference is attributable to a shift in the first pulse and last pulse positions. Initial movement values 5S5M0 and 5M5S0 are therefore corrected according to the sign of the difference so that, for example, the first pulse and last pulse each move the same time-base distance in opposite directions. The corrected values are then overwritten to memory 127.

It is to be noted that the stored movement values are corrected and overwritten to 5M5S and 5S5M using a single feedback loop (through 110, 109, 108, 112, 115, 120, 126) in the above exemplary embodiment. It will be obvious, however, that a plurality of feedback loops can be alternatively used. As a result, 5S5M and 5M5S values whereby 6T marks can be recorded at the correct length can be obtained. By thus correcting the physical length of a mark used as a reference, marks in other groups can also be recorded at the correct length, and recording with less jitter can be achieved.

The output signal 203 from the pulse moving circuit 110 is input to

the laser drive circuit 109 whereby laser power is modulated so that the laser emits at peak power while output signal 203 is high, and emits at bias power while the signal is low, to form a mark sequence 204 as shown in Fig. 2.

During reproduction, the collimator lens 104 converts the laser beam emitted from the semiconductor laser 103 to parallel light, which is then incident on the beam splitter 105. Light passing the beam splitter 105 is focused to a light spot by the objective lens 106, and emitted to the optical disk 101.

Light reflected from the optical disk 101 is then collected by the objective lens 106, and passed back to the beam splitter 105. Light reflected by the beam splitter 105 is collected by collective lens 107, and focused on photodetector 108.

The photodetector 108 converts light incident thereon to an electrical signal, which is then amplified by the preamp 112. The output signal from the preamp 112 is then passed through the low pass filter 113 whereby high frequency signal components are blocked. The reproduction equalizer 114 then equalizes the signal, which is next binarized by the digitizing circuit 115 using a predetermined slice level. A reproduction signal 205 converted to a sequence of 0s and 1s is thus output from the digitizing circuit 115 to the pulse position offset measuring circuit 120. The pulse position offset measuring circuit 120 measures the specific edge intervals 221, 222, 223, and 224 in the reproduction signal 205.

If the measured edge interval 221 in Fig. 2 is longer than the normal 9T interval, the setting for last pulse movement 3M5S in Fig. 4A is reduced by the difference between the measured interval 221 and the normal 9T interval from the current setting of 3M5S0 by way of bus 126. The setting for first pulse movement 5S3M in Fig. 4A is similarly increased from the current 5S5M0 setting by the difference between the edge interval 222 and the normal

9T interval by way of bus 126 if the edge interval 222 is longer than the normal 9T interval. The values stored for 4S5M and 5M4S are likewise corrected based on the measured edge intervals 223 and 224.

When these four settings are updated, the first pattern signal 201 is again recorded and the edge intervals are measured. This process is repeated until the difference between the normal interval and the measured edge interval is below a predetermined threshold level simultaneously for all four edge intervals. Note that when measuring the edge intervals, the edge that is not moved is the falling edge of 6T mark 209, and the immediately following space is 6T space 210, in the case of edge interval 221, for example. In the case of edge interval 222, the rising edge of 6T mark 213 is not moved, and the immediately preceding space is 6T space 212.

The mark and space between which are located the edge that is not moved within a mark/space pattern are referred to herein as a reference signal. This edge is further referred to as the reference edge. If the reference edge moves in conjunction with an edge that is moved, movement settings cannot be correctly determined because there is no fixed point of reference. The position of the reference edge must therefore must remain stationary and cannot move in conjunction with the edge that is moved.

Furthermore, even when the edge in the reference signal does not change in conjunction with an edge that is moved, it may be necessary to change the reference signal so that the reference edge does not move in conjunction with the shifted edge. For example, if the reference signal includes a mark of the shortest possible length, it is necessary to change the reference signal so that the reference signal edge does not change at any of the movement settings defined for the shortest marks. Considering the potential for setting variations, the reference marks are preferably fixed.

If the reference signal is included in the same group as the longest

signal, the same reference signal can be used for all settings shown in Fig. 4A, and mark start and end positions can be more accurately determined in various mark/space combinations.

Though small, there are also differences in the change of the mark edge position even in the longest signal group because of differences in heat accumulation and thermal interference within the group for changing first pulse and last pulse movement. However, by selecting as the reference signal a mark/space signal with a high frequency of occurrence that also belongs to the group containing the longest possible signal as in this preferred embodiment of the invention, an overall reduction in the occurrence of imprecise edge positions can be achieved.

Furthermore, though small there are also differences in the output amplitude of the reproduction equalizer when reproducing different mark/space signals in the group containing the longest possible mark because of differences in the output amplitude of the reproduction equalizer 114 within the group for changing first pulse and last pulse movement. However,by selecting as the reference signal a mark/space signal with a high frequency of occurrence that also belongs to the group containing the longest possible signal as in this preferred embodiment of the invention, the occurrence of imprecise edge positions can be reduced in the overall recording and reproducing system.

By thus achieving an overall reduction in the occurrence of edges at imprecise positions, the probability of reliable error correction by the demodulation and error correction circuit 117 during actual data recording is improved.

It is to be noted that the frequency of signal occurrence increases and the output amplitude of the reproduction equalizer increases as signal length decreases. Selecting the reference mark therefore involves a trade-off between frequency of occurrence and output amplitude. Furthermore, while

marks and spaces of 5T or longer are in the same signal group in this preferred embodiment of the invention, a 6T reference mark is used in consideration of the reproduction equalizer characteristics.

It is to be further noted that the initial values set for 3S3M0 and 3M3S0 are selected to that the reference marks will be recorded with the correct length. Different initial values can, however, be used based on the structure of the optical disk 101.

When recording the first pattern signal is completed, a second pattern signal is recorded. Shown in Fig. 11 are second pattern signal 1101, which is the output signal from the pattern signal generator 125; output signal 1102 from the pulse generator 111; output signal 1103 from the pulse moving circuit 110; and mark pattern 1104 formed in the recording track of the optical disk 101 based on output signal 1103. The first pulse settings 5S4M and 3S5M, and last pulse settings 4M5S and 5M3S in Fig. 4A are then updated using the same method described above using the first specific pattern signal 201.

When recording the second pattern signal is completed, a third pattern signal is recorded. Shown in Fig. 12 are third pattern signal 1201, which is the output signal from the pattern signal generator 125; output signal 1202 from the pulse generator 111; output signal 1203 from the pulse moving circuit 110; and mark pattern 1204 formed in the recording track of the optical disk 101 based on output signal 1203. In Fig. 12, the 10T period of 1210 and 1211 (a 6T space and 4T mark) and the 10T period of 1212 and 1213 (a 4T mark and 6T space) have the same time length and appear as a continuous wave. Measured signal 1210 - 1211 and the next measured signal 1212 - 1213 therefore have the same length, and it is difficult to accurately separate and measure the measured signals. Utilizing the fact that jitter is minimized if the two 10T periods are substantially the same length, a jitter meter can therefore be substituted for measurement. Other than these signal periods, the same

method used with the first pattern is applied to set and update the first pulse settings 4S4M and 3S3M, and last pulse settings 4M4S and 3M3S in Fig. 4A.

When recording the third pattern signal is completed, a fourth pattern signal is recorded. Shown in Fig. 13 are fourth pattern signal 1301, which is the output signal from the pattern signal generator 125; output signal 1302 from the pulse generator 111; output signal 1303 from the pulse moving circuit 110; and mark pattern 1304 formed in the recording track of the optical disk 101 based on output signal 1303. The first pulse setting 4S3M and last pulse setting 4M3S in Fig. 4A are updated using the same method used with the first pattern signal.

When recording the fourth pattern signal is completed, a fifth pattern signal is recorded. Shown in Fig. 14 are fifth pattern signal 1401, which is the output signal from the pattern signal generator 125; output signal 1402 from the pulse generator 111; output signal 1403 from the pulse moving circuit 110; and mark pattern 1404 formed in the recording track of the optical disk 101 based on output signal 1403. The first pulse setting 3S4M and last pulse setting 3M4S in Fig. 4A are updated using the same method used with the fourth pattern signal.

It is therefore possible with the method according to this preferred embodiment to compensate during recording for the effects of heat accumulation and thermal interference during recording and distortion from the equalizer during reproduction, and thus record a mark/space pattern with little jitter, by determining the mark start position from the length of the recorded mark and the length of the space preceding the mark, and determining the mark end position from the length of the recorded mark and the length of the space following thereafter.

In addition, by recording first to fifth patterns and compensating the mark start and end positions to minimize the offset from a specific reference

edge and the normal mark length, optimum first pulse and last pulse movement can be determined for any signal pattern not contained in the first to fifth patterns. It is therefore possible to record marks at the correct position during actual data recording, and recording with little jitter can thus be achieved.

It should also be noted that the method according to this preferred embodiment uses simple symbol patterns whereby the difference DSV is controlled to substantially zero only when DSV is not 0. As noted above, DSV is the difference between the reference signal, measured signal, and marks and spaces in a specific period.

For example, the sum of marks in the first pattern signal 201 in Fig. 2 is 34T and the sum of spaces is also 34T. By incorporating into one pattern two types of measured marks with different edge intervals, the settings shown in Fig. 4A can be determined using fewer patterns. It is also possible to minimize the time and recording track space, and the scale of the pattern signal generator 125, needed to determine the settings.

As described above, the pulse position offset measuring circuit 120 measures the position offset of the output signal from the digitizing circuit 115 to detect the edge interval or jitter interval, modifies the table stored in memory 127 based on the measured results, and sends a signal indicative of the corrected pulse edge position to the pulse moving circuit 110 to shift the first pulse and last pulse.

It is alternatively possible, however, to pass the output signal from the digitizing circuit 115 over a general purpose interface bus (GPIB) to a timer interval analyzer or other analyzer for measuring the time interval or jitter, further connect the time interval analyzer over a GPIB to a personal computer, and then pass signals from the personal computer to the pulse moving circuit 110 through a SCSI or other bus interface. In this case it is not necessary for the recording device to comprise the pulse position offset measuring circuit 120,

and can thus be simplified.

It is to be noted that while this preferred embodiment shifts the first pulse and last pulse according to the specific mark/space combination, the same method can be applied to optimize the pulse width in a recording method whereby the pulse width of the first pulse and last pulse are modified.

Fig. 22 shows the signal parts corresponding to 6T mark 213 in first pattern signal 201 and 6T mark 213 in pulse generator output signal 202 in Fig. 2 when the space length before the 6T mark is 6T, 4T and 3T according to an alternative method of the present embodiment whereby optimization is achieved by pulse width modification.

The width of the first pulse changes according to the length of the mark and the preceding space. In this preferred embodiment, both marks and spaces are separated into three groups of 3T, 4T, and 5T or longer, and mark edge movement is therefore defined for nine possible combinations of marks and spaces.

Movement of the rising edge of the first pulse is expressed as movement TF referenced to the rising edge of first pattern signal 201, for example. The falling edge of the first pulse does not move. 6T mark 213 belongs to the 5S5M group because the preceding space is 6T long, and TF1 is approximately 1 ns. When the preceding space is 4T long, movement of the rising edge of the first pulse is in the 4S5M group, and TF2 is approximately 3 ns. When the preceding space is 3T long, the first pulse width is in the 3S5M group, and TF3 is approximately 5 ns. Note that while the value of TF changes, the falling edge of the first pulse does not move. As a result, the width of the first pulse changes.

Fig. 23 shows the signal parts corresponding to 6T mark 213 in first pattern signal 201 and 6T mark 213 in pulse generator output signal 202 in Fig. 2 when the space length before the 6T mark is 6T, 4T and 3T according to

a further alternative method of the present embodiment whereby optimization is achieved by pulse width modification.

In this case movement of the rising edge of the last pulse is expressed as TL referenced, for example, to two clocks before the falling edge of the first pattern signal 201. The falling edge of the last pulse does not move. Because the following space is 6T long, 6T mark 213 is in the 5M5S group, and TL1 is approximately 13 ns. When the following space is 4T, movement of the rising edge of the last pulse is in the 5M4S group, and TL2 is approximately 11 ns. When the following space is 3T, the last pulse width group is 5M3S, and TL3 is approximately 9 ns. Note that while the value of TL changes, the rising edge of the last pulse does not change. As a result, the width of the last pulse changes.

It is to be noted that various methods other than changing the pulse position or pulse width can be used for controlling the mark start and mark end positions, including adjusting the laser power at a specific pulse. Using the TF and TL value tables to achieve the intended optimized recording benefits of the present invention therefore requires that the optimization method used to correct these tables be recorded with the tables. This can be accomplished by recording the control method or by recording a predetermined code indicative of the control method.

A data recording medium and optical data recording method according to alternative embodiments of the present invention are described next below with reference to the accompanying diagrams. Fig. 15 is a block diagram of a data recording medium and optical data recording device according to a second preferred embodiment of the present invention. Shown in Fig. 15 are: an optical disk 1501, spindle motor 1502, semiconductor laser 1503, collimator lens 1504, beam splitter 1505, objective lens 1506, collective lens 1507, photodetector 1508, laser drive circuit 1509, pulse moving circuit 1510,

delay circuits 1528 and 1529, pulse generator 1511, preamp 1512, low pass filter 1513, reproduction equalizer 1514, digitizing circuit 1515, PLL 1516, demodulation and error correction circuit 1517, reproduction data signal 1518, power setting circuit 1519, and memory 1520.

Fig. 16 is a plan view of the optical disk 1501. In this exemplary embodiment the optimum position information for the mark start and end positions, that is, the two corrected tables shown in Fig. 4A and determined as described in the first embodiment of the present invention, is stored in recording area 1601. These tables comprise pit and land or mark and space bit sequences printed to the inside circumference area of the disk by the disk manufacturer prior to shipping. These two corrected tables are compiled by the manufacturer of the optical disk, and are prestored to every optical disk. The end-user thus obtains optical disks to which these two corrected tables have already been stored, and uses such disks with the device shown in Fig. 15.

The optical data recorder shown in Fig. 15 has an optical head comprising semiconductor laser 1503, collimator lens 1504, beam splitter 1505, objective lens 1506, collective lens 1507, and photodetector 1508. When an optical disk 1501 is loaded into this optical data recorder and the recorder completes a specific operation for recognizing the disk, the optical head moves to the recording area 1601 storing the optimum mark start and end position data tables, and reads the stored information. The data read from recording area 1601 thus contains the information compiled in the two tables shown in Fig. 4A, and the reproduced tables are thus stored to memory 1520.

Mass manufacturing optical disks thus containing the corrected tables described above is described next below.

Two corrected tables such as shown in Fig. 4A are first compiled by determining the optimum mark start and end positions using a method such as described in the above first exemplary embodiment of the present invention.

The content of these tables is then recorded to the recording area 1601 of the optical disk 1501 using a laser to cut the information into the master that will be used for stamping the optical disk 1501 during production when the recording area 1601 is recorded with a pit and land sequence.

Fig. 27 shows a mastering system for cutting an optical disk master. Shown in Fig. 27 are memory 2701, adjustment method data generator 2702, recording signal generator 2703, light modulator 2704, beam generator 2705, lens assembly 2706, glass master 2708 coated with a photosensitive material 2707, turntable 2709, and motor 2710.

The two corrected tables shown in Fig. 4A are stored to the memory 2701 in Fig. 27. Next, the method used for adjusting the first and last pulses is output from the adjustment method data generator 2702, and the content of the two tables is then output from memory 2701. The recording signal generator 2703 then processes the adjustment method and table data, including modulation, adding an error correction code, scrambling, and other desired processes, and generates the two-value data used for recording. The laser beam generated from the solid laser generator 2705, which oscillates at the wavelength of ultraviolet or the like wavelength, is power modulated by the output signal from the recording signal generator 2703. The modulated laser beam is fed through the lens assembly and impinges onto the photosensitive material 2707 on the glass master 2708. Recording the two-value signal is achieved at this time by turning the laser beam on and off to expose or not expose the photosensitive layer appropriately. It is to be noted that the two tables stored to the memory 2701 are recorded to an area on the inside circumference side of the user data area where the end user records data, and the adjustment method data is recorded to the area to the inside circumference side of the area to which the two tables are stored.

The area exposed by an ultraviolet laser is then melted and a

metal stamping master with pits and lands is produced by sputtering the glass substrate with nickel or metal. This metal stamping master is used as a die for producing a disk substrate on which a recording film is formed. A single disk is produced by combining two substrates, at least one of which has a recording film formed thereon.

Returning to Fig. 15, the laser beam emitted from the semiconductor laser 1503 is converted to parallel light by the collimator lens 1504, and passed to the beam splitter 1505. Light passing the beam splitter 1505 is collected by the objective lens 1506, and emitted to the optical disk 1501 as a light spot.

Light reflected from the optical disk 1501 is then collected by the objective lens 1506, and passed again through the beam splitter 1505. Light reflected from the beam splitter is collected by the collective lens 1507, and focused on the photodetector 1508.

The photodetector 1508 converts the light quantity to an electrical signal, which is amplified by the preamp 1512. The output signal from the preamp 1512 is then passed through the low pass filter 1513 whereby high frequency signal components are blocked. The reproduction equalizer 1514 then equalizes the signal, which is next binarized by the digitizing circuit 1515 using a predetermined slice level to output a signal of 0s and 1s. The clock of the output signal from the digitizing circuit 1515 is extracted by the PLL 1516. An output signal synchronized to the clock is then supplied to the demodulation and error correction circuit 1517 for demodulation and error correction of correctable data, resulting in reproduction signal 1518.

The reproduction signal 1518, that is, the content of the two tables and the adjustment method information, is then stored to memory 1520. The optimum movement information for the mark start and end positions is then passed over bus 1521 to the pulse moving circuit 1510.

During actual recording, the power setting circuit 1519 sets the laser drive circuit 1509 to either peak power or bias power level. Subsequent signal flow is described further below with reference to Fig. 17.

Shown in Fig. 17 are the data recording signal 1701 input to the pulse generator 1511, the output signal 1702 from the pulse generator 1511, and the output signal 1703 from the pulse moving circuit 1510. The recording marks 1704 are formed in the recording track of the optical disk 1501 by modulating laser power between peak power and bias power levels. Note that signals 1701, 1702, and 1703 are not actually on the same time axis, but are shown with corresponding parts aligned vertically in Fig. 17 for ease of understanding only.

In data recording signal 1701, mark parts 1706, 1708, and 1710 are the parts of the signal whereby a mark is formed on the disk, and space parts 1707, 1709, and 1711 are the parts of the signal that appear as a space on disk.

For example, when data generated by (2,10) run-length limited modulation is recorded using a mark edge recording method, the marks and spaces have a shortest length of 3T and a longest length of 11T where T is the reference period. Mark part 1706 is a 6T mark, space 1707 is a 6T space, 1708 is a 4T mark, 1709 is a 4T space, 1710 is a 6T mark, and 1711 is a 6T space.

This data recording signal 1701 is converted to a pulse sequence by the pulse generator 1511, resulting in output signal 1702. Pulse output from the pulse generator 1511 corresponding to marks of lengths 3T to 11T is shown in Fig. 18.

Referring by way of example to a 6T signal in Fig. 18, the pulse at the start of the signal is referred to as the first pulse 1801, and the pulse at the end of the signal is the last pulse 1804. The pulses between the first pulse 1801 and last pulse 1804 are referred to as multiple pulses 1802 and have a

constant period.

In a 6T mark there are two multiple pulses 1802, in a 7T mark there are three, and in a 5T mark there is one. It will thus be obvious that the number of multiple pulses 1802 between the first and last pulses increases by one with each 1T increase in signal length, and decreases one with each 1T decrease in signal length. A 4T mark, therefore comprises only the first and last pulses, and has no multiple pulses 1802 therebetween. In addition, a 3T mark comprises one pulse.

It is to be noted that in this preferred embodiment the time-base length of the first pulse is 1.5T, the last pulse is 0.5T, and the length of the multiple pulses is also 0.5T. The invention shall not be so limited, however, and the length of these pulses can be varied as necessary according to the structure of the optical disk 1501.

As noted above, data recording signal 1701 and output signal 1702 are not on the same time base. However, the difference between the rising edge of data recording signal 1701 and the rising edge of the first pulse of output signal 1702 is the same for any particular mark parts, and the difference between the falling edge of the data recording signal 1701 and the falling edge of the last pulse of output signal 1702 is also the same for any particular mark parts.

The pulse generator output signal 1702 is input to the pulse moving circuit 1510, which generates and outputs a signal 1703 in which the positions of the first pulse and last pulse are moved. Fig. 19 shows the tables stored to memory 1520.

It is to be noted that the tables in Fig. 19 are identical to the tables shown in Fig. 4A, and show the combinations of marks and spaces used for shifting the first pulse and last pulse positions.

The position of the first pulse changes according to the length of

the mark and the immediately preceding space. In this preferred embodiment, the marks and spaces are separated into three groups, that is, 3T, 4T, and 5T or longer. A total of nine different last pulse positions are therefore defined.

Movement of the last pulse position is similarly corrected. That is, last pulse position movement changes according to the mark length and the length of the following space. In this exemplary embodiment marks and spaces are separated into three groups based on length, 3T, 4T, and 5T or longer, and pulse position movement is defined for each of the nine possible mark/space combinations. The last pulse movement TL is then calculated using the same method used to calculate first pulse movement TF as described in the first embodiment.

The output signal 1703 from the pulse moving circuit 1510 is input to the laser drive circuit 1509, which produces a laser beam at peak power at high pulses and at bias power at low pulses in the output signal 1703. The resulting sequence of marks 1704 is shown in Fig. 17.

It is therefore possible to reproduce from a predetermined area on the optical disk and store in the optical data recorder data for changing mark start and end positions according to a data signal input to the optical data recorder for recording. As a result, it is possible for the optical data recorder to optimally record a signal of marks and spaces even using optical disks having different disk structures and recording films.

It is to be noted that it is not necessary to obtain the optimized mark start and end position information recorded to a particular area of the disk for all disks. More specifically, if the variation between disks is small, the values obtained for disks of the same structure and same recording film composition can be recorded as typical optimized values.

Furthermore, when the optimized mark start and end position values are obtained again during actual recording to further improve jitter, the

time required for the optimization process can be reduced if typical optimized values are prerecorded to a particular area of the disk as in this exemplary embodiment, and these typical values are used as default values for obtaining mark start and end position values optimized for jitter.

Furthermore, while marks and spaces are separated into three groups, 3T, 4T, and 5T or longer, in this preferred embodiment, the method for determining these groupings is the same as in the first embodiment above. Insofar as the optimized values for first and last pulse movement are recorded to disk, various other groupings can be used according to particular conditions. For example, four groups, such as 3T, 4T, 5T, and 6T or longer, could be alternatively used.

Tables for pulse movement groupings based on mark and space lengths of 3T, 4T, 5T, and 6T or longer are shown in Fig. 24. Increasing the number of length groups used makes it possible to more precisely control first pulse movement and last pulse movement according to the specific symbol pattern recorded, and thus enables recording with even less jitter.

It is to be noted that this preferred embodiment of the present invention determines and stores optimized movement information for both first and last pulses, but the invention shall not be so limited. Recording optimized movement information for only one of the pulses is still beneficial for determining the optimum pulse movement, and makes it possible to achieve recording with little jitter.

It will also be obvious to one with ordinary skill in the related art that while this exemplary embodiment has been described recording first and last pulse movement information optimized for particular mark and space combinations, a recording method whereby the pulse width of the first pulse and last pulse is change can be alternatively used as described in the first embodiment. Optimized recording of mark and space sequences can be

achieved even with different types of optical disks, such as when the disk structure or recording film is different, by prerecording optimized pulse width information to a particular area of the disk.

It is to be noted that various methods other than changing the pulse position or width can be used for controlling the mark start and end positions, including changing laser emission power at a particular pulse. Using the TF and TL value tables to achieve the intended optimized recording benefits of the present invention therefore requires that the optimization method used to correct these tables be recorded with the tables.

Fig. 25 is a plan view of an optical disk 2501. In this exemplary embodiment user data is recorded to data area 2502. Information indicative of the method used to adjust the first pulse and last pulse according to the input data signal is recorded to area 2503 at the inside-most circumference area of the disk using a sequence of pits and lands (marks and spaces). The optimized or typical mark start and end position information, that is, tables such as shown in Fig. 4A or Fig. 24, is recorded to area 2504 using a sequence of pits and lands (marks and spaces).

It is therefore possible to know by reproducing the data stored to area 2503 what method is used for adjusting the marks and spaces, that is, whether the first or last pulse is moved or whether the pulse width is changed.

It is to be noted that variables introduced by the recording device, such as the shape of the laser spot emitted to the disk, can also cause the optimum position of the mark start and end positions required for the best recording results to vary. To compensate for this, the optimized or typical position information recorded to a particular area of the disk during disk manufacture can be reproduced and these initial values used for a recording test whereby the position values are optimized for the recording device.

This makes it possible to reduce the number of patterns that must

be recorded to determine the optimum mark start and end positions for actual data recording. It also reduces the time required for this optimization procedure.

Fig. 26 is a plan view of a further optical disk 2601. In this exemplary embodiment user data is recorded to data area 2602. Information indicative of the method used to adjust the first pulse and last pulse according to the input data signal is recorded to area 2603 at the inside-most circumference area of the disk using a sequence of pits and lands (marks and spaces). The optimized or typical mark start and end position information is recorded to area 2604 using a sequence of pits and lands (marks and spaces). In addition, this optical disk 2601 comprises a test recording area 2605.

With an optical disk 2601 thus comprised, the optimization method is read from area 2603, and the mark start and end position information is read from area 2604, and based on this information a test recording is made in area 2605 using a method such as described in the first embodiment of the present invention. This makes it possible to achieve more optimized recording than is possible using only the settings prerecorded to the disk.

It should be noted that by recording the area 2503 or 2603 containing the method used for adjusting the first pulse and last pulse to the inside circumference side of the area 2504 or 2604 to which the optimized or typical mark start and end position information is recorded during disk manufacture as shown in Fig. 25 or Fig. 26, respectively, the recording method can be quickly determined when reproduction proceeds from the inside circumference area of the disk, and the time required to complete any settings that are dependent upon the recording method can be reduced.

It will also be obvious to one with ordinary skill in the related art that while the preferred embodiments of the present invention have been described above using an optical disk by way of example, the invention shall not be so limited. More specifically, the same benefits can be achieved using a

tape or card type recording medium or recording and reproducing device without departing from the scope of the accompanying claims.

It will thus be known from the above that an optical data recording device according to the present invention records first to fifth patterns of exemplary recording symbol sequences, and then reproduces these patterns to determine the optimum movement of the first and last pulses. These optimized first and/or last pulse movement values are then recorded to the recording medium during production. As a result, when an end user records information to the recording medium, this information can be reproduced to reduce or eliminate the time and effort required for the recording device to learn the optimum movement information. Marks can therefore recorded with higher precision, and recording with little jitter can be achieved.

Furthermore, optimized recording can be achieved even with different types of optical disks, that is, optical disks having different disk structures or recording film compositions, using a data recording medium according to the present invention by recording to a particular area of the data recording medium information indicative of the change in the mark start and end positions required for input data signals of different symbol patterns, and then reproducing and storing this information in the recording device at the time of data recording.

Although the present invention has been described in connection with the preferred embodiments thereof with reference to the accompanying drawings, it is to be noted that various changes and modifications will be apparent to those skilled in the art. Such changes and modifications are to be understood as included within the scope of the present invention as defined by the appended claims, unless they depart therefrom.

CLAIMS

1. A data recording medium having a plurality of tracks for recording information represented as marks and spaces between the marks, the marks being formed by emitting to a track in the data recording medium an optical beam modulated by one or a plurality of drive pulses where a number of the drive pulses is determined according to a length of a mark part in the original signal to be recorded to the track, the data recording medium comprising:

a data recording area for recording data, and

a control information recording area for storing at least one of a first pulse position Tu value for determining a start position of a mark to be recorded, and a last pulse position Td value for determining an end position of a mark to be recorded.

2. The data recording medium as set forth in claim 1, wherein the first pulse position Tu is obtained from a length of a mark part and immediately preceding space part in the original signal, and last pulse position Td is obtained from a length of a mark part and immediately following space part in the original signal.

3. The data recording medium as set forth in claim 1, wherein the first pulse position Tu is expressed as a time difference TF between a first reference point R1, which is a leading edge of a mark part in the original signal to be recorded, and a first edge of the first pulse in a plurality of drive pulses, and

the last pulse position Td is expressed as a time difference TL between a second reference point R2, which has a specific known position relative to a trailing edge of a mark part in the original signal to be recorded, and a trailing edge of the last pulse in a plurality of drive pulses.

This Sheet Has Been Replaced

THIS SHEET HAS BEEN REPLACED

4. The data recording medium as set forth in claim 1, wherein the length of mark parts in the original signal and the length of space parts between the mark parts are expressed as a value NT where

T is a reference period, and

N is a positive integer from n1 to n2;

mark and space parts are separated into a plurality of groups according to mark and space length; and

specific first pulse position Tu and last pulse position Td values are set for each group.

5. The data recording medium as set forth in claim 4, wherein mark parts are separated by length into three groups, and space parts are separated by length into three groups.

6. The data recording medium as set forth in claim 4, wherein mark parts are separated by length into four groups, and space parts are separated by length into four groups.

7. The data recording medium as set forth in claim 4, wherein the number of adjustment groups increases as a length of the mark part and a length of the space part decreases.

8. The data recording medium as set forth in claim 4, wherein n1 is 3 and n2 is 11.

9. The data recording medium as set forth in claim 4, wherein mark parts are separated by length into three groups of 3T, 4T, and 5T or longer

THIS SHEET HAS BEEN REPLACED

marks, and space parts are separated by length into three groups of 3T, 4T, and 5T or longer spaces.

10. The data recording medium as set forth in claim 4, wherein mark parts are separated by length into four groups of 3T, 4T, 5T, and 6T or longer marks, and space parts are separated by length into three groups of 3T, 4T, 5T, and 6T or longer spaces.

11. The data recording medium as set forth in claim 1, wherein there are two or more methods of using Tu and Td with a plurality of pulses, and information indicative of the method of use is prerecorded to the control information recording area.

12. The data recording medium as set forth in claim 11, wherein the method of Tu use uses Tu to change the rising edge position of a first drive pulse without changing the width thereof, and the method of Td use uses Td to change the falling edge position of a last drive pulse without changing the width thereof.

13. The data recording medium as set forth in claim 11, wherein the method of Tu use uses Tu to change the width of a first drive pulse without changing the falling edge position thereof, and the method of Td use uses Td to change the width of a last drive pulse without changing the rising edge position thereof.

14. The data recording medium as set forth in claim 11, wherein the information indicative of the method of Tu and Td use is recorded to a position before the position where the Tu and Td values are recorded referenced to the

direction in which information is recorded.

15. A method for obtaining a first pulse position Tu for a data recording medium having

a plurality of tracks,

marks to be formed by emitting to a track in the data recording medium an optical beam modulated by one or a plurality of drive pulses where a number of the drive pulses is determined according to a length of a mark part in the original signal to be recorded to the track,

a data recording area for recording information using the marks and spaces between the marks, and

a control information recording area having recorded thereto at least a first pulse position Tu value and a last pulse position Td value whereby at least a first pulse position Tu and a last pulse position Td of the drive pulse is changed so as to make a reproduction jitter a specific value or less,

said method comprising:

generating a pattern signal containing a pattern of consecutive mark parts with a specific length of PT and space parts with a specific length of QT where T is a reference period, P is a positive integer from n1 to n2, and Q is a positive integer from n1 to n2;

storing the pattern signal;

generating a plurality of drive pulses from the pattern signal;

forming spaces and marks on the data recording medium by generating and emitting thereto an optical beam modulated according to the plurality of drive pulses;

reproducing the marks and spaces recorded to the data recording medium;

This Sheet Has Been Replaced

THIS SHEET HAS BEEN REPLACED

comparing and obtaining a difference between a combination of mark and space parts in the reproduced reproduction signal, and a combination of mark and space parts in the stored pattern signal; and

obtaining from this difference a first pulse position Tu for application to an original signal containing a sequence of space parts of length QT and mark parts of length PT.

16. The method as set forth in claim 15, wherein first pulse position Tu is obtained for a plurality of combinations of mark lengths and space lengths by changing P and Q.

17. The method as set forth in claim 15, wherein the pattern signal contains an adjustment signal for obtaining a DSV of 0.

18. A method for obtaining a last pulse position Td for a data recording medium having

a plurality of tracks,

marks formed by emitting to a track in the data recording medium an optical beam modulated by one or a plurality of drive pulses where a number of the drive pulses is determined according to a length of a mark part in the original signal to be recorded to the track, and

a control information recording area for recording information using the marks and spaces between the marks, and having recorded thereto at least a first pulse position Tu value and a last pulse position Td value whereby at least a first pulse position Tu and a last pulse position Td of the drive pulse is changed so as to make a reproduction jitter a specific value or less,

said method comprising:

This Sheet Has Been Replaced

THIS SHEET HAS BEEN REPLACED

generating a pattern signal containing a pattern of consecutive mark parts with a specific length of PT and space parts with a specific length of QT where T is a reference period, P is a positive integer from n1 to n2, and Q is a positive integer from n1 to n2;

storing the pattern signal;

generating a plurality of drive pulses from the pattern signal;

forming spaces and marks on the data recording medium by generating and emitting thereto an optical beam modulated according to the plurality of drive pulses;

reproducing the marks and spaces recorded to the data recording medium;

comparing and obtaining a difference between a combination of mark and space parts in the reproduced reproduction signal, and a combination of mark and space parts in the stored pattern signal; and

obtaining from this difference a last pulse position Td for application to an original signal containing a sequence of space parts of length QT and mark parts of length PT.

19. The method as set forth in claim 18, wherein last pulse position Td is obtained for a plurality of combinations of mark lengths and space lengths by changing P and Q.

20. The method as set forth in claim 18, wherein the pattern signal contains an adjustment signal for obtaining a DSV of 0.

21. An apparatus for obtaining a first pulse position Tu for a data recording medium having

a plurality of tracks,

This Sheet Has Been Replaced

THIS SHEET HAS BEEN REPLACED

marks formed by emitting to a track in the data recording medium an optical beam modulated by one or a plurality of drive pulses where a number of the drive pulses is determined according to a length of a mark part in the original signal to be recorded to the track, and

a control information recording area for recording information using the marks and spaces between the marks, and having recorded thereto at least a first pulse position Tu value and a last pulse position Td value whereby at least a first pulse position Tu and a last pulse position Td of the drive pulse is changed so as to make a reproduction jitter a specific value or less,

said apparatus comprising:

means for generating a pattern signal containing a pattern of consecutive mark parts with a specific length of PT and space parts with a specific length of QT where T is a reference period, P is a positive integer from n1 to n2, and Q is a positive integer from n1 to n2;

means for storing the pattern signal;

means for generating a plurality of drive pulses from the pattern signal;

means for forming spaces and marks on the data recording medium by generating and emitting thereto an optical beam modulated according to the plurality of drive pulses;

means for reproducing the marks and spaces recorded to the data recording medium;

means for comparing and obtaining a difference between a combination of mark and space parts in the reproduced reproduction signal, and a combination of mark and space parts in the stored pattern signal; and

means for obtaining from this difference a first pulse position Tu for an original signal containing a sequence of space parts of length QT and

THIS SHEET HAS BEEN REPLACED

This Sheet Has Been Replaced

mark parts of length PT, and storing first pulse position Tu.

22. The apparatus as set forth in claim 21, wherein first pulse position Tu is obtained for a plurality of combinations of mark lengths and space lengths by changing P and Q.

23. The apparatus as set forth in claim 22, wherein the combinations are classified, and wherein the reproducing means comprises an equalizer, and the ratio between the output amplitude of the equalizer at the frequency of the longest mark and the output amplitude of the equalizer at the frequency of the shortest mark is 3 dB or less, provided that the longest mark and the shortest mark are from the same classification.

24. The apparatus as set forth in claim 21, wherein the pattern signal contains an adjustment signal for obtaining a DSV of 0.

25. An apparatus for obtaining a last pulse position Td for a data recording medium having

a plurality of tracks,

marks formed by emitting to a track in the data recording medium an optical beam modulated by one or a plurality of drive pulses where a number of the drive pulses is determined according to a length of a mark part in the original signal to be recorded to the track, and

a control information recording area for recording information using the marks and spaces between the marks, and having recorded thereto at least a first pulse position Tu value and a last pulse position Td value whereby at least a first pulse position Tu and a last pulse position Td of the drive pulse is changed so as to make a reproduction jitter a specific value

This Sheet Has Been Replaced

THIS SHEET HAS BEEN REPLACED

or less,

said apparatus comprising:

means for generating a pattern signal containing a pattern of consecutive mark parts with a specific length of PT and space parts with a specific length of QT where T is a reference period, P is a positive integer from n1 to n2, and Q is a positive integer from n1 to n2;

means for storing the pattern signal;

means for generating a plurality of drive pulses from the pattern signal;

means for forming spaces and marks on the data recording medium by generating and emitting thereto an optical beam modulated according to the plurality of drive pulses;

means for reproducing the marks and spaces recorded to the data recording medium;

means for comparing and obtaining a difference between a combination of mark and space parts in the reproduced reproduction signal, and a combination of mark and space parts in the stored pattern signal; and

means for obtaining from this difference a last pulse position Td for an original signal containing a sequence of space parts of length QT and mark parts of length PT, and storing last pulse position Td.

26. The apparatus as set forth in claim 25, wherein first pulse position Tu is obtained for a plurality of combinations of mark lengths and space lengths by changing P and Q.

27. The apparatus as set forth in claim 26, wherein the combinations are classified, and wherein the reproducing means comprises an equalizer, and the ratio between the output amplitude of the equalizer at the frequency of the

This Sheet Has Been Replaced

THIS SHEET REPLACED

longest mark and the output amplitude of the equalizer at the frequency of the shortest mark is 3 dB or less, provided that the longest mark and the shortest mark are from the same classification.

28. The apparatus as set forth in claim 25, wherein the pattern signal contains an adjustment signal for obtaining a DSV of 0.

29. A recording and reproducing apparatus for recording and reproducing a data recording medium having

a plurality of tracks,

marks formed by emitting to a track in the data recording medium an optical beam modulated by one or a plurality of drive pulses where a number of the drive pulses is determined according to a length of a mark part in the original signal to be recorded to the track, and

a control information recording area for recording information using the marks and spaces between the marks, and having recorded thereto at least a first pulse position Tu value and a last pulse position Td value whereby at least a first pulse position Tu and a last pulse position Td of the drive pulse is changed so as to make a reproduction jitter a specific value or less,

said apparatus comprising:

means for reproducing a first pulse position Tu and a last pulse position Td prerecorded to the data recording medium;

means for storing the reproduced first pulse position Tu and last pulse position Td;

means for generating a drive pulse based on a data recording signal, and correcting the generated drive pulse based on the first pulse position Tu and last pulse position Td;

This Sheet Has Been Replaced

THIS SHEET HAS BEEN REPLACED

means for emitting an optical beam based on the corrected drive pulses to form spaces and marks on the data recording medium.

30. The recording and reproducing apparatus as set forth in claim 29, wherein each of said first pulse position Tu and last pulse position Td is set with respect to a class of combinations of mark lengths and space lengths, and wherein the reproducing means comprises an equalizer, and the ratio between the output amplitude of the equalizer at the frequency of the longest mark and the output amplitude of the equalizer at the frequency of the shortest mark is 3 dB or less, provided that the longest mark and the shortest mark are from the same classification.

31. A manufacturing apparatus for manufacturing a data recording medium having a plurality of tracks,

marks formed by emitting to a track in the data recording medium an optical beam modulated by one or a plurality of drive pulses where a number of the drive pulses is determined according to a length of a mark part in the original signal to be recorded to the track, and

a control information recording area for recording information using the marks and spaces between the marks, and having recorded thereto at least one of a first pulse position Tu value and a last pulse position Td value whereby at least one of a first pulse position Tu and a last pulse position Td of the drive pulse is changed so as to make a reproduction jitter a specific value or less,

said apparatus comprising:

means for storing previously obtained first pulse position Tu and last pulse position Td values for a drive pulse sequence;

adjustment method information storage for storing information

This Sheet Has Been Replaced

THIS SHEET HAS BEEN REPLACED

indicative of a pulse position adjustment method;

means for converting the adjustment method information, first drive pulse position Tu, and last drive pulse position Td to a signal for recording, and generating a recording signal; and

laser generating means for generating a laser beam based on the recording signal.

This Sheet Has Been Replaced

THIS SHEET HAS BEEN REPLACED



REPRODUCTION DATA SIGNAL
118
DEMODULATION AND ERROR CORRECTION CIRCUIT
117
PULSE POSITION OFFSET MEASURING CIRCUIT
120
PATTERN SIGNAL GENERATOR
125
DATA RECORDING SIGNAL
123
122
121
124
PULSE GENERATOR
111
PLL
116
131
130
ASYMMETRY MEASURING CIRCUIT
DIGITIZING CIRCUIT
115
126
129
DELAY
128
DELAY
EQ
114
PULSE MOVING CIRCUIT
110
126
127
MEMORY
LPF
113
LASER DRIVE CIRCUIT
109
119
POWER SETTING CIRCUIT
PREAMP
112
SEMICONDUCTOR LASER
104
107
108
101
(OPTICAL DISK)
(SPINDLE MOTOR)
102
103
105
106

Fig. 1

Fig.2



209
211
213
215
216
217
219
210
212
214
218
220
201
6T
3T
6T
6T
6T
6T
4T
6T
7T
6T
202
203
204
(3M5S)
222
(5M4S)
223
205
221
(5S3M)
224
(4S5M)
206
207
208

Fig.3



11T MARK SIGNAL
301
302
304
11T PULSE SIGNAL
10T PULSE SIGNAL
9T PULSE SIGNAL
8T PULSE SIGNAL
7T PULSE SIGNAL
301
302
304
6T PULSE SIGNAL
0.5T
0.5T
5T PULSE SIGNAL
4T PULSE SIGNAL
3T PULSE SIGNAL

Fig.4A

FIRST PULSE MOVEMENT (TF) \ PRECEDING SPACE SIGNAL	MARK SIGNAL 3T	4T	≧5T
3T	3S3M	3S4M	3S5M
4T	4S3M	4S4M	4S5M
≧5T	5S3M	5S4M	5S5M

LAST PULSE MOVEMENT (TL) \ FOLLOWING SPACE SIGNAL	MARK SIGNAL 3T	4T	≧5T
3T	3M3S	4M3S	5M3S
4T	3M4S	4M4S	5M4S
≧5T	3M5S	4M5S	5M5S

Fig.4B

FIRST PULSE MOVEMENT (TF) \ PRECEDING SPACE SIGNAL	MARK SIGNAL 3T	4T	≧5T
3T	3S3M0	3S4M0	3S5M0
4T	4S3M0	4S4M0	4S5M0
≧5T	5S3M0	5S4M0	5S5M0

LAST PULSE MOVEMENT (TL) \ FOLLOWING SPACE SIGNAL	MARK SIGNAL 3T	4T	≧5T
3T	3M3S0	4M3S0	5M3S0
4T	3M4S0	4M4S0	5M4S0
≧5T	3M5S0	4M5S0	5M5S0

Fig.5



ORIGINAL SIGNAL 500
tm0
tm2
ts1
503
504
505
506
MARK 501
11T
11T
SXT
11T
11T
REPRODUCTION SIGNAL 502
tm10
tm11
tm12
r
507
ORIGINAL SIGNAL 520
tm20
ts21
tm22
523
524
525
526
MARK 521
11T
11T+α1
11T+α2
11T
SXT−α2−α1
REPRODUCTION SIGNAL 522
tm30
ts31
tm32
r
527

Fig.6





Fig.7






LAST PULSE
MARK SIGNAL
3T
4T
5T
6T
7T
8T
9T
10T
11T
FOLLOWING
SPACE SIGNAL
3T 4T 5T 6T 7T 8T 9T 10T 11T
FIRST PULSE
MARK SIGNAL
3T
4T
5T
6T
7T
8T
9T
10T
11T
PRECEDING
SPACE SIGNAL
3T 4T 5T 6T 7T 8T 9T 10T 11T

Fig.8


LAST PULSE
MARK SIGNAL
3T
4T
5T
6T
7T
8T
9T
10T
11T
3T 4T 5T 6T 7T 8T 9T 10T 11T
FOLLOWING
SPACE SIGNAL



FIRST PULSE
MARK SIGNAL
3T
4T
5T
6T
7T
8T
9T
10T
11T
3T 4T 5T 6T 7T 8T 9T 10T 11T
PRECEDING
SPACE SIGNAL

Fig.9

Fig.10




Fig.11



1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
6T
4T
3T
7T
(4M5S)
1122
(5M3S)
1123
1121
(5S4M)
1124
(3S5M)

Fig.12



1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
6T
4T
3T
7T
(4M5S)
1122
(5M3S)
1123
1121
(5S4M)
1124
(3S5M)

Fig. 13



1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
6T
4T
3T
6T
6T
6T
6T
4T
3T
6T
(4M3S)
(4S3M)
1319
1320
1321
1322
1301
1302
1303
1304
1305
1306
1307
1308

Fig.14



1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
6T
3T
4T
(3M4S)
(3S4M)
1419
1420
1421
1422

Fig.15



1529
DELAY
1509
LASER DRIVE CIRCUIT
1510
PULSE MOVING CIRCUIT
1528
DELAY
1511
PULSE GENERATOR
1701
DATA RECORDING SIGNAL
1521
1520
1519
POWER SETTING CIRCUIT
MEMORY
1503
SEMICONDUCTOR LASER
1504
1507
1505
1506
1508
PREAMP
1512
LPF
1513
EQ
1514
DIGITIZING CIRCUIT
1515
PLL
1516
DEMODULATION AND ERROR CORRECTION CIRCUIT
1517
1518
REPRODUCTION DATA SIGNAL
1501
(OPTICAL DISK)
1502
(SPINDLE MOTOR)

Fig.16



1601
1602

Fig.17



1706
1708
1709
1710
1707
1711
1701
6T
4T
6T
6T
4T
6T
1702
1703
1704
1705

Fig.18




Fig.19



FIRST PULSE MOVEMENT (TF)
MARK SIGNAL
3T
4T
≧5T
PRECEDING SPACE SIGNAL
3T
4T
≧5T
3S3M
3S4M
3S5M
4S3M
4S4M
4S5M
5S3M
5S4M
5S5M
LAST PULSE MOVEMENT (TL)
MARK SIGNAL
3T
4T
≧5T
FOLLOWING SPACE SIGNAL
3T
4T
≧5T
3M3S
4M3S
5M3S
3M4S
4M4S
5M4S
3M5S
4M5S
5M5S

Fig.20



R1
217
R2
T
6T
2T
201
4T
6T
1.5T
TL
TF
0.5T
4S5M
TF1=3ns
202
4T
6T
TIME

Fig.21




Fig.22



R1
R2
T
6T
2T
6T
1.7T
TL
TF1
0.1T
TF1=1ns
5S5M
6T
6T
TF2
TF2=3ns
4S5M
4T
6T
TF3
TF3=5ns
3S5M
3T
6T
TIME

Fig.23



R1
R2
T
6T
2T
6T
1.7T
TL1
TE
0.1T
TL1=13ns
5M5S
6T
6T
TL2
TL2=11ns
5M4S
6T
4T
TL3
TL3=9ns
5M3S
6T
3T
TIME

Fig.24



LAST PULSE MOVEMENT (TL)
MARK SIGNAL
FOLLOWING SPACE SIGNAL
3T 4T 5T ≧6T
3T 3M3S 4M3S 5M3S 6M3S
4T 3M4S 4M4S 5M4S 6M4S
5T 3M5S 4M5S 5M5S 6M5S
≧6T 3M6S 4M6S 5M6S 6M6S
FIRST PULSE MOVEMENT (TF)
MARK SIGNAL
PRECEDING SPACE SIGNAL
3T 4T 5T ≧6T
3T 3S3M 3S4M 3S5M 3S6M
4T 4S3M 4S4M 4S5M 4S6M
5T 5S3M 5S4M 5S5M 5S6M
≧6T 6S3M 6S4M 6S5M 6S6M

Fig.25




Fig.26




Fig.27




2704
LIGHT MODULATOR
2703
RECORDING SIGNAL GENERATOR
2701
MEMORY
2702
ADJUSTMENT METHOD DATA GENERATOR
2705
BEAM GENERATOR
2706
LENS ASSEMBLY
2707 PHOTOSENSITIVE MATERIAL
2709 TURNTABLE
2708 GLASS MASTER
2710 MOTOR

Fig.28


2801
6T
6T
6T
6T
6T
2802
2803
2804
2809
2805
2810
2811
2812
GND
2806
2807
2813
2808
2814
2815
2816
GND

Eisenführ, Speiser Partner

Bremen
Patentanwalte
European Patent Attorneys
Dipl -Ing Gunther Eisenführ
Dipl -Ing Dieter K. Speiser
Dr -Ing Werner W Rabus
Dipl -Ing. Jurgen Brugge
Dipl -Ing Jurgen Klinghardt
Dipl -Ing Klaus G Goken
Jochen Ehlers
Dipl -Ing Mark Andres

Rechtsanwalte
Ulrich H Sander
Sabine Richter

Martinistrasse 24
D-28195 Bremen
Tel +49-(0)421-36 35 0
Fax +49-(0)421-337 8788 (G3)
Fax +49-(0)421-328 8631 (G4)
mail@eisenfuhr com

Hamburg
Patentanwalt
European Patent Attorney
Dipl -Phys. Frank Meier

Rechtsanwalte
Christian Spintig
Rainer Bohm
Silja J. Greische!*
*Maitre en Droit

München
Patentanwalte
European Patent Attorneys
Dipl -Wirt.-Ing. Rainer Fntsch
Dipl -Chem. Gabriele Leißler-
Patentanwalt
Dipl -Chem Dr Peter Schuler

Berlin
Patentanwalte
European Patent Attorneys
Dipl -Ing Henning Christiansε
Dipl -Ing Joachim von Oppen
Dipl -Ing Jutta Kaden
Dipl -Ing Mathias Karlhuber

Alicante
European Trademark Attorney
Dipl -Ing Jurgen Klinghardt

Bremen, 28 September 2000

Our Ref.: M 6015 JOE/aw

Applicant: MATSUSHITA ELECTRIC INDUSTRIAL CO., LTD.
Serial Number: PCT/JP99/03699

* C L M S *

New Claims

1. A data recording medium having a plurality of tracks for recording information represented as marks and spaces between the marks in a data recording area of the data recording medium, the marks being formed by an optical beam modulated by one or a plurality of drive pulses comprising a first pulse, a last pulse and one or more multiple pulses between the first and last pulses, where a number of the drive pulses is determined according to a length of a mark part in the input signal to be recorded on the track,

characterized by a control information recording area storing:

first pulse movements (TF) for modifying said first pulse of said drive pulses, said first pulse movements (TF) being separated at least into nine groups determined by a combination of three groups of different length of a mark and three groups of different length of a space immediately preceding said mark, the three groups of different mark length being a group with only the first pulse, a group with the first pulse and the last pulse, and a group with the first pulse, the multiple pulse and the last pulse, wherein said first pulse movement (TF) indicates either a pulse shift amount for shifting said first pulse without changing the pulse width, or a pulse width amount for changing the pulse width of said first pulse, and,

a code indicating a method for using said first pulse movement (TF) either as a pulse shift amount or as a pulse width amount.

This Sheet Has Been Replaced

AMENDED SHEET

THIS SHEET HAS BEEN REPLACED

2. The data recording medium as set forth in claim 1, wherein the first pulse movement TF is expressed as a time difference TF between a first reference point R1, which is a leading edge of a mark part in the original signal to be recorded, and a first edge of the first pulse in a plurality of drive pulses.

3. The data recording medium as set forth in claim 1, wherein the length of mark parts in the original signal and the length of space parts between the mark parts are expressed as a value NT where

T is a reference period, and

N is a positive integer from n1 to n2;

mark and space parts are separated into a plurality of groups according to mark and space length; and

specific first pulse movement TF is set for each group.

4. The data recording medium as set forth in claim 1, wherein mark parts are separated by length into four groups, and space parts are separated by length into four groups.

5. The data recording medium as set forth in claim 1, wherein the separation of groups becomes fine as a length of the mark part and a length of the space part decreases.

6. The data recording medium as set forth in claim 3, wherein n1 is 3 and n2 is 11.

7. A recording and reproducing apparatus for recording and reproducing a data recording medium as claimed in claim 1,

said apparatus comprising:

means (1505 - 1508, 1512 - 1517) for reproducing said first pulse movements (TF) and the code from said data recording medium;

means (1520) for storing the reproduced first pulse movements (TF) and the code;

means (1510) for generating a drive pulse based on a data recording signal, and correcting the generated drive pulse based on the first pulse movements (TF) and the code;

means (109, 103 - 106) for emitting an optical beam based on the corrected drive pulses to form spaces and marks on the data recording medium,

wherein said first pulse movement (TF) is set with respect to a class of

combinations of mark lengths and space lengths, and wherein the reproducing means comprises an equalizer (1514), and the ratio between the output amplitude of the equalizer at the frequency of the longest mark and the output amplitude of the equalizer at the frequency of the shortest mark is 3 dB or less, provided that the longest mark and the shortest mark are from the same classification.

8. The recording and reproducing apparatus as set forth in claim 7, wherein said first pulse movements (TF) is set with respect to the type of the recording film composition changes.

9. The recording and reproducing apparatus as set forth in claim 7 or 8, wherein said first pulse movements (TF) being set with respect to the disk structure or recording film composition.

10. A data recording medium having a plurality of tracks for recording information represented as marks and spaces between the marks in a data recording area of the data recording medium, the marks being formed by an optical beam modulated by one or a plurality of drive pulses comprising a first pulse, a last pulse and one or more multiple pulses between the first and last pulses, where a number of the drive pulses is determined according to a length of a mark part in the input signal to be recorded on the track,

characterized by a control information recording area storing:

last pulse movements (TL) for modifying said last pulse of said drive pulses, said last pulse movements (TL) being separated at least into nine groups determined by a combination of three groups of different length of a mark and three groups of different length of a space immediately following said mark, the three groups of different mark length being a group with only the first pulse, a group with the first pulse and the last pulse, and a group with the first pulse, the multiple pulse and the last pulse, wherein said last pulse movements (TL) indicates either a pulse shift amount for shifting said last pulse without changing the pulse width, or a pulse width amount for changing the pulse width of said last pulse, and,

a code indicating a method for using said last pulse movement (TL) either as a pulse shift amount or as a pulse width amount.

11. The data recording medium as set forth in claim 10, wherein the last pulse movement TL is expressed as a time difference TL between a first reference point R1, which is a leading edge of a mark part in the original signal to be recorded, and a first edge of the last pulse in a plurality of drive pulses.

12. The data recording medium as set forth in claim 10, wherein the length of mark parts in the original signal and the length of space parts between the mark parts are expressed as a value NT where

T is a reference period, and

N is a positive integer from n1 to n2;

mark and space parts are separated into a plurality of groups according to mark and space length; and

specific last pulse movement TL is set for each group.

13. The data recording medium as set forth in claim 10, wherein mark parts are separated by length into four groups, and space parts are separated by length into four groups.

14. The data recording medium as set forth in claim 10, wherein the separation of groups becomes fine as a length of the mark part and a length of the space part decreases.

15. The data recording medium as set forth in claim 12, wherein n1 is 3 and n2 is 11.

16. A recording and reproducing apparatus for recording and reproducing a data recording medium as claimed in claim 10,

said apparatus comprising:

means (1505 - 1508, 1512 - 1517) for reproducing said last pulse movements (TL) and the code from said data recording medium;

means (1520) for storing the reproduced last pulse movements (TL) and the code;

means (1510) for generating a drive pulse based on a data recording signal, and correcting the generated drive pulse based on the last pulse movements (TL) and the code;

means (109, 103 - 106) for emitting an optical beam based on the corrected drive pulses to form spaces and marks on the data recording medium,

wherein said last pulse movement (TL) is set with respect to a class of combinations of mark lengths and space lengths, and wherein the reproducing means comprises an equalizer (1514), and the ratio between the output amplitude of the equalizer at the frequency of the longest mark and the output amplitude of the equalizer at the frequency of the shortest mark is 3 dB or less, provided that the longest mark and the shortest mark are from the same classification.

This Sheet Has Been Replaced

THIS SHEET H[illegible]EN
REPLACED

17. The recording and reproducing apparatus as set forth in claim 16, wherein said last pulse movements (TL) is set with respect to the type of the recording film composition changes.

18. The recording and reproducing apparatus as set forth in claim 16 or 17, wherein said last pulse movements (TL) being set with respect to the disk structure or recording film composition.

19. A data recording medium having a plurality of tracks for recording information represented as marks and spaces between the marks in a data recording area of the data recording medium, the marks being formed by an optical beam modulated by one or a plurality of drive pulses where a number of the drive pulses is determined according to a length of a mark part in the input signal to be recorded on the track,

characterized by a control information recording area storing:

a first pulse movement (TF) for modifying a first pulse of said drive pulses, and a last pulse movement (TL) for modifying a last pulse of said drive pulses, wherein said first pulse movement (TF) and last pulse movement (TL) indicate either a pulse shift amount for shifting said first and last pulses, respectively, without changing the pulse width, or a pulse width amount for changing the pulse width of said first and last pulses, respectively, and,

a code indicating a method for using said first pulse movement (TF) and last pulse movement (TL) either as a pulse shift amount or as a pulse width amount.

20. The data recording medium as set forth in claim 19, wherein the first pulse amount (TF) is expressed as a time difference between a reference point (R1), which is located a predetermined distance from a leading edge of a mark, and a first edge of the first pulse, and

the last pulse amount (TL) is expressed as a time difference between a reference point (R2), which is located a predetermined distance from a trailing edge of a mark, and a trailing edge of the last pulse.

21. The data recording medium as set forth in claim 19, wherein the length of a mark in the input signal and the length of a space between the marks are expressed as a value NT where

T is a reference period, and

N is a positive integer from n1 to n2;

This Sheet Has Been Replaced

AMENDED SHEET

THIS SHEET HAS BEEN REPLACED

marks and spaces are classified into a plurality of groups according to the mark length and the space length; and

a specific first pulse movement (TF) and last pulse movement (TL) are set for each group.

22. The data recording medium as set forth in claim 21, wherein the marks are classified by length into three groups, and the spaces are classified by length into three groups.

23. The data recording medium as set forth in claim 21, wherein the marks are classified by length into four groups, and the spaces are classified by length into four groups.

24. The data recording medium as set forth in claim 21, wherein the number of groups increases as the length of the mark and the length of the space decreases.

25. The data recording medium as set forth in claim 21, wherein n1 is 3 and n2 is 11.

26. The data recording medium as set forth in claim 21, wherein marks are classified by length into three groups of 3T, 4T, and 5T or longer marks, and spaces are classified by length into three groups of 3T, 4T, and 5T or longer spaces.

27. The data recording medium as set forth in claim 21, wherein marks are classified by length into four groups of 3T, 4T, 5T, and 6T or longer marks, and spaces are classified by length into three groups of 3T, 4T, 5T, and 6T or longer spaces.

28. The data recording medium as set forth in claim 19, wherein there are two more methods of using the first pulse movement (TF) and last pulse movement (TL), and wherein information indicative of the method of use is prerecorded to the control information recording area.

29. The data recording medium as set forth in claim 28, wherein the method of using the first pulse movement (TF) is to use the first pulse movement (TF) to change the rising edge portion of the first pulse without changing the width thereof, and the method of using the last pulse movement (TL) is to use the last pulse

movement (TL) to change the falling edge position of the last pulse without changing the width thereof.

30. The data recording medium as set forth in claim 28, wherein the method of using the first pulse movement (TF) is to use the first pulse movement (TF) to change the width of the first pulse without changing the falling edge position thereof, and the method of using the last pulse movement (TL) is to use the last pulse movement (TL) to change the width of the last pulse without changing the rising edge position thereof.

31. The data recording medium as set forth in claim 28, wherein the information indicative of the method of the first pulse movement (TF) and the last pulse movement (TL) is recorded to the position before the position where the first pulse movement (TF) and last pulse movement (TL) values are recorded relatively to the direction in which information is recorded.

32. A recording and reproducing apparatus for recording and reproducing a data recording medium according to claim 19, said apparatus comprising:

means (1505 — 1508, 1512 — 1517) for reproducing the first pulse movement (TF) and the code, which are prerecorded to the data recording medium;

means (1520) for storing the reproduced first pulse movement (TF) and the code;

means (1510) for generating a drive pulse based on a data recording signal, and correcting the generated drive pulse based on the first pulse movement (TF) and the last pulse movement (TL), said code selecting the use of said first pulse movement (TF) and said last pulse movement (TL) either as a pulse shift amount or as a pulse width amount.;

means (109, 103 — 106) for emitting an optical beam based on the corrected drive pulses to form spaces and marks on the data recording medium.

33. The recording and reproducing apparatus as set forth in claim 32, wherein each of said first pulse movement (TF) and last pulse movement (TL) is set with respect to a class of combinations of a mark length and a space length, and wherein the reproducing means comprises an equalizer (1514), and the ratio between the output amplitude of the equalizer at the frequency of the longest mark and the output amplitude of the equalizer at the frequency of the shortest mark is 3 dB or less.

This Sheet Has Been Replaced

THIS SHEET HAS BEEN REPLACED

34. A data recording medium having a plurality of tracks for recording information represented as marks and spaces between the marks in a data recording area of the data recording medium, the marks being formed by an optical beam modulated by one or a plurality of drive pulses where a number of the drive pulses is determined according to a length of a mark part in the input signal to be recorded on the track,

characterized by a control information recording area storing:

a first pulse movement (TF) for modifying a first pulse of said drive pulses, wherein said first pulse movement (TF) indicates either a pulse shift amount for shifting said first pulse without changing the pulse width, or a pulse width amount for changing the pulse width of said first pulse, and

a code indicating a method for using said first pulse movement (TF) either as a pulse shift amount or as a pulse width amount.

35. The data recording medium as set forth in claim 34, wherein the first pulse amount (TF) is expressed as a time difference between a reference point (R1), which is located a predetermined distance from a leading edge of a mark, and a first edge of the first pulse.

36. The data recording medium as set forth in claim 34, wherein the length of a mark in the input signal and the length of a space between the marks are expressed as a value NT where

T is a reference period, and

N is a positive integer from n1 to n2;

marks and spaces are classified into a plurality of groups according to the mark length and the space length; and

a specific first pulse movement (TF) is set for each group.

37. The data recording medium as set forth in claim 36, wherein the marks are classified by length into three groups, and the spaces are classified by length into three groups.

38. The data recording medium as set forth in claim 36, wherein the marks are classified by length into four groups, and the spaces are classified by length into four groups.

39. The data recording medium as set forth in claim 36, wherein the number of groups increases as the length of the mark and the length of the space decreases.

This Sheet Has Been Replaced

THIS SHEET HAS BEEN ...PLACED

AMENDED SHEET

40. The data recording medium as set forth in claim 36, wherein n1 is 3 and n2 is 11.

41. The data recording medium as set forth in claim 36, wherein marks are classified by length into three groups of 3T, 4T, and 5T or longer marks, and spaces are classified by length into three groups of 3T, 4T, and 5T or longer spaces.

42. The data recording medium as set forth in claim 36, wherein marks are classified by length into four groups of 3T, 4T, 5T, and 6T or longer marks, and spaces are classified by length into three groups of 3T, 4T, 5T, and 6T or longer spaces.

43. The data recording medium as set forth in claim 34, wherein the method of using the first pulse movement (TF) is to use the first pulse movement (TF) to change the rising edge position of the first pulse without changing the width thereof.

44. The data recording medium as set forth in claim 34, wherein the method of using the first pulse movement (TF) is to use the first pulse movement (TF) to change the width of the first pulse without changing the falling edge position thereof.

45. The data recording medium as set forth in claim 34, wherein the code is recorded at a position before the position where said first pulse movement (TF) is recorded relatively to the direction in which information is recorded.

46. A recording and reproducing apparatus for recording and reproducing a data recording medium according to claim 34,

said apparatus comprising:

means (1505 — 1508, 1512 — 1517) for reproducing the first pulse movement (TF) and the code, which are prerecorded to the data recording medium;

means (1520) for storing the reproduced first pulse movement (TF) and the code;

means (1510) for generating a drive pulse based on a data recording signal, and correcting the generated drive pulse based on the first pulse movement (TF), said code selecting the use of said first pulse movement (TF) either as a pulse shift amount or as a pulse width amount;

This Sheet Has Been Replaced

THIS SHEET H[illegible]
RE[illegible]

means (109, 103 — 106) for emitting an optical beam based on the corrected drive pulses to form spaces and marks on the data recording medium.

47. The recording and reproducing apparatus as set forth in claim 46, wherein each of said first pulse movement (TF) is set with respect to a class of combinations of a mark length and a space length, and wherein the reproducing means comprises an equalizer (1514), and the ratio between the output amplitude of the equalizer at the frequency of the longest mark and the output amplitude of the equalizer at the frequency of the shortest mark is 3 dB or less.

48. A data recording medium having a plurality of tracks for recording information represented as marks and spaces between the marks in a data recording area of the data recording medium, the marks being formed by an optical beam modulated by one or a plurality of drive pulses where a number of the drive pulses is determined according to a length of a mark part in the input signal to be recorded on the track,

characterized by a control information recording area storing:

a last pulse movement (TL) for modifying a last pulse of said drive pulses, wherein said last pulse movement (TL) indicates either a pulse shift amount for shifting said last pulse without changing the pulse width, or a pulse width amount for changing the pulse width of said last pulse, and,

a code indicating a method for using said last pulse movement (TL) either as a pulse shift amount or as a pulse width amount.

49. The data recording medium as set forth in claim 48, wherein the last pulse amount (TL) is expressed as a time difference between a reference point (R2), which is located a predetermined distance from a trailing edge of a mark, and a trailing edge of the last pulse.

50. The data recording medium as set forth in claim 48, wherein the length of a mark in the input signal and the length of a space between the marks are expressed as a value NT where

T is a reference period, and

N is a positive integer from n1 to n2;

marks and spaces are classified into a plurality of groups according to the mark length and the space length; and

a specific last pulse movement (TL) is set for each group.

This Sheet Has Been Replaced

THIS SHEET HAS BEEN REPLACED

51. The data recording medium as set forth in claim 50, wherein the marks are classified by length into three groups, and the spaces are classified by length into three groups.

52. The data recording medium as set forth in claim 50, wherein the marks are classified by length into four groups, and the spaces are classified by length into four groups.

53. The data recording medium as set forth in claim 51, wherein the number of groups increases as the length of the mark and the length of the space decreases.

54. The data recording medium as set forth in claim 50, wherein n1 is 3 and n2 is 11.

55. The data recording medium as set forth in claim 50, wherein marks are classified by length into three groups of 3T, 4T, and 5T or longer marks, and spaces are classified by length into three groups of 3T, 4T, and 5T or longer spaces.

56. The data recording medium as set forth in claim 50, wherein marks are classified by length into four groups of 3T, 4T, 5T, and 6T or longer marks, and spaces are classified by length into three groups of 3T, 4T, 5T, and 6T or longer spaces.

57. The data recording medium as set forth in claim 48, wherein the method of using the last pulse movement (TL) is to use the last pulse movement (TL) to change the falling edge position of the last pulse without changing the width thereof.

58. The data recording medium as set forth in claim 48, wherein the method of using the last pulse movement (TL) is to use the last pulse movement (TL) to change the width of the last pulse without changing the rising edge position thereof.

59. The data recording medium as set forth in claim 48, wherein the code is recorded at a position before the position where said last pulse movement (TL) is recorded relatively to the direction in which information is recorded.

This Sheet Has Been Replaced

THIS SHEET HAS BEEN REPLACED

AMENDED SHEET

60. A recording and reproducing apparatus for recording and reproducing a data recording medium according to claim 48, said apparatus comprising:

means (1505 - 1508, 1512 — 1517) for reproducing the last pulse movement (TL) and the code, which are prerecorded to the data recording medium;

means (1520) for storing the reproduced last pulse movement (TL) and the code;

means (1510) for generating a drive pulse based on a data recording signal, and correcting the generated drive pulse based on the last pulse movement (TL) and the code;

means (109, 103 — 106) for emitting an optical beam based on the corrected drive pulses to form spaces and marks on the data recording medium.

61. The recording and reproducing apparatus as set forth in claim 60, wherein each of said last pulse movement (TL) is set with respect to a class of combinations of a mark length and a space length, and wherein the reproducing means comprises an equalizer (1514), and the ratio between the output amplitude of the equalizer at the frequency of the longest mark and the output amplitude of the equalizer at the frequency of the shortest mark is 3 dB or less.

62. A method for obtaining a first pulse movement TF for a data recording medium having a plurality of tracks and marks formed by an optical beam modulated by one or a plurality of drive pulses,

said method comprising the steps of

a) generating a pattern signal containing:
   a1) a measuring signal having a mark part with a specific length of PT and a neighboring space part with a specific length of QT where T is a reference period, P is a positive integer and Q is a positive integer, and;
   a2) a reference signal having a mark part with a predetermined length and neighboring space part with a predetermined length, said reference signal located adjacent said measuring signal and is provided to define reference edges adjacent measuring signals;
b) storing the pattern signal;
c) generating one or a plurality of drive pulses corresponding to said mark part of the pattern signal;
d) forming spaces and marks on the data recording medium by an optical beam modulated according to the plurality of drive pulses;
e) reproducing the marks and spaces recorded to the data recording

This Sheet Has Been Replaced

THIS SHEET HAS BEEN REPLACED

medium to obtain a reproduced reproduction signal;

f) obtaining a difference between the reproduced reproduction signal and the stored pattern signal; and

g) obtaining from this difference a first pulse movement TF for application to an original signal containing a sequence of space parts of length QT and mark parts of length PT.

63. The method as set forth in claim 62, wherein said measuring signal has a mark with various lengths each representing a group of one or more mark length, and a space with various lengths each representing a group of one or more space length, and wherein said reference signal has a mark length corresponding to the length of the mark contained in a group of the longest entry in the measuring signal and a space length corresponding to the length of the space contained in a group of the longest entry in the measuring signal.

64. The method as set forth in claim 62, wherein said first pulse movement TF is obtained for a plurality of combinations of mark lengths and space lengths by changing P and Q.

65. The method as set forth in claim 62, wherein the pattern signal contains an adjustment signal for obtaining a DSV of 0.

66. A method for obtaining a last pulse movement TL for a data recording medium having

a plurality of tracks and

marks formed by an optical beam modulated by one or a plurality of drive pulses,

said method comprising the steps of

a) generating a pattern signal containing:

a1) a measuring signal having a mark part with a specific length of PT and a neighboring space part with a specific length of QT where T is a reference period, P is a positive integer, and Q is a positive integer, and;

a2) a reference signal having a mark part with a predetermined length and a neighboring space part with a predetermined length, said reference signal located adjacent said measuring signal and is provided to define reference edges adjacent measuring signals;

b) storing the pattern signal;

c) generating one or a plurality of drive pulses corresponding to said mark

* C L M S *

part of the pattern signal;

d) forming spaces and marks on the data recording medium by an optical beam modulated according to the plurality of drive pulses;

e) reproducing the marks and spaces recorded to the data recording medium to obtain a reproduced reproduction signal;

f) obtaining a difference between the reproduced reproduction signal and the stored pattern signal; and

g) obtaining from this difference a last pulse movement TL for application to an original signal containing a sequence of space parts of length QT and mark parts of length PT.

67. The method as set forth in claim 66, wherein said measuring signal has a mark with various lengths each representing a group of one or more mark length, and a space with various lengths each representing a group of one or more mark length, and wherein said reference signal has a mark length corresponding to the length of the mark contained in a group of the longest entry in the measuring signal and a space length corresponding to the length of the space contained in a group of the longest entry in the measuring signal.

68. The method as set forth in claim 66, wherein said last pulse movement TL is obtained for a plurality of combinations of mark lengths and space lengths by changing P and Q.

69. The method as set forth in claim 66, wherein the pattern signal contains an adjustment signal for obtaining a DSV of 0.

70. An apparatus for obtaining a first pulse movement TF for a data recording medium having

a plurality of tracks and

marks formed by an optical beam modulated by one or a plurality of drive pulses,

said apparatus comprising:

means (125) for generating a pattern signal containing:

a measuring signal having a mark part with a specific length of PT and a neighboring space part with a specific length of QT where T is a reference period, P is a positive integer, and Q is a positive integer, and;

a reference signal having a mark part with a predetermined length and neighboring space part with a predetermined length, said reference signal located

This Sheet Has Been Replaced

THIS SHEET ... BEEN REPLACED

adjacent said measuring signal and is provided to define reference edges adjacent measuring signals;

means (120) for storing the pattern signal;

means (111) for generating one or a plurality of drive pulses corresponding to said mark part of the pattern signal;

means (109, 103-106) for forming spaces and marks on the data recording medium by an optical beam modulated according to the plurality of drive pulses;

means (105-108, 112-115) for reproducing the marks and spaces recorded to the data recording medium to obtain a reproduced reproduction signal;

means (120) for obtaining a difference between the reproduced reproduction signal and the stored pattern signal; and

means (127) for obtaining from this difference a first pulse movement TF for an original signal containing a sequence of space parts of length QT and mark parts of length PT.

71. The apparatus as set forth in claim 70, wherein said measuring signal has a mark with various lengths each representing a group of one or more mark length, and a space with various lengths each representing a group of one or more mark length, and wherein said reference signal has a mark length corresponding to the length of the mark contained in a group of the longest entry in the measuring signal and a space length corresponding to the length of the space contained in a group of the longest entry in the measuring signal.

72. The apparatus as set forth in claim 70, wherein first pulse movement TF is obtained for a plurality of combinations of mark lengths and space lengths by changing P and Q.

73. The apparatus as set forth in claim 70, wherein the combinations are classified, and wherein the reproducing means comprises an equalizer (114), and the ratio between the output amplitude of the equalizer at the frequency of the longest mark and the output amplitude of the equalizer at the frequency of the shortest mark is 3 dB or less, provided that the longest mark and the shortest mark are from the same classification.

74. The apparatus as set forth in claim 70, wherein the pattern signal contains an adjustment signal for obtaining a DSV of 0.

75. An apparatus for obtaining a last pulse movement TL for a data recording

This Sheet Has Been Replaced

AMENDED SHEET

THIS SHEET HAS BEEN REPLACED



medium having

a plurality of tracks and

marks formed by an optical beam modulated by one or a plurality of drive pulses,

said apparatus comprising:

means (125) for generating a pattern signal containing:

a measuring signal having a mark part with a specific length of PT and a neighboring space part with a specific length of QT where T is a reference period, P is a positive integer, and Q is a positive integer, and;

a reference signal having a mark part with a predetermined length and a neighboring space part with a predetermined length, said reference signal located adjacent said measuring signal and is provided to define reference edges adjacent measuring signals;

means (120) for storing the pattern signal;

means (110) for generating one or a plurality of drive pulses corresponding to said mark part of the pattern signal;

means (109, 103-106) for forming spaces and marks on the data recording medium by an optical beam modulated according to the plurality of drive pulses;

means (105-108, 112-115) for reproducing the marks and spaces recorded to the data recording medium to obtain a reproduced reproduction signal;

means (120) for obtaining a difference between the reproduced reproduction signal and the stored pattern signal; and

means (127) for obtaining from this difference a last pulse movement TL for an original signal containing a sequence of space parts of length QT and mark parts of length PT, and storing last pulse movement TL.

76. The apparatus as set forth in claim 75, wherein said measuring signal has a
mark with various lengths each representing a group of one or more mark length, and a space with various lengths each representing a group of one or more mark length, and wherein said reference signal has a mark length corresponding to the length of the mark contained in a group of the longest entry in the measuring signal and a space length corresponding to the length of the space contained in a group of the longest entry in the measuring signal.

77. The apparatus as set forth in claim 75, wherein said first pulse movement TF is obtained for a plurality of combinations of mark lengths and space lengths by changing P and 0.



THIS SHEET HAS BEEN REPLACED

* C L M S *

78. The apparatus as set forth in claim 75, wherein the combinations are classified, and wherein the reproducing means comprises an equalizer (114), and the ratio between the output amplitude of the equalizer at the frequency of the longest mark and the output amplitude of the equalizer at the frequency of the shortest mark is 3 dB or less, provided that the longest mark and the shortest mark are from the same classification.

79. The apparatus as set forth in claim 75, wherein the pattern signal contains an adjustment signal for obtaining a DSV of 0.

This Sheet Has Been Replaced

AMENDED SHEET

THIS SHEET HAS BEEN REPLACED

REPLACEMENT SHEET
05 JUL 2001

CLAIMS

1. A data recording medium having a plurality of tracks for recording information represented as marks and spaces between the marks in a data recording area of the data recording medium, the marks being formed by an optical beam modulated by one or a plurality of drive pulses comprising a first pulse, a last pulse and one or more multiple pulses between the first and last pulses, where a number of the drive pulses is determined according to a length of a mark part in the input signal to be recorded on the track,

characterized by a control information recording area storing:

first pulse movements (TF) for modifying said first pulse of said drive pulses, said first pulse movements (TF) being separated at least into nine groups determined by a combination of three groups of different length of a mark and three groups of different length of a space immediately preceding said mark, the three groups of different mark length being a group with only the first pulse, a group with the first pulse and the last pulse, and a group with the first pulse, the multiple pulse and the last pulse, wherein said first pulse movement (TF) indicates either a pulse shift amount for shifting said first pulse without changing the pulse width, or a pulse width amount for changing the pulse width of said first pulse, and,

a code indicating a method for using said first pulse movement (TF) either as a pulse shift amount or as a pulse width amount.

REPLACEMENT SHEET
05 JUL. 2001

2. The data recording medium as set forth in claim 1, wherein the first pulse movement TF is expressed as a time difference TF between a first reference point R1, which is a leading edge of a mark part in the original signal to be recorded, and a first edge of the first pulse in a plurality of drive pulses.

3. The data recording medium as set forth in claim 1, wherein the length of mark parts in the original signal and the length of space parts between the mark parts are expressed as a value NT where

T is a reference period, and

N is a positive integer from n1 to n2;

mark and space parts are separated into a plurality of groups according to mark and space length; and

specific first pulse movement TF is set for each group.

4. The data recording medium as set forth in claim 1, wherein mark parts are separated by length into four groups, and space parts are separated by length into four groups.

5. The data recording medium as set forth in claim 1, wherein the separation of groups becomes fine as a length of the mark part and a length of the space part decreases.

6. The data recording medium as set forth in claim 3, wherein n1 is 3 and n2 is 11.

7. A recording and reproducing apparatus for recording and reproducing a data recording medium as claimed in claim 1,

said apparatus comprising:

means (1505 - 1508, 1512 - 1517) for reproducing said first pulse movements (TF) and the code from said data recording medium;

means (1520) for storing the reproduced first pulse movements (TF) and the code;

means (1510) for generating a drive pulse based on a data recording signal, and correcting the generated drive pulse based on the first pulse movements (TF) and the code;

means (109, 103 - 106) for emitting an optical beam based on the corrected drive pulses to form spaces and marks on the data recording medium,

wherein said first pulse movement (TF) is set with respect to a class of

* C L M S *

REPLACEMENT SHEET
05 JUL 2001

combinations of mark lengths and space lengths, and wherein the reproducing means comprises an equalizer (1514), and the ratio between the output amplitude of the equalizer at the frequency of the longest mark and the output amplitude of the equalizer at the frequency of the shortest mark is 3 dB or less, provided that the longest mark and the shortest mark are from the same classification.

8. The recording and reproducing apparatus as set forth in claim 7, wherein said first pulse movements (TF) is set with respect to the type of the recording film composition changes.

9. The recording and reproducing apparatus as set forth in claim 7 or 8, wherein said first pulse movements (TF) being set with respect to the disk structure or recording film composition.

10. A data recording medium having a plurality of tracks for recording information represented as marks and spaces between the marks in a data recording area of the data recording medium, the marks being formed by an optical beam modulated by one or a plurality of drive pulses comprising a first pulse, a last pulse and one or more multiple pulses between the first and last pulses, where a number of the drive pulses is determined according to a length of a mark part in the input signal to be recorded on the track,

characterized by a control information recording area storing:

last pulse movements (TL) for modifying said last pulse of said drive pulses, said last pulse movements (TL) being separated at least into nine groups determined by a combination of three groups of different length of a mark and three groups of different length of a space immediately following said mark, the three groups of different mark length being a group with only the first pulse, a group with the first pulse and the last pulse, and a group with the first pulse, the multiple pulse and the last pulse, wherein said last pulse movements (TL) indicates either a pulse shift amount for shifting said last pulse without changing the pulse width, or a pulse width amount for changing the pulse width of said last pulse, and,

a code indicating a method for using said last pulse movement (TL) either as a pulse shift amount or as a pulse width amount.

11. The data recording medium as set forth in claim 10, wherein the last pulse movement TL is expressed as a time difference TL between a first reference point R1, which is a leading edge of a mark part in the original signal to be recorded, and a first edge of the last pulse in a plurality of drive pulses.

* C L H S *

REPLACEMENT SHEET
0 5 JUL 2001

12. The data recording medium as set forth in claim 10, wherein the length of mark parts in the original signal and the length of space parts between the mark parts are expressed as a value NT where

T is a reference period, and

N is a positive integer from n1 to n2;

mark and space parts are separated into a plurality of groups according to mark and space length; and

specific last pulse movement TL is set for each group.

13. The data recording medium as set forth in claim 10, wherein mark parts are separated by length into four groups, and space parts are separated by length into four groups.

14. The data recording medium as set forth in claim 10, wherein the separation of groups becomes fine as a length of the mark part and a length of the space part decreases.

15. The data recording medium as set forth in claim 12, wherein n1 is 3 and n2 is 11.

16. A recording and reproducing apparatus for recording and reproducing a data recording medium as claimed in claim 10,

said apparatus comprising:

means (1505 - 1508, 1512 - 1517) for reproducing said last pulse movements (TL) and the code from said data recording medium;

means (1520) for storing the reproduced last pulse movements (TL) and the code;

means (1510) for generating a drive pulse based on a data recording signal, and correcting the generated drive pulse based on the last pulse movements (TL) and the code;

means (109, 103 - 106) for emitting an optical beam based on the corrected drive pulses to form spaces and marks on the data recording medium,

wherein said last pulse movement (TL) is set with respect to a class of combinations of mark lengths and space lengths, and wherein the reproducing means comprises an equalizer (1514), and the ratio between the output amplitude of the equalizer at the frequency of the longest mark and the output amplitude of the equalizer at the frequency of the shortest mark is 3 dB or less, provided that the longest mark and the shortest mark are from the same classification.

REPLACEMENT SHEET
05 JUL 2001

17. The recording and reproducing apparatus as set forth in claim 16, wherein said last pulse movements (TL) is set with respect to the type of the recording film composition changes.

18. The recording and reproducing apparatus as set forth in claim 16 or 17, wherein said last pulse movements (TL) being set with respect to the disk structure or recording film composition.

19. A data recording medium having a plurality of tracks for recording information represented as marks and spaces between the marks in a data recording area of the data recording medium, the marks being formed by an optical beam modulated by one or a plurality of drive pulses where a number of the drive pulses is determined according to a length of a mark part in the input signal to be recorded on the track,

characterized by a control information recording area storing:

a first pulse movement (TF) for modifying a first pulse of said drive pulses, and a last pulse movement (TL) for modifying a last pulse of said drive pulses, wherein said first pulse movement (TF) and last pulse movement (TL) indicate either a pulse shift amount for shifting said first and last pulses, respectively, without changing the pulse width, or a pulse width amount for changing the pulse width of said first and last pulses, respectively, and,

a code indicating a method for using said first pulse movement (TF) and last pulse movement (TL) either as a pulse shift amount or as a pulse width amount.

20. The data recording medium as set forth in claim 19, wherein the first pulse amount (TF) is expressed as a time difference between a reference point (R1), which is located a predetermined distance from a leading edge of a mark, and a first edge of the first pulse, and

the last pulse amount (TL) is expressed as a time difference between a reference point (R2), which is located a predetermined distance from a trailing edge of a mark, and a trailing edge of the last pulse.

21. The data recording medium as set forth in claim 19, wherein the length of a mark in the input signal and the length of a space between the marks are expressed as a value NT where

T is a reference period, and

N is a positive integer from n1 to n2;

REPLACEMENT SHEET
05 JUL 2001

marks and spaces are classified into a plurality of groups according to the mark length and the space length; and

a specific first pulse movement (TF) and last pulse movement (TL) are set for each group.

22. The data recording medium as set forth in claim 21, wherein the marks are classified by length into three groups, and the spaces are classified by length into three groups.

23. The data recording medium as set forth in claim 21, wherein the marks are classified by length into four groups, and the spaces are classified by length into four groups.

24. The data recording medium as set forth in claim 21, wherein the number of groups increases as the length of the mark and the length of the space decreases.

25. The data recording medium as set forth in claim 21, wherein n1 is 3 and n2 is 11.

26. The data recording medium as set forth in claim 21, wherein marks are classified by length into three groups of 3T, 4T, and 5T or longer marks, and spaces are classified by length into three groups of 3T, 4T, and 5T or longer spaces.

27. The data recording medium as set forth in claim 21, wherein marks are classified by length into four groups of 3T, 4T, 5T, and 6T or longer marks, and spaces are classified by length into three groups of 3T, 4T, 5T, and 6T or longer spaces.

28. The data recording medium as set forth in claim 19, wherein there are two more methods of using the first pulse movement (TF) and last pulse movement (TL), and wherein information indicative of the method of use is prerecorded to the control information recording area.

29. The data recording medium as set forth in claim 28, wherein the method of using the first pulse movement (TF) is to use the first pulse movement (TF) to change the rising edge portion of the first pulse without changing the width thereof, and the method of using the last pulse movement (TL) is to use the last pulse

* C L M S *

REPLACEMENT SHEET
05 JUL 2001

movement (TL) to change the falling edge position of the last pulse without changing the width thereof.

30. The data recording medium as set forth in claim 28, wherein the method of using the first pulse movement (TF) is to use the first pulse movement (TF) to change the width of the first pulse without changing the falling edge position thereof, and the method of using the last pulse movement (TL) is to use the last pulse movement (TL) to change the width of the last pulse without changing the rising edge position thereof.

31. The data recording medium as set forth in claim 28, wherein the information indicative of the method of the first pulse movement (TF) and the last pulse movement (TL) is recorded to the position before the position where the first pulse movement (TF) and last pulse movement (TL) values are recorded relatively to the direction in which information is recorded.

32. A recording and reproducing apparatus for recording and reproducing a data recording medium according to claim 19, said apparatus comprising:

means (1505 — 1508, 1512 — 1517) for reproducing the first pulse movement (TF) and the code, which are prerecorded to the data recording medium;

means (1520) for storing the reproduced first pulse movement (TF) and the code;

means (1510) for generating a drive pulse based on a data recording signal, and correcting the generated drive pulse based on the first pulse movement (TF) and the last pulse movement (TL), said code selecting the use of said first pulse movement (TF) and said last pulse movement (TL) either as a pulse shift amount or as a pulse width amount.;

means (109, 103 — 106) for emitting an optical beam based on the corrected drive pulses to form spaces and marks on the data recording medium.

33. The recording and reproducing apparatus as set forth in claim 32, wherein each of said first pulse movement (TF) and last pulse movement (TL) is set with respect to a class of combinations of a mark length and a space length, and wherein the reproducing means comprises an equalizer (1514), and the ratio between the output amplitude of the equalizer at the frequency of the longest mark and the output amplitude of the equalizer at the frequency of the shortest mark is 3 dB or less.

* C L M S *

REPLACEMENT SHEET
05 JUL 2001

34. A data recording medium having a plurality of tracks for recording information represented as marks and spaces between the marks in a data recording area of the data recording medium, the marks being formed by an optical beam modulated by one or a plurality of drive pulses where a number of the drive pulses is determined according to a length of a mark part in the input signal to be recorded on the track,

characterized by a control information recording area storing:

a first pulse movement (TF) for modifying a first pulse of said drive pulses, wherein said first pulse movement (TF) indicates either a pulse shift amount for shifting said first pulse without changing the pulse width, or a pulse width amount for changing the pulse width of said first pulse, and

a code indicating a method for using said first pulse movement (TF) either as a pulse shift amount or as a pulse width amount.

35. The data recording medium as set forth in claim 34, wherein the first pulse amount (TF) is expressed as a time difference between a reference point (R1), which is located a predetermined distance from a leading edge of a mark, and a first edge of the first pulse.

36. The data recording medium as set forth in claim 34, wherein the length of a mark in the input signal and the length of a space between the marks are expressed as a value NT where

T is a reference period, and

N is a positive integer from n1 to n2;

marks and spaces are classified into a plurality of groups according to the mark length and the space length; and

a specific first pulse movement (TF) is set for each group.

37. The data recording medium as set forth in claim 36, wherein the marks are classified by length into three groups, and the spaces are classified by length into three groups.

38. The data recording medium as set forth in claim 36, wherein the marks are classified by length into four groups, and the spaces are classified by length into four groups.

39. The data recording medium as set forth in claim 36, wherein the number of groups increases as the length of the mark and the length of the space decreases.

REPLACEMENT SHEET
05 JUL 2001

40. The data recording medium as set forth in claim 36, wherein n1 is 3 and n2 is 11.

41. The data recording medium as set forth in claim 36, wherein marks are classified by length into three groups of 3T, 4T, and 5T or longer marks, and spaces are classified by length into three groups of 3T, 4T, and 5T or longer spaces.

42. The data recording medium as set forth in claim 36, wherein marks are classified by length into four groups of 3T, 4T, 5T, and 6T or longer marks, and spaces are classified by length into three groups of 3T, 4T, 5T, and 6T or longer spaces.

43. The data recording medium as set forth in claim 34, wherein the method of using the first pulse movement (TF) is to use the first pulse movement (TF) to change the rising edge position of the first pulse without changing the width thereof.

44. The data recording medium as set forth in claim 34, wherein the method of using the first pulse movement (TF) is to use the first pulse movement (TF) to change the width of the first pulse without changing the falling edge position thereof.

45. The data recording medium as set forth in claim 34, wherein the code is recorded at a position before the position where said first pulse movement (TF) is recorded relatively to the direction in which information is recorded.

46. A recording and reproducing apparatus for recording and reproducing a data recording medium according to claim 34,

said apparatus comprising:

means (1505 — 1508, 1512 — 1517) for reproducing the first pulse movement (TF) and the code, which are prerecorded to the data recording medium;

means (1520) for storing the reproduced first pulse movement (TF) and the code;

means (1510) for generating a drive pulse based on a data recording signal, and correcting the generated drive pulse based on the first pulse movement (TF), said code selecting the use of said first pulse movement (TF) either as a pulse shift amount or as a pulse width amount;

REPLACEMENT SHEET
05 JUL 2001

means (109, 103 — 106) for emitting an optical beam based on the corrected drive pulses to form spaces and marks on the data recording medium.

47. The recording and reproducing apparatus as set forth in claim 46, wherein each of said first pulse movement (TF) is set with respect to a class of combinations of a mark length and a space length, and wherein the reproducing means comprises an equalizer (1514), and the ratio between the output amplitude of the equalizer at the frequency of the longest mark and the output amplitude of the equalizer at the frequency of the shortest mark is 3 dB or less.

48. A data recording medium having a plurality of tracks for recording information represented as marks and spaces between the marks in a data recording area of the data recording medium, the marks being formed by an optical beam modulated by one or a plurality of drive pulses where a number of the drive pulses is determined according to a length of a mark part in the input signal to be recorded on the track,

characterized by a control information recording area storing:

a last pulse movement (TL) for modifying a last pulse of said drive pulses, wherein said last pulse movement (TL) indicates either a pulse shift amount for shifting said last pulse without changing the pulse width, or a pulse width amount for changing the pulse width of said last pulse, and,

a code indicating a method for using said last pulse movement (TL) either as a pulse shift amount or as a pulse width amount.

49. The data recording medium as set forth in claim 48, wherein the last pulse amount (TL) is expressed as a time difference between a reference point (R2), which is located a predetermined distance from a trailing edge of a mark, and a trailing edge of the last pulse.

50. The data recording medium as set forth in claim 48, wherein the length of a mark in the input signal and the length of a space between the marks are expressed as a value NT where

T is a reference period, and

N is a positive integer from n1 to n2;

marks and spaces are classified into a plurality of groups according to the mark length and the space length; and

a specific last pulse movement (TL) is set for each group.

REPLACEMENT SHEET

05 JUL 2001

51. The data recording medium as set forth in claim 50, wherein the marks are classified by length into three groups, and the spaces are classified by length into three groups.

52. The data recording medium as set forth in claim 50, wherein the marks are classified by length into four groups, and the spaces are classified by length into four groups.

53. The data recording medium as set forth in claim 51, wherein the number of groups increases as the length of the mark and the length of the space decreases.

54. The data recording medium as set forth in claim 50, wherein n1 is 3 and n2 is 11.

55. The data recording medium as set forth in claim 50, wherein marks are classified by length into three groups of 3T, 4T, and 5T or longer marks, and spaces are classified by length into three groups of 3T, 4T, and 5T or longer spaces.

56. The data recording medium as set forth in claim 50, wherein marks are classified by length into four groups of 3T, 4T, 5T, and 6T or longer marks, and spaces are classified by length into three groups of 3T, 4T, 5T, and 6T or longer spaces.

57. The data recording medium as set forth in claim 48, wherein the method of using the last pulse movement (TL) is to use the last pulse movement (TL) to change the falling edge position of the last pulse without changing the width thereof.

58. The data recording medium as set forth in claim 48, wherein the method of using the last pulse movement (TL) is to use the last pulse movement (TL) to change the width of the last pulse without changing the rising edge position thereof.

59. The data recording medium as set forth in claim 48, wherein the code is recorded at a position before the position where said last pulse movement (TL) is recorded relatively to the direction in which information is recorded.

* C L M S *

REPLACEMENT SHEET

60. A recording and reproducing apparatus for recording and reproducing a data recording medium according to claim 48, said apparatus comprising:

means (1505 - 1508, 1512 — 1517) for reproducing the last pulse movement (TL) and the code, which are prerecorded to the data recording medium;

means (1520) for storing the reproduced last pulse movement (TL) and the code;

means (1510) for generating a drive pulse based on a data recording signal, and correcting the generated drive pulse based on the last pulse movement (TL) and the code;

means (109, 103 — 106) for emitting an optical beam based on the corrected drive pulses to form spaces and marks on the data recording medium.

61. The recording and reproducing apparatus as set forth in claim 60, wherein each of said last pulse movement (TL) is set with respect to a class of combinations of a mark length and a space length, and wherein the reproducing means comprises an equalizer (1514), and the ratio between the output amplitude of the equalizer at the frequency of the longest mark and the output amplitude of the equalizer at the frequency of the shortest mark is 3 dB or less.

62. A method for obtaining a first pulse movement TF for a data recording medium having a plurality of tracks and marks formed by an optical beam modulated by one or a plurality of drive pulses,

said method comprising the steps of

a) generating a pattern signal containing:
   a1) a measuring signal having a mark part with a specific length of PT and a neighboring space part with a specific length of QT where T is a reference period, P is a positive integer and Q is a positive integer, and;
   a2) a reference signal having a mark part with a predetermined length and neighboring space part with a predetermined length, said reference signal located adjacent said measuring signal and is provided to define reference edges adjacent measuring signals;
b) storing the pattern signal;
c) generating one or a plurality of drive pulses corresponding to said mark part of the pattern signal;
d) forming spaces and marks on the data recording medium by an optical beam modulated according to the plurality of drive pulses;
e) reproducing the marks and spaces recorded to the data recording

REPLACEMENT SHEET
05 JUN 2001

medium to obtain a reproduced reproduction signal;

f) obtaining a difference between the reproduced reproduction signal and the stored pattern signal; and

g) obtaining from this difference a first pulse movement TF for application to an original signal containing a sequence of space parts of length QT and mark parts of length PT.

63. The method as set forth in claim 62, wherein said measuring signal has a mark with various lengths each representing a group of one or more mark length, and a space with various lengths each representing a group of one or more space length, and wherein said reference signal has a mark length corresponding to the length of the mark contained in a group of the longest entry in the measuring signal and a space length corresponding to the length of the space contained in a group of the longest entry in the measuring signal.

64. The method as set forth in claim 62, wherein said first pulse movement TF is obtained for a plurality of combinations of mark lengths and space lengths by changing P and Q.

65. The method as set forth in claim 62, wherein the pattern signal contains an adjustment signal for obtaining a DSV of 0.

66. A method for obtaining a last pulse movement TL for a data recording medium having

a plurality of tracks and

marks formed by an optical beam modulated by one or a plurality of drive pulses,

said method comprising the steps of

a) generating a pattern signal containing:

a1) a measuring signal having a mark part with a specific length of PT and a neighboring space part with a specific length of QT where T is a reference period, P is a positive integer, and Q is a positive integer, and;

a2) a reference signal having a mark part with a predetermined length and a neighboring space part with a predetermined length, said reference signal located adjacent said measuring signal and is provided to define reference edges adjacent measuring signals;

b) storing the pattern signal;

c) generating one or a plurality of drive pulses corresponding to said mark

REPLACEMENT SHEET

05 JUN 2001

part of the pattern signal;

d) forming spaces and marks on the data recording medium by an optical beam modulated according to the plurality of drive pulses;

e) reproducing the marks and spaces recorded to the data recording medium to obtain a reproduced reproduction signal;

f) obtaining a difference between the reproduced reproduction signal and the stored pattern signal; and

g) obtaining from this difference a last pulse movement TL for application to an original signal containing a sequence of space parts of length QT and mark parts of length PT.

67. The method as set forth in claim 66, wherein said measuring signal has a mark with various lengths each representing a group of one or more mark length, and a space with various lengths each representing a group of one or more mark length, and wherein said reference signal has a mark length corresponding to the length of the mark contained in a group of the longest entry in the measuring signal and a space length corresponding to the length of the space contained in a group of the longest entry in the measuring signal.

68. The method as set forth in claim 66, wherein said last pulse movement TL is obtained for a plurality of combinations of mark lengths and space lengths by changing P and Q.

69. The method as set forth in claim 66, wherein the pattern signal contains an adjustment signal for obtaining a DSV of 0.

70. An apparatus for obtaining a first pulse movement TF for a data recording medium having

a plurality of tracks and

marks formed by an optical beam modulated by one or a plurality of drive pulses,

said apparatus comprising:

means (125) for generating a pattern signal containing:

a measuring signal having a mark part with a specific length of PT and a neighboring space part with a specific length of QT where T is a reference period, P is a positive integer, and Q is a positive integer, and;

a reference signal having a mark part with a predetermined length and neighboring space part with a predetermined length, said reference signal located

REPLACEMENT SHEET

05 JAN 2001

adjacent said measuring signal and is provided to define reference edges adjacent measuring signals;

means (120) for storing the pattern signal;

means (111) for generating one or a plurality of drive pulses corresponding to said mark part of the pattern signal;

means (109, 103-106) for forming spaces and marks on the data recording medium by an optical beam modulated according to the plurality of drive pulses;

means (105-108, 112-115) for reproducing the marks and spaces recorded to the data recording medium to obtain a reproduced reproduction signal;

means (120) for obtaining a difference between the reproduced reproduction signal and the stored pattern signal; and

means (127) for obtaining from this difference a first pulse movement TF for an original signal containing a sequence of space parts of length QT and mark parts of length PT.

71. The apparatus as set forth in claim 70, wherein said measuring signal has a mark with various lengths each representing a group of one or more mark length, and a space with various lengths each representing a group of one or more mark length, and wherein said reference signal has a mark length corresponding to the length of the mark contained in a group of the longest entry in the measuring signal and a space length corresponding to the length of the space contained in a group of the longest entry in the measuring signal.

72. The apparatus as set forth in claim 70, wherein first pulse movement TF is obtained for a plurality of combinations of mark lengths and space lengths by changing P and Q.

73. The apparatus as set forth in claim 70, wherein the combinations are classified, and wherein the reproducing means comprises an equalizer (114), and the ratio between the output amplitude of the equalizer at the frequency of the longest mark and the output amplitude of the equalizer at the frequency of the shortest mark is 3 dB or less, provided that the longest mark and the shortest mark are from the same classification.

74. The apparatus as set forth in claim 70, wherein the pattern signal contains an adjustment signal for obtaining a DSV of 0.

75. An apparatus for obtaining a last pulse movement TL for a data recording

REPLACEMENT SHEET

05 JUL 2001

medium having

a plurality of tracks and

marks formed by an optical beam modulated by one or a plurality of drive pulses,

said apparatus comprising:

means (125) for generating a pattern signal containing:

a measuring signal having a mark part with a specific length of PT and a neighboring space part with a specific length of QT where T is a reference period, P is a positive integer, and Q is a positive integer, and;

a reference signal having a mark part with a predetermined length and a neighboring space part with a predetermined length, said reference signal located adjacent said measuring signal and is provided to define reference edges adjacent measuring signals;

means (120) for storing the pattern signal;

means (110) for generating one or a plurality of drive pulses corresponding to said mark part of the pattern signal;

means (109, 103-106) for forming spaces and marks on the data recording medium by an optical beam modulated according to the plurality of drive pulses;

means (105-108, 112-115) for reproducing the marks and spaces recorded to the data recording medium to obtain a reproduced reproduction signal;

means (120) for obtaining a difference between the reproduced reproduction signal and the stored pattern signal; and

means (127) for obtaining from this difference a last pulse movement TL for an original signal containing a sequence of space parts of length QT and mark parts of length PT, and storing last pulse movement TL.

76. The apparatus as set forth in claim 75, wherein said measuring signal has a

mark with various lengths each representing a group of one or more mark length, and a space with various lengths each representing a group of one or more mark length, and wherein said reference signal has a mark length corresponding to the length of the mark contained in a group of the longest entry in the measuring signal and a space length corresponding to the length of the space contained in a group of the longest entry in the measuring signal.

77. The apparatus as set forth in claim 75, wherein said first pulse movement TF is obtained for a plurality of combinations of mark lengths and space lengths by changing P and Q.

* C L M S *

REPLACEMENT SHEET
05 JUL 2001

78. The apparatus as set forth in claim 75, wherein the combinations are classified, and wherein the reproducing means comprises an equalizer (114), and the ratio between the output amplitude of the equalizer at the frequency of the longest mark and the output amplitude of the equalizer at the frequency of the shortest mark is 3 dB or less, provided that the longest mark and the shortest mark are from the same classification.

79. The apparatus as set forth in claim 75, wherein the pattern signal contains an adjustment signal for obtaining a DSV of 0.