

WIRELESS COMMUNICATION METHOD, TERMINAL DEVICE AND NETWORK DEVICE

TECHNICAL FIELD

[0001] The present application relates to the field of communication, and more particularly,
5 to a wireless communication method, a terminal device, and a network device.

BACKGROUND

[0002] In a wireless communication system, a demodulation reference signal (DMRS) sequence may be used for correlation demodulation of a channel. When multi-user multiplexing is performed in an uplink, orthogonality may be obtained between different terminal devices by
10 using a same DMRS sequence, but different cyclic shifts or different orthogonal codes. A number of terminal devices that use orthogonal codes to obtain orthogonality for supporting multiplexing is small.

[0003] The terminal device may use, for example, discrete Fourier transform orthogonal frequency division multiplexing based spread spectrum (DFT-S-OFDM) multiple access mode
15 or cyclic prefix orthogonal frequency division multiplexing (CP-OFDM) multiple access mode for uplink transmission. The DFT-S-OFDM multiple access mode may also be referred to as single carrier-frequency division multiple access (SC-FDMA) mode. The CP-OFDM system may also be referred to as orthogonal frequency division multiple access (OFDMA) mode.

[0004] How to realize multi-user multiplexing performed by terminal devices that transmit
20 DMRS sequences using different multiple access modes is an urgent problem to be solved.

SUMMARY

[0005] Embodiments of the present application provide a wireless communication method, a terminal device and a network device, which can realize multi-user multiplexing performed

by terminal devices that transmit DMRS sequences using different multiple access modes.

[0006] A first aspect provides a wireless communication method, including:

[0007] determining, by a terminal device, a quantity K of demodulation reference signal DMRS sequences corresponding to a first DMRS port and a physical resource occupied by each

5 DMRS sequence in the K DMRS sequences, where K is a positive integer; and

[0008] sending, on the determined physical resource occupied by the each DMRS sequence, the each DMRS sequence to a network device using the first DMRS port.

[0009] In combination with the first aspect, in a possible implementation of the first aspect, the determining, by a terminal device, a quantity K of DMRS sequences corresponding to a first
10 DMRS port and a physical resource occupied by each DMRS sequence in the K DMRS sequences, includes:

[0010] determining, by the terminal device, the quantity K of the DMRS sequences corresponding to the first DMRS port and/or the physical resource occupied by the each DMRS sequence in the K DMRS sequences according to a multiple access mode used in sending the

15 DMRS sequences using the first DMRS port.

[0011] In combination with the first aspect or any one of the above possible implementations thereof, in a possible implementation of the first aspect, the determining, by the terminal device, the quantity K of the DMRS sequences corresponding to the first DMRS port according to a multiple access mode used in sending the DMRS sequences using the first

20 DMRS port, includes:

[0012] determining the quantity K of the DMRS sequences corresponding to the first DMRS port according to a first corresponding relation and the multiple access mode used in sending the DMRS sequences using the first DMRS port;

[0013] where, the first corresponding relation is configured to indicate a quantity of DMRS
25 sequences corresponding to the first DMRS port under each multiple access mode in at least one multiple access mode.

[0014] In combination with the first aspect or any one of the above possible implementations thereof, in a possible implementation of the first aspect, the determining, by the terminal device, the physical resource occupied by the each DMRS sequence in the K
30 DMRS sequences according to a multiple access mode used in sending the DMRS sequences

using the first DMRS port, includes:

[0015] determining the physical resource occupied by the each DMRS sequence in the K DMRS sequences according to a second corresponding relation and the multiple access mode used in sending the DMRS sequences using the first DMRS port;

5 **[0016]** where, the second corresponding relation is configured to indicate a physical resource corresponding to each DMRS sequence in at least one DMRS sequence corresponding to the first DMRS port under each multiple access mode in the at least one multiple access mode.

[0017] In combination with the first aspect or any one of the above possible
10 implementations thereof, in a possible implementation of the first aspect, when the multiple access mode used in sending the DMRS sequences using the first DMRS port is a first multiple access mode, the K DMRS sequences include a first DMRS sequence, where the first DMRS sequence occupies a same physical resource and/or uses a same root sequence as a second DMRS sequence included in DMRS sequences transmitted using a same DMRS port when a
15 second multiple access mode is used, where the second multiple access mode is difference from the first multiple access mode.

[0018] In combination with the first aspect or any one of the above possible implementations thereof, in a possible implementation of the first aspect, the first multiple access mode is a discrete Fourier transform orthogonal frequency division multiplexing based
20 spread spectrum DFT-S-OFDM multiple access mode, and the second multiple access mode is a cyclic prefix orthogonal frequency division multiplexing CP-OFDM multiple access mode;
or,

[0019] the first multiple access mode is the CP-OFDM multiple access mode, and the second multiple access mode is the DFT-S-OFDM multiple access mode.

25 **[0020]** In combination with the first aspect or any one of the above possible implementations thereof, in a possible implementation of the first aspect, when the multiple access mode used in sending the DMRS sequences using the first DMRS port is a DFT-S-OFDM multiple access mode, K is an integer greater than 1; and/or,

[0021] when the multiple access mode used in sending the DMRS sequences using the first
30 DMRS port is a CP-OFDM multiple access mode, K is 1.

[0022] In combination with the first aspect or any one of the above possible implementations thereof, in a possible implementation of the first aspect, the determining, by a terminal device, a quantity K of demodulation reference signal DMRS sequences corresponding to a first DMRS port, includes:

5 **[0023]** determining, by the terminal device, the quantity K of the DMRS sequences corresponding to the first DMRS port according to DMRS sequence indication information carried in downlink control information DCI transmitted by scheduling data corresponding to the DMRS sequences by the network device.

[0024] In combination with the first aspect or any one of the above possible
10 implementations thereof, in a possible implementation of the first aspect, K is an integer greater than 1.

[0025] In combination with the first aspect or any one of the above possible implementations thereof, in a possible implementation of the first aspect, when a value of K is greater than 1, DMRS sequences in the K DMRS sequences having a same length uses a same
15 sequence.

[0026] In combination with the first aspect or any one of the above possible implementations thereof, in a possible implementation of the first aspect, when a value of K is greater than 1, the each DMRS sequence in the K DMRS sequences occupies, in at least one OFDM symbol, different sub-carriers in a same frequency domain bandwidth respectively.

20 **[0027]** In combination with the first aspect or any one of the above possible implementations thereof, in a possible implementation of the first aspect, a sub-carrier occupied by an m^{th} DMRS sequence in the K DMRS sequences is: an $(m+iK)^{\text{th}}$ sub-carrier in the frequency domain bandwidth, where $i = 0, 1, \dots, \lfloor (S - m) / K \rfloor$, and S is a quantity of sub-carriers included in the frequency domain bandwidth.

25 **[0028]** In combination with the first aspect or any one of the above possible implementations thereof, in a possible implementation of the first aspect, $K=2$, and a subcarrier occupied by a first DMRS sequence in the K DMRS sequences is an $(n+jN)^{\text{th}}$ subcarrier in the frequency domain bandwidth, and a second DMRS sequence occupies the rest subcarrier in the frequency domain bandwidth, where $j = 0, 1, \dots, \lfloor (S - n) / N \rfloor$, N is a positive integer greater

than 1, and n is a positive integer less than or equal to N .

[0029] In combination with the first aspect or any one of the above possible implementations thereof, in a possible implementation of the first aspect, each DMRS sequence in at least one DMRS sequence in the K DMRS sequences occupies different sub-carriers in different OFDM symbols.

[0030] In combination with the first aspect or any one of the above possible implementations thereof, in a possible implementation of the first aspect, the determining, by a terminal device, a quantity K of DMRS sequences corresponding to a first DMRS port and a physical resource occupied by each DMRS sequence in the K DMRS sequences includes:

[0031] determining, by the terminal device, the quantity K of the DMRS sequences corresponding to the first DMRS port; and

[0032] determining, by the terminal device, a resource offset between physical resources occupied by different DMRS sequences in the K DMRS sequences according to the quantity K when the K is greater than 1.

[0033] A second aspect provides a wireless communication method, including:

[0034] determining, by a network device, a quantity K of demodulation reference signal DMRS sequences sent by a terminal device using a first DMRS port, and a physical resource occupied by each DMRS sequence in the K DMRS sequences; and

[0035] receiving, on the determined physical resource occupied by the each DMRS sequence, the each DMRS sequence sent by the terminal device.

[0036] In combination with the second aspect, in a possible implementation of the second aspect, the determining, by a network device, a quantity K of demodulation reference signal DMRS sequences sent by a terminal device using a first DMRS port and a physical resource occupied by each DMRS sequence in the K DMRS sequences, includes:

[0037] determining, by the network device, the quantity K of the DMRS sequences sent by the terminal device using the first DMRS port and/or the physical resource occupied by the each DMRS sequence in the K DMRS sequences according to a multiple access mode used by the terminal device in sending the DMRS sequences using the first DMRS port.

[0038] In combination with the second aspect or any one of the above possible implementations thereof, in a possible implementation of the second aspect, the determining,

by the network device, the quantity K of the DMRS sequences sent by the terminal device using the first DMRS port according to a first multiple access mode used by the terminal device in sending the DMRS sequences using the first DMRS port includes:

[0039] determining the quantity K of the DMRS sequences sent by the terminal device using the first DMRS port according to a first corresponding relation and the multiple access mode used by the terminal device in sending the DMRS sequences using the first DMRS port; where,

[0040] the first corresponding relation is configured to indicate a quantity of DMRS sequences corresponding to the first DMRS port under each multiple access mode in at least one multiple access mode.

[0041] In combination with the second aspect or any one of the above possible implementations thereof, in a possible implementation of the second aspect, the determining, by the network device, the physical resource occupied by the each DMRS sequence in the K DMRS sequences according to a multiple access mode used by the terminal device in sending the DMRS sequences using the first DMRS port, includes:

[0042] determining the physical resource occupied by the each DMRS sequence in the K DMRS sequences according to a second corresponding relation and the multiple access mode used by the terminal device in sending the DMRS sequences using the first DMRS port; where,

[0043] the second corresponding relation is configured to indicate a physical resource corresponding to each DMRS sequence in at least one DMRS sequence corresponding to the first DMRS port under each multiple access mode in the at least one multiple access mode.

[0044] In combination with the second aspect or any one of the above possible implementations thereof, in a possible implementation of the second aspect, the method further includes:

[0045] indicating, by the network device, the quantity K of the DMRS sequences corresponding to the DMRS port to the terminal device by DMRS sequence indication information carried in downlink control information DCI transmitted by scheduling data corresponding to the DMRS sequences.

[0046] In combination with the second aspect or any one of the above possible implementations thereof, in a possible implementation of the second aspect, when the multiple

access mode used by the terminal device in sending the DMRS sequences using the first DMRS port is a DFT-S-OFDM multiple access mode, K is an integer greater than 1; and/or,

[0047] when the multiple access mode used by the terminal device in sending the DMRS sequences using the first DMRS port is a CP-OFDM multiple access mode, K is 1.

5 **[0048]** In combination with the second aspect or any one of the above possible implementations thereof, in a possible implementation of the second aspect, K is an integer greater than 1.

[0049] In combination with the second aspect or any one of the above possible implementations thereof, in a possible implementation of the second aspect, when a value of K is greater than 1, the each DMRS sequence in the K DMRS sequences occupies, in at least one OFDM symbol, different sub-carriers in a same frequency domain bandwidth respectively.

10 **[0050]** In combination with the second aspect or any one of the above possible implementations thereof, in a possible implementation of the second aspect, each DMRS sequence in at least one DMRS sequence in the K DMRS sequences occupies different sub-carriers in different OFDM symbols.

[0051] A third aspect provides a terminal device, which may include a unit configured to implement the method of the first aspect or any one of the possible implementations of the first aspect described above.

20 **[0052]** A fourth aspect provides a network device, which may include a unit configured to implement the method of the second aspect or any one of the possible implementations of the second aspect described above.

[0053] A fifth aspect provides a terminal device, which may include a memory and a processor, where the memory stores an instruction, and the memory is configured to invoke the instruction stored in the memory to perform the method according to the first aspect or any one of the possible implementations of the first aspect.

[0054] A sixth aspect provides a network device, which may include a memory and a processor, where the memory stores an instruction, and the memory is configured to invoke the instruction stored in the memory to perform the method according to the second aspect or any one of the possible implementations of the second aspect.

30 **[0055]** A seventh aspect provides a computer readable medium, configured to store a

program code executed by a terminal device, where the program code includes an instruction configured to perform the method according to the first aspect or the various implementations of the first aspect, or includes an instruction configured to perform the method according to the second aspect or the various implementations of the second aspect.

5 **[0056]** An eighth aspect provides a system chip, including an input interface, an output interface, a processor and a memory, where the processor is configured to execute a code in the memory, and when the code is executed, the processor may implement the method according to the first aspect and the various implementations of the first aspect described above, or perform the method according to the second aspect and the various implementations of the second aspect described above.

10 **[0057]** Therefore, in the embodiments of the present application, a quantity of DMRS sequences corresponding to one DMRS port may not be unique and may be flexibly changed. For example, such corresponding relationship may be set according to a multiple access mode used by a plurality of terminal devices which need orthogonal multiplexing, so that multi-user multiplexing of terminal devices that use different multiple access modes may be supported.

15 Further, since the quantity of the DMRS sequences corresponding to one DMRS port and resource occupied by each sequence may be flexibly changed, it may be realized that there is at least one DMRS sequence in the terminal devices using different multiple access modes that corresponds to a same root sequence and/or occupy a same physical resource, so that the

20 terminal devices using different multiple access modes can obtain DMRS orthogonality by using different cyclic shifts, thereby enabling multi-user multiplexing transmission supporting more terminal devices.

BRIEF DESCRIPTION OF DRAWINGS

25 **[0058]** In order to more clearly illustrate technical solutions in embodiments of the present application, accompanying drawings required for describing the embodiments or the prior art will be briefly described below. Obviously, the accompanying drawings in the following description are some of the embodiments of the present application, and other drawings can be obtained by those skilled in the art based on these accompanying drawings without any creative

effort.

[0059] FIG. 1 is a schematic diagram of a wireless communication system according to an embodiment of the present application;

5 **[0060]** FIG. 2 is a schematic flowchart of a wireless communication method according to an embodiment of the present application;

[0061] FIG. 3 is a schematic diagram of resource occupancy of a DMRS sequence according to an embodiment of the present application;

[0062] FIG. 4 is a schematic diagram of resource occupancy of a DMRS sequence according to an embodiment of the present application;

10 **[0063]** FIG. 5 is a schematic diagram of resource occupancy of a DMRS sequence according to an embodiment of the present application;

[0064] FIG. 6 is a schematic diagram of resource occupancy of a DMRS sequence according to an embodiment of the present application;

15 **[0065]** FIG. 7 is a schematic diagram of resource occupancy of a DMRS sequence according to an embodiment of the present application;

[0066] FIG. 8 is a schematic diagram of resource occupancy of a DMRS sequence according to an embodiment of the present application;

[0067] FIG. 9 is a schematic diagram of resource occupancy of a DMRS sequence according to an embodiment of the present application;

20 **[0068]** FIG. 10 is a schematic block diagram of a terminal device according to an embodiment of the present application;

[0069] FIG. 11 is a schematic block diagram of a network device according to an embodiment of the present application;

25 **[0070]** FIG. 12 is a schematic block diagram of a communication device according to an embodiment of the present application; and

[0071] FIG. 13 is a schematic block diagram of a system chip according to an embodiment of the present application.

DESCRIPTION OF EMBODIMENTS

[0072] Technical solutions in the embodiments of the present application will be described in combination with the accompanying drawings in the embodiments of the present application. It is obvious that the described embodiments are some of, instead all of, the embodiments of the present application. All other embodiments obtained by those skilled in the art based on the
5 embodiments of the present application without any creative effort are within the protection scope of the present application.

[0073] The technical solutions of the embodiments of the present application can be applied to various communication systems, for example, a global system of mobile communication
10 (GSM) system, a code division multiple access (CDMA) system, a wideband code division multiple access (WCDMA) system, a general packet radio service (GPRS), a long term evolution (LTE) system, an LTE frequency division duplex (FDD) system, an LTE time division duplex (TDD), a universal mobile telecommunication system (UMTS), a worldwide interoperability for Microwave Access (WiMAX) communication system or a future 5G system,
15 or the like.

[0074] FIG. 1 illustrated a wireless communication system 100 applied in the embodiments of the application. The wireless communication system 100 may include a network device 110. The network device 100 may be a device communicated with a terminal device. The network device 100 may provide communication coverage for a particular geographic area and may
20 communicate with a terminal device (e.g., a UE) located within the coverage area. Optionally, the network device 100 may be a base transceiver station (BTS) in a GSM system or a CDMA system, or may be a base station (NodeB, NB) in a WCDMA system, or may also be an evolutionary Node B (eNB or eNodeB) in an LTE system, or a wireless controller in a cloud radio access network (CRAN), or the network device may be a relay station, an access point,
25 an in-vehicle device, a wearable device, a network side device in a future 5G network or a network device in a future evolved public land mobile network (PLMN), or the like.

[0075] The wireless communication system 100 also includes at least one terminal device 120 located within the coverage of the network device 110. Terminal device 120 may be mobile or stationary. Optionally, the terminal device 120 may refer to an access terminal, a user

equipment (UE), a subscriber unit, a subscriber station, a mobile station, a mobile platform, a remote station, a remote terminal, a mobile device, a user terminal, a terminal, a wireless communication device, a user agent, or a user apparatus. The access terminal may be a cellular phone, a cordless phone, a session initiation protocol (SIP) phone, a wireless local loop (WLL) station, a personal digital assistant (PDA), a handheld device or a computing device with a wireless communication function, or other processing devices connected to a wireless modem, an in-vehicle device, a wearable device, a terminal devices in a future 5G network, or a terminal device in a future evolved PLMN, or the like.

[0076] Alternatively, the 5G system or network may also be referred to as a new radio (NR) system or network.

[0077] FIG. 1 exemplarily shows one network device and two terminal devices. Optionally, the wireless communication system 100 may include a plurality of network devices and other numbers of terminal devices may be located within coverage of each network device, which is not limited in the embodiments of the present application.

[0078] Optionally, the wireless communication system 100 may further include other network entities, such as network controllers, mobility management entities, or the like, which is not limited in the embodiments of the present application.

[0079] It should be understood that the terms “system” and “network” are generally used interchangeably herein. The term “and/or” in the present application is merely a relationships describing associated objects, indicating that there may be three types of relationships, for example, A and/or B may indicate three situations: only A existing, both A and B existing, and only B existing. In addition, the character “/” herein generally indicates that a relationship between contextual objects is “or”.

[0080] FIG. 2 is a schematic flowchart of a wireless communication method 200 according to an embodiment of the present application. Optionally, the method 200 may be used in the wireless communication system 100 described above.

[0081] As shown in FIG. 2, the method 200 may include the following:

[0082] In 210, a terminal device determines a quantity K of DMRS sequences corresponding to a first DMRS port and a physical resource occupied by each DMRS sequence in the K DMRS sequences, where K is a positive integer.

[0083] K may equal to or greater than 1. For example, K may be 2, 3, 4, 6 or the like.

[0084] The first DMRS port is one DMRS port in N DMRS ports currently used by the terminal device.

[0085] Optionally, DMRS sequences transmitted through the N DMRS ports may occupy
5 a same physical resource, but use different cyclic shifts.

[0086] Optionally, quantities of DMRS sequences corresponding to different sequences may be the same or different.

[0087] Optionally, the physical resource occupied by the DMRS sequences may be a time domain resource, a frequency domain resource and/or an airspace resources, or the like.

10 **[0088]** Optionally, in the embodiment of the present application, the terminal device may determine the quantity K of the DMRS sequences corresponding to the first DMRS port and the physical resource occupied by the each DMRS sequence in the K DMRS sequences in multiple manners.

[0089] In an implementation, the terminal device may determine the quantity K of the
15 DMRS sequences corresponding to the first DMRS port according to DMRS sequence indication information carried in downlink control information DCI transmitted by scheduling data corresponding to the DMRS sequences by the network device.

[0090] In an implementation, the terminal device determines the quantity K of the DMRS sequences corresponding to the first DMRS port and/or the physical resource occupied by the
20 each DMRS sequence in the K DMRS sequences according to a multiple access mode used in sending the DMRS sequences using the first DMRS port. DMRS resource patterns corresponding to different multiple access modes may be different.

[0091] Specifically, the terminal device may determine the quantity K of the DMRS sequences corresponding to the first DMRS port according to a first corresponding relation and
25 the used multiple access mode; where, the first corresponding relation is configured to indicate a quantity of DMRS sequences corresponding to the first DMRS port under each multiple access mode in at least one multiple access mode.

[0092] The terminal device may determine the physical resource occupied by the each DMRS sequence in the K DMRS sequences according to a second corresponding relation and
30 the used multiple access mode; where, the second corresponding relation is configured to

indicate a physical resource corresponding to each DMRS sequence in at least one DMRS sequence corresponding to the first DMRS port under each multiple access mode in the at least one multiple access mode.

[0093] The first corresponding relation and/or the second corresponding relation may be notified by the network device to the terminal device, or may be pre-configured by the terminal device, or may be pre-agreed by the terminal device and the network device.

[0094] It should be understood that, the terminal device may determine the quantity K, but not the physical resources occupied by the K sequences, according to the used multiple access modes, where the physical resource of each sequence is preset or configured by the network device.

[0095] Alternatively, the terminal device may determine the quantity K according to the DCI sent by the network device, and determine the physical resource occupied by the each sequence in the K sequences according to the used multiple access mode.

[0096] Optionally, when the used multiple access mode is a CP-OFDM multiple access mode, K is 1.

[0097] Specifically, when the multiple access mode used by the terminal device in sending the DMRS sequences is the CP-OFDM multiple access mode, the terminal device may send only one DMRS sequence.

[0098] The one DMRS sequence may use a discrete resource element (RE), and on the OFDM symbol where DMRS is transmitted, the DMRS sequence occupies a part of subcarriers, and other subcarriers may be configured to transmit data, specifically, as shown in FIG. 3.

[0099] Of course, when the used multiple access mode is the CP-OFDM multiple access mode, K may also be greater than 1.

[0100] Optionally, when the used multiple access mode is a DFT-S-OFDM multiple access mode, K may be an integer greater than 1.

[0101] Optionally, in the embodiment of the present application, in a situation where the terminal devices performing multi-user multiplexing use different multiple access modes, there is at least one DMRS sequence in DMRS sequences sent by the terminal devices that occupies a same physical resource and/or a same root sequence as at least one DMRS sequence of the rest terminal devices.

[0102] Alternatively, in the embodiment, in a situation where the terminal devices may select multiple access modes, there is at least one DMRS sequence in DMRS sequences sent through the various multiple access modes selected by the terminal devices that occupies a same physical resource and/or a same root sequence as at least one DMRS sequence in DMRS sequences sent by selecting other multiple access modes.

[0103] Optionally, when the used multiple access mode is the DFT-S-OFDM multiple access mode, the K DMRS sequences include a first DMRS sequence, where the first DMRS sequence occupies a same physical resource and/or uses a same root sequence as a second DMRS sequence transmitted using a same DMRS port when the used multiple access mode is the CP-OFDM multiple access mode.

[0104] Specifically, when the used multiple access mode is the DFT-S-OFDM multiple access mode, the K DMRS sequences include the first DMRS sequence, where the first DMRS sequence occupies the same physical resource and/or uses the same root sequence as the second DMRS sequence transmitted using the same DMRS port when the terminal device uses the CP-OFDM multiple access mode.

[0105] Alternatively, when the used multiple access mode is the DFT-S-OFDM multiple access mode, the K DMRS sequences include the first DMRS sequence, where the first DMRS sequence occupies the same physical resource and/or uses the same root sequence as the second DMRS sequence transmitted using the same DMRS port when the other terminal devices use the CP-OFDM multiple access mode.

[0106] Optionally, when the used multiple access mode is the CP-OFDM multiple access mode, the K DMRS sequences include the second DMRS sequence, where the second DMRS sequence occupies the same physical resource and/or uses the same root sequence as the first DMRS sequence in multiple DMRS sequences transmitted using the same DMRS port when the used multiple access mode is the DFT-S-OFDM multiple access mode.

[0107] Specifically, when the used multiple access mode is the CP-OFDM multiple access mode, the K DMRS sequences include the second DMRS sequence, where the second DMRS sequence occupies the same physical resource and/or uses the same root sequence as the first DMRS sequence in the multiple DMRS sequences transmitted using the same DMRS port when the terminal device uses the DFT-S-OFDM multiple access mode.

[0108] Alternatively, optionally, when the used multiple access mode is the CP-OFDM multiple access mode, the K DMRS sequences include the second DMRS sequence, where the second DMRS sequence occupies the same physical resource and/or uses the same root sequence as the first DMRS sequence in the multiple DMRS sequences transmitted using the same DMRS port when the other terminal devices use the DFT-S-OFDM multiple access mode.

[0109] It should be understood that, the multiple access mode is illustrated as the CP-OFDM multiple access mode and the DFT-S-OFDM multiple access mode in the embodiment of the present application, but the multiple access mode in the embodiment of the present application may also be other multiple access modes, which is not limited in the present application.

[0110] Therefore, in the embodiment of the present application, determining the quantity of the DMRS sequences sent by one DMRS port and/or the resource of each DMRS sequence according to the multiple access mode may enable that there is at least one DMRS sequences in the terminal devices using different multiple access modes that occupies a same physical resource and/or uses a same root sequence, so that the terminal devices using different multiple access modes can obtain DMRS orthogonality by using different cyclic shifts, thereby enabling flexible multi-user multiplexing transmission.

[0111] Optionally, when a value of K is greater than 1, the each DMRS sequence in the K DMRS sequences occupies, in at least one OFDM symbol, different sub-carriers in a same frequency domain bandwidth respectively. Such same frequency domain bandwidth may be a transmission bandwidth of data corresponding to the DMRS sequences.

[0112] In an implementation, a sub-carrier occupied by an m^{th} DMRS sequence in the K DMRS sequences is: an $(m+iK)^{\text{th}}$ sub-carrier in the frequency domain bandwidth, where $i = 0, 1, \dots, \lfloor (S-m)/K \rfloor$, and S is a quantity of sub-carriers included in the frequency domain bandwidth.

[0113] In an implementation, $K=2$, and a subcarrier occupied by a first DMRS sequence in the K DMRS sequences is an $(n+jN)^{\text{th}}$ subcarrier in the frequency domain bandwidth, and a second DMRS sequence occupies the rest subcarrier in the frequency domain bandwidth, where $j = 0, 1, \dots, \lfloor (S-n)/N \rfloor$, N is a positive integer greater than 1, and n is a positive integer less

than or equal to N.

[0114] A value of n or N may be notified by the network device to the terminal device through a downlink signaling, or may be a preset value in the network device and the terminal device.

5 **[0115]** For example, the network device may indicate the value to the terminal device by DCI transmitted by scheduling data corresponding to the DMRS, or preconfigure the value for the terminal device through an upper layer signaling. Different manners may be used to obtain the values of n and N. For example, n may be indicated to the terminal device by the DCI, and N may be a preset fixed value in the terminal device and the network device.

10 **[0116]** n and N may have different values in different OFDM symbols. For example, in an OFDM symbol transmitting the DMRS, $n=1$ and $N=2$, and in another OFDM symbol transmitting the DMRS, $n=2$ and $N=2$. Alternatively, in four OFDM symbols transmitting DMRSs, the values of n respectively are $n=1, 2, 3, 4$, and $N=4$.

[0117] Optionally, each DMRS sequence in at least one DMRS sequence in the K DMRS sequences occupies different sub-carriers in different OFDM symbols.

[0118] Specifically, the subcarriers occupied by the same DMRS subsequence in different OFDM symbols may use a fixed subcarrier offset, or the same DMRS subsequence may use different frequency domain densities in different OFDM symbols.

15 **[0119]** Optionally, when the value of K is greater than 1, DMRS sequences in the K DMRS sequences having a same length use a same sequence.

[0120] For example, it may be a ZC (Zadoff-Chu) sequence generated by using a same sequence length and a same root sequence ID, so that a peak-to-average ratio can be effectively reduced compared to that when different sequences are used.

20 **[0121]** Optionally, the terminal device determines the quantity K of the DMRS sequences corresponding to the first DMRS port; and the terminal device determines a resource offset between physical resources occupied by different DMRS sequences in the K DMRS sequences according to the quantity K when the K is greater than 1.

[0122] Specifically, the terminal device may determine, according to the value of K, that the resource offset is a value in $\{0, 1, \dots, K-1\}$. The resource offset may be a time domain resource offset or a frequency domain resource offset. For example, physical resources of

different sub-sequences may be offset by n subcarriers, or offset by n OFDM symbols, where n is an integer greater than or equal to 0 and less than K .

[0123] In 220, the terminal device sends, on determined the physical resource occupied by the each DMRS sequence, the each DMRS sequence to a network device using the first DMRS port.

[0124] In 230, the network device determines the quantity K of the demodulation reference signal DMRS sequences sent by the terminal device using the first DMRS port and the physical resource occupied by the each DMRS sequence in the K DMRS sequences.

[0125] Optionally, the network device determines the quantity K of the DMRS sequences sent by the terminal device using the first DMRS port and/or the physical resource occupied by the each DMRS sequence in the K DMRS sequences according to a multiple access mode used by the terminal device in sending the DMRS sequences using the first DMRS port.

[0126] Specifically, the network device determines the quantity K of the DMRS sequences sent by the terminal device using the first DMRS port according to a first corresponding relation and the used multiple access mode; where, the first corresponding relation is configured to indicate a quantity of DMRS sequences corresponding to the first DMRS port under each multiple access mode in at least one multiple access mode.

[0127] The network device determines the physical resource occupied by the each DMRS sequence in the K DMRS sequences according to a second corresponding relation and the used multiple access mode; where, the second corresponding relation is configured to indicate a physical resource corresponding to each DMRS sequence in at least one DMRS sequence corresponding to the first DMRS port under each multiple access mode in the at least one multiple access mode.

[0128] In 240, the network device receives, on the determined physical resource occupied by the each DMRS sequence, the each DMRS sequence sent by the terminal device.

[0129] Therefore, in the embodiments of the present application, a quantity of DMRS sequences corresponding to one DMRS port may not be unique and may be flexibly changed. For example, such corresponding relationship may be set according to a multiple access mode used by a plurality of terminal devices which need orthogonal multiplexing, so that multi-user multiplexing of terminal devices that use different multiple access modes may be supported.

Further, since the quantity of the DMRS sequences corresponding to one DMRS port and resource occupied by each sequence may be flexibly changed, it may be realized that there is at least one DMRS sequence in the terminal devices using different multiple access modes that corresponds to a same root sequence and/or occupy a same physical resource, so that the terminal devices using different multiple access modes can obtain DMRS orthogonality by using different cyclic shifts, thereby enabling multi-user multiplexing transmission supporting more terminal devices.

[0130] In order to facilitate a clearer understanding of the present application, the multiple access mode is illustrated as the DFT-S-OFDM in the following, and resources occupied by multiple DMRS sequences are described in combination with FIG. 4 to FIG. 9.

[0131] Embodiment 1

[0132] As shown in FIG. 4 and FIG. 5, when $K=2$, two DMRS sequences of a terminal device 1 respectively occupy an odd subcarrier and an even subcarrier in a physical resource block (PRB).

[0133] A DMRS sequence 2 may be combined with a DMRS sequence 1 to obtain a better channel estimation performance.

[0134] Sequences of the two DMRS sequences may be the same.

[0135] A DMRS sequence in FIG. 4 may occupy a same subcarrier in two OFDM symbols, and a DMRS sequence in FIG. 5 occupies different subcarriers in two OFDM symbols and use different densities.

[0136] If resource occupancy of the terminal device 1 using the DFT-S-OFDM multiple access mode is as shown in FIG. 4, a terminal device 2 using the CP-OFDM multiple access mode may use a DMRS resource occupation mode as shown in FIG. 3, thus, when the terminal device 1 and the terminal device 2 are multiplexed on a same resource, the DMRS sequence 1 may obtain orthogonality by using a same root sequence as a DMRS sequence of the terminal device 2, but a different cyclic shift from the DMRS sequence of the terminal device 2.

[0137] If the resource occupancy of the terminal device 1 using the DFT-S-OFDM multiple access mode is as shown in FIG. 5, a resource occupation mode of a DMRS sequence sent by the terminal device 2 using the CP-OFDM multiple access mode may be the same as that of the DMRS sequence 1, where the DMRS sequence sent by the terminal device 2 using the CP-

OFDM multiple access mode may use different combs in different OFDMs. Specifically, on an OFDM symbol 1, comb=2, and on an OFDM symbol 2, comb =4.

[0138] Thus, the sequences in the DMRS sequences sent by the terminal device 1 and the terminal device 2 occupying the same resource can obtain orthogonality by using the same root sequence but different cyclic shifts.

[0139] Embodiment 2

[0140] As shown in FIG. 6 and FIG. 7, when $K=4$, four DMRS sequences of a terminal device 3 respectively occupy $\{(4n+1)^{\text{th}}, (4n+2)^{\text{th}}, (4n+3)^{\text{th}}, (4n+4)^{\text{th}}\}$ subcarriers in a PRB, $n=0, 1, 2$.

[0141] A DMRS sequence in FIG. 6 occupies a same subcarrier in two OFDM symbols, and a DMRS sequence in FIG. 7 occupies different subcarriers in two OFDM symbols and use a fixed subcarrier offset.

[0142] If a terminal device 4 using the CP-OFDM waveform uses a DMRS sequence of Comb=4, then, when the terminal device 3 and the terminal device 4 are multiplexed on a same resource, one of the DMRS sequences of the terminal device 3 (for example, a DMRS sequence 1) may obtain orthogonality by using a same root sequence as the DMRS sequence of the terminal device 4, but a different cyclic shift from the DMRS sequence of the terminal device 4. At the same time, DMRS subsequences $\{2, 3, 4\}$ may be combined with a DMRS subsequence 1 to obtain a better channel estimation performance.

[0143] Further, if a DMRS resource of a terminal device using the CP-OFDM multiple access mode supports offset in the frequency domain, it is not necessary to perform additional configuration on a terminal device using the DFT-S-OFDM multiple access mode to ensure mutual DMRS orthogonality.

[0144] Embodiment 3

[0145] As shown in FIG. 8 and FIG. 9, $K=2$, in two DMRS sequences of a terminal device 5, a first DMRS sequence occupies an $(4n+1)^{\text{th}}$ subcarrier in a PRB, $n=0, 1, 2$, and a second DMRS sequences occupies other subcarriers in the PRB.

[0146] A DMRS sequence in FIG. 8 occupies a same subcarrier in two OFDM symbols, and a DMRS sequence in FIG. 9 occupies different subcarriers in two OFDM symbols and use a fixed subcarrier offset.

[0147] If the terminal device 4 using the CP-OFDM waveform uses the DMRS sequence of Comb=4, then when the terminal device 5 and the terminal device 4 are multiplexed on a same resource, DMRS sequence 1 may obtain orthogonality by using a same root sequence as the DMRS sequence of the terminal device 4, but a different cyclic shift from the DMRS sequence of the terminal device 4. At the same time, a DMRS sequence 2 may be combined with a DMRS sequence 1 to obtain a better channel estimation performance.

[0148] Therefore, in this embodiment of the present application, in a situation where terminal devices using different multiple access methods performs multi-user multiplexing to send DMRS sequences, resources occupied by the DMRS sequences sent by the terminal device and a comb may be flexibly set, so that the terminal devices that support different multiple access modes may obtain orthogonality by cyclic shifting, thereby performing multi-user multiplexing.

[0149] FIG. 10 is a schematic block diagram of a terminal device 300 according to an embodiment of the present application. As shown in FIG. 10, the terminal device 300 includes a processing unit 310 and a sending unit 320.

[0150] The processing unit 310 is configured to determine a quantity K of demodulation reference signal (DMRS) sequences corresponding to a first DMRS port and a physical resource occupied by each DMRS sequence in the K DMRS sequences, where K is a positive integer; and the sending unit 320 is configured to send, on the physical resource occupied by the each DMRS sequence determined by the processing unit, the each DMRS sequence to a network device using the first DMRS port.

[0151] Optionally, the processing unit 310 is further configured to:

[0152] determine the quantity K of the DMRS sequences corresponding to the first DMRS port and/or the physical resource occupied by the each DMRS sequence in the K DMRS sequences according to a multiple access mode used in sending the DMRS sequences using the first DMRS port.

[0153] Optionally, the processing unit 310 is further configured to:

[0154] determine the quantity K of the DMRS sequences corresponding to the first DMRS port according to a first corresponding relation and the multiple access mode used in sending the DMRS sequences using the first DMRS port;

[0155] where, the first corresponding relation is configured to indicate a quantity of DMRS sequences corresponding to the first DMRS port under each multiple access mode in at least one multiple access mode.

[0156] Optionally, the processing unit 310 is further configured to:

5 **[0157]** determine the physical resource occupied by the each DMRS sequence in the K DMRS sequences according to a second corresponding relation and the multiple access mode used in sending the DMRS sequences using the first DMRS port;

[0158] where, the second corresponding relation is configured to indicate a physical resource corresponding to each DMRS sequence in at least one DMRS sequence corresponding to the first DMRS port under each multiple access mode in the at least one multiple access mode.

[0159] Optionally, when the multiple access mode used in sending the DMRS sequences using the first DMRS port is a first multiple access mode, the K DMRS sequences include a first DMRS sequence, where the first DMRS sequence occupies a same physical resource and/or uses a same root sequence as a second DMRS sequence included in DMRS sequences transmitted using a same DMRS port when a second multiple access mode is used, where the second multiple access mode is difference from the first multiple access mode.

[0160] Optionally, the first multiple access mode is a discrete Fourier transform orthogonal frequency division multiplexing based spread spectrum DFT-S-OFDM multiple access mode, and the second multiple access mode is a cyclic prefix orthogonal frequency division multiplexing (CP-OFDM) multiple access mode; or,

[0161] the first multiple access mode is the CP-OFDM multiple access mode, and the second multiple access mode is the DFT-S-OFDM multiple access mode.

25 **[0162]** Optionally, when the multiple access mode used in sending the DMRS sequences using the first DMRS port is the DFT-S-OFDM multiple access mode, K is an integer greater than 1; and/or,

[0163] when the multiple access mode used in sending the DMRS sequences using the first DMRS port is the CP-OFDM multiple access mode, K is 1.

[0164] Optionally, the processing unit 310 is further configured to:

30 **[0165]** determine the quantity K of the DMRS sequences corresponding to the first DMRS

port according to DMRS sequence indication information carried in downlink control information DCI transmitted by scheduling data corresponding to the DMRS sequences by the network device.

[0166] Optionally, K is an integer greater than 1.

5 **[0167]** Optionally, when a value of K is greater than 1, DMRS sequences in the K DMRS sequences having a same length use a same sequence.

[0168] Optionally, when a value of K is greater than 1, the each DMRS sequence in the K DMRS sequences occupies, in at least one OFDM symbol, different sub-carriers in a same frequency domain bandwidth respectively.

10 **[0169]** Optionally, a sub-carrier occupied by an m^{th} DMRS sequence in the K DMRS sequences is: an $(m+iK)^{\text{th}}$ sub-carrier in the frequency domain bandwidth, where $i = 0, 1, \dots, \lfloor (S-m)/K \rfloor$, and S is a quantity of sub-carriers included in the frequency domain bandwidth.

[0170] Optionally, K=2, and a subcarrier occupied by a first DMRS sequence in the K
15 DMRS sequences is an $(n+jN)^{\text{th}}$ in the frequency domain bandwidth, a second DMRS sequence occupies the rest subcarrier in the frequency domain bandwidth, where $j = 0, 1, \dots, \lfloor (S-n)/N \rfloor$, N is a positive integer greater than 1, and n is a positive integer less than or equal to N.

[0171] Optionally, each DMRS sequence in at least one DMRS sequence in the K DMRS sequences occupies different sub-carriers in different OFDM symbols.

20 **[0172]** Optionally, the processing unit 310 is further configured to:

[0173] determine the quantity K of the DMRS sequences corresponding to the first DMRS port; and

[0174] determine a resource offset between physical resources occupied by different DMRS sequences in the K DMRS sequences according to the quantity K when the K is greater than 1.

25 **[0175]** It should be understood that, the terminal device 300 may be corresponding to the terminal device in the method 200 and can implement corresponding functions of the terminal device in the method 200, which will not be repeated herein for the sake of conciseness.

[0176] FIG. 11 is a schematic block diagram of a network device 400 according to an embodiment of the present application. As shown in FIG. 11, the network device includes a

processing unit 410 and a transceiving unit 420.

[0177] The processing unit 410 is configured to determine a quantity K of demodulation reference signal DMRS sequences sent by a terminal device using a first DMRS port and a physical resource occupied by each DMRS sequence in the K DMRS sequences; and the transceiving unit 420 is configured to receive, on the determined physical resource occupied by the each DMRS sequence, the each DMRS sequence sent by the terminal device.

[0178] Optionally, the processing unit 410 is further configured to:

[0179] determine the quantity K of the DMRS sequences sent by the terminal device using the first DMRS port and/or the physical resource occupied by the each DMRS sequence in the K DMRS sequences according to a multiple access mode used by the terminal device in sending the DMRS sequences using the first DMRS port.

[0180] Optionally, the processing unit 410 is further configured to:

[0181] determine the quantity K of the DMRS sequences sent by the terminal device using the first DMRS port according to a first corresponding relation and the multiple access mode used by the terminal device in sending the DMRS sequences using the first DMRS port; where, **[0182]** the first corresponding relation is configured to indicate a quantity of DMRS sequences corresponding to the first DMRS port under each multiple access mode in at least one multiple access mode.

[0183] Optionally, the processing unit 410 is further configured to:

[0184] determine the physical resource occupied by the each DMRS sequence in the K DMRS sequences according to a second corresponding relation and the multiple access mode used by the terminal device in sending the DMRS sequences using the first DMRS port; where, **[0185]** the second corresponding relation is configured to indicate a physical resource corresponding to each DMRS sequence in at least one DMRS sequence corresponding to the first DMRS port under each multiple access mode in the at least one multiple access mode.

[0186] Optionally, the transceiving unit 420 is further configured to:

[0187] indicate the quantity K of the DMRS sequences corresponding to the DMRS port to the terminal device by DMRS sequence indication information carried in downlink control information DCI transmitted by scheduling data corresponding to the DMRS sequences.

[0188] Optionally, when the multiple access mode used by the terminal device in sending

the DMRS sequences using the first DMRS port is a DFT-S-OFDM multiple access mode, K is an integer greater than 1; and/or,

[0189] when the multiple access mode used by the terminal device in sending the DMRS sequences using the first DMRS port is a CP-OFDM multiple access mode, K is 1.

5 **[0190]** Optionally, K is an integer greater than 1.

[0191] Optionally, when a value of K is greater than 1, the each DMRS sequence in the K DMRS sequences occupies, in at least one OFDM symbol, different sub-carriers in a same frequency domain bandwidth respectively.

[0192] Optionally, each DMRS sequence in at least one DMRS sequence in the K DMRS
10 sequences occupies different sub-carriers in different OFDM symbols.

[0193] It should be understood that, the network device 400 may be corresponding to the network device in the method 200 and can implement corresponding functions of the network device in the method 200, which will not be repeated herein for the sake of conciseness.

[0194] FIG. 12 is a schematic block diagram of a communication device 500 according to
15 an embodiment of the present application. As shown in FIG. 12, the communication device 500 includes a processor 510 and a memory 520. The memory 520 may store a program code, and the processor 510 may execute the program code stored in the memory 520.

[0195] Optionally, as shown in FIG. 12, the communication device 500 may include a
20 transceiver 530, and the processor 510 may control the transceiver 530 to communicate with the outside.

[0196] Optionally, the processor 510 may invoke the program code stored in the memory 520 to perform corresponding operations of the terminal device in the method 200 shown in FIG. 2, which will not be repeated herein for the sake of conciseness.

[0197] Optionally, the processor 510 may invoke the program code stored in the memory
25 520 to perform corresponding operations of the network device in the method 200 shown in FIG. 2, which will not be repeated herein for the sake of conciseness.

[0198] FIG. 13 is a schematic structural diagram of a system chip 600 according to an
embodiment of the present application. The system chip 600 of FIG. 13 includes an input
interface 601, an output interface 602, a processor 603 and a memory 604, which are connected
30 by a communication connection, where the processor 603 is configured to execute a code in the

memory 604.

[0199] Optionally, when the code is executed, the processor 603 implements a method performed by the terminal device in the method 200 shown in FIG. 2, which will not be repeated herein for the sake of conciseness.

5 **[0200]** Optionally, when the code is executed, the processor 603 implements a method performed by the network device in the method 200 shown in FIG. 2, which will not be repeated herein for the sake of conciseness.

[0201] Those skilled in the art will appreciate that units and algorithm steps of the various examples described in combination with the embodiments disclosed herein may be
10 implemented in electronic hardware or a combination of computer software and electronic hardware. Whether these functions are performed in hardware or software depends on specific applications and design constraints of the technical solution. Those skilled in the art may use different methods to implement the described functions for each particular application, but such implementation should not be considered to be beyond the scope of the present application.

15 **[0202]** Those skilled in the art can clearly understand that, for the convenience and conciseness of the description, the specific working process of the systems, the apparatuses and the units described above may refer to the corresponding process in the foregoing method embodiments, which will not be described herein again.

[0203] In the several embodiments according to the present application, it should be
20 understood that, the disclosed systems, apparatuses, and methods may be implemented in other manners. For example, the apparatus embodiments described above are merely illustrative. For example, the division of the units is only a logical function division. In actual implementation, there may be other division manners. For example, multiple units or components may be combined or may be integrated into another system, or some features may be ignored or not
25 executed. In addition, the mutual coupling or direct coupling or communication connection shown or discussed may be an indirect coupling or communication connection through some interfaces, apparatuses or units, which may be in an electrical form, a mechanical form or other forms.

[0204] The units described as separate components may or may not be physically separated,
30 and the components shown as units may or may not be physical units, that is, may be located

in one place, or may be distributed to multiple network units. Some or all of the units may be selected according to actual needs to achieve the purpose of the solution of this embodiment.

[0205] In addition, functional units in the embodiment of the present application may be integrated into one processing unit, or each unit may exist physically separately, or two or more units may be integrated into one unit.

[0206] The functions may be stored in a computer readable storage medium if implemented in the form of a software functional unit and sold or used as a standalone product. Based on such understanding, the technical solutions of the present application essentially, or its portion contributing to the prior art, or a portion of the technical solutions, may be embodied in the form of a software product, where the computer software product is stored in a storage medium including several instructions to cause a computer device (which may be a personal computer, a server, or a network device, or the like) to perform all or part of the steps of the methods described in the embodiments of the present application. The foregoing storage medium includes various media that can store a program code, such as a U disk, a mobile hard disk, a read-only memory (ROM), a random access memory (RAM), a magnetic disk, or an optical disk, or the like.

[0207] The foregoing is only specific implementations of the present application, but the protection scope of the present application is not limited thereto, and any change or substitution that can be easily conceived by those skilled in the art within the technical scope disclosed by the present application should be covered within the protection scope of the present application. Therefore, the protection scope of the present application should be subjected to the protection scope of the claims.

CLAIMS

1. A wireless communication method, comprising:

determining, by a terminal device, a quantity K of demodulation reference signal DMRS sequences corresponding to a first DMRS port and a physical resource occupied by each DMRS sequence in the K DMRS sequences, wherein K is a positive integer; and

sending, on the determined physical resource occupied by the each DMRS sequence, the each DMRS sequence to a network device using the first DMRS port.

2. The method according to claim 1, wherein, the determining, by a terminal device, a quantity K of DMRS sequences corresponding to a first DMRS port and a physical resource occupied by each DMRS sequence in the K DMRS sequences, comprises:

determining, by the terminal device, the quantity K of the DMRS sequences corresponding to the first DMRS port and/or the physical resource occupied by the each DMRS sequence in the K DMRS sequences according to a multiple access mode used in sending the DMRS sequences using the first DMRS port.

3. The method according to claim 2, wherein, the determining, by the terminal device, the quantity K of the DMRS sequences corresponding to the first DMRS port according to a multiple access mode used in sending the DMRS sequences using the first DMRS port, comprises:

determining the quantity K of the DMRS sequences corresponding to the first DMRS port according to a first corresponding relation and the multiple access mode used in sending the DMRS sequences using the first DMRS port;

wherein, the first corresponding relation is configured to indicate a quantity of DMRS sequences corresponding to the first DMRS port under each multiple access mode in at least one multiple access mode.

4. The method according to claim 2 or 3, wherein, the determining, by the terminal device, the physical resource occupied by the each DMRS sequence in the K DMRS sequences according to a multiple access mode used in sending the DMRS sequences using the first DMRS port, comprises:

determining the physical resource occupied by the each DMRS sequence in the K DMRS sequences according to a second corresponding relation and the multiple access mode used in sending the DMRS sequences using the first DMRS port;

5 wherein, the second corresponding relation is configured to indicate a physical resource corresponding to each DMRS sequence in at least one DMRS sequence corresponding to the first DMRS port under each multiple access mode in the at least one multiple access mode.

5. The method according to any one of claims 2 to 4, wherein, when the multiple access mode used in sending the DMRS sequences using the first DMRS port is a first multiple access mode, the K DMRS sequences comprise a first DMRS sequence, wherein the first DMRS sequence occupies a same physical resource and/or uses a same root sequence as a second DMRS sequence comprised in DMRS sequences transmitted using a same DMRS port when a second multiple access mode is used, wherein the second multiple access mode is difference from the first multiple access mode.

6. The method according to claim 5, wherein, the first multiple access mode is a discrete Fourier transform orthogonal frequency division multiplexing based spread spectrum DFT-S-OFDM multiple access mode, and the second multiple access mode is a cyclic prefix orthogonal frequency division multiplexing CP-OFDM multiple access mode; or,

the first multiple access mode is the CP-OFDM multiple access mode, and the second multiple access mode is the DFT-S-OFDM multiple access mode.

20 7. The method according to any one of claims 2 to 6, wherein, when the multiple access mode used in sending the DMRS sequences using the first DMRS port is a DFT-S-OFDM multiple access mode, K is an integer greater than 1; and/or,

when the multiple access mode used in sending the DMRS sequences using the first DMRS port is a CP-OFDM multiple access mode, K is 1.

25 8. The method according to claim 1, wherein, the determining, by a terminal device, a quantity K of demodulation reference signal DMRS sequences corresponding to a first DMRS port, comprises:

determining, by the terminal device, the quantity K of the DMRS sequences corresponding to the first DMRS port according to DMRS sequence indication information carried in downlink

control information DCI transmitted by scheduling data corresponding to the DMRS sequences by the network device.

9. The method according to any one of claims 1 to 8, wherein, K is an integer greater than 1.

5 10. The method according to any one of claims 1 to 9, wherein, when a value of K is greater than 1, DMRS sequences in the K DMRS sequences having a same length use a same sequence.

11. The method according to any one of claims 1 to 10, wherein, when a value of K is greater than 1, the each DMRS sequence in the K DMRS sequences occupies, in at least one
10 OFDM symbol, different sub-carriers in a same frequency domain bandwidth respectively.

12. The method according to claim 11, wherein, a sub-carrier occupied by an m^{th} DMRS sequence in the K DMRS sequences is: an $(m+iK)^{\text{th}}$ sub-carrier in the frequency domain bandwidth, wherein $i = 0, 1, \dots, \lfloor (S - m) / K \rfloor$, and S is a quantity of sub-carriers comprised in the frequency domain bandwidth.

15 13. The method according to claim 11, wherein, $K=2$, and a subcarrier occupied by a first DMRS sequence in the K DMRS sequences is an $(n+jN)^{\text{th}}$ subcarrier in the frequency domain bandwidth, a second DMRS sequence occupies the rest subcarrier in the frequency domain bandwidth, wherein $j = 0, 1, \dots, \lfloor (S - n) / N \rfloor$, N is a positive integer greater than 1, and n is a positive integer less than or equal to N.

20 14. The method according to any one of claims 1 to 13, wherein, each DMRS sequence in at least one DMRS sequence in the K DMRS sequences occupies different sub-carriers in different OFDM symbols.

15. The method according to any one of claims 1 to 14, wherein, the determining, by a terminal device, a quantity K of DMRS sequences corresponding to a first DMRS port and a
25 physical resource occupied by each DMRS sequence in the K DMRS sequences, comprises:

determining, by the terminal device, the quantity K of the DMRS sequences corresponding to the first DMRS port; and

determining, by the terminal device, a resource offset between physical resources occupied by different DMRS sequences in the K DMRS sequences according to the quantity K when the K is greater than 1.

16. A wireless communication method, comprising:

5 determining, by a network device, a quantity K of demodulation reference signal DMRS sequences sent by a terminal device using a first DMRS port and a physical resource occupied by each DMRS sequence in the K DMRS sequences; and

receiving, on the determined physical resource occupied by the each DMRS sequence, the each DMRS sequence sent by the terminal device.

10 17. The method according to claim 16, wherein, the determining, by a network device, a quantity K of demodulation reference signal DMRS sequences sent by a terminal device using a first DMRS port and a physical resource occupied by each DMRS sequence in the K DMRS sequences, comprises:

15 determining, by the network device, the quantity K of the DMRS sequences sent by the terminal device using the first DMRS port and/or the physical resource occupied by the each DMRS sequence in the K DMRS sequences according to a multiple access mode used by the terminal device in sending the DMRS sequences using the first DMRS port.

18. The method according to claim 17, wherein, the determining, by the network device, the quantity K of the DMRS sequences sent by the terminal device using the first DMRS port according to a first multiple access mode used by the terminal device in sending the DMRS sequences using the first DMRS port, comprises:

20 determining the quantity K of the DMRS sequences sent by the terminal device using the first DMRS port according to a first corresponding relation and the multiple access mode used by the terminal device in sending the DMRS sequences using the first DMRS port; wherein,
25 the first corresponding relation is configured to indicate a quantity of DMRS sequences corresponding to the first DMRS port under each multiple access mode in at least one multiple access mode.

19. The method according to claim 17 or 18, wherein, the determining, by the network device, the physical resource occupied by the each DMRS sequence in the K DMRS sequences

according to a multiple access mode used by the terminal device in sending the DMRS sequences using the first DMRS port, comprises:

determining the physical resource occupied by the each DMRS sequence in the K DMRS sequences according to a second corresponding relation and the multiple access mode used by the terminal device in sending the DMRS sequences using the first DMRS port; wherein,

the second corresponding relation is configured to indicate a physical resource corresponding to each DMRS sequence in at least one DMRS sequence corresponding to the first DMRS port under each multiple access mode in the at least one multiple access mode.

20. The method according to claim 16, wherein, the method further comprises:

indicating, by the network device, the quantity K of the DMRS sequences corresponding to the DMRS port to the terminal device by DMRS sequence indication information carried in downlink control information DCI transmitted by scheduling data corresponding to the DMRS sequences.

21. The method according to any one of claims 17 to 19, wherein, when the multiple access mode used by the terminal device in sending the DMRS sequences using the first DMRS port is a DFT-S-OFDM multiple access mode, K is an integer greater than 1; and/or,

when the multiple access mode used by the terminal device in sending the DMRS sequences using the first DMRS port is a CP-OFDM multiple access mode, K is 1.

22. The method according to any one of claims 16 to 21, wherein, K is an integer greater than 1.

23. The method according to any one of claims 16 to 22, wherein, when a value of K is greater than 1, the each DMRS sequence in the K DMRS sequences occupies, in at least one OFDM symbol, different sub-carriers in a same frequency domain bandwidth respectively.

24. The method according to any one of claims 16 to 23, wherein, each DMRS sequence in at least one DMRS sequence in the K DMRS sequences occupies different sub-carriers in different OFDM symbols.

25. A terminal device, comprising:

a processing unit, configured to determine a quantity K of demodulation reference signal DMRS sequences corresponding to a first DMRS port and a physical resource occupied by each DMRS sequence in the K DMRS sequences, wherein K is a positive integer; and

a sending unit, configured to send, on the physical resource occupied by the each DMRS sequence determined by the processing unit, the each DMRS sequence to a network device using the first DMRS port.

26. The terminal device according to claim 25, wherein, the processing unit is further
5 configured to:

determine the quantity K of the DMRS sequences corresponding to the first DMRS port and/or the physical resource occupied by the each DMRS sequence in the K DMRS sequences according to a multiple access mode used in sending the DMRS sequences using the first DMRS port.

10 27. The terminal device according to claim 26, wherein, the processing unit is further configured to:

determine the quantity K of the DMRS sequences corresponding to the first DMRS port according to a first corresponding relation and the multiple access mode used in sending the DMRS sequences using the first DMRS port;

15 wherein, the first corresponding relation is configured to indicate a quantity of DMRS sequences corresponding to the first DMRS port under each multiple access mode in at least one multiple access mode.

28. The terminal device according to claim 26 or 27, wherein, the processing unit is further configured to:

20 determine the physical resource occupied by the each DMRS sequence in the K DMRS sequences according to a second corresponding relation and the multiple access mode used in sending the DMRS sequences using the first DMRS port;

25 wherein, the second corresponding relation is configured to indicate a physical resource corresponding to each DMRS sequence in at least one DMRS sequence corresponding to the first DMRS port under each multiple access mode in the at least one multiple access mode.

29. The terminal device according to any one of claims 26 to 28, wherein, when the multiple access mode used in sending the DMRS sequences using the first DMRS port is a first multiple access mode, the K DMRS sequences comprise a first DMRS sequence, wherein the first DMRS sequence occupies a same physical resource and/or uses a same root sequence as a
30 second DMRS sequence comprised in DMRS sequences transmitted using a same DMRS port

when a second multiple access mode is used, wherein the second multiple access mode is difference from the first multiple access mode.

30. The terminal device according to claim 29, wherein, the first multiple access mode is a discrete Fourier transform orthogonal frequency division multiplexing based spread spectrum DFT-S-OFDM multiple access mode, and the second multiple access mode is a cyclic prefix orthogonal frequency division multiplexing CP-OFDM multiple access mode; or,

the first multiple access mode is the CP-OFDM multiple access mode, and the second multiple access mode is the DFT-S-OFDM multiple access mode.

31. The terminal device according to any one of claims 26 to 30, wherein, when the multiple access mode used in sending the DMRS sequences using the first DMRS port is a DFT-S-OFDM multiple access mode, K is an integer greater than 1; and/or,

when the multiple access mode used in sending the DMRS sequences using the first DMRS port is a CP-OFDM multiple access mode, K is 1.

32. The terminal device according to claim 25, wherein, the processing unit is further configured to:

determine the quantity K of the DMRS sequences corresponding to the first DMRS port according to DMRS sequence indication information carried in downlink control information DCI transmitted by scheduling data corresponding to the DMRS sequences by the network device.

33. The terminal device according to any one of claims 25 to 32, wherein, K is an integer greater than 1.

34. The terminal device according to any one of claims 25 to 33, wherein, when a value of K is greater than 1, DMRS sequences in the K DMRS sequences having a same length use a same sequence.

35. The terminal device according to any one of claims 25 to 34, wherein, when a value of K is greater than 1, the each DMRS sequence in the K DMRS sequences occupies, in at least one OFDM symbol, different sub-carriers in a same frequency domain bandwidth respectively.

36. The terminal device according to claim 35, wherein, a sub-carrier occupied by an m^{th} DMRS sequence in the K DMRS sequences is: an $(m+iK)^{\text{th}}$ sub-carrier in the frequency domain

bandwidth, wherein $i = 0, 1, \dots, \lfloor (S - m) / K \rfloor$, and S is a quantity of sub-carriers comprised in the frequency domain bandwidth.

37. The terminal device according to claim 35, wherein, $K=2$, and a subcarrier occupied by a first DMRS sequence in the K DMRS sequences is an $(n+jN)^{\text{th}}$ subcarrier in the frequency domain bandwidth, a second DMRS sequence occupies the rest subcarrier in the frequency domain bandwidth, wherein $j = 0, 1, \dots, \lfloor (S - n) / N \rfloor$, N is a positive integer greater than 1, and n is a positive integer less than or equal to N.

38. The terminal device according to any one of claims 25 to 37, wherein, each DMRS sequence in at least one DMRS sequence in the K DMRS sequences occupies different sub-carriers in different OFDM symbols.

39. The terminal device according to any one of claims 25 to 38, wherein, the processing unit is further configured to:

determine the quantity K of the DMRS sequences corresponding to the first DMRS port; and

15 determine a resource offset between physical resources occupied by different DMRS sequences in the K DMRS sequences according to the quantity K when the K is greater than 1.

40. A network device, comprising:

a processing unit, configured to determine a quantity K of demodulation reference signal DMRS sequences sent by a terminal device using a first DMRS port and a physical resource occupied by each DMRS sequence in the K DMRS sequences; and

20 a transceiving unit, configured to receive, on the determined physical resource occupied by the each DMRS sequence, the each DMRS sequence sent by the terminal device.

41. The network device according to claim 40, wherein, the processing unit is further configured to:

25 determine the quantity K of the DMRS sequences sent by the terminal device using the first DMRS port and/or the physical resource occupied by the each DMRS sequence in the K DMRS sequences according to a multiple access mode used by the terminal device in sending the DMRS sequences using the first DMRS port.

42. The network device according to claim 41, wherein, the processing unit is further configured to:

determine the quantity K of the DMRS sequences sent by the terminal device using the first DMRS port according to a first corresponding relation and the multiple access mode used by the terminal device in sending the DMRS sequences using the first DMRS port; wherein, the first corresponding relation is configured to indicate a quantity of DMRS sequences corresponding to the first DMRS port under each multiple access mode in at least one multiple access mode.

43. The network device according to claim 41 or 42, wherein, the processing unit is further configured to:

determine the physical resource occupied by the each DMRS sequence in the K DMRS sequences according to a second corresponding relation and the multiple access mode used by the terminal device in sending the DMRS sequences using the first DMRS port; wherein, the second corresponding relation is configured to indicate a physical resource corresponding to each DMRS sequence in at least one DMRS sequence corresponding to the first DMRS port under each multiple access mode in the at least one multiple access mode.

44. The network device according to claim 40, wherein, the transceiving unit is further configured to:

indicate the quantity K of the DMRS sequences corresponding to the DMRS port to the terminal device by DMRS sequence indication information carried in downlink control information DCI transmitted by scheduling data corresponding to the DMRS sequences.

45. The network device according to any one of claims 41 to 43, wherein, when the multiple access mode used by the terminal device in sending the DMRS sequences using the first DMRS port is a DFT-S-OFDM multiple access mode, K is an integer greater than 1; and/or, when the multiple access mode used by the terminal device in sending the DMRS sequences using the first DMRS port is a CP-OFDM multiple access mode, K is 1.

46. The network device according to any one of claims 40 to 45, wherein, K is an integer greater than 1.

47. The network device according to any one of claims 40 to 46, wherein, when a value of K is greater than 1, the each DMRS sequence in the K DMRS sequences occupies, in at least one OFDM symbol, different sub-carriers in a same frequency domain bandwidth respectively.

48. The network device according to any one of claims 40 to 47, wherein, each DMRS
5 sequence in at least one DMRS sequence in the K DMRS sequences occupies different sub-carriers in different OFDM symbols.