

## DESCRIPTION

## COMMUNICATION APPARATUS AND COMMUNICATION METHOD

## TECHNICAL FIELD

5 [0001]

A technology disclosed herein relates to a communication apparatus and a communication method that are capable of performing transmission processing in a state of detecting an interference signal (such as a  
10 signal that arrives from an adjacent cell).

## BACKGROUND ART

[0002]

IEEE 802.11 serving as one example of a  
15 representative standard for a wireless LAN defines carrier sense multiple access/collision avoidance (CSMA/CA) as a mechanism in which each terminal station autonomously acquires a transmission opportunity. Specifically, a terminal station performs transmission  
20 standby (backoff) during a random time period, and observes ambient radio wave environment (performs carrier sensing) during this backoff. When the terminal station detects radio waves having a power that is greater than or equal to a certain detection threshold, the terminal  
25 station stops backoff, and suppresses transmission of a packet. Due to this mechanism of backoff and carrier sensing, the terminal station avoids packet collision while acquiring a transmission opportunity in an autonomous distributed manner.

30 [0003]

However, in an environment in which many terminal

stations exist in high density, if the detection of radio waves and the avoidance of collision that are described above are performed by using a detection threshold set according to the IEEE 802.11 standard, for example, a  
5 signal that has been transmitted from a terminal station that belongs to an adjacent cell is detected, and transmission is suppressed excessively or unnecessarily. Such a case has been regarded as a problem. Note that the "cell" described above is equivalent to, for example,  
10 a basic service set (BSS) that a base station configures together with terminal stations under control. Furthermore, the adjacent cell is equivalent to another BSS having an overlapping receivable range (hereinafter also referred to as an "overlapping basic service set  
15 (OBSS)").

[0004]

Accordingly, for example, in IEEE 802.11ax serving as one example of a next-generation wireless LAN standard, a spatial reuse (SR) technology has been being examined  
20 in which adjacent cells reuse a single frequency channel and frequency resources are efficiently used. Specifically, even if terminal stations in cells adjacent to each other detect a signal from each other, the terminal stations are enabled to transmit their own  
25 packets. The SR technology described above can be realized by describing a simplified BSS identifier called a "BSS Color" in a PHY header of a packet so as to enable a reception side to discriminate a signal (hereinafter also referred to as a "local-cell signal") of a BSS (the  
30 local cell) that the reception side belongs to from a signal (hereinafter also referred to as an "adjacent-cell

signal") from an OBSS (an adjacent cell) on the basis of the BSS Color described in the PHY header (see, for example, Patent Document 1).

[0005]

5           For example, in a case where a terminal station that has received a packet can determine that the packet is an adjacent-cell signal on the basis of the content described in the PHY header, the terminal station interrupts the reception of a packet at this point in  
10 time. Moreover, if the reception power of the received signal is less than or equal to a detection threshold (an OBSS-power detection (PD) threshold) of the adjacent-cell signal, the start of backoff is permitted. This enables spatial reuse to be realized. Due to spatial reuse, even  
15 if a signal is still being transmitted from the OBSS, an opportunity to transmit a signal to the terminal station increases. This results in improvements in a throughput of the entirety of a system.

[0006]

20           Note that, in SR transmission based on the detection of the OBSS-PD threshold, the OBSS-PD threshold is generally adjusted. For example, the terminal station can increase the OBSS-PD threshold by reducing its own transmission power, and can easily acquire a transmission  
25 opportunity using spatial reuse by adjusting the transmission power according to interference power.

#### CITATION LIST

#### PATENT DOCUMENT

30 [0007]

Patent Document 1: Japanese Patent Application Laid-Open

No. 2016-28465

#### SUMMARY OF THE INVENTION

#### PROBLEMS TO BE SOLVED BY THE INVENTION

5 [0008]

It is an object of the technology disclosed herein to provide a communication apparatus and a communication method having high quality that are capable of suitably performing transmission processing in a state of  
10 detecting an interference signal.

#### SOLUTIONS TO PROBLEMS

[0009]

The technology disclosed herein has been made in  
15 consideration of the problems above. A first aspect of the technology disclosed herein is a communication apparatus including:

a communication unit that transmits or receives a signal;

20 an information obtaining unit that obtains information relating to interference that each transmission destination candidate receives from an interference source; and

a controller that selects each of the transmission  
25 destination candidates on the basis of the information when an interference signal arrives.

[0010]

Furthermore, a second aspect of the technology disclosed herein is a communication method including:

30 an information obtaining step of obtaining information relating to interference that each

transmission destination candidate receives from an interference source; and

a controlling step of selecting each of the transmission destination candidates on the basis of the information when an interference signal arrives.  
[0011]

Furthermore, a third aspect of the technology disclosed herein is a communication apparatus that operates under a control of an access point, the communication apparatus including:

a controller that performs control to transmit, to the access point, information relating to an intensity of a received signal of an OBSS signal.

## 15 EFFECTS OF THE INVENTION [0012]

According to the technology disclosed herein, a communication apparatus and a communication method having high quality can be provided that are capable of suitably performing transmission processing in a state of detecting an interference signal.  
[0013]

Note that effects described herein are merely examples, and effects of the present invention are not limited to the effects described herein. Furthermore, the present invention further exhibits additional effects in addition to the effects described above in some cases.  
[0014]

Yet other objects, features, and advantages of the technology disclosed herein will be clarified by a more detailed description based on the embodiments described

later and the attached drawings.

#### BRIEF DESCRIPTION OF DRAWINGS

[0015]

5           Fig. 1 illustrates an example of an ideal configuration of a wireless LAN system to which SR transmission based on OBSS-PD is applied.

          Fig. 2 illustrates an example of a signal transmission sequence in a wireless LAN system 100  
10   illustrated in Fig. 1.

          Fig. 3 illustrates an example of a configuration of a wireless LAN system 300.

          Fig. 4 is a flowchart illustrating a processing procedure performed when a terminal station receives a  
15   frame.

          Fig. 5 is a block diagram illustrating an example of implementation for recording reception power and a BSS Color of an OBSS signal.

          Fig. 6 is a flowchart illustrating a processing  
20   procedure for reporting OBSS RSSI information to an AP.

          Fig. 7 illustrates an example of a configuration of a measurement report frame.

          Fig. 8 illustrates an example of a table that reflects a rough positional relationship among each STA  
25   under the control of the AP, OBSS's, and the AP.

          Fig. 9 is a diagram explaining an example of a method in which the AP realizes SR transmission based on OBSS-PD.

          Fig. 10 illustrates an example of a signal  
30   transmission sequence at a time when the AP realizes SR transmission based on OBSS-PD.

Fig. 11 is a diagram explaining another example of the method in which the AP realizes SR transmission based on OBSS-PD.

Fig. 12 illustrates an example of a signal  
5 transmission sequence at a time when the AP realizes SR transmission based on OBSS-PD.

Fig. 13 is a diagram explaining another example of the method in which the AP realizes SR transmission based on OBSS-PD.

10 Fig. 14 illustrates an example of a signal transmission sequence at a time when the AP realizes SR transmission based on OBSS-PD.

Fig. 15 is a flowchart illustrating a processing procedure in which the AP realizes SR transmission based  
15 on OBSS-PD.

Fig. 16 illustrates an example of a configuration of a wireless LAN system 1600.

Fig. 17 illustrates a result of performing clustering processing on the wireless LAN system 1600  
20 illustrated in Fig. 16.

Fig. 18 illustrates an example of a table obtained by dividing STAs and OBSS's into clusters on the basis of an arrival angle.

Fig. 19 is a flowchart illustrating a processing  
25 procedure in which the AP realizes SR transmission based on OBSS-PD.

Fig. 20 illustrates an example of a functional configuration of a communication apparatus 2000.

30 MODE FOR CARRYING OUT THE INVENTION

[0016]

Embodiments of the technology disclosed herein are described below in detail with reference to the drawings.  
[0017]

Fig. 1 schematically illustrates an example of an  
5 ideal configuration of a wireless LAN system 100 to which  
SR transmission based on OBSS-PD is applied. The  
illustrated wireless LAN system 100 includes a plurality  
of base stations (access points: APs) and a plurality of  
terminal stations (stations: STAs) among which connection  
10 has been established. It is assumed that an interference  
source such as an adjacent cell or another system exists  
around the wireless LAN system 100. In the illustrated  
example, a BSS that an AP configures together with STA 1  
to STA 3 under control is denoted by reference number 101.  
15 Furthermore, an OBSS (an OBSS-STA) having a receivable  
range that overlaps a receivable range of the BSS 101 is  
denoted by reference number 102. From among STA 1 to STA  
3 under the control of the AP, STA 1 and STA 3 have a  
receivable range that overlaps a receivable range of the  
20 OBSS 102, but STA 2 does not have a receivable range that  
overlaps the receivable range of the OBSS 102.  
[0018]

Furthermore, Fig. 2 illustrates an example of a  
signal transmission sequence in the wireless LAN system  
25 100 illustrated in Fig. 1 (note that a horizontal axis is  
a time axis). While a STA (an OBSS-STA) in the OBSS 102  
is transmitting a signal, STA 1 to STA 3 are set to a  
busy state and stand by for transmission until the  
transmission processing of the OBSS-STA is terminated.  
30 On the other hand, even if the OBSS-STA does not complete  
signal transmission, the AP can determine that the AP can

transmit a signal to STA 2. This is because STA 2 exists outside the receivable range of the OBSS 102, and does not receive interference or only receives small interference from the OBSS-STA.

5 [0019]

By setting an OBSS-PD threshold that is less than the reception power of a signal from the OBSS-STA, the AP returns to an IDLE state (in other words, a non-busy state) after detecting a BSS Color in a PHY header of the received signal, and the AP can start the transmission of a signal to STA 2. In contrast, in a case where the AP transmits a signal to STA 1 rather than STA 2, it is obvious that a signal received by STA 1 is strongly interfered with by the OBSS-STA.

15 [0020]

Accordingly, in SR transmission based on OBSS-PD, the key to success is to appropriately select a transmission destination of a signal. However, in practice, a wireless LAN is not a centralized system but is a distributed system, and all of the STAs autonomously perform communication. Therefore, in a case where SR transmission based on OBSS-PD is applied, it is significantly difficult to select an appropriate transmission destination.

25 [0021]

SR transmission based on OBSS-PD is defined in the latest IEEE 802.11ax specification, but no prior arts, such as documents, that discuss the dynamic adjustment of an OBSS-PD threshold have not been discovered. In general, if the OBSS-PD threshold is a fixed value, only a limited effect of SR is realized. The most significant

obstacle in dynamically utilizing SR transmission based on OBSS-PD is that the AP lacks information relating to interference from the OBSS that each candidate for a transmission destination will receive. Therefore, the AP fails to correctly determine both whether or not a higher OBSS-PD threshold is to be set in order to create a transmission opportunity and which transmission destination a signal is to be transmitted to.

[0022]

In order to easily perform dynamic SR transmission based on OBSS-PD, a minimum level of information exchange is required. If a report about a result of measuring reception power is added to OBSS information, APs can mutually exchange information relating to OBSS interference that a BSS of the local AP is receiving. By doing this, an AP can grasp a situation of another AP, and this enables the performance of the entirety of a system to be optimized while the respective APs cooperate with each other.

[0023]

Herein, a method relating to the exchange of information that causes dynamic SR transmission based on OBSS-PD to be easily performed is proposed below.

Example 1

[0024]

In Example 1, when an AP performs downlink SR transmission based on OBSS-PD, the AP uses a receiving signal strength indicator (RSSI) of an OBSS signal of each STA under control as information for appropriately selecting a transmission destination. The RSSI is information that can almost directly indicates an

influence of interference that a STA receives from an OBSS, and the AP can select a more appropriate transmission destination. Furthermore, the AP needs a minimum sequence (overhead) to exchange information relating to the RSSI of the OBSS with each of the STAs under control in order to realize downlink SR transmission based on OBSS-PD.

[0025]

Fig. 3 illustrates an example of a configuration of a wireless LAN system 300 to which the technology disclosed herein can be applied. In this drawing, an AP configures a single BSS together with STA 1 to STA 4 under control (that are not APs). Furthermore, four OBSS's having an overlapping receivable range exist to be adjacent to this BSS. Assume that (BSS Colors of) the respective OBSS's are OBSS 1, OBSS 2, OBSS 3, and OBSS 4. Example 1 of the technology disclosed herein is described below in detail with appropriate reference to Fig. 3.

[0026]

When a STA of one of the OBSS's is transmitting a signal and terminal stations (STA 1 to STA 4 and the AP) receive a frame, the terminal stations check the field "BSS Color" in a PHY header of the frame so as to identify whether or not the received frame is a frame that has arrived from the OBSS.

[0027]

Fig. 4 illustrates a processing procedure performed when a terminal station receives a frame in the form of a flowchart.

[0028]

Upon receipt of a frame (step S401), a terminal

station checks the field "BSS Color" in a PHY header of the frame (step S402).

[0029]

First, the terminal station checks whether or not  
5 the field "BSS Color" in the PHY header is available  
(step S403). In a case where a transmission source of  
the frame does not conform to IEEE 802.11ax, the field  
"BSS Color" does not exist in the PHY header, and in  
other words, the field "BSS Color" is not available.

10 [0030]

On the other hand, in a case where the field "BSS  
Color" in the PHY header is available (Yes in step S403),  
the terminal station further checks whether or not the  
received frame is a frame that has arrived from an OBSS  
15 on the basis of whether or not a value of the BSS Color  
is different from a value of the terminal station (step  
S404).

[0031]

Then, in a case where the received frame is a frame  
20 that has arrived from the OBSS (Yes in step S404), the  
terminal station records, for example, reception power  
measured in a preamble portion of the received frame,  
namely, an RSSI, together with the value of the BSS Color  
obtained in step S403 (step S405).

25 [0032]

When a time period has passed, the terminal station  
can record RSSI's and BSS Colors from all or most of  
neighboring OBSS's. However, it is to be noted that a  
position and an ambient environment of each of the  
30 terminal stations change with time, and therefore each of  
the terminal stations needs to update the information

above relating to the OBSS.

[0033]

Fig. 5 illustrates an implementation example of a STA that can realize functionality relating to downlink SR transmission based on OBSS-PD, as described above, by using the valid complexity of hardware in the form of a block diagram.

[0034]

A BSS Color detector 501 detects a BSS Color described in a PHY header of a frame that has arrived. Whether an arrival signal is a BSS signal or an OBSS signal can be determined on the basis of the detected BSS Color. A bank of moving average (MA) filters 502-1, 502-2, ..., and 502-N is arranged in order to process an RSSI of a received signal from each of the OBSS's. Once the BSS Color detector 501 specifies the BSS Color of the frame that has arrived, an RSSI of the frame is pushed into a corresponding MA filter 502-1, 502-2, ..., or 502-N, and an output of the corresponding MA filter is labeled a BSS Color of a corresponding OBSS, and is stored in a table (an OBSS RSSI table) 503.

[0035]

Even a signal from the same transmitter has a large deviation in reception power in some cases. However, by using the MA filters 502-1 and the like, the effectiveness of the deviation in reception power can be reduced due to fading and shadowing. Additionally, the MA filters 502-1 and the like can track a change in reception power that is generated due to a change in the position or ambient environment of a terminal station, as described above.

[0036]

Upon receipt of a measurement request from an AP, a STA transmits, to the AP, information stored in the OBSS RSSI table 503. It is to be noted that the number of  
5 OBSS's is an indefinite value depending on a situation of a BSS or an individual STA, and it is preferable that minimum information be transmitted instead of all pieces of information stored in the OBSS RSSI table 503.

[0037]

10 Accordingly, a rearrangement/search unit 504 rearranges records of the OBSS RSSI table 503 according to the size of the RSSI, extracts, from the OBSS RSSI table 503, maximum value information (Max) that includes a pair of a maximum value (RSSI\_max) of the RSSI and a  
15 BSS Color (Color\_max) of a corresponding OBSS, and minimum value information (Min) that includes a pair of a minimum value (RSSI\_min) of the RSSI and a BSS Color (Color\_min) of a corresponding OBSS, and transmits the maximum value information and the minimum value  
20 information to the AP.

[0038]

As described above, the AP transmits the measurement request so as to be able to periodically obtain OBSS RSSI information, as described above, from a  
25 specified STA (under control) that is not an AP. After the STA under the control of the AP receives a measurement request frame from the AP, the STA checks the OBSS RSSI table 503, and transmits, to the AP, a measurement report frame that includes the maximum value  
30 and the minimum value of the RSSI and information relating to respective paired BSS Colors.

[0039]

Fig. 6 illustrates a processing procedure in which the STA under the control of the AP reports the OBSS RSSI information to the AP in the form of a flowchart.

5 [0040]

Upon receipt of a measurement request from the AP (step S601), the STA under the control of the AP checks the OBSS RSSI table 503 (see Fig. 5), and searches for BSS Colors that respectively correspond to the maximum  
10 value and the maximum value of the RSSI (step S602).

[0041]

Then, the STA writes the maximum value and the minimum value of the RSSI and the respective paired BSS Colors to a measurement report frame (step S603), and  
15 transmits the measurement report frame to the AP (step S604).

[0042]

The number of OBSS's is indefinite and depends on a specified situation, and therefore the size of the OBSS  
20 RSSI table 503 is variable. Therefore, it is to be noted that it is preferable that a limited minimum piece of information, rather than the entirety of the table, be transmitted from the STA to the AP. Herein, as described with reference to Figs. 5 and 6, it is recommended that  
25 the STA only transmit, to the AP, the maximum value and the maximum value of the RSSI and the respective BSS Colors that have been recorded.

[0043]

Fig. 7 illustrates an example of a configuration of  
30 the measurement report frame. The frame includes a preamble located at the top, a physical layer convergence

protocol (PLCP) header, and an MPDU that is equivalent to a media access control (MAC) frame. Furthermore, the MAC protocol data unit (MPDU) includes a MAC header, a frame body, and a frame check sequence (FCS). In the  
5 illustrated frame configuration example, information relating to a measurement report of reception power is described in the frame body of the MPDU.

[0044]

In the frame body, respective fields, Category,  
10 Action, and Information Element, are provided. In the field "Category", a value indicating an action to be performed on this frame is set, and the field "Category" is probably set to 5 in order to mean a frame for wireless measurement. The field "Action" is set to 1,  
15 and this indicates a measurement report frame (incidentally, 0 indicates a measurement request frame). In the field "Information Element", OBSS RSSI information that includes a pair of a maximum value (Max OBSS RSSI) of an OBSS RSSI to be reported and color information (Max  
20 OBSS RSSI Color) of the maximum value and a pair of a minimum value (Min OBSS RSSI) of the OBSS RSSI and color information (Min OBSS RSSI Color) of the minimum value, and an element ID used to indicate a measurement report (of reception power) are stored. The OBSS RSSI  
25 information is information obtained by pairing an RSSI of a signal of an OBSS and a BSS Color of the OBSS, and may further include information that is different from the maximum value and the minimum value of the RSSI that are described above.

30 [0045]

Note that the STA may transmit the OBSS RSSI

information described above to the AP by using a management frame or an action frame.

[0046]

After the AP collects the OBSS RSSI information by  
 5 using the measurement report frames transmitted from all  
 of the STAs in a BSS of the AP, the AP can construct a  
 table or a database that reflects a rough positional  
 relationship among each of the STAs under control, OBSS's,  
 and the AP. Fig. 8 illustrates an example of the table  
 10 above. In the illustrated table, for each of the OBSS's,  
 a STA (Min RSSI) having a minimum RSSI and a STA (Max  
 RSSI) having a maximum RSSI are listed.

[0047]

Referring to the network configuration illustrated  
 15 in Fig. 3, STA 2 and STA 4 are located apart from OBSS 1,  
 and therefore an RSSI from OBSS 1 has a minimum value,  
 and STA 2 and STA 4 are listed in the row "Min RSSI of  
 the column OBSS 1 in the table illustrated in Fig. 8.  
 Furthermore, STA 2 is located closest to OBSS 2, and  
 20 therefore an RSSI from OBSS 2 has a maximum value, and  
 STA 2 is listed in the row "Max RSSI" of the column "OBSS  
 2" in the same table. Furthermore, STA 4 is located  
 closest to OBSS 3, and therefore an RSSI from OBSS 3 has  
 a maximum value, and STA 4 is listed in the row "Max  
 25 RSSI" of the column "OBSS 3" in the same table.

[0048]

Furthermore, STA 1 is located closest to OBSS 4, an  
 RSSI from OBSS 4 has a maximum value, and STA 1 is listed  
 in the row "Max RSSI" of the column "OBSS 4" in the same  
 30 table. In addition, STA 1 is located apart from OBSS 2,  
 an RSSI from OBSS 2 has a minimum value, and STA 1 is

listed in the row "Min RSSI" of the column "OBSS 2" in the same table.

[0049]

Furthermore, STA 3 is located closest to OBSS 1, an RSSI from OBSS 1 has a maximum value, and STA 3 is listed in the row "Max RSSI" of the column "OBSS 1" in the same table. In addition, STA 3 is located apart from OBSS 3, an RSSI from OBSS 3 has a minimum value, and STA 3 is listed in the row "Min RSSI" of the column "OBSS 3".

10 [0050]

In brief, the table illustrated in Fig. 8 lists a STA for which an RSSI from each of the OBSS's becomes minimum or maximum on the basis of the measurement report frame that the AP has received from each of the STAs under control. A table having the structure above reflects a rough positional relationship among each of the STAs under the control of an AP, OBSS's, and the AP, and can also be said to reflect degrees of interference that each of the STAs under the control of the AP receives from the OBSS's.

20 receives from the OBSS's.

[0051]

Note that under a communication environment where the transmittance of radio waves is uniform, the RSSI is almost proportional to a distance between transceivers.

25 Therefore, a table that is constructed on the basis of RSSI's from OBSS's, as illustrated in Fig. 8, can be said to indicate a positional relationship among each of the STAs under the control of an AP, the OBSS's, and the AP. On the other hand, under a communication environment where an obstacle having a low transmittance of radio waves (such as a screen door, a window glass, or the

30 waves (such as a screen door, a window glass, or the

like) is distributed, there is a possibility that an RSSI that is lower than an RSSI to be expected from an actual distance will be measured for a STA that an OBSS signal arrives at via the obstacle. However, even if a table is  
5 constructed on the basis of an RSSI that does not reflect an actual positional relationship with a STA or an OBSS due to the presence of the obstacle, it is thought that no problem arises in the viewpoint of avoiding interference with an OBSS signal and realizing SR  
10 transmission.

[0052]

Fig. 9 explains an example of a method in which an AP utilizes the table illustrated in Fig. 8 so as to realize SR transmission based on OBSS-PD in the wireless  
15 LAN system 300 illustrated in Fig. 3. Furthermore, Fig. 10 illustrates an example of a signal transmission sequence at a time when a signal has been transmitted from OBSS 2 (note that a horizontal axis is a time axis).

[0053]

20 When a signal has arrived from OBSS 2, the AP is temporarily set to a busy state, and stands by for transmission. At this time, when the AP detects that the field "BSS Color" in a PHY header of a frame received from OBSS 2 is available and that the received signal is  
25 a signal that has arrived from OBSS 2 (OBSS Color filtering), the AP makes an attempt to realize SR transmission based on OBSS-PD (by setting an appropriate OBSS-PD threshold, for example, by increasing an OBSS-PD threshold). In other words, the AP refers to the  
30 category "Min RSSI" of OBSS 2 in the table illustrated in Fig. 8, and senses that an OBSS 2 signal having a minimum

RSSI arrives at STA 1 at this point in time. Accordingly, the AP can determine to perform SR transmission to STA 1 for which interference received from OBSS 2 is smaller than interference of the other STAs because STA 1 is  
5 located apart from OBSS 2.

[0054]

Furthermore, Fig. 11 explains another example of the method in which the AP utilizes the table illustrated in Fig. 8 so as to realize SR transmission based on OBSS-  
10 PD in the wireless LAN system 300 illustrated in Fig. 3. Fig. 12 illustrates an example of a signal transmission sequence at a time when a signal has been transmitted from OBSS 1 (note that a horizontal axis is a time axis). The AP is temporarily set to a busy state, and stands by  
15 for transmission. The AP also refers to a PHY header of a received frame, and detects that the received signal is a signal that has arrived from OBSS 1. Then, the AP refers to the category "Min RSSI" of OBSS 1 in the table illustrated in Fig. 8, and senses that an OBSS 1 signal  
20 having a minimum RSSI arrives at STA 2 and STA 4 at this point in time. Accordingly, the AP can determine to perform SR transmission to STA 2 or STA 4 because STA 2 and STA 4 are located apart from OBSS 1. At this time, the AP may determine which of STA 2 and STA 4  
25 transmission is to be performed on in accordance with a certain standard such as an original queue sequence or a priority order.

[0055]

Furthermore, in a method for configuring a table on  
30 the basis of the measurement report frames received from STAs under control, it is also assumed that an OBSS for

which the category "Min RSSI" becomes blank exists, for example, as illustrated as OBSS 4 in the table illustrated in Fig. 8. In such a case, the AP may make an attempt to perform SR transmission to one of STAs that

5 an OBSS 4 signal that does not have a maximum RSSI arrives at. In a case where OBSS 4 is transmitting a signal (see Figs. 13 and 14), the AP is temporarily set to a busy state, and stands by for transmission. The AP also refers to a PHY header of a received frame, and

10 detects that the received signal is a signal that has arrived from OBSS 4. Then, the AP refers to the category "Min RSSI" of OBSS 4 in the table illustrated in Fig. 8, and fails to sense a STA that an OBSS 4 signal having a minimum RSSI arrives at at this point in time. However,

15 the AP refers to the category "Max RSSI" of OBSS 4 in the same table, and can discover that STA 1 is located closest to OBSS 4. Accordingly, the AP can determine to perform SR transmission to a STA other than STA 1, namely, one of STA 2 to STA 4. At this time, the AP may

20 determine which of STA 2 to STA 4 transmission is to be performed on in accordance with a certain standard such as an original queue sequence or a priority order.

[0056]

Fig. 15 illustrates a processing procedure in which

25 an AP realizes SR transmission based on OBSS-PD by utilizing the table illustrated in Fig. 8 (that has been constructed on the basis of the measurement reports of reception power from STAs under control) in the form of a flowchart.

30 [0057]

Upon receipt of a frame (step S1501), the AP checks

the field "BSS Color" in a PHY header of the frame (step S1502).

[0058]

First, the AP checks whether or not the field "BSS Color" in the PHY header is available (step S1503). In a case where a transmission source of the frame does not conform to IEEE 802.11ax, the field "BSS Color" does not exist in the PHY header, and in other words, the field "BSS Color" is not available.

10 [0059]

On the other hand, in a case where the field "BSS Color" in the PHY header is available (Yes in step S1503), the AP further checks whether or not the received frame is a frame that has arrived from an OBSS on the basis of whether or not a value of the BSS Color is different from a value of the AP (step S1504).

[0060]

Then, in a case where the received frame is a frame that has arrived from the OBSS (Yes in step S1504), when the AP confirms that an RSSI of a signal of the OBSS is greater than or equal to a minimum value (OBSS-PD Thld\_min) of an OBSS-PD threshold and is less than or equal to a maximum value (OBSS-PD Thld\_max) of the OBSS-PD threshold (Yes in step S1505), the AP sets an appropriate OBSS-PD threshold, and also stops processing for receiving the OBSS frame (step S1506).

[0061]

Next, the AP checks a database (for example, the table illustrated in Fig. 8 that has been constructed on the basis of the measurement reports of reception power from STAs under control), and searches for a STA having a

30

minimum RSSI with respect to a BSS Color (identified in step S1503) of an OBSS signal that has currently arrived (step S1507).

[0062]

5           Here, in a case where a STA having a minimum RSSI with respect to the BSS Color of a current arrival frame has been discovered and the AP has transmission data for the STA (Yes in step S1508), the AP moves the discovered STA to the top of a transmission queue (step S1509).

10   [0063]

          On the other hand, in a case where a STA having a minimum RSSI with respect to the BSS Color of the current arrival frame has not been discovered (No in step S1508), the AP further checks the database, and searches for a STA that does not exist in the category "Max RSSI" with respect to the BSS Color of the current arrival frame (step S1510).

[0064]

          Then, in a case where a STA that does not exist in the category "Max RSSI" with respect to the BSS Color of the current arrival frame has been discovered and the AP has transmission data for the STA (Yes in step S1511), the AP moves the discovered STA to the top of a transmission queue (step S1509).

25   [0065]

          Thereafter, the AP restarts backoff (step S1512). Then, in a case where a backoff time has elapsed but the frame that has arrived in step S1501 has not yet been finished (Yes in step S1513), the AP sets an appropriate transmission power, and transmits a packet (step S1514).

[0066]

As described above, when the AP performs downlink SR transmission based on OBSS-PD, the AP uses an RSSI of an OBSS signal of each of the STAs under control as information for appropriately selecting a transmission destination. The RSSI is information that can almost directly indicates an influence of interference that a STA receives from an OBSS, and the AP can select a more appropriate transmission destination. However, the AP needs a minimum sequence (overhead) to exchange information relating to the RSSI of the OBSS with each of the STAs under control in order to realize downlink SR transmission based on OBSS-PD.

#### Example 2

[0067]

In Example 2, when the AP performs downlink SR transmission based on OBSS-PD, the AP uses information relating to an angle of arrival (AoA) as information for appropriately selecting a transmission destination. The AoA itself does not directly indicate an influence of an interference signal. However, an influence of interference that a STA receives from an OBSS also changes according to a degree of similarity in the AoA to an OBSS signal, and therefore the AP can utilize the AoA as information for selecting a candidate for the transmission destination.

[0068]

Then, the AP uses the measurement of AoA's of a BSS signal and the OBSS signal by spontaneously using a directional antenna without obtaining information such as the OBSS RSSI information (described above) from each of the STAs under control so as to be able to generate a

table that reflects a rough positional relationship among each of the STAs under control, OBSS's, and the AP. This enables exchange of information with the STAs or the like to be omitted. Such a table reflects a rough positional relationship between the STAs and the OBSS's, and can also be said to reflect degrees of interference that each of the STAs under the control of the AP receives from the OBSS's.

[0069]

10           In a wireless LAN system 1600 illustrated in Fig. 16, an AP configures a single BSS together with STA 1 to STA 4 under control (that are not APs). Furthermore, two OBSS's, OBSS 1 and OBSS 2, are adjacent to this BSS. The AP can obtain AoA's of STA 1 to STA 4 under control, OBSS 1, and OBSS 2 by using AoA measurement by spontaneously using a directional antenna. The AP uses MA processing that is similar to MA processing illustrated in Fig. 5 so as to reduce the effectiveness of a deviation in reception power due to fading and shadowing, and obtains an average AoA of STA 1 to STA 4, OBSS 1, and OBSS 2. However, the AP may obtain AoA's of each of the STAs under control and the OBSS's by using an arbitrary method other than spontaneous measurement.

[0070]

25           After data of the AoA becomes available, the AP divides a space into a plurality of clusters (four clusters 1 to 4 in the illustrated example), as illustrated in Fig. 17, performs clustering processing for grouping STAs and an OBSS that have a similar AoA into the same cluster, and classifies the wireless LAN system 1600 each of the STAs and the OBSS's into clusters

different from each other.

[0071]

As described above, the AP can generate a table in which the STAs under control and the OBSS's have been  
5 classified into clusters 1 to 4 on the basis of the AoA, as illustrated in Fig. 18. AoA's of signals that arrive at the AP from STA 1, STA 3, and OBSS 1 are similar to each other, and therefore STA 1, STA 3, and OBSS 1 are grouped into cluster 1. Furthermore, AoA's of signals  
10 that arrive at the AP from STA 2 and OBSS 2 are similar to each other, and therefore STA 2 and OBSS 2 are grouped into cluster 3. On the other hand, there are neither STAs nor OBSS's that belong to cluster 2, and only STA 4 exists in cluster 4. A STA and an OBSS in the same  
15 cluster mean to have a similar angle of arrival at the AP, and it is also understood from Fig. 17 that the STA and the OBSS in the same cluster are physically close to each other. In contrast, it is also understood from Fig. 17 that there is a possibility that a STA and an OBSS that  
20 respectively belong to clusters in which angles of arrival at the AP are located on sides opposite to each other are physically located apart from each other.

[0072]

For example, when OBSS 1 is transmitting a signal,  
25 as illustrated in Fig. 17, the AP can understand that STA 1 and STA 3 belong to cluster 1 serving as the same cluster as a cluster that OBSS 1 belongs to, by searching the table illustrated in Fig. 18. Accordingly, because there is a possibility that OBSS 1 is physically close to  
30 each of STA 1 and STA 3, the AP may avoid transmission to STA 1 and STA 3, and may perform SR transmission to STA 2

that belongs to cluster 3 that is located at an AoA opposite to an AoA of cluster 1.

[0073]

Note that Fig. 17 illustrates an example where 360  
5 degrees around the AP are equally divided into four  
clusters at each AoA of 90 degrees, but do not need to be  
divided into clusters at each identical AoA. For example,  
a direction in which OBSS's and STAs exist in high  
density may be divided into clusters at each narrow AoA.  
10 In contrast, in a direction in which OBSS's and STAs  
exist in low density, the STAs and the OBSS's may be  
grouped into a single cluster by using a wide AoA.  
Furthermore, cluster division may be performed in such a  
way that an almost equal number of OBSS's and STAs are  
15 accommodated in each of the clusters, or cluster division  
may be performed in such a way that OBSS's are  
distributed.

[0074]

Furthermore, Figs. 17 and 18 illustrate an example  
20 where the circumference of the AP is divided into four  
clusters, but the circumference of the AP can be divided  
into three or less clusters, or may be divided into five  
or more clusters.

[0075]

25 In brief, the table illustrated in Fig. 18 lists  
clusters obtained by performing clustering processing on  
STAs and OBSS's on the basis of an angle of arrival at  
the AP. A STA and an OBSS in the same cluster have a  
similar AoA, and therefore the STA and the OBSS are  
30 physically close to each other. There is a possibility  
that an influence of interference is significant. In

contrast, a STA and an OBSS that respectively belong to clusters in which angles of arrival at the AP are located opposite to each other are physically located apart from each other, and there is a possibility that an influence  
5 of interference is small. Accordingly, the cluster table described above reflects a rough positional relationship among each of the STAs under the control of an AP, OBSS's, and the AP, and can also be said to reflect degrees of interference that each of the STAs under the control of  
10 the AP receives from the OBSS's.

[0076]

Note that radio waves that arrive at the AP from a STA or an OBSS are not limited to direct waves, and there is a possibility that the radio waves are reflected waves  
15 that have been reflected by a wall or the like or other indirect waves. If arrival waves of the AP are not direct waves, a STA or an OBSS serving as a signal source of the arrival waves does not exist in a direction of an AoA measured in the AP, and a table obtained by  
20 performing clustering processing on the basis of the arrival waves does not necessarily reflect an actual positional relationship with the STA or the OBSS. However, if radio waves propagate through the same route in a going path and a returning path and sending-out is  
25 performed in a direction of an AoA, it can be assumed that a signal is transmitted to a corresponding party. Accordingly, even if a cluster table that does not reflect an actual positional relationship is constructed on the basis of an AoA of arrival waves including  
30 indirect waves, it is thought that no problem arises in the viewpoint of avoiding interference with an OBSS

signal and realizing SR transmission.

[0077]

Fig. 19 illustrates a processing procedure in which an AP realizes SR transmission based on OBSS-PD by  
 5 utilizing the table illustrated in Fig. 18 (that has been constructed on the basis of AoA's of a STA and an OBSS) in the form of a flowchart.

[0078]

Upon receipt of a frame (step S1901), the AP checks  
 10 the field "BSS Color" in a PHY header of the frame (step S1902).

[0079]

First, the AP checks whether or not the field "BSS Color" in the PHY header is available (step S1903). In a  
 15 case where a transmission source of the frame does not conform to IEEE 802.11ax, the field "BSS Color" does not exist in the PHY header, and in other words, the field "BSS Color" is not available.

[0080]

On the other hand, in a case where the field "BSS Color" in the PHY header is available (Yes in step S1903),  
 20 the AP further checks whether or not the received frame is a frame that has arrived from an OBSS on the basis of whether or not a value of the BSS Color is different from a value of the AP (step S1904).

[0081]

Then, in a case where the received frame is a frame that has arrived from the OBSS (Yes in step S1904), when  
 30 the AP confirms that an RSSI of a signal of the OBSS is greater than or equal to a minimum value (OBSS-PD Thld\_min) of an OBSS-PD threshold and is less than or

equal to a maximum value (OBSS-PD Thld\_max) of the OBSS-PD threshold (Yes in step S1905), the AP sets an appropriate OBSS-PD threshold, and also stops processing for receiving the OBSS frame (step S1906).

5 [0082]

Next, the AP checks a database (for example, the table illustrated in Fig. 18 that has been constructed by performing clustering on a STA and an OBSS on the basis of an AoA), and searches for a STA that belongs to a cluster that is located on an opposite side of a cluster that an OBSS from which an interference signal has currently arrived belongs to (step S1907).

[0083]

Here, in a case where a STA that belongs to a cluster that is located on an opposite side of the cluster that the OBSS from which an interference signal has currently arrived belongs to has been discovered and the AP has transmission data for the STA (Yes in step S1908), the AP moves the discovered STA to the top of a transmission queue (step S1909).

[0084]

On the other hand, in a case where a STA that belongs to a cluster that is located on an opposite side of the cluster that the OBSS from which an interference signal has currently arrived belongs to has not been discovered (No in step S1908), the AP further checks the database, and searches for a STA that belongs to a cluster that is different from (is located as far as possible from) the cluster that the OBSS from which an interference signal has currently arrived belongs to (step S1910).

[0085]

Then, in a case where a STA that belongs to a cluster that is different from (is located as far as possible from) the cluster that the OBSS from which an interference signal has currently arrived belongs to has been discovered and the AP has transmission data for the STA (Yes in step S1911), the AP moves the discovered STA to the top of a transmission queue (step S1909).

[0086]

10        Thereafter, the AP restarts backoff (step S1912). Then, in a case where a backoff time has elapsed but the frame that has arrived in step S1901 has not yet been finished (Yes in step S1913), the AP sets an appropriate transmission power, and transmits a packet (step S1914).

15        [0087]

As described above, when the AP performs downlink SR transmission based on OBSS-PD, the AP uses information relating to AoA's of STAs under control and OBSS's as information for appropriately selecting a transmission destination. The AoA itself does not directly indicate an influence of an interference signal. However, an influence of interference that a STA receives from an OBSS also changes according to a degree of similarity in the AoA to an OBSS signal, and therefore the AP can utilize the AoA as information for selecting a candidate for the transmission destination. Furthermore, the AP can measure AoA's of signals that arrive from the STAs under control and the OBSS's by spontaneously using a directional antenna. Accordingly, the AP can select an appropriate transmission destination on the basis of information relating to the AoA without exchanging

20  
25  
30

information with the STAs under control, or the like.

[0088]

Note that the method described in Example 2 for performing downlink SR transmission based on OBSS-PD can also be used in combination with the method described in Example 1.

[0089]

Fig. 20 illustrates an example of a functional configuration of a communication apparatus 2000 that performs a communication operation as an AP or a STA in Examples 1 and 2 described above. It should be understood that both the AP and the STA have a similar basic configuration.

[0090]

The communication apparatus 2000 includes a data processing unit 2001, a controller 2002, a communication unit 2003, and a power source 2004. Furthermore, the communication unit 2001 further includes a modulator/demodulator 2011, a spatial signal processing unit 2012, a channel estimator 2013, a wireless interface (IF) 2014, an amplifier 2015, and an antenna 2016. However, a set of the wireless interface 2014, the amplifier 2015, and the antenna 2016 may configure a single transmission/reception branch, and the communication unit 2001 may include two or more transmission/reception branches. Furthermore, a function of the amplifier 2015 is included in the wireless interface 2014 in some cases.

[0091]

At the time of transmission of data that has been input from a protocol upper layer (not illustrated), the

data processing unit 2001 generates a packet for wireless transmission from the data, performs processing such as the addition of a header for MAC processing or the addition of an error detection code, and provides data  
5 after processing to the modulator/demodulator 2011.

Furthermore, at the time of reception at which an input is performed from the modulator/demodulator 2011, the data processing unit 2001 performs analysis of a MAC header, the detection of a packet error, reordering  
10 processing, and the like, and provides data after processing to a protocol upper layer of the data processing unit 2001.

[0092]

The controller 2002 communicates information with  
15 each unit in the communication apparatus 2000.

Furthermore, the controller 2002 performs parameter setting in the modulator/demodulator 2011 and the spatial signal processing unit 2012 and packet scheduling (the management of a transmission queue, and the like) in the  
20 data processing unit 2001. Furthermore, the controller 2002 performs parameter setting and transmission power control in the wireless interface 2014 and the amplifier 2015.

[0093]

25 In a case where the communication apparatus 2000 operates as an AP, the controller 2002 controls SR transmission based on an OBSS-PD threshold.

[0094]

Furthermore, in a case where the communication  
30 apparatus 2000 operates as an AP in Example 1, the controller 2002 processing for transmitting a measurement

request frame to STAs under control, sums a measurement report frame transmitted from each of the STAs, and constructs a table or a database (see Fig. 8) that indicates a rough positional relationship among each of the STAs under control, OBSS's, and the AP by being used in RSSI information, on the basis of OBSS RSSI information. Then, when the controller 2002 detects an OBSS signal, the controller 2002 refers to the table or database described above, selects an appropriate STA on which SR transmission will be performed, and controls packet transmission in accordance with the processing procedure illustrated in Fig. 15.

[0095]

Furthermore, in a case where the communication apparatus 2000 operates as a STA in Example 1, the controller 2002 stores a pair of an RSSI measured for each of the received OBSS signals and a BSS Color of each of the OBSS's (see Fig. 5). Then, upon receipt of a measurement request frame from the AP, the controller 2002 controls the transmission of a measurement report frame (see Fig. 7) storing OBSS RSSI information that includes a pair of a maximum value of an OBSS RSSI and corresponding color information and a pair of a minimum value of the OBSS RSSI and corresponding color information.

[0096]

Furthermore, in a case where the communication apparatus 2000 operates as an AP in Example 2, the controller 2002 performs clustering processing on the basis of a measurement result of AoA's of signals that arrive from STAs under control and OBSS's, groups STAs

and OBSS's having a similar AoA into a cluster, and constructs a table or a database (see Fig. 18) that indicates a rough positional relationship among each of the STAs under control, the OBSS's, and the AP by using  
5 clusters. Then, when the controller 2002 detects an OBSS signal, the controller 2002 refers to the table or database described above, selects an appropriate STA on which SR transmission will be performed, and controls packet transmission in accordance with the processing  
10 procedure illustrated in Fig. 19.

[0097]

At the time of transmission, the modulator/demodulator 2011 performs encoding, interleaving, and modulation processing on an input data  
15 from the data processing unit 2001 in accordance with a coding and modulation method that has been set by the controller 2001, generates a data symbol stream, and provides the data symbol stream to the spatial signal processing unit 2012. Furthermore, at the time of  
20 reception, the modulator/demodulator 2011 performs processing, such as demodulation, deinterleaving, or decoding, that is inverse to processing at the time of transmission on an input from the spatial signal processing unit 2012 in accordance with a coding and  
25 modulation method set by the controller 2001, and provides data to the data processing unit 2001 or the controller 2002.

[0098]

At the time of transmission, the spatial signal  
30 processing unit 2012 performs signal processing provided for spatial separation on an input from the

modulator/demodulator 2011 as needed, and provides one or more obtained transmission symbol streams to respective wireless interfaces 2014. On the other hand, at the time of reception, the spatial signal processing unit 2012  
5 performs signal processing on reception symbol streams that have been input from the respective wireless interfaces 2014, spatially resolves the streams as needed, and provides the streams to the modulator/demodulator 2011.

10 [0099]

The channel estimator 2013 calculates complex channel gain information of a propagation path from preamble portions and training signal portions of input signals from the respective wireless interfaces 2014.

15 Then, the calculated complex channel gain information is used in demodulation processing of the modulator/demodulator 2011 and spatial processing of the spatial signal processing unit 2012 via the controller 2002, so that spatial multiplex communication such as  
20 MIMO can be performed.

[0100]

At the time of transmission, the wireless interface 2014 converts an input from the spatial signal processing unit 2012 into an analog signal, performs filtering and  
25 up-conversion to a carrier frequency, and sends out the analog signal to the antenna 2016 or the amplifier 2015. On the other hand, at the time of reception, the wireless interface 2014 performs processing, such as down-conversion or conversion into a digital signal, that is  
30 inverse to processing at the time of transmission on an input (a received signal having the carrier frequency)

from the antenna 2016 or the amplifier 2015, and provides data to the spatial signal processing unit 2012 and the channel estimator 2013.

[0101]

5           In a case where the communication apparatus 2000 operates as a STA in Example 1, the wireless interface 2014 includes a bank of MA filters to measure an RSSI of an OBSS signal and obtain a moving average of the RSSI.

[0102]

10           At the time of transmission, the amplifier 2015 amplifies the analog signal that has been input from the wireless interface 2014 to a prescribed power, and sends out the analog signal to the antenna 2016. Furthermore, at the time of reception, the amplifier 2015 performs  
15 low-noise amplification on a received signal that has been input from the antenna 2016 to a prescribed power, and outputs the received signal to the wireless interface 2014. At least one of a function at the time of transmission or a function at the time of reception of  
20 the amplifier 2015 that is described above is included in the wireless interface 2014 in some cases.

[0103]

          In a case where the communication apparatus 2000 operates as an AP in Example 2, the antenna 2016 is a  
25 directional antenna, and the wireless interface 2014 measures AoA's of signals that arrive from STAs under control and OBSS's. Furthermore, the wireless interface 2014 includes a bank of MA filters to obtain a moving average of the AoA's.

30 [0104]

          The power source 2004 includes a battery power

source or a fixed power source such as a commercial power source, and supplies power for driving to each of the units in the communication apparatus 2000.

[0105]

5           Note that the communication apparatus 2000 can further include a function module other than illustrated units. However, this is not directly associated with the technology disclosed herein, and illustration and a description are omitted here.

10   [0106]

          According to the technology disclosed herein, the following effects are expected.

[0107]

          (1) STAs can report, to an AP, reception power  
15   measurement results from an OBSS, and the AP can perform a communication operation based on OBSS-PD by using these pieces of information, and can perform SR transmission to a STA having the smallest interference with the OBSS. Alternatively, the AP can perform a communication  
20   operation based on OBSS-PD by using information obtained by performing clustering processing on STAs under control and an OBSS on the basis of AoA's, and can transmit a signal to a STA that is estimated to belong to a cluster on an opposite side of a cluster of the OBSS and to be  
25   located apart from the OBSS. In brief, the AP can simply determine a STA that is unlikely to receive interference from the OBSS, and can increase an opportunity to perform transmission to a STA.

[0108]

30           (2) The communication operation in (1) described above results in improvements in a spatial reuse rate

based on OBSS-PD. Furthermore, the AP transmits a signal to a STA having the smallest interference with the OBSS, and this also results in improvements in a success rate of transmission.

5 [0109]

(3) The AP can acquire more transmission opportunities, and this principally results in improvements in a downlink throughput in a wireless LAN system.

10 [0110]

(4) The AP can obtain information required to realize downlink SR transmission based on OBSS-PD by exchanging minimum information with STAs under control (for example, by transmitting a measurement request frame and receiving a measurement report frame) or by performing minimum measurement (for example, the measurement of an AoA), and this results in a small overhead.

20 INDUSTRIAL APPLICABILITY

[0111]

The technology disclosed herein has been described above in detail with reference to specified embodiments. However, it is obvious that those skilled in the art could make modifications or substitutions to the  
25 embodiments without departing from the gist of the technology disclosed herein.

[0112]

The technology disclosed herein is suitably  
30 applicable to, for example, a wireless LAN system that conforms to the IEEE 802.11ax standard, but an

application range of the technology disclosed herein is not limited to this. The technology disclosed herein is applicable to various network systems such as a wireless LAN system in which an AP performs downlink signal

5 transmission to a STA while permitting interference or a wireless LAN system in which a terminal station (regardless of whether or not it is an AP or a STA) performs one-to-one signal transmission while permitting interference.

10 [0113]

In brief, the technology disclosed herein has been described in the form of an example, and the content described herein is not to be construed to be restrictive. In order to determine the gist of the technology  
15 disclosed herein, the claims should be considered.  
[0114]

Note that the technology disclosed herein can also employ the configuration described below.

(1) A communication apparatus including:

20 a communication unit that transmits or receives a signal;

an information obtaining unit that obtains information relating to interference that each transmission destination candidate receives from an  
25 interference source; and

a controller that selects each of the transmission destination candidates on the basis of the information when an interference signal arrives.

(2) The communication apparatus described in (1)  
30 described above,

in which the controller identifies whether or not

the interference signal has arrived from an OBSS on the basis of BSS identification information described in a PHY header of a received frame.

(3) The communication apparatus described in (2)  
5 described above,

in which the BSS identification information includes a BSS Color defined by IEEE 802.11.

(4) The communication apparatus described in any of  
(1) to (3) described above,

10 in which the communication apparatus operates as an access point, and

the information obtaining unit obtains the information relating to respective terminal stations serving as each of the transmission destination  
15 candidates in a local BSS and interference received from an OBSS serving as the interference source.

(5) The communication apparatus described in (4) described above,

in which when a reception power of an OBSS signal  
20 serving as the interference signal is less than or equal to a prescribed threshold, the controller selects one of the respective terminal stations in the local BSS on the basis of the information, and causes the signal to be transmitted.

25 (6) The communication apparatus described in any of (1) to (5) described above,

in which the controller selects a transmission destination candidate that the information indicates that is located farthest from the interference source that  
30 corresponds to the interference signal or is not located closest to the interference source.

(7) The communication apparatus described in any of (1) to (5) described above,

in which the information obtaining unit obtains the information relating to an intensity of a received signal  
5 from the interference source of each of the transmission destination candidates, and

the controller selects each of the transmission destination candidates on the basis of the intensity of the received signal from the interference source that  
10 corresponds to the interference signal.

(8) The communication apparatus described in (7) described above,

in which the controller selects a transmission destination candidate that the information indicates that  
15 has a lowest intensity of the received signal from the interference source that corresponds to the interference signal or does not have a highest intensity of the received signal from the interference source.

(9) The communication apparatus described in any of  
20 (7) and (8) described above,

in which the information obtaining unit obtains the information on the basis of a report relating to the intensity of the received signal from the interference source, the report being transmitted from each of the  
25 transmission destination candidates.

(10) The communication apparatus described in any of (7) to (9) described above,

in which the information obtaining unit obtains the information on the basis of a report relating to a  
30 measurement result of the intensity of the received signal from the interference source, the report being

transmitted by each of the transmission destination candidates in response to a measurement request from a local station.

(11) The communication apparatus described in any  
5 of (7) to (10) described above,

in which the communication apparatus operates as an access point,

the information obtaining unit obtains the information relating to the intensity of the received  
10 signal of an OBSS signal in each terminal station serving as each of the transmission destination candidates in a local BSS, and

the controller manages the information of each of the terminal stations in association with BSS  
15 identification information of an OBSS.

(12) The communication apparatus described in (11) described above,

in which the information obtaining unit obtains, from each of the terminal stations, the information  
20 including the BSS identification information that indicates at least one of an OBSS having a maximum intensity of the received signal or an OBSS having a minimum intensity of the received signal.

(13) The communication apparatus described in any  
25 of (1) to (11) described above,

in which the information obtaining unit obtains the information relating to an angle of arrival of each of the transmission destination candidates and the interference source, and

30 the controller selects each of the transmission destination candidates on the basis of a relationship of

the angle of arrival between the interference source that corresponds to the interference signal and each of the transmission destination candidates.

(14) The communication apparatus described in (13)  
5 described above,

in which the controller selects a transmission destination candidate that the information indicates that is most different in the angle of arrival from the interference source that corresponds to the interference  
10 signal or is not most similar in the angle of arrival to the interference source.

(15) The communication apparatus described in any of (13) and (14) described above,

in which the communication unit includes a  
15 directional antenna, and

the information obtaining unit obtains the information relating to the angle of arrival on the basis of a result of receiving signals from each of the transmission destination candidates and the interference  
20 source by using the directional antenna.

(16) The communication apparatus described in any of (13) to (15) described above,

in which the communication apparatus operates as an access point,

25 the information obtaining unit obtains the information relating to the angle of arrival of terminal stations serving as each of the transmission destination candidates in a local BSS and OBSS's, and

the controller groups terminal stations and an OBSS  
30 that are similar in the angle of arrival into a cluster, and manages respective clusters in association with the

BSS identification information of each of the OBSS's.

(17) A communication method including:

an information obtaining step of obtaining  
information relating to interference that each

5 transmission destination candidate receives from an  
interference source; and

a controlling step of selecting each of the  
transmission destination candidates on the basis of the  
information when an interference signal arrives.

10 (18) A communication apparatus that operates under  
a control of an access point, the communication apparatus  
including:

a controller that performs control to transmit, to  
the access point, information relating to an intensity of  
15 a received signal of an OBSS signal.

(18-1) The communication apparatus described in  
(18) described above, further including:

a measuring unit that identifies the OBSS signal on  
the basis of BSS identification information described in  
20 a PHY header of a received frame, and measures an  
intensity of a received signal of the OBSS signal.

(19) The communication apparatus described in (18)  
described above,

in which the controller performs control to  
25 transmit, to the access point, the information that  
associates the intensity of the received signal of the  
OBSS signal with BSS identification information of an  
OBSS.

(20) The communication apparatus described in any  
30 of (18) and (19) described above,

in which the controller performs control to

transmit, to the access point, the information including the BSS identification information that indicates at least one of an OBSS having a maximum intensity of the received signal or an OBSS having a minimum intensity of the received signal.

(21) The communication apparatus described in any of (18) to (20) described above,

in which the controller causes a report frame to be transmitted to the access point in response to a request frame from the access point, the report frame including the information.

(22) A communication method in a communication apparatus that operates under a control of an access point, the communication method including:

a controlling step of performing control to transmit, to the access point, information relating to an intensity of a received signal of an OBSS signal.

#### REFERENCE SIGNS LIST

[0115]

|                          |                           |
|--------------------------|---------------------------|
| 100                      | Wireless LAN system       |
| 101                      | BSS                       |
| 102                      | OBSS                      |
| 300                      | Wireless LAN system       |
| 501                      | BSS Color detector        |
| 502-1, 502-2, ..., 502-N | MA filter                 |
| 503                      | OBSS RSSI table           |
| 504                      | Rearrangement/search unit |
| 1600                     | Wireless LAN system       |
| 2000                     | Communication apparatus   |
| 2001                     | Data processing unit      |

- 2002 Controller
- 2003 Communication unit
- 2004 Power source
- 2011 Modulator/demodulator
- 5 512 Spatial signal processing unit
- 2013 Channel estimator
- 2014 Wireless interface
- 2015 Amplifier
- 2016 Antenna

## CLAIMS

1. A communication apparatus comprising:  
a communication unit that transmits or receives a  
5 signal;  
an information obtaining unit that obtains  
information relating to interference that each  
transmission destination candidate receives from an  
interference source; and  
10 a controller that selects each of the transmission  
destination candidates on a basis of the information when  
an interference signal arrives.
2. The communication apparatus according to claim 1,  
15 wherein the controller identifies whether or not  
the interference signal has arrived from an overlapping  
basic service set (OBSS) on a basis of basic service set  
(BSS) identification information described in a PHY  
header of a received frame.  
20
3. The communication apparatus according to claim 2,  
wherein the BSS identification information includes  
a BSS Color defined by IEEE 802.11.
- 25 4. The communication apparatus according to claim 1,  
wherein the communication apparatus operates as an  
access point, and  
the information obtaining unit obtains the  
information relating to respective terminal stations  
30 serving as each of the transmission destination  
candidates in a local BSS and interference received from

an OBSS serving as the interference source.

5. The communication apparatus according to claim 4,  
wherein when a reception power of an OBSS signal  
5 serving as the interference signal is less than or equal  
to a prescribed threshold, the controller selects one of  
the respective terminal stations in the local BSS on a  
basis of the information, and causes the signal to be  
transmitted.

10

6. The communication apparatus according to claim 1,  
wherein the controller selects a transmission  
destination candidate that the information indicates that  
is located farthest from the interference source that  
15 corresponds to the interference signal or is not located  
closest to the interference source.

7. The communication apparatus according to claim 1,  
wherein the information obtaining unit obtains the  
20 information relating to an intensity of a received signal  
from the interference source of each of the transmission  
destination candidates, and

the controller selects each of the transmission  
destination candidates on a basis of the intensity of the  
25 received signal from the interference source that  
corresponds to the interference signal.

8. The communication apparatus according to claim 7,  
wherein the controller selects a transmission  
30 destination candidate that the information indicates that  
has a lowest intensity of the received signal from the

interference source that corresponds to the interference signal or does not have a highest intensity of the received signal from the interference source.

5     9.     The communication apparatus according to claim 7,  
          wherein the information obtaining unit obtains the  
          information on a basis of a report relating to the  
          intensity of the received signal from the interference  
          source, the report being transmitted from each of the  
10    transmission destination candidates.

          10.    The communication apparatus according to claim 7,  
          wherein the information obtaining unit obtains the  
          information on a basis of a report relating to a  
15    measurement result of the intensity of the received  
          signal from the interference source, the report being  
          transmitted by each of the transmission destination  
          candidates in response to a measurement request from a  
          local station.

20                   11.    The communication apparatus according to claim 7,  
          wherein the communication apparatus operates as an  
          access point,  
          the information obtaining unit obtains the  
25    information relating to the intensity of the received  
          signal of an OBSS signal in each terminal station serving  
          as each of the transmission destination candidates in a  
          local BSS, and  
          the controller manages the information of each of  
30    the terminal stations in association with BSS  
          identification information of an OBSS.

12. The communication apparatus according to claim 11,  
wherein the information obtaining unit obtains,  
from each of the terminal stations, the information  
5 including the BSS identification information that  
indicates at least one of an OBSS having a maximum  
intensity of the received signal or an OBSS having a  
minimum intensity of the received signal.

10 13. The communication apparatus according to claim 1,  
wherein the information obtaining unit obtains the  
information relating to an angle of arrival of each of  
the transmission destination candidates and the  
interference source, and  
15 the controller selects each of the transmission  
destination candidates on a basis of a relationship of  
the angle of arrival between the interference source that  
corresponds to the interference signal and each of the  
transmission destination candidates.

20 14. The communication apparatus according to claim 13,  
wherein the controller selects a transmission  
destination candidate that the information indicates that  
is most different in the angle of arrival from the  
25 interference source that corresponds to the interference  
signal or is not most similar in the angle of arrival to  
the interference source.

15. The communication apparatus according to claim 13,  
30 wherein the communication unit includes a  
directional antenna, and

the information obtaining unit obtains the information relating to the angle of arrival on a basis of a result of receiving signals from each of the transmission destination candidates and the interference  
5 source by using the directional antenna.

16. The communication apparatus according to claim 13,  
wherein the communication apparatus operates as an access point,

10 the information obtaining unit obtains the information relating to the angle of arrival of terminal stations serving as each of the transmission destination candidates in a local BSS and OBSS's, and

the controller groups terminal stations and an OBSS  
15 that are similar in the angle of arrival into a cluster, and manages respective clusters in association with BSS identification information of each of the OBSS's.

17. A communication method comprising:  
20 an information obtaining step of obtaining information relating to interference that each transmission destination candidate receives from an interference source; and

a controlling step of selecting each of the  
25 transmission destination candidates on a basis of the information when an interference signal arrives.

18. A communication apparatus that operates under a control of an access point, the communication apparatus  
30 comprising:

a controller that performs control to transmit, to

the access point, information relating to an intensity of a received signal of an OBSS signal.

19. The communication apparatus according to claim 18,  
5 wherein the controller performs control to transmit, to the access point, the information that associates the intensity of the received signal of the OBSS signal with BSS identification information of an OBSS.

10 20. The communication apparatus according to claim 18, wherein the controller performs control to transmit, to the access point, the information including BSS identification information that indicates at least one of an OBSS having a maximum intensity of the received signal  
15 or an OBSS having a minimum intensity of the received signal.

21. The communication apparatus according to claim 18,  
wherein the controller causes a report frame to be  
20 transmitted to the access point in response to a request frame from the access point, the report frame including the information.