

Description

Technical Field

The present invention relates to touch buttons typically used to activate or deactivate some electrical or electronic function, such as signaling, when touched typically by a human operator touching or "pushing" on the button with a finger. The invention more particularly relates to a light ring containing a circular array of light emitting diodes (LEDs) for a solid state touch button system operated, for example, by capacitive sensing, and even more particularly to such a button which can be used in many different applications, including particularly a touch or push button for elevator car calling or control, with the light ring providing visual feedback to the operator that the button has been actuated.

Background Art

In the elevator art it is common to provide "up" and "down" touch or push buttons at the entry areas to the elevators and to include similar buttons within the elevators for the passenger(s) to indicate at which floor(s) the elevator car should stop.

It is also common practice to include with such buttons an encircling light ring, which is illuminated when the button has been actuated as a visual feedback to the operator. Typically, such rings received light from incandescent bulbs.

Some elevator related, U.S. patents which may be of interest are listed below:

Patent No.	Patentee(s)	Issue Date
4,650,037	Hussen <i>et al</i>	March 17, 1987
4,716,992	Kunii	Jan. 5, 1988
4,805,739	Lind <i>et al</i>	Feb. 21, 1989

The '739 patent (Lind *et al*) discloses an elevator control switch and position indicator assembly for mounting in a panel comprising a piezoelectric element and a control circuit connected to the element for generating an elevator control pulse in response to an output signal from the element. A circular push button assembly is arranged such that, when the push button is operated, a force is applied to the piezoelectric element, and the push button assembly is restrained so that it can only deflect the element a predetermined distance sufficient to produce an output signal. The assembly further comprises an integral indicator device for providing an indication to the operator that an elevator control signal has been generated. The device is indicated as being configurable to provide an indication of the position of an elevator car.

In the first embodiment (Fig. 1) of the Lind *et al* patent, the light from a single, centrally located, long-life LED (44) with multiple elements for increased luminous intensity, in place of the short lived bulb of the prior art, is fed through a lens guide (16), forming a generally annular cross-section lens for guiding light to an externally disposed lens ring (42), to form a halo effect. The ring is illustrated as being integrally formed with the lens guide, which can be made of optical grade polycarbonate. Although the surfaces facing the LED are not described, they are illustrated as appearing primarily, if not completely, laterally extended, with the nature of the facing surface not being clearly illustrated, with two laterally extended, parallel lines appearing in the drawing (Fig. 1).

In a second embodiment (Fig. 6) of the Lind *et al* patent a separately actuated LED (74) without any light pipe is positioned above the other LED and its lens guide to separately illuminate a centrally located, translucent graphic disk (76) positioned directly over it (in place of the operator button) to serve as an elevator car position indicator.

There is no admission that the '739 patent, which was filed on January 14, 1988, is prior art to the present invention. However, assuming *arguendo* that it were, it does not teach, *inter alia*, an annular, circular array of a multiple number of LEDs beyond a circular bottom surface, feeding the light rays from the multiple LEDs to the button surrounding light ring, producing a highly diffused, bright halo, with a relatively even luminosity, much less any of the many other innovative features of the present invention.

The '037 patent (Husson *et al*) discloses the use of separated, independent LEDs in a controller apparatus for detecting lamp failures in an elevator system, an application not at all analogous to a touch or push button with a surrounding light ring.

The '992 patent (Kunii) discloses the use of "light emitting means" (14) to illuminate indication marks on an elevator panel. Exactly what the "light emitting means" is, is not clear. But again, regardless of the nature of the "light emitting means," there is no suggestion of, *inter alia*, an annular, circular array of a multiple number of LEDs above a circular surface feeding the light rays from the multiple LEDs to the button surrounding light ring, producing a highly diffused, bright halo, with a relatively even luminosity, much less any of the many other innovative features of the present invention.

Disclosure of Invention

The light ring of the invention preferably includes an annular, transparent or translucent, light pipe section having an open center at its end which faces the exterior (such as, for example, the hall or car, as the case may be, when used in an elevator system), and a restricted, basal end, which is hidden in the wall behind the button touch surface. A plurality of LEDs are mounted inside the basal end of the light ring in an annular, circular array, and, preferably, an alternating series of saw-toothed or grooved annulus of light dispersing, internal, triangular interfaces or light receiving surfaces is disposed between the LEDs and the ring end of the rim.

In this way light is evenly piped to the open end of the ring, in which the button disc element is located, to form a bright, even halo around the button disc element to serve, for example, as a visual feedback to the button pusher that the button has been activated.

Various, other innovative features preferably are included to, *inter alia*, insure the proper alignment and keying of the sub-elements which make up the light ring, including a printed circuit board (PCB) base, which carries the LEDs and some of its associated circuitry, and the molded light transmitting body of the light ring.

The invention may be practiced in a wide variety of applications, including but certainly not restricted to elevator car call or control buttons, utilizing known technology, in the light of the teachings of the invention, which are discussed in detail hereafter.

Other features and advantages will be apparent from the specification and claims and from the accompanying drawings, which illustrate at least one exemplary embodiment of the invention.

Brief Description of Drawings

Figure 1 is an exploded, perspective view of an exemplary solid state push button assembly, including the button, light ring, printed circuit (PC) board and holder for attaching the PC board to the push button elements and the overall button assembly to a face plate or panel, with the PC board carrying the electrical components which form the exemplary electronics and circuitry of the present invention. (It is noted that the touch button elements of Figure 1 are basically symmetrical about their longitudinal center-line, except for the PC board and its associated holder.)

Figures 2A, 2B & 2C are top, side/cross-sectional and bottom views, respectively, of the light ring element of the button assembly of Figure 1.

Figure 3 is a partial, side view showing the bottom portion of the light ring element of Figs. 2A-2C.

Figure 4 is a top view of the LED base element of the light ring element of Figs. 2A-2C; while Figure 5 is a side view thereof, and Figure 6 is a further side view with the base rotated ninety (90°) from its position in Fig. 5.

Figure 7 is a schematic diagram of the LED circuitry of the light ring element of Figs. 2A-2C.

Figure 8 is a cross-sectional view of the light ring element of Figs. 2A-2C (taken along section line 8-8 of Figure 2B) looking up into the triangularly topped cavities in the light ring element in which the LEDs are positioned, and which cause the light emanating from the LEDs to be disbursed up into and through the transparent material of the upper portion of the light ring element to be transmitted out of the surrounding ring portion of the element to be viewed by, for example, the button pusher.

Best Mode for Carrying Out the Invention

- BUTTON ASSEMBLY (10) -

As can be seen in Figure 1, the exemplary "solid state button" (SSB) assembly 10 of the present invention preferably includes a non-moving, capacitive sensing button surface 1, that can be used, for example, as a call button in the car operating panel (COP) and/or hall fixtures of an elevator system. The SSB is capable of capacitively sensing a human touch, preferably providing both visual feed back

(illumination) to the button pusher, as well as communication to the operational control of the elevator system via a remote station (RS; not illustrated) interface that the button has been actuated, so that the system accordingly can react.

The exemplary button system of Figure 1 includes the non-moving button element 1 fitted within a light ring element 2, in which ring is carried a circular array of light emitting diodes (LEDs) 3 at its bottom, there being preferably at least five (5) LEDs, with nine being used in the illustrated, exemplary, currently preferred embodiment.

A printed circuit board 4, into which the light ring element 2 is pin inserted, is carried on the back side of the button elements 1, 2, and is held to the button elements by a bracket 5 and a rear bolt 6 having a bolt head 6B. As can be generally visualized in Figure 1, the bolt head 6B extends past the bottoms of all of the other button elements of the button assembly 10.

An interconnecting bolt or stem 7 has a front, threaded, male end 7A, which is screwed into the back side of the button surface 1, and a rear, threaded, male end 7B, which is screwed into the front end 6A of the rear bolt 6 with a lock washer 7C. The interconnecting bolt 7 extends through a center, generally circular opening 20 (which can be seen in Figures 2A-2C and 4 & 8) in the light ring element 2 and through an opening in the PC board 4, while the head 6B of the rear bolt 6 fits into a notch in a "U" shaped rear strap 8, which is part of the bracket holder 5. The bolt or stem 7 has a series of longitudinally extended, flat, side surfaces 7C, forming a hexagonal cross-section for the stem which mates with a like configured, interior surface 21, which forms the lower part of the central opening 20.

When assembled, the intermediate elements of the button assembly 10 are held in compression between the button surface 1 and the head 6B of the bolt 6. The flat surface interfacing of the stem 7 and the interior opening 21 fixes and keys them together about their common, longitudinal axis, thus preventing the light ring 2 from being rotatable or movable around the stem about their common, longitudinal axis.

The bracket 5 includes a series of peripherally spaced, lateral extensions or arms 9, through which threaded screw pins 9B are placed for fastening the button assembly 10 to a face plate or panel by means of like threaded female orifices in the face plate or panel. When so fastened, the only elements of the button assembly 10 which are seen by the user is the non-moving, circular button surface 1 surrounded by the translucent ring 2A, which is illuminated with relatively bright, relatively evenly diffused light originally emanating from the internally contained LEDs when the button is actuated. Alternatively, if so desired and depending on the application involved, the top ring portion 2A could be illuminated by its associated circuitry when the button is in its "off" condition.

The printed circuit board 4 carries on it the electronic components and associated circuitry which perform the monitoring functions of the button. The circuitry/push button assembly preferably is an autobalancing or a constant pressure arrangement.

- LIGHT RING (2) -

As will be detailed more fully below, the substantially cylindrical body of the light ring 2 includes a top ring portion 2A of light emitting material encircling the button surface element 1, an upper portion 27 of light transmitting material, and a bottom portion, which is (but need not be) of light transmitting material. The bottom portion includes a base 23 carrying an array of LEDs 3.

The illumination of the light ring 2 is controlled by the button surface 1 through appropriate circuitry, as discussed in some detail in the co-pending application (OT-791). The source of the illumination is comprised, for example, of two strings of LEDs 3 located at the bottom of the light ring 2 and are fed preferably by dedicated current regulators through pin connectors J2 and J3 (note Figs. 2C & 7), which pin connectors are inserted into connector openings in the printed circuit board (PCB) 4. The current through each string of LEDs 3 is regulated to, for example, thirty (30mA) milliamps, by appropriately controlling the voltage. Compensating resistors 35 can be included with the LEDs 3, if so desired.

As can be seen in Figures 4-7, an exemplary nine LEDs 3 are included, preferably equally spaced about the periphery of the bottom base area 22 of the light ring 2, forming an annular array.

As can be seen in Figure 2C, the connecting pins for the nine (1-9) LEDs 3 all fall on the periphery of a circle about the longitudinal center line (C.L.; note Fig. 2B) of the light ring 2, except for the initial, first (1) and second (2) LEDs in each string (note schematic of Fig. 7) and the sixth (6) one, which is oppositely positioned to the positions of the first and second ones. The two pin connections or leads for each of these three LEDs are preferably positioned in a line parallel to a lateral line LL bisecting the base 23.

The base 23, which is substantially circular in its lateral extent, is a printed circuit board (PCB), which includes printed, conductive lead lines interconnecting the LEDs 3 in two parallel strings, along with two associated, compensating resistors 35, if such is needed or desired, in accordance with the circuitry

schematic of Figure 7.

As can be seen in Figure 8, each LED 3 "looks up" into the center of an triangulated chamber 24, with each individual chamber preferably being made up of three, inclined, triangular surfaces sharing a common apex 25, which is located at the outermost point of the central triangular surface and is at the outermost periphery of the inside of the light ring 2. Each of the three triangular surfaces of each chamber 24 includes a series of molded-in straight edges 26, each of which extends across its respective surface leading up to their common apex in a stepped fashion.

Each of these chambers 24 serves as the light receiving surfaces for its respective LED 3, channeling the light in a highly diffused manner into and through the light-pipe-like, solid interior of the upper portion 27 of the light ring 2 leading to the encircling, top, light ring portion 2A, through which the light from the light ring 2 is seen by the button user. The series of straight edges or steps function as Fresnel-like grooving on the underside of the upper interior of the light ring 2.

The interior side 20A (note Figs. 8 & 2B) of the surface 20 preferably is frosted, which frosted surface 20A, as can be seen in Figure 8, is convex and terminates in the base side of the central one of the three triangulated surfaces forming the chambers 24. As can be further seen, one of the triangulated surfaces of each chamber 24 is positioned between the other two, sharing common sides with them, while the saw-toothed grooves or Fresnel-like edges 26 are disposed parallel to their respective bases of the triangulated surfaces.

As can best be seen in Figure 2B, the upper, central, conical, circular area or centrally facing, exterior surface 20 is sloped at an angle of, for example, sixty (60°) degrees, that is, at an angle of thirty (30°) degrees to the center line C.L. This is done in order to provide diffusion reflection in the solid, light transmitting interior 27 and thus minimize the loss of any light from the solid interior of the ring 2 into the open, center area defined by the interior, center side of the conical surface 20, where the light effectively would be lost or wasted.

This overall arrangement produces a relatively uniform intensity of light at and about the outer, encircling ring 2A, although the light ultimately seen there originated in fact from the relatively discrete, spaced, light sources generated by the nine, peripherally spaced LEDs 3. The light ring 2, and in particular the upper, solid, light "pipe" portion 27, can be made of a single, integral, molded piece of transparent "LEXAN™" (940 AR), with the exception of the PCB base 23 and its associated electrical components.

Although the illustrated (as described above and below) overall arrangement is currently preferred, it is of course subject to substantial variations, with many of the factors producing the desired light diffusion being interdependent, as known to those of ordinary skill in the optics art.

In order to properly align the molded body portion of the light ring 2 and the PCB base 23 with its LEDs 3, the molded body includes two, longitudinally extended, peripherally positioned but off-set, integrally molded pins or projections 28, which mate into circular indentations or cut-outs 29 similarly located in the periphery of the base, keying the two sub-elements together. The base 23 also includes two, opposed, radially directed projections 30, which fit into openings 31 (note Fig. 3) in flexible longitudinal extensions 32 in the molded body portion of the ring 2.

The pins 28 (and accordingly the indentations 29) preferably are offset, rather than being directly opposed, by being peripherally spaced from one another by an angle of, for example, one hundred and sixty (160°) degrees (vis-a-vis 180°). This insures that there is only one way or one mating alignment in which the base 23 can be positioned with respect to the ring body.

When the base 23 and the body of the ring 2 are properly aligned with the pins 28 in the indentations 29 and then brought together in a longitudinal direction, the extensions 32 flex out, allowing the radially directed projections to snap into the openings 31, latching the two sub-elements together. When it is desired to separate the two sub-elements, the extensions 32 are merely pulled laterally out, allowing the base 23 and its electrical components to be removed down and out away from the ring body.

When assembled, the pin connectors J2 & J3 are inserted into their respective mating openings in the PCB 4 to be connected into the circuit for the button assembly 10. Peripheral, longitudinally extended portions or bosses 34 are included to support the bottom of the ring 2 on the PCB 4 and prevent any rocking of the ring 2 about the bottom surfaces of the headers of the pin connectors J2 & J3.

If desired and as illustrated, two, vertically or longitudinally disposed resistors 35 could be included on and carried by the PCB base 23, along with their associated LEDs 3 (note Figs. 5 & 6). These resistors 35 are connected into the circuitry of the base, as shown in the schematic of Figure 7, by appropriately placed, printed circuit board lead lines on the base.

A rectangular "label" area 33 (note Fig. 3) can be provided on the lower side of the ring molded body to identify or serialize the ring 2, if so desired.

Approximate, exemplary dimensions for the light ring 2 are outlined below:

Part	Dimension
Diameter of top ring portion 2A	1"
Longitudinal length of body of light ring 2	1.1"
Longitudinal length of cylindrical, interior part of upper part 27	0.25"
Longitudinal length of inclined, conical part 20	0.5"
Longitudinal length of hex. area 21	1.5"
Lateral width of hex. area 21	0.25"

- EXEMPLARY ELEVATOR APPLICATIONS -

The exemplary solid state button assembly 10 described in detail above is designed to be applied in a hall fixture and/or car operating panel (COP) of an elevator, although, of course, many other uses and applications are possible.

The hall fixture application allows for two button assemblies (not illustrated), a beeper or key switch assembly and an RS-4 type board to fit into a commercially available masonry box. The masonry box (not illustrated) used should provide a shallow wall depth for the entire assembly. A shallow wall depth [for example, sixty-five (65 mm) millimeters] avoids penetrating the hoist-way fire barrier in common commercial construction.

The face plates can be made of, for example, die cast metal and be available in various finishes. Also one, two or three (1, 2 or 3) position combinations of buttons or key switches can be used. A tamper proof fastener (not illustrated) preferably is used to fasten the face plate to the masonry box.

The COP application allows for multiple buttons to be mounted in a panel and connected to a Remote Serial Extender Board (not illustrated).

In hall fixture applications the face plate should be connected to the masonry box with, for example, an insulated flat braided conductor (not illustrated), having, for example, a maximum length of eighteen (18 cm.) centimeters. The masonry box should be bonded to building steel through wiring conduit or a flat braided conductor to the closest building steel.

A chassis ground is applied on the button from the face plate (hall fixture) or return panel (COP). In hall fixture applications the face plate should be grounded to the fixture electrical box, while the electrical box should be bonded to building steel through the wiring conduit.

The only product variations needed for the exemplary applications are the two colors of light rings, namely, red and green, and the application of the button to a hall fixture and a COP.

The exemplary unit described above is a relatively low cost, easily replaceable device, taking, for example, five (5) minutes to replace.

Having thus described at least one exemplary embodiment of the invention, that which is new and desired to be secured by Letters Patent is claimed below.

Claims

1. An illuminated touch button system for activating or deactivating an electrically controlled function, having a light ring (2A) surrounding the touch button surface for illuminating the button (1), comprising:

a light ring element having a top ring portion (2A) of light transmitting material, an upper portion (27) having a solid interior of light transmitting material, and a bottom portion;

a button element (1) located within said light ring element (2) and being surrounded by its light transmitting top ring portion; and

an array of peripherally spaced, light emitting diodes (LEDs) (3) located at said bottom portion (23), said upper portion of light transmitting material transmitting light from the LEDs (3) to said top ring portion (2) to be viewed by a button pusher indicating the "on"/"off" condition of the button (1).

2. The touch button system of Claim 1, wherein:

said upper portion of light transmitting material has a light receiving underside (24) facing said array of LEDs (3) receiving some of the light from said LEDs when the LEDs are turned on, said underside including a series of spaced, Fresnel-like edges (26).



Part	Dimension
Diameter of top ring portion 2A	1"
Longitudinal length of body of light ring 2	1.1"
Longitudinal length of cylindrical, interior part of upper part 27	0.25"
Longitudinal length of inclined, conical part 20	0.5"
Longitudinal length of hex. area 21	1.5"
Lateral width of hex. area 21	0.25"

- EXEMPLARY ELEVATOR APPLICATIONS -

The exemplary solid state button assembly 10 described in detail above is designed to be applied in a hall fixture and/or car operating panel (COP) of an elevator, although, of course, many other uses and applications are possible.

The hall fixture application allows for two button assemblies (not illustrated), a beeper or key switch assembly and an RS-4 type board to fit into a commercially available masonry box. The masonry box (not illustrated) used should provide a shallow wall depth for the entire assembly. A shallow wall depth [for example, sixty-five (65 mm) millimeters] avoids penetrating the hoist-way fire barrier in common commercial construction.

The face plates can be made of, for example, die cast metal and be available in various finishes. Also one, two or three (1, 2 or 3) position combinations of buttons or key switches can be used. A tamper proof fastener (not illustrated) preferably is used to fasten the face plate to the masonry box.

The COP application allows for multiple buttons to be mounted in a panel and connected to a Remote Serial Extender Board (not illustrated).

In hall fixture applications the face plate should be connected to the masonry box with, for example, an insulated flat braided conductor (not illustrated), having, for example, a maximum length of eighteen (18 cm.) centimeters. The masonry box should be bonded to building steel through wiring conduit or a flat braided conductor to the closest building steel.

A chassis ground is applied on the button from the face plate (hall fixture) or return panel (COP). In hall fixture applications the face plate should be grounded to the fixture electrical box, while the electrical box should be bonded to building steel through the wiring conduit.

The only product variations needed for the exemplary applications are the two colors of light rings, namely, red and green, and the application of the button to a hall fixture and a COP.

The exemplary unit described above is a relatively low cost, easily replaceable device, taking, for example, five (5) minutes to replace.

Having thus described at least one exemplary embodiment of the invention, that which is new and desired to be secured by Letters Patent is claimed below.

Claims

1. An illuminated touch button system for activating or deactivating an electrically controlled function, having a light ring (2A) surrounding the touch button surface for illuminating the button (1), comprising:

a light ring element having a top ring portion (2A) of light transmitting material, an upper portion (27) having a solid interior of light transmitting material, and a bottom portion;

a button element (1) located within said light ring element (2) and being surrounded by its light transmitting top ring portion; and

an array of peripherally spaced, light emitting diodes (LEDs) (3) located at said bottom portion (23), said upper portion of light transmitting material transmitting light from the LEDs (3) to said top ring portion (2) to be viewed by a button pusher indicating the "on"/"off" condition of the button (1).

2. The touch button system of Claim 1, wherein:

said upper portion of light transmitting material has a light receiving underside (24) facing said array of LEDs (3) receiving some of the light from said LEDs when the LEDs are turned on, said underside including a series of spaced, Fresnel-like edges (26).



3. The touch button system of Claim 1, wherein:
said upper portion of light transmitting material has a light receiving underside (24) facing said array of LEDs (3) receiving some of the light from said LEDs, said underside including a series of individual chambers (24) spaced about the periphery of said underside, with each LED (3) located below one of said chambers, transmitting its light to said chamber (24) when it is turned on.
4. The touch button system of Claim 3, wherein:
each of said chambers (24) includes an inclined surface facing its respective LED (3) receiving light from its respective LED into the solid interior of said upper portion.
5. The touch button system of Claim 4, wherein:
each of said inclined surfaces having a series of spaced, Fresnel-like edges (26) facing toward its respective LED.
6. The touch button system of Claim 3, wherein:
each of said chambers (24) includes a set of at least two, light receiving, triangulated surfaces inclined down toward its respective LED (3).
7. The touch button system of Claim 6, wherein each chamber includes:
at least three of said inclined triangulated surfaces, each sharing a common apex (25) located toward the outer exterior of the light ring.
8. The touch button system of Claim 7, wherein:
each of said inclined, triangulated surfaces having a series of spaced, Fresnel-like edges (26) facing toward its respective LED disposed parallel to the base of its respective triangulated surface.
9. The touch button system of Claim 8, wherein:
one of said three triangulated surfaces is located between the other two, sharing common sides therewith; and wherein there is further included:
an outwardly curved, convex, inclined surface which terminates in the base side of said one of said three triangulated surfaces.
10. The touch button system of Claim 9, wherein:
said convex, inclined surface is frosted.
11. The touch button system of any one of claims 1 to 10, wherein:
said upper portion has an exterior, centrally directed side having a center line axis (C.L.) and includes on said exterior, centrally directed side (20) a conical surface making an angle to its center line axis which produces diffusion reflection for the light rays traveling within its solid, light transmitting material, as the light rays which have entered into it from said LEDs (3) are transmitted to said top ring portion (2), at least reducing the light going from said LEDs to the open interior of said upper portion.
12. The touch button system of Claim 11, wherein:
said angle is of the order of about thirty (30°) degrees.
13. The touch button system of any one of claims 1 to 12, wherein:
said LEDs (3) are carried on a printed circuit board (PCB) base (23) which is fastened to and carried by said bottom portion of said light ring element.
14. The touch button system of Claim 13, wherein:
said light ring element (2) is longitudinally extended from said top ring portion to said bottom portion and forms a substantially cylindrical shape on its outwardly facing exterior side, with there being at least five of said peripherally spaced LEDs (3) in an annular circular array located at its bottom portion carried by said PCB base (23).
15. The touch button system of Claim 13 or 14, wherein:
said bottom portion includes at its outer periphery at least two, flexible, bottom extensions (28) each having a latching opening; and wherein:



said base (23) is substantially circular in shape and includes two radially directed projections (30) which fit into said latching openings (31); said base (23) being latched to said bottom portion through the interfacing of said projections (30) into said latching openings (31).

5 16. The touch button system of any one of claims 13 to 15, wherein:

said bottom portion includes at its outer periphery at least two, peripherally off-set, longitudinally extended, keying pins; (32, 33) and wherein said:

base (23) includes two mating indentations on its periphery configured to the exterior shape of said keying pins; said keying pins (32, 33) being located in said mating indentations.

10

17. The touch button system of any one of claims 13 to 16, wherein:

said LEDs are electrically connected together in at least two parallel strings by conductive lead lines printed on said PCB base (23).

15 18. The touch button system of Claim 17, wherein:

said base (23) is substantially circular and each of said LEDs (3) has two electrical leads, at least one of said LEDs having its two lead disposed parallel to a laterally extended line bisecting across said base, with at least four of said LEDs each having its respective two leads located along the periphery of a common circle about the center of said base.

20

19. The touch button system of Claim 1, wherein:

said ring element (2) has a centrally located opening through it, at least part of which has a series of flat, longitudinally extended, keying surfaces; and

25 said button element (1) has an underside facing toward said bottom portion of said light ring element and has a centrally located, threaded part on said underside; and wherein there is further included:

a base (23) carrying said LEDs fastened to said bottom portion and having a centrally located opening through it; said centrally located openings and said threaded portions being aligned in a straight line; and

30

a longitudinally extended stem bolt element (7) having a head end located past said base and a threaded end mating with said centrally located threaded part; said bolt element (7) causing said base (23), said light ring element (2) and said button element (1) to be held together.

20. The touch button system of Claim 19, wherein there is further included:

35 a printed circuit board (PCB) (23) including electrical components associated electrically with said LEDs (3) and interfaced to said base by means of pin connections associated with the underside of said base and having a centrally located opening through it aligned with said centrally located openings in said light ring element and said base (23); and

40 a holder bracket associated with said PCB; said bolt element (7) extending through all of said centrally located openings with the head of said bolt element located past said PCB and at least part of said holder bracket, said bolt element holding said light ring element, said PCB and said holder bracket together under compression between said button surface and said head.

Patentansprüche

45

1. Beleuchtetes Berührungsknopfsystem zum Aktivieren oder Deaktivieren einer elektrisch gesteuerten Funktion, mit einem die Berührungsknopfoberfläche umgebenden Lichtring (2A) zum Beleuchten des Knopfes (1), das aufweist:

50 ein Lichtringelement mit einem obersten Ringbereich (2A) aus lichtdurchlässigem Material, einem oberen Bereich (27) mit einem Vollinneren aus lichtdurchlässigem Material und einem unteren Bereich; ein Knopfelement (1), das in dem Lichtringelement (2) angeordnet ist und von seinem lichtdurchlässigen obersten Ringbereich umgeben ist;

55 und eine Gruppierung umfangsmäßig beabstandeter, an dem unteren Bereich (23) angeordneter, lichtemittierender Dioden (LEDs) (3), wobei der obere Bereich aus lichtdurchlässigem Material das Licht, das von einem Knopf-Bediener gesehen werden soll und den "Ein"/"Aus"-Zustand des Knopfes (1) anzeigt, von den LEDs (3) zu dem obersten Ringbereich (2) überträgt.



2. Berührungsknopfsystem nach Anspruch 1, bei dem der obere Bereich aus lichtdurchlässigem Material eine lichtaufnehmende Unterseite (24) besitzt, die der Gruppierung aus LEDs (3) zugewandt ist, die, wenn die LEDs eingeschaltet sind, einiges von dem Licht der LEDs aufnimmt und die eine Reihe beabstandeter, Fresnel-artiger Kanten (26) aufweist.
- 5 3. Berührungsknopfsystem nach Anspruch 1, bei dem der obere Bereich aus lichtdurchlässigem Material eine lichtaufnehmende Unterseite (24) besitzt, die der Gruppierung aus LEDs (3) zugewandt ist, die einiges von dem Licht der LEDs aufnimmt und die eine Reihe einzelner, auf dem Umfang der Unterseite beabstandeter Kammern (24) aufweist, wobei jede der LEDs unter einer der Kammern
- 10 angeordnet ist und ihr Licht, wenn sie angeschaltet ist, auf die Kammer (24) überträgt.
4. Berührungsknopfsystem nach Anspruch 3, bei dem jede der Kammern (24) eine geneigte Fläche aufweist, die ihrer jeweiligen LED (3) zugewandt ist und von dieser Licht in das Vollinnere des oberen Bereichs aufnimmt.
- 15 5. Berührungsknopfsystem nach Anspruch 4, bei dem jede der geneigten Flächen eine Reihe beabstandeter, Fresnel-artiger Kanten (26) besitzt, die ihrer jeweiligen LED zugewandt sind.
6. Berührungsknopfsystem nach Anspruch 3, bei dem jede der Kammern (24) einen Satz aus wenigstens zwei lichtaufnehmenden, dreieckigen Oberflächen aufweist, die nach unten in Richtung auf ihre jeweilige LED geneigt sind.
- 20 7. Berührungsknopfsystem nach Anspruch 6, bei dem jede Kammer aufweist: wenigstens drei geneigte, dreieckige Oberflächen, die jeweils an einer gemeinsamen Spitze (25) teilhaben, die in Richtung auf die äußere Außenseite des Lichtrings angeordnet ist.
- 25 8. Berührungsknopfsystem nach Anspruch 7, bei dem jede der geneigten, dreieckigen Oberflächen eine Reihe von beabstandeten, Fresnel-artigen Kanten aufweist, die ihrer jeweiligen LED zugewandt sind und parallel zur Grundlinie ihrer jeweiligen dreieckigen Oberfläche angeordnet sind.
- 30 9. Berührungsknopfsystem nach Anspruch 8, bei dem eine der drei dreieckigen Oberflächen zwischen den anderen beiden angeordnet ist, und sich mit diesen gemeinsame Seitenlinien teilt; und bei dem außerdem eine nach außen gekrümmte, konvexe, geneigte Oberfläche enthalten ist, die in der Grundlinie dieser einen der drei dreieckigen Oberflächen endet.
- 35 10. Berührungsknopfsystem nach Anspruch 9, bei dem die konvexe, geneigte Oberfläche mattiert ist.
11. Berührungsknopfsystem nach einem der Ansprüche 1 bis 10, bei dem der obere Bereich eine äußere, zur Mitte gerichtete Seite mit einer Mittellinienachse (C.L.) besitzt und an dieser äußeren, zur Mitte gerichteten Seite (20) eine konische Oberfläche aufweist, die einen Winkel mit ihrer Mittellinienachse bildet, was für die Lichtstrahlen, die sich in seinem lichtdurchlässigen Vollmaterial fortbewegen diffuse Reflexion wirkt, wenn die von den LEDs (3) in das Vollmaterial eingetretenen Lichtstrahlen zu dem obersten Ringbereich übertragen werden, wobei das Licht, das von den LEDs in das offene Innere des oberen Bereichs geht, wenigstens reduziert wird.
- 40 45 12. Berührungsknopfsystem nach Anspruch 11, bei dem der Winkel in der Größenordnung von dreißig (30°) Grad liegt.
13. Berührungsknopfsystem nach einem der Ansprüche 1 bis 12, bei dem die LEDs (3) auf einer gedruckten Schaltplatten (PCB)-Basis (23) getragen sind, die an dem unteren Bereich des Lichtringelements befestigt ist und von diesem getragen ist.
- 50 55 14. Berührungsknopfsystem nach Anspruch 13, bei dem das Lichtringelement (2) in Längsrichtung von dem obersten Ringbereich zu dem untersten Bereich ausgedehnt ist und an seiner nach außen gewandten Außenseite eine im wesentlichen zylindrische Gestalt hat, wobei an seinem unterem Bereich von der PCB-Basis (23) getragen in einer ringförmigen Rundgruppierung mindestens fünf umfangsmäßig beabstandete LEDs (3) angeordnet sind.



15. Berührungsknopfsystem nach Anspruch 13 oder 14, bei dem der untere Bereich an seinem äußeren Umfang mindestens zwei flexible, untere Verlängerungen (28), jede mit einer Einrastöffnung, aufweist; und bei dem die Basis (23) eine im wesentlichen runde Form hat sowie zwei radial gerichtete Vorsprünge (30) aufweist, die in die Einrastöffnungen (31) passen, wobei die Basis (23) am unteren Bereich durch Zusammenwirken der Vorsprünge (30) mit den Einrastöffnungen (31) verrastet ist.
16. Berührungsknopfsystem nach einem der Ansprüche 13 bis 15, bei dem der untere Bereich an seinem äußeren Umfang mindestens zwei umfangmäßig versetzte, sich in Längsrichtung erstreckende Verriegelungsstifte (J2, J3) aufweist; und bei dem die Basis (23) an ihrem Umfang zwei nach der äußeren Gestalt der Verriegelungsstifte (J2, J3) geformte, Verbindungseintiefungen aufweist, in denen die Verriegelungsstifte (J2, J3) angeordnet sind.
17. Berührungsknopfsystem nach einem der Ansprüche 13 bis 16, bei dem die LEDs mittels auf der PCB-Basis (23) gedruckter Leiterbahnen in mindestens zwei parallelen Strängen elektrisch miteinander verbunden sind.
18. Berührungsknopfsystem nach Anspruch 17, bei dem die Basis (23) im wesentlichen rund ist und jede der LEDs (3) zwei elektrische Leitungen aufweist, wobei mindestens eine LED ihre beiden Leiter parallel einer, die Basis halbierenden, sich lateral erstreckenden Linie angeordnet hat, und wobei mindestens vier LEDs ihre jeweiligen beiden Leiter entlang dem Umfang eines gemeinsamen Kreises um den Mittelpunkt der Basis angeordnet haben.
19. Berührungsknopfsystem nach Anspruch 1, bei dem das Ringelement (2) eine mittig angeordnete Durchgangsöffnung aufweist, von der mindestens ein Teil eine Reihe flacher, langgestreckter, lagedefinierender Flächen besitzt; und das Knopfelement (1) eine Unterseite besitzt, die in Richtung zu dem unteren Bereich des Lichtringelements weist und an der Unterseite einen mittig angeordneten, mit einem Gewinde versehenen Teil besitzt; und bei dem außerdem eine Basis (23) enthalten ist, welche die an dem unteren Bereich befestigten LEDs trägt und eine mittig angeordnete Durchgangsöffnung besitzt, wobei die mittig angeordneten Öffnungen und die mit Gewinde versehenen Bereiche in einer geraden Linie ausgerichtet sind; und bei dem außerdem ein langgestrecktes Stielbolzenelement (7) mit einem hinter der Basis angeordneten Kopfende und einem Gewindeende enthalten ist; das mit dem mittig angeordneten, mit einem Gewinde versehenen Teil zusammenpaßt, wobei das Bolzenelement (7) die Basis (23), das Lichtringelement (2) und das Knopfelement (1) zusammenhält.
20. Berührungsknopfsystem nach Anspruch 19, bei dem außerdem enthalten sind: eine gedruckte Schaltplatte (PCB) (23), die elektrische Bauteile aufweist, die den LEDs (3) elektrisch zugeordnet sind und mittels Stiftverbindungen, die der Unterseite des Basis zugeordnet sind, an die Basis angeschlossen sind, wobei die PCB eine mittig angeordnete Durchgangsöffnung besitzt, die mit den mittig angeordneten Öffnungen in dem Lichtringelement und der Basis (23) ausgerichtet ist; und ein Befestigungshalter, welcher der PCB zugeordnet ist; wobei sich das Bolzenelement (7) durch alle mittig angeordneten Öffnungen erstreckt und mit seinem Kopf hinter der PCB sowie hinter mindestens einem Teil des Befestigungshalters angeordnet ist, wobei das Bolzenelement das Lichtringelement, die PCB und den Befestigungshalter unter Druck zwischen der Knopfoberfläche und dem Kopf zusammenhält.

Revendications

1. Système de bouton tactile éclairé servant à activer ou désactiver une fonction commandée électriquement, comprenant un anneau lumineux (2A) entourant la surface du bouton tactile pour éclairer le bouton (1), comprenant :
 - un élément d'anneau lumineux ayant une portion supérieure d'anneau (2A) faite d'une matière capable de transmettre la lumière, une portion supérieure (27) ayant une partie intérieure massive faite d'une matière transmettant la lumière, et une portion inférieure ;
 - un élément (1) de bouton placé dans ledit élément d'anneau lumineux (2) et entouré par sa portion supérieure d'anneau qui transmet la lumière ; et
 - une rangée de diodes électroluminescentes (DEL) (3), espacées sur la périphérie, situées au



niveau de ladite portion inférieure (23), ladite portion supérieure de matière capable de transmettre la lumière transmettant la lumière des DEL (3) à ladite portion supérieure (2) de l'anneau de façon qu'elle soit vue par une personne qui presse le bouton, indiquant ainsi l'état marche/arrêt du bouton (1).

- 5 2. Système de bouton tactile selon la revendication 1, dans lequel :
ladite portion supérieure faite de matière capable de transmettre la lumière possède une face inférieure (24) recevant la lumière, qui fait face à ladite rangée de DEL (3) pour recevoir une partie de la lumière desdites DEL lorsque celles-ci sont allumées, ladite face inférieure comprenant une série d'arêtes espacées (26), du type Fresnel.
- 10 3. Système de bouton tactile selon la revendication 1, dans lequel :
ladite portion supérieure faite d'une matière capable de transmettre la lumière possède une face inférieure (24) capable de recevoir la lumière, qui fait face audit ensemble de DEL (3) en recevant une partie de la lumière qu'elles émettent, ladite face inférieure comprenant une série de chambres individuelles (24) espacées le long de la périphérie de ladite face inférieure, chaque DEL (3) placée sous une desdites chambres transmettant sa lumière à ladite chambre (24) lorsqu'elle est allumée.
- 15 4. Système de bouton tactile selon la revendication 3, dans lequel :
chacune desdites chambres (24) comprend une surface inclinée qui fait face à une DEL (3) respective, en recevant ainsi la lumière de sa DEL respective pour l'introduire dans la matrice intérieure massive de ladite portion supérieure.
- 20 5. Système de bouton tactile selon la revendication 4, dans lequel :
chacune desdites surfaces inclinées possède une série d'arêtes espacées (26), du type Fresnel, qui fait face à sa DEL respective.
- 25 6. Système de bouton tactile selon la revendication 3, dans lequel :
chacune desdites chambres (24) comprend un jeu d'au moins deux surfaces triangulaires, réceptrices de lumière, inclinées vers le bas en direction de sa DEL (3) respective.
- 30 7. Système de bouton tactile selon la revendication 6, dans lequel chaque chambre comprend :
au moins trois desdites surfaces triangulaires inclinées, qui ont toutes en commun un sommet (25) situé vers la partie la plus extérieure de l'anneau lumineux.
- 35 8. Système de bouton tactile selon la revendication 7, dans lequel :
chacune desdites surfaces triangulaires inclinées possède une série d'arêtes espacées (26), du type Fresnel, qui font face à la DEL respective, disposées parallèlement à la base de la surface triangulaire respective.
- 40 9. Système de bouton tactile selon la revendication 8, dans lequel :
une des trois surfaces triangulaires est placée entre les deux autres, en partageant des côtés commun avec celle-ci, et dans lequel est encore incluse :
une surface inclinée convexe, incurvée vers l'extérieur, qui se termine dans le côté de base de l'une de ces trois surfaces triangulaires.
- 45 10. Système de bouton tactile selon la revendication 9, dans lequel :
ladite surface inclinée convexe est dépolie.
- 50 11. Système de bouton tactile selon une quelconque des revendications 1 à 10, dans lequel :
ladite portion supérieure possède une face externe, dirigée vers le centre, possédant un axe central (C.L.) et porte sur ladite face externe (20) dirigée vers le centre, une surface conique qui, forme avec ledit axe central un angle qui assure une réflexion diffuse pour les rayons lumineux qui passent dans sa matière capable de transmettre la lumière, lorsque les rayons lumineux qui y pénètrent, en provenance desdites DEL (3), sont transmises à ladite portion supérieure (2) de l'anneau, en réalisant au moins une réduction de la lumière allant desdites DEL à l'intérieur ouvert de ladite portion supérieure.
- 55 12. Système de bouton tactile selon la revendication 11, dans lequel :
ledit angle est de l'ordre d'environ trente degrés (30°).



13. Système de bouton tactile selon une quelconque des revendications 1 à 12, dans lequel :
lesdites DEL (3) sont portées par une base (23) comprenant un panneau de circuit imprimé, qui est fixée à ladite portion inférieure dudit élément d'anneau lumineux, et qui est portée par cette portion inférieure.
14. Système de bouton tactile selon la revendication 13, dans lequel :
ledit élément d'anneau lumineux (2) est prolongé longitudinalement de ladite portion supérieure de l'anneau à ladite portion inférieure et forme une configuration sensiblement cylindrique sur sa face externe qui regarde vers l'extérieur, et il y a au moins cinq desdites DEL (3) espacées selon la périphérie dans une rangée circulaire annulaire placée au niveau de sa portion inférieure qui est portée par ladite base (23) comprenant la plaquette de circuit imprimé (PCI).
15. Système de bouton tactile selon la revendication 13 ou 14, dans lequel :
ladite portion inférieure comprend, le long de sa périphérie extérieure, au moins deux prolongements inférieurs flexibles (28), dont chacun possède une ouverture de verrouillage, et dans lequel :
ladite base est de forme sensiblement circulaire et comprend deux saillies (30) dirigées radialement, qui s'emboîtent dans lesdites ouvertures de verrouillage (31), ladite base (23) étant verrouillée par rapport à ladite portion inférieure par l'engagement desdites saillies (30) dans lesdites ouvertures de verrouillage (31).
16. Système de bouton tactile selon l'une quelconque des revendications 13 à 15, dans lequel :
ladite portion inférieure comprend, le long de sa périphérie extérieure, au moins deux broches de verrouillage (J2, J3) décalées selon la périphérie, s'étendant longitudinalement, et dans lequel :
ladite base (23) comprend sur sa périphérie deux encoches complémentaires présentant la forme extérieure desdites broches de verrouillage, ces dernières étant placées dans lesdites indentations d'accouplement.
17. Système de bouton tactile selon une quelconque des revendications 13 à 16, dans lequel :
lesdites DEL sont connectées électriquement entre elles en au moins deux files parallèles par des pistes conductrices imprimées sur ladite base (23) comprenant un PCI.
18. Système de bouton tactile selon la revendication 17, dans lequel :
ladite base (23) est sensiblement circulaire et chacune desdites DEL (3) possède deux conducteurs électriques, au moins l'une desdites DEL ayant ses deux conducteurs disposés parallèlement à une ligne s'étendant latéralement qui divise ladite base en deux parties égales, au moins quatre desdites DEL ayant chacune ses deux conducteurs respectifs disposés le long de la périphérie d'un cercle commun centré sur le centre de ladite base.
19. Système de bouton tactile selon la revendication 1, dans lequel :
ledit élément d'anneau (2) est traversé par une ouverture centrale, dont au moins une partie possède une série de surfaces de clavetage méplates, s'étendant longitudinalement ; et
ledit élément de bouton (1) possède une face inférieure qui regarde vers ladite portion inférieure dudit élément d'anneau lumineux et possède une partie filetée, disposée en position centrale, sur ladite face inférieure, et dans lequel est également incluse :
une base (23) portant lesdites DEL fixées à ladite portion inférieure et ayant une ouverture centrale qui la traverse ; lesdites ouvertures centrales et lesdites portions filetées étant alignées sur une ligne droite ; et
un élément cheville ou tige (7) allongé longitudinalement ayant une extrémité de tête située au-delà de ladite base et une extrémité filetée qui s'accouple à ladite partie filetée centrale, ledit élément cheville (7) ayant pour effet de maintenir ensemble ladite base (23), ledit élément d'anneau lumineux (2) et ledit élément de bouton (1).
20. Système de bouton tactile selon la revendication 19, dans lequel sont en outre inclus :
un panneau de circuit imprimé (PCI) (23) comprenant des composants électriques associés électriquement auxdites DEL (3) et connectés à ladite base à l'aide de connexions à broches associées à la face inférieure de ladite base et ayant une ouverture centrale traversante alignée sur lesdites ouvertures centrales dudit élément anneau lumineux et de ladite base (23) ; et
une monture associée audit PCI ; ledit élément cheville maintenant ledit élément d'anneau

lumineux, ledit PCI et ladite monture ensemble en compression entre ladite surface de bouton et ladite tête.

5

10

15

20

25

30

35

40

45

50

55

