

Description

BACKGROUND OF THE INVENTION

Field of the Invention:

The present invention generally relates to CCD (charge coupled device) solid state image sensing devices and method of forming a CCD solid state image sensing device and, more particularly, is directed to a structure of a photo-sensitive section formed by a PN junction of a semiconductor.

Description of the Prior Art:

In general, a photo-sensitive section of a CCD solid state image sensing device is formed of a photodiode by a PN junction of a semiconductor.

FIG. 1 shows an example of a photo-sensitive section according to the prior art in which an N-type impurity diffusion region 22 is formed on the surface of a P-type silicon substrate and a photodiode PD is formed by a PN junction J of the silicon substrate 21 and the N-type impurity diffusion region 22.

FIG. 2 shows an example of a photo-sensitive section according to the prior art in which the N-type impurity diffusion region 22 is formed on the surface of a P-type well region 24 formed on an N-type silicon substrate 23 and the photodiode PD is formed by the PN junction J of the P-type well region 24 and the N-type impurity diffusion region 22. The above-mentioned photodiode PD constructs a photo-sensitive section 25 of a CCD solid state image sensing device.

Then, the above N-type impurity diffusion region 22 is formed by the ion implantation technique of phosphor (P) in the prior art.

However, in the conventional CCD solid state image sensing device, since the N-type diffusion region 22 constructing the photo-sensitive section 25 is formed by the ion implantation technique of phosphor (P), there is then the disadvantage such that a lattice distortion and stress tends to occur on the PN junction plane J formed by the contact of the N-type diffusion region 22 with the P-type silicon substrate 21 or the P-type well region 24.

This is a phenomenon which tends to occur because an atomic radius of the crystal of phosphor (P) is small as compared with that of silicon Si. This phenomenon exerts an influence on an electric characteristic of the CCD solid state image sensing device manufactured. More specifically, due to the lattice distortion and the stress, a leakage current of the reverse direction is increased on the plane of the PN junction J and a dark current is locally increased (i.e., a so-called fluctuation of dark current). There is then the problem such that a white noise, which is one of the defects encountered with an imaging screen,

tends to occur.

Further, in the case of phosphorus (P), its diffusion coefficient is large so that the phosphorus (P) is diffused over a wide region by the activation treatment (heat treatment) after the ion implantation process of phosphorus (P). As a consequence, the N-type impurity diffusion region 22 cannot be reduced in size, which brings a disadvantage in making the CCD solid state image sensing device compact in size.

OBJECTS AND SUMMARY OF THE INVENTION

Therefore, it is an object of the present invention to provide an improved CCD solid state image sensing device in which the aforesaid shortcomings and disadvantages of the prior art can be eliminated and a manufacturing method thereof.

More specifically, it is an object of the present invention to provide a CCD solid state image sensing device in which lattice distortion and stress can be alleviated and a manufacturing method thereof.

Another object of the present invention is to provide a CCD solid state image sensing device in which an occurrence of a leakage current can be reduced and a manufacturing method thereof.

Still another object of the present invention is to provide a CCD solid state image sensing device in which a dark current can be reduced and a manufacturing method thereof.

A further object of the present invention is to provide a CCD solid state image sensing device in which a bright flaw, which is one of defects encountered with an image sensing screen, can be reduced and a manufacturing method thereof.

A still further object of the present invention is to provide a CCD solid state image sensing device in which an N-type impurity diffusion region constructing a PN junction can be reduced in size and a manufacturing method thereof.

A yet further object of the present invention is to provide a CCD solid state image sensing device in which the solid state image sensor itself can be made compact in size and a manufacturing method thereof.

As a first aspect of the present invention, the present invention is directed to a CCD solid state image sensing device in which a photo-sensitive section formed of an N-type impurity diffusion region is formed within a P-type substrate or within a P-type impurity diffusion region in correspondence with a pixel. In this case, the CCD solid state image sensing device is characterized in that the single impurity substance in the N-type impurity diffusion region is arsenic.

In accordance with a second aspect of the present invention, a method of manufacturing a CCD solid state image sensing device is comprised of the steps of forming a first insulating layer made of SiO₂ on a P-type substrate or on a P-type impurity diffusion re-

gion, forming a second insulating layer made of Si_3N_4 on the first insulating layer, forming a third insulating layer made of SiO_2 on the second insulating layer, removing the second and third insulating layers formed on the photo-sensitive section, forming a transfer electrode on the third insulating layer, implanting only arsenic into the P-type substrate or into the P-type impurity diffusion region in correspondence with pixels by using the transfer electrode as a mask, and carrying out a heat treatment in a nitrogen atmosphere to form the N-type impurity diffusion region.

According to the structure of this invention, since the N-type impurity diffusion region constructing the PN junction of the photo-sensitive section is formed by the impurity diffusion process of only arsenic (As) whose atomic radius is larger than that of phosphorus (P) and which is substantially the same as that of silicon (Si) from a crystal standpoint, that is, the N-type impurity diffusion region is formed by the activation process after the arsenic (As) is injected onto the surface of the first P-type well region by the ion implantation technique, the lattice distortion and stress on the PN junction plane are alleviated, the occurrence of the leakage current of the reverse direction on the PN junction plane is reduced and the dark current is reduced, which leads to the reduction of bright flaw which is one of the defects encountered with the image sensing screen. Further, the N-type impurity diffusion region constructing the PN junction can be reduced in size and also the CCD solid state image sensing device itself can be made compact in size.

The above and other objects, features, and advantages of the present invention will become apparent from the following detailed description of an illustrative embodiment thereof when read in conjunction with the accompanying drawings, in which like reference numerals are used to identify the same or similar parts in the several views.

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a schematic diagram showing a structure of a photo-sensitive section of an example of a CCD solid state image sensing device according to the prior art;

FIG. 2 is a schematic diagram showing a structure of a photo-sensitive section of another example of a CCD solid state image sensing device according to the prior art;

FIG. 3 is a schematic diagram showing a structure of a main portion of a CCD solid state image sensing device according to an embodiment of the present invention;

FIGS. 4A through 4C are respectively process diagrams showing a method of manufacturing the CCD solid state image sensing device according to the embodiment of the present invention; and FIGS. 5A and 5B are respectively process dia-

grams showing a method of manufacturing the CCD solid state image sensing device according to the embodiment of the present invention.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENT

The present invention will hereinafter be described with reference to FIG. 3 to FIGS. 5A and 5B.

FIG. 3 is a schematic diagram showing a structure of a main portion of a CCD solid state image sensing device A according to an embodiment of the present invention.

In the CCD solid state image sensing device A, as shown in FIG. 3, an N-type impurity diffusion region 3, a vertical register 4 and a P-type channel stopper region 5 are formed within a first P-type well region 2 formed on an N-type silicon substrate 1, respectively. A P-type positive charge storage region 6 is formed on the N-type impurity diffusion region 3 and a second P-type well region 7 are formed beneath the vertical register 4, respectively. A photo-sensitive section (photoelectric converting section) 8 is formed of a photodiode PD which is formed by a PN junction J between the N-type impurity diffusion region 3 and the first P-type well region 2. This photo-sensitive section 8 is formed in correspondence with a pixel.

An oxide layer 9 made of SiO_2 is formed over the whole surface involving the channel stopper region 5, the vertical register 4 and the positive charge storage region 6 of the first P-type well region 2. Further, an Si_3N_4 layer 10 and an SiO_2 layer 11 are sequentially laminated on the vertical register 4 and the channel stopper region 5 over the oxide layer 9. The oxide layer 9, the Si_3N_4 layer 10 and the SiO_2 layer 11 formed on the vertical register 4 and the channel stopper region 5 constitute a gate insulating layer 12 of a trilayer structure.

A transfer electrode 13 made of a polycrystalline silicon layer is formed on the above-mentioned gate insulating layer 12 on the first P-type well region 2, and an interlayer 14 made of PSG (phosphor-silicate-glass) or the like is laminated on the transfer electrode 13 and the oxide layer 9 on the positive charge storage region 6. Further, an Al light shielding layer 15 is selectively formed on the transfer electrode 13 through the interlayer 14. A read-out gate 17 is constructed between the photo-sensitive section 8 and the vertical register 4.

According to this embodiment, the N-type impurity diffusion region 3 is formed by the ion implantation of arsenic (As). In the process for forming the N-type impurity diffusion region 3, atomic radiiuses of phosphorus (P) used in the prior art, of arsenic (As) used in this embodiment and of silicon (Si) constructing the substrate 1 are 0.11 nm (1.10 Å), 0.118 nm (1.18 Å) and 0.117 nm (1.17 Å) from a crystal standpoint, respectively. As it is clear from the above-mentioned

atomic radiuses, the atomic radiuses of arsenic (As) and silicon (Si) are very close to each other. Accordingly, when the N-type impurity region 3 is formed by the ion implantation of arsenic (As) according to this embodiment, the lattice distortion and the stress on the PN junction plane J can be alleviated unlike the case where phosphorus (P) is employed.

A method of manufacturing the CCD solid state image sensing device according to the embodiment of the present invention will be described next with reference to process diagrams forming FIGS. 4A through 4C and FIGS. 5A, 5B. Throughout FIGS. 4A to 4C and FIGS. 5A, 5B, like parts corresponding to those of FIG. 3 are marked with the same references and therefore need not be described in detail.

As shown in FIG. 4A, after the oxide layer 9 made of SiO_2 is formed on the first P-type well region 2 formed on the N-type silicon substrate 1, N- and P-type impurities are selectively ion-injected into the first P-type well region 2, thereby the N-type vertical register 4, the P-type channel stopper region 5 and the second P-type well region 7 being formed, respectively.

Then, as shown in FIG. 4B, after the Si_3N_4 layer 10 and the SiO_2 layer 11 are sequentially laminated on the entire surface of the oxide layer 9 formed on the first P-type well region 2, the Si_3N_4 layer 10 and the SiO_2 layer 11 are selectively etched away at their portions, which will form the photo-sensitive section 8 later, by the etching process. The oxide layer 9, the Si_3N_4 layer 10 and the SiO_2 layer 11 on the vertical register 4 and the channel stopper region 5 constitute the gate insulating layer 12. Thereafter, the transfer electrode 13 made of the polycrystalline silicon layer is formed on the gate insulating layer 12.

As shown in FIG. 4C, after N-type impurity, arsenic (As) in this embodiment is selectively injected into the first P-type well region 2, particularly at a relatively deep position such as depth of 0.3 μm to 0.4 μm from the surface of the substrate 1, namely, the first P-type well region 2 by the ion implantation technique by using the transfer electrode 13 as a mask, the heat treatment is carried out in the atmosphere of nitrogen to thereby form the N-type impurity diffusion region 3. At that time, the photodiode PD formed by the PN junction J between the N-type impurity diffusion region 3 and the first P-type well region 2 constructs the photo-sensitive section 8. The above-mentioned heat treatment is carried out by a short time annealing treatment in which a temperature is 1000°C or more and a heating time lies in a range of from 10 seconds to several 10s of seconds. Particularly, in this embodiment, the above heat treatment is carried out by a short time annealing technique (i.e., lamp anneal) in which a temperature is 1050°C and a time is 10 seconds.

Then, as shown in FIG. 5A, the transfer electrode 13 is employed as a mask and P-type impurity, e.g.,

boron (B) is selectively injected onto the surface of the photo-sensitive section 8 by the ion implantation technique. Then, the product is heat-treated in the atmosphere of nitrogen and the P-type impurity thus injected is diffused and activated, thereby the P-type positive charge storage region 6 being formed on the surface of the photo-sensitive section 8.

Then, as shown in FIG. 5B, after the interlayer 14 made of PSG or the like is formed on the entire surface involving the transfer electrode 13, the Al light shielding layer 15 is selectively formed on the transfer electrode 13 over the interlayer 14, thereby the CCD solid state image sensing device A according to this embodiment being obtained.

As described above, according to this embodiment, since the N-type impurity diffusion region 3 constructing the PN junction J of the photo-sensitive section 8 is formed by the impurity diffusion process of only arsenic (As) whose atomic radius is larger than that of phosphorus (P) and which is substantially the same as that of silicon (Si) from a crystal standpoint, that is, the N-type impurity diffusion region 3 is formed by the activation process after the arsenic (As) is injected onto the surface of the first P-type well region 2 by the ion implantation technique, the lattice distortion and stress on the PN junction plane J are alleviated, the occurrence of the leakage current in the reverse direction on the PN junction plane J is reduced and hence the dark current is reduced, which leads to the reduction of bright flaw on the image sensing screen which is one of the defects encountered with the image sensing screen.

Further, since the arsenic (As) is low in diffusion coefficient, the As impurity can be suppressed from being diffused over a wide area in the succeeding heat treatment, whereby the N-type impurity diffusion region 3 constructing the PN junction J is reduced. In addition, the CCD solid state image sensing device A itself can be made compact in size.

Particularly, in this embodiment, since the arsenic (As) is injected by the ion implantation technique and then the N-type impurity diffusion region 3 is formed by the short time annealing process in the nitrogen atmosphere in which the temperature is 1000°C or more and the time is in a range of from 10 to several 10s of seconds, the local residual defects by the ion implantation of arsenic (As) can be reduced efficiently. As a consequence, the increase of the local dark current due to the residual defects can be prevented and therefore the bright flaw on the image sensing screen can be reduced effectively. Further, since the annealing process is carried out in a short period of time and also the diffusion coefficient of arsenic (As) is small, the N-type impurity diffusion region 3 can be reduced efficiently and the CCD solid state image sensing device A itself can be made compact in size efficiently.

While the N-type impurity diffusion region 3 con-

structing the photo-sensitive section 8 is formed on the first P-type well region 2 formed on the N-type silicon substrate 1 as described above, the present invention is not limited thereto and a P-type silicon substrate may be used, in which the N-type impurity diffusion region 3 may be directly formed on the P-type silicon substrate. Furthermore, in the above-mentioned embodiment, the P-type hole storage region 6 formed on the surface of the photo-sensitive section 8 may be omitted.

According to the CCD solid state image sensing device of the present invention, the bright flaw on the image sensing screen, which is one of the defects encountered with the image sensing screen, can be reduced. Also, the N-type impurity diffusion region constructing the PN junction can be reduced in size and also the CCD solid state image sensing device itself can be made compact in size.

Claims

1. A CCD solid state image sensing device (A) in which a photo-sensitive section formed of an N-type impurity diffusion region (3) is formed within a P-type substrate (2) or within a P-type impurity diffusion region in correspondence with a pixel, characterized in that the single impurity substance in said N-type impurity diffusion region (3) is arsenic.
2. A method of manufacturing a CCD solid state image sensing device comprising the steps of:
 - (a) forming a first insulating layer (9) made of SiO_2 on a P-type substrate (2) or on a P-type impurity diffusion region;
 - (b) forming a second insulating layer (10) made of Si_3N_4 on said first insulating layer;
 - (c) forming a third insulating layer (11) made of SiO_2 on said second insulating layer;
 - (d) removing said second and third insulating layers formed on said photo-sensitive section;
 - (e) forming a transfer electrode (13) on said third insulating layer;
 - (f) implanting only arsenic into said P-type substrate or into said P-type impurity diffusion region in correspondence with a pixel by using said transfer electrode (13) as a mask; and
 - (g) carrying out a heat treatment in a nitrogen atmosphere to form said N-type impurity diffusion region (3).
3. The method according to claim 2, in which said arsenic is implanted to a depth of 0.3 to 0.4 μm from the substrate surface.

Patentansprüche

1. CCD-Festkörper-Bildaufnahmeverrichtung (A), in der ein aus einem n-Fremdstoffdiffusionsbereich (3) bestehender photoempfindlicher Abschnitt innerhalb eines p-Substrats (2) oder eines p-Fremdstoffdiffusionsbereichs einem Pixel entsprechend ausgebildet ist, dadurch gekennzeichnet, daß die einzige Fremdstoffsubstanz im n-Fremdstoffdiffusionsbereich (3) Arsen ist.
2. Verfahren zum Herstellen einer CCD-Festkörper-Bildaufnahmeverrichtung, umfassend die folgenden Schritte:
 - (a) Herstellen einer ersten Isolierschicht (9) aus SiO_2 auf einem p-Substrat (2) oder einem p-Fremdstoffdiffusionsbereich;
 - (b) Herstellen einer zweiten Isolierschicht (10) aus Si_3N_4 auf der ersten Isolierschicht;
 - (c) Herstellen einer dritten Isolierschicht (11) aus SiO_2 auf der zweiten Isolierschicht;
 - (d) Entfernen der auf dem photoempfindlichen Abschnitt hergestellten zweiten und dritten Isolierschicht;
 - (e) Herstellen einer Übertragungselektrode (13) auf der dritten Isolierschicht;
 - (f) Implantieren nur von Arsen in das p-Substrat oder in den p-Fremdstoffdiffusionsbereich, entsprechend einem Pixel, unter Verwendung der Übertragungselektrode (13) als Maske; und
 - (g) Ausführen einer Wärmebehandlung in einer Stickstoffatmosphäre, um den n-Fremdstoffdiffusionsbereich (3) auszubilden.
3. Verfahren nach Anspruch 2, bei dem das Arsen mit einer Tiefe von 0,3 bis 0,4 μm ausgehend von der Substratoberfläche implantiert wird.

Revendications

1. Dispositif capteur d'images à solide à CCD (A), dans lequel une section photosensible formée sur une région de diffusion d'une impureté du type N (3) est formée dans un substrat du type P (2) ou dans une région de diffusion d'une impureté du type P, en correspondance avec un élément d'image, caractérisé en ce que l'unique substance d'impureté dans ladite région de diffusion d'une impureté du type N (3) est l'arsenic.
2. Procédé de fabrication d'un dispositif capteur d'images à solide à CCD, comprenant les étapes consistant à:
 - (a) former une première couche isolante (9) constituée de SiO_2 sur un substrat du type P (2) ou sur une région de diffusion d'une impureté



structuring the photo-sensitive section 8 is formed on the first P-type well region 2 formed on the N-type silicon substrate 1 as described above, the present invention is not limited thereto and a P-type silicon substrate may be used, in which the N-type impurity diffusion region 3 may be directly formed on the P-type silicon substrate. Furthermore, in the above-mentioned embodiment, the P-type hole storage region 6 formed on the surface of the photo-sensitive section 8 may be omitted.

According to the CCD solid state image sensing device of the present invention, the bright flaw on the image sensing screen, which is one of the defects encountered with the image sensing screen, can be reduced. Also, the N-type impurity diffusion region constructing the PN junction can be reduced in size and also the CCD solid state image sensing device itself can be made compact in size.

Claims

1. A CCD solid state image sensing device (A) in which a photo-sensitive section formed of an N-type impurity diffusion region (3) is formed within a P-type substrate (2) or within a P-type impurity diffusion region in correspondence with a pixel, characterized in that the single impurity substance in said N-type impurity diffusion region (3) is arsenic.
2. A method of manufacturing a CCD solid state image sensing device comprising the steps of:
 - (a) forming a first insulating layer (9) made of SiO_2 on a P-type substrate (2) or on a P-type impurity diffusion region;
 - (b) forming a second insulating layer (10) made of Si_3N_4 on said first insulating layer;
 - (c) forming a third insulating layer (11) made of SiO_2 on said second insulating layer;
 - (d) removing said second and third insulating layers formed on said photo-sensitive section;
 - (e) forming a transfer electrode (13) on said third insulating layer;
 - (f) implanting only arsenic into said P-type substrate or into said P-type impurity diffusion region in correspondence with a pixel by using said transfer electrode (13) as a mask; and
 - (g) carrying out a heat treatment in a nitrogen atmosphere to form said N-type impurity diffusion region (3).
3. The method according to claim 2, in which said arsenic is implanted to a depth of 0.3 to 0.4 μm from the substrate surface.

Patentansprüche

1. CCD-Festkörper-Bildaufnahmeverrichtung (A), in der ein aus einem n-Fremdstoffdiffusionsbereich (3) bestehender photoempfindlicher Abschnitt innerhalb eines p-Substrats (2) oder eines p-Fremdstoffdiffusionsbereichs einem Pixel entsprechend ausgebildet ist, dadurch gekennzeichnet, daß die einzige Fremdstoffsubstanz im n-Fremdstoffdiffusionsbereich (3) Arsen ist.
2. Verfahren zum Herstellen einer CCD-Festkörper-Bildaufnahmeverrichtung, umfassend die folgenden Schritte:
 - (a) Herstellen einer ersten Isolierschicht (9) aus SiO_2 auf einem p-Substrat (2) oder einem p-Fremdstoffdiffusionsbereich;
 - (b) Herstellen einer zweiten Isolierschicht (10) aus Si_3N_4 auf der ersten Isolierschicht;
 - (c) Herstellen einer dritten Isolierschicht (11) aus SiO_2 auf der zweiten Isolierschicht;
 - (d) Entfernen der auf dem photoempfindlichen Abschnitt hergestellten zweiten und dritten Isolierschicht;
 - (e) Herstellen einer Übertragungselektrode (13) auf der dritten Isolierschicht;
 - (f) Implantieren nur von Arsen in das p-Substrat oder in den p-Fremdstoffdiffusionsbereich, entsprechend einem Pixel, unter Verwendung der Übertragungselektrode (13) als Maske; und
 - (g) Ausführen einer Wärmebehandlung in einer Stickstoffatmosphäre, um den n-Fremdstoffdiffusionsbereich (3) auszubilden.
3. Verfahren nach Anspruch 2, bei dem das Arsen mit einer Tiefe von 0,3 bis 0,4 μm ausgehend von der Substratoberfläche implantiert wird.

Revendications

1. Dispositif capteur d'images à solide à CCD (A), dans lequel une section photosensible formée sur une région de diffusion d'une impureté du type N (3) est formée dans un substrat du type P (2) ou dans une région de diffusion d'une impureté du type P, en correspondance avec un élément d'image, caractérisé en ce que l'unique substance d'impureté dans ladite région de diffusion d'une impureté du type N (3) est l'arsenic.
2. Procédé de fabrication d'un dispositif capteur d'images à solide à CCD, comprenant les étapes consistant à:
 - (a) former une première couche isolante (9) constituée de SiO_2 sur un substrat du type P (2) ou sur une région de diffusion d'une impu-



reté du type P;

(b) former une deuxième couche isolante (10) constituée de Si_3N_4 sur ladite première couche isolante;

(c) former une troisième couche isolante (11) constituée de SiO_2 sur ladite deuxième couche isolante;

(d) éliminer lesdites deuxième et troisième couches isolantes formées sur ladite section photosensible;

(e) former une électrode de transfert (13) sur ladite troisième couche isolante;

(f) planter uniquement de l'arsenic dans ledit substrat du type P ou dans ladite région de diffusion d'une impureté du type P en correspondance avec un élément d'image en utilisant ladite électrode de transfert (13) comme masque; et

(g) exécuter un traitement thermique dans une atmosphère d'azote pour former ladite région de diffusion d'une impureté du type N (3).

3. Procédé selon la revendication 2, dans lequel ledit arsenic est implanté à une profondeur de 0,3 à 0,4 μm à partir de la surface du substrat.