

SILICON-ON-INSULATOR WITH CRYSTALLINE SILICON OXIDE

BACKGROUND

5 [0001] Silicon-on-insulator (SOI) structures may be used as substrates and building blocks for various types of semiconductor devices, such as MOSFETs and other types of transistors, and other types of microelectronic components and circuits, as well as
10 silicon photonic components.

[0002] The quality of a SOI structure may be crucial for the performance of a device formed on such substrate. In many applications, crystalline, high quality SOI structures may result in the best device
15 performance.

[0003] Conventionally, SOI layer structures have been manufactured by ion implantation, comprising oxygen ion bombardment of an existing silicon surface, followed by annealing. This results in formation of an
20 amorphous silicon oxide layer within the silicon substrate. As one disadvantage, the ion bombardment affects adversely the quality of the remaining silicon layer above the silicon oxide.

[0004] In US 20060003500 A1, a method is disclosed
25 where one atomic layer of oxygen is first deposited self-limitedly on an existing silicon surface to form one molecular layer of crystalline silicon dioxide. Thereafter, an overlaying silicon layer may be formed epitaxially on the silicon dioxide.

30

SUMMARY

[0005] This Summary is provided to introduce a selection of concepts in a simplified form that are

further described below in the Detailed Description. This Summary is not intended to identify key features or essential features of the claimed subject matter, nor is it intended to be used to limit the scope of
5 the claimed subject matter.

[0006] In one aspect, a method is disclosed for forming a semiconductor structure comprising a silicon-on-insulator layer structure with crystalline silicon oxide SiO_x as the insulator material. The
10 method comprises: providing a crystalline silicon substrate having a substantially clean deposition surface in a vacuum chamber; heating the silicon substrate to an oxidation temperature T_0 in the range of 550 to 1200°C; supplying, while keeping the
15 substrate in the oxidation temperature, with an oxidation pressure P_0 in the range of $1 \cdot 10^{-8}$ to $1 \cdot 10^{-4}$ mbar in the vacuum chamber, molecular oxygen O_2 into the vacuum chamber with an oxygen dose D_0 in the range of 0.1 to 1000 Langmuir (L); whereby at least part of
20 the oxygen supplied into the vacuum chamber is adsorbed onto the deposition surface and diffuses into the silicon substrate, and a crystalline silicon oxide layer with a thickness of at least two molecular layers is formed within the silicon substrate,
25 between a crystalline silicon base layer and a crystalline silicon top layer. In some embodiments, the oxidation temperature may lie in the range of 550 to 1000 °C, or in the range of 550 to 850 °C.

[0007] In another aspect, a semiconductor structure
30 is disclosed which comprises a silicon-on-insulator layer structure with crystalline silicon oxide SiO_x as the insulator material. The semiconductor structure

comprises: a crystalline silicon base layer; a crystalline silicon oxide layer with a thickness of at least two molecular layers on the base layer; and a crystalline silicon top layer on the crystalline silicon oxide layer which may be formed by the above method. The semiconductor structure may be formed by the above method.

[0008] Many of the attendant features will be more readily appreciated as the same becomes better understood by reference to the following detailed description considered in connection with the accompanying drawings.

DESCRIPTION OF THE DRAWINGS

[0009] The present description will be better understood from the following detailed description read in light of the accompanying drawings, wherein: FIGs. 1, 3, and 5 show flow charts of method for manufacturing a semiconductor structure comprising a silicon-on-insulator (SOI) layer structure; FIGs. 2 and 6 illustrate schematically semiconductor structures comprising a SOI layer structure; FIG. 4 shows scanning tunneling microscope images of a sample of a semiconductor structure comprising a SOI layer structure; and FIG. 7 shows schematically the band structure of a semiconductor structure comprising a SOI layer structure. FIGs. 8 and 9 show capacitance-voltage (C-V) curves measured for metal-oxide-semiconductor (MOS) capacitor samples comprising SOI layer structures and MOS capacitor references not comprising SOI layer structures.

[0010] The drawings of FIGs. 2 and 6 are not in scale.

5 DETAILED DESCRIPTION

[0011] The detailed description provided below in connection with the appended drawings is intended as a description of a number of embodiments and is not
10 intended to represent the only forms in which the embodiments may be constructed, implemented, or utilized.

[0012] At least some of the embodiments and examples discussed below may provide, for example, a
15 simple, substantially single-step process for forming a high-quality SOI structure with crystalline silicon oxide as the material of the insulator layer. Further, at least some of the embodiments and examples discussed below may provide, for example, a high-
20 quality SOI layer structure suitable for being incorporated as part of various semiconductor devices. For example, the SOI layer structure may serve as a deposition surface for depositing semiconductor device layers on it.

25 [0013] The method 100 of FIG. 1 may be used for forming a semiconductor structure which comprises a silicon-on-insulator (SOI) layer structure with crystalline silicon oxide SiO_x as the material of the insulator layer. The semiconductor substrate may be in
30 accordance with that of FIG. 2, and in the following, the method is discussed with reference to both FIG. 1 and FIG. 2.

[0014] The method comprises providing, in operation 120, a crystalline silicon substrate 201 which has a substantially clean deposition surface 202 in a vacuum chamber.

5 [0015] The crystalline silicon substrate may be in the form of a plain silicon wafer of any appropriate diameter and thickness. Alternatively, the silicon substrate may be formed in any other appropriate configuration, shape, and size. For example, it may be
10 cut from or etched on a silicon wafer. The silicon substrate may be a self-supporting structure or it may be a structure attached or formed on a carrier substrate or support structure. The silicon substrate may be a part of a larger structure or assembly
15 incorporating also parts, structures, and elements not formed of silicon.

[0016] A deposition surface refers to a surface of the silicon substrate on which additional material may be introduced and/or adsorbed. With regard to the
20 crystal orientation, the deposition surface may be, for example, a silicon {100}, silicon {111}, or silicon {110} surface.

[0017] Being substantially clean refers to the deposition surface being substantially free of any
25 native silicon oxide or impurity atoms of any other type. "Substantially free" means that the concentration of foreign atoms and molecules on the silicon surface does not exceed $3 \cdot 10^{13}$ cm⁻². Such substantially clean deposition surface may be provided
30 as cleaned beforehand, i.e. before the method. Alternatively, a cleaning thereof may be included in the method, as illustrated by the optional cleaning

operation 110 in the method of FIG. 1. Such cleaning may be carried out by any appropriate cleaning process.

[0018] The vacuum chamber may be any appropriate type of vacuum chamber of a system capable of producing a pressure of $1 \cdot 10^{-4}$ mbar or lower, preferably at least down to $1 \cdot 10^{-8}$ mbar, in the vacuum chamber. There may be any appropriate type of carrier or holder member on or to which the silicon substrate may be positioned or attached. Any appropriate type of heating and cooling system may be connected to such carrier or holder member to heat and cool the silicon substrate lying on it.

[0019] The method further comprises, in operation 130, heating the silicon substrate which has been provided in the vacuum chamber, to an oxidation temperature T_0 lying in the range of 550 to 1200 °C, for example, in the range of 550 to 1000 °C, 550 to 850 °C, or 550 to 750 °C.

[0020] In step 140, the method comprises supplying, while keeping the substrate in the oxidation temperature, molecular oxygen O_2 into the vacuum chamber with an oxidation pressure P_0 which lies in the range of $1 \cdot 10^{-8}$ to $1 \cdot 10^{-4}$ mbar, for example, in the range of $1 \cdot 10^{-7}$ to $1 \cdot 10^{-8}$ mbar. The oxygen supply is continued until an oxygen dose in the range of 0.1 to 1000 L, for example, in the range of 5 to 300 L has been supplied into the vacuum chamber.

[0021] Those ranges specified above define a parameter space within which the actual process parameters may be selected. Thus, the method may be carried out using different combinations of the actual

process parameters, i.e. the oxidation temperature, the oxidation pressure, and the oxygen dose. For example, actual process parameters may be selected within any of the following parameter sub-spaces: To =
5 550 to 700 °C, Po = $1 \cdot 10^{-7}$ to $1 \cdot 10^{-4}$ mbar, Do = 10 to 50 L; To = 650 to 700 °C, Po = $1 \cdot 10^{-7}$ to $1 \cdot 10^{-6}$ mbar, Do = 50 to 100 L; To = 650 to 750 °C, Po = $1 \cdot 10^{-7}$ to $5 \cdot 10^{-7}$ mbar, Do = 50 to 300 L; To = 700 to 750 °C, Po = $1 \cdot 10^{-5}$ to $5 \cdot 10^{-5}$ mbar, Do = 5 to 50 L; To = 550 to 600 °C, Po
10 = $1 \cdot 10^{-7}$ to $5 \cdot 10^{-7}$ mbar, Do = 5 to 75 L; and To = 700 to 750 °C, Po = $5 \cdot 10^{-6}$ to $1 \cdot 10^{-5}$ mbar, Do = 10 to 100 L.

[0022] The duration of the oxygen supply may vary depending, for example, on the oxygen pressure and the targeted oxygen dose. The oxygen pressure, in turn,
15 may be affected, for example, by the detailed properties of the vacuum chamber and the oxygen supply arrangement. To ensure accurate control of the oxygen dose, the molecular oxygen may be supplied into the vacuum chamber for an oxidation period which is at
20 least 0.5 seconds, for example, at least about 1 second, preferably at least 10 seconds. Increasing the length of the oxidation period may enable better control of the oxygen dose.

[0023] As a result of said oxygen supply with said
25 oxidation pressure, oxidation time, and oxidation temperature of the silicon substrate, the oxygen supplied into the vacuum chamber is at least partially adsorbed onto the deposition surface and diffuses into the silicon substrate. Consequently, a crystalline
30 silicon oxide layer with a thickness of at least two molecular layers is formed within the silicon

substrate, between a crystalline silicon base layer and a crystalline silicon top layer. In other words, a SOI structure with crystalline silicon oxide SiO_x layer as a dielectric layer is formed below a crystalline silicon top layer. Thereby, the method comprises forming a crystalline silicon oxide layer within an existing silicon crystal, without any need, for example, for additional deposition steps to form the crystalline silicon top layer. Then, the top layer may have basically or mostly the same diamond cubic crystal structure as the base layer. "Basically" and "mostly" refer to the fact that the crystalline silicon oxide layer may have a crystal structure deviating from the diamond cubic crystal structure, and that may have some effect on the crystal structure of the silicon top layer also, at least close to the Si/SiO_x interface. On the other hand, the $(2 \times 1) + (1 \times 2)$ reconstruction of the free surface of the crystalline silicon top layer affects the crystal structure of the top layer close to said free surface thereof.

[0024] According to established understanding in the art, when oxidizing crystalline silicon using known methods, the oxygen incorporation sites in the crystal lie at the deposition surface; see e.g. Miyamoto et al., Physical Review B 43, 9287, 1991.

[0025] However, the above method is based on a surprising observation that with suitably selected novel combination of the oxidation parameters, oxygen adsorbed onto the deposition surface may be made diffuse through a surface or top layer of the silicon substrate so that crystalline oxide is formed within the bulk silicon crystal clearly below the deposition surface. At the same time, silicon atoms from the bulk

crystal of the silicon substrate may diffuse towards the outermost surface due to the incorporation of the oxygen atoms into the silicon substrate. Such diffused silicon atoms may form new structures on the deposition surface. The crystal structure of the crystalline oxide SiO_x layer may be different from the diamond lattice of bulk silicon.

[0026] The semiconductor structure 200 of FIG. 2, comprising a silicon-on-insulator (SOI) structure, may be manufactured using a method as discussed above with reference to FIG. 1. In that case, as illustrated in FIG. 2, the starting point for the manufacturing is a crystalline silicon substrate 201 having a substantially clean deposition surface 202 thereon. The semiconductor structure 200 comprises a crystalline silicon base layer 203, a crystalline silicon oxide SiO_x layer 204 which widens out to a thickness of more than one molecular layer on the silicon base layer; and a crystalline silicon top layer 205 on the crystalline silicon oxide layer. The crystalline silicon top layer 205 may have basically or mostly the same diamond cubic crystal structure as the crystalline silicon base layer 203.

[0027] The accurate thickness of the crystalline SiO_x layer may vary and it may have a thickness of several nanometers. When formed by a method as discussed above with reference to FIG. 1, the thickness may be affected, for example, by the oxidation temperature, the oxidation pressure, and/or the oxygen dose. The selection of the thickness may be used to tailor the band gap of the SiO_x layer. For example, an increase in the band gap may advantageously provide increase in the effective

insulating barrier thickness of the oxide layer. Appropriate adjustment of the thickness of the crystalline SiO_x layer may be used, for example, to adjust the tunneling through SiO_x layer in the semiconductor structure. This is discussed in more detail below.

[0028] In the case of semiconductor structures manufactured using a method as discussed above with reference to FIG. 1, the silicon-silicon oxide interfaces between the silicon oxide layer and the silicon base and top layers have been found to be graded instead of absolutely abruptly formed, due to the diffusion. This may advantageously result in bent energy bands at the SiO_x/Si interface between the silicon oxide layer and the silicon base layer, driving the charge carriers away from the interface region, which may, for example, decrease undesired surface recombination of charge carriers.

[0029] The method 300 of FIG. 3 differs from that of FIG. 1 in that it comprises an additional annealing operation 350 where the silicon substrate with the adsorbed oxygen is annealed in the vacuum chamber, after the supply of molecular oxygen, at a post heating temperature lying in the range of 650 to 750 °C to remove possible excess oxygen not contributing the formation of the crystalline silicon oxide layer. The annealing may have duration of 30 seconds to 60 minutes, for example, 5 to 20 minutes. Pressure of 10^{-8} mbar or less in the vacuum chamber may be used during the annealing.

[0030] Before the annealing, the semiconductor structure formed in the operations of 310 or 320 to

340 may be cooled to a temperature which substantially lower than the oxidation and post heating temperatures. Alternatively, the temperature of the silicon substrate/semiconductor structure may be
5 adjusted directly from the oxidation temperature to the post heating temperature. In the case the oxidation temperature is equal to the post heating temperature, no adjustment is needed.

[0031] Feasibility of the methods discussed above
10 was tested by oxidation procedure examples.

[0032] In first example, a 5 mm x 10 mm rectangular Si sample was cut from an n-type Si (100) wafer to serve as a crystalline silicon substrate with a Si (100) deposition surface. The Si sample was attached
15 via its shorter edges on a sample holder made of Mo and allowing direct current feeding through the Si sample. The sample holder was transferred into a manipulator located in a vacuum chamber of a multi-chamber vacuum system, and the Si sample was
20 repeatedly rapidly heated up to a cleaning temperature of 1100 to 1200 °C to remove the native oxide and carbon contaminants from the Si (100) deposition surface. X-ray photoelectron spectroscopy (XPS) was used to confirm that the oxygen and carbon
25 contaminants were effectively removed/desorbed from the deposition surface. Furthermore, low-energy electron diffraction (LEED) analysis showed a sharp (2x1)+(1x2) reconstruction arising from an inherent double-domain surface structure. Scanning-tunneling-
30 microscopy (STM) images captured after the surface cleaning supported the presence of the double-domain reconstruction on large two-dimensional terraces.

[0033] After the cleaning phase, the Si sample with the clean Si (100) deposition surface was oxidized in the same vacuum system, using O₂ gas introduced into the vacuum chamber via a leak valve. Before opening the leak valve, the temperature of the Si sample was increased to a heating temperature of 670 °C. Then the O₂ pressure in the vacuum chamber was increased to 1·10⁻⁷ mbar (the pressure was measured by an ion gauge pressure meter), and the Si sample was oxidized at the heating temperature for 500 seconds, resulting in an oxidation dose of 50 Langmuir (L). Thereafter, the leak valve was closed and the Si heating was stopped simultaneously.

[0034] The STM images of FIG. 4 show the development of the surface of the Si sample during the oxidation. In the uppermost image, the deposition surface has a terrace-like or stepped micro-structure. When the oxidation proceeds, the incorporation of oxygen atoms into the Si crystal may result in diffusion of Si atoms from the bulk crystal to the deposition surface where they start to form new islands or rows with the initial (2x1) dimer-row structure, as illustrated in the middle and the lowermost images.

[0035] After completion of the oxidation of the Si sample, LEED image of the Si sample still showed a sharp (2x1)+(1x2) pattern, indicating that the outermost topmost surface layer of the sample was formed of crystalline silicon. On the other hand, O1s intensity measured from the sample by XPS clearly revealed the incorporation of oxygen atoms within the bulk silicon crystal, below the silicon top layer.

[0036] In second example, a Si sample was prepared and cleaned similarly to the first example discussed above. Oxidation was carried out basically similarly with the first example but with oxidation temperature of 600 °C, using oxygen pressure of $1 \cdot 10^{-6}$ mbar and oxygen supply time of 75 s, resulting in oxygen dose of 75 L. Similarly to the first example, sharp (2x1)+(1x2) LEED pattern was observed and O1s intensity was measured by XPS, indicating formation of crystalline SOI structure also with those oxidation parameters.

[0037] In third example, basically similar to the first and the second examples, oxidation was carried out with oxidation temperature of 700 °C, using oxygen pressure of $1 \cdot 10^{-4}$ mbar and oxygen supply time of 1 s, resulting in an oxygen dose of about 100 to 200 L. After the oxidation, LEED image of the sample showed only a weak (1x1), indicating presence of excess oxygen, not incorporated into the Si bulk crystal and forming crystalline SiO_x, at the deposition surface. The sample was then annealed at a post-heating temperature of 700 °C for 10 minutes. The annealing resulted in sharp (2x1)+(1x2) LEED pattern, similar to that of FIG. 7b, and O1s intensity was measured by XPS, indicating again the formation of a crystalline silicon oxide layer beneath a crystalline silicon top layer.

[0038] The method 500 of FIG. 5 comprises an oxidation phase which may be carried out in accordance with any of the methods discussed above with reference to FIGs. 1 and 3. It comprises the operations 520, 530, 540 of providing the crystalline silicon

substrate in a vacuum chamber, heating it to an oxidation temperature, and supplying molecular oxygen into the vacuum chamber to oxidize the silicon substrate. Further, it may comprise one or both of the optional operations 510, 550 of cleaning the deposition surface of the silicon substrate, and annealing the silicon substrate with the silicon oxide layer formed therein.

[0039] Further, the method comprises, in operation 560, depositing a cap layer on the silicon top layer. The cap layer may comprise, for example, an oxide or nitride, and it may be amorphous or crystalline. The additional oxide layer may comprise, for example, silicon dioxide SiO_2 , aluminum oxide Al_2O_3 , hafnium oxide HfO_2 , or titanium oxide TiO_2 . In other embodiments, it may comprise, for example, mixed composition of hafnium oxide and titanium oxide $\text{HfO}_2 - \text{TiO}_2$, zirconium oxide ZrO_2 , cerium oxide CeO_2 , yttrium oxide Y_2O_3 , zirconium silicate ZrSiO_4 , hafnium silicate HfSiO_4 , aluminum oxide Al_2O_3 , hafnium silicon oxynitride HfSiON , hafnium silicon nitride, lanthanum oxide La_2O_3 , bismuth silicon oxide $\text{Bi}_4\text{Si}_2\text{O}_{12}$, tantalum oxide Ta_2O_5 , tungsten oxide WO_3 , lanthanum aluminum oxide LaAlO_3 , barium strontium oxide $\text{Ba}_{1-x}\text{Sr}_x\text{O}_3$, lead (II) titanate PbTiO_3 , barium titanate BaTiO_3 , strontium titanate SrTiO_3 , or any appropriate mixture thereof. The cap layer may have a thickness, for example, in the range of 1 to 500, 1 to 400, or 3 to 300 nm.

[0040] The cap layer may be deposited, for example, by atomic layer deposition ALD or chemical vapor deposition CVD. Thus, the overall method 500 may be carried out using a method in accordance with any of those discussed above with reference to FIGs. 1 and 3

for forming the SOI structure, followed by depositing the cap layer thereon, for example, by ALD or CVD.

[0041] The semiconductor structure 600 of FIG. 6 may be manufactured, for example, by the method 500 of FIG. 5. The semiconductor structure 600 comprises a SOI composition which may be in accordance with any of the semiconductor structures discussed above with reference to FIGs. 2 and 4. The SOI composition comprises a crystalline silicon base layer 603, a crystalline silicon oxide SiO_x layer 604 with a thickness of at least two molecular layers on the silicon base layer; and a crystalline silicon top layer 605 on the crystalline silicon oxide layer. The semiconductor structure 600 further comprises a cap layer 606 on the crystalline silicon top layer 605. The cap layer may comprise, for example, silicon dioxide SiO_2 , aluminum oxide Al_2O_3 , hafnium oxide HfO_2 , or titanium oxide TiO_2 . In other embodiments, it may comprise, for example, mixed composition of hafnium oxide and titanium oxide $\text{HfO}_2 - \text{TiO}_2$, zirconium oxide ZrO_2 , cerium oxide CeO_2 , or yttrium oxide Y_2O_3 , zirconium silicate ZrSiO_4 , hafnium silicate HfSiO_4 , aluminum oxide Al_2O_3 , hafnium silicon oxynitride HfSiON , hafnium silicon nitride, lanthanum oxide La_2O_3 , bismuth silicon oxide $\text{Bi}_4\text{Si}_2\text{O}_{12}$, tantalum oxide Ta_2O_5 , tungsten oxide WO_3 , lanthanum aluminum oxide LaAlO_3 , barium strontium oxide $\text{Ba}_{1-x}\text{Sr}_x\text{O}_3$, lead (II) titanate PbTiO_3 , barium titanate BaTiO_3 , strontium titanate SrTiO_3 , or any appropriate mixture thereof. The cap layer may have a thickness, for example, in the range of 1 to 500, 1 to 400, or 3 to 300 nm.

[0042] It has been found that for a semiconductor structure manufactured using a method in accordance

with any of those discussed above with reference to FIGs. 1, 3, and 5, the tunneling gap of the semiconductor structure, measurable by scanning tunneling spectroscopy (STS) is clearly higher than
5 for a clean surface of a Si bulk sample. For example, STS analysis has shown that oxidizing a Si(100)(2x1) surface at 600 °C with as low oxygen dose as 10 L may result in a tunneling gap having a width which is four times the width of the tunneling gap of a clean non-
10 oxidized Si (100)(2x1) reference surface. Due to the inherent property of STS being most sensitive to the outermost atomic layer of the sample to be investigated, the measured tunneling gap may be assumed not representing the SiO_x gap. This assumption
15 has been confirmed by STM analysis of samples, showing no presence of any oxygen on the surface thereof. Instead, it may be assumed that the oxygen incorporated within the bulk below the outermost Si surface causes bending of the valence and conductive
20 bands, increasing the band gap between the conductive band minimum (CBM) and the valence band maximum (VBM) at the outermost surface layers of the oxidized Si sample comprising the SOI structure. This effect is illustrated in FIG. 7a.

25 **[0043]** The effect of such band bending on the band structure in a semiconductor structure as that of FIG. 600, comprising a cap layer on the crystalline silicon top layer, is illustrated in FIG. 7b. As known in the art, in structures with an insulating oxide layer on a
30 crystalline Si substrate, there are typically interface defects at the insulator/Si interface. Those interface defects may cause undesired surface recombination of charge carriers. In a structure in

accordance with FIG. 6, the SiO_x - induced increase of the band gap (and the band bending) may "repel" charge carriers from the most defect-rich region of the structure, as illustrated in FIG. 7b by small balls
5 denoting the charge carriers, and an arrow denoting said repelling effect.

[0044] The presence of the assumed effect schematically illustrated in FIGs. 7a and 7b was investigated by analyzing, using a surface
10 recombination velocity (SRV) instrument of Aalto University, a test sample in accordance with the semiconductor structure 600 of FIG. 6 and a reference sample. The test sample was manufactured in accordance with the method of FIG. 5 using oxidation temperature
15 of 600 °C, and the reference sample was manufactured by oxidizing a Si substrate at room temperature. The reference sample was capped with a similar amorphous Al_2O_3 film, serving as a cap layer, as the test sample. The test sample provided clearly higher lifetime than
20 the reference sample, which may be seen confirming the assumed effect explained above with reference to FIGs. 7a and 7b.

[0045] In the examples discussed above with reference to FIGs. 1 to 7, planar silicon substrates
25 with one planar deposition surface, and planar semiconductor structures with a SOI layer structure are discussed. However, the methods discussed above may also be used for oxidizing silicon substrate structures having several deposition surfaces which
30 may be differently oriented and may have different crystal orientations. Consequently, three-dimensional SOI layer structures may be formed. Correspondingly, what is discussed above with regard to the planar

semiconductor structures illustrated in FIGs. 2 and 6 may be implemented also as semiconductor structures with three-dimensional SOI layer structures.

[0046] Semiconductor structures manufactured as described above with reference to FIGs 1, 3, and 5, as well as semiconductor structures as described above with reference to FIGs. 2, 4, and 6, may be used in any kinds of applications where SOI structures are useful. For example, those semiconductor structures may be used in field-effect transistors FETs, solar cells, and various components or barrier structures designed to guide current flow in a semiconductor device. Further, those semiconductor structures have also been found potentially useful for passivating various semiconductor surfaces.

[0047] A semiconductor structure as that illustrated in FIG. 6, having a cap layer on the crystalline silicon top layer, may be used, for example, for surface passivation and/or antireflection coating of a solar cell structure, or in the gate stack of a field-effect transistor FET. The advantageous surface recombination velocity characteristics may improve the performance of such semiconductor structures and devices. Similar semiconductor structure may also be used, for example, for electrically and/or chemically passivating a three dimensional structure, such as a nanostructure formed by etching, against changes induced by ambient conditions surrounding the structure.

[0048] In fourth example, two 5 mm x 10 mm rectangular pieces were diced from an n-type Si (100) wafer to serve as a Si sample substrate and a Si

reference substrate. The substrates were then cleaned in vacuum inside a vacuum chamber of a multi-chamber vacuum system by repeatedly rapidly heating them up to a cleaning temperature of 1100 °C.

5 [0049] Following this cleaning procedure, the Si sample substrate was subjected to a heating temperature of 650 °C, and an outer surface of the sample substrate was oxidized at an O₂ pressure of 1·10⁻⁷ mbar, resulting in an oxidation dose of 50 L, in
10 order to produce a SOI layer structure according to the invention, after which HfO₂ films with thicknesses of 25 nm were grown by ALD, using water and tetrakis(dimethylamido)hafnium(IV) (TDMAH) as the precursors, on the oxidized sample substrate and the
15 reference substrate.

[0050] After the deposition of HfO₂, circular gate-metal pads with diameters of 100 microns were deposited by sputtering 10 nm of chromium followed by 50 nm of gold through a shadow mask onto the HfO₂ films
20 in order to fabricate two metal-oxide-semiconductor (MOS) structures: a MOS capacitor sample and a MOS capacitor reference, comprising either the sample substrate or the reference substrate as the semiconductor, respectively. The MOS capacitor
25 structures were then taken out of the vacuum system and connected to an LCR meter, using conductive silver paste to form back contacts.

[0051] FIG. 8 shows capacitance-voltage (C-V) curves measured for the two different MOS capacitor
30 structures according to the fourth example. The C-V curves in FIGs. 8a and 8b correspond to measurements conducted on the MOS capacitor sample and the MOS

capacitor reference, respectively. Based on FIG. 8, it can be seen that a depletion-region capacitance step, occurring close to short-circuit conditions while shifting from negative to positive voltages, of the MOS capacitor reference is more structured (e.g., shouldered and/or gradual) than the corresponding step of the MOS capacitor sample. Such depletion region features may indicate a higher defect density in the MOS capacitor reference than in the MOS capacitor sample due to a crystalline SiO_x layer embedded inside the Si sample substrate. Additionally, based on the results, the cleaning procedure conducted at a temperature of 1100 °C may have resulted in band bending in the sample and reference substrates, affecting the shapes of the C-V curves.

[0052] In fifth example, a MOS capacitor sample and a MOS capacitor reference were prepared and connected to an LCR meter similarly to the fourth example discussed above. However, in contrast to the fourth example, the step of cleaning sample and reference substrates in vacuum was replaced by a standard RCA cleaning procedure. The sample and reference substrates were also subjected to additional post-metallization annealing at a temperature of 400 °C prior to the addition of silver paste to form the back contacts.

[0053] FIG. 9 shows capacitance-voltage (C-V) curves measured for the two different MOS capacitor structures according to the fifth example. The C-V curves in FIGs. 9a and 9b correspond to measurements conducted on the MOS capacitor sample and the MOS capacitor reference, respectively. In FIG. 9b, inversion capacitance of the reference sample is seen

to increase at negative voltages. This may be caused by a detrimental hole-inversion layer in the MOS capacitor reference; see e.g. O'Connor et al., Journal of Applied Physics 111, 124104, 2012. The hole-inversion layer may result from an inherent fixed negative charge in HfO_2 ; see e.g. Foster et al., Physical Review Letters 89, 225901, 2002. The hole-inversion layer, which hinders switching off the MOS capacitor reference, may be removable via the provision of a SOI layer structure, as shown in FIG. 9a, due to compensating fixed positive charge of SiO_x ; see e.g. Schmidt et al., Applied Physics A 86, 187, 2007. Such fixed positive charge in crystalline SiO_x may also be utilizable in various components or barrier structures designed to guide current flow (e.g., induced p-n junctions in p-type Si or diffusion barriers for holes) in a semiconductor device (e.g., a solar cell).

[0054] Although the subject matter has been described in language specific to structural features and/or methodological acts, it is to be understood that the subject matter defined in the appended claims is not necessarily limited to the specific features or acts described above. Rather, the specific features and acts described above are disclosed as example forms of implementing the claims.

[0055] It will be understood that the benefits and advantages described above may relate to one embodiment or may relate to several embodiments. The embodiments are not limited to those that solve any or all of the stated problems or those that have any or all of the stated benefits and advantages. It will

further be understood that reference to 'an' item refers to one or more of those items.

[0056] The term "comprising" is used in this specification to mean including the feature(s) or
5 act(s) followed thereafter, without excluding the presence of one or more additional features or acts.

[0057] It is to be noted that the embodiments of the claims are not limited to those discussed above, but further embodiments may exist within the scope of
10 the claims.