

SIGNALING PICTURE SIZE IN VIDEO CODING

[0001] This application claims the benefit of:

U.S. Provisional Application No. 61/508,659, filed July 17, 2011;

U.S. Provisional Application No. 61/530,819, filed September 2, 2011; and

U.S. Provisional Application No. 61/549,480 filed October 20, 2011, each of which are hereby incorporated by reference in their entirety.

TECHNICAL FIELD

[0002] This disclosure relates to the field of video coding.

BACKGROUND

[0003] Digital video capabilities can be incorporated into a wide range of devices, including digital televisions, digital direct broadcast systems, wireless broadcast systems, personal digital assistants (PDAs), laptop or desktop computers, tablet computers, e-book readers, digital cameras, digital recording devices, digital media players, video gaming devices, video game consoles, cellular or satellite radio telephones, so-called "smart phones," video teleconferencing devices, video streaming devices, and the like. Digital video devices implement video compression techniques, such as those described in the standards defined by MPEG-2, MPEG-4, ITU-T H.263, ITU-T H.264/MPEG-4, Part 10, Advanced Video Coding (AVC), the High Efficiency Video Coding (HEVC) standard presently under development, and extensions of such standards. Video devices may transmit, receive, encode, decode, and/or store digital video information more efficiently by implementing such video compression techniques.

[0004] Video compression techniques perform spatial (intra-picture) prediction and/or temporal (inter-picture) prediction to reduce or remove redundancy inherent in video sequences. For block-based video coding, a video slice (i.e., a video frame or a portion of a video frame) may be partitioned into video blocks, which may also be referred to as treeblocks, coding units (CUs) and/or coding nodes. Video blocks in an intra-coded (I) slice of a picture are encoded using spatial prediction with respect to reference samples in neighboring blocks in the same picture. Video blocks in an inter-coded (P or B) slice of a picture may use spatial prediction with respect to reference samples in neighboring blocks in the same picture or temporal prediction with respect to reference samples in

other reference pictures. Pictures may be referred to as frames, and reference pictures may be referred to a reference frames.

[0005] Spatial or temporal prediction results in a predictive block for a block to be coded. Residual data represents pixel differences between the original block to be coded and the predictive block. An inter-coded block is encoded according to a motion vector that points to a block of reference samples forming the predictive block, and the residual data indicating the difference between the coded block and the predictive block. An intra-coded block is encoded according to an intra-coding mode and the residual data. For further compression, the residual data may be transformed from the pixel domain to a transform domain, resulting in residual transform coefficients, which then may be quantized. The quantized transform coefficients, initially arranged in a two-dimensional array, may be scanned in order to produce a one-dimensional vector of transform coefficients, and entropy coding may be applied to achieve even more compression.

SUMMARY

[0006] In general, this disclosure describes techniques for coding video data included in pictures or frames of a video sequence. In particular, this disclosure describes techniques where a picture size for a group of pictures in the video sequence may be coded based on an aligned coding unit size for the video sequence. The aligned coding unit size for the video sequence may be selected from several possible coding unit sizes supported by the video coding scheme. The techniques of this disclosure include signaling an aligned coding unit size for one or more of the pictures in the video sequence, and coding a size for the one or more pictures as a multiple of the smallest coding unit.

[0007] In one example of the disclosure, a method for encoding video data comprises determining a smallest coding unit size for each of a plurality of pictures defining a video sequence, wherein a smallest coding unit size is selected from a plurality of possible coding unit sizes including a maximum possible coding unit size; determining an aligned coding unit size for the video sequence based on the plurality of possible coding unit sizes; determining a picture size associated with the video sequence, wherein the picture size associated with the video sequence is an multiple of the aligned

coding unit size; and signaling the aligned coding unit size value in sequence level syntax information.

[0008] In another example, a method of decoding video data comprises obtaining a coded video sequence including a first picture coded using a first smallest coding unit size and a second picture coded using second smallest coding unit size; obtaining a picture size of a decoded picture to be stored in a decoded picture buffer wherein the picture size is a multiple of one of the first coding unit size, the second coding unit size, or a maximum coding unit size; and storing the decoded picture in a decoded picture buffer.

[0009] In another example, an apparatus for encoding video data comprises a video encoding device configured to determine a smallest coding unit size for each of a plurality of pictures defining a video sequence, wherein a smallest coding unit size is selected from a plurality of possible coding unit sizes including a maximum possible coding unit size; determine an aligned coding unit size for the video sequence based on the plurality of possible coding unit sizes; determine a picture size associated with the video sequence, wherein the picture size associated with the video sequence is an multiple of the aligned coding unit size; and signal the aligned coding unit size value in sequence level syntax information.

[0010] In another example, an apparatus for decoding video data comprises a video decoding device configured to obtain a coded video sequence including a first picture coded using a first smallest coding unit size and a second picture coded using second smallest coding unit size; obtain a picture size of a decoded picture to be stored in a decoded picture buffer wherein the picture size is a multiple of one of the first coding unit size, the second coding unit size, or a maximum coding unit size; and store the decoded picture in a decoded picture buffer.

[0011] In another example, a device for encoding video data comprises means for determining a smallest coding unit size for each of a plurality of pictures defining a video sequence, wherein a smallest coding unit size is selected from a plurality of possible coding unit sizes including a maximum possible coding unit size; means for determining an aligned coding unit size for the video sequence based on the plurality of possible coding unit sizes; means for determining a picture size associated with the video sequence, wherein the picture size associated with the video sequence is an multiple of the aligned coding unit size; and means for signaling the aligned coding unit size value in sequence level syntax information.

[0012] In another example, a device for decoding video data comprises means for obtaining a coded video sequence including a first picture coded using a first smallest coding unit size and a second picture coded using second smallest coding unit size; means for obtaining a picture size of a decoded picture to be stored in a decoded picture buffer wherein the picture size is a multiple of one of the first coding unit size, the second coding unit size, or a maximum coding unit size; and means storing the decoded picture in a decoded picture buffer.

[0013] In another example, a computer-readable storage medium comprises instructions stored thereon that, when executed, cause a processor of a device for encoding video data to determine a smallest coding unit size for each of a plurality of pictures defining a video sequence, wherein a smallest coding unit size is selected from a plurality of possible coding unit sizes including a maximum possible coding unit size; determine an aligned coding unit size for the video sequence based on the plurality of possible coding unit sizes; determine a picture size associated with the video sequence, wherein the picture size associated with the video sequence is an multiple of the aligned coding unit size; and signal the aligned coding unit size value in sequence level syntax information.

[0014] In another example, a computer-readable storage medium comprises instructions stored thereon that, when executed, cause a processor of a device for decoding video data to obtain a coded video sequence including a first picture coded using a first smallest coding unit size and a second picture coded using second smallest coding unit size; obtain a picture size of a decoded picture to be stored in a decoded picture buffer wherein the picture size is a multiple of one of the first coding unit size, the second coding unit size, or a maximum coding unit size; and store the decoded picture in a decoded picture buffer.

[0015] The details of one or more examples are set forth in the accompanying drawings and the description below. Other features, objects, and advantages will be apparent from the description and drawings, and from the claims.

BRIEF DESCRIPTION OF DRAWINGS

[0016] FIG. 1 is a block diagram illustrating an example video encoding and decoding system.

[0017] FIG. 2 is a block diagram illustrating an example video encoder that may implement the techniques described in this disclosure.

[0018] FIG. 3 is a flowchart illustrating an example technique for encoding video data according to the techniques of this disclosure.

[0019] FIG. 4 is a block diagram illustrating an example video decoder that may implement the techniques described in this disclosure.

[0020] FIG. 5 is a flowchart illustrating an example technique for decoding video data according to the techniques of this disclosure.

DETAILED DESCRIPTION

[0021] A video sequence may include a group of pictures. Each picture in the group of pictures may have a smallest coding unit size. In one example, the smallest coding unit size may be a rectangle or square with one of the following pixel or sample dimensions: four pixels, eight pixels, 16 pixels, 32 pixels, and 64 pixels. In order to increase coding efficiency of the video sequence, it may be useful to determine the smallest coding unit size for the video sequence and specify a picture size for the group of pictures where the picture size is a multiple of the minimum of the smallest coding unit size for the video sequence.

[0022] FIG. 1 is a block diagram illustrating one example of a video encoding and decoding system 10 that may implement techniques of this disclosure. As shown in FIG. 1, system 10 includes a source device 12 that transmits encoded video to a destination device 16 via a communication channel 15. Source device 12 and destination device 16 may comprise any of a wide range of devices. In some cases, source device 12 and destination device 16 may comprise wireless communication device handsets, such as so-called cellular or satellite radiotelephones. The techniques of this disclosure, however, which apply generally to the encoding and decoding may be applied to non-wireless devices including video encoding and/or decoding capabilities. Source device 12 and destination device 16 are merely examples of coding devices that can support the techniques described herein.

[0023] In the example of FIG. 1, source device 12 may include a video source 20, a video encoder 22, a modulator/demodulator (modem) 23 and a transmitter 24. Destination device 16 may include a receiver 26, a modem 27, a video decoder 28, and a display device 30.

[0024] Video source 20 may comprise a video capture device, such as a video camera, a video archive containing previously captured video, a video feed from a video content provider or another source of video. As a further alternative, video source 20 may

generate computer graphics-based data as the source video, or a combination of live video, archived video, and computer-generated video. In some cases, if video source 20 is a video camera, source device 12 and destination device 16 may form so-called camera phones or video phones. In each case, the captured, pre-captured or computer-generated video may be encoded by video encoder 22.

[0025] In some examples (but not all cases), once the video data is encoded by video encoder 22, the encoded video information may then be modulated by modem 23 according to a communication standard, e.g., such as code division multiple access (CDMA), orthogonal frequency division multiplexing (OFDM) or any other communication standard or technique. The encoded and modulated data can then be transmitted to destination device 16 via transmitter 24. Modem 23 may include various mixers, filters, amplifiers or other components designed for signal modulation. Transmitter 24 may include circuits designed for transmitting data, including amplifiers, filters, and one or more antennas. Receiver 26 of destination device 16 receives information over channel 15, and modem 27 demodulates the information. The video decoding process performed by video decoder 28 may include reciprocal techniques to the encoding techniques performed by video encoder 22.

[0026] Communication channel 15 may comprise any wireless or wired communication medium, such as a radio frequency (RF) spectrum or one or more physical transmission lines, or any combination of wireless and wired media. Communication channel 15 may form part of a packet-based network, such as a local area network, a wide-area network, or a global network such as the Internet. Communication channel 15 generally represents any suitable communication medium, or collection of different communication media, for transmitting video data from source device 12 to destination device 16. Again, FIG. 1 is merely an example and the techniques of this disclosure may apply to video coding settings (e.g., video encoding or video decoding) that do not necessarily include any data communication between the encoding and decoding devices. In other examples, data could be retrieved from a local memory, streamed over a network, or the like. An encoding device may encode and store data to memory, and/or a decoding device may retrieve and decode data from memory. In many cases, the encoding and decoding is performed by unrelated devices that do not communicate with one another, but simply encode data to memory and/or retrieve and decode data from memory. For example, after video data has been encoded, the video data may be packetized for transmission or storage. The video data may be assembled into a video

file conforming to any of a variety of standards, such as the International Organization for Standardization (ISO) base media file format and extensions thereof, such as AVC.

[0027] In some cases, video encoder 22 and video decoder 28 may operate substantially according to a video compression standard such as the emerging HEVC standard. However, the techniques of this disclosure may also be applied in the context of a variety of other video coding standards, including some old standards, or new or emerging standards. Although not shown in FIG. 1, in some cases, video encoder 22 and video decoder 28 may each be integrated with an audio encoder and decoder, and may include appropriate MUX-DEMUX units, or other hardware and software, to handle encoding of both audio and video in a common data stream or separate data streams. If applicable, MUX-DEMUX units may conform to the ITU H.223 multiplexer protocol, or other protocols such as the user datagram protocol (UDP).

[0028] Video encoder 22 and video decoder 28 each may be implemented as one or more microprocessors, digital signal processors (DSPs), application specific integrated circuits (ASICs), field programmable gate arrays (FPGAs), discrete logic, software, hardware, firmware or combinations thereof. Each of video encoder 22 and video decoder 28 may be included in one or more encoders or decoders, either of which may be integrated as part of a combined encoder/decoder (CODEC) in a respective mobile device, subscriber device, broadcast device, server, or the like. In this disclosure, the term coder refers to an encoder, a decoder, or CODEC, and the terms coder, encoder, decoder and CODEC all refer to specific machines designed for the coding (encoding and/or decoding) of video data consistent with this disclosure. In this disclosure, the term “coding” may refer to either or both of encoding and/or decoding.

[0029] In some cases, source device 12 and destination device 16 may operate in a substantially symmetrical manner. For example, each of source device 12 and destination device 16 may include video encoding and decoding components. Hence, system 10 may support one-way or two-way video transmission between source device 12 and destination device 16, e.g., for video streaming, video playback, video broadcasting, or video telephony.

[0030] Video encoder 22 and video decoder 28 may perform predictive coding in which a video block being coded is compared to one or more predictive candidates in order to identify a predictive block. Video blocks may exist within individual video frames or pictures (or other independently defined units of video, such as slices). Frames, slices, portions of frames, groups of pictures, or other data structures may be defined as units

of video information that include video blocks. The process of predictive coding may be intra (in which case the predictive data is generated based on neighboring intra data within the same video frame or slice) or inter (in which case the predictive data is generated based on video data in previous or subsequent frames or slices). Video encoder 22 and video decoder 28 may support several different predictive coding modes. Video encoder 22 may select a desirable video coding mode. In predictive coding, after a predictive block is identified, the differences between the current video block being coded and the predictive block are coded as a residual block, and prediction syntax (such as a motion vector in the case of inter coding, or a predictive mode in the case of intra coding) is used to identify the predictive block. In some cases, the residual block may be transformed and quantized. Transform techniques may comprise a DCT process or conceptually similar process, integer transforms, wavelet transforms, or other types of transforms. In a DCT process, as an example, the transform process converts a set of pixel values (e.g., residual pixel values) into transform coefficients, which may represent the energy of the pixel values in the frequency domain. Video encoder 22 and video decoder 28 may apply quantization to the transform coefficients. Quantization generally involves a process that limits the number of bits associated with any given transform coefficient.

[0031] Following transform and quantization, video encoder 22 and video decoder 28 may perform entropy coding on the quantized and transformed residual video blocks. Video encoder 22 may generate syntax elements as part of the encoding process to be used by video decoder 28 in the decoding process. Video encoder 22 may also entropy encode syntax elements and include syntax elements in the encoded bitstream. In general, entropy coding comprises one or more processes that collectively compress a sequence of quantized transform coefficients and/or other syntax information. Video encoder 22 and video decoder 28 may perform scanning techniques on the quantized transform coefficients in order to define one or more serialized one-dimensional vectors of coefficients from two-dimensional video blocks. The scanned coefficients may then entropy coded along with any syntax information, e.g., via content adaptive variable length coding (CAVLC), context adaptive binary arithmetic coding (CABAC), or another entropy coding process.

[0032] In some examples, as part of the encoding process, video encoder 22 may decode encoded video blocks in order to generate the video data that is used for subsequent prediction-based coding of subsequent video blocks. This is often referred

to as a decoding loop of the encoding process, and generally mimics the decoding that is performed by a decoder device. In the decoding loop of an encoder or a decoder, filtering techniques may be used to improve video quality, and e.g., smooth pixel boundaries and possibly remove artifacts from decoded video. This filtering may be in-loop or post-loop. With in-loop filtering, the filtering of reconstructed video data occurs in the coding loop, which means that the filtered data is stored by an encoder or a decoder for subsequent use in the prediction of subsequent image data. In contrast, with post-loop filtering the filtering of reconstructed video data occurs out of the coding loop, which means that unfiltered versions of the data are stored by an encoder or a decoder for subsequent use in the prediction of subsequent image data. The loop filtering often follows a separate deblock filtering process, which typically applies filtering to pixels that are on or near boundaries of adjacent video blocks in order to remove blockiness artifacts that manifest at video block boundaries.

[0033] Efforts are currently in progress to develop a new video coding standard, currently referred to as High Efficiency Video Coding (HEVC). The upcoming standard is also referred to as H.265. A recent draft of the HEVC standard, referred to as “HEVC Working Draft 3” or “WD3,” is described in document JCTVC-E603, Wiegand et al., “High efficiency video coding (HEVC) text specification draft 3,” Joint Collaborative Team on Video Coding (JCT-VC) of ITU-T SG16 WP3 and ISO/IEC JTC1/SC29/WG11, 5th Meeting: Geneva, CH, 16-23 March, 2011, which is hereby incorporated by reference in its entirety. The standardization efforts are based on a model of a video coding device referred to as the HEVC Test Model (HM). The HM presumes several capabilities of video coding devices over devices configured to code video data according to ITU-T H.264/AVC. For example, whereas H.264 provides nine intra-prediction encoding modes, HM provides as many as thirty-four intra-prediction encoding modes. Video encoder 22 may operate on blocks of video data consistent with the HEVC standard and HEVC Test Model.

[0034] The HEVC standard includes specific terms and block sizes for blocks of video data. In particular, HEVC includes the terms largest coding unit (LCU), coding unit (CU), prediction unit (PU), and transform unit (TU). LCUs, CUs, PUs, and TUs are all video blocks within the meaning of this disclosure. This disclosure also uses the term block to refer to any of a LCU, CU, PU, or TU. In HEVC, syntax elements may be defined at the LCU level, the CU level, the PU level and the TU level. In HEVC, an LCU refers to the largest sized coding unit which is a largest coding unit in terms of

number of pixels supported in a given situation. In general, in HEVC a CU has a similar purpose to a macroblock of H.264, except that a CU does not have a size distinction. Thus, a CU may be split into sub-CUs and an LCU may be partitioned into smaller CUs. Further, the CUs may be partitioned into prediction units (PUs) for purposes of prediction. A PU may represent all or a portion of the corresponding CU, and may include data for retrieving a reference sample for the PU. PUs may have square or rectangular shapes. TUs represent a set of pixel difference values or pixel residuals that may be transformed to produce transform coefficients, which may be quantized. Transforms are not fixed in the HEVC standard, but are defined according to transform unit (TU) sizes, which may be the same size as a given CU, or possibly smaller.

[0035] In HEVC, an LCU may be associated with a quadtree data structure. Further, in some examples residual samples corresponding to a CU may be subdivided into smaller units using a quadtree partitioning scheme which includes a quadtree structure known as "residual quad tree" (RQT). In general, a quadtree data structure includes one node per CU, where a root node may correspond to the LCU. For example, CU₀ may refer to the LCU, and CU₁ through CU₄ may comprise sub-CUs of the LCU. If a CU is split into four sub-CUs, the node corresponding to the CU includes four leaf nodes, each of which corresponds to one of the sub-CUs. Each node of the quadtree data structure may provide syntax data for the corresponding CU. For example, a node in the quadtree may include a split flag in the CU-level syntax to indicate whether the CU corresponding to the node is split into sub-CUs. Syntax elements for a CU may be defined recursively, and may depend on whether the CU is split into sub-CUs. If a CU is not split further, it is referred to as a leaf-CU. In this disclosure, four sub-CUs of a leaf-CU may also be referred to as leaf-CUs although there is no explicit splitting of the original leaf-CU. For example, if a CU at 16x16 size is not split further, the four 8x8 sub-CUs will also be referred to as leaf-CUs although the 16x16 CU was never split.

[0036] The leaf nodes or leaf-CUs of the RQT may correspond to TUs. That is, a leaf-CU may include a quadtree indicating how the leaf-CU is partitioned into TUs. A leaf-CU may include one or more transform units (TUs). This disclosure may refer to the quadtree indicating how an LCU is partitioned as a CU quadtree and the quadtree indicating how a leaf-CU is partitioned into TUs as a TU quadtree. The root node of a TU quadtree generally corresponds to a leaf-CU, while the root node of a CU quadtree generally corresponds to an LCU. TUs of the TU quadtree that are not split are referred

to as leaf-TUs. A split flag may indicate whether a leaf-CU is split into four transform units. Then, each transform unit may be split further into four sub TUs. When a TU is not split further, it may be referred to as a leaf-TU.

[0037] Further, the leaf nodes or leaf-CUs may include one or more prediction units (PUs). For example, when the PU is inter-mode encoded, the PU may include data defining a motion vector for the PU. The data defining the motion vector may describe, for example, a horizontal component of the motion vector, a vertical component of the motion vector, a resolution for the motion vector (e.g., one-quarter pixel precision or one-eighth pixel precision), a reference frame to which the motion vector points, and/or a reference list (e.g., list 0 or list 1) for the motion vector. Data for the leaf-CU defining the PU(s) may also describe, for example, partitioning of the CU into one or more PUs. Partitioning modes may differ depending on whether the CU is uncoded, intra-prediction mode encoded, or inter-prediction mode encoded. For intra coding, a PU may be treated the same as a leaf transform unit described below.

[0038] Generally, for intra coding in HEVC, all the leaf-TUs belonging to a leaf-CU share the same intra prediction mode. That is, the same intra-prediction mode is generally applied to calculate predicted values for all TUs of a leaf-CU. For intra coding, video encoder 22 may calculate a residual value for each leaf-TU using the intra prediction mode, as a difference between the portion of the predictive values corresponding to the TU and the original block. The residual value may be transformed, quantized, and scanned. For inter coding in HEVC, video encoder 22 may perform prediction at the PU level and may calculate a residual for each PU. The residual values corresponding to a leaf-CU may be transformed, quantized, and scanned. For inter coding, a leaf-TU may be larger or smaller than a PU. For intra coding, a PU may be collocated with a corresponding leaf-TU. In some examples, the maximum size of a leaf-TU may be the size of the corresponding leaf-CU.

[0039] As described above, the HEVC standard allows for transformations according to transformation units (TUs), which may be different for different CUs. The TUs are typically sized based on the size of PUs within a given CU defined for a partitioned LCU, although this may not always be the case. The TUs are typically the same size or smaller than the PUs. Pixel difference values associated with the TUs may be transformed to produce transform coefficients, which may be quantized. Further, quantization may be applied according to a quantization parameter (QP) defined at the LCU level. Accordingly, the same level of quantization may be applied to all transform

coefficients in the TUs associated with different PUs of CUs within an LCU. However, rather than signal the QP itself, a change or difference (i.e., a delta) in the QP may be signaled with the LCU to indicate the change in QP relative to that of a previous LCU.

[0040] Video encoder 22 may perform video encoding of pictures, frames, slices, portions of frames, groups of pictures, or other video data by using LCUs, CUs, PUs and TUs defined according to the HEVC standard as units of video coding information.

[0041] For example, video encoder 22 may encode one or more pictures of video data comprising largest coding units (LCUs), wherein the LCUs are partitioned into a set of block-sized coded units (CUs) according to a quadtree partitioning scheme. Video encoder 22 and video decoder 28 may use CUs that have varying sizes consistent with the HEVC standard. For example, video encoder 22 may use possible CU sizes of 64x64, 32x32, 16x16, 8x8 and 4x4 pixels. For a given video sequence, video encoder 22 may use a maximum CU size of 64x64 pixels for all pictures in the video sequence while some pictures in the video sequence may be encoded using a smallest possible CU size of 4x4 pixels while other pictures in the video sequence may be encoded using a smallest CU size of 8x8 pixels.

[0042] As described above, references in this disclosure to a CU may refer to a largest coding unit of a picture or a sub-CU of an LCU. Video encoder 22 may split an LCU into sub-CUs, and each sub-CU may be further split into sub-CUs. Video encoder 22 may include syntax data for a bitstream defined to indicate a maximum number of times an LCU is split. The number of time a LCU is split may be referred to as CU depth.

[0043] Further, video encoder 22 may also define a smallest coding unit (SCU) for each picture in a video sequence. An SCU may refer to the smallest coding unit size used to code a picture when several possible CU sizes are available. For example, video encoder 22 may be configured to use one of possible CU sizes 64x64, 32x32, 16x16, 8x8 and 4x4 pixels to encode pictures in a video sequence. In one example, all pictures in the video sequence may be encoded using the same SCU size, e.g., 4x4 pixels or 8x8 pixels. In other examples, some pictures in the video sequence may be encoded using a SCU size of 4x4 pixels while other pictures in the video sequence may be encoded using a SCU size of 8x8 pixels. Thus, in this example, pictures in the video sequence may have respective SCUs of 4x4 pixels and 8x8 pixels, i.e., the SCU size may change among frames. Video encoder 22 may determine a minimum SCU or a maximum SCU for a video sequence. In this example, the minimum SCU would be 4x4, while the maximum SCU would be 8x8.

[0044] Video encoder 22 may include various levels of syntax data within a bitstream that defines sizes of LCUs, CUs, PUs, TUs, and SCUs. For example, video encoder 22 may signal the size of LCU using sequence level syntax.

[0045] In addition to signaling the size of CUs used to encode a picture in a video sequence, video encoder 22 may use various techniques to signal the size of a picture in the video sequence. The size of a picture associated with a video sequence may be equal to a picture size of a decoded picture stored in a decoded picture buffer (DPB). Pictures may have a unit size, such as a block of a selected height and width. The picture size may be picture sizes supported by HEVC or another video standard e.g., picture sizes may include 320x240, 1920x1080, and 7680x4320. Further, video encoder 22 may signal syntax elements for coding texture view components in a slice header. Thus, video encoder 22 may signal the size of a picture associated with a video sequence and/or a minimum smallest coding unit size associated with the video sequence using various syntax elements. Likewise, video decoder 28 may obtain various syntax elements indicating the size of a picture associated with a coded video sequence and/or a minimum smallest coding unit size associated with the coded video sequence and use such syntax elements in decoding the coded video sequence. In one example, video encoder 22 may signal the minimum smallest coding unit size and the size of a picture associated with a video sequence in sequence level syntax information wherein the picture size is a multiple of the minimum smallest coding unit size. In one example, video decoder 28 may obtain a coded video sequence including one or more coded pictures and a minimum smallest coding unit size for the video sequence in sequence level syntax information. Video decoder 28 may decode the coded pictures in the coded video sequence and store the decoded pictures in a decoded picture buffer with a picture size equal to a multiple of the minimum smallest coding unit size.

[0046] In some video compression techniques that utilize fixed sized macroblocks (e.g., 16x16), the size of a picture may be signaled in the unit of macroblocks. When the width or height is not equal to a multiple of the fixed sized macroblock, a cropping window may be used. For example, a 1920x1080 picture can be coded as 1920x1088 in the bitstream, but the cropping window signals the real window to make the picture to be displayed as 1920x1080. In other techniques, the size of a picture may be signaled in the unit of pixel. One example of signaling the size of a picture in the unit of pixel is provided by the HEVC standard.

[0047] In one example, video encoder 22 and video decoder 28 may code video data where a size of a coded picture in a picture sequence is defined in terms of a particular type of coded unit (CU). The particular types of coded blocks may be a LCU, a SCU, a minimum smallest CU, or a maximum smallest CU of each picture in the sequence of pictures, as described above. More specifically, video encoder 22 may indicate a unit used to signal a size of a picture relative to a size of a coding unit (CU) of the picture. In one example, the unit may be equal to a size of the smallest CU size that is allowed in the coded video sequence. In some cases, the smallest CU size is the same for all pictures in the video sequence. In other cases, the smallest CU size of each picture in the video sequence may be different. In that case, the smallest CU size for each picture in a video sequence may not be smaller than the smallest possible CU size for the video sequence. In another example, the unit indicated by video encoder 22 may be equal to a size of the largest coding unit (LCU) for a group of pictures. In some examples, a cropping window may be applied to the picture by video encoder 22 or video decoder 28 to reduce the size of the picture. The cropping window may crop at least one of a right side or a bottom side of a picture, for example.

[0048] In another example, video encoder 22 may signal a picture size relative to an aligned CU (ACU) size. An aligned CU size may be a CU size that is used to specify a picture size of a decoded picture stored in a decoded picture buffer (DPB). Such a picture size may have a width and height both as multiplications of the width and height of the aligned CU size. Similarly, the picture height may be a multiplication of a height of an aligned CU. The size (width and height) of the aligned CU can be signaled in the same way as in the other alternatives. For example video encoder 22 may signal an aligned CUs at various levels of syntax.

[0049] An ACU size may defined accord to the following examples: if all pictures in a video sequence have the same SCU size, the ACU may be defined as the SCU size. If, on the other hand, pictures in the video sequence have different SCU sizes, the ACU may be defined as the maximum or minimum SCU size among all pictures. Regardless of how the ACU is defined, the ACU size may be explicitly signaled by video encoder 22 in a sequence parameter set (SPS) or picture parameter set (PPS) associated with the video sequence. In some cases, the ACU size may be restricted such that it is equal to or less than the LCU size for a video sequence and equal to or larger than a SCU size for a video sequence.

[0050] Further, in some examples, video encoder 22 may signal a picture size in a unit of LCU or a unit of SCU. In some examples, the unit used to signal a size of a coded picture may be signaled in a SPS. This unit may be equal to the size of a smallest CU size that is allowed for the coded video sequence. In the PPS, the relative size of the smallest CU size for pictures referring to this PPS may be signaled by video encoder 22. In the case where all pictures in a video sequence have the same SCU size, additional signaling of the relative size of the smallest CU may not be necessary in the PPS. In the case where the smallest CU size varies between pictures in a video sequence, a relative smallest CU size for a portion of the pictures in the video sequence may be signaled in the PPS where the relative smallest CU size is larger than the minimum smallest CU for the video sequence. The relative smallest CU size may be signaled in the PPS as a difference between the relative smallest CU size for the portion of the pictures and the minimum smallest CU size for the video sequence.

[0051] Alternatively, the picture size can be signaled by video encoder 22 with a unit of LCU in SPS. However, since the cropping window can be further signaled by video encoder 22, using the cropping window may help video decoder identify the picture size, as long as the ACU size is known.

[0052] Alternatively, when the SCU size varies for the pictures in the video sequence, the unit may be equal to the size of a maximum smallest CU size allowed in pictures in the coded video sequence. In an example where the maximum CU size is 64x64 pixels, and some pictures have CU size of 4x4 pixels while others have a smallest CU size of 8x8 pixels, the unit of the picture size may be 8x8 pixels. In this example, if a picture has a size of 64x65 pixels, a picture size would be signaled by video encoder 22 as 8 times 8 pixels by 9 times 8 pixels. Pixels in a picture that exceeded the 64x65 pixel size may be cropped using frame cropping syntax elements.

[0053] In some examples, a maximum CU size is 64x64 pixels and some pictures have a smallest possible CU size of 4x4 pixels while others have a smallest CU size of 8x8 pixels. For this example, if the particular type of CU is the minimum possible smallest CU, the unit for the picture size is of 4x4 pixels. Continuing with the example, if the particular type of CU is the maximum possible smallest CU, the unit for the picture size is of 8x8 pixels.

[0054] Tables 1-7 below provide example syntax that may be implemented by video encoder 22 and video decoder 28 to perform techniques described herein. Example

syntax may be implemented by video encoder 22 and video decoder 28 using hardware, software, firmware, or any combination thereof.

[0055] As described above, video encoder 22 may signal the unit used to signal the size of the coded picture in the SPS (Sequence Parameter set). In one example, this unit may be equal to the size of the smallest CU size that is allowed in the coded video sequence. In this example, if the smallest CU size may vary in a coded bitstream between pictures in a group of pictures, the smallest CU size shall not be smaller than the size of this unit. Table 1 below provides an example of SPS raw byte sequence payload (RBSP) syntax used to signal the minimum smallest CU size for the coded picture in the video sequence. In the picture parameter set (PPS), the relative size of the smallest CU size for pictures referring to this PPS may be signaled.

seq_parameter_set_rbsp() {	Descriptor
profile_idc	u(8)
reserved_zero_8bits /* equal to 0 */	u(8)
level_idc	u(8)
seq_parameter_set_id	ue(v)
max_temporal_layers_minus1	u(3)
 pic_width_in_luma_samples	u(16)
 pic_height_in_luma_samples	u(16)
bit_depth_luma_minus8	ue(v)
bit_depth_chroma_minus8	ue(v)
pcm_bit_depth_luma_minus1	u(4)
pcm_bit_depth_chroma_minus1	u(4)
log2_max_frame_num_minus4	ue(v)
pic_order_cnt_type	ue(v)
if(pic_order_cnt_type == 0)	
log2_max_pic_order_cnt_lsb_minus4	ue(v)
else if(pic_order_cnt_type == 1) {	
delta_pic_order_always_zero_flag	u(1)
offset_for_non_ref_pic	se(v)
num_ref_frames_in_pic_order_cnt_cycle	ue(v)
for(i = 0; i < num_ref_frames_in_pic_order_cnt_cycle; i++)	
offset_for_ref_frame[i]	se(v)
}	
max_num_ref_frames	ue(v)
gaps_in_frame_num_value_allowed_flag	u(1)
log2_min_max_coding_block_size_minus3	ue(v)
 log2_diff_max_min_coding_block_size	ue(v)
log2_min_transform_block_size_minus2	ue(v)
log2_diff_max_min_transform_block_size	ue(v)
log2_min_pcm_coding_block_size_minus3	ue(v)
max_transform_hierarchy_depth_inter	ue(v)
max_transform_hierarchy_depth_intra	ue(v)
chroma_pred_from_luma_enabled_flag	u(1)
loop_filter_across_slice_flag	u(1)
sample_adaptive_offset_enabled_flag	u(1)
adaptive_loop_filter_enabled_flag	u(1)
pcm_loop_filter_disable_flag	u(1)

cu_qp_delta_enabled_flag	u(1)
temporal_id_nesting_flag	u(1)
rbsp_trailing_bits()	
}	

Table 1: Sequence parameter set RBSP syntax

[0056] In Table 1, syntax element **log2_max_coding_block_size_minus3** may specify the maximum size of a coding block. A variable Log2MaxCUsSize may be set equal to:

$$\text{log2_max_coding_block_size_minus3} + 3.$$

[0057] In Table 1, syntax element

log2_diff_max_pic_aligned_min_coding_block_size may specify the difference between the minimum size of a coding block in the whole coded video sequence and the maximum size of a coding block. In some cases, a group of pictures may be defined such that a picture in a group of pictures shall not have a smallest coding CU size smaller than the difference value.

[0058] A variable Log2SeqMinCUsSize may be set equal to

$$\text{log2_minmax_coding_block_size_minus3} + 3 -$$

$$\text{log2_diff_max_pic_aligned_min_coding_block_size}.$$

[0059] This value may range from 0 to **log2_max_coding_block_size_minus3**. Variables Log2MaxCUsSize and Log2SeqMinCUsSize may be used by video encoder 22 and video decoder 28 to process for video coding.

[0060] It should be noted that Table 1 includes syntax elements **pic_width_in_luma_samples**, **pic_height_in_luma_samples**, and **log2_min_coding_block_size_minus3**, which appear in Table 1 with a strikethrough. These syntax elements represent an alternative example where the size of a picture may be signaled by the video encoder 22 in the unit of pixels. In one example, where a picture size has a width and height both as multiplications of the width and height of the ACU size, where the ACU size is equal to the minimum SCU of a video sequence, as described above, video decoder 28 may determine whether a bitstream is conforming based on whether a condition the values of **pic_width_in_luma_samples**, **pic_height_in_luma_samples**, are integer multiples of **log2_min_coding_block_size_minus3**.

[0061] Table 2, below, provides another example of a SPS RBSP syntax, in accordance with the techniques that may be performed by video encoder 22 and video decoder 28.

seq_parameter_set_rbsp() {	Descriptor
profile_idc	u(8)
reserved_zero_8bits /* equal to 0 */	u(8)
level_idc	u(8)
seq_parameter_set_id	ue(v)
max_temporal_layers_minus1	u(3)
pic_width_in_aligned_scu	ue(v)
pic_height_in_aligned_scu	ue(v)
bit_depth_luma_minus8	ue(v)
bit_depth_chroma_minus8	ue(v)
pcm_bit_depth_luma_minus1	u(4)
pcm_bit_depth_chroma_minus1	u(4)
log2_max_frame_num_minus4	ue(v)
pic_order_cnt_type	ue(v)
if(pic_order_cnt_type == 0)	
log2_max_pic_order_cnt_lsb_minus4	ue(v)
else if(pic_order_cnt_type == 1) {	
delta_pic_order_always_zero_flag	u(1)
offset_for_non_ref_pic	se(v)
num_ref_frames_in_pic_order_cnt_cycle	ue(v)
for(i = 0; i < num_ref_frames_in_pic_order_cnt_cycle; i++)	
offset_for_ref_frame[i]	se(v)
}	
max_num_ref_frames	ue(v)
gaps_in_frame_num_value_allowed_flag	u(1)
log2_max_coding_block_size_minus3	ue(v)
log2_diff_max_pic_aligned_min_coding_block_size	ue(v)
log2_min_transform_block_size_minus2	ue(v)
log2_diff_max_min_transform_block_size	ue(v)
log2_min_pcm_coding_block_size_minus3	ue(v)
max_transform_hierarchy_depth_inter	ue(v)
max_transform_hierarchy_depth_intra	ue(v)
chroma_pred_from_luma_enabled_flag	u(1)
loop_filter_across_slice_flag	u(1)
sample_adaptive_offset_enabled_flag	u(1)
adaptive_loop_filter_enabled_flag	u(1)
pcm_loop_filter_disable_flag	u(1)
cu_qp_delta_enabled_flag	u(1)
temporal_id_nesting_flag	u(1)

rbsp_trailing_bits()	
}	

Table 2: Sequence parameter set RBSP syntax

[0062] According to Table 2, a width and height of a picture may be indicated by video encoder 22 relative to a width and height of an aligned CU. As described above, an aligned CU may be a CU that is used by video encoder 22 and video decoder 28 to specify a picture size. That is, the picture width may be a multiplication of a width of an aligned CU. As described above, the aligned CU size may be a size used to specify a picture size of a decoded picture stored in a decoded picture buffer (DPB). In some examples, a picture may contain one or more complete aligned CUs. In some examples, the aligned CU is an aligned smallest CU (SCU).

[0063] Table 2 specifies a height of a picture as **pic_height_in_aligned_scu** and a width of the picture as **pic_width_in_aligned_scu**. **pic_width_in_aligned_cu** may specify the width of the pictures in the coded video sequence in a unit of aligned CUs. **pic_height_in_aligned_cu** may specify the height of the pictures in the coded video sequence in a unit of aligned CUs.

[0064] **log2_max_coding_block_size_minus3** may specify the maximum size of a coding block. A variable **Log2MaxCUsSize** may be set equal to **log2_max_coding_block_size_minus3 + 3**.

[0065] **log2_diff_max_pic_aligned_min_coding_block_size** may specify a difference between a minimum size of a coding block in the whole coded video sequence and a maximum size of a coding block. In some examples, any picture may not have a smallest coding CU size smaller than that.

[0066] Table 3 below provides additional syntax elements for PPS RBSP that may be implemented by video encoder 22 and video decoder 28 in conjunction with SPS RBSP provided in either Table 1 or Table 2.

pic_parameter_set_rbsp() {	Descriptor
pic_parameter_set_id	ue(v)
seq_parameter_set_id	ue(v)
entropy_coding_mode_flag	u(1)
num_temporal_layer_switching_point_flags	ue(v)
for(i = 0; i < num_temporal_layer_switching_point_flags; i++)	
temporal_layer_switching_point_flag[i]	u(1)
num_ref_idx_l0_default_active_minus1	ue(v)
num_ref_idx_l1_default_active_minus1	ue(v)
pic_init_qp_minus26 /* relative to 26 */	se(v)
pic_scu_size_delta	ue(v)
constrained_intra_pred_flag	u(1)
slice_granularity	u(2)
shared_pps_info_enabled_flag	u(1)
if(shared_pps_info_enabled_flag)	
if(adaptive_loop_filter_enabled_flag)	
alf_param()	
if(cu_qp_delta_enabled_flag)	
max_cu_qp_delta_depth	u(4)
rbbsp_trailing_bits()	
}	

Table 3: Picture parameter set RBSP syntax

[0067] In Table 3, **pic_scu_size_delta** may specify a minimum size of a coding unit of the pictures referring to this picture parameter set. This value may range from 0 to $\log_2_diff_max_pic_aligned_min_coding_block_size$.

[0068] The variable **Log2MinCUSize** may be set equal to **Log2SeqMinCUSize** + **pic_scu_size_delta**. Alternatively, if the size of the aligned CU is a maximum of the smallest CU sizes of all the pictures, the variable **Log2MinCUSize** may be set equal to **Log2SeqMinCUSize** - **pic_scu_size_delta**. Alternatively, if the aligned CU size can be of any possible CU size, in this case, **pic_scu_size_delta** can be a signed value (se(v)) and the variable **Log2MinCUSize** may be set equal to **Log2SeqMinCUSize** - **pic_scu_size_delta**.

[0069] In addition to the examples described above, in one example, an LCU size for a video sequence may be defined as N by N and the ACU size, selected according to one of the examples described above, may be defined as M by M. In this case, the picture

size may be signaled by video encoder 22 in the unit of LCU size may be defined as WL by HL. Thus, the picture size with respect to the aligned CU size may be derived by video decoder 28 according to the following equation:

$(WL*N - \text{crop_right_offset} + M - 1) / M * M$ by $(HL*N - \text{crop_bottom_offset} + M - 1) / M * M$, wherein crop_right_offset and $\text{crop_bottom_offset}$ are signaled by video encoder 22 in the cropping window and are the numbers of pixels cropped from the right and bottom boundary, respectively. It should be noted that WL may be the value of the pic_width_in_LCU and WH is the value of pic_height_in_LCU in the Table 5 below. It should also be noted that the operations (e.g., divisions) in the equation above may be integer calculations.

[0070] Table 4 below provides another example of additional syntax elements for $\text{seq_parameter_set_rbp}()$. In this example, the sizes of one or more pictures may be signaled by video encoder 22 relative to a size of a largest coding unit (LCU). The sizes of the one or more pictures may be signaled by video encoder 22 in the sequence parameter set, for example.

[0071] The picture size may also be signaled by video encoder 22 with a $\text{num_right_offset_ACU}$ and $\text{num_bottom_offset_ACU}$, so the picture size is $(WL*N - M * \text{num_right_offset_ACU})$ by $(HL*N - M * \text{num_bottom_offset_ACU})$. These two parameters can be signaled in SPS or PPS. The decoded picture is to be stored in the decoded picture buffer with a picture with respect to the aligned CU, which is $(WL*N - \text{num_crop_acu_right} * M)$ by $(HL*N - \text{num_crop_acu_right} * M)$.

[0072] In some examples, a cropping window may be further signaled by video encoder 22. A cropping window may define at least a right side or a bottom side of a picture or other to be cropped. However, since the cropping window can be further signaled, the cropping window may be used to identifying the picture size when the aligned CU size is known.

seq_parameter_set_rbsp() {	Descriptor
profile_idc	u(8)
reserved_zero_8bits /* equal to 0 */	u(8)
level_idc	u(8)
seq_parameter_set_id	ue(v)
max_temporal_layers_minus1	u(3)
pic_width_in_LCU	ue(v)
pic_height_in_LCU	ue(v)
num_crop_acu_right	ue(v)
num_crop_acu_bottom	ue(v)
bit_depth_luma_minus8	ue(v)
bit_depth_chroma_minus8	ue(v)
pcm_bit_depth_luma_minus1	u(4)
pcm_bit_depth_chroma_minus1	u(4)
log2_max_frame_num_minus4	ue(v)
pic_order_cnt_type	ue(v)
if(pic_order_cnt_type == 0)	
log2_max_pic_order_cnt_lsb_minus4	ue(v)
else if(pic_order_cnt_type == 1) {	
delta_pic_order_always_zero_flag	u(1)
offset_for_non_ref_pic	se(v)
num_ref_frames_in_pic_order_cnt_cycle	ue(v)
for(i = 0; i < num_ref_frames_in_pic_order_cnt_cycle; i++)	
offset_for_ref_frame[i]	se(v)
}	
max_num_ref_frames	ue(v)
gaps_in_frame_num_value_allowed_flag	u(1)
log2_max_coding_block_size_minus3	ue(v)
log2_diff_max_pic_aligned_min_coding_block_size	ue(v)
log2_min_transform_block_size_minus2	ue(v)
log2_diff_max_min_transform_block_size	ue(v)
log2_min_pcm_coding_block_size_minus3	ue(v)
max_transform_hierarchy_depth_inter	ue(v)
max_transform_hierarchy_depth_intra	ue(v)
chroma_pred_from_luma_enabled_flag	u(1)
loop_filter_across_slice_flag	u(1)
sample_adaptive_offset_enabled_flag	u(1)
adaptive_loop_filter_enabled_flag	u(1)
pcm_loop_filter_disable_flag	u(1)
cu_qp_delta_enabled_flag	u(1)

temporal_id_nesting_flag	u(1)
frame_cropping_flag	u(1)
if(frame_cropping_flag) {	
frame_crop_left_offset	ue(v)
frame_crop_right_offset	ue(v)
frame_crop_top_offset	ue(v)
frame_crop_bottom_offset	ue(v)
}	
rbsp_trailing_bits()	
}	

Table 4: Sequence parameter set RBSP syntax

[0073] In the example show in Table 4, a size of a picture in terms of width and height are given in terms of a largest coding unit (LCU). That is, **pic_width_in_LCU** may specify a size in pixels of one or more pictures relative to an LCU. Similarly, **pic_height_in_LCU** may specify a size in pixels of one or more pictures relative to an LCU. The syntax element **num_crop_acu_right** may be signaled in the cropping window and define a number of pixels to be cropped on a right side of a picture or other video block. Similarly, the syntax element **num_crop_acu_bottom** may be signaled in the cropping window and define a number of pixels to be cropped on a bottom side of a picture or other video block. In other examples, other sides of cropping windows are signaled.

[0074] An example is provided for illustrative purposes only. In this example, the LCU size is N by N and the aligned CU size is M by M. The picture size is signaled in terms of a unit of LCU size is given as WL by HL. In this example, WL is the value of **pic_width_in_LCU** and HL is the value of **pic_height_in_LCU**. **Crop_right_offset** may define a number of pixels to crop on a right side, and may be equal to **num_crop_acu_right**. **Crop_bottom_offset** may define a number of pixels to crop on a bottom side, and may be equal to **num_crop_acu_bottom**.

[0075] From the picture size relative to the LCU size and the aligned CU size, the picture size with respect to the aligned CU (ACU) size can be determined from the following equations

$$\text{width of picture relative to ACU} = \frac{(WL*N - \text{crop_right_offset} + M - 1)}{M} M \quad (1)$$

$$\text{height of picture relative to ACU} = \frac{(HL*N - \text{crop_bottom_offset} + M - 1)}{M} M \quad (2)$$

It should be note that the operations in equations 1 and 2 may be integer calculations.

[0076] Table 5 provides yet another example of additional syntax elements for `pic_parameter_set_rbsp()`. In this example, at least one of **num_right_offset_ACU** and **num_bottom_offset_ACU** may be signaled. Table 6 shows **num_right_offset_ACU** and **num_bottom_offset_ACU** being signaled in the SPS, however, these values may be signaled elsewhere. For example, at least one of **num_right_offset_ACU** and **num_bottom_offset_ACU** may be signaled in a PPS.

seq_parameter_set_rbsp() {	Descriptor
profile_idc	u(8)
reserved_zero_8bits /* equal to 0 */	u(8)
level_idc	u(8)
seq_parameter_set_id	ue(v)
max_temporal_layers_minus1	u(3)
pic_width_in_LCU	ue(v)
pic_height_in_LCU	ue(v)
num_crop_acu_right	ue(v)
num_crop_acu_bottom	ue(v)
bit_depth_luma_minus8	ue(v)
bit_depth_chroma_minus8	ue(v)
pcm_bit_depth_luma_minus1	u(4)
pcm_bit_depth_chroma_minus1	u(4)
log2_max_frame_num_minus4	ue(v)
pic_order_cnt_type	ue(v)
if(pic_order_cnt_type == 0)	
log2_max_pic_order_cnt_lsb_minus4	ue(v)
else if(pic_order_cnt_type == 1) {	
delta_pic_order_always_zero_flag	u(1)
offset_for_non_ref_pic	se(v)
num_ref_frames_in_pic_order_cnt_cycle	ue(v)
for(i = 0; i < num_ref_frames_in_pic_order_cnt_cycle; i++)	
offset_for_ref_frame[i]	se(v)
}	
max_num_ref_frames	ue(v)
gaps_in_frame_num_value_allowed_flag	u(1)
log2_max_coding_block_size_minus3	ue(v)
log2_diff_max_pic_aligned_min_coding_block_size	ue(v)
log2_min_transform_block_size_minus2	ue(v)
log2_diff_max_min_transform_block_size	ue(v)
log2_min_pcm_coding_block_size_minus3	ue(v)
max_transform_hierarchy_depth_inter	ue(v)
max_transform_hierarchy_depth_intra	ue(v)
chroma_pred_from_luma_enabled_flag	u(1)
loop_filter_across_slice_flag	u(1)
sample_adaptive_offset_enabled_flag	u(1)
adaptive_loop_filter_enabled_flag	u(1)
pcm_loop_filter_disable_flag	u(1)
cu_qp_delta_enabled_flag	u(1)

temporal_id_nesting_flag	u(1)
frame_cropping_flag	u(1)
if(frame_cropping_flag) {	
frame_crop_left_offset	ue(v)
frame_crop_right_offset	ue(v)
frame_crop_top_offset	ue(v)
frame_crop_bottom_offset	ue(v)
}	
rbsp_trailing_bits()	
}	

Table 5: Sequence parameter set RBSP syntax

[0077] The value **num_crop_acu_right** in Table 5 may specify a number of aligned CU sizes to be cropped from the LCU aligned picture from the right. The cropped picture may be stored in the DPB. The value **num_crop_acu_bottom** may specify a number of aligned CU sizes to be cropped from the LCU aligned picture from the bottom, to get the picture to be stored in the DPB.

[0078] In an example corresponding with Table 5, the picture size can also be signaled with a **num_right_offset_ACU** and **num_bottom_offset_ACU**. The picture size may be determined as:

$$\text{width of picture relative to ACU} = WL(N - M)(\text{num_right_offset_ACU}) \quad (3)$$

$$\text{height of picture relative to ACU} = WL(N - M)(\text{num_bottom_offset_ACU}) \quad (4)$$

[0079] A decoded picture that may be stored in a decoded picture buffer with a picture size with respect to the aligned CU may be given as follows:

$$(WL * N - \text{num_crop_acu_right} * M) \text{ by } (HL * N - \text{num_crop_acu_bottom} * M) \quad (5)$$

[0080] Thus, a size (height and width in pixels) of the aligned CU may be signaled in the same way as in the examples above with respect to the picture size. For example, if all pictures have the same smallest CU (SCU) size, the size of the aligned CU may be

the SCU size. As another example, if the pictures have different SCU sizes, the aligned CU size may be a maximum or a minimum SCU size among all the pictures. The aligned CU size may be signaled explicitly in at least one of the SPS or in the PPS. The aligned CU size may be equal or less than a size of the LCU and equal or larger than the size of the SCU.

[0081] Table 6 below provides one example of frame cropping syntax that may be used in conjunction with any of the example embodiments described above. In one example, the cropping window may be in sequence parameter set and follow the same semantics as those in H.264/AVC).

frame_cropping_flag	0	u(1)
if(frame_cropping_flag) {		
frame_crop_left_offset	0	ue(v)
frame_crop_right_offset	0	ue(v)
frame_crop_top_offset	0	ue(v)
frame_crop_bottom_offset	0	ue(v)
}		

Table 6: Frame Cropping Syntax

[0082] FIG. 2 is a block diagram illustrating an example video encoder that may be configured to perform the techniques described in this disclosure. Video encoder 50 may be configured to determine a smallest coding unit size for each of a plurality of pictures defining a video sequence, wherein a smallest coding unit size is selected from a plurality of possible coding unit sizes. Further, video encoder 50 may be configured to determine a minimum coding unit size for the video sequence based on the smallest coding unit determined for each of the plurality pictures defining the video sequence. In addition, video encoder 50 may be configured to determine a picture size associated with the video sequence, wherein the picture size associated with the video sequence is an multiple of the minimum coding unit size value. Moreover, video encoder 50 may be configured to signal the minimum coding unit size value in sequence level syntax information.

[0083] Video encoder 50 may correspond to video encoder 22 of device 20, or a video encoder of a different device. As shown in FIG. 2, video encoder 50 may include a prediction encoding module 32, quadtree partition module 31, adders 48 and 51, and a memory 34. Video encoder 50 may also include a transform module 38 and a quantization module 40, as well as an inverse quantization module 42 and an inverse

transform module 44. Video encoder 50 may also include an entropy coding module 46, and a filter module 47, which may include deblock filters and post loop and/or in loop filters. The encoded video data and syntax information that defines the manner of the encoding may be communicated to entropy encoding module 46, which performs entropy encoding on the bitstream.

[0084] As shown in FIG. 2, prediction encoding module 32 may support a plurality of different coding modes 35 used in the encoding of video blocks. Prediction encoding module 32 may also comprise a motion estimation (ME) module 36 and a motion compensation (MC) module 37.

[0085] During the encoding process, video encoder 50 receives input video data. Quadtree partition module 31 may partition units of video data into smaller units. For example, quadtree partition module 31 may break an LCU into smaller CU's and PU's according to HEVC partitioning described above. Prediction encoding module 32 performs predictive coding techniques on video blocks (e.g. CUs and PUs). For inter coding, prediction encoding module 32 compares CUs or PUs to various predictive candidates in one or more video reference frames or slices (e.g., one or more "list" of reference data) in order to define a predictive block. For intra coding, prediction encoding module 32 generates a predictive block based on neighboring data within the same video frame or slice. Prediction encoding module 32 outputs the prediction block and adder 48 subtracts the prediction block from the CU or PU being coded in order to generate a residual block. At least some video blocks may be coded using advanced motion vector prediction (AMVP) described in HEVC.

[0086] In some cases, prediction encoding module may include a rate-distortion (R-D) module that compares coding results of video blocks (e.g., CUs or PUs) in different modes. In this case, prediction encoding module 32 may also include a mode selection module to analyze the coding results in terms of coding rate (i.e., coding bits required for the block) and distortion (e.g., representing the video quality of the coded block relative to the original block) in order to make mode selections for video blocks. In this way, the R-D module may provide analysis of the results of different modes to allow the mode selection module to select the desired mode for different video blocks.

[0087] Referring again to FIG. 2, after prediction encoding module 32 outputs the prediction block, and after adder 48 subtracts the prediction block from the video block being coded in order to generate a residual block of residual pixel values, transform module 38 applies a transform to the residual block. The transform may comprise a

discrete cosine transform (DCT) or a conceptually similar transform such as that defined by the ITU H.264 standard or the HEVC standard. So-called “butterfly” structures may be defined to perform the transforms, or matrix-based multiplication could also be used. In some examples, consistent with the HEVC standard, the size of the transform may vary for different CUs, e.g., depending on the level of partitioning that occurs with respect to a given LCU. Transform units (TUs) may be defined in order to set the transform size applied by transform module 38. Wavelet transforms, integer transforms, sub-band transforms or other types of transforms could also be used. In any case, transform module 38 applies the transform to the residual block, producing a block of residual transform coefficients. The transform, in general, may convert the residual information from a pixel domain to a frequency domain.

[0088] Quantization module 40 then quantizes the residual transform coefficients to further reduce bit rate. Quantization module 40, for example, may limit the number of bits used to code each of the coefficients. In particular, quantization module 40 may apply the delta QP defined for the LCU so as to define the level of quantization to apply (such as by combining the delta QP with the QP of the previous LCU or some other known QP). After quantization is performed on residual samples, entropy coding module 46 may scan and entropy encode the data.

[0089] CAVLC is one type of entropy coding technique supported by the ITU H.264 standard and the emerging HEVC standard, which may be applied on a vectorized basis by entropy coding module 46. CAVLC uses variable length coding (VLC) tables in a manner that effectively compresses serialized “runs” of coefficients and/or syntax elements. CABAC is another type of entropy coding technique supported by the ITU H.264 standard or the HEVC standard, which may be applied on a vectorized basis by entropy coding module 46. CABAC may involve several stages, including binarization, context model selection, and binary arithmetic coding. In this case, entropy coding module 46 codes coefficients and syntax elements according to CABAC. Many other types of entropy coding techniques also exist, and new entropy coding techniques will likely emerge in the future. This disclosure is not limited to any specific entropy coding technique.

[0090] Following the entropy coding by entropy encoding module 46, the encoded video may be transmitted to another device or archived for later transmission or retrieval. The encoded video may comprise the entropy coded vectors and various syntax information. Such information can be used by the decoder to properly configure

the decoding process. Inverse quantization module 42 and inverse transform module 44 apply inverse quantization and inverse transform, respectively, to reconstruct the residual block in the pixel domain. Summer 51 adds the reconstructed residual block to the prediction block produced by prediction encoding module 32 to produce a reconstructed video block for storage in memory 34. Memory 34 may include a decoded picture buffer and reconstructed video blocks may form a decoded picture. Prior to such storage, however, filter module 47 may apply filtering to the video block to improve video quality. The filtering applied by filter module 47 may reduce artifacts and smooth pixel boundaries. Moreover, filtering may improve compression by generating predictive video blocks that comprise close matches to video blocks being coded.

[0091] FIG. 3 is a flowchart illustrating an example technique for encoding video data that may be performed by video encoder 22 or video encoder 50. Video encoder 20 or video encoder 50 may determine a smallest coding unit size for each of a plurality of pictures defining a video sequence (302). In some cases, a smallest coding unit size may be selected from a plurality of possible coding unit sizes. For example, the smallest coding unit may be one of 4x4, 8x8, 16x16, 32x32 or 64x64, where 64x64 is the maximum possible coding unit size. Video encoder 20 or video encoder 50 may determine an aligned coding unit size for the video sequence from the determined smallest coding units (304). Video encoder 20 or video encoder 50 may determine the aligned coding size based on the techniques described above. Video encoder 20 or video encoder 50 determine a picture size associated with the video sequence, wherein the picture size associated with the video sequence is an multiple of the aligned coding unit size value (306). In some cases the picture size associated with the video sequence may be a picture size of a decoded picture stored in a decoded picture buffer. Video encoder 20 or video encoder 50 may signal the aligned coding unit size value in sequence level syntax information (308).

[0092] FIG. 4 is a block diagram illustrating an example of a video decoder 60, which decodes a video sequence that is encoded in the manner described herein. The techniques of this disclosure may be performed by video decoder 60 in some examples. Video decoder 60 may be configured to obtain a coded video sequence including a first picture coded using a first smallest coding unit size and a second picture coded using second smallest coding unit size. Further, video decoder 60 may be configured to obtain a picture size of a decoded picture to be stored in a decoded picture buffer

wherein the picture size is a multiple of one of the first coding unit size and the second coding unit size. In addition, video decoder 60 may be configured to store the decoded picture in a decoded picture buffer.

[0093] Video decoder 60 includes an entropy decoding module 52, which performs the reciprocal decoding function of the encoding performed by entropy encoding module 46 of FIG. 2. In particular, entropy decoding module 52 may perform CAVLC or CABAC decoding, or any other type of entropy decoding used by video encoder 50. Video decoder 60 also includes a prediction decoding module 54, an inverse quantization module 56, an inverse transform module 58, a memory 62, and a summer 64. In particular, like video encoder 50, video decoder 60 includes a prediction decoding module 54 and a filter module 57. Prediction decoding module 54 of video decoder 60 may include motion compensation module 86, which decodes inter coded blocks and possibly includes one or more interpolation filters for sub-pixel interpolation in the motion compensation process. Prediction decoding module 54 may also include an intra prediction module for decoding intra modes. Prediction decoding module 54 may support a plurality of modes 35. Filter module 57 may filter the output of summer 64, and may receive entropy decoded filter information so as to define the filter coefficients applied in the loop filtering.

[0094] Upon receiving encoded video data, entropy decoding module 52 performs reciprocal decoding to the encoding performed by entropy encoding module 46 (of encoder 50 in FIG. 2). At the decoder, entropy decoding module 52 parses the bitstream to determine LCU's and the corresponding partitioning associated with the LCU's. In some examples, an LCU or the CUs of the LCU may define coding modes that were used, and these coding modes may include the bi-predictive merge mode. Accordingly, entropy decoding module 52 may forward the syntax information to prediction unit that identifies the bi-predictive merge mode. Memory 62 may include a decoded picture buffer. Decoded picture buffer may store a decoded picture. The decoded picture may be associated with a video sequences such that the decoder picture is referenced during prediction decoding. Syntax information may be used by video decoder 60 to determine the size of the decoded picture to be stored in the decoded picture buffer according to the techniques described herein.

[0095] FIG. 5 is a flowchart illustrating an example technique for decoding video data that may be performed by video decoder 28 or video decoder 60. Video decoder 28 or video decoder 60 may obtain a coded video sequence including a first picture coded

using a first smallest coding unit size and a second picture coded using second smallest coding unit size (502). In one example, first picture may be coded using a smallest coding unit size of 4x4 and second picture may be coded using a smallest coding unit size of 8x8. Video decoder 28 or video decoder 60 may obtain a picture size of a decoded picture to be stored in a decoded picture buffer wherein the picture size is a multiple of one of the first coding unit size, the second coding unit size or a maximum coding unit size(504). In one example, the picture size may be 1920x1080. Video decoder 28 or video decoder 60 may store the decoded picture in a decoded picture buffer (506). Further, video decoder 28 or video decoder 60 may determine whether a bitstream including a video sequence is a conforming bitstream based on whether the obtained picture size is a multiple of the aligned coding unit size.

[0096] In one or more examples, the functions described may be implemented in hardware, software, firmware, or any combination thereof. If implemented in software, the functions may be stored on or transmitted over as one or more instructions or code on a computer-readable medium and executed by a hardware-based processing unit. Computer-readable media may include computer-readable storage media, which corresponds to a tangible medium such as data storage media, or communication media including any medium that facilitates transfer of a computer program from one place to another, e.g., according to a communication protocol. In this manner, computer-readable media generally may correspond to (1) tangible computer-readable storage media which is non-transitory or (2) a communication medium such as a signal or carrier wave. Data storage media may be any available media that can be accessed by one or more computers or one or more processors to retrieve instructions, code and/or data structures for implementation of the techniques described in this disclosure. A computer program product may include a computer-readable medium.

[0097] By way of example, and not limitation, such computer-readable storage media can comprise RAM, ROM, EEPROM, CD-ROM or other optical disk storage, magnetic disk storage, or other magnetic storage devices, flash memory, or any other medium that can be used to store desired program code in the form of instructions or data structures and that can be accessed by a computer. Also, any connection is properly termed a computer-readable medium. For example, if instructions are transmitted from a website, server, or other remote source using a coaxial cable, fiber optic cable, twisted pair, digital subscriber line (DSL), or wireless technologies such as infrared, radio, and microwave, then the coaxial cable, fiber optic cable, twisted pair, DSL, or wireless

technologies such as infrared, radio, and microwave are included in the definition of medium. It should be understood, however, that computer-readable storage media and data storage media do not include connections, carrier waves, signals, or other transitory media, but are instead directed to non-transitory, tangible storage media. Disk and disc, as used herein, includes compact disc (CD), laser disc, optical disc, digital versatile disc (DVD), floppy disk and blu-ray disc where disks usually reproduce data magnetically, while discs reproduce data optically with lasers. Combinations of the above should also be included within the scope of computer-readable media.

[0098] Instructions may be executed by one or more processors, such as one or more digital signal processors (DSPs), general purpose microprocessors, application specific integrated circuits (ASICs), field programmable logic arrays (FPGAs), or other equivalent integrated or discrete logic circuitry. Accordingly, the term “processor,” as used herein may refer to any of the foregoing structure or any other structure suitable for implementation of the techniques described herein. In addition, in some aspects, the functionality described herein may be provided within dedicated hardware and/or software modules configured for encoding and decoding, or incorporated in a combined codec. Also, the techniques could be fully implemented in one or more circuits or logic elements.

[0099] The techniques of this disclosure may be implemented in a wide variety of devices or apparatuses, including a wireless handset, an integrated circuit (IC) or a set of ICs (e.g., a chip set). Various components, modules, or units are described in this disclosure to emphasize functional aspects of devices configured to perform the disclosed techniques, but do not necessarily require realization by different hardware units. Rather, as described above, various units may be combined in a codec hardware unit or provided by a collection of interoperative hardware units, including one or more processors as described above, in conjunction with suitable software and/or firmware.

[0100] Various aspects of the disclosure have been described. These and other aspects are within the scope of the following claims.

CLAIMS

1. A method of encoding video data comprising:
 - determining a smallest coding unit size for a video sequence, wherein the video sequence comprises a plurality of pictures and wherein the smallest coding unit size is selected from a plurality of possible coding unit sizes;
 - determining a picture size associated with the video sequence, wherein the picture size associated with the video sequence is determined as a multiple of the smallest coding unit size;
 - signaling the smallest coding unit size in sequence level syntax information and signaling the picture size as a multiple of smallest coding unit size in sequence level syntax information; and
 - encoding the video sequence using the smallest coding unit size and the picture size.
2. The method of claim 1, wherein the plurality of possible coding unit sizes includes a maximum coding unit size of 64x64 pixels.
3. The method of claim 1, wherein determining a smallest coding unit size for the video sequence includes determining a first smallest coding unit size for a first picture and determining a second smallest coding unit size for a second picture, wherein the first smallest coding unit size is less than the second smallest coding unit size, and wherein the smallest coding unit size for the video sequence is the first smallest coding unit size.
4. The method of claim 1, wherein the picture size includes a picture width determined as a multiple of the smallest coding unit size and a picture height determined as a multiple of the smallest coding unit size.
5. The method of claim 1, wherein the picture size specifies a picture size of a decoded picture stored in a decoded picture buffer.

6. A device configured to encode video data comprising:
means for determining a smallest coding unit size for a video sequence,
wherein the video sequence comprises a plurality of pictures and wherein the smallest coding unit size is selected from a plurality of possible coding unit sizes;
means for determining a picture size associated with the video sequence,
wherein the picture size associated with the video sequence is determined as a multiple of the smallest coding unit size;
means for signaling the smallest coding unit size in sequence level syntax information and mean for signaling the picture size as a multiple of smallest coding unit size in sequence level syntax information; and
means for encoding the video sequence using the smallest coding unit size and the picture size.
7. The device of claim 6, wherein the plurality of possible coding unit sizes includes a maximum coding unit size of 64x64 pixels.
8. The device of claim 6, wherein the means for determining a smallest coding unit size for the video sequence includes means for determining a first smallest coding unit size for a first picture and determining a second smallest coding unit size for a second picture, wherein the first smallest coding unit size is less than the second smallest coding unit size, and wherein the smallest coding unit size for the video sequence is the first smallest coding unit size.
9. The device of claim 1, wherein the picture size includes a picture width determined as a multiple of the smallest coding unit size and a picture height determined as a multiple of the smallest coding unit size.
10. The device of claim 6, wherein the picture size specifies a picture size of a decoded picture stored in a decoded picture buffer.

11. A device comprising a video encoder configured to:
 - determine a smallest coding unit size for a video sequence, wherein the video sequence comprises a plurality of pictures and wherein the smallest coding unit size is selected from a plurality of possible coding unit sizes;
 - determine a picture size associated with the video sequence, wherein the picture size associated with the video sequence is determined as a multiple of the smallest coding unit size;
 - signal the smallest coding unit size in sequence level syntax information and signal the picture size as a multiple of smallest coding unit size in sequence level syntax information; and
 - encode the video sequence using the smallest coding unit size and the picture size.
12. The device of claim 11, wherein the plurality of possible coding unit sizes includes a maximum coding unit size of 64x64 pixels.
13. The device of claim 11, wherein determining a smallest coding unit size for the video sequence includes determining a first smallest coding unit size for a first picture and determining a second smallest coding unit size for a second picture, wherein the first smallest coding unit size is less than the second smallest coding unit size, and wherein the smallest coding unit size for the video sequence is the first smallest coding unit size.
14. The device of claim 11, wherein the picture size includes a picture width determined as a multiple of the smallest coding unit size and a picture height determined as a multiple of the smallest coding unit size.
15. The device of claim 11, wherein the picture size specifies a picture size of a decoded picture stored in a decoded picture buffer.
16. A computer readable storage medium for encoding video data comprising instructions stored thereon that when executed cause a processor to:

determine a smallest coding unit size for a video sequence, wherein the video sequence comprises a plurality of pictures and wherein the smallest coding unit size is selected from a plurality of possible coding unit sizes;

determine a picture size associated with the video sequence, wherein the picture size associated with the video sequence is determined as a multiple of the smallest coding unit size;

signal the smallest coding unit size in sequence level syntax information and signal the picture size as a multiple of smallest coding unit size in sequence level syntax information; and

encode the video sequence using the smallest coding unit size and the picture size.

17. The computer readable storage medium of claim 16, wherein the plurality of possible coding unit sizes includes a maximum coding unit size of 64x64 pixels.

18. The computer readable storage medium of claim 16, wherein determining a smallest coding unit size for the video sequence includes determining a first smallest coding unit size for a first picture and determining a second smallest coding unit size for a second picture, wherein the first smallest coding unit size is less than the second smallest coding unit size, and wherein the smallest coding unit size for the video sequence is the first smallest coding unit size.

19. The computer readable storage medium of claim 16, wherein the picture size includes a picture width determined as a multiple of the smallest coding unit size and a picture height determined as a multiple of the smallest coding unit size.

20. The computer readable storage medium of claim 16, wherein the picture size specifies a picture size of a decoded picture stored in a decoded picture buffer.

21. A method of decoding video data comprising:
obtaining a coded video sequence including a plurality of coded pictures;

obtaining sequence level syntax information indicating a smallest coding unit size of the video sequence, wherein the smallest coding unit size is selected from a plurality of possible coding unit sizes in an encoding process of the video sequence;

obtaining sequence level information indicating a picture size associated with the video sequence, the picture size having been signaled as a multiple of smallest coding unit size, and wherein the picture size is determined as a multiple of the smallest coding unit size in the encoding process;

decoding the pictures using the smallest coding unit size and the picture size;

and

storing the decoded pictures in a decoded picture buffer.

22. The method of claim 21, wherein a first picture of the video sequence has a first smallest coding unit size and a second picture of the video sequence has a second smallest coding unit size, the first smallest coding unit size is less than the second smallest coding unit size, the smallest coding unit size is the first smallest coding unit size, and the picture size is a multiple of the first smallest coding unit size.

23. The method of claim 21, wherein the picture size includes a picture width determined as a multiple of the smallest coding unit size and a picture height determined as a multiple of the smallest coding unit size.

24. The method of claim 21, wherein the plurality of possible coding unit sizes includes a maximum coding unit size of 64x64 pixels.

25. A device configured to decode video data comprising:

means for obtaining a coded video sequence including a plurality of coded pictures;

means for obtaining sequence level syntax information indicating a smallest coding unit size of the video sequence, wherein the smallest coding unit size is selected from a plurality of possible coding unit sizes in an encoding process of the video sequence;

means for obtaining sequence level information indicating a picture size associated with the video sequence, the picture size having been signaled as a multiple

of smallest coding unit size, and wherein the picture size is determined as a multiple of the smallest coding unit size in the encoding process;

means for decoding the pictures using the smallest coding unit size and the picture size; and

means for storing the decoded pictures in a decoded picture buffer.

26. The device of claim 25, wherein a first picture of the video sequence has a first smallest coding unit size and a second picture of the video sequence has a second smallest coding unit size, the first smallest coding unit size is less than the second smallest coding unit size, the smallest coding unit size is the first smallest coding unit size, and the picture size is a multiple of the first smallest coding unit size.

27. The device of claim 25, wherein the picture size includes a picture width determined as a multiple of the smallest coding unit size and a picture height determined as a multiple of the smallest coding unit size.

28. The device of claim 25, wherein the plurality of possible coding unit sizes includes a maximum coding unit size of 64x64 pixels.

29. A device comprising a video decoder configured to:

obtain a coded video sequence including a plurality of coded pictures;

obtain sequence level syntax information indicating a smallest coding unit size of the video sequence, wherein the smallest coding unit size is selected from a plurality of possible coding unit sizes in an encoding process of the video sequence;

obtain sequence level information indicating a picture size associated with the video sequence, the picture size having been signaled as a multiple of smallest coding unit size, and wherein the picture size is determined as a multiple of the smallest coding unit size in the encoding process;

decode the pictures using the smallest coding unit size and the picture size;

and

store the decoded pictures in a decoded picture buffer.

30. The device of claim 29, wherein a first picture of the video sequence has a first smallest coding unit size and a second picture of the video sequence has a second smallest coding unit size, the first smallest coding unit size is less than the second smallest coding unit size, the smallest coding unit size is the first smallest coding unit size, and the picture size is a multiple of the first smallest coding unit size.

31. The device of claim 29, wherein the picture size includes a picture width determined as a multiple of the smallest coding unit size and a picture height determined as a multiple of the smallest coding unit size.

32. The device of claim 29, wherein the plurality of possible coding unit sizes includes a maximum coding unit size of 64x64 pixels.

33. A computer readable storage medium comprising instructions stored thereon that when executed cause a processor to:

obtain a coded video sequence including a plurality of coded pictures;

obtain sequence level syntax information indicating a smallest coding unit size of the video sequence, wherein the smallest coding unit size is selected from a plurality of possible coding unit sizes in an encoding process of the video sequence;

obtain sequence level information indicating a picture size associated with the video sequence, the picture size having been signaled as a multiple of smallest coding unit size, and wherein the picture size is determined as a multiple of the smallest coding unit size in the encoding process;

decode the pictures using the smallest coding unit size and the picture size;

and

store the decoded pictures in a decoded picture buffer.

34. The computer readable storage medium of claim 33, wherein a first picture of the video sequence has a first smallest coding unit size and a second picture of the video sequence has a second smallest coding unit size, the first smallest coding unit size is less than the second smallest coding unit size, the smallest coding unit size is the first smallest coding unit size, and the picture size is a multiple of the first smallest coding unit size.

35. The computer readable storage medium of claim 33, wherein the picture size includes a picture width determined as a multiple of the smallest coding unit size and a picture height determined as a multiple of the smallest coding unit size.

36. The computer readable storage medium of claim 33, wherein the plurality of possible coding unit sizes includes a maximum coding unit size of 64x64 pixels.