

INTEGRATED VERTICAL SPIRAL INDUCTOR ON SEMICONDUCTOR MATERIAL

BACKGROUND OF THE INVENTION

5 (1) Field of the Invention

The invention relates to the fabrication of integrated circuit devices, and more particularly, to a method and structure for creating a high Q inductor while simultaneously reducing the surface space that is consumed
10 by such an inductor. The inductor of the invention is a spiral inductor that is positioned in a plane that is perpendicular to the plane of the substrate on which the conductor is created.

15 (2) (2) Description of the Prior Art

Modern semiconductor technology requires the creation of high performance semiconductor devices that are produced at competitive prices. A direct result of these requirements is that device density and inter-device
20 packaging density continue to increase from which directly follows the requirement that the surface area or space that is available on the surface of a semiconductor substrate is carefully allocated and maximized in its use.

While the majority of semiconductor devices relate to the field of digital data processing, electronic circuitry can nevertheless be divided into two broad fields. One field addresses digital processing while the second field addresses the manipulation of analog signals. Digital semiconductor devices have as function the manipulation or storage of digital information. The functions of analog electronic circuitry have in previous years typically been handled by separate components such as relatively large capacitors or relatively large inductors. The separate components may have been applied in combination with digital processing capabilities, whereby however a significant portion of the functional implementation has been realized by the use of for instance capacitive and inductive components in addition to and functionally collaborating with the digital components. Circuit requirements that are imposed on components that are required for analog processing have in the past limited the integration of such components into typical semiconductor integrated circuit devices.

Modern mobile communication applications center around compact high-frequency equipment. With the

continued improvements in the performance characteristics of this equipment, continued emphasis will be placed on small size of the equipment, low power consumption, increased frequency applications and low noise levels.

5 Semiconductor devices are used in the field of mobile communication for the creation of Radio Frequency (RF) amplifiers. A major component of a typical RF amplifier is a tuned circuit that contains inductive and capacitive components. The tuned circuit has as electrical
10 characteristic that, dependent on and determined by the values of its inductive and capacitive components, can form an impedance that is frequency dependent, which enables the tuned circuit to either form a high or a low impedance for signals of a certain frequency. In this
15 manner the tuned circuit can either reject or pass and further amplify components of an analog signal based on the frequency of that component. The tuned circuit can therefore be used as a filter to filter out or remove signals of certain frequencies or to remove noise from a
20 circuit configuration that is aimed at manipulating analog signals. The tuned circuit can also be used to form a high electrical impedance by using the LC resonance of the circuit and to thereby counteract the effect of parasitic

capacitances that are part of a circuit. The self-resonance that is caused by the parasitic capacitance between the (spiral) inductor and the underlying substrate will limit the use of the inductor at high frequencies.

5

One of the key components that is applied in creating high frequency analog semiconductor devices is the inductor that forms part of a LC resonance circuit. The key challenge in the creation of the inductor is to

10 minimize the surface area that is required for the creation of the inductor while maintaining a high Q value for the inductor. Conventional inductors that are created on the surface of a substrate are of a spiral shape, whereby the spiral is created in a plane that is parallel

15 with the plane of the surface of the substrate. Conventional methods that are used to create the inductor on the surface of a substrate suffer several limitations. Most high Q inductors form part of a hybrid device configuration or of Monolithic Microwave Integrated

20 Circuits (MMIC's) or are created as discrete components, the creation of which is not readily integratable into a typical process of Integrated Circuit manufacturing.

By combining the creation on one semiconductor monolithic substrate of circuitry that is aimed at the function of analog data manipulation and analog data storage with the functions of digital data manipulation and digital data storage, a number of significant advantages are achieved. Such advantages include the reduction of manufacturing costs and the reduction of power consumption by the combined functions. To reach required inductive values for particular applications, inductors can be of significant physical size and can therefore require a significant surface area of the semiconductor substrate. To limit this impact of space requirement, inductors are typically formed on the surface of a substrate in a spiral form. The spiral form of the inductor however results in parasitic capacitances between the inductor wiring and the underlying substrate, due to the physical size of the inductor. These parasitic capacitances have a serious negative effect on the functionality of the created LC circuit by sharply reducing resonance frequency of the tuned circuit of the application.

Widely used in the industry to describe the applicability of a created inductor is the Quality (Q) factor of the inductor. The quality factor Q of an inductor is defined as follows: $Q = E_s/E_l$ wherein E_s is the energy that is stored in the reactive portion of the component while E_l is the energy that is lost in the reactive portion of the component. The higher the quality of the component, the closer the resistive value of the component approaches zero while the Q factor of the component approaches infinity. The quality factor for components differs from the quality that is associated with filters or resonators. For components, the quality factor serves as a measure of the purity of the reactance (or the susceptance) of the component, which can be degraded due to parasitics. In an actual configuration, there are always some physical resistors that will dissipate power, thereby decreasing the power that can be recovered. The quality factor Q is dimensionless. A Q value of greater than 100 is considered very high for discrete inductors that are mounted on the surface of Printed Circuit Boards. For inductors that form part of an integrated circuit, the Q value is typically in the range between about 3 and 10.

In creating an inductor on a monolithic substrate on which additional semiconductor devices are created, the parasitic capacitances that occur as part of this creation limit to about 10 the quality factor that can be achieved for the inductor using the conventional silicon process. This limitation is, for many applications, not acceptable. Dependent on the frequency at which the LC circuit is designed to resonate, significantly larger values of quality factor, such as for instance 100 or more, must be available. Prior Art has in this been limited to creating values of higher quality factors as separate units, and in integrating these separate units with the surrounding device functions. This negates the advantages that can be obtained when using the monolithic construction of creating both the inductor and the surrounding devices on one and the same semiconductor substrate. The non-monolithic approach also has the disadvantage that additional wiring is required to interconnect the sub-components of the assembly, thereby again introducing additional parasitic capacitances and resistive losses over the interconnecting wiring network. For many of the applications of the RF amplifier, such as portable battery powered applications, power consumption is at a premium

and must therefore be as low as possible. By raising the power consumption, the effects of parasitic capacitances and resistive power loss can be partially compensated but there are limitations to even this approach. These

5 problems take on even greater urgency with the rapid expansion of wireless applications such as portable telephones and the like. Wireless communications is a rapidly expanding market, where the integration of RF integrated circuits is one of the most important

10 challenges. One of the approaches is to significantly increase the frequency of operation to for instance the range of 10 to 100 GHz. For such high frequencies, the values of the quality factor obtained from silicon-based inductors are significantly degraded. For applications in

15 this frequency range, monolithic inductors have been researched using other than silicon as the base for the creation of the inductors. Such monolithic inductors have for instance been created using sapphire or GaAs as a base. These inductors have a considerably lower parasitic

20 capacitance than their silicon counterparts and therefore provide higher frequencies of resonance of the LC circuit. Where however more complex applications are required, the need still exists to create inductors using silicon as a

substrate. For those applications, the approach of using a base material other than silicon has proven to be too cumbersome while for instance GaAs as a medium for the creation of semiconductor devices is as yet a technical
5 challenge that needs to be addressed.

The incorporation of RF inductors without sacrificing device performance due to substrate losses has been extensively researched in recent years. Some of the
10 techniques that have been used for this approach include:

- the selective removing (by etching) of the silicon underneath the inductor (using methods of micro-machining) thereby removing substrate parasitic effects
- using multiple layers of metal (such as aluminum)
15 interconnects or of copper damascene interconnects
- using a high resistivity silicon substrate thereby reducing resistive losses in the silicon substrate, since resistive substrate losses form a dominant factor in determining the Q value of silicon inductors
- 20 - using metals that are particularly adaptable to the process of the formation of inductors, a concern is thereby however raised by the use of AlCu (a metal that is frequently used in semiconductor metallization) since

5 October 2004

AlCu has higher resistivity than gold (Au) metallization that is frequently used in GaAs technology

- employing biased wells underneath a spiral conductor
- inserting various types of patterned ground shields
- 5 between the spiral inductor and the silicon substrate, and
- creating an active inductive component that simulates the electrical properties of an inductor as it is applied in active circuitry; this approach however
- 10 results in high power consumption by the inductor and in noise performance that is unacceptable for low power, high frequency applications

The above listing of researched alternatives is not
15 meant to be complete or all inconclusive. The above approaches have as common objectives to:

- 1) enhance the quality (Q) value of the inductor
- 2) increase the frequency of the LC self-resonance
thereby increasing the frequency range over which the
20 inductor can be used, and
- 3) reduce the surface area that is required for the creation of the inductor.

The inductor of the invention addresses the objectives that have been listed above and provides for a method of creating an inductor that sharply reduces the surface area that is required for the inductor. The method
5 of the invention creates a vertical spiral inductor, which has performance characteristics that differ sharply from the performance characteristics of a typical spiral inductor that is created in a plane that is parallel with the surface of the substrate. The vertical spiral inductor
10 of the invention uses current processes of multilevel interconnect to create the return patterns of the spiral, the return patterns are vertical with respect to the plane of the surface of the substrate. The electromagnetic field of the vertical return sections of the spiral inductor
15 limit the resistive losses that are typically obtained in the silicon substrate since the electromagnetic field of these return sections is essentially parallel to the surface of the substrate and does therefore not penetrate the substrate. In addition, the surface area that is
20 required for the creation of the inductor is sharply reduced due to its vertical construction, that is vertical with respect to the plane of the surface of the substrate.

Fig. 1a shows a top view of a Prior Art horizontal spiral inductor 25. Some of the design parameters of conductor 25 are highlighted as follows:

- 5 - 10 is the body of the inductor and contains a conductive material
- 11 is one extremity of the conductive body 10 of the inductor 25 and is, for convenience sake and arbitrarily, referred to as the beginning of the conductive body 10 of the inductor
- 10 - 12 is a conductive connector that connects to the beginning 11 of the conductive body 10 of the inductor 25,
- 13 is the opposing extremity of the conductive body 10 of the inductor 25 and will be referred to as the end of
- 15 the conductive body of the inductor
- 14 is a contact via that interconnects metal strip 12 with the conductive body 10 of the inductor
- 16 is the spacing between the spirals of the conductive body 10 of inductor 25
- 20 - 18 is the width of the spirals of the conductive body 10 of inductor 25

- 20 is the length of the longest spiral of the conductive body 10 of inductor 25, and
- 22 is the length of the shortest spiral of the conductive body 10 of inductor 25.

5

The top view of the Prior Art inductor that is shown in Fig. 1 is not shown in order to highlight in extensive detail all the parameters that can be associated with such an inductor but merely serves to point out the essence of the Prior Art inductor, that is:

10

- the geometric shape of the inductor is that of a spiral
- the individual sections that make up the spiral of the inductor alternately intersect at an angle of 90 degrees and have a length and a width and are separated by a

15

spacing

- the spiral that forms the inductor ends in two extremities, the inductor is electrically interconnected to surrounding circuitry by being connected to these two extremities, and

20

- the body of the inductor is contained in a plane that is parallel to the plane of the surface of the substrate on which the inductor is created.

Not shown in Fig. 1 is the height of each of the linear segments that collectively form the body of the inductor 10, this height can be defined as the thickness of the conductive layer that is deposited on the surface of the substrate for the formation of the inductor. The lower surface of the inductor is the surface of the inductor that is parallel to the surface of the substrate and that is closest to the surface of the substrate, the upper surface of the inductor is the surface of the inductor that is parallel to the surface of the substrate and that is furthest removed from the surface of the substrate. The distance between the upper surface and the lower surface of the inductor as measured in a direction that is perpendicular to the plane of the substrate is the height of the inductor. A cross section of the inductor that is taken in a plane between the upper and the lower surface of the inductor shows the geometric shape of the inductor, which is the shape of a spiral. The height of the inductor of Prior Art is essentially the same along the spiral of the inductor.

US 5,936,298 (Capocelli coil. teaches process for a Helix coil.

US 5,576,680 (Ling) Structure and fabrication process of inductors on semiconductor chip, shows a vertical coil. See Figs. 3e through 4c. Also a helix coil with a core.

5 US 5,372,967 (Sundram) - Method for fabricating a vertical trench inductor, shows a vertical trench coil process.

US 5,884,990 (Burghartz et al.) shows another
10 vertical coil process.

SUMMARY OF THE INVENTION

A principle objective of the invention is to reduce
15 the surface area that is required for the creation of an inductor on the surface of a silicon semiconductor substrate.

Another objective of the invention is to create an
20 inductor on the surface of a silicon semiconductor substrate whereby the electromagnetic field of the inductor has sharply reduced resistive losses induced by the underlying substrate.

In accordance with the objectives of the invention a new method and structure is provided for the creation of an inductor on the surface of a silicon semiconductor substrate. The inductor is of spiral design, whereby the
5 plane of a cross section of the inductor that reflects the spiral design of the inductor is perpendicular to the plane of the underlying substrate. The first embodiment of the invention provides a method of creating a vertical spiral inductor with thin conductor width. The second
10 embodiment of the invention provides a method of creating a vertical spiral inductor with thin conductor width whereby ferromagnetic material is incorporated in the creation of the inductor. The third embodiment of the invention provides a method of creating a vertical spiral
15 inductor with wide conductor width. The fourth embodiment of the invention provides a method of creating a vertical spiral inductor with wide conductor width whereby ferromagnetic material is incorporated in the creation of the inductor. The fifth embodiment of the invention
20 provides two vertical spiral inductors that are connected in series. The sixth embodiment of the invention provides two vertical spiral inductors that are connected in series whereby ferromagnetic material is incorporated in the

creation of the inductor. The seventh embodiment of the invention provides for the creation of a vertical spiral inductor that has a construction of protruding spirals. The eighth embodiment of the invention provides for the
5 creation of a vertical spiral inductor that is combined with a horizontal spiral inductor whereby ferromagnetic materials are incorporated in the creation of the vertical inductor whereby the horizontal spiral inductor is overlaying the vertical spiral inductor. The ninth
10 embodiment of the invention provides for the creation of a vertical spiral inductor that is combined with a horizontal spiral inductor whereby ferromagnetic materials are incorporated in the creation of the vertical inductor whereby the horizontal spiral inductor is in the plane of
15 the top surface of the vertical spiral inductor.

BRIEF DESCRIPTION OF THE DRAWINGS

Fig. 1 shows a top view of a Prior Art horizontal
20 spiral conductor.

Fig. 2 addresses a vertical inductor of the invention that uses thin conductor width, as follow:

Fig. 2a is a right hand extended three-dimensional view of the vertical inductor of the invention with a small conductor width.

5 Fig. 2b shows a top view the vertical inductor of the invention with a small conductor width.

Fig. 2c shows a cross section in an Y-direction of the vertical inductor of the invention with a small
10 conductor width.

Fig. 2d shows a cross section in a Z-direction of the vertical inductor of the invention with a small conductor width.

15

Fig. 3 addresses a vertical inductor of the invention that uses small conductor width whereby furthermore ferromagnetic material is incorporated, as follow:

20 Fig. 3a is a right hand extended three-dimensional view of the vertical inductor of the invention with a small conductor width whereby ferromagnetic material is incorporated.

Fig. 3b shows a top view the vertical inductor of the invention with a small conductor width whereby ferromagnetic material is incorporated.

5 Fig. 3c shows a cross section in an X-direction of the vertical inductor of the invention with a small conductor width whereby ferromagnetic material is incorporated.

10 Fig. 3d shows a cross section in an Y-direction of the vertical inductor of the invention with a small conductor width whereby ferromagnetic material is incorporated.

15 Fig. 4 is a right hand extended three-dimensional view of the vertical inductor of the invention with a large conductor width.

20 Fig. 5 is a right hand extended three-dimensional view of the vertical inductor of the invention with a large conductor width whereby ferromagnetic material is incorporated.

Fig. 6 addresses a vertical inductor of the invention whereby two vertical spiral inductors are connected in series, as follow:

5 Fig. 6a is a right hand extended three-dimensional view of vertical inductor of the invention whereby two vertical spiral inductors are connected in series.

10 Fig. 6b shows a top view the vertical inductor of the invention whereby two vertical spiral inductors are connected in series.

15 Fig. 6c shows a cross section in an X-direction of the vertical inductor of the invention whereby two vertical spiral inductors are connected in series.

20 Fig. 6d shows a cross section in an Y-direction of the vertical inductor of the invention whereby two vertical spiral inductors are connected in series.

Fig. 7 is a right hand extended three dimensional view of vertical inductor of the invention whereby two

vertical spiral inductors are connected in series whereby furthermore ferromagnetic material is incorporated.

Fig. 8 addresses an inductor of the invention whereby
5 the spirals of the inductor protrude from the vertical plane of the inductor, as follows:

Fig. 8a shows an expanded three-dimensional front side view of a vertical inductor of the invention whereby
10 the spirals of the inductor progressively protrude from the body of the inductor.

Fig. 8b shows an expanded three-dimensional backside view of a vertical inductor of the invention whereby the
15 spirals of the inductor progressively protrude from the body of the inductor.

Fig. 8c shows a cross section in an X-dimension of a vertical inductor of the invention whereby the spirals of
20 the inductor progressively protrude from the body of the inductor.

Fig. 9 addresses an inductor of the invention whereby a conventional horizontal spiral inductor is combined with a vertical spiral inductor of the invention whereby the horizontal inductor overlays the vertical inductor, as follows:

Fig. 9a shows a three-dimensional expanded right hand view of an inductor of the invention whereby a horizontal spiral inductor is connected in series with a vertical spiral inductor.

Fig. 9b shows a cross section taken in a plane that is perpendicular with the surface of the underlying substrate of an inductor of the invention whereby a horizontal spiral inductor is connected in series with a vertical spiral inductor.

Fig. 10 addresses an inductor of the invention whereby a conventional horizontal spiral inductor is combined with a vertical spiral inductor of the invention whereby the horizontal inductor is located in the plane of the top layer of the vertical inductor, as follows:

Fig. 10a shows a three dimensional expanded right
hand view of an inductor of the invention whereby a
horizontal spiral inductor is connected in series with a
vertical spiral inductor whereby furthermore the
5 horizontal inductor is located in the plane of the top
layer of the vertical inductor.

Fig. 10b shows a cross section taken in an X-
direction in a plane that is perpendicular with the
10 surface of the underlying substrate of an inductor of the
invention whereby a horizontal spiral inductor is
connected in series with a vertical spiral inductor
whereby furthermore the horizontal inductor is located in
the plane of the top layer of the vertical inductor.

15

DESCRIPTION OF THE PREFERRED EMBODIMENTS

The process of the invention will be highlighted by
concentrating on the geometric and constructional details
20 of the creation of the inductor of the invention.

Processing steps that are required to implement these
structural details will not be highlighted for reasons of
simplicity while in addition these processing steps are

well established in the art. Among these processing steps are steps of depositing layers of dielectric and the patterning and etching of openings in these layers of dielectric whereby these openings are aligned with
5 underlying patterns. To include these processing steps in the description of the inventions would require the entry of state of the art conditions of deposition, patterning and etching that would make the current document unnecessarily cumbersome while not providing added value
10 that relates to the process of the invention.

Referring now specifically to Fig. 2, Figs. 2a through 2d address a vertical inductor of the invention that uses small conductor width.

15

Fig. 2a is a right hand extended three-dimensional view of the vertical inductor of the invention with a small conductor width.

20 In order to facilitate the following discussions, the familiar concept of three-dimensional Cartesian coordinates is briefly discussed with an emphasis on how these coordinates will be used for the subject discussion.

The Cartesian coordinates as used herein have three axis, the X, Y and Z-axis whereby the angle between each of the three axis and the other two axis is 90 degrees. The X and Y axis are in a plane that is parallel with the surface of the substrate on which the inductor will be formed, the Z axis is therefore perpendicular to the plane of the substrate. The three axis of the Cartesian coordinates intersect in one point, which is considered the geometric center of the Cartesian coordinates.

10

Where the spiral of the Prior Art inductor that has been shown in Fig. 1 is contained in a plane that is parallel to the surface of the substrate, the spiral of the inductor of the invention is in a plane that is perpendicular to the surface of the substrate. This means that the body of the inductor has been rotated by 90 degrees, which alters the meaning of the concept of inductor height that has been highlighted in Fig. 1 for the Prior Art inductor. That parameter of Fig. 1 now becomes, due to the 90 degrees rotation of the plane of the inductor, the thickness of the layer of conductive material that is used to create the inductor. This will become apparent by a close examination of the three

dimensional view of the inductor of the invention that is shown in Fig. 2a. The three Cartesian coordinates that have previously introduced are shown in the lower left-hand corner of Fig. 2a. It is readily apparent from Fig. 5 2a that a cross section of the inductor taken in a plane that is parallel to the Y-Z plane indicates the spiral form of the inductor of the invention whereby the spiral is in a plane that is perpendicular to the surface of the substrate. The surface of the substrate on which the 10 inductor is being formed is parallel with the plane in which the X-Y axis resides.

The parameters that are of importance to the three dimensional view that is shown in Fig. 2a are the 15 following:

- the horizontal conductors of the vertical spiral inductor have been numbered using even numbers, starting with the lowest layer and starting with the number 22, these horizontal conductors are therefore in sequence 20 conductors 22, 24, 26, 28, 30, 32 and 34
- the vertical conductors of the vertical spiral inductor, also referred to as the connecting conductors, have been numbered using uneven numbers, starting with the left most

conductor and starting with the number 21, these horizontal conductors are therefore in sequence conductors 21, 23, 25, 27, 29, and 31

- 20' is the length of the lower layer 22 of the
5 conductive material that forms the body of the inductor
- 21' is the width of the lower layer 22 of the conductive material that forms the body of the inductor
- 22' is the first of two connectors to the body of the inductor
- 10 - 23' is the second of two connectors to the body of the inductor
- 24' is the thickness of the conductive material that forms the body of the inductor
- 25' is the distance between adjacent layers of
15 conductive material, and
- 26' is the dielectric that is deposited between the adjacent layers of conductive material.

The layer 22 is the first layer that is created in a
20 layer of dielectric. The technology that is used to create layer 22 is the conventional technology that is used to create interconnect lines in a layer of

dielectric. Layer 22 may be created directly on the surface of a substrate or may be created on the surface of a layer of dielectric (not shown in Fig. 2a) that has first been deposited on the surface of a substrate. If a layer of dielectric is deposited before the layer 22 is formed in a second layer of dielectric, the body of the inductor is further removed from the underlying silicon substrate thereby reducing resistive losses that are suffered by the electromagnetic field of the inductor. This reduction is however not as pronounced as a similar reduction that can be achieved for the inductor of Prior Art since the electromagnetic field of the inductor of the invention that is shown in Fig. 2a is essentially parallel to the surface of the underlying substrate and therefore does not intersect to a significant degree with that surface.

Of importance to the process of the invention is the creation of the first or lowest layer of the connecting vias 21 and 31. After layer 22 has been formed as indicated above, a second layer of dielectric is deposited over the surface of layer 22, this second layer of dielectric is patterned such that openings for the lower

sections of the connecting conductors 21 and 31 (on both extremities of the layer 22 and covering the layer 22 over its width 21') are formed in the second layer of dielectric. The second layer of dielectric has a thickness that essentially equals the distance 25' between layer 22 and the overlying layer 24. The process is then continued by the deposition of a third layer of dielectric, this third layer of dielectric as patterned and etch creating openings for layer 24 and for extensions of the connecting conductors 21 and 31 that overlay the first openings that have been created in the second layer of dielectric for the connecting conductors 21 and 31. This process is repeated, creating increasingly smaller openings for the horizontal conductors. The spiral shaped body of the inductor can in this manner be created, after the level of the spiral of the inductor that is created in this manner is higher than the center of the spiral of the inductor, the horizontal conductors increase in size to form the upper part of the spiral, all the while creating overlaying openings for the connecting conductor vias. Input/output connectors 22' and 23' are created in similar manner and in the desired locations of the inductor using the same processing steps of dielectric depositions (to

form the spacings between the conductors of the inductive spiral) and dielectric patterning for the conductors and the connecting conductor vias.

5 The small conductor width of the invention is a width 21' (Fig. 2a) that is between about 4 and 6 times the height of layer 22, Fig. 2a.

 In further addressing the method in which the
10 vertical spiral inductor of the invention is created, it is important to differentiate between a number of sections of the inductor, as follows:

 1) the lower horizontal conductor 22 is created first and as indicated above, no steps of repetition are involved in
15 the creation of layer 22

 2) once the lower horizontal conductor 22 has been created, the lower section of the inductor is created where the lower section of the inductor is the section that is between the surface of layer 22 and below vertical
20 interconnect 27. This process of creating the lower section is a repetitive cycle whereby horizontal conductors of decreasing length are created overlaying

layer 22 while at the same time creating vias for the extension of the vertical conductors 21, 23, 29 and 31

3) after the lower section has been created, the first input/output connector 28 is created by creating the vertical interconnect 27 (which connects the first I/O connector 28 to the spiral of the vertical inductor) after which the first I/O connector 28 is created

4) after the first I/O connector has been created, the upper section of the inductor is created where the upper section is the section that is located between the surface of the first I/O connector 28 and the top surface of the last horizontal conductor 32. This process of creating the upper section is a repeat process whereby horizontal conductors of increasing length are created that overlay the first I/O connector 28 while at the same time creating vias that serve as extensions of vertical conductors. The process of creating the upper section of the helix coil uses the creation of dual damascene patterns where the trench of the dual damascene pattern forms a horizontal conductor while the vias of the dual damascene patterns form the extended vertical conductors

5) after the upper section has been completed, the second I/O connector 34 is created by depositing a layer of

dielectric, creating an opening in this layer of dielectric that is used to connect the second I/O connector to the remaining vertical conductor 21 that is up to this point as yet not connected, depositing a second layer of dielectric and patterning and etching the second I/O connector 34 in this second layer of dielectric.

From the above it is clear that some of the processing cycles for the creation of the vertical spiral are one time cycles while others lead themselves to repetition to the point where certain sections of the inductor have been completed.

It is further of interest to notice that the view of the vertical inductor that is shown in Fig. 2a is a right hand view of the inductor. From this it follows that vertical conductors can be differentiated between right hand vertical conductors and left-hand vertical conductors. For instance, vertical conductor 31 is a right-hand vertical conductor that overlays the surface of layer 22 on a right-hand vertical contact area in the surface of layer 22, vertical conductor 21 is a left-hand vertical conductor that overlays the surface of layer 22

on a left-hand vertical contact area in the surface of layer 22. It is finally interesting to note that the coil-like nature of the inductor becomes clear best by starting with the first I/O connector 28 and from there following
5 the alternating vertical and horizontal conductors in a clockwise rotation until the second I/O connector 34 is reached.

Fig. 2b shows a top view the vertical inductor of the
10 invention with a thin conductor width. The top view is taken in the direction of the Z-axis, that is looking down in the direction of the substrate, thereby looking down on plane 34 of Fig. 2a. In such a top view, the I/O connectors 22' and 23' are visible as indicated in Fig.
15 2b.

Fig. 2c shows a side view taken in the Y-direction (that is looking at the X-Z plane of Fig. 2a) of the spiral inductor of the invention. The side view that is shown highlights not only the I/O interconnects 22' and
20 23' but also shows a cross section of the conductive layers and the connecting conductor vias that have previously been indicated in Fig. 2a and that form the inductor of the invention. The conductor height 27' is

also indicated. Underlying the body of the vertical inductor of the invention is the silicon substrate 10', a layer 15' of passivation material is deposited over the surface of the completed vertical inductor of the invention.

Fig. 2d shows a top view taken in the Z-direction (that is looking at the X-Y plane of Fig. 2a) of the spiral inductor of the invention. The regions that are highlighted in Fig. 2d have previously been identified including the dielectric 26' that is present between the conductive material that forms the body of the inductor. Layer 22 is the lower horizontal conductor, layer 34 is the upper horizontal conductor. Layer 28 is the inner conductor.

Fig. 3 addresses a vertical inductor of the invention that uses small conductor width whereby furthermore ferromagnetic material is incorporated. The views of the spiral inductor of the invention that are shown in Fig. 3a through 3d are therefore essentially the same as the views of the spiral inductor of the invention that have been

shown as Figs. 2a through 2d with the exception of the addition of the layer 36 of ferromagnetic material.

Fig. 3a is a right hand extended three-dimensional
5 view of the vertical inductor of the invention with a thin conductor width whereby ferromagnetic material 36 is incorporated. The same numbering scheme and related designations that have been shown in Fig. 2a apply to Fig. 3a with the exception of the parameter 36 for the added
10 ferromagnetic material.

Fig. 3b shows a top view the vertical inductor of the invention with a thin conductor width whereby ferromagnetic material 36 is incorporated.

15

Fig. 3c shows a cross section in an X-direction of the vertical inductor of the invention with a thin conductor width whereby ferromagnetic material 36 is incorporated. The same numbering scheme and related
20 designations that have been shown in Fig. 2c apply to Fig. 3c with the exception of the parameter 36 for the added ferromagnetic material.

Fig. 3d shows a cross section in an Y-direction of the vertical inductor of the invention with a thin conductor width whereby ferromagnetic material is incorporated.

5

Fig. 4 is a right hand extended three-dimensional view of the vertical inductor of the invention with a large conductor width. The artwork that relates to the third embodiment of the invention is essentially identical to the artwork that has been shown as Figs. 2a through 2d, the same numbering scheme and related designations that have been shown in Fig. 2a apply to Fig. 4 with the exception of the parameter 38. The essential difference between the vertical spiral of the invention that is shown in Fig. 4 is that the conductor width 38 of Fig. 4a is considerably larger than the conductor width 21' that is shown in Fig. 2a. This increase in conductor width has as effect that the electromagnetic field of the vertical spiral inductor is further concentrated resulting in improved performance of Q factor, inductance and performance at higher frequencies, even though these improvements are achieved at the cost of a slightly increased surface area that is required for the creation

of the vertical spiral inductor of the third embodiment of the invention.

The device configuration of the vertical spiral inductor of the invention that is shown in Fig. 5 is identical to the configuration that is shown in Fig. 4 with the exception of the addition of ferromagnetic material 40 to the inductor. The ferromagnetic material is interposed between physically adjacent layers of the spiral construction and completely or partially takes the place of the dielectric 26' of Fig. 4.

Fig. 6 addresses the fifth embodiment of the invention, which is a vertical inductor of the invention whereby two vertical spiral inductors are connected in series. The construction of each of the two vertical spiral inductors can follow either the first embodiment of the invention, whereby narrow conductor width is used, or the second embodiment of the invention, whereby narrow conductor width with the incorporation of ferromagnetic material is used or the third embodiment of the invention, whereby wide connector width is used of the fourth

embodiment of the invention, whereby wide conductor width with the incorporation of ferromagnetic materials is used.

Fig. 6a is a right hand extended three-dimensional
5 view of vertical inductor of the invention whereby two vertical spiral inductors are connected in series. The first vertical inductor 42 is connected to the second vertical inductor 44 by means of the series connector 48. The input and output connections to the two vertical
10 spiral inductors is provided by the connectors 46 and 46'.

Fig. 6b shows a top view the vertical inductor of the invention whereby two vertical spiral inductors are connected in series. The various components that make up
15 the subject construction have previously been highlighted and are highlighted in Fig. 6b.

Fig. 6c shows a cross section in an X-direction of the vertical inductor of the invention whereby two
20 vertical spiral inductors are connected in series. The various components that make up the subject construction have previously been highlighted and are highlighted in Fig. 6c.

Fig. 6d shows a cross section in an Y-direction of the vertical inductor of the invention whereby two vertical spiral inductors are connected in series.

5 Fig. 7 is a right hand extended three dimensional view of vertical inductor of the invention whereby two vertical spiral inductors are connected in series whereby furthermore ferromagnetic material is incorporated. The first vertical spiral inductor 50 is connected to the
10 second vertical spiral inductor 52 by means of the series connector 56. Input/output connectors to the two vertical spiral inductors is provided by connectors 54 and 54'. Multi-layer ferromagnetic material that has been incorporated into each of the two vertical spiral
15 connectors is labeled 58.

Fig. 8 addresses the seventh embodiment of the invention, that is an inductor of the invention whereby the spirals of the inductor protrude from the vertical
20 plane of the inductor. This construction of the vertical spiral inductor further amplifies the magnetic field that is concentrated around the geometric center of the inductor, thereby increasing the Q value of the inductor.

Fig. 8a shows an expanded three-dimensional front side view of a vertical inductor of the invention whereby the spirals of the inductor progressively protrude from the body of the inductor. The protruding layers of the vertical inductor are labeled 60, 62 and 64 whereby the protruding feature can be observed by noticing that significant surface areas of these layers are not aligned with the top surface 66 but extend from the body of the vertical spiral inductor by a measurable amount.

10

Fig. 8b shows an expanded three-dimensional backside view of a vertical inductor of the invention whereby the spirals of the inductor progressively protrude from the body of the inductor. The protruding turns of the spiral inductor are now essentially hidden from view by the body of the vertical spiral inductor, the input/output connectors 68/68' are clearly visible.

Fig. 8c shows a cross section in an X-dimension of a vertical inductor of the invention whereby the spirals 64, 66 and 68 of the inductor progressively protrude from the body of the inductor.

Fig. 9 addresses an inductor of the invention whereby a horizontal spiral inductor is combined with a vertical spiral inductor whereby the horizontal inductor overlays the vertical inductor.

5

Fig. 9a shows a three-dimensional expanded right hand view of an inductor 70 of the invention whereby a horizontal spiral inductor 72 is connected in series with a vertical spiral inductor. Further shown in Fig. 9a are the input/output connection points 74 for the vertical inductor, the layers 76 of ferromagnetic material that has been inserted between the spirals of the inductor, the input/output connection points 78 for the horizontal inductor 72 and the point 80 of interconnect between the vertical inductor 70 and the horizontal inductor 72.

Fig. 9b shows a cross section taken in a plane that is perpendicular with the surface of the underlying substrate of an inductor of the invention whereby a horizontal spiral inductor 72 is connected in series with a vertical spiral inductor 70.

Fig. 10 addresses an inductor of the invention whereby a horizontal spiral inductor is combined with a

vertical spiral inductor whereby the horizontal inductor is located in the plane of the top layer of the vertical inductor, as follows:

5 Fig. 10a shows a three dimensional expanded right hand view of an inductor 70 of the invention whereby a horizontal spiral inductor 72 is connected in series with a vertical spiral inductor whereby furthermore the horizontal inductor is located in the plane of the top
10 layer of the vertical inductor. Input/output connections 84 for the horizontal spiral inductor 72 are indicated as are input/output connections 82 for the vertical spiral inductor 70 of the invention.

15 Fig. 10b shows a cross section taken in an X-direction in a plane that is perpendicular with the surface of the underlying substrate of an inductor 70 the invention whereby a horizontal spiral inductor 72 connected in series with a vertical spiral inductor 70
20 whereby furthermore the horizontal inductor 72 is located in the plane of the top layer of the vertical inductor.

Although the invention has been described and illustrated with reference to specific illustrative embodiments thereof, it is not intended that the invention be limited to those illustrative embodiments. Those
5 skilled in the art will recognize that variations and modifications can be made without departing from the spirit of the invention. It is therefore intended to include within the invention all such variations and modifications which fall within the scope of the appended
10 claims and equivalents thereof.

Claims

1. A structure of a vertical spiral inductor having a height H_c having a direction, having a width W_c having a direction, and having a length L_c having a direction, and a body whereby said body of said spiral conductor is bounded lengthwise and in a plane that is perpendicular to said surface of said substrate by a front surface and a back surface, whereby said vertical spiral conductor can be created on a surface of a silicon semiconductor substrate said surface having a plane, containing:
- a base horizontal conductor that is a horizontal conductor that is located closest to said surface of said substrate when compared with all other horizontal conductors;
 - a section of lower horizontal conductors and a section of upper horizontal conductors overlaying said base horizontal conductor whereby all horizontal conductors including said base horizontal conductor are separated by a space of height H_s in a direction that is perpendicular to said surface of said substrate whereby a plane in which said horizontal conductors are created is parallel to a plane of said surface of said substrate whereby said horizontal

conductors can be divided in lower horizontal conductors
and upper horizontal conductors;
a first input/output section located between said lower and
said upper horizontal conductors containing a horizontal
5 conductor of extended width that serves as one of two
input/output connectors to said spiral inductor in addition
to containing a point of connect to said lower horizontal
conductors;
a second input/output section containing a horizontal
10 conductor that serves as one of two input/output
connections to the spiral inductor; and
vertical connecting conductors separated by space H_s
whereby a plane of said vertical connecting conductors is
perpendicular to said plane of said horizontal conductors
15 whereby said vertical connecting conductors establish
electrical contact between horizontal conductors such that
a combined configuration of said horizontal conductors and
said vertical conductors forms a spiral.

20 2. The structure of claim 1 wherein each of said horizontal
conductors comprises:
a conductor length C_l in said direction L_c and in a plane
that is parallel to said surface of said substrate;

conductor sidewalls in a direction of said conductor length
and in a plane that is perpendicular to said surface of
said substrate henceforth referred to as lengthwise
horizontal conductor sidewalls;

- 5 a conductor width C_w in a said direction W_c and in a plane
that is parallel to said surface of said substrate whereby
said conductor width C_w is smaller than said conductor
length C_l ;

conductor sidewalls in a direction of said conductor width
10 and in a plane that is perpendicular to said surface of
said substrate henceforth referred to as widthwise
horizontal conductor sidewalls;

a conductor thickness C_h in a plane that is perpendicular
to said surface of said substrate;

- 15 a conductor upper surface in a plane that is parallel to
said surface of said substrate whereby said conductor upper
surface has a geometric shape of a rectangle;

a conductor lower surface in a plane that is parallel to
said surface of said substrate whereby said conductor lower
20 surface has a geometric shape of a rectangle; and

vertical interconnect surface areas that occupy opposing
extremities of either said conductor upper or lower surface
of said horizontal conductor in a direction of width of

said horizontal conductors whereby said vertical interconnect surface areas are used to establish contact with said vertical connecting conductors.

5 3. The structure of claim 1 wherein said horizontal conductors contain a multiplicity of horizontal conductors whereby:

all horizontal conductors are of equal width C_w therefrom excluding said first and second input/output conductors;

10 all horizontal conductors are of equal thickness C_h ; points of intercept of diagonals of said rectangles that form said geometric shape of said upper and lower surface of said horizontal conductors are located on two lines that are perpendicular to a surface of said substrate whereby a

15 first of said two lines applies to horizontal conductors that are located below said first input/output section of said vertical spiral inductor thereby including said base horizontal conductor while a second of said two lines applies to horizontal conductors that are located above
20 said first input/output section of said vertical spiral inductor;

a space separates adjacent horizontal conductors thereby including said base horizontal conductor;

a horizontal conductor that is furthest removed from said surface of said substrate when compared with all other horizontal conductors henceforth referred to as a second input/output horizontal conductor;

5 a multiplicity of lower level horizontal conductors overlying said base horizontal conductor that are equally spaced between said base horizontal conductor and said first input/output section whereby said length of adjacent horizontal conductors starting with a horizontal conductor

10 that is adjacent to said base horizontal conductor is reduced up to a point of height where said first input/output section is reached;

a first input/output horizontal conductor separated from said lower level conductors by a space of height H_s and

15 overlying said lower level horizontal conductors which is that horizontal conductor that has a smallest horizontal conductor length when compared with all other horizontal conductors whereby the width of said innermost horizontal conductor is extended said extension to serve as a first

20 input/output connection for said vertical spiral inductor said first input/output horizontal conductor being connected to said lower level horizontal conductors;

a multiplicity of upper level horizontal conductors overlying said first input/output section that are equally spaced between said first input/output section and said second input/output section whereby said length of adjacent horizontal conductors starting with a horizontal conductor that is adjacent to said first input/output section is increased up to a point of height where said second input/output section is reached; and a second input/output horizontal conductor overlying said upper level horizontal conductors and separated from said upper level horizontal conductors by a space of height H_s which is that horizontal conductor that has a largest horizontal conductor length when compared with all other horizontal conductors whereby a dimension of width of said innermost horizontal conductor is extended said extension to serve as a second input/output connection for said vertical spiral inductor.

4. The structure of claim 1 wherein each conductor of said vertical connecting conductors comprises:

a conductor height in said direction H_c in a plane that is perpendicular to said surface of said substrate;

a conductor width of W_c in said direction W_c in a plane that is parallel to said surface of said substrate;

a conductor thickness of H_b in said direction L_c in a plane that is parallel to said surface of said substrate;
a conductor cross section in a plane that is parallel to said surface of said substrate that has the shape of a
5 geometric rectangle;
a conductor upper surface in a plane that is perpendicular to said surface of said substrate;
a conductor lower surface in a plane that is perpendicular to said surface of said substrate;
10 two conductor sidewalls that are parallel with the length of said a vertical connecting conductor henceforth referred to as lengthwise vertical conductor sidewalls; and
two conductor sidewalls that are parallel with the width of said a vertical connecting conductor henceforth referred to
15 as widthwise vertical conductor sidewalls.

5. The structure of claim 1 wherein said vertical conductors contain a multiplicity of vertical conductors whereby:
20 the upper surface and lower surface of each vertical conductor has a geometric shape of a rectangle whereby opposing corners of each of said rectangles can be connected by two lines that form diagonals of said

rectangles whereby said diagonals have a point of intercept
whereby said points of intercept are located on a line that
is parallel to said surface of said substrate and further
is in a direction that is parallel with said conductor
5 lengthwise horizontal conductor sidewalls;
adjacent vertical conductors are separated by a space;
two vertical conductors henceforth referred to as outer
vertical conductors that are connected to said base
horizontal conductor whereby said connections are
10 established between said one of two widthwise vertical
conductor sidewalls of each of said outer vertical
conductors and said vertical interconnect surface areas on
said upper surface of said base horizontal conductor;
a multiplicity of vertical conductors that are spaced
15 between said outer vertical conductors whereby said height
of adjacent vertical conductors is adjusted such that the
combined structure of horizontal and vertical conductors
forms a spiral said spiral to be apparent in a cross
section of said body of said spiral inductor with a plane
20 that is perpendicular to said surface of said substrate
that furthermore is parallel with said lengthwise conductor
sidewalls of said horizontal conductors.

6. The structure of claim 1 wherein said conductor width is between about 4 and 10 times said conductor thickness.

7. The structure of claim 6 whereby said space between said
5 horizontal conductors and said space between said vertical interconnect conductors is filled with one or more layers of a dielectric.

8. The structure of claim 6 whereby said space between said
10 horizontal conductors and said space between said vertical interconnect conductors is filled with one or more layers of a ferromagnetic material.

9. The structure of claim 6 whereby two spiral inductors
15 are connected in series.

10. The structure of claim 1 wherein said conductor width is between about 10 and 50 times the conductor thickness.

20 11. The structure of claim 10 whereby said space between said horizontal conductors and said space between said vertical interconnect conductors is filled with one or more layers of a dielectric.

12. The structure of claim 10 whereby said space between said horizontal conductors and said space between said vertical interconnect conductors is filled with one or more layers of a ferromagnetic material.

5

13. The structure of claim 10 whereby two spiral inductors are connected in series.

14. The structure of claim 1 wherein said second
10 input/output section that contains one of two input/output connections to the spiral inductor comprises:
a main conductor having all attributes of said horizontal conductors;
a first and a second vertical interconnect surface area
15 that occupy opposing extremities of either said upper or lower surfaces of said main conductor in a direction of said widthwise horizontal conductor sidewalls whereby said first vertical interconnect surface area is used for establishing contact with the outer vertical connecting
20 conductors of which not both widthwise vertical sidewalls are in contact with horizontal conductors; and
an extension that is attached to said rectangle of said main conductor having two sidewalls in a plane that is

perpendicular to the surface of said substrate whereby one of said two sidewalls is an extension of that widthwise horizontal sidewall of said main conductor that has not previously been connected to a vertical conductor whereby
5 said extension preferably has a geometric shape of a rectangle.

15. The structure of claim 1 wherein each of said horizontal conductors thereby including said first and said
10 second input/output sections has a geometric shape of a rectangle whereby opposing corners of each of said rectangles can be connected with two lines that form diagonals of said rectangles whereby said diagonals have a point of intercept whereby said points of intercept for
15 said closest spaced horizontal conductor and said furthest spaced horizontal conductors are located on a line that is perpendicular to said surface of said substrate and forms a start and an end point of a line that interconnects said points of intercept of said diagonals of said horizontal
20 conductors whereby said line is located in a plane that is perpendicular to said surface of said substrate said plane furthermore being parallel with said lengthwise sidewalls of said horizontal conductors whereby said line is non-

linear thereby creating a spiral structure whereby spirals of said spiral inductor protrude from said body of said spiral inductor whereby said first and second input sections are further created as input/output connectors to
5 said vertical spiral conductor after said protrusion of said spiral inductor has been determined whereby said body of said spiral conductor is no longer bounded lengthwise and in a plane that is perpendicular to said surface of said substrate by a front surface and a back surface of
10 said vertical spiral inductor.

16. The structure of claim 15 wherein said line that interconnects said points of intercept of said diagonals of said horizontal conductors is a parabola.

15

17. The structure of claim 15 wherein said conductor width is between about 4 and 10 times said conductor thickness.

18. The structure of claim 15 whereby said space between
20 said horizontal conductors and said space between said vertical interconnect conductors is filled with one or more layers of a dielectric.

19. The structure of claim 15 whereby said space between said horizontal conductors and said space between said vertical interconnect conductors is filled with one or more layers of a ferromagnetic material.

5

20. The structure of claim 1 wherein said conductor width is between about 10 and 50 times the conductor thickness.

21. The structure of claim 20 whereby said space between
10 said horizontal conductors and said space between said vertical interconnect conductors is filled with one or more layers of a dielectric.

22. The structure of claim 20 whereby said space between
15 said horizontal conductors and said space between said vertical interconnect conductors is filled with one or more layers of a ferromagnetic material.

23. The structure of claim 1 whereby said vertical spiral
20 inductor is connected in series with a conventional horizontal inductor whereby said horizontal inductor overlays said vertical inductor.

24. The structure of claim 23 wherein space between spirals of said horizontal conductors and space between spirals of said vertical inductor is filled with one or more layers of dielectric material.

5

25. The structure of claim 23 wherein space between spirals of said horizontal conductors and space between spirals of said vertical inductor is filled with one or more layers of ferromagnetic material.

10

26. The structure of claim 1 whereby said vertical spiral inductor is connected in series with a conventional horizontal inductor whereby a plane of an upper surface of said horizontal inductor coincides with a plane of an upper surface of said vertical inductor.

15

27. The structure of claim 26 wherein space between spirals of said horizontal conductors and space between spirals of said vertical inductor is filled with one or more layers of dielectric material.

20

28. The structure of claim 26 wherein space between spirals of said horizontal conductors and space between spirals of

said vertical inductor is filled with one or more layers of ferromagnetic material.

29. A structure of a vertical spiral inductor having a body
5 that can be created on the surface of a silicon
semiconductor substrate, containing:
horizontal conductors separated by space having a
horizontal conductor width and thickness whereby said
horizontal conductors are parallel with said surface of
10 said substrate and that are separated by space;
vertical connecting conductors separated by space having a
vertical connecting conductor width and thickness whereby
said vertical connecting conductors are perpendicular to
said horizontal conductors and are separated by space
15 whereby said width of said vertical connecting conductor
equals said width of said horizontal conductors whereby
furthermore a direction of width of said vertical
connecting conductors coincides with a direction of width
of said horizontal conductors ;
20 areas of interconnect between said horizontal conductors
and said vertical conductors creating a structure such that
a cross section of said body of said vertical spiral
inductor taken in a plane that is perpendicular to said

surface of said substrate and perpendicular to said
direction of width of said horizontal conductors has a
geometric shape of a spiral;
an extension provided to an innermost horizontal conductor
5 that protrudes from the body of said vertical spiral
inductor and that serves as input/output connection to said
spiral inductor; and
a horizontal upper conductor that makes contact with a
vertical conductor of maximum longitudinal dimension that
10 has furthermore been provided with a conductor that is an
extension of said horizontal upper conductor in a direction
of width of said horizontal conductor whereby said
extension has a surface with a geometric shape of a
rectangle whereby said extension is provided on that side
15 of said horizontal upper conductor that is not connected to
a vertical conductor said extension to serve as an
input/output connection.

30. The structure of claim 29 whereby said horizontal
20 conductor width and said vertical connecting conductor
width are between about 6 and 10 times said horizontal and
vertical conductor thickness.

31. The structure of claim 30 whereby said space between said horizontal conductors and said vertical connecting conductors is filled with one or more layers of dielectric material.

5

32. The structure of claim 30 whereby said space between said horizontal conductors and said vertical connecting conductors is filled with one or more layers of ferromagnetic material.

10

33. The structure of claim 30 whereby two or more of said vertical spiral inductors are connected in series.

34. The structure of claim 30 whereby said vertical spiral inductor is connected in series with a conventional horizontal spiral inductor whereby said horizontal spiral inductor overlays said vertical spiral inductor.

35. The structure of claim 30 whereby said vertical spiral inductor is connected in series with a conventional horizontal spiral inductor whereby an upper surface of said horizontal spiral inductor is in a plane of an upper surface of said vertical spiral inductor.

36. The structure of claim 30 whereby said horizontal conductor width and said vertical connecting conductor width are between about 10 and 50 times said horizontal and vertical conductor thickness.

5

37. The structure of claim 36 whereby said space between said horizontal conductors and said vertical connecting conductors is filled with one or more layers of dielectric material.

10

38. The structure of claim 36 whereby said space between said horizontal conductors and said vertical connecting conductors is filled with one or more layers of ferromagnetic material.

15

39. The structure of claim 36 whereby two or more of said vertical spiral inductors are connected in series.

40. The structure of claim 36 whereby said vertical spiral inductor is connected in series with a conventional horizontal spiral inductor whereby said horizontal spiral inductor overlays said vertical spiral inductor.

20

41. The structure of claim 36 whereby said vertical spiral inductor is connected in series with a conventional horizontal spiral inductor whereby an upper surface of said horizontal spiral inductor is in a plane of an upper
5 surface of said vertical spiral inductor.

42. The structure of claim 36 whereby said horizontal and said vertical conductors are protruding from the body of said vertical spiral inductor whereby said protrusion is
10 most prominent and centered between a horizontal conductor of said spiral inductor that is closest to said surface of said substrate and a horizontal conductor that is furthest removed from said surface of said substrate with said protrusion further diminishing from a point of maximum
15 protrusion when proceeding in a direction of outermost vertical interconnecting conductors of said vertical spiral inductor.

43. The structure of claim 42 whereby said horizontal
20 conductor width and said vertical connecting conductor width are between about 6 and 10 times said horizontal and vertical conductor thickness.

44. The structure of claim 42 whereby said space between said horizontal conductors and said vertical connecting conductors is filled with one or more layers of dielectric material.

5

45. The structure of claim 42 whereby said space between said horizontal conductors and said vertical connecting conductors is filled with one or more layers of ferromagnetic material.

10

46. The structure of claim 42 whereby said horizontal conductor width and said vertical connecting conductor width are between about 10 and 50 times said horizontal and vertical conductor thickness.

15

47. The structure of claim 46 whereby said space between said horizontal conductors and said vertical connecting conductors is filled with one or more layers of dielectric material.

20

48. The structure of claim 46 whereby said space between said horizontal conductors and said vertical connecting

conductors is filled with one or more layers of ferromagnetic material.

49. A method of creating a vertical spiral inductor
- 5 containing horizontal and vertical conductors of a width W_c said width having a direction separated by spacing further containing a first and a second input/output connector, said vertical spiral inductor containing a body that is bounded by while including in said body a base horizontal
- 10 conductor, two outer vertical conductors and said second input/output connector, whereby said vertical spiral inductor can be viewed in a direction of width that is parallel with said surface of said substrate resulting in horizontal view one of said inductor, comprising the steps
- 15 of:
- providing a semiconductors substrate said substrate having a surface;
- depositing a base layer of dielectric having a surface over said surface of said substrate;
- 20 creating a base section of said vertical spiral inductor having a surface further having a height H_b and a width W_c said base section to be created on said surface of said base layer of dielectric;

creating a lower section of said vertical spiral inductor
having a height H_l said lower section to be created
overlying said surface of said base section;
creating a first input/output connector section having a
5 height H_{fio} further having a surface said first
input/output section to be created on said surface of said
lower section;
creating an upper section of said vertical spiral inductor
having a surface further having a height H_u said upper
10 section to be created on said surface of said first
input/output section;
creating a second input/output connector section having a
surface further having a height H_{sio} said second
input/output section to be created on said surface of said
15 upper section.

50. The method of claim 49 wherein said step of depositing
a base layer of dielectric is eliminated thereby creating
said base section of said vertical spiral inductor directly
20 on said surface of said substrate.

51. The method of claim 49 wherein said creating a base section of said vertical spiral inductor comprises the steps of:

depositing a first layer of dielectric having a surface

5 over said surface of said base layer of dielectric;

patterning and etching said first layer of dielectric thereby creating a trench in said first layer of dielectric for a base horizontal conductor;

depositing a first layer of metal over said surface of said

10 first layer of dielectric thereby filling said trench;

planarizing said first layer of metal down to said surface of said first layer of dielectric thereby creating a base horizontal conductor said base horizontal conductor having a surface, a length, a height, a width, a thickness and two

15 surface areas that are a subset of said surface of said base horizontal conductor and that serve as vertical conductor contact areas that occupy opposite extremities of said surface of said base horizontal conductor in a direction of width over the width of said base horizontal

20 conductor and in a direction of length that equals said thickness of said horizontal conductor whereby said vertical conductor contact areas can be divided into a right most vertical contact area and a left most vertical

contact area said division to be derived at by facing said vertical spiral in a direction of width of said vertical spiral in a plane that is parallel to said plane of said substrate.

5

52. The method of claim 49 wherein said creating a lower section of said vertical spiral inductor comprises the steps of:

depositing a second layer of dielectric over said base section of said vertical spiral thereby including said planarized surface of said base horizontal conductor whereby a thickness of said second layer of dielectric equals said spacing between said horizontal and said vertical conductors;

15 patterning and etching said second layer of dielectric thereby creating openings in said second layer of dielectric that align with said vertical contact areas in said base horizontal conductor;

depositing a third layer of dielectric over said second layer of dielectric;

20 patterning and etching said third layer of dielectric thereby creating a trench in said third layer of dielectric that aligns with said base horizontal conductor said trench

having a length whereby said length equals said length of
said base horizontal conductor minus two times the combined
value of said thickness of said vertical conductors and
said gap between said vertical conductors in addition to
5 creating openings in said third layer of dielectric that
align with said vertical contact areas in said base
horizontal conductor two vertical conductor contact areas
when facing said vertical spiral is a direction of width of
said horizontal conductors;
10 depositing a layer of metal over said surface of said third
layer of dielectric thereby including said trench and said
openings that have been created in said second and said
third layer of dielectric;
planarizing said layer of metal that has been deposited
15 over said surface of said third dielectric thereby creating
partial vertical conductors overlaying said vertical
conductor contact areas further creating a first horizontal
conductor said first horizontal conductor having a height
Hb further having a width Wc further containing two upper
20 surface areas that serve as vertical contact areas that
occupy opposite extremities of said surface of said first
horizontal conductor in a direction of width over the width
of said horizontal conductor and in a direction of length

that equals said thickness of said horizontal conductor
whereby said vertical conductor contact areas can be
divided into a right most vertical contact area and a left
most vertical contact area said division to be derived at
5 by facing said vertical spiral in a direction of width of
said vertical spiral in a plane that is parallel to said
plane of said substrate; and
repeating previous steps starting with depositing a second
layer of dielectric up through and including said
10 planarizing said layer of metal that has been deposited
over said surface of said third dielectric whereby for each
repetition an additional horizontal conductor to a
preceding horizontal conductor is created that aligns with
said preceding horizontal conductor of height H_b and width
15 W_c whereby a length for each additional horizontal
conductor equals a length of said preceding horizontal
conductor minus two times the combined value of said
thickness of said vertical conductor and said gap between
said vertical conductors while furthermore for each
20 repetition two additional extensions are created in said
second and third layer of dielectric that align with
vertical conductor contact areas of underlying horizontal
conductors said repetition to be continued until the

combined thickness of said second and third layer of dielectric equals said lower section height H1.

53. The method of claim 49 wherein said creating said first
5 input/output connector section comprises the steps of:
depositing a fourth layer of dielectric having a surface
over said surface of said lower section;
patterning and etching said fourth layer of dielectric
thereby creating an opening in aid fourth layer of
10 dielectric that aligns with a rightmost vertical conductor
contact area in a horizontal conductor that is exposed in
said surface of said lower section of said vertical spiral
conductor whereby said rightmost vertical conductor contact
area is the rightmost of said two vertical conductor
15 contact areas when facing said vertical spiral is a
direction of width of said horizontal conductors whereby
said rightmost opening is the opening that aligns with said
first input/output connector;
depositing a fifth layer of dielectric having a surface
20 over said surface of said fourth layer of dielectric;
patterning and etching said fifth layer of dielectric
thereby creating a trench in said fifth layer of dielectric
in addition to creating openings that align with said

underlying vertical contact areas of underlying horizontal
conductors whereby said trench aligns and makes contact
with said right most opening that has been created in said
fourth layer of dielectric whereby furthermore said trench
5 extends in said dimension of width of said horizontal
conductors by a considerable amount;
depositing a layer of metal over said surface of said fifth
layer of dielectric thereby including said trench and said
openings that have been created in said fifth layer of
10 dielectric; and
planarizing said layer of metal that has been deposited
over said surface of said fifth dielectric thereby creating
a first input/output connector.

15 54. The method of claim 49 wherein said creating an upper
section of said vertical spiral inductor is:
depositing a sixth layer of dielectric having a surface and
a seventh layer of dielectric having a surface over said
surface of said first input/output section of said vertical
20 spiral inductor;
forming a dual damascene pattern in said sixth and seventh
layer of dielectric said dual damascene pattern containing
a left most via and a right most via and a trench

connecting said left most via with said right most via
whereby said trench of said dual damascene pattern is
designed to contain a horizontal conductor whereby said
vias align with innermost partially completed vertical
5 conductors whereby furthermore said trench of said dual
damascene pattern is bounded by said vias;
depositing a layer of metal over said surface of said
seventh layer of dielectric thereby including said trench
and said openings that have been created in said sixth and
10 seventh layers of dielectric;
planarizing said layer of metal that has been deposited
over said surface of said seventh layer of dielectric
thereby creating a first horizontal conductor of said upper
section of said vertical spiral inductor;
15 repeating said steps of depositing a sixth and seventh
layer of dielectric thereby creating layers of horizontal
conductors that align with said first input/output
connector further having a length whereby said horizontal
conductors are progressively further removed from said
20 surface of said substrate whereby said length of said
trench of said dual damascene pattern is adjusted such that
the thereby created vias step wise expand from said
innermost partially completed vertical conductors and

further connect said horizontal conductors in said upper section of said vertical spiral with said horizontal conductor in said lower section in said vertical spiral in a spiral pattern said repetition to be continued to the point where the total thickness of the aggregate deposits of sixth and seventh layer of dielectric equals said H_u at which point one vertical conductor remains unconnected at a lengthwise extremity of this conductor that is furthest removed from said surface of said substrate whereby said unconnected vertical conductor aligns with said left most vertical conductor connect area in said surface of said base horizontal conductor.

55. The method of claim 49 wherein said creating a second input/output connector section comprises the steps of: depositing an eighth and ninth layer of dielectric having a surface over said surface of said upper section of said vertical spiral; creating and etching a dual damascene pattern in said eighth and ninth layer of dielectric whereby a via of said dual damascene pattern aligns with said unconnected remaining vertical conductor while furthermore a trench of said dual

damascene pattern extends in said dimension of width of
said horizontal conductors by a considerable amount;
depositing a layer of metal over said surface of said ninth
layer of dielectric thereby including said via that has
5 been created in said eighth layer of dielectric and said
trench that has been created in said ninth layer of
dielectric;
planarizing said layer of metal down to said surface of
said ninth layer of dielectric; and
10 depositing a layer of passivation material over said
surface of said ninth layer of dielectric thereby providing
environmental protection for said vertical spiral.

56. The method of claim 49 wherein each of said horizontal
15 conductors comprises:
a conductor length in a plane that is parallel to said
surface of said substrate;
conductor sidewalls in a direction of said conductor length
and in a plane that is perpendicular to said surface of
20 said substrate henceforth referred to as lengthwise
horizontal conductor sidewalls;

a conductor width in a plane that is parallel to said surface of said substrate whereby said conductor width is smaller than said conductor length;
conductor sidewalls in a direction of said conductor width
5 and in a plane that is perpendicular to said surface of said substrate henceforth referred to as widthwise horizontal conductor sidewalls;
a conductor thickness in a plane that is perpendicular to said surface of said substrate;
10 a conductor upper surface in a plane that is parallel to said surface of said substrate whereby said conductor upper surface has a geometric shape of a rectangle whereby opposing corners of each of said rectangles can be connected with two lines that form diagonals of said
15 rectangles whereby said diagonals have a point of intercept;
a conductor lower surface in a plane that is parallel to said surface of said substrate whereby said conductor lower surface has a geometric shape of a rectangle whereby
20 opposing corners of each of said rectangles can be connected with two lines that form diagonals of said rectangles whereby said diagonals have a point of intercept; and

vertical interconnect surface areas that occupy opposing
extremities of either said conductor upper or lower surface
of said horizontal conductor in a direction of width of
said horizontal conductors whereby said vertical
5 interconnect surface areas are used for establishing
contact with said vertical connecting conductors.

57. The method of claim 49 wherein each conductor of said
vertical connecting conductors comprises:

10 a conductor height in a plane that is perpendicular to said
surface of said substrate;
a conductor width in a plane that is parallel to said
surface of said substrate;
a conductor thickness in a plane that is parallel to said
15 surface of said substrate;
a conductor cross section in a plane that is parallel to
said surface of said substrate that has the shape of a
geometric rectangle;
a conductor upper surface in a plane that is perpendicular
20 to said surface of said substrate;
a conductor lower surface in a plane that is perpendicular
to said surface of said substrate;

two conductor sidewalls that are parallel with the length
of said a vertical connecting conductor henceforth referred
to as lengthwise vertical conductor sidewalls; and
two conductor sidewalls that are parallel with the width of
5 said a vertical connecting conductor henceforth referred to
as widthwise vertical conductor sidewalls.

58. The method of claim 49 wherein said conductor width
is between about 4 and 10 times said conductor thickness.

10

59. The method of claim 49 wherein each step of patterning
and etching to create openings and trenches in each of said
layers of dielectric that are used in said vertical spiral
inductor is preceded by the steps of:

15 patterning and etching said layer of dielectric whereby
said patterning uses the mirror image pattern of a pattern
that is used for patterning and etching to create openings
and trenches in each of said layers of dielectric for said
horizontal and vertical conductors whereby said mirror
20 image pattern is bounded by said base horizontal conductor,
said two outer vertical conductors and said second
input/output connector, hereby creating openings and
trenches in said layer of dielectric that are within said

bounds of said vertical spiral and that are mirror image openings and trenches to said horizontal and vertical conductors;

filling said mirror image openings and trenches with a
5 ferromagnetic material; and
planarizing said ferromagnetic material.

60. The structure of claim 49 whereby two spiral inductors are connected in series.

10

61. The structure of claim 49 wherein said conductor width is between about 10 and 50 times the conductor thickness.

62. The method of claim 49 wherein each of said horizontal conductors thereby including said first and said second
15 input/output connectors has a geometric shape of a rectangle whereby opposing corners of each of said rectangles can be connected with two lines that form diagonals of said rectangles whereby said diagonals have a point of intercept whereby said points of intercept for
20 said closest spaced horizontal conductor and said furthest spaced horizontal conductors are located on a line that is perpendicular to said surface of said substrate and form a start and an end point of a line that interconnects said

points of intercept of said diagonals of said horizontal
conductors whereby said line is located in a plane that is
perpendicular to said surface of said substrate said plane
furthermore being parallel with said lengthwise sidewalls
5 of said horizontal conductors whereby said line is non-
linear thereby creating a spiral structure whereby spirals
of said spiral inductor protrude from said body of said
spiral inductor.

10 63. The method of claim 62 wherein said conductor width
is between about 4 and 10 times said conductor thickness.

64. The method of claim 62 wherein each step of patterning
and etching to create openings and trenches in each of said
15 layers of dielectric that are used in said vertical spiral
inductor is preceded by the steps of:
patterning and etching said layer of dielectric whereby
said patterning uses the mirror image pattern of a pattern
that is used patterning and etching to create openings and
20 trenches in each of said layers of dielectric thereby
creating mirror image openings and trenches;
filling said mirror image openings and trenches with a
ferromagnetic material; and

planarizing said ferromagnetic material.

65. The structure of claim 62 whereby two spiral inductors are connected in series.

5

66. The structure of claim 62 wherein said conductor width is between about 10 and 50 times the conductor thickness.

67. The method of claim 66 wherein each step of patterning
10 and etching to create openings and trenches in each of said layers of dielectric that are used in said vertical spiral inductor is preceded by the steps of:

patterning and etching said layer of dielectric whereby
said patterning uses the mirror image pattern of a pattern
15 that is used patterning and etching to create openings and trenches in each of said layers of dielectric thereby creating mirror image openings and trenches;
filling said mirror image openings and trenches with a
ferromagnetic material; and
20 planarizing said ferromagnetic material.

68. The structure of claim 66 whereby two spiral inductors are connected in series.

69. The method of claim 49 wherein said creating said first input/output connector section comprises the steps of:
depositing a fourth layer of dielectric having a surface over said surface of said lower section;
5 patterning and etching said fourth layer of dielectric thereby creating an opening in said fourth layer of dielectric that aligns with a leftmost vertical conductor contact area in a horizontal conductor that is exposed in said surface of said lower section of said vertical
10 conductor whereby said leftmost vertical conductor contact area is the leftmost of said two vertical conductor contact areas when facing said vertical spiral coil in a direction of width of said horizontal conductors whereby said leftmost opening is the opening that aligns with said first
15 input/output connector;
depositing a fifth layer of dielectric having a surface over said surface of said fourth layer of dielectric;
patterning and etching said fifth layer of dielectric thereby creating a trench in said fifth layer of dielectric
20 in addition to creating openings that align with said underlying vertical contact areas of underlying horizontal conductors whereby said trench aligns and makes contact with said leftmost opening that has been created in said

fourth layer of dielectric whereby furthermore said trench extends in said dimension of width of said horizontal conductors by a considerable amount; depositing a layer of metal over said surface of said fifth layer of dielectric thereby including said trench and said openings that have been created in said fifth layer of dielectric; and planarizing said layer of metal that has been deposited over said surface of said fifth dielectric thereby creating a first input/output connector.

70. The method of claim 49 wherein said horizontal view one of said vertical spiral inductor shows said spiral of said vertical spiral inductor whereby said spiral starts at said first input/output connector and further continues by following interconnected vertical and horizontal conductors of said vertical spiral inductor in a clock-wise direction.

71. The method of claim 49 wherein said horizontal view one of said vertical spiral inductor shows said spiral of said vertical spiral inductor whereby said spiral starts at said first input/output connector and further continues by following interconnected vertical and horizontal conductors

of said vertical spiral inductor in a counter clock-wise direction.