

Description

The present invention relates to wideband packet communication networks, and to methods of transmitting information between a plurality of transmitters and a central node.

Local Area Networks (LANs) have included many different architectures such as the bus, loop, ring, star, tree, etc. One such LAN is disclosed in the article "A New Local Area Network Architecture Using A Centralized Bus" by A. Acampora et al. in IEEE Communications Magazine, Vol. 22, No. 8, August 1984, at pages 12-21. There, a centralized bus is used with all user devices being hard-wired to a central node as shown in FIGs. 1-3 of the article.

Indoor wireless communications networks have also been developed over the years. In the article "Cordless Telephone System" by M. Komura et al., published in the Japanese Telecommunications Review, Vol. 15, No. 4, 1973, at pages 257-261, a cordless radio telephone system is disclosed which permits telephones to communicate via radio to a localized antenna which is directly connected to a base station. Another technique for wireless indoor communication is disclosed by F. Gfeller in the IBM Technical Disclosure Bulletin, Vol. 24, No. 8, January 1982, at pages 4043-4046 wherein an infrared micro-broadcasting network for in-house data communication is disclosed. There, a host controller is directly connected to a plurality of spaced-apart transponders for transmitting 2-way communications via infrared signals with the various stations forming the in-house system.

More recently, an office information network was disclosed in Globecom '85, Vol. 1, December 2-5, 1985, New Orleans, Louisiana, at pages 15.2.1-15.2.6 wherein a slotted-ring access protocol and a dynamic bandwidth allocation scheme offering preferential service to high-priority traffic is provided. There, a dual optical fiber ring, transmitting in opposite directions, propagates the communication signals to various nodes along the fibers. Connections between the network nodes and local facilities or servers are copper pairs or, where appropriate, wireless drops.

Indoor radio communication is not without problems, however. Buildings in general, and office buildings in particular, present a harsh environment for high-speed radio transmission because of numerous reflections from stationary objects such as walls, furniture, and movable objects such as people. The link between a given pair of transmitters and receivers is thereby corrupted by severe multipath distortion arising from the random superimposition of all reflected rays, and by shadow fading caused by the absence of line-of-sight paths. At low data rates, the effects of multipath can be characterized by Rayleigh fading, while at higher rates the channel additionally exhibits

dispersion over the communication band. Shadow fading is spectrally flat and characterized by a log-normal distribution.

It is to be understood that all effects vary dynamically with time as the environment slowly changes. Rayleigh fading produces a wide variation in the level of signals arriving at a particular receiver from different transmitters, thereby precluding the use of standard techniques for multiple access of the radio channel. Dispersion within the channel produces serious intersymbol interference, thereby limiting the maximum data rate of the channel and causing a fraction of users to experience an unacceptably high bit error rate, and a link experiencing such condition is said to have suffered an outage and is temporarily unavailable. Therefore, the problem in the prior art is to provide a technique or network which will permit as high a data rate as possible while encountering changing conditions.

US-A-4466001 discloses a system for polling multiple terminals units from a base station. The base station transmits a reference signal which each terminal uses as a sync signal. Each terminal unit having data to send to the base station responds with a signal during an assigned time slot in a queue of slots. Those units which respond are polled during a subsequent polling cycle. The address code of a terminal unit is encoded to carry other information in both directions.

According to one aspect of this invention there is provided a wideband packet communication network as claimed in claim 1.

According to another aspect of this invention there is provided a method as claimed in claim 7.

An exemplary wideband indoor packet communications network may comprise (1) a plurality of transceivers; and (2) a central node. In addition, one or more concentrators associated with certain separate groups of wireless, and possibly hard-wired, transceivers, may be present. Each transceiver is associated with a separate user of the network, and, some or all of the plurality of transceivers communicate wirelessly with associated interface units in the concentrators or central node. The central node comprises (a) means for determining and communicating the necessary transmission requirements to each of the active plurality of wireless transceivers during a first subperiod of each frame period, and (b) means for receiving packets of information from each of the plurality of transceivers, transmitted as instructed by the communicating means, and retransmitting the packets to the transceivers of the destined users during a second subperiod of the frame period. More particularly, the communicating means of the central node (i) determines the packet transmission requirements and any transmission impairments of each network user when communicating with the associated interface unit in a concentrator or central node, and (ii)

causes the transceivers associated with users determined to have packet transmission requirements to transmit their packets of information with a length sufficient to overcome the determined transmission impairment. Additionally, (1) diversity antennas can be used at the concentrators and central node, and one or more antennas can be used at each transceiver, and (2) access to the radio channel used by all wireless transceivers can be performed by a modified polling scheme which permits resource sharing to provide added protection against channel impairments on an as-needed basis.

Brief Description of the Drawing

FIG. 1 is a block diagram of an exemplary arrangement of a wideband communication network embodying the present invention including various hard-wired and wireless user connections; and

FIG. 2 is a diagram of a media access technique using polling that can be employed in the network of FIG. 1.

Detailed Description

FIG. 1 illustrates an exemplary system topology which is functionally that of a star Local Area Network (LAN) comprising a central node 30, remote concentrators 20 and 21, and a plurality of user devices 10-19. Each user device 10-19 is associated with a separate user of the network and can communicate with central node 30 (1) via a hard-wired connection 26, as shown for the indirect connections between user devices 10-13 and concentrators 20 and 21; or (2) via a wireless link as shown for (a) the channel comprising links 27 between a subgroup of user devices 18-19 and central node 30, or (b) the indirect channel comprising links 28 between a subgroup of users 14-15 and a subgroup of users 16-17 and concentrators 20 and 21, respectively. It is to be understood that user devices 10-19 can each be coupled to a separate user terminal (not shown) such as, for example, a data device, printer, personal computer, host computer, telephone, etc.

Each of remote concentrators 20 and 21 is positioned between the associated subgroup of user terminals 10-17 and central node 30 and is shown as including (a) user interface modules (UIM) 22 and 23 which are each coupled to a separate portion of the associated subgroup of user devices (UDs) 10-17, (b) a clock module (24), and (c) a trunk module 25. It is to be understood that each of exemplary concentrators 20 and 21 includes only two UIMs, for purposes of simplicity and that additional UIMs could be disposed in parallel with UIMs 22-23 shown, and connected to other portions of the associated user devices (not shown) via either separate hard-wired or wire-

less connections.

Each UIM 22 or 23 functions to translate the protocol of the signal received from the associated user devices to a standard protocol of the network as used by central node 30. The translated signal is then transmitted, at the appropriate time, to trunk module 25 on a time division multiplex (TDM) basis via a concentrator bus 29, for transmission to central node 30, and vice versa for the other direction of two-way communications using concentrator bus 29. Where a user device already transmits and receives signals using the standard network protocol, an associated UIM need only transmit the received signal at the appropriate time based on the received clock signals from clock module 24. The trunk module 25 in each of remote concentrators 20 and 21 functions to transmit each of the signals associated with that concentrator between each of the UIMs 22 and 23 and central node 30 at the appropriate times. The clock modules 24 provide the timing signals for each of the UIMs 22 and 23, and trunk module 25 to achieve coordinated operation within the associated remote concentrator 20 or 21. Central node 30 is shown as including a clock module 31 for providing the clock signals used in central node 30; network interface units (NIU) 32-34 which are each coupled either to a separate one of remote concentrators 20 or 21 or to a separate subgroup of one or more user devices; a call processor 35; and buses 36 and 37.

To describe the operation of the present network, the network components associated only with hard-wired user devices, e.g., user devices 10-13, UIMs 22 and NIUs 32 and 34 will first be considered. Each hard-wired user device 10-13 is shown connected to the network via terminal interface wires 26 and a UIM 22. Continuous (voice) or bursty (data) traffic arriving at UIM 22 in concentrator 20 from user devices 10-11, or at UIM 22 in concentrator 21 from user devices 12-13, are formed into fixed length packets for time-multiplexed high speed transmission to central node 30 via trunk module 25. Each such packet is provided therein with a logical channel number which allows central node 30 to re-route the packet to the appropriate concentrator 20 or 21 where the indicated destination user's device is connected. Central node 30 includes a contention bus 36, 37 operating at the speed of each high speed link, to accomplish this re-routing. All traffic, including that traffic arising at a particular concentrator 20 or 21 and destined for that same concentrator, is routed through central node 30.

The receiving concentrator demultiplexes all arriving packets from central node 30 for distribution via bus 29, to the appropriate UIM and transmission to the destined user device. Logical channel numbers are preferably assigned for the entire network at the beginning of a predetermined time period of communications by call processor 35 in central node 30. Additional device configurations and operational details

are described in the article "A New Local Area Network Architecture Using A Centralized Bus" by Acampora et al. in IEEE Communications Magazine, Vol. 22, No. 8, August 1984, at pages 12-21.

Radio links may be introduced, as shown in FIG. 1, via either a wireless link between a UIM 23 in either one of concentrators 20 or 21 as shown for link 28, or a wireless link directly to a NIU 33 in central node 30 as shown for link 27. For link 27, the high-speed links from trunk modules 25 in concentrators 20 and 21 to central node 30 have been augmented by the inclusion of an NIU 33 in central node 30 which becomes a radio base station providing a high-speed channel to collect traffic from a subgroup of radio user devices 18-19 located throughout the building. It is to be understood that the term channel hereinafter implies full duplex operation, with separate bands used to transmit to and receive from NIU 33. This radio channel operates at a rate less than or equal to that of the central node's contention buses 36 and 37 and each of the high-speed links between trunk modules 25 and NIUs 32 and 34. With an appropriate access protocol, the radio channel may be shared among all radio users 18-19 and appear, to central node 30, as a virtual concentrator. Fixed length packets arriving over links 27 contend for the nodal bus 36 along with packets arriving via high-speed buses at NIUs 32 and 34 from trunk modules 25. The packets arriving from the wired links 26 may be rerouted by central node 30 to a radio link 27, and vice-versa, according to a destination address included in each packet.

A wireless link 28 establishes a communication path from each user of a subgroup of users 14-15 or 16-17, to an associated UIM 23 in one of remote concentrators 20 or 21. Although multiple paths are established within a subgroup of users associated with a UIM 23 or NIU 33, these links time-share a single radio channel. More particularly, at any moment, only one radio user of a subgroup of users may access the radio channel. It should be noted that there is no need to provide an aggregate data rate over all radio links 27 or 28 in excess of the transmission speed of central node 30 since all packets must be routed through central node 30. Therefore, it is pointless to reuse the radio channel among user subgroups, as this increased capacity could not be used. Thus, by sharing a single channel, operating at the speed of central node 30, among all radio users, each user can potentially access the full system bandwidth, and interference among clusters caused by simultaneous use of the channel by users in different clusters is avoided. From the perspective of central node 30, a radio link 28 established from each concentrator 20 or 21 to each of its subgroups of radio users appears as another wired port (UIM 22) on the concentrator.

Regarding the radio or wireless links only, each of the UIMs 23 or NIU 33 are preferably equipped with multiple antennas for diversity to protect against mul-

tipath fading, and each user device 14-19 is preferably equipped with only a single antenna, although multiple antennas could be used. The combination of limited diversity at the concentrators 20 and 21, and central node 30, along with resource sharing can be used to provide arbitrarily high availability. No direct communication is permitted among users, since all users may communicate only with concentrators 20 and 21 or central node 30. It should be understood that common media access techniques, such as Carrier Sense Multiple Access (CSMA), are inappropriate in the radio environment because free space path loss and multipath fading result in too large a variation of signal strength to insure that all channel usage can be detected. To keep the wireless user devices 14-19 inexpensive, sophisticated timing requirements should be avoided. Finally, because of problems with delay spread, it is desired that the throughput of the system not be significantly reduced by a media access technique, and separate receive and transmit channels must be provided to allow full duplex operation.

For the present network shown in FIG. 1, an exemplary modified polling technique is used, with central node 30 controlling the transmit token. Polling is performed by call processor 35 in central node 30; with the radio UIMs 23, located at concentrators 20 and 21, and NIU 33, located at central node 30, being slaved to processor 35 such that, at any point in time, only one UIM 23 or NIU 33 is allowed to transmit the token to its community of UD's. It should be understood that all of radio UD's 14-19 time share a single radio channel without frequency reuse.

The present exemplary polling technique for use with the radio channel associated with the wireless UD's 14-19 is shown in FIG. 2. There, time is divided into a sequence of fixed length intervals called frames, as shown at the top of FIG. 2. At the start of each frame a polling interval 40 appears, followed by multiple intervals for transmission of continuous (voice) traffic packets 41, and bursty (data) traffic packets 42. The length of the continuous traffic intervals 41 depends on the amount of continuous traffic. This continuous traffic is transmitted periodically, at least once per frame period, with the time interval between continuous traffic intervals used for bursty traffic. Transmission of one fixed length packet per continuous traffic interval constitutes some standard grade service, e.g., 64 kbps. Continuous traffic UD's may request multiples of this basic rate by accessing multiple time slots per continuous traffic interval. The polling sequence is shown at the bottom two lines of FIG. 2 for transmissions from and to central node 30.

The following steps forming the exemplary overall transmission sequence for the radio channel are:

1. Via the UIMs 23 located at concentrators 20 and 21, and NIU 33, call processor 35 at central node 30 sequentially polls each UD associated

with the radio channel using sub-packets P1-PN.

2. When polled, UDs 14-19 sequentially respond, after being polled, using the associated one of packets R1-RN as to whether the UD has continuous or bursty traffic, and, if bursty traffic, the number of blocks of data.

3. Processor 35 then sequentially sends a signal, i.e., transmit token, $TS-TS_j$, to each continuous traffic user to send one fixed length packet, designated V_1 to V_j , including a preset number of data symbols in each packet.

4. Processor 35 then sequentially sends a signal, designated TS_K-TS_L , i.e., a transmit token, to each bursty traffic user to send their first data block designated packets D_K-D_L , then the second data block, etc.

5. During steps 3 and 4, while the UDs are transmitting to concentrators 20 and 21 in blocks V_1-V_j and D_K-D_L , processor 35, through the UIMs 23 at the concentrators, is transmitting voice and data to the UDs 14-17 in associated blocks 44.

6. When it is time again for continuous traffic to be transmitted, then step 3 is reiterated.

7. When it is time again for polling, i.e., the beginning of another frame, then step 1 is reiterated.

The above described polling technique meets necessary requirements since (a) the system handles continuous traffic, i.e., periodic data or voice, with priority, (b) the system has the same maximum data rate for each user, i.e., a fair distribution of resources, which depends on the system loading, (c) there is no timing requirements at the remote UDs 14-19, (d) the throughput on the channel is not significantly reduced by this technique because the polling has a low duty cycle, mainly due to the short propagation delays between the concentrators 20, 21 and the remote UDs 14-19, and (e) the system has duplex operation.

What must also be considered is that in a multipath environment, paths of different lengths cause delay spread at a receiver. The delay spread, i.e., the dispersion or frequency selective fading in the channel, produces intersymbol interference which limits the maximum data rate in a given building and depends primarily on the rms delay spread and not the delay spread function. Thus, within the coverage area, there is some probability that the received signal bit error rate (BER) for each UD is more than the required value, hereinafter called the outage probability. If one UD 14-19 does not work in one location, the user can move the UD or its antenna. However, the delay spread may vary slowly with time as people and objects move within the building. Therefore, it is desirable to keep the outage probability due to delay spread as low as possible so that the wireless system is almost as reliable as any wired portion of the system.

In addition to the technique described above, resource sharing can be used to increase the maximum

data rate and/or decrease the outage probability. With resource sharing, users normally transmit at some high rate R_1 . When channel conditions between concentrators 20 or 21, or central node 30, and a particular UD no longer permits operation at this high rate, the rate is lowered to some value such as R_2 such that the BER objective is maintained. Such techniques are well known in the satellite system art as disclosed, for example, in the articles by A. S. Acampora in BSTJ, Vol. 58, No. 9, November 1979, at pages 2097-2111; and IEEE Journal On Selected Areas In Communications, Vol. SAC-1, Jan. 1983, at pages 133-142 where a pool of spare time slots are used, and each packet is transmitted with or without coding, to reduce the outage probability. Although it takes longer to complete transmission at this lower rate, the number of users simultaneously slowed down is usually a small fraction of the total population, and the overall throughput remains high. More particularly, during non-fade conditions, convolutional codes with a large channel signaling alphabet are employed to permit a high rate of information transfer as described hereinbefore for the 7-step transmission sequence, and when the fade depth exceeds the built in fade margin, the signaling alphabet is reduced and enough time slots are borrowed from a resource sharing reserved time slot pool to maintain the data rate at the fade site. From the prior art, it is known that a small pool of spare time slots can protect a large community of users. In the present technique, the use of coding during fade events is not considered because the channel is dispersive.

Implementation of resource sharing with two transmission rates requires modification of the 7-step media access technique described hereinbefore. With resource sharing, transmission would normally be at the higher rate R_1 during non-transmission impairment periods. If errors are detected at the higher rate via standard error detection techniques, a receiver in UDs 14-19, UIMs 23, or NIU 33 can request call processor 35 to schedule a retransmission of the last block of data at the lower rate R_2 . Call processor 35 would then cause the transmitter to retransmit the last block of information during a subsequent corresponding continuous 41 or bursty 42 traffic period at the lower data using, for example, a longer block V_1 , D_1 , or 44, or two or more equal length blocks. A transmitter for accomplishing such technique of resource sharing is described, for example, in U.S. patent 4,309,764 issued to A. Acampora on January 5, 1982, and the previously cited article to A. Acampora in BSTJ, Vol. 58, No. 9, November 1979, at pages 2097-2111. Periodically the transmitter can retry transmission at the higher rate. The frequency of retries depends on the dynamics of the delay spread in the channel. Requests for lower rate transmission and retries at the higher rate need only occur infrequently since the channel normally varies very slowly with



time.

Claims

1. A wideband packet communication network comprising a plurality of transmitters (10-19), each transmitter being associated with a separate user or group of users for transmitting packets of information, and a central node (30) for communicating with each of the plurality of transmitters via a hard-wired or wireless connection and comprising processor means (35) for (a) determining packet transmission requirements associated with each transmitter communicating with the central node via a wireless connection during a first subperiod of each frame period, and (b) causing each wireless transmitter determined to have a packet transmission requirement to transmit its packets of information during a separate second subperiod of time of each frame period, CHARACTERIZED IN THAT the processor means serves also for (c) detecting during the first and/or second subperiods of each frame period transmission impairments associated with each wireless transmitter, and (d) causing packets of information transmitted from each transmitter determined to have a transmission impairment to be transmitted at a transmission rate sufficient to lessen the determined transmission impairment, and the central node comprises means (32-34) for (a) receiving packets of information from the plurality of transmitters, and (b) retransmitting the packets to receivers associated with the destined users of the packets of information via an appropriate hard-wired or wireless connection.
2. A network according to claim 1 wherein the receiving and retransmitting means comprises a high-speed bus (36,37) for propagating packets of information from the plurality of transmitters on a time division multiplexed basis, and a plurality of network interface units (NIUs) (32-34), each NIU being associated with a separate subgroup of one or more of the plurality of transmitters, and connected to the transmitters of the separate subgroup via a wireless communication link or separate hard-wired connections for receiving the packets of information from the associated subgroup of transmitters and transmitting each packet over the high-speed bus during a free time slot period to the NIU associated with a user destined to receive the packet of information.
3. A network according to claim 2 comprising at least one concentrator (20,21), the or each con-

centrator being disposed between a separate subgroup of the plurality of transmitters and a predetermined one of the plurality of NIUs, the or each concentrator comprising a plurality of user interface modules (UIM) (22,23), each UIM providing duplex communications with a separate portion of the subgroup of transmitters associated with that concentrator, where at least one of the subgroup portions communicates with its UIM via a separate wireless link, a trunk module (25) for providing duplex communications between the UIMs of the concentrator and the predetermined associated one of the plurality of NIUs in the central node on a time division multiplexed basis, and a bus (29_a, 29_b) for propagating packets of information between the plurality of UIMs of the concentrator and the trunk module on a time division multiplexed basis.

4. A network according to claim 1, 2 or 3 wherein the processor means comprises means responsive to the beginning of a frame period for (a) sequentially sending first control signals (P_i) to each of the plurality of transmitters and sequentially receiving second control signals (R_i) from the transmitters indicative of whether or not a transmitter has a packet of information to be transmitted during the frame period, and (b) in response to each received second control signal indicating that a transmitter is active and has a packet information to be sent, sequentially transmitting third control signals (TS_i) to the active transmitters for causing the packet of information to be sent by the transmitter for routing by the central node to a destined user of the packet of information.
5. A network according to claim 1, 2, 3 or 4 wherein the receiving and retransmitting means comprises means for detecting that a packet of information was received from a transmitter with a bit error rate that is more than a predetermined value, and for generating a separate transmission impairment control signal, and the processor means is responsive to a transmission impairment control signal from the receiving and retransmitting means for transmitting a subsequent control signal to the transmitter detected as having a transmission impairment for causing the transmitter to retransmit the packet of information at a slower data rate using a predetermined resource sharing technique.
6. A network according to any preceding claim wherein the receiving and retransmitting means includes diversity antennas associated with the wireless connections.



7. A method of transmitting information between a plurality of transmitters (10-19) and a central node (30), comprising processor means (35), via either one of a hard-wired or wireless connection during a frame period in a wideband packet communication network, each transmitter being associated with a separate user or group of users, the method comprising the steps of

(a) the processor means determining the packet transmission requirements of each transmitter communicating with the central node during a first subperiod of time of each frame period, and

(b) causing a wireless transmitter determined in step (a) to have packet transmission requirements, to transmit its packets of information during a separate second subperiod of time of each frame period,

CHARACTERIZED BY

(c) the processor means detecting, during the first and/or second subperiods of time of each frame period, transmission impairments associated with each wireless transmitter, and

(d) the processor means causing packets of information transmitted from each transmitter determined to have a transmission impairment in step (c) to be transmitted at a transmission rate sufficient to lessen the determined transmission impairment.

8. A method according to claim 7 comprising in step (a) the substeps of

(a1) the processor means sequentially transmitting first control signals (P_i) to each of the plurality of transmitters, and
(a2) sequentially receiving second control signals (R_i) from the plurality of transmitters indicative of whether or not a transmitter has a packet of information to be transmitted during the frame period, and

in step (b), the step of

(b1) in response to each received second control signal in step (a2) indicating that a transmitter is active and has a packet of information to be sent, sequentially transmitting third control signals (TS_i) to the active transmitters for causing the packet of information to be sent by the transmitter for routing by the central node to a destined user of the packet of information.

9. A method according to claim 7 or 8 comprising in step (c) the substeps of

(c1) detecting at the central node that a packet of information was received from a transmitter with a bit error rate that is more than a predetermined value,
(c2) transmitting a subsequent control signal

to the transmitter detected as having a transmission impairment in response to the detection of a bit error rate more than a predetermined value in step (c1), and

(c3) a transmitter having a transmission impairment being responsive to the subsequent control signal transmitted in step (c2) for retransmitting the packet of information at a slower transmission rate using a predetermined resource sharing technique such that the packet of information is received at the central node with a bit error rate below the predetermined value.

Patentansprüche

1. Breitband-Paketübertragungsnetzwerk mit einer Vielzahl von Sendern (10-19), die je einen getrennten Benutzer oder einer getrennten Benutzergruppe zur Übertragung von Informationspaketen zugeordnet sind, und einem zentralen Knoten (30), der mit jedem Sender über eine verdrahtete oder drahtlose Verbindung in Nachrichtenverbindung steht und eine Prozessoreinrichtung (35) aufweist, die (a) Paketübertragungsanforderungen in Verbindung mit jedem Sender bestimmt, der mit dem zentralen Knoten über eine drahtlose Verbindung während einer ersten Unterperiode jeder Rahmenperiode in Nachrichtenverbindung steht, und die (b) jeden drahtlosen Sender, für den eine Paketübertragungsanforderung bestimmt worden ist, veranlaßt, seine Informationspakete während einer zweiten Unterperiode jeder Rahmenperiode zu übertragen, dadurch gekennzeichnet, daß die Prozessoreinrichtung außerdem (c) während der ersten und/oder zweiten Unterperiode jeder Rahmenperiode Übertragungsbeeinträchtigungen in Verbindung mit jedem drahtlosen Sender feststellt und (d) veranlaßt, daß von jedem Sender, für den eine Übertragungsbeeinträchtigung festgestellt worden ist, übertragene Informationspakete mit einer Übertragungsrate übertragen werden, die zur Verringerung der festgestellten Übertragungsbeeinträchtigung ausreicht, und daß der zentrale Knoten eine Einrichtung (32-34) aufweist, die (a) Informationspakete von der Vielzahl von Sendern aufnimmt und (b) die Pakete zu festgelegten Benutzern der Pakete zugeordneten Empfängern über eine verdrahtete oder drahtlose Verbindung erneut aussendet.
2. Netzwerk nach Anspruch 1, bei dem die Empfangs- und die Neuaussendungseinrichtung einen Hochgeschwindigkeitsbus (36,37) zur Weiterleitung von Informationspaketen von der Vielzahl von Sendern auf einer Zeitmultiplexbasis sowie



eine Vielzahl von Netzwerk-Schnittstelleneinheiten (NIUs) (32-34) aufweist, wobei jede NIU einer getrennten Untergruppe mit einem oder mehreren Sendern zugeordnet und mit den Sendern der getrennten Untergruppe über eine drahtlose Verbindungseinrichtung oder getrennte, verdrahtete Verbindungen zur Aufnahme der Informationspakete von der zugeordneten Untergruppe von Sendern sowie zur Übertragung jedes Pakets über den Hochgeschwindigkeitsbus während einer freien Zeitlagenperiode zu der NIU verbunden ist, die einem zum Empfang des Informationspakets vorgesehenen Benutzer zugeordnet ist.

3. Netzwerk nach Anspruch 2 mit wenigstens einem Konzentrator (20,21), der oder von denen jeder zwischen einer getrennten Untergruppe der Vielzahl von Sendern und einer vorbestimmten NIU angeordnet ist, wobei der bzw. jeder Konzentrator eine Vielzahl von Benutzer-Schnittstellenmodulen (UIM) (22,23) aufweist und jedes UIM Duplexübertragungen mit einem getrennten Teil der diesem Konzentrator zugeordneten Untergruppe von Sendern bereitstellt, wobei wenigstens einer der Untergruppenteile mit ihrem UIM über eine getrennte drahtlose Verbindung in Nachrichtenverbindung steht, ein Verbindungsleitungsmodul (25) zur Bereitstellung von Duplexübertragungen zwischen den UIMs des Konzentrators und der vorbestimmten, zugeordneten NIU der Vielzahl von NIUs im zentralen Knoten auf einer Zeitmultiplexbasis vorgesehen ist, sowie ein Bus (29_a, 29_b) zur Übertragung von Informationspaketen zwischen der Vielzahl von UIMs des Konzentrators und dem Verbindungsleitungsmodul auf einer Zeitmultiplexbasis.

4. Netzwerk nach Anspruch 1, 2 oder 3, bei dem die Prozessoreinrichtung eine Einrichtung aufweist, die unter Ansprechen auf den Beginn einer Rahmenperiode (a) sequentiell erste Steuersignale (P_i) zu jedem der Vielzahl von Sendern aussendet und sequentiell zweite Steuersignale (R_i) von den Sendern empfängt, die anzeigen, ob bei einem Sender ein Informationspaket während der Rahmenperiode auszusenden ist oder nicht, und die (b) unter Ansprechen auf jedes empfangene, zweite Steuersignal, das anzeigt, daß ein Sender aktiv ist und ein auszusendendes Informationspaket aufweist, sequentiell dritte Steuersignale (TS_i) zu den aktiven Sendern überträgt, um die Aussendung des Informationspakets durch den Sender und eine Übertragung zu dem angegebenen Benutzer des Informationspakets durch den zentralen Knoten zu veranlassen.

5. Netzwerk nach Anspruch 1, 2, 3 oder 4, bei dem

die Empfangs- und Neuaussendungseinrichtung eine Einrichtung aufweist, die feststellt, daß ein Informationspaket von einem Sender mit einer Bitfehlerrate größer als ein vorbestimmter Wert empfangen worden ist und ein getrenntes Übertragungsbeeinträchtigungs-Steuersignal erzeugt, und bei dem die Prozessoreinrichtung unter Ansprechen auf ein Übertragungsbeeinträchtigungs-Steuersignal von der Empfangs- und Neuaussendungseinrichtung ein nachfolgendes Steuersignal an den Sender überträgt, für den eine Übertragungsbeeinträchtigung festgestellt worden ist, um den Sender zu veranlassen, das Informationspaket unter Anwendung eines vorbestimmten Ressourcen-Teilungsverfahrens neu auszusenden.

6. Netzwerk nach einem der vorhergehenden Ansprüche, bei dem die Empfangs- und Neuaussendungseinrichtung Diversity-Antennen besitzt, die den drahtlosen Verbindungen zugeordnet sind.

7. Verfahren zur Übertragung von Informationen zwischen einer Vielzahl von Sendern (10-19) und einem zentralen Knoten (30), der eine Prozessoreinrichtung (35) aufweist, über eine verdrahtete oder drahtlose Verbindung während einer Rahmenperiode in einem Breitband-Paketübertragungsnetzwerk, wobei jeder Sender einem getrennten Benutzer oder einer getrennten Gruppe von Benutzern zugeordnet ist, mit den Verfahrensschritten:

- a) die Prozessoreinrichtung bestimmt die Paketübertragungsanforderungen jedes Senders, der mit dem zentralen Knoten während einer ersten Unterperiode jeder Rahmenperiode in Nachrichtenverbindung steht, und
- b) ein drahtloser Sender, für den beim Schritt a) Übertragungsanforderungen festgestellt worden ist, wird veranlaßt, seine Informationspakete während einer getrennten, zweiten Unterperiode jeder Rahmenperiode zu übertragen, gekennzeichnet durch die Schritte:
- c) die Prozessoreinrichtung stellt während der ersten und/oder zweiten Unterperiode jeder Rahmenperiode Übertragungsbeeinträchtigungen in Verbindung mit jedem drahtlosen Sender fest, und
- d) die Prozessoreinrichtung veranlaßt, daß Informationspakete, die von jedem Sender übertragen werden, für den beim Schritt c) eine Übertragungsbeeinträchtigung festgestellt worden ist, mit einer Übertragungsrate übertragen werden, die zur Verringerung der festgestellten Übertragungsbeeinträchtigung ausreicht.

8. Verfahren nach Anspruch 7 mit



den Unterschriften im Schritt a)

a1) die Prozessoreinrichtung überträgt sequentiell erste Steuersignale (P_i) zu jedem der Vielzahl von Sendern und

a2) sequentielles Empfangen zweiter Steuersignale (R_i) von der Vielzahl von Sendern, die anzeigen, ob bei einem Sender ein Informationspaket während der Rahmenperiode zu übertragen ist, und mit dem Unterschrift beim Schritt b)

b1) unter Ansprechen auf jedes empfangene, zweite Steuersignal beim Schritt (a2) anzeigen, daß ein Sender aktiv ist und ein auszusendendes Informationspaket besitzt, sowie sequentielles Übertragen dritter Steuersignale (TS_i) zu den aktiven Sendern, um zu veranlassen, daß das durch den Sender auszusendende Informationspaket durch den zentralen Knoten zu einem vorgesehenen Benutzer des Informationspakets geführt wird.

9. Verfahren nach Anspruch 7 oder 8 mit den Unterschriften beim Schritt c)

c1) Feststellen im zentralen Knoten, daß ein Informationspaket von einem Sender mit einer Bitfehlerrate empfangen worden ist, die größer ist als ein vorbestimmter Wert,

c2) unter Ansprechen auf die Feststellung einer Bitfehlerrate größer als ein vorbestimmter Wert gemäß Schritt c1) Übertragen eines nachfolgenden Steuersignals an den Sender, für den eine Übertragungsbeeinträchtigung festgestellt worden ist, und

c3) unter Ansprechen auf das beim Schritt c2) übertragene, nachfolgende Steuersignal überträgt ein Sender mit einer Übertragungsbeeinträchtigung das Informationspaket mit einer langsameren Übertragungsrate unter Anwendung vorbestimmter Ressourcen-Teilungsverfahren neu, derart, daß das Informationspaket im zentralen Knoten mit einer Bitfehlerrate unterhalb des vorbestimmten Wertes empfangen wird.

Revendications

1. Réseau de communications par paquets à large bande comprenant une pluralité d'émetteurs (10-19), chaque émetteur étant associé à un utilisateur ou groupe d'utilisateurs distinct pour transmettre des paquets d'informations, et un noeud central (30) pour communiquer avec chacun d'une pluralité d'émetteurs par l'intermédiaire d'une connexion câblée ou sans fil et comprenant un moyen de processeur (35) pour (a) déterminer des exigences de transmission de paquets associées à chaque émetteur communiquant avec le

noeud central par l'intermédiaire d'une connexion sans fil durant une première sous-période de chaque période de trame, et (b) forcer chaque émetteur sans fil déterminé comme ayant une exigence de transmission de paquets à transmettre ses paquets d'informations durant une seconde sous-période de temps distincte de chaque période de trame, CARACTERISE EN CE QUE le moyen de processeur sert aussi à (c) détecter durant les première et/ou seconde sous-périodes de chaque période de trame des dégradations de transmission associées à chaque émetteur sans fil, et (d) forcer la transmission des paquets d'informations transmis à partir de chaque émetteur déterminé comme ayant une dégradation de transmission à une vitesse de transmission suffisante pour amoindrir la dégradation de transmission déterminée, et le noeud central comprend un moyen (32-34) pour (a) recevoir des paquets d'informations provenant de la pluralité d'émetteurs, et (b) retransmettre les paquets vers les récepteurs associés aux utilisateurs prévus des paquets d'informations par l'intermédiaire d'une connexion câblée ou sans fil appropriée.

2. Réseau selon la revendication 1, dans lequel le moyen de réception et retransmission comprend un bus haute vitesse (36,37) pour propager les paquets d'informations provenant de la pluralité d'émetteurs selon un principe de multiplexage temporel, et une pluralité d'unités d'interface de réseau (NIU) (32-34), chaque NIU étant associée à un sous-groupe distinct d'un ou plusieurs de la pluralité d'émetteurs, et connectée aux émetteurs du sous-groupe distinct par l'intermédiaire d'une liaison de communication sans fil ou de connexions câblées distinctes pour recevoir les paquets d'informations provenant du sous-groupe associé d'émetteurs et transmettre chaque paquet sur le bus haute vitesse durant une période de tranche de temps libre vers la NIU associée à un utilisateur devant recevoir le paquet d'informations.

3. Réseau selon la revendication 2, comprenant au moins un concentrateur (20,21), le ou chaque concentrateur étant disposé entre un sous-groupe distinct de la pluralité d'émetteurs et une NIU prédéterminée de la pluralité de NIU, le ou chaque concentrateur comprenant une pluralité de modules d'interface d'utilisateur (UIM) (22,23), chaque UIM assurant des communications duplex avec une partie distincte du sous-groupe d'émetteurs associé à ce concentrateur, où au moins une des parties du sous-groupe communique avec son UIM par l'intermédiaire d'une liaison sans fil distincte, un module de jonction (25) pour assurer des communications du-



plex entre les UIM du concentrateur et la NIU associée prédéterminée de la pluralité de NIU dans le noeud central selon un principe de multiplexage temporel, et un bus (29_a, 29_b) pour propager des paquets d'informations entre la pluralité d'UIM du concentrateur et le module de jonction selon un principe de multiplexage temporel.

4. Réseau selon la revendication 1, 2 ou 3, dans lequel le moyen de processeur comprend un moyen sensible au commencement d'une période de trame pour (a) envoyer séquentiellement des premiers signaux de commande (P_i) à chacun de la pluralité d'émetteurs et recevoir séquentiellement des deuxième signaux de commande (R_i) provenant des émetteurs indiquant si oui ou non un émetteur a un paquet d'informations à transmettre durant la période de trame, et (b) en réponse à chaque deuxième signal de commande reçu indiquant qu'un émetteur est actif et a un paquet d'informations à envoyer, transmettre séquentiellement des troisième signaux de commande (TS_i) aux émetteurs actifs pour forcer l'envoi du paquet d'informations par l'émetteur pour son acheminement par le noeud central vers un utilisateur prévu du paquet d'informations. 10 15 20 25
5. Réseau selon la revendication 1, 2, 3 ou 4, dans lequel le moyen de réception et retransmission comprend un moyen pour détecter qu'un paquet d'informations a été reçu d'un émetteur avec un taux d'erreur sur les bits qui est supérieur à une valeur prédéterminée, et pour générer un signal de commande de dégradation de transmission distinct, et le moyen de processeur est sensible à un signal de commande de dégradation de transmission provenant du moyen de réception et retransmission pour transmettre un signal de commande subséquent à l'émetteur détecté comme ayant une dégradation de transmission pour forcer l'émetteur à retransmettre le paquet d'informations à un débit plus lent en utilisant une technique de partage de ressources prédéterminée. 30 35 40 45
6. Réseau selon l'une quelconque des revendications précédentes, dans lequel le moyen de réception et retransmission comprend des antennes de réception en diversité associées aux connexions sans fil. 50
7. Méthode de transmission d'informations entre une pluralité d'émetteurs (10-19) et un noeud central (30), comprenant un moyen de processeur (35), par l'intermédiaire d'une connexion câblée ou sans fil durant une période de trame dans un réseau de communications par paquets à lar-

ge bande, chaque émetteur étant associé à un utilisateur ou groupe d'utilisateurs distinct, la méthode comprenant les étapes de

- (a) détermination par le moyen de processeur des exigences de transmission de paquets de chaque émetteur communiquant avec le noeud central durant une première sous-période de chaque période de trame, et
- (b) forçage d'un émetteur sans fil déterminé à l'étape (a) comme ayant des exigences de transmission de paquets, à transmettre ses paquets d'informations durant une seconde sous-période de temps distincte de chaque période de trame,

CARACTERISEE PAR

- (c) la détection par le moyen de processeur, durant les première et/ou seconde sous-périodes de chaque période de trame, de dégradations de transmission associées à chaque émetteur sans fil, et
- (d) forçage par le moyen de processeur de la transmission des paquets d'informations transmis à partir de chaque émetteur déterminé comme ayant une dégradation de transmission à l'étape (c) à une vitesse de transmission suffisante pour amoindrir la dégradation de transmission déterminée.

8. Méthode selon la revendication 7, comprenant à l'étape (a) les sous-étapes de
 - (a1) transmission séquentielle par le moyen de processeur de premiers signaux de commande (P_i) à chacun de la pluralité d'émetteurs, et
 - (a2) réception séquentielle de deuxième signaux de commande (R_i) provenant de la pluralité d'émetteurs indiquant si oui ou non un émetteur a un paquet d'informations à transmettre durant la période de trame, et
 à l'étape (b), l'étape de
 - (b1) en réponse à chaque deuxième signal de commande reçu à l'étape (a2) indiquant qu'un émetteur est actif et a un paquet d'informations à envoyer, transmission séquentielle de troisième signaux de commande (TS_i) aux émetteurs actifs pour forcer l'envoi du paquet d'informations par l'émetteur pour son acheminement par le noeud central vers un utilisateur prévu du paquet d'informations.
9. Méthode selon la revendication 7 ou 8, comprenant à l'étape (c) les sous-étapes de
 - (c1) détection au niveau du noeud central qu'un paquet d'informations a été reçu d'un émetteur avec un taux d'erreur sur les bits qui est supérieur à une valeur prédéterminée,
 - (c2) transmission d'un signal de commande



subséquent à l'émetteur détecté comme ayant une dégradation de transmission en réponse à la détection d'un taux d'erreur sur les bits supérieur à une valeur prédéterminée à l'étape (c1), et

5

(c3) retransmission par un émetteur ayant une dégradation de transmission sensible au signal de commande subséquent transmis à l'étape (c2) du paquet d'informations à une vitesse de transmission plus lente en utilisant une technique de partage de ressources prédéterminée de sorte que le paquet d'informations est reçu au noeud central avec un bit d'erreurs sur les bits inférieur à la valeur prédéterminée.

10

15

20

25

30

35

40

45

50

55