

'97年02月08日(土) 12:58

発信 KKMラサセイサクシヨ チキザ イサシ

P02

This Sheet Has Been Replaced



Final Version

P/1071-291

- 1 -

**SURFACE-MOUNT-TYPE ANTENNA AND
COMMUNICATION EQUIPMENT USING SAME**

BACKGROUND OF THE INVENTION

1. Field of the Invention

5 The present invention relates to a current-inducing-type surface-mount-type antenna for use in mobile communication equipment, such as portable telephones, and a radio LAN (Local Area Network), and communication equipment using the same.

10 2. Description of the Related Art

15 A conventional surface-mount-type antenna is shown in Fig. 8. A radiation electrode 72 and a power supply electrode 73 are formed on the surface of a base 71 of this surface-mount-type antenna 70 with a gap g therebetween. A grounding terminal 72a and a power supply electrode 73a, which are connected to one end of the radiation electrode 72 and to one end of the power supply electrode 73, are formed on one end surface 71a of the base 71. A capacity loaded electrode 74 is formed on
20 the other end surface 71b of the base 71, which capacity loaded electrode 74 is connected to the other end of the radiation electrode 72.

25 In the conventional surface-mount-type antenna 70, the capacity loaded electrode 74 is provided for shortening the wavelength. However, the {capacity}—capacitance formed by this capacity loaded electrode 74 can be increased only by the specific inductive capacity of the base 71 and the thickness of the base 71. Also, even if the radiation electrode 72 is formed into a
30 meandering shape in order to increase the length of the

'87年02月08日(土) 12:58


発 信 電 子 有 限 公 司 特 許 出 願 第 1 5 3 3 0 6 9 4 号

P03

NO. 042

- 2 -

This Sheet Has Been Replaced



radiation electrode 72 which resonates at a predetermined wavelength, there are limitations in terms of dimensions and shape, and the length of the base 71 cannot be made short. Therefore, it is difficult to achieve a small size with the conventional surface-mount-type antenna 70 ~~[has a problem in achieving a small size]~~. Further, communication equipment having the conventional surface-mount-type antenna 70 incorporated therein has the drawback of the housing of the communication equipment being incapable of being formed to be small in size.

SUMMARY OF THE INVENTION


Accordingly, it is an object of the present invention to provide a surface-mount-type antenna which is short in length and thin in thickness and which can be formed into a small size, and communication equipment having the same mounted therein.

To achieve the above ~~[described object]~~ and other objects, according to one aspect of the present invention, there is provided a current-inducing-type surface-mount-type antenna, ~~[wherein]~~ comprising a radiation electrode ~~[which is curved]~~ arranged substantially in the shape of a letter L or a sideways U, in which one end is open and the other end is short-circuited~~[,]~~ and a power supply electrode for exciting the radiation electrode ~~[are formed]~~, the radiation electrode and power supply electrode formed with a gap therebetween on one main surface of a base made of a dielectric or a magnetic substance ~~[with a gap therebetween]~~, ~~[and]~~ the radiation electrode and the power supply electrode ~~[are]~~ being connected to a grounding terminal and a power supply terminal, respectively, formed on ~~[any]~~ an end surface of the base.

SPECIFICATION

- 3 -

This Sheet Has Been Replaced



According to another aspect of the present invention, there is provided a current-inducing-type surface-mount-type antenna, ~~{wherein}~~ comprising a radiation electrode ~~{which is curved}~~ arranged
5 substantially in the shape of a letter L or a sideways U, in which one end is open and the other end is short-circuited, ~~{is}~~ the radiation electrode being formed extending over one main surface and at least one end surface of a base made of a dielectric or a magnetic
10 substance, a power supply electrode ~~{is}~~ formed on one main surface of the base with a gap ~~{with the radiation electrode, and}~~ being provided between the radiation electrode and the power supply electrode ~~{are}~~, the radiation electrode and the power supply electrode being
15 connected to a grounding terminal and a power supply terminal, respectively, formed on another end surface of the base.

According to a further aspect of the present invention, there is provided communication equipment
20 having the surface-mount-type antenna mounted therein

In the present invention, as described above, since a radiation electrode substantially in the shape of a letter L or a sideways U is provided on at least one main surface from among the main surfaces and the end
25 surfaces of a base, it is possible to increase the resonance wavelength with respect to the chip (base) size, and since a ~~{capacity}~~ capacitance similar to a loading capacity is formed between the open end portion of the radiation electrode and the grounding electrode,
30 it is possible to increase the resonance wavelength even further. This fact means that when the frequency is made fixed, it is possible to decrease the chip (base) size. Therefore, a small-sized surface-mount-type antenna can


'97年02月08日(土) 12:59

発信 KKAラヂオイサツヨ チキザ イサツ

P05
441041

- 4 -

This Sheet Has Been Replaced



be realized, and thus communication equipment having the same mounted therein can be formed into a small size.

The above and further objects, aspects and novel features of the invention will become more apparent from the following detailed description when read in connection with the accompanying drawings.

BRIEF DESCRIPTION OF THE DRAWINGS

Fig. 1 is a perspective view of a first embodiment of a surface-mount-type antenna according to the present invention;

Fig. 2 is an equivalent electrical circuit diagram of the surface-mount-type antenna shown in Fig. 1;

Fig. 3 is a perspective view of a second embodiment of a surface-mount-type antenna according to the present invention;

Fig. 4 is a perspective view of a third embodiment of a surface-mount-type antenna according to the present invention;

Fig. 5 is a perspective view of a fourth embodiment of a surface-mount-type antenna according to the present invention;

Fig. 6 is a perspective view of a fifth embodiment of a surface-mount-type antenna according to the present invention;

Fig. 7 is a perspective view of communication equipment having the surface-mount-type antenna mounted therein according to the present invention; and

Fig. 8 is a perspective view of a conventional surface-mount-type antenna.

- 5 -

This Sheet Has Been Replaced



DETAILED DESCRIPTION OF ~~THE PREFERRED~~ EMBODIMENTS OF
THE INVENTION

The preferred embodiments of the present invention will be described below with reference to the accompanying drawings. Fig. 1 shows a surface-mount-type antenna 10 according to a first embodiment of the present invention. A radiation electrode 2 in the shape of a letter L is formed on the surface of a rectangular base 1, made of a dielectric or a magnetic substance, of the surface-mount-type antenna 10. In the L-shaped radiation electrode 2, a short-circuit end 2a thereof is positioned on one short edge of the surface of the base 1, a main body 2b thereof extends straight to the other short edge ~~[which faces]~~ opposite said one short edge and bends at right angles towards a long edge and extends in that direction, and an open end 2c is positioned at one corner of the surface of the base 1. The short-circuit end 2a of the radiation electrode 2 is connected to a grounding terminal 4 formed on one end surface of the base 1 and extends onto a rear surface thereof.

Further, a power supply electrode 3 is formed on the surface of the base 1 separated by a gap g from the short-circuit end portion 2a of the radiation electrode 2. This power supply electrode 3 is connected to a power supply terminal 5 which is formed on one end surface of the base 1 and extends to the rear surface thereof.

This power supply electrode 3 and the open end 2c of the radiation electrode 2 are equivalently spaced by a distance d and are electric-field-coupled with a capacitance Cd formed within this distance d. The power supply electrode 3 and the radiation electrode 2 are closest to each other at a gap g; however, since the

'97年02月08日(土) 13:00

発信 KKMラタセイサグソ チデキザ イサン

P07

4033

- 6 -

This Sheet Has Been Replaced



short-circuit end portion 2a of the radiation electrode 2 is inductive, the degree of coupling is small. Meanwhile, even if the power supply electrode 3 and the open end 2c are apart from each other, since the surface-mount-type antenna 10 itself is small, the degree of coupling is large.

An equivalent electrical circuit diagram of this embodiment is shown in Fig. 2. In Fig. 2, reference letter L denotes the radiation inductance of the radiation electrode 2. Reference letter R denotes radiation resistance. Reference letter Cd denotes capacitance which is formed mainly between the open end portion 2c of the radiation electrode 2 and the power supply electrode 3. Reference letter Cg denotes capacitance which is formed in the gap g. Reference letter C denotes capacitance between the radiation electrode and ground.

In this embodiment, since the radiation electrode 2 bends substantially in the shape of a letter L which increases its length, the radiation inductance L is increased. Therefore, as described above, a small chip (base) size can be achieved by itself, and the above-described capacitance Cd is increased by the capacitance loading effect of the open end portion 2c, thus achieving an even smaller size.

Next, a second embodiment of the present invention will be described below with reference to Fig. 3. A radiation electrode 22 substantially shaped like a sideways U and a power supply electrode 23 are formed on the surface of a rectangular base 21, made of a dielectric or a magnetic substance, of a surface-mount-type antenna 20 with a gap g therebetween. A short-circuit end 22a of the radiation electrode 22 is

SPECIFICATION

'97年02月08日(土) 13:01

発信 KKMラセイサクソ チキザ イサ

P08

000000

- 7 -

This Sheet Has Been Replaced



positioned on one short edge of the surface of the base 21, and a main body 22b thereof extends straight to the other short edge facing said one short edge and bends at right angles there, extending to one corner of a long edge along said other short edge and further bends at right angles there and extends along this long edge, and an open end 22c thereof is positioned approximately in the middle of this long edge. As a result, the radiation electrode 22 is formed substantially in the shape of a sideways U.

The short-circuit end 22a of the radiation electrode 22 and the power supply electrode 23 are respectively connected to a grounding terminal 24 and a power supply terminal 25 formed on one end surface of the base 21.

The power supply electrode 23 and the open end 22c of the radiation electrode 22 are equivalently spaced by a distance d in the same way as in the first embodiment and are electric-field-coupled with a capacitance Cd formed within this distance d . The power supply electrode 23 and the radiation electrode 22 are closest to each other at a gap g ; however, since the short-circuit end portion 22a is inductive, the degree of coupling is small. Meanwhile, even if the power supply electrode 23 and the open end 22c are apart from each other, since the surface-mount-type antenna 10 itself is small, the degree of coupling is large.

This embodiment is structured as described above, and its equivalent electrical circuit diagram is similar to Fig. 2 which is referred to in the first embodiment.


In this embodiment, as compared with the radiation electrode 2 substantially shaped like a letter

'97年02月08日(土) 13:02

発信 KKMラッセイサクソ チネキサ イヤソ

P09

This Sheet Has Been Replaced



- 8 -

L shown in Fig. 1, there is provided the radiation electrode 22 substantially shaped like a sideways U, and the effective length of the radiation electrode 22 ~~is~~ is longer and the loading capacity effect is large as the power supply electrode 23 and the open end 22c of the radiation electrode 22 ~~is~~ are close to each other. Thus, an even smaller size can be achieved.

Next, a third embodiment of the present invention will be described below with reference to Fig. 4. A part of a radiation electrode 32 in the shape of a letter L and a power supply electrode 33 are formed on the surface of a rectangular base 31, made of a dielectric or a magnetic substance, of a surface-mount-type antenna 30 with a gap g therebetween. A short-circuit end 32a of the radiation electrode 32 is positioned on one edge side of the surface of the base 31~~, and a~~. A main body 32b thereof extends straight to the other short edge facing said one short edge and bends from said other short edge to an adjacent end surface 31b, and extends in one direction on the adjacent end surface 31b~~, and an~~. An open end 32c thereof is positioned at an edge of the adjacent end surface 31b. As a result, the radiation electrode 32 is formed substantially in the shape of a letter L extending over the surface and the end surface of the base 31.

The short-circuit end 32a of the radiation electrode 32 and the power supply electrode 33 are respectively connected to a grounding terminal 34 and a power supply terminal 35 formed on one end surface of the base 31.

The power supply electrode 33 and the open end 32c of the radiation electrode are equivalently spaced by a distance d in the same way as in the first embodiment

'97年02月08日(土) 13:02

発信 KKMラタセイサクショ チチキザ イヤン

P10
441030

- 9 -

This Sheet Has Been Replaced



and are electric-field-coupled with a capacitance C_d formed within this distance d .

5 This embodiment is structured as described above and is expressed by the equivalent electrical circuit diagram shown in Fig. 2. The same effects and advantages as those of the first embodiment described with reference to Fig. 1 can be realized. In particular, an even smaller size can be achieved due to a large capacitance loading effect.

10 Next, a fourth embodiment of the present invention will be described below with reference to Fig. 5. A part of a radiation electrode 42 substantially in the shape of a sideways U and a power supply electrode 43 are formed on the surface of a rectangular base 41, made
15 of a dielectric or a magnetic substance, of a surface-mount-type antenna 40 with a gap g therebetween. A short-circuit end 42a of the radiation electrode 42 is positioned on one short edge of the surface of the base 41, a main body 42b thereof extends straight to the other
20 short edge facing said one short edge, bends from said other short edge to an end surface 41b adjacent thereto, extends in one direction on this adjacent end surface 41b, bends to the above-mentioned surface again at the end of the adjacent end surface 41b, and extends on this
25 surface along a long edge thereof, ~~and an~~. An open end 42c thereof is positioned in the middle of this long edge. As a result, the radiation electrode 42 is formed substantially in the shape of a sideways U such that it extends from the surface of the base 41 along the end
30 surface thereof and returns to the surface and extends in parallel.

A short-circuit end 42a of the radiation electrode 42 and the power supply electrode 43 are

'97年02月08日(土) 13:03

発信 KKムラサキイサクソ チキザ イサン

P11
@UJ7

- 10 -

This Sheet Has Been Replaced



respectively connected to a grounding terminal 44 and a power supply terminal 45 formed on one end surface of the base 41.

5 The power supply electrode 43 and the open end 42c of the radiation electrode 42 are equivalently spaced by a distance d in the same way as in the first embodiment and are electric-field-coupled with a capacitance Cd formed within this distance d .

10 This embodiment is structured as described above and is expressed by the equivalent electrical circuit diagram shown in Fig. 2. The same effects and advantages as those of the second embodiment described with reference to Fig. 3 can be realized. In particular, the capacitance loading effect is large, and an even
15 smaller size can be achieved.

Next, a fifth embodiment of the present invention will be described below with reference to Fig. 6. In a surface-mount-type antenna 50 of this embodiment, there is provided a radiation electrode 42d
20 formed by changing the shape of the base 41 of the radiation electrode 42 in the fourth embodiment shown in Fig. 5 from a line shape to a meandering shape.

This embodiment is expressed by the equivalent electrical circuit shown in Fig. 2, and the same effects and advantages as those of the fourth embodiment
25 described with reference to Fig. 5 can be realized. Since, in particular, the radiation electrode 42d has a meandering shape, an even smaller size can be ~~{pursued}~~ achieved.

30 Next, Fig. 7 shows a state in which the surface-mount-type antennas 10 to 50 of the above-described embodiments are mounted into communication equipment. The surface-mount-type antennas 10 to 50 are


'97年02月08日(土) 13:03

発信 KKAラヂオイサツヨ チネギザ イサツ

P12
000000

- 11 -

This Sheet Has Been Replaced



mounted by soldering grounding terminals and power supply terminals to predetermined terminals (not shown) on a set board (or a subboard thereof) 61 in communication equipment 60.

5 In the present invention, a radiation electrode in the shape of a letter L or a sideways U is provided on at least one main surface from among the main surfaces and end surfaces of a base, and a small thin base can respond to a long wavelength, i.e., a low frequency.

10 Therefore, when the frequency is made fixed, it is possible to realize a small-sized current-inducing-type surface-mount-type antenna.

15 Since a surface-mount-type antenna can be made very small, the space occupied by communication equipment having a surface-mount-type antenna mounted therein is small, thus achieving a small size.

20 Many different embodiments of the present invention may be constructed without departing from the spirit and scope of the present invention. It should be understood that the present invention is not limited to the specific embodiments described in this specification. To the contrary, the present invention is intended to cover various modifications and equivalent arrangements included within the spirit and scope of the invention as

25 hereafter claimed. The scope of the following claims is to be accorded the broadest interpretation so as to encompass all such modifications, equivalent structures and functions.

'97年02月08日(土) 13:04

発信 KKMラケセイサクソ チチギザ イソ

P13

- 12 -

WHAT IS CLAIMED IS:

1. A current-inducing-type surface-mount-type antenna ~~f, wherein a radiation electrode which is curved substantially in the shape of a letter L or a sideways U, in which one end is open and the other end is short-circuited, and a power supply electrode for exciting the radiation electrode, are formed on one main surface of a base made of a dielectric or a magnetic substance with a gap therebetween, and said radiation electrode and said power supply electrode are connected to a grounding terminal and a power supply terminal, respectively, formed on any end surface of said base.~~
2. A current-inducing-type surface-mount-type antenna, wherein a radiation electrode which is curved substantially in the shape of a letter L or a sideways U, in which one end is open and the other end is short-circuited, is formed in such a manner as to extend over one main surface and at least one end surface of a base made of a dielectric or a magnetic substance, a power supply electrode is formed on one main surface of said base with a gap to said radiation electrode, and said radiation electrode and said power supply electrode are connected to a grounding terminal and a power supply terminal, respectively, formed on another end surface of said base.
3. Communication equipment having mounted therein a ~~surface-mount-type antenna according to one of claims 1 and 2.~~ comprising a radiation electrode arranged substantially in the shape of a letter L or a sideways U and having a first open end and a second short-circuited end, a power supply electrode for exciting the radiation

SPECI100500

This Sheet Has Been Replaced



'97年02月08日(土) 13:04

発信 KKMラヂオイサクシヨ チキザ' イサシ

P14

- 13 -



35 electrode, the radiation electrode and power supply
electrode disposed with a gap therebetween on one main
surface of a base comprising at least one of a dielectric
material and a magnetic material, said radiation
electrode and said power supply electrode being connected
respectively to a grounding terminal and a power supply
terminal disposed on ^{at least one of} an end surface of said base,
and another main surface of the base.

2. The current-inducing-type surface-mount-
type antenna of claim 1, wherein the radiation electrode
has at least a portion of the L-shaped or U-shaped
radiation electrode comprising a meandering shape.

3. The current-inducing-type surface-mount-
type antenna of claim 1, wherein a capacitance is
provided between the open end of the radiation electrode
and the power supply electrode.

5 4. A current-inducing-type surface-mount-type
antenna comprising a radiation electrode arranged
substantially in the shape of a letter L or a sideways U
and having a first open end and a second short-circuited
end, the radiation electrode extending over one main
surface and at least one end surface of a base comprising
at least one of a dielectric material and a magnetic
material, a power supply electrode disposed on one main
10 surface of said base, a gap being provided between said
power supply electrode and said radiation electrode, said
radiation electrode and said power supply electrode being
connected respectively to a grounding terminal and a
power supply terminal disposed on another end surface of
said base.

#ECN400

This Sheet Has Been Replaced



'97年02月08日(土) 13:05

発信 KKMラヂオイサツヨ テキザ イサツ

P15

- 14 -



5. The current-inducing-type surface-mount-type antenna of claim 4, wherein the power supply electrode and the radiation electrode are disposed on said one main surface with the gap disposed therebetween.

6. The current-inducing-type surface-mount-type antenna of claim 4, wherein the radiation electrode has at least a portion of the L-shaped or U-shaped radiation electrode comprising a meandering shape.

7. The current-inducing-type surface-mount-type antenna of claim 4, wherein a capacitance is provided between the open end of the radiation electrode and the power supply electrode.

8. The current-inducing-type surface-mount-type antenna of claim 4, wherein the radiation electrode is I-shaped and the open end is disposed on said end surface.


9. The current-inducing-type surface-mount-type antenna of claim 4, wherein the radiation electrode is U-shaped and the portion of the U-shape between the legs of the U is disposed on the end surface.

10. The current-inducing-type surface-mount-type antenna of claim 9, wherein both legs of the U-shaped radiation electrode are disposed on the main surface.

11. The current-inducing-type surface-mount-type antenna of claim 9, wherein both legs of the radiation electrode have a meandering shape.

SPECIMEN

This Sheet Has Been Replaced



'97年02月08日(土) 13:05

発信 KKムラタセイサクソ テレキザ イサソ

P16
000000

- 15 -



5 12. Communication equipment comprising at
 least one of an electromagnetic frequency transmitter and
 an electromagnetic frequency receiver, an antenna
 connected to at least one of the transmitter and
10 receiver, the antenna comprising a surface-mount-type
 antenna comprising a radiation electrode arranged
 substantially in the shape of a letter L or a sideways U
 and having a first open end and a second short-circuited
 end, a power supply electrode for exciting the radiation
15 electrode, the radiation electrode and power supply
 electrode disposed with a gap therebetween on one main
 surface of a base comprising at least one of a dielectric
 material and a magnetic material, said radiation
20 electrode and said power supply electrode being connected
 respectively to a grounding terminal and a power supply
 terminal disposed on an end surface of said base.

13. The communication equipment of claim 12,
 wherein the radiation electrode has at least a portion of
 the L-shaped or U-shaped electrode comprising a
 meandering shape.

14. The communication equipment of claim 12,
 wherein a capacitance is provided between the open end of
 the radiation electrode and the power supply electrode.

5 15. Communication equipment comprising at
 least one of an electromagnetic frequency transmitter and
 an electromagnetic frequency receiver, an antenna
 connected to at least one of the transmitter and
 receiver, the antenna comprising a surface-mount-type
 antenna comprising a radiation electrode arranged

SPEC100000

This Sheet Has Been Replaced



'97年02月08日(土) 13:06

発信 KKムラタセイサクシヨ チネザ イヤシ

P17

- 16 -



10 substantially in the shape of a letter L or a sideways U
and having a first open end and a second short-circuited
end, the radiation electrode extending over one main
surface and at least one end surface of a base comprising
15 at least one of a dielectric material and a magnetic
material, a power supply electrode disposed on one main
surface of said base, a gap being provided between said
power supply electrode and said radiation electrode, said
20 radiation electrode and said power supply electrode being
connected respectively to a grounding terminal and a
power supply terminal disposed on another end surface of
said base.

16. The communication equipment of claim 15,
wherein the power supply electrode and the radiation
electrode are disposed on said one main surface with the
gap disposed therebetween.

17. The communication equipment of claim 15,
wherein the radiation electrode has at least a portion of
the L-shaped or U-shaped electrode comprising a
meandering shape.

18. The communication equipment of claim 15,
wherein a capacitance is provided between the open end of
the radiation electrode and the power supply electrode.

19. The communication equipment of claim 15,
wherein the radiation electrode is U-shaped and the open
end is disposed on said end surface.

20. The communication equipment of claim 15,
wherein the radiation electrode is U-shaped and the

SPEC188800

This Sheet Has Been Replaced



'97年02月08日(土) 13:06

発信 KKムラセイサクシヨ チデキザ イサン

P18 ..

- 17 -



portion of the U-shape between the legs of the U is disposed on the end surface.

21. The communication equipment of claim 20, wherein both legs of the U-shaped radiation electrode are disposed on the main surface.

22. The communication equipment of claim 20, wherein both legs of the radiation electrode have a meandering shape.

This Sheet Has Been Replaced



275011200