

METHODS AND APPARATUS FOR CLEANING SUBSTRATES

FIELD OF THE INVENTION

[0001] The present invention generally relates to method and apparatus for cleaning substrate. More particularly, relates to controlling the bubble cavitation generated by ultra or mega sonic device during the cleaning process to achieve a stable or controlled cavitation on the entire substrate, which removes fine particles efficiently in vias, trenches or recessed areas with high aspect ratio.

BACKGROUND

[0002] Semiconductor devices are manufactured or fabricated on semiconductor substrates using a number of different processing steps to create transistor and interconnection elements. Recently, the transistors are built from two dimensions to three dimensions such as finFET transistors and 3D NAND memory. To electrically connect transistor terminals associated with the semiconductor substrate, conductive (e.g., metal) trenches, vias, and the like are formed in dielectric materials as part of the semiconductor device. The trenches and vias couple electrical signals and power between transistors, internal circuit of the semiconductor devices, and circuits external to the semiconductor device.

[0003] In forming the finFET transistors and interconnection elements on the semiconductor substrate may undergo, for example, masking, etching, and deposition processes to form the desired electronic circuitry of the semiconductor devices. In particular, multiple masking and plasma etching step can be performed to form a pattern of finFET, 3D NAND flash cell and or recessed areas in a dielectric layer on a semiconductor substrate that serve as fin for the transistor and or trenches and vias for the interconnection elements. In order to removal particles and contaminations in fin structure and or trench and via post etching or photo resist ashing, a wet cleaning step is necessary. Especially, when device manufacture node migrating to 14 or 16 nm and beyond, the side wall loss in fin and or trench and via is crucial for maintaining the critical dimension. In order to reduce or eliminate the side wall loss, it is important to use moderate, dilute chemicals, or sometime de-ionized water only. However, the dilute chemical or de-ionized water usually is not efficient to remove the particles in the fin structure, 3D NAND hole and or trench

and via. Therefore the mechanical force such as ultra or mega sonic is needed in order to remove those particles efficiently. Ultra sonic or mega sonic wave will generate bubble cavitation which applies mechanical force to substrate structure, the violent cavitation such as transit cavitation or micro jet will damage those patterned structures. To maintain a stable or controlled cavitation is key parameters to control the mechanical force within the damage limit and at the same time efficiently to remove the particles. In the 3D NAND hole structure, the transit cavitation may not damage the hole structure, but however, the bubble cavitation saturated inside hole will stop or reduce the cleaning effects.

[0004] Mega sonic energy coupled with nozzle to clean semiconductor wafer is disclosed in U.S. Pat. No. 4,326,553. The fluid is pressurized and mega sonic energy is applied to the fluid by a mega sonic transducer. The nozzle is shaped to provide a ribbon-like jet of cleaning fluid vibrating at ultra/mega sonic frequencies for the impingement on the surface.

[0005] A source of energy vibrates an elongated probe which transmits the acoustic energy into the fluid is disclosed in U.S. Pat. No. 6,039,059. In one arrangement, fluid is sprayed onto both sides of a wafer while a probe is positioned close to an upper side. In another arrangement, a short probe is positioned with its end surface close to the surface, and the probe is moved over the surface as wafer rotates.

[0006] A source of energy vibrates a rod which rotates around its axis parallel to wafer surface is disclosed in U.S. Pat. No. 6,843,257 B2. The rod surface is etched to curve grooves, such as spiral groove.

[0007] It is needed to have a better method for controlling the bubble cavitation generated by ultra or mega sonic device during the cleaning process to achieve a stable or controlled cavitation on the entire substrate, which removes fine particles efficiently in vias, trenches or recessed areas with high aspect ratio.

SUMMARY

[0008] One method of the present invention is to achieve a damage free ultra/mega-sonic cleaning on a wafer with patterned structure by maintaining a stable bubble cavitation. The stable bubble cavitation is controlled by setting a sonic power supply with power P_1 at a time interval shorter than τ_1 , and setting the sonic power supply with power P_2 at a time interval longer than τ_2 , and repeat above steps till the wafer is cleaned, where power P_2 is equal to zero or much smaller than power P_1 , τ_1 is a time interval that the

temperature inside bubble raises to a critical implosion temperature; and τ_2 is a time interval that the temperature inside bubble falls down to a temperature much lower than the critical implosion temperature.

[0009] Another method of the present invention is to achieve a damage free ultra/mega sonic cleaning on a wafer with patterned structure by maintaining a stable bubble cavitation. The stable bubble cavitation is controlled by setting a sonic power supply with frequency f_1 at a time interval shorter than τ_1 , and setting the sonic power supply with frequency f_2 at a time interval longer than τ_2 , and repeat above steps till the wafer is cleaned, where f_2 is much higher than f_1 , better to be 2 times or 4 times higher, τ_1 is a time interval that the temperature inside bubble raises to a critical implosion temperature; and τ_2 is a time interval that the temperature inside bubble falls down to a temperature much lower than the critical implosion temperature.

[0010] Another method of the present invention is to achieve a damage free ultra/mega-sonic cleaning on a wafer with patterned structure by maintaining a stable bubble cavitation with bubble size less than space in patterned structure. The stable bubble cavitation with bubble size less than space in patterned structure is controlled by setting a sonic power supply at power P_1 for a time interval shorter than τ_1 , and setting the sonic power supply at power P_2 for a time interval longer than τ_2 , and repeat above steps till the wafer is cleaned, where P_2 is equal to zero or much smaller than P_1 , τ_1 is a time interval that the bubble size increases to a critical size equal to or larger than the space in patterned structures; and τ_2 is a time interval that the bubble size decreases to a value much smaller than the space in patterned structure.

[0011] Another method of the present invention is to achieve a damage free ultra/mega-sonic cleaning on a wafer with patterned structure by maintaining a stable bubble cavitation with bubble size less than space in patterned structure. The stable bubble cavitation with bubble size less than space in patterned structure is controlled by setting a sonic power supply with frequency f_1 for a time interval shorter than τ_1 , and setting the sonic power supply with frequency f_2 for a time interval longer than τ_2 , and repeat above steps till the wafer is cleaned, where f_2 is much higher than f_1 , better to be 2 times or 4 times higher, τ_1 is a time interval that the bubble size increases to a critical size equal to or larger than the space in patterned structures; and τ_2 is a time interval that the bubble size decreases to a value much smaller than the space in patterned structure.

[0012] One method of the present invention is to achieve an effective ultra/mega-sonic cleaning on a substrate with features of deep holes by maintaining a non-saturated bubble cavitation. The non-saturated bubble cavitation is controlled by setting a sonic power supply with power P_1 at a time interval shorter than τ_1 , and setting the sonic power supply with power P_2 at a time interval longer than τ_2 , and repeating above steps till the substrate is cleaned, where power P_2 is equal to zero or much smaller than power P_1 , τ_1 is a time interval that the cavitation or bubble density inside the deep hole raises to saturated status; and τ_2 is a time interval that bubble density falls down to a level much lower than the saturated status.

[0013] Another method of the present invention is to achieve an effective ultra/mega-sonic cleaning on a substrate with features of deep holes by maintaining a non-saturated bubble cavitation. The non-saturated bubble cavitation is controlled by setting a sonic power supply with frequency f_1 at a time interval shorter than τ_1 , and setting the sonic power supply with frequency f_2 at a time interval longer than τ_2 , and repeating above steps till the substrate is cleaned, where f_2 is much higher than f_1 , better to be 2 times or 4 times higher, τ_1 is a time interval that the cavitation or bubble density inside the deep hole raises to saturated status; and τ_2 is a time interval that bubble density falls down to a level much lower than the saturated status.

[0014] One method of the present invention is to achieve an effective ultra/mega-sonic cleaning on a substrate with features of deep holes by maintaining a certain size of bubble in cavitation status. The certain size of bubble in cavitation status is controlled by setting a sonic power supply with power P_1 at a time interval shorter than τ_1 , and setting the sonic power supply with power P_2 at a time interval longer than τ_2 , and repeating above steps till the substrate is cleaned, where power P_2 is equal to zero or much smaller than power P_1 , τ_1 is a time interval that the cavitation or bubble density inside the deep hole raises to saturated status; and τ_2 is a time interval that bubble size falls down to a level much smaller than the certain size.

[0015] Another method of the present invention is to achieve an effective ultra/mega-sonic cleaning on a substrate with features of deep holes by maintaining a certain size of bubble in cavitation status. The certain size of bubble in cavitation status is controlled by setting a sonic power supply with frequency f_1 at a time interval shorter than τ_1 , and setting the sonic power supply with frequency f_2 at a time interval longer than τ_2 , and

repeating above steps till the substrate is cleaned, where f_2 is much higher than f_1 , better to be 2 times or 4 times higher, τ_1 is a time interval that the cavitation or bubble density inside the deep hole raises to saturated status; and τ_2 is a time interval that bubble size falls down to a level much smaller than the certain size.

BRIEF DESCRIPTION OF THE DRAWINGS

- [0016] FIGs.1A-1B depict an exemplary wafer cleaning apparatus using ultra/mega sonic device;
- [0017] FIGs.2A-2G depict variety of shape of ultra/mega sonic transducers;
- [0018] FIG. 3 depicts bubble cavitation during wafer cleaning process;
- [0019] FIGs.4A-4B depict a transit cavitation damaging patterned structure on a wafer during cleaning process;
- [0020] FIGs.5A-5C depict thermal energy variation inside bubble during cleaning process;
- [0021] FIGs.6A-6C depict an exemplary wafer cleaning method;
- [0022] FIGs.7A-7C depict another exemplary wafer cleaning method;
- [0023] FIGs.8A-8D depict another exemplary wafer cleaning method;
- [0024] FIGs.9A-9D depict another exemplary wafer cleaning method;
- [0025] FIGs.10A-10B depict another exemplary wafer cleaning method;
- [0026] FIGs.11A-11B depict another exemplary wafer cleaning method;
- [0027] FIGs.12A-12B depict another exemplary wafer cleaning method;
- [0028] FIGs.13A-13B depict another exemplary wafer cleaning method;
- [0029] FIGs.14A-14B depict another exemplary wafer cleaning method;
- [0030] FIGs.15A-15C depict a stable cavitation damaging patterned structure on a wafer during cleaning process;
- [0031] FIG.16 depicts another exemplary wafer cleaning apparatus using ultra/mega sonic device; and
- [0032] FIG.17 depicts an exemplary wafer cleaning apparatus using ultra/mega sonic device;
- [0033] FIGs.18A-18C depict another exemplary wafer cleaning method;
- [0034] FIG.19 depicts another exemplary wafer cleaning method;

[0035] FIG.20A to FIG.20D depict bubbles in the status of below the saturation point in the feature of vias or trenches;

[0036] FIG.20E to FIG.20H depict the size of bubbles expanded by the ultra/mega sonic device to result in the ratio R of total bubbles volume V_B to the volume of via, trench or recessed space V_{VTR} being closed to or above the saturation point;

[0037] FIG.20I and FIG.20J depict the size of bubbles expanded by the ultra/mega sonic device within a limitation to result in the ratio R of total bubbles volume V_B to the volume of via, trench or recessed space V_{VTR} being much below the saturation point;

[0038] FIGs.21A-21D depict an exemplary substrate cleaning method;

[0039] FIGs.22A-22D depict another exemplary substrate cleaning method;

[0040] FIGs.23A-23C depict another exemplary substrate cleaning method.

DETAILED DESCRIPTION

[0041] Figs. 1A to 1B show a wafer cleaning apparatus using a ultra/mega sonic device. The wafer cleaning apparatus consists of wafer 1010, wafer chuck 1014 being rotated by rotation driving mechanism 1016, nozzle 1012 delivering cleaning chemicals or de-ionized water 1032, and ultra/mega sonic device 1003 and ultra/mega sonic power supply. The ultra/mega sonic device 1003 further consists of piezoelectric transducer 1004 acoustically coupled to resonator 1008. Transducer 1004 is electrically excited such that it vibrates and the resonator 1008 transmits high frequency sound energy into liquid. The bubble cavitation generated by the ultra/mega sonic energy oscillates particles on wafer 1010. Contaminants are thus vibrated away from the surfaces of the wafer 1010, and removed from the surfaces through the flowing liquid 1032 supplied by nozzle 1012.

[0042] Figs. 2A to 2G show top view of ultra/mega sonic devices according to the present invention. Ultra/mega sonic device 1003 shown in Fig.1 can be replaced by different shape of ultra/mega sonic devices 3003, i.e. triangle or pie shape as shown in Fig. 2A, rectangle as shown in Fig. 2B, octagon as shown in Fig. 2C, elliptical as shown in Fig. 2D, half circle as shown in Fig. 2E, quarter circle as shown in Fig. 2F, and circle as shown in Fig. 2G.

[0043] Fig. 3 shows a bubble cavitation during compression phase. The shape of bubbler is gradually compressed from a spherical shape A to an apple shape G, finally the bubble reaches to an implosion status I and forms a micro jet. As shown in Fig.4A and 4B,

the micro jet is very violent (can reaches a few thousands atmospheric pressures and a few thousands °C), which can damage the fine patterned structure 4034 on the semiconductor wafer 4010, especially when the feature size t shrinks to 70 nm and smaller.

[0044] Figs. 5A to 5C show simplified model of bubble cavitation according to the present invention. As sonic positive pressure acting on the bubble, the bubble reduces its volume. During this volume shrinking process, the sonic pressure P_M did a work to the bubble, and the mechanical work converts to thermal energy inside the bubble, therefore temperature of gas and/or vapor inside bubble increases.

[0045] The idea gas equation can be expressed as follows:

$$[0046] \quad p_0 v_0 / T_0 = p v / T \quad (1),$$

[0047] where, p_0 is pressure inside bubbler before compression, v_0 initial volume of bubble before compression, T_0 temperature of gas inside bubbler before compression, p is pressure inside bubbler in compression, v volume of bubble in compression, T temperature of gas inside bubbler in compression.

[0048] In order to simplify the calculation, assuming the temperature of gas is no change during the compression or compression is very slow and temperature increase is cancelled by liquid surrounding the bubble. So that the mechanical work w_m did by sonic pressure P_M during one time of bubbler compression (from volume N unit to volume 1 unit or compression ratio = N) can be expressed as follows:

$$[0049] \quad w_m = \int_0^{x_0-1} p S dx = \int_0^{x_0-1} (S(x_0 p_0) / (x_0 - x)) dx = S x_0 p_0 \int_0^{x_0-1} dx / (x_0 - x) \\ = - S x_0 p_0 \ln (x_0 - x) \Big|_0^{x_0-1} = S x_0 p_0 \ln (x_0) \quad (2)$$

Where, S is area of cross section of cylinder, x_0 the length of the cylinder, p_0 pressure of gas inside cylinder before compression. The equation (2) does not consider the factor of temperature increase during the compression, so that the actual pressure inside bubble will be higher due to temperature increase. Therefore the actual mechanical work conducted by sonic pressure will be larger than that calculated by equation (2).

If assuming all mechanical work did by sonic pressure is partially converted to thermal energy and partially converted mechanical energy of high pressure gas and vapor inside bubble, and such thermal energy is fully contributed to temperature increase of gas inside of bubbler (no energy transferred to liquid molecules surrounding the bubble), and assuming the mass of gas inside bubble staying constant before and after compression,

then temperature increase ΔT after one time of compression of bubble can be expressed in the following formula:

$$\Delta T = Q/(mc) = \beta w_m/(mc) = \beta S x_0 p_0 \ln(x_0)/(mc) \quad (3)$$

where, Q is thermal energy converted from mechanical work, β ratio of thermal energy to total mechanical works did by sonic pressure, m mass of gas inside the bubble, c gas specific heat coefficient. Substituting $\beta = 0.65$, $S=1E-12 \text{ m}^2$, $x_0=1000 \text{ }\mu\text{m}=1E-3 \text{ m}$ (compression ratio $N = 1000$), $p_0=1 \text{ kg/cm}^2= 1E4 \text{ kg/m}^2$, $m=8.9E-17 \text{ kg}$ for hydrogen gas, $c = 9.9E3 \text{ J/(kg } ^\circ\text{K)}$ into equation (3), then $\Delta T = 50.9 ^\circ\text{K}$.

The temperature T_1 of gas inside bubbler after first time compression can be calculated as

$$[0050] \quad T_1 = T_0 + \Delta T = 20 ^\circ\text{C} + 50.9 ^\circ\text{C} = 70.9 ^\circ\text{C} \quad (4)$$

[0051] When the bubble reaches the minimum size of 1 micron as shown in Fig.5B. At such a high temperature, of cause some liquid molecules surrounding bubble will evaporate. After then, the sonic pressure become negative and bubble starts to increase its size. In this reverse process, the hot gas and vapor with pressure P_G will do work to the surrounding liquid surface. At the same time, the sonic pressure P_M is pulling bubble to expansion direction as shown in Fig.5C, therefore the negative sonic pressure P_M also do partial work to the surrounding liquid too. As the results of the joint efforts, the thermal energy inside bubble cannot be fully released or converted to mechanical energy, therefore the temperature of gas inside bubble cannot cool down to original gas temperature T_0 or the liquid temperature. After the first cycle of cavitation finishes, the temperature T_2 of gas in bubble will be somewhere between T_0 and T_1 as shown in Fig.6B. Or T_2 can be expressed as

$$[0052] \quad T_2 = T_1 - \delta T = T_0 + \Delta T - \delta T \quad (5)$$

[0053] Where δT is temperature decrease after one time of expansion of the bubble, and δT is smaller than ΔT .

[0054] When the second cycle of bubble cavitation reaches the minimum bubble size, the temperature T_3 of gas and or vapor inside bubbler will be

$$[0055] \quad T_3 = T_2 + \Delta T = T_0 + \Delta T - \delta T + \Delta T = T_0 + 2\Delta T - \delta T \quad (6)$$

[0056] When the second cycle of bubble cavitation finishes, the temperature T_4 of gas and/or vapor inside bubbler will be

$$[0057] \quad T_4 = T_3 - \delta T = T_0 + 2\Delta T - \delta T - \delta T = T_0 + 2\Delta T - 2\delta T \quad (7)$$

[0058] Similarly, when the nth cycle of bubble cavitation reaches the minimum bubble size, the temperature T_{2n-1} of gas and or vapor inside bubbler will be

$$[0059] \quad T_{2n-1} = T_0 + n\Delta T - (n-1)\delta T \quad (8)$$

[0060] When the nth cycle of bubble cavitation finishes, the temperature T_{2n} of gas and/or vapor inside bubbler will be

$$[0061] \quad T_{2n} = T_0 + n\Delta T - n\delta T = T_0 + n(\Delta T - \delta T) \quad (9)$$

[0062] As cycle number n of bubble cavitation increase, the temperature of gas and vapor will increase, therefore more molecules on bubble surface will evaporate into inside of bubble 6082 and size of bubble 6082 will increase too, as shown in Fig.6C. Finally the temperature inside bubble during compression will reach implosion temperature T_i (normally T_i is as high as a few thousands $^{\circ}\text{C}$), and violent micro jet 6080 forms as shown in Fig.6C.

[0063] From equation (8), implosion cycle number n_i can be written as following:

$$[0064] \quad n_i = (T_i - T_0 - \Delta T) / (\Delta T - \delta T) + 1 \quad (10)$$

[0065] From equation (10), implosion time τ_i can be written as following:

$$[0066] \quad \begin{aligned} \tau_i &= n_i t_1 = t_1 ((T_i - T_0 - \Delta T) / (\Delta T - \delta T) + 1) \\ &= n_i / f_1 = ((T_i - T_0 - \Delta T) / (\Delta T - \delta T) + 1) / f_1 \end{aligned} \quad (11)$$

Where, t_1 is cycle period, and f_1 frequency of ultra/mega sonic wave.

[0067] According to formulas (10) and (11), implosion cycle number n_i and implosion time τ_i can be calculated. Table 1 shows calculated relationships among implosion cycle number n_i , implosion time τ_i and $(\Delta T - \delta T)$, assuming $T_i = 3000^{\circ}\text{C}$, $\Delta T = 50.9^{\circ}\text{C}$, $T_0 = 20^{\circ}\text{C}$, $f_1 = 500 \text{ KHz}$, $f_1 = 1 \text{ MHz}$, and $f_1 = 2 \text{ MHz}$.

[0068] Table 1

$\Delta T - \delta T (^{\circ}\text{C})$	0.1	1	10	30	50
n_i	29018	2903	291	98	59
τ_i (ms) $f_1 = 500 \text{ KHz}$	58.036	5.806	0.582	0.196	0.118
τ_i (ms) $f_1 = 1 \text{ MHz}$	29.018	2.903	0.291	0.098	0.059
τ_i (ms) $f_1 = 2 \text{ MHz}$	14.509	1.451	0.145	0.049	0.029

[0069] In order to avoid damage to patterned structure on wafer, a stable cavitation must be maintained, and the bubble implosion or micro jet must be avoided. Figs.7A to 7C shows a method to achieve a damage free ultra or mega-sonic cleaning on a wafer with patterned structure by maintaining a stable bubble cavitation according to the present invention. Fig.7A shows waveform of power supply outputs, and Fig.7B shows the temperature curve corresponding to each cycle of cavitation, and Fig. 7C shows the bubble size expansion during each cycle of cavitation. Operation process steps to avoid bubble implosion according to the present invention are disclosed as follows:

[0070] Step 1: Put ultra/mega sonic device adjacent to surface of wafer or substrate set on a chuck or tank;

[0071] Step 2: Fill chemical liquid or gas (hydrogen, nitrogen, oxygen, or CO₂) doped water between wafer and the ultra/mega sonic device;

[0072] Step 3: Rotate chuck or oscillate wafer;

[0073] Step 4: Set power supply at frequency f_1 and power P_1 ;

[0074] Step 5: Before temperature of gas and vapor inside bubble reaches implosion temperature T_i , (or time reach $\tau_1 < \tau_i$ as being calculated by equation (11)), set power supply output to zero watts, therefore the temperature of gas inside bubble start to cool down since the temperature of liquid or water is much lower than gas temperature.

[0075] Step 6: After temperature of gas inside bubble decreases to room temperature T_0 or time (zero power time) reaches τ_2 , set power supply at frequency f_1 and power P_1 again.

[0076] Step 7: repeat Step 1 to Step 6 until wafer is cleaned.

[0077] In step 5, the time τ_1 must be shorter than τ_i in order to avoid bubble implosion, and τ_i can be calculated by using equation (11).

[0078] In step 6, the temperature of gas inside bubble is not necessary to be cooled down to room temperature or liquid temperature; it can be certain temperature above room temperature or liquid temperature, but better to be significantly lower than implosion temperature T_i .

[0079] According to equations 8 and 9, if $(\Delta T - \delta T)$ can be known, the τ_i can be calculated. But in general, $(\Delta T - \delta T)$ is not easy to be calculated or measured directly. The following method can determine the implosion time τ_i experimentally.

[0080] Step 1: Based on Table 1, choosing 5 different time τ_1 as design of experiment (DOE) conditions,

[0081] Step 2: choose time τ_2 at least 10 times of τ_1 , better to be 100 times of τ_1 at the first screen test

[0082] Step 3: fix certain power P_0 to run above five conditions cleaning on specific patterned structure wafer separately. Here, P_0 is the power at which the patterned structures on wafer will be surely damaged when running on continuous mode (non-pulse mode).

[0083] Step 4: Inspect the damage status of above five wafers by SEMS or wafer pattern damage review tool such as AMAT SEM vision or Hitachi IS3000, and then the implosion time τ_i can be located in certain range.

[0084] Step 1 to 4 can be repeated again to narrow down the range of implosion time τ_i . After knowing the implosion time τ_i , the time τ_1 can be set at a value smaller than $0.5\tau_i$ for safety margin. One example of experimental data is described as following.

[0085] The patterned structures are 55 nm poly-silicon gate lines. Ultra/mega sonic wave frequency was 1 MHz, and ultra/mega-sonic device manufactured by Prosys was used and operated in a gap oscillation mode (disclosed by PCT/CN2008/073471) for achieving better uniform energy dose within wafer and wafer to wafer. Other experimental parameters and final pattern damage data are summarized in Table 2 as follows:

[0086] Table 2

Wafer ID	CO ₂ conc. (18 μ s/cm)	Process Time (sec)	Power Density (Watts/cm ²)	Cycle Number	τ_1 (ms)	τ_2 (ms)	Number of Damage Sites
#1	18	60	0.1	2000	2	18	1216
#2	18	60	0.1	100	0.1	0.9	0

[0087] It was clear that the $\tau_1 = 2$ ms (or 2000 cycle number) introduced as many as 1216 damage sites to patterned structure with 55 nm feature size, but that the $\tau_1 = 0.1$ ms (or 100 cycle number) introduced zero (0) damage sites to patterned structure with 55 nm feature size. So that the τ_i is some number between 0.1 ms and 2 ms, more detail tests need to be done to narrow its range. Obviously, the cycle number related to ultra or mega sonic power density and frequency, the larger the power density, the less the cycle number; and

the lower the frequency, the less the cycle number. From above experimental results, we can predict that the damage-free cycle number should be smaller than 2,000, assuming the power density of ultra or mega sonic wave is larger than 0.1 watts/cm^2 , and frequency of ultra or mega sonic wave is equal to or less than 1MHz. If the frequency increases to a range larger than 1 MHz or power density is less than 0.1 watts/cm^2 , it can be predicted that the cycle number will increase.

[0088] After knowing the time τ_1 , then the time τ_2 can be shorten based on similar DEO method described above, i.e. fix time τ_1 , gradually shorten the time τ_2 to run DOE till damage on patterned structure being observed. As the time τ_2 is shorten, the temperature of gas and or vapor inside bubbler cannot be cooled down enough, which will gradually shift average temperature of gas and vapor inside bubbler up, eventually it will trigger implosion of bubble. This trigger time is called critical cooling time. After knowing critical cooling time τ_c , the time τ_2 can be set at value larger than $2\tau_c$ for the same reason to gain safety margin.

,

[0089] FIGs.8A to 8D show another embodiment of wafer cleaning method using a ultra/mega sonic device according to the present invention. The method is similar to that shown in Fig. 7A, except in step 4 setting ultra/mega sonic power supply at frequency f_1 and power with changing amplitude of waveform. Fig. 8A shows another cleaning method of setting ultra/mega sonic power at frequency f_1 and power with increasing amplitude of waveform in step 4. Fig. 8B shows another cleaning method of setting ultra/mega sonic power supply at frequency f_1 and power with decreasing amplitude of waveform in step 4. Fig. 8C shows another cleaning method of setting ultra/mega sonic power supply at frequency f_1 and power with decreasing first and increasing later amplitude of waveform in step 4. Fig. 8D shows further another cleaning method of setting ultra/mega sonic power at frequency f_1 and power with increasing first and decreasing later amplitude of waveform in step 4.

[0090] FIGs.9A to 9D show another embodiment of wafer cleaning method using a ultra/mega sonic device according to the present invention. The method is similar to that shown in Fig. 7A, except in step 4 setting ultra/mega sonic power supply at changing frequency. Fig. 9A shows another cleaning method of setting ultra/mega sonic power supply at frequency f_1 first then frequency f_3 later, f_1 is higher than f_3 in step 4. Fig. 9B

shows another cleaning method of setting ultra/mega sonic power supply at frequency f_3 first then frequency f_1 later, f_1 is higher than f_3 in step 4. Fig. 9C shows another cleaning method of setting ultra/mega sonic power supply at frequency f_3 first, frequency f_1 later and f_3 last, f_1 is higher than f_3 in step 4. Fig. 9D shows another cleaning method of setting ultra/mega sonic power supply at frequency f_1 first, frequency f_3 later and f_1 last, f_1 is higher than f_3 in step 4.

[0091] Similar to method shown in Fig. 9C, the ultra/mega sonic power can be set at frequency f_1 first, at frequency f_3 later and at frequency f_4 at last in step 4, where f_4 is smaller than f_3 , and f_3 is smaller than f_1 .

[0092] Again similar to method shown in Fig. 9C, the ultra/mega sonic power can be set at frequency f_4 first, at frequency f_3 later and at frequency f_1 at last in step 4, where f_4 is smaller than f_3 , and f_3 is smaller than f_1 .

[0093] Again similar to method shown in Fig. 9C, the ultra/mega sonic power can be set at frequency f_1 first, at frequency f_4 later and at frequency f_3 at last in step 4, where f_4 is smaller than f_3 , and f_3 is smaller than f_1 .

[0094] Again similar to method shown in Fig. 9C, the ultra/mega sonic power can be set at frequency f_3 first, at frequency f_4 later and at frequency f_1 at last in step 4, where f_4 is smaller than f_3 , and f_3 is smaller than f_1 .

[0095] Again similar to method shown in Fig. 9C, the ultra/mega sonic power can be set at frequency f_3 first, at frequency f_1 later and at frequency f_4 at last in step 4, where f_4 is smaller than f_3 , and f_3 is smaller than f_1 .

[0096] Again similar to method shown in Fig. 9C, the ultra/mega sonic power can be set at frequency f_4 first, at frequency f_1 later and at frequency f_3 at last in step 4, where f_4 is smaller than f_3 , and f_3 is smaller than f_1 .

[0097] Figs.10A to 10B show another method to achieve a damage free ultra/mega-sonic cleaning on a wafer with patterned structure by maintaining a stable bubble cavitation in according to the present invention. Fig.10A shows waveform of power supply outputs, and Fig.10B shows the temperature curve corresponding to each cycle of cavitation. Operation process steps according to the present invention are disclosed as follows:

[0098] Step 1: Put ultra/mega sonic device adjacent to surface of wafer or substrate set on a chuck or tank;

[0099] Step 2: Fill chemical liquid or gas doped water between wafer and the ultra/mega sonic device;

[00100] Step 3: Rotate chuck or oscillate wafer;

[00101] Step 4: Set power supply at frequency f_1 and power P_1 ;

[00102] Step 5: Before temperature of gas and vapor inside bubble reaches implosion temperature T_i , (total time τ_1 elapses), set power supply output at frequency f_1 and power P_2 , and P_2 is smaller than P_1 . Therefore the temperature of gas inside bubble start to cool down since the temperature of liquid or water is much lower than gas temperature.

[00103] Step 6: After temperature of gas inside bubble decreases to certain temperature close to room temperature T_0 or time (zero power time) reach τ_2 , set power supply at frequency f_1 and power P_1 again.

[00104] Step 7: repeat Step 1 to Step 6 until wafer is cleaned.

[00105] In step 6, the temperature of gas inside bubble can not be cooled down to room temperature due to power P_2 , there should be a temperature difference ΔT_2 existing in later stage of τ_2 time zone, as shown in Fig. 10B.

[00106] FIGs.11A to 11B show another embodiment of wafer cleaning method using a ultra/mega sonic device according to the present invention. The method is similar to that shown in Fig. 10A, except in step 5 setting ultra/mega sonic power at frequency f_2 and power P_2 , where f_2 is lower than f_1 and P_2 is less than P_1 . Since f_2 is lower than f_1 , the temperature of gas or vapor inside bubble increasing faster, therefore the P_2 should be set significantly less than P_1 , better to be 5 or 10 times less in order to reduce temperature of gas and or vapor inside bubble.

[00107] FIGs.12A to 12B show another embodiment of wafer cleaning method using a ultra/mega sonic device according to the present invention. The method is similar to that shown in Fig. 10A, except in step 5 setting ultra/mega sonic power at frequency f_2 and power P_2 , where f_2 is higher than f_1 , and P_2 is equal to P_1 .

[00108] FIGs.13A to 13B show another embodiment of wafer cleaning method using a ultra/mega sonic device according to the present invention. The method is similar to that shown in Fig. 10A, except in step 5 setting ultra/mega sonic power at frequency f_2 and power P_2 , where f_2 is higher than f_1 , and P_2 is less than P_1 .

[00109] FIGs.14A-14B shows another embodiment of wafer cleaning method using a ultra/mega sonic device according to the present invention. The method is similar to that shown in Fig. 10A, except in step 5 setting ultra/mega sonic power at frequency f_2 and

power P_2 , where f_2 is higher than f_1 , and P_2 is higher than P_1 . Since f_2 is higher than f_1 , the temperature of gas or vapor inside bubble increasing slower, therefore the P_2 can be slightly higher than P_1 , but must make sure the temperature of gas and vapor inside bubbler decreases in time zone τ_2 comparing to temperature zone τ_1 , as shown in Fig.14B

[00110] Fig.4A and 4B show that patterned structure is damaged by the violent micro jet. Fig.15A and 15B show that the stable cavitation can also damage the patterned structure on wafer. As bubble cavitation continues, the temperature of gas and vapor inside bubble increases, therefore size of bubble 15046 also increases as shown in Fig.15A. When size of bubble 15048 becomes larger than dimension of space W in patterned structure as shown in Fig.15B, the expansion force of bubble cavitation can damage the patterned structure 15034 as shown in Fig.15C. Another cleaning method according to the present invention are disclosed as follows:

[00111] Step 1: Put ultra/mega sonic device adjacent to surface of wafer or substrate set on a chuck or tank;

[00112] Step 2: Fill chemical liquid or gas doped water between wafer and the ultra/mega sonic device;

[00113] Step 3: Rotate chuck or oscillate wafer;

[00114] Step 4: Set power supply at frequency f_1 and power P_1 ;

[00115] Step 5: Before size of bubble reaches the same dimension of space W in patterned structures (time τ_1 elapse), set power supply output to zero watts, therefore the temperature of gas inside bubble starts to cool down since the temperature of liquid or water is much lower than gas temperature;

[00116] Step 6: After temperature of gas inside bubble continues to reduce (either it reaches room temperature T_0 or time (zero power time) reach τ_2 , set power supply at frequency f_1 power P_1 again;

[00117] Step 7: repeat Step 1 to Step 6 until wafer is cleaned;

[00118] In step 6, the temperature of gas inside bubble is not necessary to be cooled down to room temperature, it can be any temperature, but better to be significantly lower than implosion temperature T_i . In the step 5, bubble size can be slightly larger than dimension of patterned structures as long as bubble expansion force does not break or damage the patterned structure. The time τ_1 can be determined experimentally by using the following method:

[00119] Step 1: Similar to Table 1, choosing 5 different time τ_1 as design of experiment (DOE) conditions,

[00120] Step 2: choose time τ_2 at least 10 times of τ_1 , better to be 100 times of τ_1 at the first screen test

[00121] Step 3: fix certain power P_0 to run above five conditions cleaning on specific patterned structure wafer separately. Here, P_0 is the power at which the patterned structures on wafer will be surely damaged when running on continuous mode (non-pulse mode).

[00122] Step 4: Inspect the damage status of above five wafers by SEMS or wafer pattern damage review tool such as AMAT SEM vision or Hitachi IS3000, and then the damage time τ_i can be located in certain range.

[00123] Step 1 to 4 can be repeated again to narrow down the range of damage time τ_d . After knowing the damage time τ_d , the time τ_1 can be set at a value smaller than $0.5 \tau_d$ for safety margin.

[00124] All cleaning methods described from Figs.7 to Figs.14 can be applied in or combined with the method described in Figs. 15.

[00125] Fig.16 shows a wafer cleaning apparatus using a ultra/mega sonic device. The wafer cleaning apparatus consists of wafer 16010, wafer chuck 16014 being rotated by rotation driving mechanism 16016, nozzle 16064 delivering cleaning chemicals or de-ionized water 16060, ultra/mega sonic device 16062 coupled with nozzle 16064, and ultra/mega sonic power supply. Ultra/mega sonic wave generated by ultra/mega sonic device 16062 is transferred to wafer through chemical or water liquid column 16060. All cleaning methods described from Figs.7 to Figs.15 can be used in cleaning apparatus described in Figs. 16.

[00126] Fig.17 shows a wafer cleaning apparatus using a ultra/mega sonic device. The wafer cleaning apparatus consists of wafers 17010, a cleaning tank 17074, a wafer cassette 17076 holding the wafers 17010 and being held in the cleaning tank 17074, cleaning chemicals 17070, a ultra/mega sonic device 17072 attached to outside wall of the cleaning tank 17074, and a ultra/mega sonic power supply. At least one inlet fills the cleaning chemicals 17070 into the cleaning tank 17074 to immerse the wafers 17010. All cleaning methods described from Figs.7 to Figs.15 can be used in cleaning apparatus described in Figs. 17.

[00127] FIGs.18A to 18C show another embodiment of wafer cleaning method using a ultra/mega sonic device according to the present invention. The method is similar to that shown in Fig. 7A, except in Step 5: Before temperature of gas and vapor inside bubble reaches implosion temperature T_i , (or time reach $\tau_1 < \tau_i$ as being calculated by equation (11)), set power supply output to a positive value or negative DC value to hold or stop ultra/mega sonic device to vibrate, therefore the temperature of gas inside bubble start to cool down since the temperature of liquid or water is much lower than gas temperature. The positive value of negative value can be bigger, equal to or smaller than power P_1 .

[00128] FIGs.19 shows another embodiment of wafer cleaning method using a ultra/mega sonic device according to the present invention. The method is similar to that shown in Fig. 7A, except in Step 5: Before temperature of gas and vapor inside bubble reaches implosion temperature T_i , (or time reach $\tau_1 < \tau_i$ as being calculated by equation (11)), set power supply output at the frequency same as f_1 with reverse phase to f_1 to quickly stop the cavitation of bubble. Therefore the temperature of gas inside bubble start to cool down since the temperature of liquid or water is much lower than gas temperature. The positive value of negative value can be bigger, equal or less than power P_1 . During above operation, the power supply output can be set at a frequency different from frequency f_1 with reverse phase to f_1 in order to quickly stop the cavitation of bubble.

[00129] As shown in Fig.20A to Fig.20D, the bubbles 20012 are in the status of below the saturation point in the feature of vias 20034 or trenches 20036 on a substrate 20010, so as to increase the fresh chemical exchange in the vias 20034 or trenches 20036 due to the bubble cavitation inside the features and also increase the removal of impurities such as residues and particles from the features. The saturation point R_s is defined by the largest amount of bubbles inside the features of vias, trenches or recessed areas. Over the saturation point, the chemical liquid is blocked by the bubbles inside the feature and hardly reaches to the bottom or side walls of the features of vias and trenches, so that the cleaning performance of the chemical liquid is influenced. While below the saturation point, the chemical liquid has enough feasibility inside the features of vias or trenches, and a good cleaning performance is achieved.

[00130] Below the saturation point, the ratio R of total bubbles volume V_B to the volume of via or trench, or recessed space V_{VTR} is:

[00131] $R = V_B / V_{VTR} < R_s$

[00132] And at or above the saturation point R_s , the ratio R of total bubbles volume V_B to the volume of via or trench, or recessed space V_{VTR} is:

[00133] $R = V_B / V_{VTR} = R_s$

[00134] The volume of the total bubbles in the features of vias, trenches or recessed space: $V_B = N v_b$

[00135] Wherein N is the total bubble numbers in the features and v_b is averaged single bubble volume.

[00136] As shown in Fig.20E to Fig.20H, the size of bubble 20012 expanded by the ultra/mega sonic device is gradually to a certain volume, which results in the ratio R of total bubbles volume V_B to the volume of via, trench or recessed space V_{VTR} is closed to or above the saturation point R_s . It leads to the expanded bubble 20012 blocking in the vias or trenches, where is the path of chemical exchanges and impurities removal. In the case, the megasonic power cannot thoroughly transfer into the vias or trenches to reach their bottom and sidewall, meanwhile, the particles, residues and other impurities 20048 trapped in the vias or trenches cannot go out efficiently. This case easily occurs as the critical dimension $W1$ decreasing smaller, and the bubbles in the features of vias and trenches intends to be saturated after being expanded.

[00137] As shown in Fig.20I to Fig.20J, the size of bubble 20012 is expanded by the ultra/mega sonic device within a limitation, and the ratio R of total bubbles volume V_B to the volume of via, trench or recessed space V_{VTR} is much below the saturation point. The fresh chemical 20047 exchanges freely in the vias or trenches due to the bubble cavitation inside the features to achieve a good cleaning performance, meanwhile, the impurities 20048 such as residues and particles go out of the features of vias, trenches and recessed space.

[00138] Due to the total bubbles in the features is related to the bubble numbers and the bubble size in the features of vias and treches, the control of bubble size expanded by the cavitation is critical for the cleaning performance in the high aspect ratio features cleaning process.

[00139] As shown in Fig. 21A to Fig. 21D, after the first cycle of cavitation finishes, the volume of V_1 of gas in bubble is compressed to a minimum size smaller than V_0 during positive sonic power working on it, and the volume of V_2 of gas in bubble will be returned back during the negative sonic power working on it. However, the temperature T_2 in the bubble with the volume of V_2 is higher than the temperature T_0 in the bubble with the

volume of V_0 , as shown in Fig. 21B, so that the volume of V_2 is bigger than the volume of V_0 due to some liquid molecules surrounding bubble will evaporate under the high temperature. And the volume of V_3 by the second compression of the bubble is somewhere between V_1 and V_2 , as shown in Fig. 21B. And V_1 , V_2 and V_3 can be expressed as

$$[00140] \quad V_1 = V_0 - \Delta V \quad (12)$$

$$[00141] \quad V_2 = V_1 + \delta V \quad (13)$$

$$[00142] \quad V_3 = V_2 - \Delta V = V_1 + \delta V - \Delta V = V_0 - \Delta V + \delta V - \Delta V = V_0 + \delta V - 2\Delta V \quad (14)$$

[00143] Where ΔV is volume compression of bubble after one time of compression due to positive pressure generated by ultra/mega sonic wave, and δV is volume increase of the bubble after one time of expansion due to negative pressure generated by ultra/mega sonic wave, and $\delta V - \Delta V$ is volume increase due to temperature increment $\Delta T - \delta T$ as calculated in equation (5) after one time cycle.

[00144] After the second cycle of bubble cavitation, the size of bubble reaches to the larger bubble size during the temperature keeping increasing, the volume of V_4 of gas and or vapor inside bubbler will be

$$[00145] \quad V_4 = V_3 + \delta V = V_0 + \delta V - 2\Delta V + \delta V = V_0 + 2(\delta V - \Delta V) \quad (15)$$

[00146] When the third cycle of bubble cavitation, the volume V_5 of gas and/or vapor inside bubbler will be

$$[00147] \quad V_5 = V_4 - \Delta V = V_0 + 2(\delta V - \Delta V) - \Delta V = V_0 + 2\delta V - 3\Delta V \quad (16)$$

[00148] Similarly, when the nth cycle of bubble cavitation reaches the minimum bubble size, the volume V_{2n-1} of gas and or vapor inside bubbler will be

$$[00149] \quad V_{2n-1} = V_0 + (n-1)\delta V - n\Delta V = V_0 + (n-1)\delta V - n\Delta V \quad (17)$$

[00150] When the nth cycle of bubble cavitation finishes, the volume V_{2n} of gas and/or vapor inside bubbler will be

$$[00151] \quad V_{2n} = V_0 + n(\delta V - \Delta V) \quad (18)$$

[00152] To restrict the volume of bubble into a desired volume V_i , which is a dimension with enough physical feasibility of movement or the bubbles status below the saturation point of cavitation or bubble density, rather than blocking the path of the chemical exchange in the features of vias, trenches or recessed areas, the cycle number n_i can be written as following:

$$[00153] \quad n_i = (V_i - V_0 - \Delta V) / (\delta V - \Delta V) + 1 \quad (19)$$

[00154] From equation (19), the desired time τ_i to achieve the V_i can be written as following:

$$\begin{aligned} [00155] \quad \tau_i &= n_i t_1 = t_1 ((V_i - V_0 - \Delta V) / (\delta V - \Delta V) + 1) \\ &= n_i / f_1 = ((V_i - V_0 - \Delta T) / (\delta V - \Delta V) + 1) / f_1 \end{aligned} \quad (20)$$

[00156] Where, t_1 is cycle period, and f_1 frequency of ultra/mega sonic wave.

[00157] According to formulas (19) and (20), a desired cycle number n_i and a time τ_i to restrict the bubble dimension can be calculated.

[00158] It should be pointed that when the cycle number n of bubble cavitation increases, the temperature of gas and liquid (water) vapor inside bubbler will increase, therefore more molecules on bubble surface will evaporate into inside of bubble, therefore the size of bubble 21082 will further increase and be bigger than value calculated by equation (18). In practical operation, since the bubble size will be determined by experimental method to be disclosed later, therefore bubble size impacted by the evaporation of liquid or water for bubble inner surface due to temperature increase will not be theoretically discussed in detail here. As the average single bubble volume keeping increasing, the ratio R of total bubbles volume V_B to the volume of via, trench or recessed space V_{VTR} increases from R_0 continuously, as shown in Fig. 21D.

[00159] As the bubble volume increases, the diameter of bubble eventually will reach the same size or same order size of feature $W1$ such as via as shown in Fig. 20E and trench or recessed area as shown in Fig. 20G. Then the bubble inside via and trench will block ultra/mega sonic energy further get into the bottom of via and trench, especially when the aspect ratio (depth/width) is larger than 3 time or more. Therefore contaminations or particles at bottom of such deep via or trench cannot be effectively removed or cleaned.

[00160] In order to avoid the bubble growth up to a critical dimension to block the path of chemical exchanges in the features of vias or trenches, Figs. 22A to 22D disclose a method to achieve an effective ultra/mega sonic cleaning on a substrate with high aspect ratio features of vias or trenches by maintaining a restricted size bubble cavitation according to the present invention. Fig. 22A shows waveform of power supply outputs, and Fig. 22B shows the bubble volume curve corresponding to each cycle of cavitation, and Fig. 22C shows the bubble size expansion during each cycle of cavitation, and Fig. 22D shows the curve of the ratio R of total bubbles volume V_B to the volume of via, trench or recessed space V_{VTR} . According to

$$[00161] \quad R = V_B / V_{VTR} = N V_b / V_{VTR},$$

[00162] the ratio R of total bubbles volume V_B to the volume of via, trench or recessed space V_{VTR} increases from R_0 to R_n , where the average single bubble volume being expanded by the sonic cavitation after a certain cycle number n , in the time of τ_1 . And the R_n is controlled below the saturation point R_s ,

[00163] $R_n = V_B / V_{VTR} = N V_b / V_{VTR} < R_s$.

And the ratio R of total bubbles volume V_B to the volume of via, trench or recessed space V_{VTR} decreases from R_n to R_0 , where the average single bubble volume return to original size in the cooling process in the time of τ_2 .

[00164] Operation process steps to avoid bubble size growth up according to the present invention are disclosed as follows:

[00165] Step 1: Put ultra/mega sonic device adjacent to surface of substrate or substrate set on a chuck or tank;

[00166] Step 2: Fill chemical liquid or gas (hydrogen, nitrogen, oxygen, or CO_2) doped water between substrate and the ultra/mega sonic device;

[00167] Step 3: Rotate chuck or oscillate substrate;

[00168] Step 4: Set power supply at frequency f_1 and power P_1 ;

[00169] Step 5: After the volume of bubble expands to a certain volume V_n or diameter w , (or time reach τ_1), set power supply output to zero watts, therefore the volume of gas inside bubble start to shrink down since the temperature of liquid or water cooling down the gas temperature;

[00170] Step 6: After the volume of bubble decreases to original volume while the gas temperature decreasing to room temperature T_0 or time (zero power time) reaches τ_2 , set power supply at frequency f_1 and power P_1 again;

[00171] Step 7: repeat Step 1 to Step 6 until substrate is cleaned.

[00172] In step 5, the expanded bubble's volume of V_n or diameter w is not necessary to be restricted to be smaller than the dimension V_i or feature size w_1 that blocking the features of vias or trenches. It can be certain volume above the V_i , but better to be smaller than the dimension V_i in order to obtain an effective cleaning with shortest process time. And the τ_1 is also not necessary to be restricted to be smaller than τ_i , but better to be smaller than the τ_i as being defined in the equation (20).

[00173] In step 6, the volume of bubble is not necessary to shrink down to an original volume. It can be certain volume above original volume, but better to be significantly

smaller than the V_i to restrict bubble size to get ultra/mega sonic power to be transmitted to the bottom of features such as via, trench, or recessed area.

[00174] Fig.22B shows that the bubble is expanded into a big volume V_n by the ultra/mega sonic power working on it during a time τ_1 . At this state, the path of mass transfer is partially blocked. And then the fresh chemical cannot thoroughly transfer into the vias or trenches to reach their bottom and sidewall, meanwhile, the particles, residues and other impurities trapped in the vias or trenches cannot go out efficiently. But the state will alternate into the next state for bubble shrinking: when the ultra/mega sonic power is off for cooling the bubble during a time τ_2 as shown in Fig.22A. In this cooling state, the fresh chemical has chance to transfer into the vias or trenches so as to clean their bottom and sidewall. When the ultra/mega sonic power is on in the next on cycle, the particles, residues and other impurities can be removed out of the vias or trenches by pull out force generated by bubble volume increment. If the two states are alternating in a cleaning process, it achieves a performance of an effective ultra/mega sonic cleaning on a substrate with high aspect ratio features of vias or trenches or recessed areas.

[00175] The cooling state in the time τ_2 plays a key role in this cleaning process. It should be defined precisely. And the $\tau_1 < \tau_i$, time to restrict bubble size, is desired, and the definition of τ_i also is preferred. The following method can determine the time τ_2 to shrink bubble size during a cooling down state and time τ_1 to restrict the bubble expanded to the blockage size experimentally. The experiment is done by using an ultra/mega sonic device coupling with a chemical liquid to clean a pattern substrate with small features of vias and trenches, where the traceable residues exist to evaluate the cleaning performance.

[00176] Step 1: choose a τ_1 which is big enough to block the features, which can be calculation as τ_i based on the equation (20).

[00177] Step 2: choose different time τ_2 to run DOE. The selection of time τ_2 is at least 10 times of τ_1 , better to be 100 times of τ_1 at the first screen test.

[00178] Step 3: Fix time τ_1 and fix certain power P_0 to run at least five conditions cleaning on specific patterned structure substrate separately. Here, P_0 is the power at which the features of vias or trenches on substrate will be surely not cleaned when running on continuous mode (non-pulse mode).

[00179] Step 4: Inspect the traceable residues status inside the features of vias or trenches of above five substrates by SEMS or element analyzer tool such as EDX.

[00180] The step 1 to step 4 can be repeated again to gradually shorten the time τ_2 till the traceable residues inside the features of vias or trenches are observed. As the time τ_2 is shorten, the volume of bubble cannot shrink down enough, which will gradually block the features and influence the cleaning performance. This time is called critical cooling time τ_c . After knowing critical cooling time τ_c , the time τ_2 can be set at value larger than $2\tau_c$ to gain safety margin.

[00181] A more detail example is shown as follows:

[00182] Step 1: choosing 10 different time τ_1 as design of experiment (DOE) conditions, such as τ_{10} , $2\tau_{10}$, $4\tau_{10}$, $8\tau_{10}$, $16\tau_{10}$, $32\tau_{10}$, $64\tau_{10}$, $128\tau_{10}$, $256\tau_{10}$, $512\tau_{10}$, as shown in Table 3;

[00183] Step 2: choosing time τ_2 at least 10 times of $512\tau_{10}$, better to be 20 times of $512\tau_{10}$ at the first screen test, as shown in Table 3;

[00184] Step 3: fixing certain power P_0 to run above ten conditions cleaning on specific patterned structure substrate separately. Here, P_0 is the power at which the features of vias or trenches on substrate will be surely not cleaned when running on continuous mode (non-pulse mode).

[00185] Table 3

Substrate#	1	2	3	4	5	6	7	8	9	10
τ_1	τ_{10}	$2\tau_{10}$	$4\tau_{10}$	$8\tau_{10}$	$16\tau_{10}$	$32\tau_{10}$	$64\tau_{10}$	$128\tau_{10}$	$256\tau_{10}$	$512\tau_{10}$
τ_2	$5120\tau_{10}$	$5120\tau_{10}$	$5120\tau_{10}$	$5120\tau_{10}$	$5120\tau_{10}$	$5120\tau_{10}$	$5120\tau_{10}$	$5120\tau_{10}$	$5120\tau_{10}$	$5120\tau_{10}$
Power	P_0	P_0	P_0	P_0	P_0	P_0	P_0	P_0	P_0	P_0
Process Time	T_0	T_0	T_0	T_0	T_0	T_0	T_0	T_0	T_0	T_0
Clean Status of Features	1	2	3	4	5	6	5	4	4	3

[00186] Step 4: Using above conditions as shown in Table 3 to process 10 substrates with features of vias or trenches post plasma etching. The reason to choose the post plasma etched substrate is that the polymers generated during etching process are formed on sidewall of trench and via. Those polymers formed on the bottom or side wall of via are difficulty to remove by a conventional method. Then inspect the cleaning status of features of vias or trenches on the ten substrates by SEMS with crossing section of substrates. The data are shown in Table 3. From the Table 3, the cleaning effect reaches the best point of 6 at $\tau_1 = 32\tau_{10}$, therefore the optimum time τ_1 is $32\tau_{10}$.

[00187] If there is no peak to be found, then the step 1 to step 4 with board time setting of τ_1 can be repeated again to find the time τ_1 . After find the initial τ_1 , then step 1 to step 4 with time setting close to τ_1 can be repeated again to narrow down the range of time τ_1 . After knowing the time τ_i , the time τ_2 can be optimized by reducing the time τ_2 from 512 τ_2 to a value till the cleaning effect is reduced. A detail procedure is disclosed as follows Table 4:

Table 4

Substrate#	1	2	3	4	5	6	7	8
τ_1	$32\tau_{10}$	$32\tau_{10}$	$32\tau_{10}$	$32\tau_{10}$	$32\tau_{10}$	$32\tau_{10}$	$32\tau_{10}$	$32\tau_{10}$
τ_2	$4096\tau_{10}$	$2048\tau_{10}$	$1024\tau_{10}$	$512\tau_{10}$	$256\tau_{10}$	$128\tau_{10}$	$64\tau_{10}$	$32\tau_{10}$
Power	P0	P0	P0	P0	P0	P0	P0	P0
Process Time	T_0	T_0	T_0	T_0	T_0	T_0	T_0	T_0
Clean Status of Features	3	4	5	6	7	6	5	3

[00188] From the Table 4, the cleaning effect reaches the best point of 7 at $\tau_2 = 256\tau_{10}$, therefore the optimum time τ_2 is $256\tau_{10}$.

[00189] FIGs.23A to 23C show another embodiment of substrate cleaning method using a ultra/mega sonic device according to the present invention. The method is similar to that shown in Figs. 22A to 22D, except that power is still on for period of $m\tau_1$ even the cavitation reaches a saturation point R_s . Here, m can be number from 0.1 to 100, preferred 2, which is depending on via and trench structure and chemicals, and it need to be optimized by experiment explained in embodiment as Figs. 22A to 22D.

[00190] Method and apparatus disclosed in Fig. 8 to Fig.14, and Fig. 16 to Fig.19 can be applied in embodiments as shown in Fig. 22 and Fig.23, it will not be described here again.

[00191] Generally speaking, an ultra/mega sonic wave with the frequency between 0.1MHz~10MHz may be applied to the method disclosed in the present invention.

[00192] As described above, the present invention discloses a method for effectively cleaning vias, trenches or recessed areas on a substrate using ultra/mega sonic device, comprising: applying liquid into a space between a substrate and an ultra/mega sonic device; setting an ultra/mega sonic power supply at frequency f_1 and power P_1 to drive said ultra/mega sonic device; after the ratio of total bubbles volume to volume inside vias, trenches or recessed areas on the substrate increasing to a first set value, setting said

ultra/mega sonic power supply at frequency f_2 and power P_2 to drive said ultra/mega sonic device; after the ratio of total bubbles volume to volume inside the vias, trenches or recessed areas reducing to a second set value, setting said ultra/mega sonic power supply at frequency f_1 and power P_1 again; repeating above steps till the substrate being cleaned.

[00193] The first set value is below the cavitation saturation point. The second set value is much lower than the cavitation saturate point. The temperature inside bubble cooling down results in the ratio of total bubbles volume to volume inside the vias, trenches or recessed areas reducing to the second set value. The temperature inside bubble cooling down to near temperature of said liquid.

[00194] At above embodiment, the first set value is a cavitation saturation point, and even after the ratio of total bubbles volume to volume inside vias, trenches or recessed areas on the substrate reaches to the cavitation saturation point, the ultra/mega sonic power supply is still kept at frequency f_1 and power P_1 for period of $m\tau_1$, here τ_1 is the time to reach the cavitation saturation point, m is multiples of τ_1 , which is a number between 0.1 to 100, preferred 2.

[00195] According to an embodiment, the present invention discloses an apparatus for effectively cleaning vias, trenches or recessed areas on a substrate using an ultra/mega sonic device. The apparatus includes a chuck, an ultra/mega sonic device, at least one nozzle, an ultra/mega sonic power supply and a controller. The chuck holds a substrate. The ultra/mega sonic device is positioned adjacent to the substrate. The at least one nozzle injects chemical liquid on the substrate and a gap between the substrate and the ultra/mega sonic device. The controller sets the ultra/mega sonic power supply at frequency f_1 and power P_1 to drive the ultra/mega sonic device; after the ratio of total bubbles volume to volume inside vias, trenches or recessed areas on the substrate increasing to a first set value, the controller setting the ultra/mega sonic power supply at frequency f_2 and power P_2 to drive the ultra/mega sonic device; after the ratio of total bubbles volume to volume inside the vias, trenches or recessed areas reducing to a second set value, the controller setting the ultra/mega sonic power supply at frequency f_1 and power P_1 again; repeating above steps till the substrate being cleaned.

[00196] According to another embodiment, the present invention discloses an apparatus for effectively cleaning vias, trenches or recessed areas on a substrate using an ultra/mega sonic device. The apparatus includes a cassette, a tank, an ultra/mega sonic device, at least

one inlet, an ultra/mega sonic power supply and a controller. The cassette holds at least one substrate. The tank holds the cassette. The ultra/mega sonic device is attached to outside wall of the tank. At least one inlet is used for filling chemical liquid into the tank to immerse the substrate. The controller sets the ultra/mega sonic power supply at frequency f_1 and power P_1 to drive the ultra/mega sonic device; after the ratio of total bubbles volume to volume inside vias, trenches or recessed areas on the substrate increasing to a first set value, the controller setting the ultra/mega sonic power supply at frequency f_2 and power P_2 to drive the ultra/mega sonic device; after the ratio of total bubbles volume to volume inside the vias, trenches or recessed areas reducing to a second set value, the controller setting the ultra/mega sonic power supply at frequency f_1 and power P_1 again; repeating above steps till the substrate being cleaned.

[00197] According to another embodiment, the present invention discloses an apparatus for effectively cleaning vias, trenches or recessed areas on a substrate using an ultra/mega sonic device. The apparatus includes a chuck, an ultra/mega sonic device, a nozzle, an ultra/mega sonic power supply and a controller. The chuck holds a substrate. The ultra/mega sonic device coupled with a nozzle is positioned adjacent to the substrate. The nozzle injects chemical liquid on the substrate. The controller sets the ultra/mega sonic power supply at frequency f_1 and power P_1 to drive the ultra/mega sonic device; after the ratio of total bubbles volume to volume inside vias, trenches or recessed areas on the substrate increasing to a first set value, the controller setting the ultra/mega sonic power supply at frequency f_2 and power P_2 to drive the ultra/mega sonic device; after the ratio of total bubbles volume to volume inside the vias, trenches or recessed areas reducing to a second set value, the controller setting the ultra/mega sonic power supply at frequency f_1 and power P_1 again; repeating above steps till the substrate being cleaned.

[00198] Although the present invention has been described with respect to certain embodiments, examples, and applications, it will be apparent to those skilled in the art that various modifications and changes may be made without departing from the invention.

CLAIMS:

1. A method for cleaning vias, trenches or recessed areas on a substrate using an ultra/mega sonic device, comprising:
 - applying liquid into a space between a substrate and an ultra/mega sonic device;
 - setting an ultra/mega sonic power supply at frequency f_1 and power P_1 to drive said ultra/mega sonic device;
 - after the ratio of total bubbles volume to volume inside vias, trenches or recessed areas on the substrate increasing to a first set value, setting said ultra/mega sonic power supply at frequency f_2 and power P_2 to drive said ultra/mega sonic device;
 - after the ratio of total bubbles volume to volume inside the vias, trenches or recessed areas reducing to a second set value, setting said ultra/mega sonic power supply at frequency f_1 and power P_1 again;
 - repeating above steps till the substrate being cleaned.
2. The method of claim 1, wherein the second set value is much lower than a cavitation saturation point.
3. The method of claim 1, wherein the first set value is below a cavitation saturation point.
4. The method of claim 1, wherein the first set value is a cavitation saturation point.
5. The method of claim 4, wherein even after the ratio of total bubbles volume to volume inside vias, trenches or recessed areas on the substrate reaches to the cavitation saturation point, the ultra/mega sonic power supply is still kept at frequency f_1 and power P_1 for period of $m\tau_1$, here τ_1 is the time to reach the cavitation saturation point, m is multiples of τ_1 , after then, setting said ultra/mega sonic power supply at frequency f_2 and power P_2 to drive said ultra/mega sonic device.
6. The method of claim 5, wherein m is a number between 0.1 to 100.
7. The method of claim 1, wherein time interval between setting said power supply at frequency f_1 and power P_1 and setting said ultra/mega sonic power supply at frequency f_2 and power P_2 is shorter than $((V_i - V_0 - \Delta V)/(\Delta V - \delta V) + 1)/f_1$, where V_i is a desired volume, V_0 original volume, ΔV volume compression

of the bubble after one time of compression, δV volume increase of the bubble after one time of expansion.

8. The method of claim 1, wherein said power value P_2 is set as zero.

9. An apparatus for cleaning vias, trenches or recessed areas on a substrate using an ultra/mega sonic device, comprising:

- a chuck holding a substrate;
- an ultra/mega sonic device being positioned adjacent to the substrate;
- at least one nozzle injecting chemical liquid on the substrate and a gap between the substrate and the ultra/mega sonic device;
- an ultra/mega sonic power supply;
- a controller setting the ultra/mega sonic power supply at frequency f_1 and power P_1 to drive said ultra/mega sonic device; after the ratio of total bubbles volume to volume inside vias, trenches or recessed areas on the substrate increasing to a first set value, setting the ultra/mega sonic power supply at frequency f_2 and power P_2 to drive said ultra/mega sonic device; after the ratio of total bubbles volume to volume inside the vias, trenches or recessed areas reducing to a second set value, setting the ultra/mega sonic power supply at frequency f_1 and power P_1 again; repeating above steps till the substrate being cleaned.

10. The apparatus of claim 9, wherein the second set value is much lower than a cavitation saturation point.

11. The apparatus of claim 9, wherein the first set value is below a cavitation saturation point.

12. The apparatus of claim 9, wherein the first set value is a cavitation saturation point.

13. The apparatus of claim 12, wherein even after the ratio of total bubbles volume to volume inside vias, trenches or recessed areas on the substrate reaches to the cavitation saturation point, the ultra/mega sonic power supply is still kept at frequency f_1 and power P_1 for period of $m\tau_1$, here τ_1 is the time to reach the cavitation saturation point, m is multiples of τ_1 , after then, setting said ultra/mega sonic power supply at frequency f_2 and power P_2 to drive said ultra/mega sonic device.

14. The apparatus of claim 13, wherein m is a number between 0.1 to 100.

15. The apparatus of claim 9, wherein time interval between setting said power supply at frequency f_1 and power P_1 and setting said ultra/mega sonic power supply at frequency f_2 and power P_2 is shorter than $((V_i - V_0 - \Delta V)/(\Delta V - \delta V) + 1)/f_1$, where V_i is a desired volume, V_0 original volume, ΔV volume compression of the bubble after one time of compression, δV volume increase of the bubble after one time of expansion.

16. The apparatus of claim 9, wherein said power value P_2 is set as zero.

17. An apparatus for cleaning vias, trenches or recessed areas on a substrate using an ultra/mega sonic device, comprising:

a cassette holding at least one substrate;

a tank holding said cassette;

an ultra/mega sonic device being attached to outside wall of said tank;

at least one inlet for filling chemical liquid into said tank to immerse said substrate;

an ultra/mega sonic power supply;

a controller setting an ultra/mega sonic power supply at frequency f_1 and power P_1 to drive said ultra/mega sonic device; after the ratio of total bubbles volume to volume inside vias, trenches or recessed areas on the substrate increasing to a first set value, setting said ultra/mega sonic power supply at frequency f_2 and power P_2 to drive ultra/mega sonic device; after the ratio of total bubbles volume to volume inside the vias, trenches or recessed areas reducing to a second set value, setting said ultra/mega sonic power supply at frequency f_1 and power P_1 again; repeating above steps till the substrate being cleaned.

18. The apparatus of claim 17, wherein the second set value is much lower than a cavitation saturation point.

19. The apparatus of claim 17, wherein the first set value is below a cavitation saturation point.

20. The apparatus of claim 17, wherein the first set value is a cavitation saturation point.

21. The apparatus of claim 20, wherein even after the ratio of total bubbles volume to volume inside vias, trenches or recessed areas on the substrate reaches to the cavitation saturation point, the ultra/mega sonic power supply is still kept at frequency f_1 and power P_1 for period of $m\tau_1$, here τ_1 is the time to reach the

cavitation saturation point, m is multiples of τ_1 , after then, setting said ultra/mega sonic power supply at frequency f_2 and power P_2 to drive said ultra/mega sonic device.

22. The apparatus of claim 21, wherein m is a number between 0.1 to 100.

23. The apparatus of claim 17, wherein said power value P_2 is set as zero.

24. An apparatus for cleaning vias, trenches or recessed areas on a substrate using an ultra/mega sonic device, comprising:

a chuck holding a substrate;

an ultra/mega sonic device coupled with a nozzle being positioned adjacent to the substrate, said nozzle injecting chemical liquid on the substrate;

an ultra/mega sonic power supply;

a controller setting the ultra/mega sonic power supply at frequency f_1 and power P_1 to drive said ultra/mega sonic device; after the ratio of total bubbles volume to volume inside vias, trenches or recessed areas on the substrate increasing to a first set value, setting said ultra/mega sonic power supply at frequency f_2 and power P_2 to drive said ultra/mega sonic device; after the ratio of total bubbles volume to volume inside the vias, trenches or recessed areas reducing to a second set value, setting said ultra/mega sonic power supply at frequency f_1 and power P_1 again; repeating above steps till the substrate being cleaned.

25. The apparatus of claim 24, wherein the second set value is much lower than a cavitation saturation point.

26. The apparatus of claim 24, wherein the first set value is below a cavitation saturation point.

27. The apparatus of claim 24, wherein the first set value is a cavitation saturation point.

28. The apparatus of claim 27, wherein even after the ratio of total bubbles volume to volume inside vias, trenches or recessed areas on the substrate reaches to the cavitation saturation point, the ultra/mega sonic power supply is still kept at frequency f_1 and power P_1 for period of $m\tau_1$, here τ_1 is the time to reach the cavitation saturation point, m is multiples of τ_1 , after then, setting said ultra/mega sonic power supply at frequency f_2 and power P_2 to drive said ultra/mega sonic device.

29. The apparatus of claim 28, wherein m is a number between 0.1 to 100.

30. The apparatus of claim 24, wherein said power value P_2 is set as zero.