

SPECIFICATION

TITLE OF THE INVENTION

MAGNETIC MARKER AND MAGNETIC MARKER DETECTION SYSTEM

5

TECHNICAL FIELD OF THE INVENTION

001 The present invention relates to magnetic markers laid on a road.

10

BACKGROUND OF THE INVENTION

002 Conventionally, a magnetic marker detection system for vehicles using a magnetic marker laid on a road has been known (for example, refer to Japanese Unexamined Patent Application Publication No. 2005-202478). This magnetic marker detection system is to provide various driving supports using the magnetic marker laid along a lane, such as automatic steering control and lane departure warning, for vehicles equipped with magnetic sensors.

Patent Literature

20

003 Patent Literature 1: JP 2005-202478

SUMMARY OF THE INVENTION

004 However, the above-described conventional magnetic marker detection system for vehicles has the following problem. That is, while the magnetic marker has to have a strong magnetic force to some extent so as to be detectable by the magnetic sensor on the vehicle attached at a high position on the order of 100 mm to 250 mm from a road surface, if the magnetic force of the magnetic marker is too strong, a metallic substance such as a nail or bolt falling on the road surface may be attracted to the magnetic marker to induce troubles such as a flat tire of a vehicle.

30

005 The present invention was made in view of the above-described

conventional problem to provide a magnetic marker and magnetic marker detection system with a reduced magnetic force.

006 A first aspect of the present invention is directed to a
5 magnetic marker laid on a road surface so as to be detectable by a magnetic sensor attached to a bottom surface side of a vehicle to achieve driving support control on a vehicle side for supporting driving of a driver, wherein

the magnetic marker has a surface taken as a reference height,
10 and a magnetism reach ratio G_h/G_s , which is a ratio of a magnetic flux density G_h at a position at a height of 250 mm with respect to a magnetic flux density G_s of the surface at a position at a height of 0 mm, is equal to or larger than 0.5%.

007 A second aspect of the present invention is directed to a
15 magnetic marker detection system in which magnetism generated from a magnetic marker laid on a road surface is detected by a magnetic sensor attached to a bottom surface side of a vehicle to achieve driving support control on a vehicle side, wherein

the magnetic marker is the magnetic marker according to the
20 first aspect.

008 The magnetic marker according to the present invention is a road marker with the magnetism reach ratio G_h/G_s , which is a ratio of the magnetic flux density G_h at the position at the height of 250 mm with respect to the magnetic flux density G_s of the surface,
25 being equal to or larger than 0.5%. If the the magnetism reach ratio G_h/G_s is equal to or larger than 0.5%, the magnetic flux density G_s of the surface of the magnetic marker can be reduced to two hundred times or less with respect to the magnetic flux density G_h at the position at the height of 250 mm.

009 As described above, the magnetic marker according to the
30 present invention is a road marker with excellent characteristics, in which the magnetic flux density G_s of the surface can be reduced

with respect to the magnetic flux density G_h at the position at the height of 250 mm and the magnetic force on the surface surface can be reduced. The magnetic marker detection system according to the present invention is a system in which by adopting the magnetic marker in which the magnetic force on the surface can be reduced as described above, a fear of the magnetic marker attracting a metallic substance is reduced.

BRIEF DESCRIPTIONS OF THE DRAWINGS

10 010 FIG. 1 is a diagram for describing a magnetic marker detection system in a first embodiment;

FIG. 2 depicts a top view and a side view of a magnetic marker in the first embodiment;

15 FIG. 3 is a block diagram depicting an electric structure of a magnetic sensor in the first embodiment;

FIG. 4 is a graph depicting a magnetic field distribution of the magnetic marker in a vertical direction in the first embodiment;

20 FIG. 5 is a graph exemplarily depicting a relation between the diameter of a magnet and a magnetic flux density G_h at a position at a height of 250 mm in the first embodiment;

FIG. 6 is a graph depicting a magnetic field distribution of the magnetic marker in the vertical direction in the first embodiment;

25 FIG. 7 is a graph depicting a relation between the diameter of the magnet and a magnetic flux density G_s in a second embodiment

FIG. 8 is a graph depicting a relation between the diameter of the magnet and a magnetism reach ratio G_h/G_s in the second embodiment; and

30 FIG. 9 is a graph depicting a relation between the thickness of the magnet and the magnetism reach ratio G_h/G_s in the second embodiment.

DESCRIPTIONS OF THE PREFERRED EMBODIMENTS

011 In consideration of the above-ground height of the vehicle's body floor of any of various vehicles including passenger vehicles, buses, and trucks, it is required to assume an attachment height
5 of the magnetic sensor which detects the magnetic marker according to the present invention in a range up to 250 mm from a road surface. Thus, in the present invention, a magnetism reach ratio G_h/G_s is defined, which is a ratio of the magnetic flux density G_h at a position at the height of 250 mm with respect to the magnetic flux
10 density G_s of the surface. The magnetic flux density may be a magnetic flux density of magnetism in a vertical direction or other directions.

012 As a magnetic marker according to the present invention, a plastic magnet or rubber magnet is suitably adopted. For example,
15 if the plastic magnet or rubber magnet resistant to cracking compared with a sintered magnet or the like is adopted, a magnetic marker resistant to use for a long period of time can be provided. Also, if the magnet of this type moldable at relatively low cost with high accuracy is adopted, a high-quality magnetic marker can be provided
20 at reduced production cost. Furthermore, for example, a flexible rubber magnet can also flexibly address asperities on a road surface at the time of construction, deformation of asperities on a road surface in operation, and so forth.

013 Various driving support control can be achieved on a vehicle
25 side by laying the magnetic marker according to the present invention, including travel control, warning control, and information notification control or the like. The travel control includes, for example, automatic steering control for causing a vehicle to travel along magnetic markers laid along a lane, merge/branch control using
30 magnetic markers laid on a merge road/branch road, and stop control for stopping the vehicle when magnetic marker laid before a stop line at an intersection or the like is detected. The warning control

includes, for example, control of warning the driver of a lane departure with reference to magnetic markers laid along a lane and control of warning the driver of an excessive speed when the vehicle passes through magnetic markers laid before an intersection or the like. The information notification control includes control for notifying that the vehicle is approaching an intersection, a branch road, or a tollgate, and control for accurately notifying that the vehicle is approaching a position of an intersection where the vehicle is to turn right during navigation for route guide. The notification control may further include control for notifying information acquirable on the vehicle side by reading the arrangement of the N pole and the S pole of the magnetic markers.

014 In the magnetic marker of one suitable aspect of the present invention, the magnetic flux density G_h is equal to or larger than $0.5 \mu\text{T}$ (microtesla) and equal to or smaller than $20 \mu\text{T}$. When the magnetism reach ratio G_h/G_s is equal to or larger than 0.5% and the magnetic flux density G_h is equal to and smaller than $20 \mu\text{T}$, the magnetic flux density G_s of the surface can be reduced within 4 mT ($20 \mu\text{T}/0.5\%$). For example, a magnetic sheet for office use to be attached to a whiteboard at an office, a stationery magnetic sheet to be attached to the door of a home refrigerator, and so forth have a magnetic flux density of a surface on the order of 20 mT to 40 mT. These magnetic sheets each have a weak magnetic force to the extent of being able to retain its own weight, and are not magnets which magnetically attract a metallic substance such as a nail or bolt falling on the road surface. If the magnetic marker merely having the magnetic flux density G_s of the surface of 4 mT, which is equal to or smaller than 1/5 of that of the magnetic sheet for office use, is laid on the road surface, a fear of magnetically attracting a metallic substance such as a nail or bolt falling on the road surface is very slight. Thus, troubles such as a flat tire of a vehicle due to the magnetic marker laid on the road surface

hardly occur.

The magnetic flux density G_h of the magnetic marker may be equal to or larger than $0.5 \mu T$ and equal to or smaller than $10 \mu T$. In this case, the magnetic flux density G_s of the surface can be further reduced. If the magnetism reach ratio G_h/G_s is equal to or larger than 0.5%, the magnetic flux density G_s of the surface can be reduced within 2 mT ($10 \mu T/0.5\%$).

015 In the magnetic marker of one suitable aspect of the present invention, the magnetism reach ratio G_h/G_s is equal to or larger than 1.0%. If the magnetism reach ratio G_h/G_s is equal to or larger than 1.0%, this further enhances the operational advantage of the present invention, in which the magnetic flux density G_s of the surface can be reduced with respect to the magnetic flux density G_h required for detection.

016 The magnetic marker of one suitable aspect of the present invention has a diameter equal to or larger than 100 mm. The inventors have found through researches and developments over a long period of time that as the larger the diameter of the magnetic marker is, the higher the magnetism reach ratio G_h/G_s is. In particular, in a diameter range equal to or larger than 100 mm, the degree of increase of the magnetism reach ratio G_h/G_s with respect to the diameter of the magnetic marker is significant. On the other hand, if the diameter of the magnetic marker is too large, it is difficult to distinguish the magnetic marker from a magnetic source such as an iron-made lid of a manhole laid on the road, for example. The size of the magnetic marker is set preferably in consideration of the type, size, magnetic field intensity, and so forth of a magnetism generation source that is present on the road where the magnetic marker is to be laid.

017 A magnetic marker of a suitable aspect of the present invention has a surface to which a coating or resin mold having a waterproof and wear-resistant effect is applied. Applying a coating or resin

mold to the surface can improve durability of the magnetic marker. The coating or resin mold may be applied also to a surface of the magnetic marker to be laid down, such as a back surface or outer peripheral side surface.

5 018 A magnetic marker of a suitable aspect of the present invention has a flat shape having a thickness equal to or smaller than 5 mm and can be laid on the road surface without boring a recessed accommodation hole. Any magnetic marker that can be laid without boring a recessed accommodation hole or the like in the road surface
10 can be laid by highly-efficient laying work at low cost. Methods for fixing to the road surface include, for example, adhesive joint with a material having an adhesive function or the like and fixing by hammering a pin or the like into the road surface.

019 In a magnetic marker detection system of one suitable aspect
15 of the present invention, at least one type among a magneto-impedance sensor (MI sensor), a fluxgate sensor, and a TMR sensor is used as the magnetic sensor. The magneto-impedance sensor, the fluxgate sensor, and the TMR sensor are all known as magnetic sensors that can detect magnetism with high sensitivity. A magnetic marker
20 detection system using at least one type among these can reliably detect magnetism generated from the magnetic marker with the reduced magnetic flux density Gs of the surface combined for use.

020 The magneto-impedance (MI) sensor is a magnetic sensor using a magneto-impedance element including a magneto-sensitive body with
25 its impedance changing in accordance with an external magnetic field. The magneto-impedance element (MI element) is an element which detects magnetism by using the magneto-impedance effect (MI effect), in which the depth (thickness) of the skin layer is fluctuated by the external magnetic field due to the skin effect, in which the
30 current density of skin layer increases when a pulse current, high-frequency current, or the like flows through the magneto-sensitive body, causing the impedance of the

magneto-sensitive body to change in a sensitive manner. According to the MI element using this MI effect, highly-sensitive magnetic measurements can be performed. The use of the MI element can achieve a low-cost, small-sized magnetic sensor capable of detecting feeble magnetism on the order of, for example, 0.5 μT to 10 μT . Note that as for the MI sensor using the MI element, many applications have been filed and detailed descriptions are in, for example, International Publication No. WO2005/19851, International Publication No. WO2009/119081, and Japanese Patent No. 4655247.

021 The magneto-sensitive body of the MI element is preferably a high-permeability alloy magnetic body. For example, a magnetic body such as a wire, a thin film, or the like made of a soft magnetic material such as a CoFeSiB-based alloy is preferable. In particular, a zero-magnetostriction amorphous wire is preferable in view of sensitivity, cost, and so forth.

022 For example, a change in impedance of the magneto-sensitive body when a high-frequency current or the like flows may be directly detected from the voltage between the ends of the magneto-sensitive body or may be indirectly detected via a detection coil (pickup coil) wound around the magneto-sensitive body as a change in electromotive force. If the MI element includes a detection coil, detection in a direction of magnetism can be usefully made.

023 The fluxgate sensor is a highly-sensitive magnetic sensor which measures magnetic intensity from a saturation timing by using the fact that the saturation timing of a core flux changes in accordance with the external magnetic field when a periodic current flows through a soft magnetic core. Note that as for the fluxgate sensor, many applications have been filed and detailed descriptions are in, for example, International Publication WO2011/155527 and Japanese Unexamined Patent Application Publication No. 2012-154786.

024 The TMR (Tunneling Magneto Resistive) sensor is a

highly-sensitive sensor with a structure in which an insulator layer having a film thickness on the order of 1 nm is interposed between ferromagnetic layers. The TMR sensor achieves high sensitivity by using the tunneling magneto resistive (TMR) effect, in which the electric resistance of the insulator layer significantly changes in accordance with the external magnetic field when a voltage applied vertically with respect to the film surface produces a tunnel effect that permits a current flow through the insulator layer. Note that as for the TMR sensor, many applications have been filed and detailed descriptions are in, for example, International Publication WO2009/078296 and Japanese Unexamined Patent Application Publication No. 2013-242299.

025 For example, if the MI sensor or the like with high magnetic detection sensitivity is used, it is sufficiently possible to detect magnetism with a magnetic flux density smaller than $0.5 \mu\text{T}$. However, in order to ensure high durability for vehicle mount while achieving high sensitivity allowing detection of subtle magnetism as described above, the cost and size of the magnetic sensor may be increased. On the other hand, if $0.5 \mu\text{T}$ can be ensured as the magnetic flux density G_h , it is possible to provide leeway to design sensitivity and so forth on a magnetic sensor side, and a small-sized, vehicle-mountable magnetic sensor with high durability can be achieved at relatively low cost.

026 (First Embodiment)

25 Described is an example regarding a magnetic marker detection system 1S for vehicles with combination of a magnetic marker 1 laid on a road surface of a road for vehicles and a magnetic sensor 2 attached to a bottom surface side of a vehicle. Details of the present example are described with reference to FIG. 1 to FIG. 6.

30 027 In the magnetic marker detection system 1S for vehicles exemplarily depicted in FIG. 1, a magnetic marker 1 is laid on a road surface 53 so as to be along the center of a lane where a vehicle

5 travels. On a vehicle 5 side, a magnetic sensor 2 is attached to a vehicle's body floor 50, which correspond to a bottom surface of the vehicle 5. An attachment height of the magnetic sensor 2 is varied depending on the vehicle type, but in a range of 100 mm to 250 mm. An output signal from the magnetic sensor 2 is inputted to an ECU, not depicted, or the like of the vehicle 5 for use in various types of control such as automatic steering control and lane departure warning to keep the lane.

028 The magnetic marker 1 exemplarily depicted in FIG. 2 has a flat circular shape having a diameter of 100 mm and a thickness of 1.5 mm, and can be adhesively jointed onto the road surface 53. The magnetic marker 1 is formed by covering both surfaces of a flat magnetic sheet 11 having a diameter of 100 mm and a thickness of 1 mm with a resin mold 12. The magnetic sheet 11 is acquired by molding an isotropic ferrite rubber magnet having a maximum energy product $(BH_{max})=6.4 \text{ kJ/m}^3$ into a sheet shape. A resin mold 12 has a thickness of 0.3 mm on an upper surface side, which corresponds to a front surface of the magnetic marker 1, and a thickness of 0.2 mm on a lower surface side, which corresponds to a surface of the magnetic marker 1 to be laid down. Laying to the road surface 53 is performed by, for example, adhesive fixing with an adhesive agent. The resin mold is preferably applied also to an outer peripheral side surface of the magnetic marker 1. In this case, the diameter of the magnetic marker 1 is increased from 100 mm by approximately 0.5 mm.

029 The specification of the magnetic marker 1 in the present example is partially depicted in Table 1.

[Table 1]

Magnet type	Ferrite rubber magnet
Outer diameter	ϕ 100 mm
Thickness	1.0 mm (except resin mold)
Magnetic flux density Gs of the surface	1mT

030 The magnetic flux density Gs of the surface of this magnetic marker 1 is 1 mT. For example, magnetic sheets for use as attached to a whiteboard at office, the door of a home refrigerator, or the like and magnetic sheets to be attached to a vehicle body such as stickers for newly-licensed drivers have a surface with a magnetic flux density on the order of 20 mT to 40 mT. Compared with these magnetic sheets, it can be intuitively grasped that the magnetic force generated from the magnetic marker 1 of the present example is subtle to the extent that the magnetic marker cannot function as a general magnet which attracts a metallic substance. The magnetic field distribution of this magnetic marker 1 in a vertical direction will be described further below with reference to FIG. 4.

031 As depicted in a block diagram exemplarily depicted in FIG. 3, the magnetic sensor 2 is a one-chip MI sensor, with a MI element 21 and a drive circuit integrated together. The MI element 21 includes an amorphous wire (an example of a magneto-sensitive body) 211 with approximately zero magnetostriction and made of a CoFeSiB-based alloy, and a pickup coil 213 wound around this amorphous wire 211. The magnetic sensor 2 measures a voltage occurring at the pickup coil 213 when a pulse current is applied to the amorphous wire 211, thereby detecting magnetism acting on the amorphous wire 211 as a magneto-sensitive body.

032 The drive circuit is an electronic circuit including a pulse circuit 23 which supplies a pulse current to the amorphous wire 211 and a signal processing circuit 25 which samples and outputs a voltage occurring at the pickup coil 213 at a predetermined timing.

The pulse circuit 23 includes a pulse generator 231 which generates a pulse signal serving as a source of a pulse current. The signal processing circuit 25 extracts an induced voltage of the pickup coil 213 via a synchronous detector 251 which is opened and closed in conjunction with the pulse signal and amplifies the voltage at a predetermined amplification factor by an amplifier 253. A signal acquired by amplification by this signal processing circuit 25 is outputted to the outside as a sensor signal.

033 The specification of the magnetic sensor 2 is partially depicted in Table 2.

[Table 2]

Measurement range	$\pm 0.6\text{mT}$
Magnetic flux resolution	$0.02\ \mu\text{T}$
Sampling period	3kHz

034 This magnetic sensor 2 is a highly-sensitive sensor having a measurement range of the magnetic flux density of $\pm 0.6\text{ mT}$ and a magnetic flux resolution in that measurement range of $0.02\ \mu\text{T}$. This high sensitivity is achieved by the MI element 21 using the MI effect, in which the impedance of the amorphous wire 211 sensitively changes in accordance with the external magnetic field. Furthermore, this magnetic sensor 2 can perform high-speed sampling with a period of 3 kHz, and also supports vehicle's high-speed traveling. In place of sampling with the period of 3 kHz, for example, a magnetic measurement may be performed every time the vehicle moves over a predetermined distance such as 20 mm.

035 Next, the magnetic field distribution of the magnetic marker 1 of the present example in the vertical direction is described with reference to FIG. 4. FIG. 4 is a semilogarithmic graph depicting simulation results by axisymmetric three-dimensional magneto-static analysis using the finite element method. In FIG. 4, a logarithmic scale of the magnetic flux density of magnetism

acting in the vertical direction is set on the vertical axis, and the height in the vertical direction with reference to the surface of the magnetic marker 1 (height from the surface of the marker) is set on the horizontal axis. In FIG. 4, the magnetic flux density when the height from the surface of the marker=0 mm is the "magnetic flux density G_s of the surface", and the magnetic flux density when the height from the surface of the marker=250 mm is the "magnetic flux density G_h at a position at a height of 250 mm (the magnetic flux density G_h at a height of 250 mm as appropriate)".

036 As depicted in FIG. 4, in the magnetic marker 1, the magnetic flux density G_h of magnetism acting at the position at the height of 250 mm is 8 μT. In this magnetic marker 1, the magnetic flux density G_s of the surface is 1 mT (refer to Table 1), and thus the magnetism reach ratio G_h/G_s, which is a ratio of the magnetic flux density G_h at the position at the height of 250 mm with respect to the magnetic flux density G_s of the surface, is 0.8%.

037 According to the magnetic marker 1 with the magnetism reach ratio G_h/G_s of 0.8% and the magnetic flux density G_s of the surface of 1 mT, in a range of 100 mm to 250 mm assumed as an attachment height of the magnetic sensor 2 (sensor attachment height), magnetism of the magnetic flux density equal to or larger than 8 μT can act. When magnetism having a magnetic flux density of 8 μT acts, the magnetic marker 1 can be reliably detected by using the magnetic sensor 2 having a magnetic flux resolution of 0.02 μT (refer to Table 2).

038 In the magnetic marker 1 of the present example, by achieving the magnetism reach ratio G_h/G_s of 0.8%, the magnetic flux density G_s of the surface is reduced to 1 mT (10×10^{-4} T) while magnetic characteristics detectable by the magnet sensor 2 are ensured. This magnetic flux density of 1 mT is smaller than one tenth of the magnetic flux density on the order of 20 mT to 40 mT of the surfaces of magnetic sheets to be attached to a whiteboard or the door of

a refrigerator, for example. The magnetic marker 1 has a very subtle magnetic force even compared with these magnetic sheets for office or home use. Thus, if this magnetic marker 1 is laid on the road surface 53, a fear of attracting a metallic substance such as a nail or bolt is very low.

039 As described above, the magnetic marker 1 of the present example is a road marker with excellent characteristics having a reduced magnetic force. In the magnetic marker detection system 1S including this magnetic marker 1, the magnetic sensor 2 using the MI element 21 is adopted to allow detection of subtle magnetism acting from the magnetic marker 1.

040 Next, the reason why the diameter of 100 mm is selected for the magnetic marker 1 is described with reference to computer simulation results of FIG. 5 and FIG. 6.

A graph in FIG. 5 depicts changes in the magnetic flux density Gh at the height of 250 mm when a columnar magnet having a diameter of 20 mm and a height of 50 mm is taken as a reference, the volume is set as constant (volume=15.7 cm³), but the diameter and the height are changed. FIG. 5 is a graph with the diameter of the magnet taken as the horizontal axis and the magnetic flux density Gh at the height of 250 mm taken as the vertical axis. In FIG. 5, the simulation results are depicted by plotting circles, which are accompanied with heights (mm) of the magnet. The simulation in FIG. 5 is a reference simulation of a neodymium magnet having a remanence (residual magnetic flux density) of 1.19 T. It has been confirmed through a computer simulation, demonstrative experiment, and so forth that an isotropic rubber magnet configuring the magnetic marker 1 of the present example has a similar qualitative tendency.

041 In the graph of FIG. 5, a plot at the left end represents data of a magnet having a diameter of 20 mm × a height of 50 mm serving as a reference. With reference to this plot at the left end, it can be found that the magnetic flux density Gh is improved as the

diameter is increased in a diameter range of of 20 mm to 60 mm. The magnetic flux density Gh becomes close to a maximum value in a diameter range of of 60 mm to 80 mm, and is decreased as the diameter is increased in a diameter range exceeding 80 mm. However, in a diameter range of 80 mm to 100 mm, a rate of variability of the magnetic flux density Gh with respect to the diameter is small, and the decrease of the magnetic flux density Gh is subtle.

042 To ensure the magnetic flux density Gh required at the position at the height of 250 mm, in view of material cost, that is, the amount of use of a magnetic material required to mold a magnet, the most favorable material cost efficiency can be achieved with a magnet having a diameter of 60 mm to 80 mm. On the other hand, in a diameter range smaller than 60 mm and exceeding 80 mm, the material cost efficiency tends to slightly decrease. However, the possibility of keeping sufficiently high material cost efficiency is high in a diameter range of 80 mm to 100 mm with a low degree of decrease of the magnetic flux density Gh.

043 A graph in FIG. 6 depicts a simulation of a magnetic field distribution in the vertical direction for magnetic markers of various sizes having the magnetic flux density Gs of the surface of 1 mT. FIG. 6 depicts the results of the computer simulation for magnetic markers each formed of a isotropic rubber magnet having a maximum energy product $(BH_{max})=6.4 \text{ kJ/m}^3$, as with the magnetic marker 1 of the present example.

044 This simulation is targeted for magnetic markers having diameters of five types from 20 mm to 150 mm including 100 mm. In this simulation, the thickness is changed so that the magnetic flux density Gs of the surface is 1 mT irrespectively of the difference in diameter. For example, $\phi 100 \text{ T } 1$ in legends represents a magnetic marker having a diameter of 100 mm and a thickness of 1 mm. Note herein that the thickness of the resin mold is ignored and the size of the magnetic marker=the size of the magnet.

045 The graph in FIG. 6 is a semilogarithmic graph with graph axes
similar to those of FIG. 4. According to FIG. 6, it can be found
that the magnetic marker having a larger diameter has a higher
magnetic flux density G_h at the height of 250 mm with respect to
5 the magnetic flux density G_s of the surface and attenuation of the
magnetic flux density in the vertical direction is reduced. For
example, by way of comparison as to the magnetic flux density G_h
at the height of 250 mm, the magnetic flux density G_h of a magnet
having a diameter of 50 mm and a thickness 0.5 mm is 2 μT , while
10 the magnetic flux density G_h of a magnet having a diameter of 100
mm and a thickness of 1 mm is 8 μT . In this manner, as the diameter
of the magnetic marker is increased, the magnetism reach ratio
(G_h/G_s) tends to increase, which is a ratio of the magnetic flux
density G_h at the height of 250 mm with respect to the magnetic flux
15 density G_s of the surface.

046 When the magnetic flux density G_h required for detection by
the magnetic sensor 2 is defined, as the above-described magnetism
reach ratio (G_h/G_s) is higher, the magnetic flux density G_s of the
surface of the magnetic marker can be more reduced. As the magnetic
20 flux density G_s of the surface is decreased, an effect is produced
in which the range of selection of a magnetic material, diameter,
thickness, shape, and so forth is widened to improve design
flexibility of the magnetic marker.

047 Thus, in the present example, the diameter of the magnetic
25 marker 1 is set at 100 mm largely on the basis of the following
findings based on simulation results depicted in FIG. 5 and FIG.
6.

(1) The most favorable material cost efficiency can be
achieved in the diameter range of 60 mm to 80 mm, and sufficiently
30 high material cost efficiency can be kept in the diameter range of
80 mm to 100 mm.

(2) The magnetism reach ratio (G_h/G_s), which is a ratio of

the magnetic flux density G_h at the height of 250 mm with respect to the magnetic flux density G_s of the surface, is improved as the diameter of the magnet (magnetic marker) is increased.

048 In place of the circular shape in the present example, the
5 magnetic marker may have a polygonal shape such as a triangular, quadrangular, or hexagonal shape, may have a rectangular shape, or may have a cross shape with two rectangles crossing.

Methods for laying on the road surface may include a method of adhesive joint by using an adhesive agent or the like and a method
10 of fixing by using a fixing pin in a nail-like shape. Furthermore, a method may be adopted in which a magnetic material before magnetization is laminated or applied in advance to a front surface side of a road surface and a predetermined range is magnetized, thereby forming a magnetic marker equivalent to that of the present
15 example. Another exemplary method may be adopted in which a line applied with a coating containing a magnetic material is printed along the center of a lane and then a predetermined position on the line is magnetized.

049 When a magnetic sensor using a highly-directive MI element
20 is adopted, one MI element is preferably provided for each direction of magnetism detection. If only magnetic components in the vertical direction are detected, one MI element is enough. However, it is preferable to provide MI elements so as to respectively correspond to three-dimensional directions. If one MI element is provided for
25 each of the three-dimensional directions, magnetic components generated from the magnetic marker can be three-dimensionally detected. It is also preferable, for example, to provide a MI element for detecting magnetism in the vertical direction of the road surface, a MI element for detecting magnetism in a vehicle's
30 traveling direction, and a MI element for detecting magnetism in a lateral direction (vehicle width direction) of the vehicle. When magnetism in the vehicle's traveling direction is detected, for

example, with a detection of an inversion of positive and negative poles in a magnetic direction, the position of the magnetic marker in the vehicle's traveling direction can be accurately measured.

050 If a plurality of MI elements are provided, a pulse circuit
5 and a signal processing circuit may not be individually provided for each MI element, but may be shared for use in a time-division manner. If these circuits can be shared for use, a reduction in size and cost of the magnetic sensor can be easily achieved.

A plurality of magnetic sensors may be disposed along the
10 lateral direction of the vehicle. With a detection of a peak in a magnetic distribution detected by each magnetic sensor, a relative position of each magnetic marker in the lateral direction may be determined.

051 While the MI sensor using an MI element has been exemplarily
15 described as a magnetic sensor, a fluxgate sensor or TMR sensor can be adopted in place of the above-described MI sensor. If two or more magnetic sensors are used, two or more types among the MI sensor, the fluxgate sensor, and the TMR sensor can be adopted in combination.

052 The type of the magnetic material or magnet of the magnetic
20 sheet configuring the magnetic marker is not limited to that of the present example. Any of various materials and types can be adopted as the type of the magnetic material or magnet. Any appropriate magnetic material and type is selectively determined in accordance
25 with the magnetic specification, environmental specification, and so forth required for the magnetic marker.

In the present example, the specification of the magnetic marker is selectively determined by using the computer simulation results. For use of a computer simulation, simulation accuracy is
30 confirmed in advance through a demonstrative experiment under part of simulation conditions. Also, as for the magnetic marker 1, it has been confirmed through a demonstrative experiment that magnetic

characteristics close to the computer simulation results can be achieved.

053 (Second Embodiment)

5 A second embodiment is an example in which a relation between the diameter of the magnet and the the magnetism reach ratio G_h/G_s is studied based on the first embodiment. The second embodiment is described with reference to FIG. 7 to FIG. 9.

FIG. 7 depicts simulation results indicating a relation between the diameter and the magnetic flux density G_s of the surface of a magnet which acts magnetism with the magnetic flux density $G_h=8$ μT at the position at the height of 250 mm. In FIG. 7, the horizontal axis represents the diameter of the magnet, and the vertical axis represents the magnetic flux density G_s of the surface. Circles are plotted, which are accompanied with thicknesses (heights, mm) of the magnet which achieves the magnetic flux density $G_h=8$ μT .
10
15

FIG. 8 is a graph depicting a relation between the diameter of the magnet and the magnetism reach ratio G_h/G_s . In the graph of FIG. 8, simulation data configuring the graph of FIG. 7 are processed to change a display format.

20 054 According to FIG. 7, it is found that the magnetic flux density G_s of the surface required to achieve the magnetic flux density $G_h=8$ μT at the height of 250 mm increases in a diameter range equal to or smaller than 80 mm. On the other hand, when the diameter exceeds 80 mm, the above-mentioned magnetic flux density G_s of the surface abruptly decreases to approximately 2 mT or smaller. When the diameter exceeds 200 mm, the degree of decrease is reduced to gradually become closer to be constant. The magnetic flux density G_s of the surface required to achieve the magnetic flux density $G_h=8$ μT at the height of 250 mm can be reduced to be approximately equal to or smaller than 1 mT when the diameter exceeds 100 mm, and further decreases as the diameter is closer toward 150 mm.
25
30

055 According to FIG. 8 depicting degrees of changes of the

magnetism reach ratio G_h/G_s with respect to the diameter, it can be found that the correlation of the magnetism reach ratio G_h/G_s with respect to the diameter is high, that is, the magnetism reach ratio G_h/G_s tends to be larger as the diameter is larger.

Furthermore, as the diameter is larger, the gradient of the graph depicting the change ratio of the magnetism reach ratio G_h/G_s with respect to the diameter is larger. In particular, this change ratio greatly changes in a diameter range of 100 mm to 200 mm. This diameter range of 100 mm to 200 mm in which the change ratio greatly changes corresponds to a range in FIG. 7 in which the magnetic flux density G_s of the surface required to achieve the magnetic flux density $G_h=8\text{ }\mu\text{T}$ at the height of 250 mm abruptly decreases.

FIG. 9 depicts simulation results of studying the degree of dependency as to whether the magnetism reach ratio G_h/G_s changes depending on the thickness (mm) of the magnet. In this simulation, with reference to a magnet in a flat shape having a diameter of 100 mm and a thickness of 1 mm, changes of the magnetism reach ratio G_h/G_s when the thickness is changed were studied. In FIG. 9, the horizontal axis represents the thickness of the magnet, and three vertical axes are set, representing the magnetic flux density G_s of the surface, the magnetic flux density G_h at the height of 250 mm, and the magnetism reach ratio G_h/G_s . Numerical values on the vertical axes are represented by plotting circles for the magnetic flux density G_s of the surface, plotting triangles for the magnetic flux density G_h , and plotting squares for the magnetism reach ratio G_h/G_s .

As depicted in the graph of FIG. 9, simulation results were acquired such that when the diameter of the magnet is set constant at 100 mm, the magnetic flux density G_s of the surface and the magnetic flux density G_h at the height of 250 mm both approximately linearly change with respect to the thickness. With the magnetic flux density G_s of the surface and the magnetic flux density G_h at

the height of 250 mm both linearly changing, the magnetism reach ratio G_h/G_s is approximately constant. In this manner, the magnetism reach ratio G_h/G_s is approximately constant irrespectively of the thickness and the magnetic flux density of the magnet. From this, it can be found that the tendency acquired in FIG. 7 and FIG. 8 is a common tendency for various flat-shaped magnetic markers of different magnetic specifications.

058 The simulation results of FIG. 7 to FIG. 9 are those all regarding the flat-shaped magnet with a small dimension in a height (thickness) direction with respect to the diameter. According to these simulation results, the following tendency can be acquired for the flat-shaped magnet. That is, while the magnetism reach ratio G_h/G_s does not change much if the thickness of the magnet is changed, the magnetism reach ratio G_h/G_s depends on the diameter of the magnet, that is, the larger the diameter of the magnet is, the larger the magnetism reach ratio G_h/G_s is. Therefore, it can be found that, to reduce the magnetic flux density G_s of the surface while ensuring the magnetic flux density G_h of magnetism acting on the magnetic sensor, the diameter of the magnet is increased to increase the magnetism reach ratio G_h/G_s .

059 In particular, if the magnetism reach ratio G_h/G_s is in a range equal to or larger than 0.5%, for example, the magnetic flux density G_s of the surface can be reduced to 1.6 mT or smaller with respect to the magnetic flux density $G_h=8\ \mu\text{T}$ at the height of 250 mm. While the magnetic flux density $G_h=8\ \mu\text{T}$ is a magnetic intensity that can be detected with leeway by using a MI element having a magnetic flux resolution of $0.02\ \mu\text{T}$, the magnetic flux density G_s of the surface=1.6 mT is a subtle magnetism lower than 1/10 of the magnetic flux density of magnet sheets for office and business use. Furthermore, if the magnetism reach ratio G_h/G_s is equal to or larger than 1%, the magnetic flux density G_s of the surface can be reduced within 0.8 mT.

060 In the case of a MI element capable of detecting a magnetic flux density of $0.5 \mu\text{T}$, if the magnetism reach ratio G_h/G_s of the magnetic marker is equal to or larger than 0.5%, the magnetic flux density G_s of the surface can be reduced as low as 0.1 mT ($0.5 \mu\text{T}/0.5\%$).

5 If the sensitivity of the MI element is enhanced, a magnetic flux density smaller than $0.5 \mu\text{T}$ can also be detected. However, since the cost and size of the magnetic sensor may be increased to enhance sensitivity, the magnetic flux density G_h at the position at the height of 250 mm is set equal to or larger than $0.5 \mu\text{T}$. Preferably, 10 the magnetic flux density G_h is equal to or larger than $1 \mu\text{T}$.

061 To achieve the magnetism reach ratio G_h/G_s equal to or larger than 0.5%, the diameter of the magnetic marker is set, for example, equal to or larger than 90 mm. More preferably, to achieve the magnetism reach ratio G_h/G_s equal to or larger than 1%, the diameter 15 of the magnetic marker is set equal to or larger than 110 mm. In particular, if the diameter of the magnetic marker is set at 120 mm to 150 mm, the magnetism reach ratio G_h/G_s is further increased, and the effect of reducing the magnetic flux density G_s of the surface is enhanced.

20 062 In general, magnetic lines of force generated from a pole face of a magnet go through a route, which has a loop shape at an outer edge of the pole face, to a pole face on an opposite side, and are tilted more with respect to the vertical direction of the pole face and, on the other hand, the magnetic lines of force tend to be more 25 analogous to a straight line in the vertical direction of the pole face as being nearer to the center away from the outer edge. Thus, as a longer distance is ensured for the magnet from the outer edge of the pole face to the center, stronger magnetism tends to act in the vertical direction of the pole face to increase the magnetism reach ratio G_h/G_s . If the area is constant, a circular shape where 30 the distance from the outer edge to the center is constant is the most advantageous shape for ensuring the magnetism reach ratio G_h/G_s .

When the magnetic marker has a polygonal shape, a shape with a more number of vertexes and closer to a circular shape is more advantageous. Also, for example, when the magnet marker has a quadrangular shape, if the shape is closer to a square with a small difference in length between a long side and a short side, a difference in distance between the center of the pole face and each side is reduced to increase a minimum value, and thus this is advantageous to ensure the magnetism reach ratio G_h/G_s . For example, when the magnetic marker has a triangular shape, similarly, an equilateral triangle shape is advantageous. Furthermore, when the magnetism reach ratio G_h/G_s of the magnetic marker in an equilateral triangle shape is desired to be further increased, the size of the triangle is increased. When the size has a limitation, each side of the equilateral triangle is swelled to the outside in a curved convex shape, such as a rotor shape of a rotary engine. This allows an increase in the distance between the center of the pole face and each side, and thus is effective to improve the magnetism reach ratio G_h/G_s .

063 The large magnetism reach ratio G_h/G_s is effective in detection by not only the MI element described above but also the fluxgate sensor and the TMR sensor, as well as a low-sensitivity Hall element. This is because the magnetic flux density G_s of the surface of the magnetic marker can be reduced with respect to the magnetic flux density G_h required for detection, and the magnetic force of the magnetic marker can be decreased. The reduction in the magnetic force of the magnetic marker can decrease the fear of attracting a metallic substance such as a nail or bolt falling on the road surface, for example. When the magnetic sensor has low sensitivity such as a Hall element, the diameter of the magnetic marker is increased so that the magnetism reach ratio G_h/G_s is equal to or larger than 1% or 2%. For example, if the diameter of the magnetic marker is set at 150 mm to 200 mm, the magnetism reach ratio

Gh/Gs can be improved to 2.4% to 5.2%, and the effect of reduction of the magnetic flux density Gs of the surface can be enhanced.

064 The diameter of the magnetic marker may be equal to or larger than 80 mm. With the diameter being 80 mm, even if the magnetic
5 flux density Gs of the surface is reduced to 1 mT, the magnetic flux density Gh at the position at the height of 250 mm is 5 μ T. With the magnetic flux density being 5 μ T, detection can be sufficiently performed by using the magnetic marker 1 having a magnetic flux resolution of 0.02 μ T (refer to Table 2). The magnetic marker may
10 have a diameter smaller than 80 mm, but the sensitivity of the magnetic sensor has to be enhanced to support a smaller magnetic flux density, thereby possibly increasing cost.

On the other hand, if the diameter of the magnetic marker 1 is too large, it is difficult to distinguish the magnetic marker
15 from a magnetic source such as an iron-made lid of a manhole, for example. The size of the magnetic marker is selectively set in consideration of the type, size, magnetic field intensity, and so forth of a magnetism generation source that is present on the road where the magnetic marker is to be laid.

065 While the specific examples of the present invention have been described above in detail as in the above embodiment, these specific examples merely describe examples of technologies included in the claims. Needless to say, the claims should not be restrictively construed by the structures, numerical values, and so forth of the
25 specific examples. The claims include technologies obtained by variously modifying, changing, and combining the specific examples as appropriate by using known technologies, knowledge, and so forth by people skilled in the art.

Description of Symbols

066

1 magnetic marker

1S magnetic marker detection system

11 flat magnetic sheet
12 resin mold
2 magnetic sensor
21 MI element
5 211 amorphous wire (magneto-sensitive body)
213 pickup coil
5 vehicle
50 vehicle's body floor (bottom surface)
53 road surface

What is claimed is:

1. A magnetic marker laid on a road surface so as to be detectable by a magnetic sensor attached to a bottom surface side of a vehicle to achieve driving support control on a vehicle side for supporting
5 driving of a driver, wherein

the magnetic marker includes a magnet which generates magnetism,

the magnet has a surface taken as a reference height, and a magnetism reach ratio G_h/G_s , which is a ratio of a magnetic flux density G_h at a position at a height of 250 mm with respect to a
10 magnetic flux density G_s at a position at a height of 0 mm, is equal to or larger than 0.5%,

the magnetic flux density G_h is equal to or larger than 0.5 μT and equal to or smaller than 10 μT (equal to or larger than 5mG and
15 equal to or smaller than 100mG),

and a diameter of the magnet is equal to or larger than 80 mm.

2. The magnetic marker according to claim 1, wherein
a coating or resin mold having a waterproof and wear-resistant
20 effect is applied to the surface.

3. The magnetic marker according to claim 1 or 2, wherein
the magnetic marker has a thickness within 5 mm and can be laid on the road surface without boring a recessed accommodation
25 hole.

4. A magnetic marker detection system in which magnetism generated from a magnetic marker laid on a road surface is detected by a magnetic sensor attached to a bottom surface side of a vehicle
30 to achieve driving support control of the vehicle side, wherein
the magnetic marker is the magnetic marker according to any one of claims 1 to 3.

5. The magnetic marker detection system according to claim 4,
wherein

as the magnetic sensor, at least one type among a
5 magneto-impedance sensor, a fluxgate sensor, and a TMR sensor is
used.