

**A MOBILE-LINK SYSTEM FOR A RADIO COMMUNICATION SYSTEM WITH DIVERSITY
RECEPTION OF SELECTED UPLINK SIGNALS**

FIELD OF THE INVENTION

The present invention relates generally to mobile-link systems for radio communication systems, and more particularly to mobile-link systems providing for diversity reception of uplink signals transmitted by mobile stations.

5

BACKGROUND OF THE INVENTION

A mobile-link system for a radio communication system functions to create communication links between a base station and mobile stations located in a coverage area of the base station. To create the communication links, the mobile-link system includes one or more mobile-link assemblies with each mobile-link assembly transmitting downlink signals to mobile stations located in the coverage area or receiving uplink signals from mobile stations located in the coverage area. In the prior art, a mobile-link system often included two or more mobile-link assemblies for receiving uplink signals from the mobile stations and a different mobile-link assembly for transmitting downlink signals to mobile stations in the coverage area.

10

15

20

The use of two or more mobile-link assemblies for receiving uplink signals is known as diversity



reception. A mobile-link system using diversity reception combines the uplink signals received at different mobile-link assemblies to produce diversity uplink signals. Because the diversity uplink signals are formed using a combination of uplink signals, the diversity uplink signals tend to more accurately correspond to the uplink signals transmitted by the mobile stations. In the prior art, diversity reception for the coverage area was typically provided by using an additional mobile-link assembly for receiving uplink signals. The addition of a mobile-link assembly to the base station increases the cost, complexity, weight, and power requirements of the mobile-link system.

These problems associated with use of an additional mobile-link assembly for diversity reception are increased when the base station and associated mobile-link system is satellite based. Weight, complexity, and power requirements are critical factors for satellites and additional mobile-link assemblies or other components used for diversity reception negatively impact all these factors. A mobile-link system is needed that provides for diversity reception and minimizes the above discussed problems.

SUMMARY OF THE INVENTION

A mobile-link system for a radio communication system including a first mobile-link assembly, a second mobile-link assembly, and a satellite feeder-link assembly located in a satellite; and an earth feeder-link assembly located in an earth station. The first and second mobile-link assemblies together provide for transmission of mobile downlink signals and reception of mobile uplink signals for both a first and second zone of a coverage area, and provide diversity reception for the second zone in the coverage area. In

the preferred embodiments, the first zone is a central zone and the second zone is an edge zone.

The first mobile-link assembly receives mobile uplink signals including zone-one uplink signals
5 transmitted from mobile stations located in a first zone of a coverage area and zone-two uplink signals transmitted from mobile stations located in a second zone of the coverage area, and outputs to the satellite feeder-link assembly received zone-one uplink signals
10 and received zone-two uplink signals. The second mobile-link assembly receives mobile uplink signals transmitted from mobile stations in the coverage area, and outputs to the satellite feeder-link assembly received zone-two uplink signals and not zone-one
15 uplink signals. The second mobile link assembly also transmits mobile downlink signals to at least the first and second zones of the coverage area.

The satellite feeder-link assembly conveys the received mobile uplink signals to the earth feeder-link
20 assembly by transmitting feeder-link downlink signals corresponding to the received mobile uplink signals. The earth feeder-link assembly is connected to and couples the mobile-link system to a communication network. The earth feeder-link assembly includes a
25 combiner for combining the feeder-link downlink signals such that the zone-two uplink signals received by the first and second mobile link assemblies are combined to produce diversity resultant signals.

Accordingly, it is an object of the present
30 invention to provide a mobile-link system having a first and second mobile-link assembly that together provide coverage for a first and second zone of a coverage area and diversity reception for only the second zone.



Another object of the present invention is to combine received zone-two uplink signals at the earth feeder-link assembly.

Another object of the present invention is to
5 minimize the components required for the satellite, and to minimize the weight and complexity of the satellite.

These and other objects of the invention, together with features and advantages therefore, will become apparent from the following detailed specification when
10 read with the accompanying drawings in which like reference numerals refer to like elements.

BRIEF DESCRIPTION OF THE DRAWINGS

Figure 1 shows a mobile-link system and its associated coverage area according to the present invention.

15 Figure 2 is a general block diagram of a mobile-link system according to the present invention.

Figure 3 is a block diagram of the first and second mobile-link assemblies according to a first preferred embodiment of the present invention.

20 Figure 4 is a schematic showing representative spot beam coverage of the coverage area by the second mobile-link assembly according to the first preferred embodiment of the present invention.

Figure 5 is a block diagram of the earth station
25 according to the present invention.

Figure 6 is a block diagram of the first and second mobile-link assemblies according to a second preferred embodiment of the present invention.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

Referring now to the drawings, a mobile-link system
30 according to the present invention is shown and indicated generally by the numeral 10. Mobile-link system 10 functions to create communication links

between a base station and mobile stations located in a coverage area of the base station. The base station is connected to a public switch telephone network (PSTN) or other communication network such that the mobile stations in the coverage area can be linked to other communication devices in the communication network. In the preferred embodiment to be described, the base station and its mobile-link system are satellite-based. A mobile-link system according to the present invention could also be implemented in a land-based base station.

Turning to Figure 1, mobile-link system 10 is based in a satellite 12 and earth station 14, and links mobile stations in a coverage area 24 to a communication network 15. The coverage area 24 for the mobile-link system 10 includes a central zone 24a and an edge zone 24b. The edge zone 24b is located along the periphery of the coverage area 24 and the central zone 24a is located in a central area of the coverage area 24. Figure 1 shows a first mobile station 26 located in the central zone 24a and a second mobile station 28 located in the edge zone 24b. The central zone 24a and edge zone 24b are determined based on the relative strength of the communication links provided to the coverage area 24. The mobile links between the mobile stations in the central zone 24a and the mobile-link system 10 are generally stronger than the mobile links between the mobile stations in the edge zone 24b and the mobile-link system 10. The generally stronger communication links for mobile stations in the central area 24a are due primarily to the relatively shorter distance between mobile stations in the central zone 24a and satellite 12, and the relatively smaller impact of shadowing on the mobile stations in the central zone 24a.

The mobile-link system 10 includes a first mobile-link assembly 16, a second mobile-link assembly 18, and

a satellite feeder-link assembly 20 located on satellite 12; and an earth feeder-link assembly 22 located in earth station 14. The first mobile-link assembly 16 and second mobile-link assembly 18 together
5 operate to transmit mobile downlink signals from satellite 12 and receive mobile uplink signals from mobile stations located in the central zone 24a and edge zone 24b of coverage area 24. In the
specification and claims, mobile downlink signals
10 transmitted to central zone 24a will be referred to as central downlink signals and mobile downlink signals transmitted to edge zone 24b will be referred to as edge downlink signals. Likewise, mobile uplink signals
transmitted by mobile stations from central zone 24a
15 will be referred to as central uplink signals and mobile uplink signals transmitted from edge zone 24b will be referred to as edge uplink signals.

The satellite feeder-link assembly 20 and earth feeder-link assembly 22 operate to form a feeder-link
20 between the satellite 12 and earth station 14. The feeder-link created by feeder-link assemblies 20 and 22 allow mobile stations in the coverage area 24 to be linked with communication network 15. For example, the
earth station 14 can be connected to a public switch
25 telephone network (PSTN) enabling mobile stations in the coverage area 24 to communicate with telephones and other communication devices in a communication network connected to the PSTN.

The first mobile-link assembly 16 and second
30 mobile-link assembly 18 of mobile-link system 10 operate in combination to transmit downlink signals to and receive uplink signals from mobile stations located both in the central zone 24a and edge zone 24b. In
addition, the first mobile-link assembly 16 and second
35 mobile-link assembly 18 provide diversity reception of edge uplink signals transmitted from mobile stations

located in the edge zone 24b. Diversity reception is not provided for central uplink signals transmitted from mobile stations located in the central zone 24a. More specifically, the second mobile-link assembly 18
5 transmits downlink signals to both the central zone 24a and the edge zone 24b, and receives uplink signals from the edge zone 24b. The first mobile-link assembly 16 receives uplink signals from both the central zone 24a and the edge zone 24b. Accordingly, an uplink signal
10 transmitted by a mobile station in edge zone 24b will be received at both the first mobile-link assembly 16 and second mobile-link assembly 18.

As discussed in more detail below, the edge uplink signals received by the first mobile-link assembly 16
15 and second mobile-link assembly 18 are combined to provide diversity reception for uplink signals transmitted from the edge zone 24b. Diversity reception is provided for edge uplink signals and not central uplink signals because the edge uplink signals
20 are generally weaker than the central uplink signals. The edge uplink signals are generally weaker due primarily to the longer distance between mobile stations in the edge zone 24b and the satellite 12, and the increased shadowing of mobile stations in the edge
25 zone 24b. Providing diversity reception for the edge uplink signals helps improve the generally lower quality communication links of mobile stations in the edge zone 24b.

Turning to Figure 2, a more detailed block diagram
30 of mobile-link system 10 is shown. The first mobile-link assembly 16 receives central and edge uplink signals, and includes a receive antenna 30 and a primary receiver 32. Receive antenna 30 converts both central and edge uplink signals to an antenna input
35 that is coupled to primary receiver 32. The primary receiver 32 processes the antenna input from receive

antenna 30 and outputs received edge uplink signals and received central uplink signals to feeder-link assembly 20. The primary receiver 32 processes the antenna input to produce the received uplink signals in a conventional manner.

The second mobile-link assembly 18 receives edge uplink signals, and transmits both central and edge downlink signals. The second mobile-link assembly includes a transmit-receive antenna 36, duplexer assembly 38, secondary receiver 40, and mobile-link transmitter 42. To receive edge uplink signals, the transmit-receive antenna 36 converts mobile uplink signals to an antenna input that is fed to duplexer assembly 38. Duplexer assembly 38 directs the antenna input to the secondary receiver 40. The secondary receiver 40 processes the antenna input and outputs received edge uplink signals. The secondary receiver 40 does not output central uplink signals. The received edge uplink signals are output to feeder-link assembly 20.

To transmit mobile downlink signals from second mobile-link assembly 18, mobile-link transmitter 42 outputs central and edge downlink signals to transmit-receive antenna 36 through a direct path 42a and a duplexer path 42b. The transmit-receive antenna 36 outputs central and edge downlink signals to the central zone 24a and edge zone 24b. The mobile downlink signals transmitted by mobile-link assembly 18 correspond to feeder-link uplink signals received at satellite feeder-link assembly 20.

Satellite feeder-link assembly 20 and earth feeder-link assembly 22 communicatively link satellite 12 and earth station 14. The satellite feeder-link assembly 20 conveys mobile uplink signals transmitted by mobile stations and received at satellite 12 to the earth station 14, and receives communication signals from

communication devices and communication network 15 that are transmitted by earth feeder-link assembly 22. The satellite feeder-link assembly 20 conveys mobile uplink signals to earth station 14 by transmitting to earth station 14 feeder-link downlink signals, which correspond to the mobile uplink signals. The communication network signals received at satellite feeder-link assembly 20 are conveyed to selected mobile stations in the coverage area 24 by the second mobile-link assembly 18.

The satellite feeder-link assembly 20 generates feeder-link downlink signals by channelizing central and edge uplink signals outputted by mobile-link assemblies 16 and 18. Accordingly, feeder-link downlink signals correspond to the received central uplink signals and received edge uplink signals.

Satellite feeder-link assembly 20 receives communication network signals from earth station 14 by receiving feeder-link uplink signals transmitted from the earth feeder-link assembly 22. The feeder-link uplink signals are used to convey communication network signals from communication devices in the communication network 15 to satellite 12. Satellite feeder-link assembly 34 channelizes the received feeder-link uplink signals and outputs channelized feeder-link uplink signals to mobile-link transmitter 42. The mobile-link transmitter 42 conveys the communication network signals to mobile stations by processing the channelized feeder-link uplink signals and transmitting corresponding mobile downlink signals. Satellite feeder-link assemblies are known in the prior art.

The earth feeder-link assembly 22 of earth station 14 receives feeder-link downlink signals and transmits feeder-link uplink signals. The feeder-link downlink signals are used to convey to earth station 14 mobile uplink signals received at satellite 12. The feeder-

link uplink signals are used to convey to satellite 12 the communication network signals from communication network 15.

5 The earth feeder-link assembly 22 includes a feeder-link antenna 44, duplexer 46, transmitter 48, receiver 50, and a controller/switch 51. Feeder-link antenna 44 converts feeder-link downlink signals to an antenna input. Duplexer 46 then directs the antenna input from feeder-link antenna 44 to receiver 50.
10 Receiver 50 includes a combiner 52 for selectively combining the feeder-link downlink signals. More specifically, the combiner 52 combines the feeder-link downlink signals that correspond to edge uplink signals received from both the first mobile-link assembly 16
15 and second mobile-link assembly 18 so as to produce resultant diversity signals. The resultant diversity signals correspond to edge uplink signals transmitted by mobile stations in the edge zone 24b. The resultant diversity signals and received feeder-link downlink
20 signals corresponding to central uplink signals are output from receiver 50 to a controller/switch 51. The controller/switch 51 controls the output of outgoing signals, which correspond to mobile uplink signals, to the communication network 15.

25 Earth feeder-link assembly 22 also transmits feeder-link uplink signals that correspond to communication network signals sent from communication devices in the communication network 15 connected to earth station 14. The communication network signals
30 are designated for mobile stations in the coverage area 24. To transmit feeder-link uplink signals. The controller/switch first receives communication network signals from communication network 15. Next, the controller/switch 51 directs the communication network
35 signals to the feeder-link transmitter 48. The feeder-link transmitter 48 transmits to feeder-link antenna 44

feeder-link uplink signals corresponding to the incoming communication network signals. Feeder-link antenna 44 transmits the feeder-link uplink signals to feeder-link assembly 20 of satellite 12.

5 Turning to Figure 3, a first preferred embodiment of the mobile-link system 10 located in satellite 12 is shown. In the first preferred embodiment, the mobile-link antenna 36 of the second mobile-link assembly is a reflector antenna. The transmit-receive antenna 36 of
10 the first mobile-link assembly includes a transmit-receive feed array 56 and a transmit feed array 58. The transmit-receive feed array 56 has transmit-receive feed elements F_i , where $i=1,2,\dots,m$, and transmit feed array 58 has transmit feed elements F_i , where
15 $i=m+1,m+2,\dots,n$.

 The transmit-receive feed elements F_i are configured on antenna 36 to convert only edge uplink signals to antenna input signals and to transmit only edge downlink signals. More specifically, the
20 transmit-receive feed element F_i are located at focal points of edge uplink signals being reflected by the transmit-receive antenna 36 and such that downlink signals transmitted by the transmit-receive feed elements F_i are reflectively directed to the edge zone
25 24b.

 The transmit-receive feed array 56 generates secondary antenna input U_{si} , where $i=1,2,\dots,m$, and outputs the secondary antenna inputs U_{si} to secondary receiver 40. The secondary antenna inputs U_{si}
30 correspond to edge uplink signals and each of the secondary antenna inputs U_{si} corresponds to an edge uplink signal transmitted by a mobile station in edge zone 24b. Secondary receiver 40 includes a bank of receiver chain R_{si} , where $i=1,2,\dots,m$. The receiver
35 chains R_{si} receive the secondary antenna input U_{si} and output received edge uplink signals $\hat{U}_{si}$ where

$i=1,2,\dots,m$. The received edge uplink signals $\hat{U}_{si}$ are outputted from the second mobile-link assembly 18 to the feeder-link assembly 20. Satellite feeder-link assembly 20 conveys the received edge uplink signals $\hat{U}_{si}$ to earth station 14. The satellite feeder-link assembly 20 conveys the received edge uplink signals $\hat{U}_{si}$ by transmitting secondary feeder-link downlink signals I_{si} , where $i=1,2,\dots,m$, to earth station 14. The secondary feeder-link downlink signals I_{si} are generated through conventional processing means including channelization.

Transmit feed elements F_i , where $i=m+1,m+2,\dots,n$, of transmit-receive antenna 36 are configured on transmit-receive antenna 36 to transmit central downlink signals to central zone 24a. More specifically, transmit feed elements F_i are located such that signals transmitted by transmit feed elements F_i are reflectively directed to the central zone 24a and not the edge zone 24b. Transmit feed elements F_i are not connected to receive components.

The transmit-receive feed array 56 and the transmit feed array 58 are both connected to mobile-link transmitter 42. Mobile-link transmitter 42 is coupled to feeder-link assembly 20 and generates mobile downlink signals which correspond to feeder-link uplink signals received at feeder-link assembly 20. Mobile-link transmitter 42 includes a bank of transmitter chains Tx_i , where $i=1,2,\dots,m, m+1,\dots,n$. Transmitter chains Tx_1 to Tx_m transmits edge downlink signals to transmit-receive feed array 56 through path 42a and duplexer assembly 38. Transmitter chains Tx_{m+1} to Tx_n transmits central downlink signals to receive feed array 58 through path 42b.

In Figure 4, transmit-receive feed array 56, transmit feed array 58, and a reflector 57 of transmit-receive antenna 36 are schematically shown generating

representative spot beam for coverage area 24. More specifically, a transmit-receive feed F_i and reflector 57 are shown generating a spot beam in edge zone 24b. Each of the transmit-receive feeds F_i generates a
5 different spot beam in the edge zone 24b so that the transmit-receive feed array 56 provides coverage for the edge zone 24b. Likewise, a transmit feed F_i and reflector 57 are shown generating a spot beam in central zone 24a. Each of the transmit feeds F_i
10 generates a different spot beam in the central zone 24a so that the transmit feed array 58 provides coverage for the central zone 24a.

In the first preferred embodiment of mobile-link system 10, the mobile-link receive antenna 30 of the
15 first mobile-link assembly 16 is also a reflector antenna and has a receive feed array 62. The receive feed assembly 62 has feed elements F_i , where $i=1,2,\dots,n$. The receive feed elements F_i are configured on receive antenna 32 to convert both
20 central and edge uplink signals to antenna inputs U_{pi} , where $i=1,2,\dots,n$. More specifically, the receive feed elements F_i of receive feed assembly 62 are located at focal points of both edge uplink signals and central uplink signals being reflected by the receive antenna
25 30.

The receive feed assembly 62 of receive antenna 30 generates primary antenna inputs $\hat{U}_{pi}$, where $i=1,2,\dots,n$, which are outputted to primary receiver 32. The
30 primary antenna inputs $\hat{U}_{pi}$ correspond to both central and edge uplink signals. Each of the primary antenna inputs U_{pi} correspond to either an edge uplink signal transmitted by a mobile station in edge zone 24b or a central uplink signal transmitted by a mobile station in central zone 24a. Primary receiver 32 includes a
35 bank of receiver chains R_{pi} where $i=1,2,\dots,n$. The receiver chains R_{pi} receive the antenna inputs U_{pi} and

output received uplink signals $\hat{U}_{pi}$, where $i=1,2,\dots,n$. Received uplink signals $\hat{U}_{pi}$ are fed from the first mobile-link assembly 16 to the satellite feeder-link assembly 20. The satellite feeder-link assembly 20 conveys the received edge uplink signals $\hat{U}_{pi}$ to earth station 14. Satellite feeder-link assembly 20 conveys the received uplink edge uplink signals $\hat{U}_{pi}$ by transmitting primary feeder-link downlink signals $\hat{I}_{pi}$, where $i=1,2,\dots,m$, to earth station 14. The primary feeder-link downlink signals $\hat{I}_{pi}$ are generated through conventional processing means including channelization.

Referring to Figure 5, the feeder-link downlink signals $\hat{I}_{si}$ and $\hat{I}_{pi}$ are intercepted by feeder-link antenna 44 of earth station 14, and converted to a secondary feeder-link input $\hat{f}_{si}$ and a primary feeder-link input $\hat{f}_{pi}$ that is directed to receiver 50 via duplexer 46. The secondary feeder-link input $\hat{f}_{si}$ corresponds to edge uplink signals transmitted by mobile stations in the edge zone. The primary feeder-link input $\hat{f}_{pi}$ corresponds to edge uplink signals transmitted by mobile stations in the edge zone and central uplink signals transmitted by mobile stations in the central zone. The primary feeder-link inputs $\hat{I}_{pi}$ corresponding to edge uplink signals are represented by inputs $\hat{f}_{p1}$ to $\hat{f}_{pm}$ and the primary feeder-link inputs $\hat{I}_{pi}$ corresponding to central uplink signals are represented by $\hat{f}_{p(m+1)}$ to $\hat{f}_{pn}$.

Receiver 50 receives the feeder-link inputs $\hat{f}_{si}$ and $\hat{f}_{pi}$ in a conventional manner. In addition, the receiver 50 diversity combines the secondary feeder-link inputs $\hat{f}_{si}$ with the primary feeder-link inputs $\hat{f}_{p1}$ to $\hat{f}_{pm}$. In the preferred embodiment, receiver 50 includes a combiner bank 52 having combiner C_i , where $i=1,2,\dots,m$, for combining the secondary feeder-link inputs $\hat{f}_{si}$ with the primary feeder-link inputs $\hat{f}_{p1}$ to $\hat{f}_{pm}$. Each of the combiners C_i combines a primary

feeder-link input i_{pi} with a secondary feeder-link input i_{si} which correspond to a particular edge uplink signal received at both the first mobile-link assembly 16 and second mobile-link assembly 18. The combiner 51
5 combines the selected primary and secondary feeder-link inputs using conventional combining processes such as selection combining, maximal ratio and equal gain combining.

Combiner bank 52 outputs diversity resultant
10 signals R_i where $i=1,2,\dots,m$. The diversity resultant signals correspond to the mobile edge uplink signals transmitted by mobile stations in the edge zone 24b of coverage area 24 and received at the first and second mobile-link assemblies 16 and 18. Receiver 50 also
15 receives primary feeder-link inputs $i_{p(m+1)}$ to i_{pn} corresponding to central uplink signals received at the first mobile-link assembly 16, and outputs received feeder-link downlink signals $R(m+1)$ to R_n . The
received feeder-link downlink signals $R(m+1)$ to R_n and
20 diversity resultant signals R_i are outputted from the earth feeder-link assembly 22 to controller/switch 51. The controller/switch 51 processes the earth feeder-link assembly output and outputs outgoing communication network information to communication network 15. The
25 outgoing communication network information corresponds to mobile uplink signals initially transmitted from mobile stations in coverage area 24.

Turning to Figure 6, a second preferred embodiment of mobile-link system 10 located in satellite 12 is
30 shown. The second preferred embodiment is different from the first preferred embodiment of mobile-link system 10 in that transmit-receive antenna 36 of the second mobile-link assembly is a direct array antenna. In the second preferred embodiment, the second mobile-
35 link assembly 18 outputs received edge uplink signals transmitted from mobile stations in the edge zone 24b

as follows. Transmit-receive feed array 56 of transmit-receive antenna 36 receives edge and central uplink signals from mobile stations in the edge zone 24b and central zone 24a, and generates secondary antenna inputs U_{si} , where $i=1,2,\dots,m$. The secondary antenna inputs U_{si} is fed to secondary receiver 40 through duplexer 38. Secondary receiver 40 processes the antenna inputs U_{si} in a conventional manner and outputs receiver output signals U_{si}' to a receive beam former 64. Receive beam former 64 includes beam weights B_i , where $i=1,2,\dots,m$, for modifying each of the receiver output signals U_{si}' . The beam weights B_i are selected so that central uplink signals received at the transmit-receive antenna 36 are canceled out after passing through receive beam former 64. The beam weights B_i are multiplied with the receiver output signals U_{si}' to produce received edge uplink signals $\hat{U}_i$ that are outputted from second mobile-link assembly 18. The receive beam former 64 includes an adder 66 for summing the received edge uplink signals prior to outputting the secondary receiver signals U_{si}' to feeder-link assembly 20.

In the second preferred embodiment, the second mobile-link assembly 18 transmits central and edge downlink signals to mobile stations in the central zone 24a and edge zone 24b as follows. Feeder-link uplink signals, after processing including channelization, are outputted from the satellite feeder-link assembly 20 to a transmit beam former 70 having beam weights B_i , where $i=1,2,\dots,n$. Transmit beam former 70 multiplies the channelized feeder-link uplink signals with beam weights B_i . The beam weights of the transmit beam former 70 are selected so that beam signals for producing spot beams for coverage area 24 are generated. The beam signals are passed through mobile-

link transmitter 42, duplexer assembly 38, and antenna 36 as shown to produce spot beams for coverage area 24.

5 The mobile-link system 10 of the present invention includes first and second mobile-link assemblies 16 and 18 that together provide for transmission of mobile downlink signals and reception of mobile uplink signals for both a first and second zone of a coverage area, and that provide diversity reception for the second zone in the coverage area. In the preferred
10 embodiments, the second zone is an edge zone, but other zones within the coverage area that would particularly benefit from diversity reception can be selected for the second zone. The mobile-link system 10 eliminates the need for providing an additional mobile-link
15 assembly used for diversity reception of mobile uplink signals. In addition, by providing diversity reception for only the second zone, the components required for satellite 12 and weight of satellite 12 is minimized. Likewise, by locating the combiner 52 in the earth
20 feeder-link assembly 22, the components required for satellite 12 and weight of satellite 12 is minimized. Accordingly, the mobile-link system 10 of the present invention helps minimize the complexity and weight of satellite 12.

25 It will be appreciated by those of ordinary skill in the art that the present invention can be embodied in other specific forms without departing from the spirit or essential character thereof. The presently disclosed embodiments are therefore considered in all
30 respects to be illustrative and not restrictive.



What is claimed is:

1. A mobile-link system for a radio communication system comprising:

- 5 a) a first mobile-link assembly for receiving mobile uplink signals including zone-one uplink signals transmitted from mobile stations located in a first zone of a coverage area and zone-two uplink signals transmitted from mobile stations located in a second zone of said coverage area, and for outputting received zone-one uplink
10 signals and received zone-two uplink signals;
- b) a second mobile-link assembly for receiving mobile uplink signals transmitted from mobile stations in said coverage area and outputting received zone-two uplink signals and not
15 zone-one uplink signals, and said second mobile-link assembly for transmitting mobile downlink signals to at least said first and second zones of said coverage area;
- 20 c) a combiner for diversity combining said received zone-two uplink signals received by both said first and second mobile-link assemblies so as to produce diversity resultant signals corresponding to zone-two uplink signals received at said first and second mobile-link assemblies.

2. The mobile-link system of claim 1, wherein said second mobile-link assembly includes:

- 5 a) a transmit-receive antenna including transmit-receive feeds for transmitting mobile downlink signals and receiving mobile uplink signals, and transmit feeds for transmitting mobile downlink signals;

THIS SHEET HAS BEEN
REPLACED



WO 97/22188

PCT/US96/19508

19

10 b) a secondary receiver for processing
mobile uplink signals received by said transmit-
receive feeds;

15 c) a mobile-link transmitter for outputting
mobile downlink signals to said transmit-receive
feeds and transmit feeds of said transmit-receive
antenna for transmission of mobile downlink signals
to mobile stations in said first zone and said
second zone;

20 d) a duplexer assembly coupled to said
secondary receiver, mobile-link transmitter, and
transmit-receiver antenna for directing received
uplink signals from said transmit-receive feeds to
said secondary receiver and for directing mobile
downlink signals from said mobile-link transmitter
to said transmit-receive feeds.

3. The mobile-link system of claim 2, wherein
the first mobile-link assembly includes:

5 a) a receive antenna for receiving zone-one
and zone-two uplink signals;

 b) a primary receiver for processing zone-
one and zone-two uplink signals received by said
receive antenna.

4. The mobile-link assembly of claim 3, wherein
the first and second mobile-link assemblies are located
in a satellite and coupled to a satellite feeder-link
assembly, said satellite feeder-link assembly for
5 conveying said received mobile uplink signals outputted
from said mobile-link assemblies to an earth station.

5. The mobile-link system of claim 4, wherein
said satellite feeder-link assembly conveys said
received uplink signals to said earth station by

THIS SHEET HAS BEEN
REPLACED



WO 97/22188

PCT/US96/19508

20

5 transmitting feeder-link downlink signals to said earth station.

6. The mobile-link system of claim 5, wherein said combiner is located in said earth station and combines said feeder-link downlink signals received at said earth station so as to produce said diversity
5 resultant signals corresponding to zone-two uplink signals received at said first and second mobile-link assemblies.

7. The mobile-link system of claim 1, wherein said transmit-receive antenna of said second mobile-link assembly is a reflector antenna, and wherein said second mobile-link assembly receives zone-two uplink
5 signals transmitted from mobile stations in said first zone and does not receive zone-one uplink signals transmitted from mobile stations in said second zone.

8. The mobile-link system of claim 2, wherein said transmit-receive antenna of said second mobile-link assembly is a reflector antenna, and wherein said second mobile-link assembly receives zone-two uplink
5 signals transmitted from mobile stations in said first zone and does not receive zone-one uplink signals transmitted from mobile stations in said second zone.

9. The mobile-link system of claim 8, wherein said transmit-receive feeds of said transmit-receive antenna receives zone-two uplink signals transmitted from mobile stations in said first zone and does not
5 receive zone-one uplink signals transmitted from mobile stations in said second zone.

THIS SHEET HAS BEEN
REPLACED



10. The mobile-link system of claim 8, wherein said mobile-link transmitter transmits zone-one downlink signals to said transmit feeds of said transmit-receive antenna and zone-two downlink signals to said transmit-receive feeds of said transmit-receive antenna.

11. The mobile-link system of claim 10, wherein said duplexer assembly direct zone-two uplink signals from said transmit-receive feeds of said transmit-receive antenna to said secondary receiver and for directing zone-two downlink signals to said transmit-receive feeds of said transmit-receive antenna.

12. The mobile-link system of claim 1, wherein said transmit-receive antenna of said second mobile-link assembly is a direct array antenna, wherein said transmit-receive antenna receives the zone-one and zone-two uplink signals, and wherein said second mobile-link assembly processes said received uplink signals so as to output received zone-two uplink signals.

13. The mobile-link system of claim 2, wherein said transmit-receive antenna of said second mobile-link assembly is a direct array antenna, wherein said transmit-receive antenna receives the zone-one and zone-two uplink signals, and wherein said second mobile-link assembly processes said received uplink signals so as to output received zone-two uplink signals.

14. The mobile-link system of claim 13, wherein said second receiver includes a receive beam former for multiplying received uplink signals from said transmit-receive feeds with predetermined beam forming weights

THIS SHEET HAS BEEN
REPLACED



WO 97/22188

PCT/US96/19508

22

5 so as to output zone-two uplink signals from said second mobile-link assembly.

15. The mobile-link system of claim 14, wherein said mobile-link transmitter includes a transmit beam former for forming downlink signals to be transmitted through said transmit-receive feed array and transmit
5 feed array of said transmit-receive antenna.

16. The mobile-link system of claim 1, wherein said first zone is a central zone of said coverage area and said second zone is an edge zone bordering said central zone.

17. A method for linking mobile-link system for a radio communication system with mobile stations, comprising:

- 5 a) receiving at a first mobile-link assembly mobile uplink signals including zone-one uplink signals transmitted from mobile stations located in a first zone of a coverage area and zone-two uplink signals transmitted from mobile stations located in a second zone of said coverage
10 area, and outputting received zone-one uplink signals and received zone-two uplink signals;
- b) receiving at a second mobile-link assembly mobile uplink signals transmitted from mobile stations in said coverage area and
15 outputting received zone-two uplink signals and not zone-one uplink signals, and transmitting from said second mobile-link assembly mobile downlink signals to at least said first and second zones of said coverage area;
- 20 c) diversity combining said received zone-two uplink signals received by both said first and second mobile-link assemblies so as to produce

THIS SHEET HAS BEEN
REPLACED



WO 97/22188

PCT/US96/19508

23

25 resultant signals corresponding to zone-two uplink signals received at said first and second mobile-link assemblies.

5 18. The method of claim 17, wherein the first and second mobile-link assemblies are located in a satellite and coupled to a satellite feeder-link assembly, and further including the step of conveying received mobile uplink signals outputted from said mobile-link assemblies to an earth station.

5 19. The method of claim 17, wherein said step of conveying received mobile uplink signals to an earth station includes transmitting feeder-link downlink signals from said satellite feeder-link assembly to said earth station.

5 20. The method of claim 17, wherein said diversity combining step includes combining feeder-link downlink signals at said earth station so as to produce said diversity resultant signals corresponding to zone-two uplink signals received at said first and second mobile-link assemblies.

5 21. The method of claim 17, wherein said step of receiving mobile uplink signals at said second mobile-link assembly includes receiving with a reflector antenna zone-two uplink signals transmitted from mobile stations in said first zone and not receiving zone-one uplink signals transmitted from mobile stations in said second zone.

22. The method of claim 17, wherein said step of receiving mobile uplink signals at said second mobile-link assembly includes receiving with a reflector antenna zone-one and zone-two uplink signals

THIS SHEET HAS BEEN
REPLACED



WO 97/22188

PCT/US96/19508

24

5 transmitted from mobile stations in said first zone and said second zone, and processing said received zone-one and zone-two uplink signals so as to output from said second mobile-link assembly received zone-two uplink signals.

23. The method of claim 17, wherein said first zone is a central zone of said coverage area and said second zone is an edge zone bordering said central zone.

THIS SHEET HAS BEEN
REPLACED