

COMMUNICATION SYSTEM, METHOD, AND APPRATUS

5 TECHNICAL FIELD

[0001]

(REFERENCE TO RELATED APPLICATION)

The present invention is based upon and claims the benefit of the
priority of Japanese patent application No. 2011-217384, filed on
10 September 30, 2011, the disclosure of which is incorporated herein in
its entirety by reference thereto.

[0002]

The present invention relates to a communication system, a
method, and an apparatus.

15 BACKGROUND

[0003]

In a core network of a mobile communication system, in order to
provide various services to various kind of terminals (mobile stations),
it is necessary that all of the nodes in the core network are provided
20 with functions required for each service. In large-scale mobile
communication network and the like, many nodes are arranged in the
core network. A terminal, on every location registration, is connected
in a distributed manner to nodes in the core network.

[0004]

25 Thus, all the nodes in the core network need to have necessary
functions for each service (service providing functions). When even a
part of the nodes in the core network do not have the necessary service
providing functions for each service, service continuity for a terminal
cannot be ensured.

30 [0005]

For example, Patent Literature 1 discloses an arrangement for
optimizing a packet forwarding path based on a type of a service
utilized by a mobile station, wherein, when the mobile station utilizes a
service from an external network, a constraint is given to a packet

35

40

forwarding path so that packet flow through a specific packet forwarding apparatus based on the external network. When the mobile station utilized a service provided by a mobile communication network,
5 no constraint is given to a packet forwarding path.

[0006]

[Patent Literature 1]

Japanese Patent Kokai Publication No. 2003-338832A

10 SUMMARY

[0007]

The following describes some analysis of the related technique.

[0008]

As described above, since each node in a core network has all
15 service providing functions, each node is required to have high functionality and high performance. Consequently, each core network node becomes expensive.

[0009]

For example, since a relatively small number of mobile terminals
20 are compatible with an MBMS (Multimedia Broadcast Multicast Service) service (a simultaneous delivery service), which is a bearer service that is standardized by 3GPP (3rd Generation Partnership Project) and that implements broadcast type delivery, there is not much opportunity to provide the MBMS service. However, to provide the
25 service to a small number of MBMS users, it is necessary for a communication operator to have all the nodes in the core network equipped with the MBMS functions. Otherwise, the communication operator cannot provide the service to the small number of MBMS users.

[0010]

30 If a node in the core network can be selected based on whether or not a mobile terminal needs to use the MBMS service, the communication operator can install a relatively small number of expensive core network nodes that are compatible with the MBMS and

many inexpensive core network nodes that are not compatible with the MBMS in combination. In this way, the equipment cost as a whole can be reduced more efficiently (first knowledge of the present inventors).
[0011]

5 In addition, 3GPP machine communication (MTC: Machine Type Communication) devices (M2M devices), which have been in widespread use in recent years, greatly differ from normal terminals used for phone calls (handset terminals) such as mobile phone terminals and smart-phones or the like, in terms of a mobility characteristic, a
10 required communication quality, and so forth. It is known that there are various types of machine communication services, such as for remote management of stocks and charging of automatic vending machines, remote monitoring control in a sensor system, vehicle monitoring, and smart grid.

15 [0012]

In core network nodes, for example, MTC-compatible nodes are customized to be suitable for accommodating a terminal (MTC device) that exchanges more control signals and less user data than normal nodes (for example, these MTC-compatible nodes are customized so that,
20 while a performance of a user plane in which user data is exchanged is reduced for cost reduction, a performance of a control plane of a control signal system is improved). Thus, unless the communication operator makes all the core network nodes equipped with necessary capabilities and functions to successfully connect to an MTC devices and a handset
25 terminal, the communication operator cannot provide the service to both of the MTC device and the handset terminal. The same applies to the MBMS service.

[0013]

If an MTC device and a handset terminal could respectively be
30 connected to appropriate core network nodes, the communication operator is allowed to arrange relatively inexpensive core network nodes for a handset terminal and relatively inexpensive core network nodes for a MTC device in combination (second knowledge of the present inventors).

[0014]

If this is the case, compared with installing relatively expensive core network nodes, each of which is compatible with both of a handset terminal and a MTC device, an equipment cost in a whole system can be reduced more efficiently (third knowledge of the present inventors).

[0015]

Embodiments of the present invention provide a system, a method, and a device for reducing an equipment cost in an entirety of a system more efficiently and achieving cost reduction.

[0016]

Embodiments of the present invention provide the following configuration (but not limited thereto).

[0017]

Disclosed herein is a communication system including a core network for a mobile communication system, wherein the core network comprises a plurality of nodes, each node serving as a node to manage mobility of a terminal, the plurality of nodes being different to each other with regard to service functions that the nodes provide to a terminal, and

wherein based on subscriber information and terminal information, a node to be connected to the terminal is selected from among the plurality of nodes, depending on a service characteristic utilized by the terminal or on a type of the terminal, and the terminal is connected to the selected node.

[0018]

Disclosed herein is a communication method, comprising:

arranging a plurality of nodes for the terminal in a mobile communication system core network, the nodes serving as nodes for managing mobility of a terminal, and being different to each other with regard to service functions that the nodes provide to a terminal;

selecting, based on subscriber information and terminal

information, a node to be connected to the terminal from among the plurality of nodes, depending on characteristics of a service used by the terminal or on a type of the terminal; and

5 connecting the terminal to the selected node.
[0019]

Disclosed herein is a node apparatus that performs control to select, as a mobility management node apparatus to manage mobility of a terminal, another mobility management node apparatus compatible
10 with a service characteristic utilized by the terminal or a type of the terminal, based on subscriber information and terminal information to connect the terminal to the selected another mobility management node apparatus.

15 [0019a] Disclosed herein is a communication system, comprising:

a general MME (Mobility Management Entity) or a general SGSN (Serving GPRS Support Node) for a general terminal other than a predetermined specific terminal, as a core network node managing mobility of a terminal; and

20 a customized MME or a customized SGSN that includes a function to provide a predetermined specific service to the specific terminal or that is customized to be compatible with the specific terminal of a predetermined type,

wherein the general MME, the general SGSN, or the specific
25 terminal selects the customized MME or the customized SGSN as a node to which the specific terminal is connected.

[0019b] According to a first aspect of the present invention, there is provided a mobile communication system, comprising:

30 a terminal (UE(User Equipment) or MS (Mobile Station)) supporting a function associated with MTC (Machine Type Communication);

a base station; and

a specific MME (Mobility Management Entity) or SGSN (a
35 Serving GPRS (General Packet Radio Service) Support Node),

wherein the terminal supporting the function associated with MTC is configured to provide the base station with information indicating that an RRC (Radio Resource Control) connection request includes the function, and

wherein the base station is configured to use the indication information provided by the terminal supporting the function to steer the terminal supporting the function to the specific MME or SGSN, or to
5 select the specific MME or SGSN.

[0019c] According to a second aspect of the present invention, there is provided a base station in a mobile communication system comprising at least a terminal (UE (User Equipment) or an MS (Mobile Station))
10 supporting a function relating to MTC (Machine Type Communication) and a specific MME (Mobility Management Entity) or SGSN (Serving GPRS (General Packet Radio Service) Support Node), characterized in that the base station comprises:

a unit configured to receive information indicating that an RRC
15 (Radio Resource Control) connection request includes the function from the terminal supporting the function; and

a unit configured to use the indication information provided by the terminal supporting the function to steer the terminal supporting the function to the specific MME or SGSN, or to select the specific MME or
20 SGSN.

[0019d] According to a third aspect of the present invention, there is provided a terminal in a mobile communication system comprising at least a base station and a specific MME (Mobility Management Entity)
25 or SGSN (Serving GPRS (General Packet Radio Service) Support Node), and that is a terminal (UE (User Equipment) or an MS (Mobile Station)) supporting a function relating to MTC (Machine Type Communication), characterized in that the terminal comprises:

a unit configured to provide the base station with information
30 indicating that an RRC (Radio Resource Control) connection request includes the function; and

a unit configured to cause the base station to use the indication information provided by the terminal to steer the terminal supporting the function to the specific MME or SGSN, or to select the specific
35 MME or SGSN.

[0019e] According to a fourth aspect of the present invention, there is provided a communication method for a mobile communication system comprising at least a terminal (UE (User Equipment) or an MS (Mobile
40 Station)) supporting a function relating to MTC (Machine Type Communication), a base station, and a specific MME (Mobility Management Entity) or SGSN (Serving GPRS (General Packet Radio Service) Support Node), characterized in that the method comprises:

the terminal supporting the function providing the base station with information indicating that an RRC (Radio Resource Control) connection request includes the function; and

5 the base station using the indication information provided by the terminal to steer the terminal supporting the function to the specific MME or SGSN, or to select the specific MME or SGSN.

[0019f] According to a fifth aspect of the present invention, there is
10 provided a communication method for a base station used in a mobile communication system comprising at least a terminal (UE (User Equipment) or an MS (Mobile Station)) supporting a function relating to MTC (Machine Type Communication) and a specific MME (Mobility Management Entity) or SGSN (Serving GPRS (General Packet Radio
15 Service) Support Node), characterized in that the method comprises:

receiving information indicating that an RRC (Radio Resource Control) connection request includes the function from the terminal supporting the function; and

20 using the indication information provided by the terminal to steer the terminal supporting the function to the specific MME or SGSN, or to select the specific MME or SGSN.

[0019g] According to a sixth aspect of the present invention, there is
25 provided a communication method for a terminal (UE (User Equipment) or an MS (Mobile Station)) in a mobile communication system comprising at least a base station and a specific MME (Mobility Management Entity) or SGSN (Serving GPRS (General Packet Radio Service) Support Node) and that supports a function relating to MTC (Machine Type Communication), characterized in that the method
30 comprises:

providing the base station with information indicating that an RRC (Radio Resource Control) connection request includes the function; and

35 causing the base station to use the indication information provided by the terminal to steer the terminal supporting the function to the specific MME or SGSN, or to select the specific MME or SGSN.

[0020]

According to embodiments of the present invention, cost
5 reduction can be achieved by reducing the equipment cost in the whole
core network system more efficiently.

BRIEF DESCRIPTION OF THE DRAWINGS

[0021]

10 Fig. 1 is a diagram illustrating a system configuration according to a
first exemplary embodiment of the present invention.

Fig. 2 is a diagram illustrating a system configuration according to a
second exemplary embodiment of the present invention.

15 Fig. 3 is a diagram illustrating a sequence according to a first example
of the present invention.

Fig. 4 is a diagram illustrating a sequence according to a second
example of the present invention.

Fig. 5 is a diagram illustrating a sequence according to a third example
of the present invention.

20 Fig. 6 is a diagram illustrating a sequence according to the third
example of the present invention.

Fig. 7 is a diagram illustrating a sequence according to a fourth example
of the present invention.

25 Fig. 8 is a diagram illustrating a sequence according to a fifth example

30

35

40

of the present invention.

Fig. 9 is a diagram illustrating a sequence according to the fifth
5 example of the present invention.

Fig. 10 is a diagram illustrating a sequence according to a sixth example
of the present invention.

Fig. 11 is a diagram illustrating a sequence according to a seventh
example of the present invention.

10 Fig. 12 is a diagram illustrating a sequence according to an eighth
example of the present invention.

Fig. 13 is a diagram illustrating a sequence according to the eighth
example of the present invention.

15 Fig. 14 is a diagram illustrating a sequence according to a ninth
example of the present invention.

Fig. 15 is a diagram illustrating a sequence according to a tenth
example of the present invention.

Fig. 16 is a diagram illustrating a sequence according to the tenth
example of the present invention.

20

PREFERRED MODES

[0022]

First, an outline of the present invention will be described with
reference to Figs. 1 and 2. According to the present invention, a core
25 network includes a plurality of nodes (21/22 in Fig. 1 or 121/122 in Fig.
2) that are different to each other with respect to service functions
provided for a terminal. Based on subscriber information and terminal
information, a node to be connected to the terminal is selected from the
plurality of nodes, in accordance with a service characteristic utilized
30 by the terminal or on a type of the terminal. The terminal (1 in Fig. 1
or 101 in Fig. 2) is connected to the selected node. Namely, in the core
network, a node with a predetermined specific service providing
function (22 in Fig. 1 or 122 in Fig. 2) and a node without the specific
service providing function (21 in Fig. 1 or 121 in Fig. 2) are installed in
35 combination.

[0023]

Thus, according to the present invention, by installing both
types,

40

namely, a node optimized with the specific service providing function and a node without the specific service providing function as the nodes that can be connected to the terminal(s), the cost in the whole system can be reduced further, as compared with cases in which all the nodes in the core network are provided with capabilities and functions for all services.

[0024]

According to the present invention, in a mobile terminal communication network, a terminal can be connected to a specific core network node, depending on a condition such as a service characteristic or a terminal type.

[0025]

<Mode 1>

A General MME (a mobility management entity), upon reception of an Attach Request from a UE (User Equipment, also termed as a user device, a terminal, or a mobile station) determines whether the UE is of a type that uses a specific service, based on subscriber information and terminal information. When the UE is this type, in order to connect the UE to a Customized MME, the General MME transmits an MME re-selection request signal (a mobility management entity re-selection request signal) to an eNodeB (evolved NodeB: a base station apparatus).

[0026]

By re-transmitting, by the eNodeB, an Attach Request to the Customized MME, the UE is connected to the Customized MME.

[0027]

<Mode 2>

A General MME, upon reception of an Attach Request from a UE, transmits an MME change request signal (a mobility management entity change request signal) to the Customized MME, in order to connect the UE to a Customized MME. By continuing an Attach Procedure by the Customized MME, the UE is connected to the Customized MME.

[0028]

<Mode 3>

A General MME, upon reception of an Attach Request from a UE,

transmits, to the UE, an Attach Reject, to which is added an identifier of the Customized MME, in order to connect the UE to a Customized MME. The UE, by re-transmitting an Attach Request, to which is added the identifier of the Customized MME to an Attach Request by the UE, is connected to the Customized MME.

[0029]

<Mode 4>

A UE transmits, to an eNodeB, an RRC (Radio Resource Control) Connection Request (radio resource connection request), to which is added connection request information requesting connection to a Customized MME (specific MME). The eNodeB, which has received the RRC connection request, when transmitting, to an MME, an Attach Request from the UE with RRC Connection established, selects the Customized MME to make the UE connected to the Customized MME.

[0030]

<Mode 5>

When a General MME with a session with a UE being established, performs release (S1 Release) of S1 connection established between an eNodeB and the General MME, the General MME instructs the eNodeB to select a Customized MME, in next selection of an MME. Then after, when the UE transmits a location management area update request (a TA (Tracking Area) Update Request), the eNodeB selects the Customized MME to make the UE connected to the Customized MME.

[0031]

<Mode 6>

A General SGSN (Serving GPRS (General Radio Packet Service) Support Node: which is described as "serving GPRS support node" in the claims), upon reception of an Attach Request from a UE, determines whether the UE is of a type that uses a specific service based on subscriber information and terminal information. If the UE is this type, in order to connect the UE to a Customized SGSN, the General SGSN transmits an SGSN re-selection request signal to an RNC (a Radio Network controller). By transmitting an Attach Request to the Customized SGSN, the RNC make the UE connected to the Customized

SGSN.

[0032]

<Mode 7>

5 A General SGSN, upon reception of an Attach Request from a UE, transmits an SGSN change request signal to the Customized SGSN, in order to connect the UE to a Customized SGSN. By continuing an Attach Procedure by the Customized SGSN, the UE is connected to the Customized SGSN.

[0033]

10 <Mode 8>

A General SGSN, upon reception of an Attach Request from a UE, transmits, to the UE, an Attach Reject, to which is added an identifier of the Customized SGSN, in order to connect the UE to a Customized SGSN. The UE, by re-transmitting an Attach Request, to which is added the
15 identifier of the Customized SGSN to an Attach Request, is connected to the Customized SGSN.

[0034]

<Mode 9>

A UE transmits, to an RNC, a connection request (an RRC Connection
20 Request), to which is added connection request information requesting connection to a Customized SGSN. The RNC, which has received the RRC connection request, when transmitting, to an SGSN, an Attach Request from the UE with RRC Connection established, selects the Customized SGSN to make the UE connected to the Customized SGSN.

25 [0035]

<Mode 10>

When a General SGSN with a session with a UE being established, performs Iu Release, the General SGSN instructs an RNC to select a Customized SGSN, in next selection of an SGSN. Then after, when the
30 UE transmits a location management area update request (an RA (Routing Area) Update Request), the RNC selects the Customized SGSN to make the UE connected to the Customized SGSN.

[0036]

As described in the above Modes 1 to 10, according to the present

invention, a core network node is selected and connected to a terminal, based on characteristics of a service used by the terminal. In this way, in the core network, nodes with specific service providing functions and nodes without such functions can be arranged in combination. Namely, the nodes can be distinguished, by optimizing specific nodes to have specific service providing functions and by configuring other nodes without such specific service providing functions. As a result, the equipment cost in the whole system can be reduced. The following describes exemplary embodiments and specific examples with reference to the drawings.

[0037]

<Exemplary embodiment 1>

Fig. 1 illustrates exemplary embodiment 1 of the present invention. As exemplary embodiment 1, a configuration with EPC (Evolved Packet Core) will be described. In this configuration, a UE transmits an Attach Request and the UE is connected to a Customized MME.

[0038]

In Fig. 1, a UE 1 (user equipment) is a terminal that receives a service from a Customized MME. For example, the UE 1 may be the above described MTC device, MBMS-compatible terminal or the like. In the case wherein the UE 1 is a normal mobile station that utilizes a normal service, such as a mobile phone terminal or a smartphone (a terminal that is not compatible with a specific service such as MTC or MBMS), the UE 1 is connected to a General MME. In addition, as will be described below, when the Customized MME is selected in response to an Attach Request from a normal mobile station (for example, from a terminal that is not compatible with a specific service such as MTC or MBMS), re-selection of an MME is performed and UE 1 is re-connected to the General MME.

[0039]

An eNodeB 11 is a base station apparatus in LTE (Long Term Evolution).

[0040]

An MME 21 and an MME 22 are mobility management devices

introduced in EPC. The Customized MME 22 is a Customized MME to which the UE 1 needs to be connected and the General MME (21) is an MME other than such Customized MME. Though not limited thereto, the Customized MME 22, for example, may be configured, as an MME customized for a machine communication (MTC) service and for terminals compatible therewith (M2M devices) (for example, the C-Plane handling network control is reinforced). Or, the Customized MME 22 may be configured as an MBMS-compatible MME.

[0041]

10 An HSS (Home Subscriber Server) 31 is a database storing subscriber information.

[0042]

An S-GW (Serving GateWay) 41 and a P-GW (Packet data network GateWay) 51 are apparatuses handling the user plane.

15 [0043]

A service network 61 is an external network.

[0044]

In Fig. 1, the eNodeB corresponds to an apparatus in a radio access network (RAN) and the MMEs, the S-GW, the P-GW, and so forth correspond to apparatuses in a core network (CN).

[0045]

Next, the above exemplary embodiment 1 will be described based on several examples. Different control schemes are described in the respective examples. Examples 1 to 5 correspond to the above Modes 1 to 5, respectively.

[0046]

<Example 1>

Fig. 3 is a sequence diagram illustrating an operation according to example 1.

30 In Fig. 3,

UE corresponds to the UE 1 in Fig. 1,

eNodeB corresponds to eNodeB 11 in Fig. 1,

General MME" corresponds to the General MME 21 in Fig. 1,

Customized MME corresponds to the Customized MME 22 in Fig. 1,

Serving GW corresponds to the S-GW 41 in Fig. 1,
 PDN GW corresponds to the P-GW 51 in Fig. 1, and
 HSS corresponds to the HSS 31 in Fig. 1.

[0047]

5 "PCRF" is a Policy and Charging Rules Function. In addition,
 an EIR (Equipment Identity Register) stores IMEI (International Mobile
 Equipment Identity) and the like and is connected to an MME via an S13
 interface.

[0048]

10 In Fig. 3, for example, "1. Attach Request" represents that
 transmission of an Attach Request from the UE to the eNodeB is
 sequence 1. To distinguish the reference character of this sequence
 from reference character 1 of the UE in Fig. 1 (from the reference
 characters of the components), this sequence number 1 will be
 15 represented in parentheses as "Attach Request (1)" in the following
 description. The other sequence numbers are also represented in the
 same way. In addition, the sequence numbers in Fig. 4 and in the
 subsequent sequence diagrams will also be represented in the same way.
 Fig. 3 is based on Figure 5.3.2.1-1: Attach Procedure in 3GPP TS23.401
 20 and the sequence numbers are in accordance with this figure. Details
 of each sequence are described in 3GPP TS23.401 5.3.2. Hereinafter,
 the operation sequence will be described with reference to Figs. 1 and 3.

[0049]

As illustrated in Fig. 3, when the UE 1 transmits an Attach
 25 Request (1), first, the eNodeB 11 receives the Attach Request (1).
 Next, the eNodeB 11 relays the Attach Request (2) to an MME.

[0050]

At this sequence, the eNodeB 11 cannot uniquely determine
 whether to forward the Attach Request (2) to the General MME 21 or to
 30 the Customized MME 22. Thus, there are cases where the eNodeB 11
 forwards the Attach Request (2) to the General MME 21.

[0051]

After receiving the Attach Request (2), the General MME 21
 acquires terminal information (ME Identity) from the UE 1 via an

Identity Request/Response (4, 5b).

[0052]

It is noted that the General MME 21 transmits an ME Identity Check Request (5b) to an EIR, and the EIR returns an ME Identity Check Ack (not illustrated) to the General MME. In addition, in coordination with the HSS 31, the General MME 21 performs authentication and acquires a subscriber profile. Namely, in this case, at least, the General MME 21 performs authentication and acquires a subscriber profile.

[0053]

The General MME 21, on acquisition of the terminal information and the subscriber profile, determines whether to connect the UE 1 to the General MME 21 or to the Customized MME 22.

[0054]

When the General MME 21 determines that the UE 1 needs to be connected to the General MME 21, the General MME 21 continues a normal Attach Procedure.

[0055]

When the General MME 21 determines that the UE 1 needs to be connected to the Customized MME 22, the General MME 21 transmits, to the eNodeB 11, an MME selection signal (an MME re-selection command) (SIAP (S1 application) signal newly introduced in the present exemplary embodiment), in order to instruct re-selection of an MME.

[0056]

In this sequence, the General MME 21 sets an identifier of the Customized MME 22 (for example, a GUMMEI (Globally Unique MME Identity)) in the MME re-selection Command signal. Namely, before creation of a bearer in the core network, the General MME 21 transmits, to the eNodeB, a re-selection request, in which the necessary information (GUMMEI) for selecting a new MME is included. The MMEs is equipped with a function of determining whether the UE is a re-selection target.

[0057]

When the eNodeB 11 receives the MME re-selection Command signal, in accordance with the identifier set in this signal, the eNodeB 11 selects the Customized MME 22 and forwards the Attach Request (2) to the Customized MME 22. Since the Customized MME 22 needs an NAS (Non-Access Stratum) parameter of the Attach Request (used in authentication between the UE and the MME), the eNodeB 11 re-transmits the Attach Request. The eNodeB 11 needs to be equipped with a function of storing such NAS message.

[0058]

Since the new MME (= the Customized MME 22) cannot determine the old MME (= the General MME), the new MME cannot take over Context from the old MME (= the General MME). Thus, the new MME (= the Customized MME: MME 22) also needs to perform authentication and acquire the subscriber profile.

[0059]

After receiving the Attach Request signal, the Customized MME 22 acquires the terminal information via an Identity Request/Response. In addition, the Customized MME 22 performs authentication and acquires a subscriber profile in coordination with the HSS 31. Namely, the Customized MME 22 performs the same processing as that performed by the General MME 21.

[0060]

After acquiring the terminal information and the subscriber profile, the Customized MME 22 determines whether to connect the UE 1 to the General MME 21 or to the Customized MME 22.

[0061]

In this case, since the Customized MME 22 has been selected after re-selection by the eNodeB 11, the Customized MME 22 continues a normal Attach Procedure without transmitting an MME re-selection Command signal. Namely, the following sequences are performed:

- transmission of an Update Location Request (8) from the Customized MME 22 to the HSS 31,
- transmission of an Update Location Ack (11) from the HSS 31 to the Customized MME 22,

- transmission of a Create Session Request (12) from the Customized MME 22 to the S-GW 41,
- transmission of a Create Session Request (13) from the S-GW 41 to the P-GW 51,
- PCEF Initiated IP-CAN Session Establishment/Modification (14) by the P-GW 51,
- transmission of a Create Session Response (15) from the P-GW 51 to the S-GW 41,
- transmission of First Down Link Data from the P-GW 51 to the S-GW 41 (if not handover (HO)),
- transmission of a Create Session Response (16) from the S-GW 41 to the customized MME22 ,
- transmission of an Initial Context Setup Request/Attach Accept) (17) from the customized MME 22 to the eNodeB 11,
- transmission of an RRC Connection Reconfiguration (18) from the eNodeB 11 to the UE 1,
- transmission of an RRC Connection Reconfiguration Complete (19) from the UE 1 to the eNodeB 11,
- transmission of an Initial Context Setup Response (20) from the eNodeB 11 to the Customized MME 22,
- Direct Transfer (21) from the UE 1 to the eNodeB,
- transmission of an Attach Complete (22) from the eNodeB 11 to the Customized MME 22,
- transmission of First Uplink Data from the UE 1 to the S-GW 41 and the P-GW 51,
- transmission of a Modify Bearer Request (23) from the Customized MME 22 to the S-GW 41,
- transmission of a Modify Bearer Request (23a) from the S-GW 41 to the PDN,
- transmission of a Modify Bearer Response (23b) from the PDN to the S-GW 41,
- transmission of a Modify Bearer Response (24) from the S-GW 41 to the Customized MME 22, and
- transmission of First Downlink data from the P-GW 51 and the S-GW

41 to the UE 1.

[0062]

In addition, the General MME 21 and the Customized MME 22 are equipped with a function of determining which MME needs to be connected to the UE 1. This determination is made based on information transmitted from the UE 1. The information may be:

- IMSI (International Mobile Subscriber Identity),
- IMEI (International Mobile Equipment Identity: (terminal Identity)),
- UE network capability,
- MS network capability,
- Mobile station classmark 2,
- Mobile station classmark 3,
- Device properties,
- a new parameter of an Attach Request signal which will be added in the future, or
- an identifier of a part of these parameters (for example, a PLMN (Public land Mobile Network)-id included in the IMSI).

Alternatively, the above determination may be made based on information transmitted from the HSS 31. The information may be:

- Feature-List,
- APN (Access Point Name),
- a new parameter of an Update Location Answer/Insert Subscriber Data Request signal which will be added in the future, or
- an identifier of a part of these parameters.

Any one of or a combination of these items of information may be used for the above determination.

[0063]

In addition, in the present example, even when an Attach Request signal is forwarded from the UE 1 that needs to be connected to the General MME 21 to the Customized MME 22, the Customized MME 22 can request the eNodeB 11 to select the General MME 21 in a like manner. For example, if the UE 1 is a normal mobile station (for example, a normal mobile station that is not compatible with a special service such as MTC or MBMS) and if the UE 1 is first connected to the

Customized MME 22, the General MME 21 is selected and a service is provided from the General MME 21.

[0064]

As described above, in the present exemplary embodiment, an MME instructs the eNodeB to perform re-selection of an MME. In response to the instruction, the eNodeB performs re-selection of an MME and the Attach Procedure is continued. In this way, the UE can be attached to an appropriate MME.

[0065]

10 <Example 2>

As example 2, another example with EPC (Evolved Packet Core) will be described. In this example, the UE transmits an Attach Request and the UE is connected to the Customized MME. In example 2, the same system configuration as that in example 1 will be used.

15 [0066]

Fig. 4 is a sequence diagram illustrating an operation according to example 2. Fig. 4 is based on Figure 5.3.2.1-1: Attach Procedure in 3GPP TS23.401 and the sequence numbers are in accordance with this figure. Details of each sequence are described in 3GPP TS23.401 5.3.2. Hereinafter, the operation will be described with reference to Figs. 1 and 4.

[0067]

When the UE 1 transmits an Attach Request (1), the eNodeB 11 receives the Attach Request (1). Next, the eNodeB 11 relays the Attach Request (2) to an MME. At this sequence, the eNodeB 11 cannot uniquely determine whether to forward the Attach Request (2) to the General MME 21 or to the Customized MME 22. Thus, there are cases where the eNodeB 11 forwards the Attach Request (2) to the General MME 21.

30 [0068]

After receiving the Attach Request (2), the General MME 21 acquires terminal information (ME Identity) via an Identity Request/Response (5b). In addition, in coordination with the HSS 31, the General MME 21 performs authentication and acquires a subscriber

profile. Namely, in this case, at least, the General MME 21 performs authentication and acquires a subscriber profile.

[0069]

After acquiring the terminal information and the subscriber
5 profile, the General MME 21 determines whether to connect the UE 1 to the General MME 21 or to the Customized MME 22. If the General MME 21 determines that the UE 1 needs to be connected to the General MME 21, the General MME 21 continues a normal Attach procedure.

[0070]

10 If the General MME 21 determines that the UE 1 needs to be connected to the Customized MME 22, to instruct change of an MME, the General MME 21 transmits an MME change request signal (MME Change Request) (a GTP (GPRS Tunneling Protocol) signal newly introduced in the present example) to the Customized MME 22.

15 [0071]

In this sequence, the General MME 21 sets context information generated by authentication of the terminal and acquisition of the subscriber profile in the MME change request signal (MME Change Request).

20 [0072]

The Customized MME 22, upon reception of the MME change request signal (MME Change Request), holds the context information set in the MME change request signal and transmits an MME Change Response signal (a GTP signal newly introduced in the present example)
25 to the General MME 21.

[0073]

Subsequently, the Customized MME 22 transmits an Update Location Request (8) to the HSS 31 to notify the HSS 31 of change of the MME.

30 [0074]

In order to notify the HSS 31 of the changed MME, the Customized MME 22 transmits an Update Location Request. The subsequent Attach Procedure is performed by the Customized MME 22.

[0075]

The Customized MME 22, in the case wherein security context information received from the General MME 21 is valid, can omit performing re-authentication.

[0076]

Subsequently, the Customized MME 22 continues the Attach Procedure and the eNodeB 11 receives an Initial Context Setup Request/Attach Accept) (17) from the Customized MME 22.

[0077]

The Initial Context Setup Request/Attach Accept (17) is a response to the Attach Request (2) received by the General MME 21. The eNodeB 11 needs to include a function of receiving a Response from another MME different from the General MME 21.

[0078]

Subsequently, the Customized MME 22 continues a normal Attach Procedure.

[0079]

The General MME 21 and the Customized MME 22 are equipped with a function of determining which MME needs to be connected to the UE 1, as is the case with example 1.

[0080]

In addition, in the present example, even when an Attach Request signal is forwarded from the UE 1 that needs to be connected to the General MME 21 to the Customized MME 22, the Customized MME 22 can request the General MME 21 for change of an MME in a like manner. For example, in the case wherein the UE 1 is a normal mobile station (for example, a normal mobile station that is not compatible with a special service such as MTC or MBMS), when the UE 1 is once connected to the Customized MME 22, the Customized MME 22 transmits an MME change request signal (MME Change Request) to the General MME 21. In this way, the General MME 21 is selected and a service is provided from the General MME 21.

[0081]

As described above, in the present example, the General MME instructs the Customized MME about change of an MME. In response

to the instruction, the Customized MME accepts the change and continues the Attach Procedure. In this way, the UE can be attached to an appropriate MME.

[0082]

5 <Example 3>

As example 3, another example with EPC will be described. In this example, the UE transmits an Attach Request and the UE is connected to the Customized MME. In example 3, the same system configuration as that in example 1 will be used.

10 [0083]

Figs. 5 and 6 are sequence diagrams illustrating an operation according to example 3. Figs. 5 and 6 are based on Figure 5.3.2.1-1: Attach Procedure in 3GPP TS23.401 and the sequence numbers are in accordance with these figures. Details of each sequence are described
15 in 3GPP TS23.401 5.3.2. Hereinafter, the operation will be described with reference to Figs. 1, 5, and 6.

[0084]

When the UE 1 transmits an Attach Request (1), first, the eNodeB 11 receives the Attach Request (1). Next, the eNodeB 11 forwards the
20 Attach Request (2) to an MME. However, the eNodeB 11 cannot uniquely determine whether to forward the Attach Request (2) to the General MME 21 or to the Customized MME 22. Thus, there are cases where the eNodeB 11 forwards the Attach Request (2) to the General MME 21.

25 [0085]

After receiving the Attach Request (2), the General MME 21 acquires terminal information (ME Identity) via an Identity Request/Response (5b). In addition, in coordination with the HSS 31, the General MME 21 performs authentication and acquires a subscriber
30 profile.

[0086]

The General MME 21, on acquisition of the terminal information and the subscriber profile, determines whether to connect the UE 1 to the General MME 21 or to the Customized MME 22. If the UE 1 is to

be connected to the General MME 21, the General MME 21 continues a normal Attach Procedure.

[0087]

If the UE 1 needs to be connected to the Customized MME 22, the General MME 21 transmits an Attach Reject message to the UE 1, instead of continuing the Attach Procedure. Namely, the General MME 21 transmits an Initial Context Setup Request/Attach Reject (17) to the eNodeB 11.

[0088]

In this sequence, the General MME 21 sets a parameter for instructing re-Attach (a new parameter introduced in the present example) and a GUTI (Globally Unique Temporary Identity (Identifier)) parameter including a GUMMEI (Globally Unique MME identifier) (a new parameter introduced in the present example) in the Attach Reject signal, so that the eNodeB 11 can select the Customized MME 22 when performing re-Attach. The GUTI parameter is formed by a GUMMEI and an M-TMSI (Temporary Mobile Station Identity). An MMEI is formed by an MCC (Mobile Country Code), an MNC (Mobile Network Code), and an MME Identifier. While these parameters are parameters that are newly introduced in the present example, since the eNodeB 11 is transparent, the eNodeB 11 is not affected.

[0089]

The UE 1, upon reception of the Attach Reject signal from the eNodeB 11, as illustrated in Fig. 6, transmits, to the eNodeB 11, the Attach Request (1) in which the GUTI is set (Attach by the GUTI), in accordance with the parameter for instructing re-Attach set in the Attach-Reject signal and the GUTI parameter. The eNodeB 11 decides an appropriate MME from the GUMMEI included in the GUTI and forwards the Attach Request (2) to the Customized MME 22.

[0090]

The UE 1 is equipped with a function of receiving a GUTI in an Attach Reject signal and using the GUTI specified in the Attach Reject when transmitting a re-Attach (Attach Request (1) in Fig. 6). The MMEs are equipped with a function of determining whether this UE is a

re-selection target.

[0091]

Subsequently, the Customized MME 22 continues a normal Attach Procedure. While the GUTI is set in the Attach Request, the
5 Customized MME 22 does not hold context information.

[0092]

Thus, upon reception of the Attach Request signal, the Customized MME 22 acquires terminal information via an Identity Request/Response (4). In addition, the Customized MME 22 performs
10 authentication and acquires a subscriber profile in coordination with the HSS 31.

[0093]

In addition, the General MME 21 and the Customized MME 22 are equipped with a function of determining which MME needs to be
15 connected to the UE 1, as is the case with example 1.

[0094]

In addition, in the present example, even when an Attach Request signal is forwarded from the UE 1 that needs to be connected to the General MME 21 to the Customized MME 22, the Customized MME 22
20 can urge the UE 1 to re-select an MME in the same manner. Namely, in the case wherein the UE 1 is a normal mobile station (for example, a normal mobile station that is not compatible with a special service such as MTC or MBMS), when the UE 1 is once connected to the Customized MME 22, the Customized MME 22 transmits an Attach Reject signal to
25 the UE 1 and urges the UE 1 to re-select the General MME 21. In this way, since the UE 1 transmits a re-Attach Request signal, the General MME 21 is selected and a service is provided from the General MME 21.

[0095]

As described above, in the present example, the General MME
30 instructs the UE to perform re-selection of an MME. In response to the instruction, the UE specifies the Customized MME and an Attach Procedure is continued. In this way, the UE can be attached to an appropriate MME.

[0096]

<Example 4>

As example 4, another example with EPC will be described. In this example, the UE transmits an Attach Request and the UE is connected to the Customized MME. In example 4, the same system configuration as that in example 1 will be used. Fig. 7 is a sequence diagram illustrating an operation according to example 4. Fig. 7 is based on Figure 5.3.2.1-1: Attach Procedure in 3GPP TS23.401 and the sequence numbers are in accordance with the figure. Details of each sequence are described in 3GPP TS23.401 5.3.2. Hereinafter, the operation will be described with reference to Figs. 1 and 7.

[0097]

In order to transmit an Attach Request (1) to an MME, the UE 1 first, establishes RRC Connection with the eNodeB 11. In order to establish RRC Connection, first, the UE 1 transmits an RRC Connection Request signal to the eNodeB 11.

[0098]

In this sequence, the UE 1 sets a parameter indicating that the UE 1 needs to be connected to the Customized MME 22 (a User Identity, a new Value or a new parameter of establishment Cause (a value or a parameter newly introduced in the present example), or an identifier of a part of such parameters (a PLMN-id included in the IMSI, for example)).

[0099]

A new parameter of the RRC Connection Request (a new value or a new parameter of establishment Cause) is implemented, so that the UE 1 can notify the eNodeB that the UE 1 can be connected to the Customized MME by using the RRC Connection Request.

[0100]

The eNodeB 11, upon reception of the RRC Connection Request signal, stores information indicating that the UE 1 needs to be connected to the Customized MME 22 and continues the subsequent RRC Connection Procedure.

[0101]

After establishing RRC Connection, when the UE 1 transmits an

Attach Request (1), the eNodeB 11 receives the Attach Request (1). In this sequence, the eNodeB 11, from the information stored upon reception of the RRC Connection Request (1), forwards an Attach Request (2) to the Customized MME 22.

[0102]

After receiving the Attach Request (2), the Customized MME 22 continues a normal Attach Procedure.

[0103]

In addition, the UE 1 is equipped with a function of instructing the eNodeB 11 about which one of the General MME 21 and the Customized MME 22 needs to be connected to the UE 1. Since the UE 1 cannot store information about all the MMEs in the core network, information indicating an MME type, a service type, or the like is used for the instruction given to the eNodeB 11, instead of an identifier by which a unique MME can be selected.

[0104]

In addition, the eNodeB 11 is equipped with a function of determining which MME needs to be connected to the UE 1.

[0105]

As described above, one of or a combination of a User Identity, a new Value or a new parameter of Establishment Cause, and an identifier of a part of such parameters in the RRC Connection Request message is used for selection of an MME by the eNodeB 11.

[0106]

As described above, in the present example, the UE instructs the eNodeB to select an MME. In response to the instruction, the eNodeB specifies the Customized MME and an Attach Procedure is continued. In this way, the UE can be attached to an appropriate MME.

[0107]

<Example 5>

As example 5, another example with EPC will be described. In this example, the UE and the Customized MME are connected when Tracking Area Update is performed. In example 5, the same system configuration as that in example 1 will be used.

[0108]

Figs. 8 and 9 are sequence diagrams illustrating an operation according to example 5. Fig. 8 is based on Figure 5.3.5-1: S1 Release Procedure in 3GPP TS23.401 (see 3GPP TS23.401 5.3.5). Fig. 9 is based on Figure 5.3.3.1-1: Tracking Area Update procedure with Serving GW change (see 3GPP TS23.401 5.3.3). The operation will be described with reference to Figs. 1, 8, and 9 (and a part in Fig. 3).

[0109]

When the UE 1 transmits an Attach Request (see 1 in Fig. 3), first, the eNodeB 11 receives the Attach Request. The eNodeB 11 relays the Attach Request to an MME (see 2 in Fig. 3).

[0110]

The eNodeB 11 cannot uniquely determine whether to forward the Attach Request to the General MME 21 or to the Customized MME 22. Thus, there are cases where the eNodeB 11 forwards the Attach Request to the General MME 21.

[0111]

After receiving the Attach Request, the General MME 21 acquires terminal information (ME Identity) via an Identity Request/Response (see 4, 5b in Fig. 3). In addition, the General MME 21 performs authentication and acquires a subscriber profile in coordination with the HSS 31.

[0112]

The General MME 21, on acquisition of the terminal information and the subscriber profile, determines whether to connect the UE 1 to the General MME 21 or to the Customized MME 22. Subsequently, a normal Attach Procedure is continued. If the UE 1 is to be connected to the General MME 21, processing completes at this point.

[0113]

If the UE 1 needs to be connected to the Customized MME 22, the General MME 21 performs S1 Release to cause the UE 1 to perform Tracking Area Update (TA Update), as illustrated in Fig. 8. The General MME 21 transmits an S1 UE Context Release Command (4) to the eNodeB 11.

[0114]

The General MME 21 gives an instruction about an MME that the eNodeB needs to select when establishing S1 Connection with an MME next time, by using an MME identifier (for example, a GUMMEI) in the S1 UE Context Release Command (4). A parameter, for example, the
 5 S1 UE Context Release Command (4). A parameter, for example, the GUMMEI specifying the next MME to be selected by the eNodeB when S1 Release for activation of Load Balancing TAU is performed, is a new parameter. Even after S1 Release is completed, while the eNodeB 11 is holding session information for the UE 1, the eNodeB 11 continues to
 10 hold the MME identifier as information for selection of the next MME.

[0115]

After S1 Release being performed, next, the UE 1 transmits a TAU Request (2), as illustrated in Fig. 9. First, the eNodeB 11 receives the TAU Request (2) from the UE 1 and forwards the TAU
 15 Request (3) to an MME. The eNodeB 11, as in a state of S1 Release being completed, performs re-selection of an MME and establishes S1 Connection. The eNodeB 11 selects the Customized MME, in accordance with the GUMMEI indicated by the old MME (= the General MME) at the time of S1 Release. The eNodeB 11 is equipped with a
 20 function of holding the next GUMMEI per UE.

[0116]

When selecting an MME, the eNodeB 11 selects the Customized MME 22 in accordance with the MME Identifier of the GUMMEI indicated in the S1 UE Context Release Command signal received from
 25 the General MME 21. Since the GUTI (GUMMEI) on NAS indicates the old MME (= General MME), m contexts can be acquired.

[0117]

After receiving the TAU Request (3), the Customized MME 22 continues a normal TA Update Procedure. The Customized MME 22
 30 transmits a Context Request (4) to the General MME 21 and receives a Context Response (5).

[0118]

The Customized MME 22, in the case wherein the S-GW is relocated, transmits a Context Acknowledge (7) including an instruction

for changing the S-GW to the General MME. When the Customized
 5 MME 22 selects a new S-GW 41 (new Serving GW), the Customized
 MME 22 transmits a Create Session Request (8) to the new S-GW 41.

[0119]

The new S-GW 41 (new Serving GW), responsive to this Create
 Session Request (8), transmits a Modify Bearer Request (9) to the P-GW
 10 51. After receiving a response to the Modify Bearer Request (9) from
 the P-GW 51, the new S-GW returns a Create Session Response (11) to
 the Customized MME 22.

[0120]

The Customized MME 22 transmits an Update Location (12) to the
 15 HSS 31.

[0121]

The General MME 21, upon reception of a Cancel Location (13)
 from the HSS 31, deletes MM contexts and transmits a Cancel Location
 Ack (14) to the HSS 31. The HSS 31 transmits an Update Location Ack
 20 (17) in response to the Update Location (12) to the Customized MME
 22.

[0122]

The General MME 21 transmits a Delete Session Request (18) to
 the old S-GW 41 (old Serving GW), and the old S-GW 41 (old Serving
 25 GW) transmits a response (19) to the Delete Session Request (18) to the
 General MME 21.

[0123]

The Customized MME 22 transmits a TAU Accept (20) to the UE0
 1.

30 [0124]

If a GUTI is included in the TAU Accept (20), the UE 1 returns a
 TAU Complete (21) to the Customized MME 22. The UE 1 uses this
 TAU Complete (21) as an acknowledge response to the received signal
 TAU Accept (20).

35 [0125]

The General MME 21 and the Customized MME 22 are equipped
 with a function of determining which MME needs to be connected to the

UE 1. This function is the same as that in example 1.

[0126]

In the present example, in the same manner as described above, when the eNodeB 11 receives a TA Update Request from the UE 1 that needs to be connected to the General MME 21 (for example, from a normal mobile station (a normal mobile station that is not compatible with a special service such as MTC or MBMS), by selecting the General MME, the UE 1 is connected to the General MME 21 and a service is provided from the General MME 21.

[0127]

In the present example, the TA Update Procedure has been performed based on the sequence in Fig. 9. However, a feature in the present example is that the eNodeB 11 selects an MME. Thus, the present example can also be realized by, for example, other Procedures for re-establishing S1 Connection, such as a Service Request.

[0128]

As described above, according to the present example, the General MME instructs the eNodeB to perform re-selection of an MME. In response to the instruction, the eNodeB specifies the Customized MME when selecting the next MME, and the Procedure is continued. In this way, the UE can be connected to an appropriate MME.

[0129]

<Exemplary embodiment 2>

As exemplary embodiment 2, a configuration with UMTS (Universal Mobile Telecommunications System) will be described. In this configuration, a UE transmits an Attach Request and the UE is connected to a Customized SGSN. Fig. 2 illustrates a system configuration according to exemplary embodiment 2.

[0130]

A UE 101 is a terminal that receives a service from a Customized SGSN. For example, the UE 101 may be the above MTC device or MBMS-compatible terminal. In the case wherein the UE 101 is a normal mobile station that utilizes normal services such as a mobile phone terminal or a smartphone (a terminal that is not compatible with a

specific service such as MTC or MBMS), the UE 101 is connected to a General SGSN. In addition, as will be described below, when the Customized SGSN is selected in response to an Attach Request from a normal mobile station (for example, from a terminal that is not compatible with a specific service such as MTC or MBMS), re-selection of an SGSN is performed. As a result, the UE 1 is connected to the General SGSN.

[0131]

A NodeB 111 and an RNC (a radio network controller) 171 are devices for Radio access adopted for the UMTS system.

[0132]

A General SGSN 121 and a Customized SGSN 122 are devices, each of which covers an area and is used in the UMTS. Depending on the connection mode, the General SGSN 121 and the Customized SGSN 122 handle the user plane. If the SGSNs do not handle the user plane, the user plane is set between an S-GW and an RNC.

[0133]

An HLR (Home Location Register) 131 is a database storing subscriber information.

[0134]

A GGSN 141 (Gateway GPRS (General Radio Packet Service) Support Node: which is described as "gateway GPRS support node" in the claims) is a gateway device connected to an external network. A service network 161 is an external network (data packet network).

[0135]

In Fig. 2, the NodeB 111 and the RNC 171 are devices in a radio access network RAN. The SGSN, the GGSN, and so forth are devices in a core network.

[0136]

Next, exemplary embodiment 2 will be described based on several examples. Different control methods are described in the respective examples. The following examples 6 to 10 correspond to the above Modes 6 to 10, respectively.

[0137]

<Example 6>

Fig. 10 is a sequence diagram illustrating an operation according to
 5 example 6 and is based on 3GPP TS 23.060 6.5 Fig. 22.

[0138]

In Fig. 10,

"MS (Mobile Station)" corresponds to the UE 101 in Fig. 2,

"RAN (Radio Access Network)" corresponds to the NodeB 111 and the
 10 RNC 171 in Fig. 2,

"General SGSN" corresponds to the General SGSN 121 in Fig. 2,

"Customized SGSN" corresponds to Customized SGSN 122 in Fig. 2,

"GGSN" corresponds to the GGSN 141 in Fig. 2, and

"HLR" corresponds to the HLR 131 in Fig. 2.

15 [0139]

A VLR of an MSC (Mobile Switching Center)/VLR (Visitor
 Location Register) is a location register for CS services other than the
 HLR. An EIR (Equipment Identifier Register) stores identifiers of
 valid mobile devices.

20 [0140]

An operation will be described with reference to Figs. 2 and 10.
 Hereinafter, the UE 101 in Fig. 2 will be used as the MS in Fig. 10.

[0141]

When the UE 101 (MS) transmits an Attach Request (1), first, the
 25 NodeB 111 receives the Attach Request (1) and forwards the Attach
 Request (1) to the RNC 171. The RNC 171 forwards the Attach
 Request (1) to an SGSN. However, the RNC 171 cannot uniquely
 determine whether to forward the Attach Request to the General SGSN
 121 or to the Customized SGSN 122. Thus, there are cases where the
 30 RNC 171 forwards the Attach Request to the General SGSN 121.

[0142]

After receiving the Attach Request, the General SGSN 121
 acquires terminal information via an Identity Request/Response (3, 4).
 In addition, the General SGSN 121 performs authentication and acquires
 35 a subscriber profile, in coordination with the HLR 131. Namely, in
 this case, the General SGSN 121 performs authentication and acquires a

subscriber profile.

[0143]

The General SGSN 121, on acquisition of the terminal information and the subscriber profile, determines whether to connect the UE 101 to the General SGSN 121 or to the Customized SGSN 122. In the case wherein the UE 101 needs to be connected to the General SGSN 121, the General SGSN 121 continues a normal Attach Procedure.

[0144]

In the case wherein the UE 101 needs to be connected to the Customized SGSN 122, to instruct re-selection of an SGSN, the General SGSN 121 transmits an SGSN re-selection Command (an RANAP signal newly introduced in the present example) to the RNC 171. In this sequence, the General SGSN 121 sets an identifier identifying the Customized SGSN 122 in the SGSN re-selection Command signal (for example, an RAI (Routing Area Identifier) or an NRI (Network Resource Identifier)). Namely, the General SGSN 121 transmits, to the RNC 171, an SGSN re-selection request in which necessary information (RAI) for selecting the customized SGSN 122 is included. In the case of re-selection being performed within a single pool, only the NRI may be used. The SGSNs are equipped with a function of determining whether the UE 101 is a re-selection target.

[0145]

When the RNC 171 receives the SGSN re-selection Command signal, in accordance with the identifier set in this signal, the RNC 171 selects the Customized SGSN 122 and forwards the Attach Request (1). Since the customized SGSN 122 needs an NAS (Non Access Stratum) parameter of the Attach Request, the RNC 171 transmits the Attach Request. The RNC 171 is equipped with a function of storing such NAS message.

[0146]

Since the new SGSN (= the Customized SGSN) cannot determine the old SGSN (= the General SGSN), the new SGSN cannot take over context. Thus, the new SGSN also needs to perform authentication and acquire the subscriber profile. After receiving the Attach Request (2),

the Customized SGSN 122 acquires terminal information via an Identity Request/Response. In addition, the Customized SGSN 122 performs authentication and acquires a subscriber profile, in coordination with the HLR 131. Namely, the Customized SGSN 122 performs the same processing as that performed by the General SGSN 121.

[0147]

The Customized SGSN 122, on acquisition of the terminal information and the subscriber profile, determines whether to connect the UE 101 to the General SGSN 121 or to the Customized SGSN (022).

In this case, since the Customized SGSN 122 has been selected after re-selection by the RNC 171, the Customized SGSN 122 continues a normal Attach Procedure, without transmitting an SGSN re-selection Command signal.

[0148]

In addition, the General SGSN 121 and the Customized SGSN 122 are equipped with a function of determining which SGSN needs to be connected to the UE 101. This determination is made based on information transmitted from the UE 101. The information may be:

- IMSI (International Mobile Subscriber Identity),
- IMEI,
- UE network capability,
- MS network capability,
- Mobile station classmark 2,
- Mobile station classmark 3,
- Device properties,
- a new parameter of an Attach Request signal which will be added in the future, or
- an identifier of a part of these parameters (for example, a PLMN-id included in the IMSI).

Alternatively, the above determination may be made based on information transmitted from the HLR 131. The information may be:

- Feature-List,
- APN,
- a new parameter of an Update Location Answer/Insert Subscriber Data

Request signal which will be added in the future, or
 - an identifier of a part of these parameters.

Any one of or a combination of these items of information may be used for the above determination.

5 [0149]

In addition, in the present example, even when an Attach Request signal is forwarded from the UE 101 that needs to be connected to the General SGSN 121 to the Customized SGSN 122, the Customized SGSN 122 can request the RNC 171 to perform re-selection of an SGSN in a like manner. If the UE 101 is a normal mobile station (for example, a normal mobile station that is not compatible with a special service such as MTC or MBMS) and if the UE 101 is first connected to the Customized SGSN 122, the General SGSN 121 requests the RNC 171 to perform re-selection of an SGSN. As a result, the General SGSN 121 is selected and a service is provided from the General SGSN 121.

[0150]

As described above, in the present example, an SGSN instructs the RNC to perform re-selection of an SGSN. In response to the instruction, the RNC performs re-selection of an SGSN and the Attach Procedure is continued. In this way, the UE can be attached to an appropriate SGSN.

[0151]

<Example 7>

As example 7, another example with UMTS will be described. In this example, the UE transmits an Attach Request and the UE is connected to the Customized SGSN. In example 7, the same system configuration as that in example 6 will be used. Fig. 11 is a sequence diagram illustrating an operation according to example 7. Hereinafter, the operation will be described with reference to Figs. 2 and 11.

30 [0152]

When the UE 101 transmits an Attach Request (1), first, the NodeB 111 receives the Attach Request (1). Next, the NodeB 111 forwards the Attach Request to the RNC 171, and the RNC 171 forwards the Attach Request to an SGSN. However, the RNC 171 cannot

uniquely determine whether to forward the Attach Request to the General SGSN 121 or to the Customized SGSN 122. Thus, there are cases where the RNC 171 forwards the Attach Request to the General SGSN 121.

5 [0153]

The General SGSN 121, upon reception of the Attach Request, acquires terminal information via an Identity Request/Response. In addition, in coordination with the HLR 131, the General SGSN 121 performs authentication and acquires a subscriber profile. Namely, in
10 this case, at least, the General SGSN 121 performs authentication and acquires a subscriber profile.

[0154]

The General SGSN 121, upon acquisition of the terminal information and the subscriber profile, determines whether to connect
15 the UE 101 to the General SGSN 121 or to the Customized SGSN 122. If the General SGSN 121 determines that the UE 101 needs to be connected to the General SGSN 121, the General SGSN 121 continues a normal Attach procedure.

[0155]

20 In the case wherein the UE 101 needs to be connected to the Customized SGSN 122, in order to instruct change of an SGSN, the General SGSN 121 transmits an SGSN Change Request (a GTP signal newly introduced in the present exemplary embodiment) to the Customized SGSN 122.

25 [0156]

In this sequence, the General SGSN 121 sets context information generated by authentication of the mobile station and acquisition of the subscriber profile in the SGSN Change Request signal. Namely, when the General SGSN 121 requests the Customized SGSN 122 for change of
30 an SGSN (SGSN Change), the General SGSN 121 notifies a new SGSN (the Customized SGSN 122) of context. The SGSNs are equipped with a function of determining whether the UE 101 is a re-selection target.

[0157]

The Customized SGSN 122, upon reception of the SGSN Change

Request signal, holds the context information set in the SGSN Change Request signal and transmits an SGSN Change Response signal (a GTP signal newly introduced in the present exemplary embodiment) to the General SGSN 121.

5 [0158]

Subsequently, the Customized SGSN 122 transmits an Update Location signal (8) to the HLR 131 to notify the HLR 131 of change of the SGSN.

[0159]

10 When security context information transmitted from the General SGSN 121 is valid, the Customized SGSN 122 can omit performing re-authentication.

[0160]

Subsequently, the Customized SGSN 122 continues the Attach Procedure and the RNC 171 receives an Attach Accept signal (9) from the Customized SGSN 122. Subsequently, a normal Attach Procedure is continued.

[0161]

20 The General SGSN 121 and the Customized SGSN 122 are equipped with a function of determining which SGSN needs to be connected to the UE 101, as is the case with example 6.

[0162]

In the present example, even when an Attach Request signal is forwarded from the UE 101 that needs to be connected to the General SGSN 121 to the Customized SGSN 122, the Customized SGSN 122 can request the General SGSN 121 for change of an SGSN in the same manner. In the case wherein the UE 101 is a normal mobile station (for example, a terminal that is not compatible with a special service such as MTC or MBMS) and if the UE 101 is connected to the Customized SGSN 122, the Customized SGSN 122 selects the General SGSN 121 and a service is provided from the General SGSN 121.

30 [0163]

As described above, in the present example, the General SGSN instructs the Customized SGSN about change of an SGSN. In response

to the instruction, the Customized SGSN accepts the change and continues the Attach Procedure. In this way, the UE can be attached to an appropriate SGSN.

[0164]

5 <Example 8>

As example 8, another example with UMTS will be described. In this example, the UE transmits an Attach Request and the UE is connected to the Customized SGSN. In example 8, the same configuration as that in example 6 will be used. Figs. 12 and 13 are sequence diagrams illustrating an operation according to example 8. Hereinafter, the operation will be described with reference to Figs. 2, 12, and 13.

[0165]

When the UE 101(MS) transmits an Attach Request (1), first, the NodeB 111 receives the Attach Request (1). Next, the NodeB 111 forwards the Attach Request to the RNC 171, and the RNC 171 forwards the Attach Request to an SGSN. However, the RNC 171 cannot uniquely determine whether to forward the Attach Request to the General SGSN 121 or to the Customized SGSN 122. Thus, there are cases where the RNC 171 forwards the Attach Request to the General SGSN 121.

[0166]

After receiving the Attach Request (1), the General SGSN 121 acquires terminal information via an Identity Request/Response (3). In addition, in coordination with the HLR 131, the General SGSN 121 performs authentication and acquires a subscriber profile.

[0167]

The General SGSN 121, on acquisition of the terminal information and the subscriber profile, determines whether to connect the UE 101 to the General SGSN 121 or to the Customized SGSN 122. In the case wherein the UE 101 needs to be connected to the General SGSN 121, the General SGSN 121 continues a normal Attach Procedure.

[0168]

In the case wherein the UE 101 needs to be connected to the Customized SGSN 122, the General SGSN 121 transmits an Attach

Reject signal (9) to the UE 101, instead of continuing the Attach Procedure.

[0169]

In this case, the General SGSN 121 sets a parameter for instructing re-Attach and an RAI (Routing Area Identity) parameter (a parameter newly introduced in the present exemplary embodiment) in the Attach Reject signal, so that the RNC 171 can select the Customized SGSN 122 when performing re-Attach. While these parameters are parameters that are newly introduced in the present example, since the RNC 171 is transparent, the RNC 171 is not affected.

[0170]

The UE 101 needs to be equipped with a function of receiving an RAI via an Attach Reject and using the RAI specified in the Attach Reject when transmitting a Re-Attach. The SGSNs are equipped with a function of determining whether the UE 101 is a re-selection target.

[0171]

The UE 101, upon reception of the Attach Reject signal (9), transmits, to the RNC 171, the Attach Request signal (1) in which the RAI has been set, in accordance with the parameter for instructing re-Attach set in the Attach-Reject signal (9) and the RAI parameter (re-Attach by a P-TMSI (Packet Temporary Mobile Subscriber Identifier)), as illustrated in Fig. 13. The RNC 171 decides an appropriate SGSN from the RAI and forwards the Attach Request to the Customized SGSN 122.

[0172]

Subsequently, the Customized SGSN 122 continues a normal Attach Procedure.

[0173]

While the RAI is set in the Attach Request, the Customized SGSN 122 does not hold context information. Thus, upon reception of the Attach Request signal (1), the Customized SGSN 122 acquires terminal information via an Identity Request/Response (3). In addition, the Customized SGSN 122 performs authentication and acquires a subscriber profile in coordination with the HLR 131.

[0174]

The General SGSN 121 and the Customized SGSN 122 are equipped with a function of determining which SGSN needs to be connected to the UE 101, as is the case with example 6.

5 [0175]

In the present example, even when an Attach Request signal is forwarded from the UE 101 that needs to be connected to the General SGSN (121) to the Customized SGSN 122, the Customized SGSN 122 can request the UE 101 for re-selection of an SGSN in a like manner.
 10 If the UE 101 is a normal mobile station (for example, a terminal that is not compatible with a special service such as MTC or MBMS) and if the UE 101 is connected to the Customized SGSN 122, the Customized SGSN 122 transmits an Attach Reject signal to the UE 101 and requests the UE 101 to select the General SGSN 121. In this way, since the UE
 15 101 transmits a re-Attach Request (Attach Request) signal, the General SGSN 121 is selected and a service is provided from the General SGSN 121.

[0176]

As described above, in the present example, the General SGSN
 20 instructs the UE to perform re-selection of an SGSN. In response to the instruction, the UE specifies the Customized SGSN and an Attach Procedure is continued. In this way, the UE can be attached to an appropriate SGSN.

[0177]

25 <Example 9>

As example 9, another example with UMTS will be described. In this example, the UE transmits an Attach Request and the UE is connected to the Customized SGSN. In example 6, the same system configuration as that in example 6 will be used. Fig. 14 is a sequence diagram
 30 illustrating an operation according to example 9. Hereinafter, the operation will be described with reference to Figs. 2 and 14.

[0178]

To transmit an Attach Request to an SGSN, first, the UE 101 establishes RRC Connection with the RNC 171. To establish RRC

Connection, first, the UE 101 transmits an RRC Connection Request signal to the RNC 171.

[0179]

In this signal, the UE 101 sets a parameter indicating that the UE 101 needs to be connected to the Customized SGSN 122 (a User Identity, a new Value or a new parameter of establishment Cause (a value or a parameter newly introduced in the present example), or an identifier of a part of such parameters (a PLMN-id included in the IMSI, for example)).

[0180]

When receiving the RRC Connection Request signal, the RNC 171 stores information indicating that the UE 101 needs to be connected to the Customized SGSN 122 and continues the subsequent RRC Connection Procedure.

[0181]

After establishing RRC Connection, the UE 101 transmits an Attach Request (1) and the NodeB 111 receives the Attach Request (1). Next, the NodeB 111 forwards the Attach Request to the RNC 171.

[0182]

The RNC 171 forwards the Attach Request to an SGSN. From the information stored when the RNC 171 has received the RRC Connection Request signal, the RNC 171 forwards the Attach Request signal to the Customized SGSN 122.

[0183]

After receiving the Attach Request signal, the Customized SGSN 122 continues a normal Attach Procedure.

[0184]

In addition, the UE 101 is equipped with a function of instructing the RNC 171 about which one of the General SGSN 121 and the Customized SGSN 122 needs to be connected to the UE 101. The UE 101 cannot store information about all the SGSNs in the core network, information indicating an SGSN type, a service type, or the like is used for the instruction given to the RNC 171, instead of an identifier by which a unique SGSN can be selected.

[0185]

The RNC 171 is equipped with a function of determining which SGSN needs to be connected to the UE 101. For this determination, as described above, one of or a combination of a User Identity, a new value
5 or a new parameter of Establishment Cause (a value or a parameter newly introduced in the present example), and an identifier of a part of such parameters is used.

[0186]

As described above, in the present example, the UE 101 instructs
10 the RNC 171 to select an SGSN. In response to the instruction, the RNC 171 specifies the Customized SGSN and an Attach Procedure is continued. In this way, the UE 101 can be attached to an appropriate SGSN.

[0187]

15 <Example 10>

As example 10, another example with UMTS will be described. In this example, the UE and the Customized SGSN are connected when RA Update is performed. In example 10, the same system configuration as that in example 6 will be used. Figs. 15 and 16 are sequence diagrams
20 illustrating an operation according to example 10. Hereinafter, the operation will be described with reference to Figs. 2, 15, 16, and a part of Fig. 10.

[0188]

When the UE 101 transmits an Attach Request (see 1 in Fig. 10),
25 first, the NodeB 111 receives the Attach Request. The NodeB 111 forwards the Attach Request to the RNC 171, and the RNC 171 forwards the Attach Request to an SGSN. The RNC 171 cannot uniquely determine whether to forward the Attach Request to the General SGSN 121 or to the Customized SGSN (12). Thus, there are cases where the
30 RNC 171 forwards the Attach Request to the General SGSN 121.

[0189]

After receiving the Attach Request, the General SGSN 121 acquires terminal information via an Identity Request/Response (see 3,
5 in Fig. 10). In addition, the General SGSN 121 performs

authentication and acquires a subscriber profile in coordination with the HLR 131.

[0190]

The General SGSN 121, on acquisition of the terminal information and the subscriber profile, determines whether to connect the UE 101 to the General SGSN 121 or to the Customized SGSN 122. In the case wherein the UE 101 needs to be connected to the General SGSN 121, the General SGSN 121 continues a normal Attach Procedure.

[0191]

In the case wherein the UE 101 needs to be connected to the Customized SGSN 122, the General SGSN 121 performs Iu Release to cause the UE 101 to perform RA (Routing Area) update, as illustrated in Fig. 15.

[0192]

The General SGSN 121 transmits an Iu Release Command signal (4 in Fig. 15) to the RNC 171. The General SGSN 121 gives an instruction about an SGSN to be selected by the RNC when establishing Iu Connection with an SGSN next time, by using an SGSN identifier (for example, an RAI or an NRI) in the Iu Release Command signal. In the case of a single pool, the NRI may be used.

[0193]

Even after Iu Release is completed, while the RNC 171 is holding session information for the UE 101, the RNC 171 continues to hold the SGSN identifier as information for selection of the next SGSN.

[0194]

After Iu Release is performed (after the RNC 171 transmits Iu Release Complete (6) to the General SGSN 121), next, as illustrated in Fig. 16, the UE 101 transmits an RAU request (RA Update Request) (2).

[0195]

First, the NodeB 111 receives the RAU Request (2), and the NodeB 111 forwards the RAU Request (3) to the RNC 171.

[0196]

Next, the RNC 171 forwards the RAU request to an SGSN. Since Iu Release (c) has already been performed, the RNC 171 performs

selection of an SGSN and establishes Iu Connection.

[0197]

In selection of an SGSN, the RNC 171 selects the Customized SGSN 122 in accordance with the SGSN Identifier specified in the Iu Release Command signal received from the General SGSN 121. The RNC selects the Customized SGSN in accordance with the RAI (or the NRI) instructed by the old SGSN (= the General SGSN) when Iu Release is performed. The RNC is equipped with a function of holding the next RAI per UE.

10 [0198]

After receiving the RAU request, the Customized SGSN 122 continues a normal RA Update Procedure. Since the P-TMSI (RAI) on the NAS indicates the General SGSN, which is the old SGSN, the Customized SGSN 122 acquires context.

15 [0199]

The General SGSN 121 and the Customized SGSN 122 are equipped with a function of determining which SGSN needs to be connected to the UE 101. This function is the same as that in example 6.

20 [0200]

In the present example, in the same means as described above, when the RNC 17 receives an RA Update Request from the UE 101 that needs to be connected to the General MME 21 (for example, from a normal mobile station (a normal mobile station that is not compatible with a special service such as MTC or MBMS)), by selecting the General SGSN 121, the UE 101 is connected to the General SGSN 121 and a service is provided from the General SGSN 121.

[0201]

In addition, in the present example, the RA Update Procedure has been performed based on the sequence in Fig. 16. However, a feature in the present example is that the RNC 171 selects an SGSN. Thus, the present example can also be realized by, for example, other procedures for re-establishing Iu Connection, such as PDP Context Activation.

[0202]

As described above, according to the present example, the General SGSN instructs the RNC to perform re-selection of an SGSN. In response to the instruction, the RNC specifies the Customized SGSN in the next selection of an SGSN, and the other procedure is continued.

5 In this way, the UE can be connected to an appropriate SGSN.

[0203]

Hereinafter, differences among the above examples will be described.

[0204]

10 <Mobile network>

Examples 1-5 are, for example, based on LTE (Long Term Evolution) (the radio access network is E-UTRAN (Evolved-Universal Terrestrial Radio Access Network) and the core network is EPC). Examples 6-10 are, for example, based on 3G (3rd Generation) (the radio access network is UTRAN (Universal Terrestrial Radio Access Network) and the core network is GPRS).

15 network is UTRAN (Universal Terrestrial Radio Access Network) and the core network is GPRS).

[0205]

<Implementation methods>

A) Examples 1 and 6: attach procedure (retry in the RAN (Radio Access Network))

20 Network))

[0206]

B) Examples 2 and 7: attach procedure (interworking in the core network (CN))

[0207]

25 C) Examples 3 and 7: retry by the terminal

[0208]

D) Examples 4 and 8: selection in the core network (CN)

[0209]

E) Examples 5 and 10: update of the location management area (RAU/TAU)

30 (RAU/TAU)

[0210]

<Extent of the impact (elements that need to be modified for implementation)>

A) Examples 1 and 6: the RAN (radio access network) and the CN (core

network)

[0211]

B) Examples 2 and 7: the CN (RAN)

[0212]

5 C) Examples 3 and 8: the terminal and the CN

[0213]

D) Examples 4 and 9: the terminal and the RAN

[0214]

E) Examples 5 and 10: the RAN and the CN

10 [0215]

<Advantageous effects, etc. provided by implementation>

A) Examples 1 and 6: while no functions need to be added to the terminal, functions need to be added to the RAN.

[0216]

15 B) Examples 2 and 7: no functions need to be added to the terminal, and in some cases, no functions need to be added to the RAN. In addition, among the examples, the least signal amount is required.

[0217]

20 C) Examples 3 and 8: no functions need to be added to the RAN, and functions can easily be added to the terminal and the CN. However, Attach Reject requires time.

[0218]

25 D) Examples 4 and 9: while no functions need to be added to the CN, more functions need to be added to the RAN than the other examples. In addition, the RAN needs to store and manage a CN list for selecting a CN. Before accessing the HLR/HSS, information used for selecting a CN is limited.

[0219]

30 E) Examples 5 and 10: no functions need to be added to the terminal. Re-selection of a CN is possible after Attach by change of a contract or the like.

[0220]

<Cases where core network node is selected>

Hereinafter, several cases where a core network node is selected based

on the above exemplary embodiments and examples will be described.

[0221]

An MTC (Machine Type Communication) device (an M2M device) is connected to a customized CN node (a node optimized for MTC devices).

[0222]

A user using MBMS is connected to a customized CN node (an MBMS-compatible CN node).

[0223]

In another case, a service is provided only by a customized CN node so that a new service is started in a small scale.

[0224]

<Cases with LTE>

A specific UE is connected to a node in which an MME and an SGW are collocated. While not particularly limited, for example, there are cases where a small amount of data traffic is transmitted to a UE via an SMS (Short Message Service). In such cases, if an MME and an SGW are collocated, implementation of SMS conversion processing can be achieved more easily.

[0225]

In addition, MMEs are switched, depending on a terminal type (CSFB (CS Fallback) terminal and a VoLTE terminal, for example). CSFB (CS Fallback) is a function of switching radio to 3G (or 2G) when a CS (Circuit Switched) service is transmitted or received during LTE connection. VoLTE (Voice over LTE) is a function of providing a voice (which have been provided via CS) service on LTE. The CSFB terminal needs to interwork with an MSC. The VoLTE terminal needs to interwork with an IMS (IP Multimedia Subsystem). When CSFB is performed, an MSC (Mobile Switching Center) that is in advance attached is caused to select a collocated MME.

[0226]

The disclosure of the above Patent Literature incorporated herein by reference thereto. Modifications and adjustments of the exemplary embodiments and examples are possible within the scope of the overall

disclosure (including the claims) of the present invention and based on the basic technical concept of the present invention. Various combinations and selections of various disclosed elements (including the elements in each of the claims, examples, drawings, etc.) are possible within the scope of the claims of the present invention. That is, the present invention of course includes various variations and modifications that could be made by those skilled in the art according to the overall disclosure including the claims and the technical concept.

REFERENCE SIGNS LIST

10	[0227]	
	1	UE
	11	eNodeB
	21	General MME
	22	Customized MME
15	31	HSS
	41	S-GW (Serving GW)
	51	P-GW (PDN GW)
	61	service network
	101	UE (MS)
20	111	NodeB
	121	General SGSN
	122	Customized SGSN
	131	HLR
	141	GGSN
25	161	service network
	171	RNC

CLAIMS:

1. A mobile communication system, comprising:
 - 5 a terminal (UE(User Equipment) or MS (Mobile Station)) supporting a function associated with MTC (Machine Type Communication);
 - a base station; and
 - a specific MME (Mobility Management Entity) or SGSN (a
 - 10 Serving GPRS (General Packet Radio Service) Support Node),wherein the terminal supporting the function associated with MTC is configured to provide the base station with information indicating that an RRC (Radio Resource Control) connection request includes the function, and
 - 15 wherein the base station is configured to use the indication information provided by the terminal supporting the function to steer the terminal supporting the function to the specific MME or SGSN, or to select the specific MME or SGSN.
-
- 20 2. A base station in a mobile communication system comprising at least a terminal (UE (User Equipment) or an MS (Mobile Station)) supporting a function relating to MTC (Machine Type Communication) and a specific MME (Mobility Management Entity) or SGSN (Serving GPRS (General Packet Radio Service) Support Node), characterized in
 - 25 that the base station comprises:
 - a unit configured to receive information indicating that an RRC (Radio Resource Control) connection request includes the function from the terminal supporting the function; and
 - a unit configured to use the indication information provided by
 - 30 the terminal supporting the function to steer the terminal supporting the function to the specific MME or SGSN, or to select the specific MME or SGSN.

3. A terminal in a mobile communication system comprising at least a base station and a specific MME (Mobility Management Entity) or SGSN (Serving GPRS (General Packet Radio Service) Support Node),
5 and that is a terminal (UE (User Equipment) or an MS (Mobile Station)) supporting a function relating to MTC (Machine Type Communication), characterized in that the terminal comprises:

10 a unit configured to provide the base station with information indicating that an RRC (Radio Resource Control) connection request includes the function; and

a unit configured to cause the base station to use the indication information provided by the terminal to steer the terminal supporting the function to the specific MME or SGSN, or to select the specific MME or SGSN.

15 4. A communication method for a mobile communication system comprising at least a terminal (UE (User Equipment) or an MS (Mobile Station)) supporting a function relating to MTC (Machine Type Communication), a base station, and a specific MME (Mobility
20 Management Entity) or SGSN (Serving GPRS (General Packet Radio Service) Support Node), characterized in that the method comprises:

the terminal supporting the function providing the base station with information indicating that an RRC (Radio Resource Control) connection request includes the function; and

25 the base station using the indication information provided by the terminal to steer the terminal supporting the function to the specific MME or SGSN, or to select the specific MME or SGSN.

5. A communication method for a base station used in a mobile
30 communication system comprising at least a terminal (UE (User Equipment) or an MS (Mobile Station)) supporting a function relating to MTC (Machine Type Communication) and a specific MME (Mobility

Management Entity) or SGSN (Serving GPRS (General Packet Radio Service) Support Node), characterized in that the method comprises:

receiving information indicating that an RRC (Radio Resource
5 Control) connection request includes the function from the terminal supporting the function; and

using the indication information provided by the terminal to steer the terminal supporting the function to the specific MME or SGSN, or to select the specific MME or SGSN.

10

6. A communication method for a terminal (UE (User Equipment) or an MS (Mobile Station)) in a mobile communication system comprising at least a base station and a specific MME (Mobility Management Entity) or SGSN (Serving GPRS (General Packet Radio Service) Support
15 Node) and that supports a function relating to MTC (Machine Type Communication), characterized in that the method comprises:

providing the base station with information indicating that an RRC (Radio Resource Control) connection request includes the function; and

20 causing the base station to use the indication information provided by the terminal to steer the terminal supporting the function to the specific MME or SGSN, or to select the specific MME or SGSN.

COMMUNICATION SYSTEM, METHOD, AND APPARATUS

ABSTRACT

5

Provided are a system, a method, and a device for reducing the equipment cost in the whole core network in a mobile communication system more efficiently to achieve cost reduction. A core network includes a plurality of nodes that serve as nodes managing mobility of a terminal and that are different with regards to service functions that nodes provide to the terminal. Based on subscriber information and terminal information, a node to be connected to the terminal is selected on the core network side, depending on a service characteristic utilized by the terminal or on a type of the terminal and the terminal is connected to the selected node.

10

15

Figure 1