

SOUNDING FRAME TRANSMISSION METHOD AND RELATED APPARATUS

[0001] This application claims priority to Chinese Patent Application No. 202111438461.3, filed with the China National Intellectual Property Administration on November 26, 2021 and
5 entitled "SOUNDING FRAME TRANSMISSION METHOD AND RELATED APPARATUS", which is incorporated herein by reference in its entirety.

TECHNICAL FIELD

[0002] This application relates to the field of communication technologies, and in particular, to a sounding frame transmission method and a related apparatus.

BACKGROUND

[0003] In a wireless local area network (wireless local area network, WLAN), a communication link may be established between a wireless access point (access point, AP) and a station (station, STA), to communicate with each other through a shared wireless communication medium. Generally, a WLAN device may adjust a transmission parameter based on channel quality
15 of the communication link, to optimize transmission throughput or reliability of the communication link. For example, in 802.11ax, channel quality of the communication link is measured by using a high efficiency long training field (high efficiency long training field, HE-LTF) sequence; and in 802.11be, channel quality of the communication link is measured by using an (extremely high throughput long training field, EHT-LTF) sequence. However, in a current stage,
20 components corresponding to tones in the HE-LTF sequence or the EHT-LTF sequence are all +1, 0, or -1. In other words, a current HE-LTF sequence or a current EHT-LTF sequence is an HE-LTF sequence or an EHT-LTF sequence under binary phase shift keying (binary phase shift keying, BPSK) modulation. It may be understood that distortion of the HE-LTF sequence or the EHT-LTF sequence under BPSK modulation is small, and a peak-to-average power ratio (peak to average
25 power ratio, PAPR) is low. Therefore, when the HE-LTF sequence or the EHT-LTF sequence is used to measure the channel quality of the communication link, only channel quality of the communication link under BPSK modulation can be accurately measured. In other words, the current HE-LTF sequence or the current EHT-LTF sequence is applicable to a single scenario, and

cannot accurately measure channel quality of the communication link in more application scenarios.

SUMMARY

[0004] This application provides a sounding frame transmission method and a related apparatus, so that channel quality of a communication link in at least one of modulation modes of QPSK, 16-QAM, 64-QAM, 256-QAM, 1024-QAM and 4096-QAM can be accurately measured when channel measurement is performed by using a first sequence, thereby enriching application scenarios of an EHT-LTF sequence.

[0005] According to a first aspect, a sounding frame transmission method is provided. The method is applied to a first device, and the method includes: generating a sounding frame, where the sounding frame includes a first field, the first field includes a predefined first sequence, the first sequence includes a sequence obtained after a second sequence is modulated by using at least one of the following modulation modes, and the modulation modes include: quadrature phase shift keying QPSK, 16-quadrature amplitude modulation 16-QAM, 64-QAM, 256-QAM, 1024-QAM, and 4096-QAM; and sending the sounding frame. In this way, channel quality of a communication link in at least one of modulation modes of QPSK, 16-QAM, 64-QAM, 256-QAM, 1024-QAM, and 4096-QAM can be measured when channel measurement is performed by using the first sequence, thereby enriching application scenarios of an HE-LTF sequence or an EHT-LTF sequence. In addition, because a PAPR of the first sequence is low, distortion of the first sequence is small, so that the channel quality of the communication link in at least one of modulation modes of QPSK, 16-QAM, 64-QAM, 256-QAM, 1024-QAM, and 4096-QAM can be accurately measured when channel measurement is performed by using the first sequence.

[0006] According to a second aspect, a sounding frame transmission method is provided. The method is applied to a second device, and the method includes: receiving a sounding frame, where the sounding frame includes a first field, the first field includes a predefined first sequence, the first sequence includes a sequence obtained after a second sequence is modulated by using at least one of the following modulation modes, and the modulation modes include: quadrature phase shift keying QPSK, 16-quadrature amplitude modulation 16-QAM, 64-QAM, 256-QAM, 1024-QAM, and 4096-QAM; and performing channel measurement based on the first sequence. In this way, channel quality of a communication link in at least one of modulation modes of QPSK, 16-QAM, 64-QAM, 256-QAM, 1024-QAM, and 4096-QAM can be measured when channel measurement is performed by using the first sequence, thereby enriching application scenarios of an HE-LTF sequence or an EHT-LTF sequence. In addition, because a PAPR of the first sequence is low,

distortion of the first sequence is small, so that the channel quality of the communication link in at least one of modulation modes of QPSK, 16-QAM, 64-QAM, 256-QAM, 1024-QAM, and 4096-QAM can be accurately measured when channel measurement is performed by using the first sequence.

[0007] According to a third aspect, a communication apparatus is provided, where the communication apparatus includes a processing module and a transceiver module. The processing module is configured to generate a sounding frame. The sounding frame includes a first field, the first field includes a predefined first sequence, the first sequence includes a sequence obtained after a second sequence is modulated by using at least one of the following modulation modes, and the modulation modes include: quadrature phase shift keying QPSK, 16-quadrature amplitude modulation 16-QAM, 64-QAM, 256-QAM, 1024-QAM, and 4096-QAM. The transceiver module is configured to send the sounding frame.

[0008] According to a fourth aspect, a communication apparatus is provided, where the communication apparatus includes a processing module and a transceiver module. The transceiver module is configured to receive a sounding frame. The sounding frame includes a first field, the first field includes a predefined first sequence, the first sequence includes a sequence obtained after a second sequence is modulated by using at least one of the following modulation modes, and the modulation modes include: quadrature phase shift keying QPSK, 16-quadrature amplitude modulation 16-QAM, 64-QAM, 256-QAM, 1024-QAM, and 4096-QAM. The processing module is configured to perform channel measurement based on the first sequence.

[0009] Optionally, with reference to the first aspect, the second aspect, the third aspect, or the fourth aspect, the second sequence is an HE-LTF sequence or an EHT-LTF sequence in a 4x mode at an 80 MHz bandwidth.

[0010] The HE-LTF sequence is:

$$\text{HE} - \text{LTF}_{4\text{y}}(-500:500) =$$

[1, -1, -1, -1, -1, 1, -1, -1, 1, -1, -1, -1, 1, 1, -1, -1, -1, 1, -1, -1, 1, 1, 1, -1,
1, -1, 1, -1, -1, -1, -1, 1, 1, 1, 1, 1, -1, -1, 1, -1, 1, -1, -1, -1, 1, 1, -1, -1, 1, 1, 1,
-1, -1, 1, 1, -1, -1, 1, -1, 1, 1, -1, 1, -1, 1, 1, 1, 1, 1, 1, -1, -1, -1, 1, -1, 1, -1,
-1, -1, 1, -1, -1, 1, 1, 1, 1, 1, 1, -1, 1, -1, 1, 1, -1, 1, -1, 1, -1, 1, -1, -1, 1, 1, 1, 1, -1, -1,
-1, -1, -1, -1, -1, -1, 1, -1, -1, 1, -1, -1, 1, 1, 1, -1, 1, -1, -1, -1, 1, 1, 1, -1, 1, 1, -1, -1, 1, -1,
-1, -1, 1, 1, 1, 1, -1, 1, 1, 1, 1, 1, 1, -1, 1, -1, -1, 1, -1, 1, -1, -1, 1, 1, 1, 1, 1, -1, 1, 1, -1, -1, 1,
1, 1, -1, 1, 1, -1, 1, 1, -1, -1, 1, 1, -1, -1, -1, -1, 1, 1, 1, 1, 1, -1, 1, 1, 1, 1, 1, -1, 1, -1, 1, -1, -
1, 1, -1, -1, -1, -1, -1, 1, -1, -1, -1, 1, 1, -1, 1, -1, 1, -1, -1, -1, -1, -1, 1, 1, 1, 1, -1, 1, -1, -1,
1, 1, -1, -1, -1, 1, 1, 1, 1, 1, -1, 1, -1, 1, -1, -1, 1, 1, 1, -1, 1, 1, 1, 1, 1, -1, 1, 1, -1, 1, -1, 1, -1,
-1, -1, -1, -1, 1, -1, -1, -1, -1, -1, 1, 1, 1, 1, -1, -1, 1, 1, -1, -1, 1, -1, -1, -1, 1, 1, -

1, -1, 1, -1, -1, -1, -1, -1, 1, 1, -1, 1, -1, 1, 1, -1, 1, -1, -1, -1, -1, -1, 1, -1, -1, -1, -1, 1, 1,
1, -1, 1, 1, -1, -1, 1, -1, -1, -1, 1, 1, 1, -1, 1, -1, 1, -1, -1, -1, 1, -1, 1, -1, 1, -1, -1, 1, -1, -
1, 1, -1, 1, 1, -1, -1, -1, 1, 1, -1, -1, -1, -1, 1, -1, 1, 1, -1, 1, 1, 1, 1, 1, -1, -1, 1, -1, -
1, -1, 1, -1, 1, -1, -1, -1, 1, 1, 1, 1, 1, -1, 1, -1, 1, 1, -1, 1, -1, 1, -1, 1, -1, 1, -1, -
5 1, 1, 1, 1, -1, -1, -1, 1, -1, -1, 1, 1, -1, -1, -1, 1, -1, 1, -1, -1, 1, 1, 1, 1, 1, -1, -1, -1, 1, -1,
1, -1, 1, 1, 1, -1, 1, -1, -1, 1, -1, -1, -1, 1, 1, -1, -1, -1, 1, -1, -1, -1, -1, 1, -1, 1, 1, -
1, -1, -1, 1, -1, -1, 0, 0, 0, 0, 0, -1, -1, 1, -1, 1, 1, 1, 1, 1, -1, -1, -1, -1, 1, -1, -1, 1, -1, -1, -
1, 1, 1, -1, -1, -1, 1, -1, -1, 1, -1, 1, 1, 1, -1, 1, -1, 1, -1, -1, -1, 1, 1, 1, 1, -1, -1, 1, -1, 1,
-1, -1, -1, 1, 1, -1, -1, 1, -1, -1, -1, 1, 1, 1, -1, -1, 1, 1, -1, -1, 1, -1, 1, 1, -1, 1, 1, -1,
10 1, -1, 1, 1, 1, 1, 1, 1, -1, -1, -1, 1, -1, 1, -1, -1, -1, 1, -1, -1, 1, 1, 1, 1, 1, -1, 1, -1, 1, 1, -1, 1,
-1, -1, -1, -1, 1, 1, -1, -1, -1, 1, 1, -1, 1, -1, -1, 1, -1, -1, -1, 1, -1, -1, -1, 1, -1, 1, -1, 1,
-1, 1, 1, 1, -1, -1, -1, 1, -1, -1, 1, 1, -1, 1, 1, 1, -1, -1, -1, -1, 1, -1, -1, -1, -1, 1, -1, 1,
1, -1, 1, -1, 1, 1, -1, -1, -1, -1, -1, 1, -1, -1, 1, 1, -1, -1, -1, 1, -1, -1, 1, -1, -1, 1, -1, -1, 1,
1, 1, 1, -1, -1, -1, -1, -1, 1, -1, -1, -1, -1, -1, 1, -1, 1, -1, 1, 1, -1, 1, 1, 1, 1, -1, 1, 1, 1, -1, -
15 1, 1, -1, 1, -1, 1, 1, 1, 1, 1, -1, -1, -1, 1, 1, -1, -1, -1, -1, -1, -1, 1, 1, 1, 1, 1, -1, 1, -1, 1,
-1, -1, 1, 1, 1, -1, 1, 1, 1, 1, 1, -1, 1, 1, -1, 1, -1, -1, -1, -1, -1, 1, -1, -1, -1, -1, 1, 1,
1, 1, -1, -1, 1, 1, -1, -1, 1, -1, -1, 1, -1, -1, -1, 1, 1, -1, -1, -1, -1, -1, -1, 1, -1, 1, -1,
1, 1, -1, 1, -1, -1, -1, -1, -1, -1, 1, -1, -1, -1, -1, 1, 1, 1, -1, 1, 1, -1, -1, -1, 1, 1, 1, -
1, 1, -1, -1, -1, 1, 1, -1, 1, 1, -1, 1, 1, 1, 1, 1, 1, 1, -1, -1, -1, -1, 1, 1, -1, 1, -1, 1, -1, 1,
20 -1, -1, 1, -1, 1, -1, -1, -1, -1, -1, -1, 1, 1, -1, 1, 1, 1, -1, 1, -1, 1, 1, 1, -1, -1, -1, -1, -1, 1,
-1, 1, -1, -1, -1, 1, -1, 1, -1, -1, 1, -1, 1, 1, -1, -1, 1, 1, -1, -1, -1, 1, 1, 1, -1, 1, 1, -1, -1, 1, 1,
1, -1, 1, -1, 1, 1, -1, -1, -1, -1, -1, 1, 1, 1, 1, -1, 1, -1, 1, -1, -1, -1, 1, 1, -1, 1, 1, 1, -1, -
1, 1, 1, -1, -1, -1, -1, -1, 1, -1, -1, -1, -1, 1, 1, 1, -1, 1, 1, -1, -1, -1, -1, 1, 1, 1, -1, -
35 -1, -1, -1, -1, -1, -1, 1, -1, -1, 1, -1, -1, 1, 1, 1, -1, 1, -1, -1, -1, 1, 1, 1, -1, 1, 1, -1, -1, 1, -1,

[0011] The expression $HE - LTF_{4x}(-500:500)$ means that values on tones whose sequence
25 numbers are -500 to 500 are values in the HE-LTF sequence successively. That is, it can be learned
that components of the second sequence are all +1, 0, or -1, and distortion of the HE-LTF sequence
under BPSK modulation is small and a PAPR is low. Therefore, channel quality of a link under
BPSK modulation can be accurately measured.

[0012] The EHT-LTF sequence is:

30 $EHT - LTF_{4x}(-500:500) =$
 $[1, -1, -1, -1, -1, 1, -1, -1, 1, -1, -1, -1, 1, 1, -1, -1, -1, 1, -1, -1, 1, -1, 1, 1, 1, -1,$
 $1, -1, 1, -1, -1, -1, -1, 1, 1, 1, 1, 1, -1, -1, 1, -1, 1, -1, -1, -1, 1, 1, -1, -1, -1, 1, 1, 1,$
 $-1, -1, 1, 1, -1, -1, 1, -1, 1, 1, -1, 1, -1, 1, 1, 1, 1, 1, -1, -1, -1, 1, -1, 1, -1,$
 $-1, -1, 1, -1, -1, 1, 1, 1, 1, 1, 1, -1, 1, -1, 1, 1, -1, 1, -1, 1, -1, -1, 1, 1, 1, 1, -1, -1,$
35 $-1, -1, -1, -1, -1, -1, 1, -1, -1, 1, -1, -1, 1, 1, 1, -1, 1, -1, -1, -1, 1, 1, 1, -1, 1, 1, -1, -1,$

[0014] The second sequence is the HE-LTF sequence, $\mathbf{a}_0$ and $\mathbf{a}_1$ are subsequences in the HE-LTF sequence, j is an imaginary unit, and i is an integer greater than or equal to 1 and less than or equal to 7.

[0015] $\mathbf{c}_1 = [1j, 1j, 1j, -1j, -1j, -1j, 1j, 1j, -1j]$.

5 **[0016]** $\mathbf{c}_2 = [-1, -1, -1, -1j, -1j, -1j, 1j, 1j, -1j]$.

[0017] $\mathbf{c}_3 = [-1, -1, -1, 1, 1, -1j, 1j, 1j, -1j]$.

[0018] $\mathbf{c}_4 = [-1, -1, -1, 1, 1, 1, 1j, 1j, -1j]$.

[0019] $\mathbf{c}_5 = [-1, -1, -1, 1, 1, 1, -1, 1j, -1j]$.

[0020] $\mathbf{c}_6 = [-1, -1, -1, 1, 1, 1, -1, -1, -1j]$.

10 **[0021]** $\mathbf{c}_7 = [-1, -1, -1, 1, 1, 1, -1, -1, 1]$.

[0022] That is, in the foregoing technical solution, a sequence under QPSK modulation is implemented, so that channel quality of a communication link under QPSK modulation can be accurately measured when the channel quality of the communication link is measured by using the sequence.

15 **[0023]** Optionally, with reference to the first aspect, the second aspect, the third aspect, or the fourth aspect, the first sequence meets the following formula:

$$\mathbf{q}_1 = \frac{2}{\sqrt{5}} e^{\frac{j\pi}{4}} \mathbf{s}_{k1} + \frac{1}{\sqrt{5}} e^{\frac{j\pi}{4}} \mathbf{s}_{k2}.$$

[0024] $\mathbf{s}_{k1} = [\mathbf{a}_0, \mathbf{c}_{k1}, 0, 0, 0, 0, 0, (-1j) * \mathbf{a}_1]$; $\mathbf{s}_{k2} = [\mathbf{a}_0, \mathbf{c}_{k2}, 0, 0, 0, 0, 0, (-1j) * \mathbf{a}_1]$; and the second sequence is the HE-LTF sequence, $\mathbf{a}_0$ and $\mathbf{a}_1$ are subsequences in the HE-LTF sequence, and j is an imaginary unit.

[0025] $k1$ is 1, and $k2$ is 7; or $k1$ is 4, and $k2$ is 5 or 6; or $k1$ is 5, and $k2$ is 1 or 2.

[0026] $\mathbf{c}_1 = [1j, 1j, 1j, -1j, -1j, -1j, 1j, 1j, -1j]$.

[0027] $\mathbf{c}_2 = [-1, -1, -1, -1j, -1j, -1j, 1j, 1j, -1j]$.

[0028] $\mathbf{c}_4 = [-1, -1, -1, 1, 1, 1, 1j, 1j, -1j]$.

25 **[0029]** $\mathbf{c}_5 = [-1, -1, -1, 1, 1, 1, -1, 1j, -1j]$.

[0030] $\mathbf{c}_6 = [-1, -1, -1, 1, 1, 1, -1, -1, -1j]$.

[0031] $\mathbf{c}_7 = [-1, -1, -1, 1, 1, 1, -1, -1, 1]$.

[0032] That is, in the foregoing technical solution, a sequence under 16-QAM modulation is implemented, so that channel quality of a communication link under 16-QAM modulation can be accurately measured when the channel quality of the communication link is measured by using the sequence.

30 **[0033]** Optionally, with reference to the first aspect, the second aspect, the third aspect, or the fourth aspect, the first sequence meets the following formula:

$$\mathbf{q}_2 = \frac{4}{\sqrt{21}} e^{\frac{j\pi}{4}} \mathbf{s}_{k3} + \frac{2}{\sqrt{21}} e^{\frac{j\pi}{4}} \mathbf{s}_{k4} + \frac{1}{\sqrt{21}} e^{\frac{j\pi}{4}} \mathbf{s}_{k5}.$$

[0034] $s_{k3} = [a_0, c_{k3}, 0,0,0,0,0, (-1j) * a_1]$; $s_{k4} = [a_0, c_{k4}, 0,0,0,0,0, (-1j) * a_1]$; $s_{k5} = [a_0, c_{k5}, 0,0,0,0,0, (-1j) * a_1]$; and the second sequence is the HE-LTF sequence, a_0 and a_1 are subsequences in the HE-LTF sequence, and j is an imaginary unit.

[0035] $k3$ is 1, $k4$ is 6, and $k5$ is 7; or $k3$ is 1, $k4$ is 7, and $k5$ is 5 or 6; or $k3$ is 2, $k4$ is 7, and $k5$ is 6 or 7; or $k3$ is 3, $k4$ is 5, and $k5$ is 6; or $k3$ is 3, $k4$ is 5, and $k5$ is 7; or $k3$ is 3, $k4$ is 6, and $k5$ is 5 or 6; or $k3$ is 3, $k4$ is 7, and $k5$ is 1, 2, 3, or 4; or $k3$ is 4, $k4$ is 4, and $k5$ is 7; or $k3$ is 4, $k4$ is 5, and $k5$ is 3, 4, or 5; or $k3$ is 4, $k4$ is 6, and $k5$ is 1, 2, 3, or 4; or $k3$ is 5, $k4$ is 1, and $k5$ is 3 or 4; or $k3$ is 5, $k4$ is 1, and $k5$ is 5; or $k3$ is 5, $k4$ is 2, and $k5$ is 4, 5, or 6; or $k3$ is 5, $k4$ is 3, and $k5$ is 1, 2, 3, or 4; or $k3$ is 5, $k4$ is 4, and $k5$ is 1 or 2; or $k3$ is 6, $k4$ is 1, and $k5$ is 1 or 2; or $k3$ is 6, $k4$ is 2, and $k5$ is 1, 2, or 3.

[0036] $c_1 = [1j, 1j, 1j, -1j, -1j, -1j, 1j, 1j, -1j]$.

[0037] $c_2 = [-1, -1, -1, -1j, -1j, -1j, 1j, 1j, -1j]$.

[0038] $c_3 = [-1, -1, -1, 1, 1, -1j, 1j, 1j, -1j]$.

[0039] $c_4 = [-1, -1, -1, 1, 1, 1, 1j, 1j, -1j]$.

[0040] $c_5 = [-1, -1, -1, 1, 1, 1, -1, 1j, -1j]$.

[0041] $c_6 = [-1, -1, -1, 1, 1, 1, -1, -1, -1j]$.

[0042] $c_7 = [-1, -1, -1, 1, 1, 1, -1, -1, 1]$.

[0043] That is, in the foregoing technical solution, a sequence under 64-QAM modulation is implemented, so that channel quality of a communication link under 64-QAM modulation can be accurately measured when the channel quality of the communication link is measured by using the sequence.

[0044] Optionally, with reference to the first aspect, the second aspect, the third aspect, or the fourth aspect, the first sequence meets the following formula:

$$q_3 = \frac{8}{\sqrt{85}} e^{\frac{j\pi}{4}} s_{k6} + \frac{4}{\sqrt{85}} e^{\frac{j\pi}{4}} s_{k7} + \frac{2}{\sqrt{85}} e^{\frac{j\pi}{4}} s_{k8} + \frac{1}{\sqrt{85}} e^{\frac{j\pi}{4}} s_{k9}.$$

[0045] $s_{k6} = [a_0, c_{k6}, 0,0,0,0,0, (-1j) * a_1]$; $s_{k7} = [a_0, c_{k7}, 0,0,0,0,0, (-1j) * a_1]$; $s_{k8} = [a_0, c_{k8}, 0,0,0,0,0, (-1j) * a_1]$; $s_{k9} = [a_0, c_{k9}, 0,0,0,0,0, (-1j) * a_1]$; and the second sequence is the HE-LTF sequence, a_0 and a_1 are subsequences in the HE-LTF sequence, and j is an imaginary unit.

[0046] $k6$ is 1, $k7$ is 7, $k8$ is 4, and $k9$ is 7; or $k6$ is 1, $k7$ is 7, $k8$ is 6, and $k9$ is 3; or $k6$ is 2, $k7$ is 7, $k8$ is 7, and $k9$ is 4; or $k6$ is 3, $k7$ is 5, $k8$ is 7, and $k9$ is 4; or $k6$ is 3, $k7$ is 6, $k8$ is 5, and $k9$ is 5; or $k6$ is 3, $k7$ is 7, $k8$ is 1, and $k9$ is 5; or $k6$ is 3, $k7$ is 7, $k8$ is 2, and $k9$ is 6; or $k6$ is 3, $k7$ is 7, $k8$ is 3, and $k9$ is 4; or $k6$ is 4, $k7$ is 4, $k8$ is 6, and $k9$ is 7; or $k6$ is 4, $k7$ is 6, $k8$ is 1, and $k9$ is 6; or $k6$ is 4, $k7$ is 6, $k8$ is 4, and

k_9 is 3; or k_6 is 5, k_7 is 1, k_8 is 1, and k_9 is 7; or k_6 is 5, k_7 is 2, k_8 is 6, and k_9 is 2; or k_6 is 5, k_7 is 4, k_8 is 1, and k_9 is 1; or k_6 is 5, k_7 is 4, k_8 is 2, and k_9 is 3; or k_6 is 6, k_7 is 1, k_8 is 1, and k_9 is 1.

[0047] $\mathbf{c}_1 = [1j, 1j, 1j, -1j, -1j, -1j, 1j, 1j, -1j].$

5 **[0048]** $\mathbf{c}_2 = [-1, -1, -1, -1j, -1j, -1j, 1j, 1j, -1j].$

[0049] $\mathbf{c}_3 = [-1, -1, -1, 1, 1, -1j, 1j, 1j, -1j].$

[0050] $\mathbf{c}_4 = [-1, -1, -1, 1, 1, 1, 1j, 1j, -1j].$

[0051] $\mathbf{c}_5 = [-1, -1, -1, 1, 1, 1, -1, 1j, -1j].$

[0052] $\mathbf{c}_6 = [-1, -1, -1, 1, 1, 1, -1, -1, -1j].$

10 **[0053]** $\mathbf{c}_7 = [-1, -1, -1, 1, 1, 1, -1, -1, 1].$

[0054] That is, in the foregoing technical solution, a sequence under 256-QAM modulation is implemented, so that channel quality of a communication link under 256-QAM modulation can be accurately measured when the channel quality of the communication link is measured by using the sequence.

15 **[0055]** Optionally, with reference to the first aspect, the second aspect, the third aspect, or the fourth aspect, the first sequence meets the following formula:

$$\mathbf{q}_4 = \frac{16}{\sqrt{341}} e^{\frac{j\pi}{4}} \mathbf{s}_{k10} + \frac{8}{\sqrt{341}} e^{\frac{j\pi}{4}} \mathbf{s}_{k11} + \frac{4}{\sqrt{341}} e^{\frac{j\pi}{4}} \mathbf{s}_{k12} + \frac{2}{\sqrt{341}} e^{\frac{j\pi}{4}} \mathbf{s}_{k13} + \frac{1}{\sqrt{345}} e^{\frac{j\pi}{4}} \mathbf{s}_{k14}.$$

[0056] $\mathbf{s}_{k10} = [\mathbf{a}_0, \mathbf{c}_{k10}, 0, 0, 0, 0, 0, (-1j) * \mathbf{a}_1] ; \quad \mathbf{s}_{k11} = [\mathbf{a}_0, \mathbf{c}_{k11}, 0, 0, 0, 0, 0, (-1j) * \mathbf{a}_1] ;$

$\mathbf{s}_{k12} = [\mathbf{a}_0, \mathbf{c}_{k12}, 0, 0, 0, 0, 0, (-1j) * \mathbf{a}_1] ; \quad \mathbf{s}_{k13} = [\mathbf{a}_0, \mathbf{c}_{k13}, 0, 0, 0, 0, 0, (-1j) * \mathbf{a}_1] ; \quad \mathbf{s}_{k14} =$

20 $[\mathbf{a}_0, \mathbf{c}_{k14}, 0, 0, 0, 0, 0, (-1j) * \mathbf{a}_1];$ and the second sequence is the HE-LTF sequence, $\mathbf{a}_0$ and $\mathbf{a}_1$ are subsequences in the HE-LTF sequence, and j is an imaginary unit.

[0057] k_{10} is 1, k_{11} is 7, k_{12} is 6, k_{13} is 1, and k_{14} is 5; or k_{10} is 2, k_{11} is 7, k_{12} is 5, k_{13} is 7, and k_{14} is 5; or k_{10} is 6, k_{11} is 1, k_{12} is 2, k_{13} is 4, and k_{14} is 4; or k_{10} is 4, k_{11} is 6, k_{12} is 4, k_{13} is 1, and k_{14} is 6; or k_{10} is 6, k_{11} is 2, k_{12} is 1, k_{13} is 4, and k_{14} is 5; or k_{10} is 3, k_{11} is 6, k_{12} is 7, k_{13} is 1, and k_{14} is 2; or k_{10} is 5, k_{11} is 3, k_{12} is 1, k_{13} is 6, and k_{14} is 1; or k_{10} is 4, k_{11} is 6, k_{12} is 2, k_{13} is 6, and k_{14} is 6.

[0058] $\mathbf{c}_1 = [1j, 1j, 1j, -1j, -1j, -1j, 1j, 1j, -1j].$

[0059] $\mathbf{c}_2 = [-1, -1, -1, -1j, -1j, -1j, 1j, 1j, -1j].$

30 **[0060]** $\mathbf{c}_3 = [-1, -1, -1, 1, 1, -1j, 1j, 1j, -1j].$

[0061] $\mathbf{c}_4 = [-1, -1, -1, 1, 1, 1, 1j, 1j, -1j].$

[0062] $\mathbf{c}_5 = [-1, -1, -1, 1, 1, 1, -1, 1j, -1j].$

[0063] $\mathbf{c}_6 = [-1, -1, -1, 1, 1, 1, -1, -1, -1j].$

[0064] $\mathbf{c}_7 = [-1, -1, -1, 1, 1, 1, -1, -1, 1].$

[0065] That is, in the foregoing technical solution, a sequence under 1024-QAM modulation is implemented, so that channel quality of a communication link under 1024-QAM modulation can be accurately measured when the channel quality of the communication link is measured by using the sequence.

5 **[0066]** Optionally, with reference to the first aspect, the second aspect, the third aspect, or the fourth aspect, the first sequence meets the following formula:

$$\mathbf{q}_5 = \frac{16}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{s}_{k15} + \frac{16}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{s}_{k16} + \frac{8}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{s}_{k17} + \frac{4}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{s}_{k18} + \frac{2}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{s}_{k19} + \frac{1}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{s}_{k20}.$$

10 **[0067]** $\mathbf{s}_{k15} = [\mathbf{a}_0, \mathbf{c}_{k15}, 0, 0, 0, 0, 0, (-1j) * \mathbf{a}_1]$; $\mathbf{s}_{k16} = [\mathbf{a}_0, \mathbf{c}_{k16}, 0, 0, 0, 0, 0, (-1j) * \mathbf{a}_1]$; $\mathbf{s}_{k17} = [\mathbf{a}_0, \mathbf{c}_{k17}, 0, 0, 0, 0, 0, (-1j) * \mathbf{a}_1]$; $\mathbf{s}_{k18} = [\mathbf{a}_0, \mathbf{c}_{k18}, 0, 0, 0, 0, 0, (-1j) * \mathbf{a}_1]$; $\mathbf{s}_{k19} = [\mathbf{a}_0, \mathbf{c}_{k19}, 0, 0, 0, 0, 0, (-1j) * \mathbf{a}_1]$; $\mathbf{s}_{k20} = [\mathbf{a}_0, \mathbf{c}_{k20}, 0, 0, 0, 0, 0, (-1j) * \mathbf{a}_1]$; and the second sequence is the HE-LTF sequence, $\mathbf{a}_0$ and $\mathbf{a}_1$ are subsequences in the HE-LTF sequence, and j is an imaginary unit.

15 **[0068]** $k15$ is 5, $k16$ is 2, $k17$ is 4, $k18$ is 7, $k19$ is 2, and $k20$ is 5; or $k15$ is 5, $k16$ is 2, $k17$ is 5, $k18$ is 1, $k19$ is 7, and $k20$ is 2; or $k15$ is 6, $k16$ is 2, $k17$ is 2, $k18$ is 3, $k19$ is 7, and $k20$ is 5; or $k15$ is 3, $k16$ is 6, $k17$ is 6, $k18$ is 4, $k19$ is 5, and $k20$ is 4; or $k15$ is 4, $k16$ is 7, $k17$ is 2, $k18$ is 2, $k19$ is 3, and $k20$ is 2; or $k15$ is 6, $k16$ is 1, $k17$ is 2, $k18$ is 3, $k19$ is 5, and $k20$ is 4; or $k15$ is 2, $k16$ is 7, $k17$ is 7, $k18$ is 3, $k19$ is 6, and $k20$ is 3; or $k15$ is 1, $k16$ is 7, $k17$ is 5, $k18$ is 5, $k19$ is 4, and $k20$ is 2.

20 **[0069]** $\mathbf{c}_1 = [1j, 1j, 1j, -1j, -1j, -1j, 1j, 1j, -1j]$.

[0070] $\mathbf{c}_2 = [-1, -1, -1, -1j, -1j, -1j, 1j, 1j, -1j]$.

[0071] $\mathbf{c}_3 = [-1, -1, -1, 1, 1, -1j, 1j, 1j, -1j]$.

[0072] $\mathbf{c}_4 = [-1, -1, -1, 1, 1, 1, 1j, 1j, -1j]$.

[0073] $\mathbf{c}_5 = [-1, -1, -1, 1, 1, 1, -1, 1j, -1j]$.

25 **[0074]** $\mathbf{c}_6 = [-1, -1, -1, 1, 1, 1, -1, -1, -1j]$.

[0075] $\mathbf{c}_7 = [-1, -1, -1, 1, 1, 1, -1, -1, 1]$.

30 **[0076]** That is, in the foregoing technical solution, a sequence under 4096-QAM modulation is implemented, so that channel quality of a communication link under 4096-QAM modulation can be accurately measured when the channel quality of the communication link is measured by using the sequence.

[0077] Optionally, with reference to the first aspect, the second aspect, the third aspect, or the fourth aspect, $\mathbf{a}_0$ is one of the first to 489th elements in the HE-LTF sequence, and $\mathbf{a}_1$ is one of the 504th to 1001st elements in the HE-LTF sequence. That is, the first sequence is generated based on the HE-LTF sequence in the 4x mode at an 80 MHz bandwidth in 802.11ax, so that the PAPR

of the first sequence is low.

[0078] Optionally, with reference to the first aspect, the second aspect, the third aspect, or the fourth aspect, the first sequence meets the following formula:

$$\mathbf{p}_u = [\mathbf{b}_0, \mathbf{d}_u, 0, 0, 0, 0, 0, (-1j) * \mathbf{b}_1].$$

5 **[0079]** The second sequence is the EHT-LTF sequence, $\mathbf{b}_0$ and $\mathbf{b}_1$ are subsequences in the EHT-LTF sequence, j is an imaginary unit, and u is an integer greater than or equal to 1 and less than or equal to 5.

[0080] $\mathbf{d}_1 = [1j, 1j, 1j, -1j, 1j, 1j].$

[0081] $\mathbf{d}_2 = [-1, 1j, 1j, -1j, 1j, 1j].$

10 **[0082]** $\mathbf{d}_3 = [-1, -1, -1, -1j, 1j, 1j].$

[0083] $\mathbf{d}_4 = [-1, -1, -1, 1, -1, 1j].$

[0084] $\mathbf{d}_5 = [-1, -1, -1, 1, -1, -1].$

[0085] That is, in the foregoing technical solution, a sequence under QPSK modulation is implemented, so that channel quality of a communication link under QPSK modulation can be
15 accurately measured when the channel quality of the communication link is measured by using the sequence.

[0086] Optionally, with reference to the first aspect, the second aspect, the third aspect, or the fourth aspect, the first sequence meets the following formula:

$$\mathbf{q}_6 = \frac{2}{\sqrt{5}} e^{\frac{j\pi}{4}} \mathbf{p}_{t1} + \frac{1}{\sqrt{5}} e^{\frac{j\pi}{4}} \mathbf{p}_{t2}.$$

20 **[0087]** $\mathbf{p}_{t1} = [\mathbf{b}_0, \mathbf{d}_{t1}, 0, 0, 0, 0, 0, (-1j) * \mathbf{b}_1]$; $\mathbf{p}_{t2} = [\mathbf{b}_0, \mathbf{d}_{t2}, 0, 0, 0, 0, 0, (-1j) * \mathbf{b}_1]$; and the second sequence is the EHT-LTF sequence, $\mathbf{b}_0$ and $\mathbf{b}_1$ are subsequences in the EHT-LTF sequence, and j is an imaginary unit.

[0088] $t1$ is 5, and $t2$ is 1, 2, 3, 4, or 5; or $t1$ is 1, and $t2$ is 5; or $t1$ is 4, and $t2$ is 5.

[0089] $\mathbf{d}_1 = [1j, 1j, 1j, -1j, 1j, 1j].$

25 **[0090]** $\mathbf{d}_2 = [-1, 1j, 1j, -1j, 1j, 1j].$

[0091] $\mathbf{d}_3 = [-1, -1, -1, -1j, 1j, 1j].$

[0092] $\mathbf{d}_4 = [-1, -1, -1, 1, -1, 1j].$

[0093] $\mathbf{d}_5 = [-1, -1, -1, 1, -1, -1].$

[0094] That is, in the foregoing technical solution, a sequence under 16-QAM modulation is
30 implemented, so that channel quality of a communication link under 16-QAM modulation can be accurately measured when the channel quality of the communication link is measured by using the sequence.

[0095] Optionally, with reference to the first aspect, the second aspect, the third aspect, or the fourth aspect, the first sequence meets the following formula:

$$\mathbf{q}_7 = \frac{4}{\sqrt{21}} e^{\frac{j\pi}{4}} \mathbf{p}_{t3} + \frac{2}{\sqrt{21}} e^{\frac{j\pi}{4}} \mathbf{p}_{t4} + \frac{1}{\sqrt{21}} e^{\frac{j\pi}{4}} \mathbf{p}_{t5}.$$

[0096] $\mathbf{p}_{t3} = [\mathbf{b}_0, \mathbf{d}_{t3}, 0, 0, 0, 0, 0, (-1j) * \mathbf{b}_1]$; $\mathbf{p}_{t4} = [\mathbf{b}_0, \mathbf{d}_{t4}, 0, 0, 0, 0, 0, (-1j) * \mathbf{b}_1]$; $\mathbf{p}_{t5} = [\mathbf{b}_0, \mathbf{d}_{t5}, 0, 0, 0, 0, 0, (-1j) * \mathbf{b}_1]$; and the second sequence is the EHT-LTF sequence, $\mathbf{b}_0$ and $\mathbf{b}_1$ are subsequences in the EHT-LTF sequence, and j is an imaginary unit.

5 **[0097]** $t3$ is 5, $t4$ is 5, and $t5$ is 1, 2, 3, 4, or 5; or $t3$ is 5, $t4$ is 1, and $t5$ is 5; or $t3$ is 5, $t4$ is 1, and $t5$ is 1.

[0098] $\mathbf{d}_1 = [1j, 1j, 1j, -1j, 1j, 1j]$.

[0099] $\mathbf{d}_2 = [-1, 1j, 1j, -1j, 1j, 1j]$.

[00100] $\mathbf{d}_3 = [-1, -1, -1, -1j, 1j, 1j]$.

10 **[00101]** $\mathbf{d}_4 = [-1, -1, -1, 1, -1, 1j]$.

[00102] $\mathbf{d}_5 = [-1, -1, -1, 1, -1, -1]$.

[00103] That is, in the foregoing technical solution, a sequence under 64-QAM modulation is implemented, so that channel quality of a communication link under 64-QAM modulation can be accurately measured when the channel quality of the communication link is measured by using the
15 sequence.

[00104] Optionally, with reference to the first aspect, the second aspect, the third aspect, or the fourth aspect, the first sequence meets the following formula:

$$\mathbf{q}_8 = \frac{8}{\sqrt{85}} e^{\frac{j\pi}{4}} \mathbf{p}_{t6} + \frac{4}{\sqrt{85}} e^{\frac{j\pi}{4}} \mathbf{p}_{t7} + \frac{2}{\sqrt{85}} e^{\frac{j\pi}{4}} \mathbf{p}_{t8} + \frac{1}{\sqrt{85}} e^{\frac{j\pi}{4}} \mathbf{p}_{t9}.$$

[00105] $\mathbf{p}_{t6} = [\mathbf{b}_0, \mathbf{d}_{t6}, 0, 0, 0, 0, 0, (-1j) * \mathbf{b}_1]$; $\mathbf{p}_{t7} = [\mathbf{b}_0, \mathbf{d}_{t7}, 0, 0, 0, 0, 0, (-1j) * \mathbf{b}_1]$; $\mathbf{p}_{t8} = [\mathbf{b}_0, \mathbf{d}_{t8}, 0, 0, 0, 0, 0, (-1j) * \mathbf{b}_1]$; $\mathbf{p}_{t9} = [\mathbf{b}_0, \mathbf{d}_{t9}, 0, 0, 0, 0, 0, (-1j) * \mathbf{b}_1]$; and the second sequence is the EHT-LTF sequence, $\mathbf{b}_0$ and $\mathbf{b}_1$ are subsequences in the EHT-LTF sequence, and j is an imaginary unit.

[00106] $t6$ is 5, $t7$ is 5, and $t8$ is 5, and $t9$ is 1, 2, 3, or 4; or $t6$ is 5, $t7$ is 5, $t8$ is 1, and $t9$ is 1, 4, or 5; or $t6$ is 5, $t7$ is 1, $t8$ is 5, and $t9$ is 5.

25 **[00107]** $\mathbf{d}_1 = [1j, 1j, 1j, -1j, 1j, 1j]$.

[00108] $\mathbf{d}_2 = [-1, 1j, 1j, -1j, 1j, 1j]$.

[00109] $\mathbf{d}_3 = [-1, -1, -1, -1j, 1j, 1j]$.

[00110] $\mathbf{d}_4 = [-1, -1, -1, 1, -1, 1j]$.

[00111] $\mathbf{d}_5 = [-1, -1, -1, 1, -1, -1]$.

30 **[00112]** That is, in the foregoing technical solution, a sequence under 256-QAM modulation is implemented, so that channel quality of a communication link under 256-QAM modulation can be accurately measured when the channel quality of the communication link is measured by using the sequence.

[00113] Optionally, with reference to the first aspect, the second aspect, the third aspect, or the

fourth aspect, the first sequence meets the following formula:

$$\mathbf{q}_9 = \frac{16}{\sqrt{341}} e^{\frac{j\pi}{4}} \mathbf{p}_{t10} + \frac{8}{\sqrt{341}} e^{\frac{j\pi}{4}} \mathbf{p}_{t11} + \frac{4}{\sqrt{341}} e^{\frac{j\pi}{4}} \mathbf{p}_{t12} + \frac{2}{\sqrt{341}} e^{\frac{j\pi}{4}} \mathbf{p}_{t13} + \frac{1}{\sqrt{345}} e^{\frac{j\pi}{4}} \mathbf{p}_{t14}.$$

[00114] $\mathbf{p}_{t10} = [\mathbf{b}_0, \mathbf{d}_{t10}, 0,0,0,0,0, (-1j) * \mathbf{b}_1]$; $\mathbf{p}_{t11} = [\mathbf{b}_0, \mathbf{d}_{t11}, 0,0,0,0,0, (-1j) * \mathbf{b}_1]$;
 $\mathbf{p}_{t12} = [\mathbf{b}_0, \mathbf{d}_{t12}, 0,0,0,0,0, (-1j) * \mathbf{b}_1]$; $\mathbf{p}_{t13} = [\mathbf{b}_0, \mathbf{d}_{t13}, 0,0,0,0,0, (-1j) * \mathbf{b}_1]$; $\mathbf{p}_{t14} =$
5 $[\mathbf{b}_0, \mathbf{d}_{t14}, 0,0,0,0,0, (-1j) * \mathbf{b}_1]$; and the second sequence is the EHT-LTF sequence, $\mathbf{b}_0$ and $\mathbf{b}_1$
are subsequences in the EHT-LTF sequence, and j is an imaginary unit.

[00115] t_{10} is 5, t_{11} is 5, t_{12} is 5, t_{13} is 1, and t_{14} is 2 or 4; or t_{10} is 5, t_{11} is 5,
 t_{12} is 5, t_{13} is 4, and t_{14} is 1 or 5; or t_{10} is 5, t_{11} is 5, t_{12} is 1, t_{13} is 5, and t_{14} is 1
or 5; or t_{10} is 5, t_{11} is 5, t_{12} is 1, t_{13} is 5, and t_{14} is 5; or t_{10} is 5, t_{11} is 5, t_{12} is 5,
10 t_{13} is 2, and t_{14} is 5; or t_{10} is 5, t_{11} is 5, t_{12} is 5, t_{13} is 1, and t_{14} is 3.

[00116] $\mathbf{d}_1 = [1j, 1j, 1j, -1j, 1j, 1j]$.

[00117] $\mathbf{d}_2 = [-1, 1j, 1j, -1j, 1j, 1j]$.

[00118] $\mathbf{d}_3 = [-1, -1, -1, -1j, 1j, 1j]$.

[00119] $\mathbf{d}_4 = [-1, -1, -1, 1, -1, 1j]$.

15 **[00120]** $\mathbf{d}_5 = [-1, -1, -1, 1, -1, -1]$.

[00121] That is, in the foregoing technical solution, a sequence under 1024-QAM modulation
is implemented, so that channel quality of a communication link under 1024-QAM modulation
can be accurately measured when the channel quality of the communication link is measured by
using the sequence.

20 **[00122]** Optionally, with reference to the first aspect, the second aspect, the third aspect, or the
fourth aspect, the first sequence meets the following formula:

$$\mathbf{q}_{10} = \frac{16}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{p}_{t15} + \frac{16}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{p}_{t16} + \frac{8}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{p}_{t17} + \frac{4}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{p}_{t18} +$$

$$\frac{2}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{p}_{t19} + \frac{1}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{p}_{t20}.$$

[00123] $\mathbf{p}_{t15} = [\mathbf{b}_0, \mathbf{d}_{t15}, 0,0,0,0,0, (-1j) * \mathbf{b}_1]$; $\mathbf{p}_{t16} = [\mathbf{b}_0, \mathbf{d}_{t16}, 0,0,0,0,0, (-1j) * \mathbf{b}_1]$;
25 $\mathbf{p}_{t17} = [\mathbf{b}_0, \mathbf{d}_{t17}, 0,0,0,0,0, (-1j) * \mathbf{b}_1]$; $\mathbf{p}_{t18} = [\mathbf{b}_0, \mathbf{d}_{t18}, 0,0,0,0,0, (-1j) * \mathbf{b}_1]$; $\mathbf{p}_{t19} =$
 $[\mathbf{b}_0, \mathbf{d}_{t19}, 0,0,0,0,0, (-1j) * \mathbf{b}_1]$; $\mathbf{p}_{t20} = [\mathbf{b}_0, \mathbf{d}_{t20}, 0,0,0,0,0, (-1j) * \mathbf{b}_1]$; and the second
sequence is the EHT-LTF sequence, $\mathbf{b}_0$ and $\mathbf{b}_1$ are subsequences in the EHT-LTF sequence, and
 j is an imaginary unit.

[00124] t_{15} is 5, t_{16} is 5, t_{17} is 5, t_{18} is 1, t_{19} is 2, and t_{20} is 5; or t_{15} is 5, t_{16} is
30 5, t_{17} is 5, t_{18} is 1, t_{19} is 1, and t_{20} is 3; or t_{15} is 5, t_{16} is 5, t_{17} is 1, t_{18} is 5, t_{19}
is 5, and t_{20} is 1; or t_{15} is 5, t_{16} is 5, t_{17} is 5, t_{18} is 5, t_{19} is 3, and t_{20} is 3; or t_{15}
is 5, t_{16} is 5, t_{17} is 5, t_{18} is 1, t_{19} is 1, and t_{20} is 2; or t_{15} is 5, t_{16} is 5, t_{17} is 5,
 t_{18} is 1, t_{19} is 4, and t_{20} is 1; or t_{15} is 5, t_{16} is 5, t_{17} is 5, t_{18} is 4, t_{19} is 5, and t_{20}

is 1; or t_{15} is 5, t_{16} is 5, t_{17} is 5, t_{18} is 1, t_{19} is 4, and t_{20} is 5.

[00125] $\mathbf{d}_1 = [1j, 1j, 1j, -1j, 1j, 1j]$.

[00126] $\mathbf{d}_2 = [-1, 1j, 1j, -1j, 1j, 1j]$.

[00127] $\mathbf{d}_3 = [-1, -1, -1, -1j, 1j, 1j]$.

5 **[00128]** $\mathbf{d}_4 = [-1, -1, -1, 1, -1, 1j]$.

[00129] $\mathbf{d}_5 = [-1, -1, -1, 1, -1, -1]$.

[00130] That is, in the foregoing technical solution, a sequence under 4096-QAM modulation is implemented, so that channel quality of a communication link under 4096-QAM modulation can be accurately measured when the channel quality of the communication link is measured by
10 using the sequence.

[00131] Optionally, with reference to the first aspect, the second aspect, the third aspect, or the fourth aspect, $\mathbf{b}_0$ is one of the first to 492nd elements in the EHT-LTF sequence, and $\mathbf{b}_1$ is one of the 504th to 1001st elements in the EHT-LTF sequence. That is, the first sequence is generated based on the EHT-LTF sequence in the 4x mode at an 80 MHz bandwidth in 802.11be, so that the
15 PAPR of the first sequence is low.

[00132] According to a fifth aspect, a chip is provided. The chip includes at least one logic circuit and an input/output interface. The logic circuit is configured to read and execute stored instructions. When the instructions are run, the chip is enabled to perform the method according to either the first aspect or the second aspect.

20 **[00133]** According to a sixth aspect, a computer-readable storage medium is provided. The computer-readable storage medium stores a computer program. The computer program includes program instructions, and when the program instructions are executed by a computer, the computer is enabled to perform the method according to either the first aspect or the second aspect.

[00134] According to a seventh aspect, a communication apparatus is provided, including a
25 processor and a transceiver. The processor is configured to support the communication apparatus in performing a corresponding function in the method in the first aspect or the second aspect. The transceiver is configured to support communication between the communication apparatus and another communication apparatus other than the communication apparatus. The communication apparatus may further include a memory. The memory is configured to be coupled to the processor,
30 and the memory stores program instructions and data that are necessary for the communication apparatus. The transceiver may be integrated into the communication apparatus or independent of the communication apparatus. This is not limited herein.

[00135] According to an eighth aspect, a computer program product including instructions is provided. When the computer program product is run on a computer, the computer is enabled to
35 perform the method according to either the first aspect or the second aspect.

[00136] According to a ninth aspect, a communication system is provided, including the first device and/or the second device described above.

BRIEF DESCRIPTION OF DRAWINGS

[00137] The following briefly describes accompanying drawings used in describing
5 embodiments.

[00138] FIG. 1 is a schematic diagram of an 80 MHz tone plan (tone plan) in 802.11ax according to an embodiment of this application;

[00139] FIG. 2 is a schematic diagram of a frame structure of a sounding frame according to an embodiment of this application;

10 [00140] FIG. 3 is a schematic diagram of an 80 MHz tone plan in 802.11be according to an embodiment of this application;

[00141] FIG. 4 is a diagram of a network architecture of a wireless local area network (wireless local area network, WLAN) according to an embodiment of this application;

15 [00142] FIG. 5 is a schematic diagram of a hardware structure of a communication apparatus that may be used in an embodiment of this application;

[00143] FIG. 6 is a schematic flowchart of a sounding frame transmission method according to an embodiment of this application;

[00144] FIG. 7 is a schematic diagram of a frame structure of a sounding frame according to an embodiment of this application; and

20 [00145] FIG. 8 is a schematic diagram of a structure of a communication apparatus according to an embodiment of this application.

DESCRIPTION OF EMBODIMENTS

[00146] The following describes technical solutions in embodiments of this application with reference to accompanying drawings in embodiments of this application. The terms "system" and
25 "network" may be used interchangeably in embodiments of this application. Unless otherwise specified, "/" represents an "or" relationship between associated objects. For example, A/B may represent A or B. The term "and/or" in this application is merely an association relationship for describing associated objects, and represents that three relationships may exist. For example, A and/or B may represent the following three cases: Only A exists, both A and B exist, and only B
30 exists, where A and B may be singular or plural. In addition, in descriptions of this application, unless otherwise specified, "a plurality of" means two or more than two. "At least one of the following" or similar expressions thereof refer to any combination of these items, including any

combination of single items or a plurality of items. For example, at least one of a, b, or c may represent a, b, c, a and b, a and c, b and c, or a, b, and c, where a, b, and c may be singular or plural. In addition, to clearly describe technical solutions in embodiments of this application, terms such as "first" and "second" are used in embodiments of this application to distinguish between same items or similar items that have basically same network elements or purposes. A person skilled in the art may understand that the terms such as "first" and "second" do not limit a quantity or an execution sequence, and the terms such as "first" and "second" do not indicate a definite difference.

[00147] Reference to "an embodiment", "some embodiments", or the like described in embodiments of this application indicates that one or more embodiments of this application include a specific feature, structure, or characteristic described with reference to embodiments. Therefore, statements such as "in an embodiment", "in some embodiments", "in some other embodiments", and "in other embodiments" that appear at different places in this specification do not necessarily refer to a same embodiment. Instead, the statements mean "one or more but not all of embodiments", unless otherwise specifically emphasized in another manner. The terms "include", "comprise", "have", and their variants mean "including but not limited to" unless especially emphasized otherwise.

[00148] The objectives, technical solutions, and beneficial effects of this application are further described in detail in the following specific implementations. It should be understood that the following descriptions are merely specific implementations of this application, but are not intended to limit the protection scope of this application. Any modification, equivalent replacement, or improvement made based on technical solutions of this application shall fall within the protection scope of this application.

[00149] In various embodiments of this application, unless otherwise stated or there is a logic conflict, terms and/or descriptions in different embodiments are consistent and may be mutually referenced, and technical features in different embodiments may be combined based on an internal logical relationship thereof, to form a new embodiment.

[00150] The following explains and describes some nouns (or communication terms) in this application.

[00151] 1. 802.11ax tone plan

[00152] It should be noted that, in this solution, a high efficiency long training field (high efficiency long training field, HE-LTF) sequence at an 80 MHz bandwidth in 802.11ax is modified. Therefore, only an 80 MHz tone plan (tone plan) in 802.11ax is described herein. FIG. 1 is a schematic diagram of an 80 MHz tone plan (tone plan) in 802.11ax according to an embodiment of this application. FIG. 1 shows an 80 MHz tone design in 802.11ax. As shown in FIG. 1, the 80 MHz bandwidth of 802.11ax includes 36 resource units (resource units, RUs) 26, or includes 16

RU52s, or includes eight RU106s, or includes four RU242s, or includes one RU996 and five direct current tones. There is no gap between a first RU242 and a second RU242. There are seven direct current tones/null tones between the second RU242 and a third RU242. There is also no gap between the third RU242 and a fourth RU242. It may be understood that an RU26 may be a resource unit including 26 consecutive tones. That is, the RU26 includes 24 data tones and two pilot (pilot) tones. Similarly, an RU52 may be a resource unit including 52 consecutive tones. That is, the RU52 includes 48 data tones and four pilot pilot tones. An RU106 may be a resource unit including 106 consecutive tones. That is, the RU106 includes 24 data tones and two pilot pilot tones. An RU242 may be a resource unit including 242 consecutive tones. That is, the RU242 includes 234 data tones and eight pilot pilot tones. An RU484 may be a resource unit including 484 consecutive tones. That is, the RU484 includes 468 data tones and 16 pilot pilot tones. An RU996 may be a resource unit including 996 consecutive tones. That is, the RU996 includes 980 data tones and 16 pilot tones.

[00153] Based on the 80 MHz tone design shown in FIG. 1, an HE-LTF sequence used for channel estimation is specified in 802.11ax, and a corresponding sounding frame format is defined.

[00154] FIG. 2 is a schematic diagram of a frame structure of a sounding frame according to an embodiment of this application. As shown in FIG. 2, the sounding frame includes a legacy short training field (legacy short training field, L-STF), a legacy long training field (legacy long training field, L-LTF), a legacy signal field (legacy signal field, L-SIG), a repeated legacy signal field (repeated legacy signal field, RL-SIG), a high efficiency signal A field (high efficiency signal A field, HE-SIG-A), a high efficiency short training field (high efficiency short training field, HE-STF), a high efficiency long training field (high efficiency long training field, HE-LTF), and a packet extension (packet extension, PE) field.

[00155] In FIG. 2, the HE-LTF field included in the sounding frame is a high efficiency long training field used for multiple-input multiple-output (multiple input multiple output, MIMO) channel estimation. The field may include one or more HE-LTF symbols, and each symbol is an orthogonal frequency division multiple access (orthogonal frequency division multiple access, OFDMA) symbol.

[00156] Two modes, namely, a 2x mode and a 4x mode are used in the HE-LTF sequence used for channel estimation in an 802.11ax system. Because this application relates to only the 4x mode, only the 4x mode is described herein. It may be understood that the 4x mode in the 802.11ax system means that a tone index (index) to which the HE-LTF sequence is mapped is the same as a sequence number of a tone in a tone plan (tone plan) of a data portion.

[00157] 2. 802.11be tone plan

[00158] It should be noted that, in this solution, an EHT-LTF sequence at an 80 MHz bandwidth

in 802.11be is modified. Therefore, only an 80 MHz tone plan in 802.11be is described herein. FIG. 3 is a schematic diagram of an 80 MHz tone plan in 802.11be according to an embodiment of this application. FIG. 3 shows an 80 MHz tone design in 802.11be. As shown in FIG. 3, the 80 MHz bandwidth of 802.11be includes 36 RU26s, or includes 16 RU52s, or includes eight RU106s, or includes four RU242s, or includes two RU484s and five direct current tones/null tones, or includes one RU996 and five direct current tones. There are five direct current tones between a first RU242 and a second RU242. There are also five direct current tones between a third RU242 and a fourth RU242.

[00159] It should be noted that, for a case of a tone plan at a larger bandwidth, for example, 160 MHz or 320 MHz, the tone plan may be obtained after the 80 MHz tone plan is replicated and phase-rotated. This is not limited herein.

[00160] 3. 4x mode

[00161] A 4x mode in an 802.11ax system may mean that a tone index (index) to which an HE-LTF sequence is mapped is the same as a sequence number of a tone in a tone plan (tone plan) of a data portion. A 4x mode in an 802.11be system may mean that a tone index (index) to which an EHT-LTF sequence is mapped is the same as a sequence number of a tone in a tone plan (tone plan) of a data portion.

[00162] The foregoing content briefly describes meanings of nouns (communication terms) in embodiments of this application to better understand the technical solutions provided in embodiments of this application, and does not constitute a limitation on the technical solutions provided in embodiments of this application.

[00163] It should be understood that embodiments of this application may be applied to a wireless local area network (wireless local area network, WLAN) scenario, and may be applied to an IEEE 802.11 system standard, for example, 802.11ax, 802.11be, or a next-generation standard. Alternatively, embodiments of this application may be applied to a wireless local area network system, for example, an internet of things (internet of things, IoT) network or a vehicle-to-everything (Vehicle to X, V2X) network. Certainly, embodiments of this application may be further applied to another possible communication system, for example, an LTE system, an LTE frequency division duplex (frequency division duplex, FDD) system, an LTE time division duplex (time division duplex, TDD) system, a universal mobile telecommunication system (universal mobile telecommunication system, UMTS), a worldwide interoperability for microwave access (worldwide interoperability for microwave access, WiMAX) communication system, and a future 6G communication system.

[00164] The following uses an example in which embodiments of this application are applicable to a WLAN scenario. It should be understood that the WLAN starts from the 802.11a/g standard,

and develops to 802.11n, 802.11ac, 802.11ax, and 802.11be that is currently being discussed. 802.11n may also be referred to as high throughput (high throughput, HT). 802.11ac may also be referred to as very high throughput (very high throughput, VHT). 802.11ax may also be referred to as high efficiency (high efficiency, HE) or Wi-Fi 6. 802.11be may also be referred to as extremely high throughput (extremely high throughput, EHT) or (Wi-Fi 7). Standards before HT, such as 802.11a/b/g, are collectively referred to as non-high throughput (Non-HT).

[00165] FIG. 4 is a diagram of a network architecture of a WLAN according to an embodiment of this application. In FIG. 4, an example in which the WLAN includes one wireless access point (access point, AP) and two stations (stations, STAs) is used. A STA associated with an AP can receive a radio frame sent by the AP, and can also send a radio frame to the AP. In addition, embodiments of this application are also applicable to communication between APs. For example, the APs may communicate with each other by using a distributed system (distributed system, DS). Embodiments of this application are also applicable to communication between STAs. It should be understood that quantities of APs and STAs in FIG. 4 are merely an example. There may be more or less APs and STAs.

[00166] The access point may be an access point used by a terminal device (such as a mobile phone) to access a wired (or wireless) network, and is mainly deployed at home, in a building, and in a park. A typical coverage radius is tens of meters to hundreds of meters. Certainly, the access point may alternatively be deployed outdoors. The access point is equivalent to a bridge that connects the wired network and the wireless network. A main function of the access point is to connect various wireless network clients together and then connect the wireless network to the Ethernet. Specifically, the access point may be a terminal device (for example, a mobile phone) or a network device (for example, a router) with a Wi-Fi chip. The access point may be a device that supports the 802.11be standard. Alternatively, the access point may be a device that supports a plurality of wireless local area network (wireless local area networks, WLAN) standards of the 802.11 family such as 802.11ax, 802.11ac, 802.11n, 802.11g, 802.11b, 802.11a, and the 802.11be next-generation. The access point in this application may be a high efficiency (high efficiency, HE) AP, an extremely high throughput (extremely high throughput, EHT) AP, or an access point applicable to a future generation Wi-Fi standard.

[00167] The STA in this embodiment of this application may be various user terminals, user apparatuses, access apparatuses, subscriber stations, subscriber units, mobile stations, user agents, user devices, or other names that have a wireless communication function. The user terminal may include various handheld devices, vehicle-mounted devices, wearable devices, computing devices, or other processing devices connected to a wireless modem that have a wireless communication function; and various forms of user equipment (user equipment, UE), mobile stations (mobile

stations, MS's), terminals (terminals), terminal equipment (terminal equipment), portable communication devices, handheld devices, portable computing devices, entertainment devices, game devices or systems, global positioning system devices, any other suitable device configured to perform network communication through a wireless medium, or the like. For example, the STA
5 may be a router, a switch, a bridge, or the like. Herein, for ease of description, the devices mentioned above are collectively referred to as a station or a STA.

[00168] The AP and the STA in embodiments of this application may be an AP and a STA that are applicable to an IEEE 802.11 system standard. The AP is an apparatus that is deployed in a wireless communication network and that provides a wireless communication function for a STA
10 associated with the AP. The AP may be used as a center of the communication system, and is usually a network-side product that supports MAC and PHY in the 802.11 system standard, for example, may be a communication device such as a base station, a router, a gateway, a repeater, a communication server, a switch, or a bridge. The base station may include various forms of macro base stations, micro base stations, relay stations, or the like. Herein, for ease of description, the
15 devices mentioned above are collectively referred to as an AP. The STA is usually a terminal product that supports media access control (media access control, MAC) and a physical layer (physical, PHY) of the 802.11 system standard, for example, a mobile phone or a notebook computer.

[00169] A sounding frame transmission method provided in this application may be applied to
20 a wireless communication system. The wireless communication system may be a wireless local area network (Wireless local area network) or a cellular network. The method may be implemented by a communication device in a wireless communication system or a chip or a processor in a communication device. The communication device may be a wireless communication device that supports parallel transmission of a plurality of links, for example, referred to as a multi-link device
25 (Multi-link device) or a multi-band device (multi-band device). Compared with a device that supports only single-link transmission, the multi-link device has higher transmission efficiency and higher throughput. The multi-link device includes one or more affiliated stations STAs (affiliated STAs). The affiliated STA is a logical station and can work on a same link. The affiliated station may be an access point (Access Point, AP) or a non-access point station (non-Access Point
30 Station, non-AP STA). For ease of description, in this application, a multi-link device whose station is an AP may be referred to as a multi-link AP, a multi-link AP device, or an AP multi-link device (AP multi-link device), and a multi-link device whose station is a non-AP STA may be referred to as a multi-link STA, a multi-link STA device, or a STA multi-link device (STA multi-link device).

[00170] In addition, the technical solutions provided in embodiments of this application are

applicable to a plurality of system architectures. Network architectures and service scenarios described in embodiments of this application are intended to more clearly describe the technical solutions in embodiments of this application, but are not intended to limit the technical solutions provided in embodiments of this application. A person of ordinary skill in the art may know that as the network architectures evolve and a new service scenario emerges, the technical solutions provided in embodiments of this application are also applicable to a similar technical problem.

[00171] Optionally, the wireless access point, the station, and the like in FIG. 4 may be implemented by one device, or may be jointly implemented by a plurality of devices, or may be a functional module in one device. This is not specifically limited in this embodiment of this application. It may be understood that the foregoing functions may be network elements in a hardware device, or may be software functions running on dedicated hardware, or may be virtualization functions instantiated on a platform (for example, a cloud platform).

[00172] For example, each device in FIG. 4 may be implemented by a communication apparatus 500 in FIG. 5. FIG. 5 is a schematic diagram of a hardware structure of a communication apparatus that may be used in an embodiment of this application. The communication apparatus 500 includes at least one processor 501, a communication line 502, a memory 503, and at least one communication interface 504.

[00173] The processor 501 may be a general-purpose central processing unit (central processing unit, CPU), a microprocessor, an application-specific integrated circuit (application-specific integrated circuit, ASIC), or one or more integrated circuits configured to control program execution in the solutions of this application.

[00174] The communication line 502 may include a path for transmitting information between the foregoing components.

[00175] The communication interface 504 is any apparatus (such as an antenna) of a transceiver type, and is configured to communicate with another device or a communication network, such as the Ethernet, a RAN, or a wireless local area network (wireless local area network, WLAN).

[00176] The memory 503 may be a read-only memory (read-only memory, ROM) or another type of static storage device that can store static information and instructions, a random access memory (random access memory, RAM), or another type of dynamic storage device that can store information and instructions, or may be an electrically erasable programmable read-only memory (electrically erasable programmable read-only memory, EEPROM), a compact disc read-only memory (compact disc read-only memory, CD-ROM), or another optical disc storage, an optical disc storage (including a compact disc, a laser disc, an optical disc, a digital versatile disc, a Blu-ray disc, and the like), a magnetic disk storage medium or another magnetic storage device, or any other medium that can be used to carry or store expected program code in instructions or data

structure form and that can be accessed by a computer, which is not limited thereto. The memory may exist independently, and is connected to the processor through the communication line 502. Alternatively, the memory may be integrated with the processor. The memory provided in embodiments of this application may be usually non-volatile. The memory 503 is configured to store computer-executable instructions for performing the solutions in this application, and the processor 501 controls execution of the computer-executable instructions. The processor 501 is configured to execute the computer-executable instructions stored in the memory 503, to implement a method provided in the following embodiments of this application.

[00177] Optionally, the computer-executable instructions in this embodiment of this application may also be referred to as application program code. This is not specifically limited in this embodiment of this application.

[00178] In a possible implementation, the processor 501 may include one or more CPUs, for example, a CPU 0 and a CPU 1 in FIG. 5.

[00179] In a possible implementation, the communication apparatus 500 may include a plurality of processors, for example, the processor 501 and a processor 507 in FIG. 5. Each of the processors may be a single-core (single-CPU) processor, or may be a multi-core (multi-CPU) processor. The processor herein may be one or more devices, circuits, and/or processing cores configured to process data (for example, computer program instructions).

[00180] In a possible implementation, the communication apparatus 500 may further include an output device 505 and an input device 506. The output device 505 communicates with the processor 501, and may display information in a plurality of manners. For example, the output device 505 may be a liquid crystal display (liquid crystal display, LCD), a light emitting diode (light emitting diode, LED) display device, a cathode ray tube (cathode ray tube, CRT) display device, a projector (projector), or the like. The input device 506 communicates with the processor 501, and may receive a user input in a plurality of manners. For example, the input device 506 may be a mouse, a keyboard, a touchscreen device, a sensing device, or the like.

[00181] The communication apparatus 500 may be a general-purpose device or a dedicated device. During specific implementation, the communication apparatus 500 may be a portable computer, a network server, a palmtop computer (personal digital assistant, PDA), a mobile phone, a tablet computer, a wireless terminal device, an embedded device, or a device having a structure similar to that in FIG. 5. A type of the communication apparatus 500 is not limited in this embodiment of this application.

[00182] After the communication apparatus is powered on, the processor 501 may read the software program in the memory 503, interpret and execute instructions of the software program, and process data of the software program. When data needs to be sent in a wireless manner, the

processor 501 performs baseband processing on the to-be-sent data, and then outputs a baseband signal to a radio frequency circuit. The radio frequency circuit performs radio frequency processing on the baseband signal, and then sends a radio frequency signal in an electromagnetic wave form by using the antenna. When data is sent to the communication apparatus, the radio frequency circuit receives a radio frequency signal by using the antenna, converts the radio frequency signal into a baseband signal, and outputs the baseband signal to the processor 501. The processor 501 converts the baseband signal into data and processes the data.

[00183] In another implementation, the radio frequency circuit and the antenna may be disposed independently of the processor for baseband processing. For example, in a distributed scenario, the radio frequency circuit and the antenna may be disposed remotely independent of the communication apparatus.

[00184] The following describes the technical solutions provided in embodiments of this application with reference to the accompanying drawings. It may be understood that a first device may be the AP in FIG. 4, and a second device may be the AP or the STA in FIG. 4; or the first device may be the STA in FIG. 4, and the second device may also be the STA in FIG. 4. This is not limited herein. The following describes the technical solutions provided in embodiments of this application by using an example in which the first device is an AP and the second device is a STA.

[00185] FIG. 6 is a schematic flowchart of a sounding frame transmission method according to an embodiment of this application. As shown in FIG. 6, the method includes but is not limited to the following steps.

[00186] 601: The first device generates a sounding frame, where the sounding frame includes a first field, the first field includes a predefined first sequence, the first sequence includes a sequence obtained after a second sequence is modulated by using at least one of the following modulation modes, and the modulation modes include: quadrature phase shift keying (quadrature phase shift keying, QPSK), 16-quadrature amplitude modulation (quadrature amplitude modulation, QAM), 64-QAM, 256-QAM, 1024-QAM, and 4096-QAM.

[00187] For a frame structure of the sounding frame, refer to FIG. 2 or FIG. 7. Details are not described herein again.

[00188] Optionally, the first field may be an HE-LTF field in FIG. 2, or the first field may be an LTF field in FIG. 7. This is not limited herein. For example, in 802.11ax, the first field is the HE-LTF field in FIG. 2, and in 802.11be, the first field is the LTF field in FIG. 7.

[00189] That the first sequence includes a sequence obtained after a second sequence is modulated by using at least one of the following modulation modes may be understood as that the first sequence includes at least one of the following: a sequence obtained after the second sequence

QPSK modulation can be accurately measured when the channel quality of the communication link is measured by using the sequence.

[00196] Manner 2: The first sequence meets the following formula (2):

$$\mathbf{q}_1 = \frac{2}{\sqrt{5}} e^{\frac{j\pi}{4}} \mathbf{s}_{k1} + \frac{1}{\sqrt{5}} e^{\frac{j\pi}{4}} \mathbf{s}_{k2} \quad (2).$$

5 **[00197]** $\mathbf{s}_{k1} = [\mathbf{a}_0, \mathbf{c}_{k1}, 0, 0, 0, 0, 0, (-1j) * \mathbf{a}_1]$; and $\mathbf{s}_{k2} = [\mathbf{a}_0, \mathbf{c}_{k2}, 0, 0, 0, 0, 0, (-1j) * \mathbf{a}_1]$.

[00198] $k1$ is 1, and $k2$ is 7; or $k1$ is 4, and $k2$ is 5 or 6; or $k1$ is 5, and $k2$ is 1 or 2. That is, a sequence under 16-QAM modulation is implemented, so that channel quality of a communication link under 16-QAM modulation can be accurately measured when the channel quality of the communication link is measured by using the sequence.

10 **[00199]** Manner 3: The first sequence meets the following formula (3):

$$\mathbf{q}_2 = \frac{4}{\sqrt{21}} e^{\frac{j\pi}{4}} \mathbf{s}_{k3} + \frac{2}{\sqrt{21}} e^{\frac{j\pi}{4}} \mathbf{s}_{k4} + \frac{1}{\sqrt{21}} e^{\frac{j\pi}{4}} \mathbf{s}_{k5} \quad (3).$$

[00200] $\mathbf{s}_{k3} = [\mathbf{a}_0, \mathbf{c}_{k3}, 0, 0, 0, 0, 0, (-1j) * \mathbf{a}_1]$; $\mathbf{s}_{k4} = [\mathbf{a}_0, \mathbf{c}_{k4}, 0, 0, 0, 0, 0, (-1j) * \mathbf{a}_1]$; and $\mathbf{s}_{k5} = [\mathbf{a}_0, \mathbf{c}_{k5}, 0, 0, 0, 0, 0, (-1j) * \mathbf{a}_1]$.

[00201] $k3$ is 1, $k4$ is 6, and $k5$ is 7; or $k3$ is 1, $k4$ is 7, and $k5$ is 5 or 6; or $k3$ is 2, $k4$ is 7, and $k5$ is 6 or 7; or $k3$ is 3, $k4$ is 5, and $k5$ is 6; or $k3$ is 3, $k4$ is 5, and $k5$ is 7; or $k3$ is 3, $k4$ is 6, and $k5$ is 5 or 6; or $k3$ is 3, $k4$ is 7, and $k5$ is 1, 2, 3, or 4; or $k3$ is 4, $k4$ is 4, and $k5$ is 7; or $k3$ is 4, $k4$ is 5, and $k5$ is 3, 4, or 5; or $k3$ is 4, $k4$ is 6, and $k5$ is 1, 2, 3, or 4; or $k3$ is 5, $k4$ is 1, and $k5$ is 3 or 4; or $k3$ is 5, $k4$ is 1, and $k5$ is 5; or $k3$ is 5, $k4$ is 2, and $k5$ is 4, 5, or 6; or $k3$ is 5, $k4$ is 3, and $k5$ is 1, 2, 3, or 4; or $k3$ is 5, $k4$ is 4, and $k5$ is 1 or 2; or $k3$ is 6, $k4$ is 1, and $k5$ is 1 or 2; or $k3$ is 6, $k4$ is 2, and $k5$ is 1, 2, or 3. That is, a sequence under 64-QAM modulation is implemented, so that channel quality of a communication link under 64-QAM modulation can be accurately measured when the channel quality of the communication link is measured by using the sequence.

[00202] Manner 4: The first sequence meets the following formula (4):

25
$$\mathbf{q}_3 = \frac{8}{\sqrt{85}} e^{\frac{j\pi}{4}} \mathbf{s}_{k6} + \frac{4}{\sqrt{85}} e^{\frac{j\pi}{4}} \mathbf{s}_{k7} + \frac{2}{\sqrt{85}} e^{\frac{j\pi}{4}} \mathbf{s}_{k8} + \frac{1}{\sqrt{85}} e^{\frac{j\pi}{4}} \mathbf{s}_{k9} \quad (4).$$

[00203] $\mathbf{s}_{k6} = [\mathbf{a}_0, \mathbf{c}_{k6}, 0, 0, 0, 0, 0, (-1j) * \mathbf{a}_1]$; $\mathbf{s}_{k7} = [\mathbf{a}_0, \mathbf{c}_{k7}, 0, 0, 0, 0, 0, (-1j) * \mathbf{a}_1]$; $\mathbf{s}_{k8} = [\mathbf{a}_0, \mathbf{c}_{k8}, 0, 0, 0, 0, 0, (-1j) * \mathbf{a}_1]$; and $\mathbf{s}_{k9} = [\mathbf{a}_0, \mathbf{c}_{k9}, 0, 0, 0, 0, 0, (-1j) * \mathbf{a}_1]$.

[00204] $k6$ is 1, $k7$ is 7, $k8$ is 4, and $k9$ is 7; or $k6$ is 1, $k7$ is 7, $k8$ is 6, and $k9$ is 3; or $k6$ is 2, $k7$ is 7, $k8$ is 7, and $k9$ is 4; or $k6$ is 3, $k7$ is 5, $k8$ is 7, and $k9$ is 4; or $k6$ is 3, $k7$ is 6, $k8$ is 5, and $k9$ is 5; or $k6$ is 3, $k7$ is 7, $k8$ is 1, and $k9$ is 5; or $k6$ is 3, $k7$ is 7, $k8$ is 2, and $k9$ is 6; or $k6$ is 3, $k7$ is 7, $k8$ is 3, and $k9$ is 4; or $k6$ is 4, $k7$ is 4, $k8$ is 6, and $k9$ is 7; or $k6$ is 4, $k7$ is 6, $k8$ is 1, and $k9$ is 6; or $k6$ is 4, $k7$ is 6, $k8$ is 4, and $k9$ is 3; or $k6$ is 5, $k7$ is 1, $k8$ is 1, and $k9$ is 7; or $k6$ is 5, $k7$ is 2, $k8$ is 6, and $k9$ is 2;

or k_6 is 5, k_7 is 4, k_8 is 1, and k_9 is 1; or k_6 is 5, k_7 is 4, k_8 is 2, and k_9 is 3; or k_6 is 6, k_7 is 1, k_8 is 1, and k_9 is 1. That is, a sequence under 256-QAM modulation is implemented, so that channel quality of a communication link under 256-QAM modulation can be accurately measured when the channel quality of the communication link is measured by using the sequence.

[00205] Manner 5: The first sequence meets the following formula (5):

$$\mathbf{q}_4 = \frac{16}{\sqrt{341}} e^{\frac{j\pi}{4}} \mathbf{s}_{k_{10}} + \frac{8}{\sqrt{341}} e^{\frac{j\pi}{4}} \mathbf{s}_{k_{11}} + \frac{4}{\sqrt{341}} e^{\frac{j\pi}{4}} \mathbf{s}_{k_{12}} + \frac{2}{\sqrt{341}} e^{\frac{j\pi}{4}} \mathbf{s}_{k_{13}} + \frac{1}{\sqrt{345}} e^{\frac{j\pi}{4}} \mathbf{s}_{k_{14}} \quad (5).$$

[00206] $\mathbf{s}_{k_{10}} = [\mathbf{a}_0, \mathbf{c}_{k_{10}}, 0, 0, 0, 0, 0, (-1j) * \mathbf{a}_1]$; $\mathbf{s}_{k_{11}} = [\mathbf{a}_0, \mathbf{c}_{k_{11}}, 0, 0, 0, 0, 0, (-1j) * \mathbf{a}_1]$; $\mathbf{s}_{k_{12}} = [\mathbf{a}_0, \mathbf{c}_{k_{12}}, 0, 0, 0, 0, 0, (-1j) * \mathbf{a}_1]$; $\mathbf{s}_{k_{13}} = [\mathbf{a}_0, \mathbf{c}_{k_{13}}, 0, 0, 0, 0, 0, (-1j) * \mathbf{a}_1]$; and $\mathbf{s}_{k_{14}} = [\mathbf{a}_0, \mathbf{c}_{k_{14}}, 0, 0, 0, 0, 0, (-1j) * \mathbf{a}_1]$.

[00207] k_{10} is 1, k_{11} is 7, k_{12} is 6, k_{13} is 1, and k_{14} is 5; or k_{10} is 2, k_{11} is 7, k_{12} is 5, k_{13} is 7, and k_{14} is 5; or k_{10} is 6, k_{11} is 1, k_{12} is 2, k_{13} is 4, and k_{14} is 4; or k_{10} is 4, k_{11} is 6, k_{12} is 4, k_{13} is 1, and k_{14} is 6; or k_{10} is 6, k_{11} is 2, k_{12} is 1, k_{13} is 4, and k_{14} is 5; or k_{10} is 3, k_{11} is 6, k_{12} is 7, k_{13} is 1, and k_{14} is 2; or k_{10} is 5, k_{11} is 3, k_{12} is 1, k_{13} is 6, and k_{14} is 1; or k_{10} is 4, k_{11} is 6, k_{12} is 2, k_{13} is 6, and k_{14} is 6. That is, a sequence under 1024-QAM modulation is implemented, so that channel quality of a communication link under 1024-QAM modulation can be accurately measured when the channel quality of the communication link is measured by using the sequence.

[00208] Manner 6: The first sequence meets the following formula (6):

$$\mathbf{q}_5 = \frac{16}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{s}_{k_{15}} + \frac{16}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{s}_{k_{16}} + \frac{8}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{s}_{k_{17}} + \frac{4}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{s}_{k_{18}} + \frac{2}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{s}_{k_{19}} + \frac{1}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{s}_{k_{20}} \quad (6).$$

[00209] $\mathbf{s}_{k_{15}} = [\mathbf{a}_0, \mathbf{c}_{k_{15}}, 0, 0, 0, 0, 0, (-1j) * \mathbf{a}_1]$; $\mathbf{s}_{k_{16}} = [\mathbf{a}_0, \mathbf{c}_{k_{16}}, 0, 0, 0, 0, 0, (-1j) * \mathbf{a}_1]$; $\mathbf{s}_{k_{17}} = [\mathbf{a}_0, \mathbf{c}_{k_{17}}, 0, 0, 0, 0, 0, (-1j) * \mathbf{a}_1]$; $\mathbf{s}_{k_{18}} = [\mathbf{a}_0, \mathbf{c}_{k_{18}}, 0, 0, 0, 0, 0, (-1j) * \mathbf{a}_1]$; $\mathbf{s}_{k_{19}} = [\mathbf{a}_0, \mathbf{c}_{k_{19}}, 0, 0, 0, 0, 0, (-1j) * \mathbf{a}_1]$; and $\mathbf{s}_{k_{20}} = [\mathbf{a}_0, \mathbf{c}_{k_{20}}, 0, 0, 0, 0, 0, (-1j) * \mathbf{a}_1]$.

[00210] k_{15} is 5, k_{16} is 2, k_{17} is 4, k_{18} is 7, k_{19} is 2, and k_{20} is 5; or k_{15} is 5, k_{16} is 2, k_{17} is 5, k_{18} is 1, k_{19} is 7, and k_{20} is 2; or k_{15} is 6, k_{16} is 2, k_{17} is 2, k_{18} is 3, k_{19} is 7, and k_{20} is 5; or k_{15} is 3, k_{16} is 6, k_{17} is 6, k_{18} is 4, k_{19} is 5, and k_{20} is 4; or k_{15} is 4, k_{16} is 7, k_{17} is 2, k_{18} is 2, k_{19} is 3, and k_{20} is 2; or k_{15} is 6, k_{16} is 1, k_{17} is 2, k_{18} is 3, k_{19} is 5, and k_{20} is 4; or k_{15} is 2, k_{16} is 7, k_{17} is 7, k_{18} is 3, k_{19} is 6, and k_{20} is 3; or k_{15} is 1, k_{16} is 7, k_{17} is 5, k_{18} is 5, k_{19} is 4, and k_{20} is 2. That is, a sequence under 4096-QAM modulation is implemented, so that channel quality of a communication link under 4096-QAM modulation can be accurately measured when the channel quality of the communication link is measured by using the sequence.

[00211] Manner 7: The first sequence meets the following formula (7):

$$\mathbf{p}_u = [\mathbf{b}_0, \mathbf{d}_u, 0, 0, 0, 0, 0, (-1j) * \mathbf{b}_1] \quad (7).$$

[00212] u is an integer greater than or equal to 1 and less than or equal to 5. That is, a sequence under QPSK modulation is implemented, so that channel quality of a communication link under QPSK modulation can be accurately measured when the channel quality of the communication link is measured by using the sequence.

[00213] Manner 8: The first sequence meets the following formula (8):

$$\mathbf{q}_6 = \frac{2}{\sqrt{5}} e^{\frac{j\pi}{4}} \mathbf{p}_{t1} + \frac{1}{\sqrt{5}} e^{\frac{j\pi}{4}} \mathbf{p}_{t2} \quad (8).$$

[00214] $\mathbf{p}_{t1} = [\mathbf{b}_0, \mathbf{d}_{t1}, 0, 0, 0, 0, 0, (-1j) * \mathbf{b}_1]$; and $\mathbf{p}_{t2} = [\mathbf{b}_0, \mathbf{d}_{t2}, 0, 0, 0, 0, 0, (-1j) * \mathbf{b}_1]$.

[00215] $t1$ is 5, and $t2$ is 1, 2, 3, 4, or 5; or $t1$ is 1, and $t2$ is 5; or $t1$ is 4, and $t2$ is 5. That is, a sequence under 16-QAM modulation is implemented, so that channel quality of a communication link under 16-QAM modulation can be accurately measured when the channel quality of the communication link is measured by using the sequence.

[00216] Manner 9: The first sequence meets the following formula (9):

$$\mathbf{q}_7 = \frac{4}{\sqrt{21}} e^{\frac{j\pi}{4}} \mathbf{p}_{t3} + \frac{2}{\sqrt{21}} e^{\frac{j\pi}{4}} \mathbf{p}_{t4} + \frac{1}{\sqrt{21}} e^{\frac{j\pi}{4}} \mathbf{p}_{t5} \quad (9).$$

[00217] $\mathbf{p}_{t3} = [\mathbf{b}_0, \mathbf{d}_{t3}, 0, 0, 0, 0, 0, (-1j) * \mathbf{b}_1]$; $\mathbf{p}_{t4} = [\mathbf{b}_0, \mathbf{d}_{t4}, 0, 0, 0, 0, 0, (-1j) * \mathbf{b}_1]$; and $\mathbf{p}_{t5} = [\mathbf{b}_0, \mathbf{d}_{t5}, 0, 0, 0, 0, 0, (-1j) * \mathbf{b}_1]$.

[00218] $t3$ is 5, $t4$ is 5, and $t5$ is 1, 2, 3, 4, or 5; or $t3$ is 5, $t4$ is 1, and $t5$ is 5; or $t3$ is 5, $t4$ is 1, and $t5$ is 1. That is, a sequence under 64-QAM modulation is implemented, so that channel quality of a communication link under 64-QAM modulation can be accurately measured when the channel quality of the communication link is measured by using the sequence.

[00219] Manner 10: The first sequence meets the following formula (10):

$$\mathbf{q}_8 = \frac{8}{\sqrt{85}} e^{\frac{j\pi}{4}} \mathbf{p}_{t6} + \frac{4}{\sqrt{85}} e^{\frac{j\pi}{4}} \mathbf{p}_{t7} + \frac{2}{\sqrt{85}} e^{\frac{j\pi}{4}} \mathbf{p}_{t8} + \frac{1}{\sqrt{85}} e^{\frac{j\pi}{4}} \mathbf{p}_{t9} \quad (10).$$

[00220] $\mathbf{p}_{t6} = [\mathbf{b}_0, \mathbf{d}_{t6}, 0, 0, 0, 0, 0, (-1j) * \mathbf{b}_1]$; $\mathbf{p}_{t7} = [\mathbf{b}_0, \mathbf{d}_{t7}, 0, 0, 0, 0, 0, (-1j) * \mathbf{b}_1]$; $\mathbf{p}_{t8} = [\mathbf{b}_0, \mathbf{d}_{t8}, 0, 0, 0, 0, 0, (-1j) * \mathbf{b}_1]$; and $\mathbf{p}_{t9} = [\mathbf{b}_0, \mathbf{d}_{t9}, 0, 0, 0, 0, 0, (-1j) * \mathbf{b}_1]$.

[00221] $t6$ is 5, $t7$ is 5, and $t8$ is 5, and $t9$ is 1, 2, 3, or 4; or $t6$ is 5, $t7$ is 5, $t8$ is 1, and $t9$ is 1, 4, or 5; or $t6$ is 5, $t7$ is 1, $t8$ is 5, and $t9$ is 5. That is, a sequence under 256-QAM modulation is implemented, so that channel quality of a communication link under 256-QAM modulation can be accurately measured when the channel quality of the communication link is measured by using the sequence.

[00222] Manner 11: The first sequence meets the following formula (11):

$$\mathbf{q}_9 = \frac{16}{\sqrt{341}} e^{\frac{j\pi}{4}} \mathbf{p}_{t10} + \frac{8}{\sqrt{341}} e^{\frac{j\pi}{4}} \mathbf{p}_{t11} + \frac{4}{\sqrt{341}} e^{\frac{j\pi}{4}} \mathbf{p}_{t12} + \frac{2}{\sqrt{341}} e^{\frac{j\pi}{4}} \mathbf{p}_{t13} + \frac{1}{\sqrt{345}} e^{\frac{j\pi}{4}} \mathbf{p}_{t14} \quad (11).$$

[00223] $\mathbf{p}_{t10} = [\mathbf{b}_0, \mathbf{d}_{t10}, 0, 0, 0, 0, 0, (-1j) * \mathbf{b}_1]$; $\mathbf{p}_{t11} = [\mathbf{b}_0, \mathbf{d}_{t11}, 0, 0, 0, 0, 0, (-1j) * \mathbf{b}_1]$;

$\mathbf{p}_{t12} = [\mathbf{b}_0, \mathbf{d}_{t12}, 0,0,0,0,0, (-1j) * \mathbf{b}_1]$; $\mathbf{p}_{t13} = [\mathbf{b}_0, \mathbf{d}_{t13}, 0,0,0,0,0, (-1j) * \mathbf{b}_1]$; and $\mathbf{p}_{t14} = [\mathbf{b}_0, \mathbf{d}_{t14}, 0,0,0,0,0, (-1j) * \mathbf{b}_1]$.

[00224] $t10$ is 5, $t11$ is 5, $t12$ is 5, $t13$ is 1, and $t14$ is 2 or 4; or $t10$ is 5, $t11$ is 5, $t12$ is 5, $t13$ is 4, and $t14$ is 1 or 5; or $t10$ is 5, $t11$ is 5, $t12$ is 1, $t13$ is 5, and $t14$ is 1 or 5; or $t10$ is 5, $t11$ is 5, $t12$ is 1, $t13$ is 5, and $t14$ is 5; or $t10$ is 5, $t11$ is 5, $t12$ is 5, $t13$ is 2, and $t14$ is 5; or $t10$ is 5, $t11$ is 5, $t12$ is 5, $t13$ is 1, and $t14$ is 3. That is, a sequence under 1024-QAM modulation is implemented, so that channel quality of a communication link under 1024-QAM modulation can be accurately measured when the channel quality of the communication link is measured by using the sequence.

[00225] Manner 12: The first sequence meets the following formula (12):

$$\mathbf{q}_{10} = \frac{16}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{p}_{t15} + \frac{16}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{p}_{t16} + \frac{8}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{p}_{t17} + \frac{4}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{p}_{t18} + \frac{2}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{p}_{t19} + \frac{1}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{p}_{t20} \quad (12).$$

[00226] $\mathbf{p}_{t15} = [\mathbf{b}_0, \mathbf{d}_{t15}, 0,0,0,0,0, (-1j) * \mathbf{b}_1]$; $\mathbf{p}_{t16} = [\mathbf{b}_0, \mathbf{d}_{t16}, 0,0,0,0,0, (-1j) * \mathbf{b}_1]$; $\mathbf{p}_{t17} = [\mathbf{b}_0, \mathbf{d}_{t17}, 0,0,0,0,0, (-1j) * \mathbf{b}_1]$; $\mathbf{p}_{t18} = [\mathbf{b}_0, \mathbf{d}_{t18}, 0,0,0,0,0, (-1j) * \mathbf{b}_1]$; $\mathbf{p}_{t19} = [\mathbf{b}_0, \mathbf{d}_{t19}, 0,0,0,0,0, (-1j) * \mathbf{b}_1]$; and $\mathbf{p}_{t20} = [\mathbf{b}_0, \mathbf{d}_{t20}, 0,0,0,0,0, (-1j) * \mathbf{b}_1]$.

[00227] $t15$ is 5, $t16$ is 5, $t17$ is 5, $t18$ is 1, $t19$ is 2, and $t20$ is 5; or $t15$ is 5, $t16$ is 5, $t17$ is 5, $t18$ is 1, $t19$ is 1, and $t20$ is 3; or $t15$ is 5, $t16$ is 5, $t17$ is 1, $t18$ is 5, $t19$ is 5, and $t20$ is 1; or $t15$ is 5, $t16$ is 5, $t17$ is 5, $t18$ is 5, $t19$ is 3, and $t20$ is 3; or $t15$ is 5, $t16$ is 5, $t17$ is 5, $t18$ is 1, $t19$ is 1, and $t20$ is 2; or $t15$ is 5, $t16$ is 5, $t17$ is 5, $t18$ is 1, $t19$ is 4, and $t20$ is 1; or $t15$ is 5, $t16$ is 5, $t17$ is 5, $t18$ is 4, $t19$ is 5, and $t20$ is 1; or $t15$ is 5, $t16$ is 5, $t17$ is 5, $t18$ is 1, $t19$ is 4, and $t20$ is 5. That is, a sequence under 4096-QAM modulation is implemented, so that channel quality of a communication link under 4096-QAM modulation can be accurately measured when the channel quality of the communication link is measured by using the sequence.

[00228] Optionally, in Manner 1 to Manner 6, $\mathbf{a}_0$ and $\mathbf{a}_1$ are subsequences in the HE-LTF sequence, and j an imaginary unit. For example, $\mathbf{a}_0$ is one of the first to 489th elements in the HE-LTF sequence, and $\mathbf{a}_1$ is one of the 504th to 1001st elements in the HE-LTF sequence. That is, the first sequence is generated based on the HE-LTF sequence in the 4x mode at the 80 MHz bandwidth in 802.11ax, so that the PAPR of the first sequence is low.

[00229] In Manner 1 to Manner 6, $\mathbf{c}_1 = [1j, 1j, 1j, -1j, -1j, -1j, 1j, 1j, -1j]$; $\mathbf{c}_2 = [-1, -1, -1, -1j, -1j, -1j, 1j, 1j, -1j]$; $\mathbf{c}_3 = [-1, -1, -1, 1, 1, -1j, 1j, 1j, -1j]$; $\mathbf{c}_4 = [-1, -1, -1, 1, 1, 1, 1j, 1j, -1j]$; $\mathbf{c}_5 = [-1, -1, -1, 1, 1, 1, -1, 1j, -1j]$; $\mathbf{c}_6 = [-1, -1, -1, 1, 1, 1, -1, -1, -1j]$; and $\mathbf{c}_7 = [-1, -1, -1, 1, 1, 1, -1, -1, 1]$. That is, $\mathbf{c}_i$ is one of the 490th to 498th elements in the first sequence.

[00230] Optionally, in Manner 7 to Manner 12, $\mathbf{b}_0$ and $\mathbf{b}_1$ are subsequences in the EHT-LTF sequence, and j an imaginary unit. For example, $\mathbf{b}_0$ is one of the first to 492nd elements in the EHT-LTF sequence, and $\mathbf{b}_1$ is one of the 504th to 1001st elements in the EHT-LTF sequence. That is, the first sequence is generated based on the EHT-LTF sequence in the 4x mode at the 80 MHz bandwidth in 802.11be, so that the PAPR of the first sequence is low.

[00231] In Manner 7 to Manner 12, $\mathbf{d}_1 = [1j, 1j, 1j, -1j, 1j, 1j]$; $\mathbf{d}_2 = [-1, 1j, 1j, -1j, 1j, 1j]$; $\mathbf{d}_3 = [-1, -1, -1, -1j, 1j, 1j]$; $\mathbf{d}_4 = [-1, -1, -1, 1, -1, 1j]$; and $\mathbf{d}_5 = [-1, -1, -1, 1, -1, -1]$. That is, $\mathbf{d}_u$ is one of the 493rd to 498th elements in the first sequence.

[00232] Optionally, for Manner 1, it is assumed that the second sequence is $\mathbf{s} = \text{HE-LTF}_{4x}(-500:500)$, a transformed position is pos , and the first sequence is $\hat{\mathbf{s}}$, that is, $\hat{\mathbf{s}}(pos) = \mathbf{s}(pos) * (-1j)$. Specifically, when the second sequence is divided into a plurality of subsequences, the second sequence may be denoted as $\mathbf{s} = [\mathbf{a}_0, \mathbf{c}, 0, 0, 0, 0, \mathbf{a}_1]$, and $\mathbf{c}$ is one of the 490th to 498th elements in the second sequence. For example, the first sequence is $\mathbf{s}_1$. That is, it may be understood as that $\mathbf{s}_1$ is obtained after one of the 490th to 498th elements in $\mathbf{s}$ and one of the 504th to 1001st elements in $\mathbf{s}$ are transformed. For another example, the first sequence is $\mathbf{s}_7$. That is, it may be understood as that $\mathbf{s}_7$ is obtained after one of the 504th to the 1001st elements in $\mathbf{s}$ is transformed.

[00233] In addition, the first sequence in any one of Manner 2 to Manner 6 may be understood as being generated based on the first sequence in Manner 1. For example, Manner 1 relates to seven sequences obtained after the second sequence is modulated by using QPSK, that is, $\mathbf{s}_1$ to $\mathbf{s}_7$. A case in which $k1$ is 1 and $k2$ is 7 in Manner 2, that is, $\mathbf{q}_1 = \frac{2}{\sqrt{5}}e^{\frac{j\pi}{4}}\mathbf{s}_1 + \frac{1}{\sqrt{5}}e^{\frac{j\pi}{4}}\mathbf{s}_7$, may be understood as that $\mathbf{q}_1$ is obtained by using $\mathbf{s}_1$ and $\mathbf{s}_7$ in Manner 1. Similarly, a case in which $k3$ is 1, $k4$ is 6, and $k5$ is 7 in Manner 3, that is, $\mathbf{q}_2 = \frac{4}{\sqrt{21}}e^{\frac{j\pi}{4}}\mathbf{s}_1 + \frac{2}{\sqrt{21}}e^{\frac{j\pi}{4}}\mathbf{s}_6 + \frac{1}{\sqrt{21}}e^{\frac{j\pi}{4}}\mathbf{s}_7$, may be understood as that $\mathbf{q}_2$ is obtained by using $\mathbf{s}_1$, $\mathbf{s}_6$, and $\mathbf{s}_7$ in the manner.

[00234] Optionally, for Manner 7, it is assumed that the second sequence is $\mathbf{p} = \text{EHT-LTF}_{4x}(-500:500)$, a transformed position is pos , and the first sequence is $\hat{\mathbf{p}}$, that is, $\hat{\mathbf{p}}(pos) = \mathbf{p}(pos) * (-1j)$. A sequence length of the second sequence occupied by the transformed position is about 0.5. Specifically, when the second sequence is divided into a plurality of subsequences, the second sequence may be denoted as $\mathbf{p} = [\mathbf{b}_0, \mathbf{d}, 0, 0, 0, 0, \mathbf{b}_1]$, and $\mathbf{d}$ is one of the 493rd to 498th elements in the second sequence. For example, the first sequence is $\mathbf{p}_1$. That is, it may be understood as that $\mathbf{p}_1$ is obtained after one of the 493rd to 498th elements in $\mathbf{p}$ and one of the 504th to 1001st elements in $\mathbf{p}$ are transformed. For another example, the first sequence is $\mathbf{p}_5$. That is, it may be understood as that $\mathbf{p}_5$ is obtained after one of the 504th to the 1001st

elements in $\mathbf{p}$ is transformed.

[00235] In addition, the first sequence in any one of Manner 8 to Manner 12 may be understood as being generated based on the first sequence in Manner 1. For example, Manner 7 relates to five sequences obtained after the second sequence is modulated by using QPSK, that is, $\mathbf{p}_1$ to $\mathbf{p}_5$. A

5 case in which t_1 is 5 and t_2 is 1 in Manner 2, that is, $\mathbf{q}_6 = \frac{2}{\sqrt{5}} e^{\frac{j\pi}{4}} \mathbf{p}_5 + \frac{1}{\sqrt{5}} e^{\frac{j\pi}{4}} \mathbf{p}_1$, may be understood as that $\mathbf{q}_6$ is obtained by using $\mathbf{p}_1$ and $\mathbf{p}_5$ in Manner 1. Similarly, a case in which t_3 is 5, t_4 is 5, and t_5 is 1 in Manner 9, that is, $\mathbf{q}_7 = \frac{4}{\sqrt{21}} e^{\frac{j\pi}{4}} \mathbf{p}_5 + \frac{2}{\sqrt{21}} e^{\frac{j\pi}{4}} \mathbf{p}_5 + \frac{1}{\sqrt{21}} e^{\frac{j\pi}{4}} \mathbf{p}_1$, may be understood as that $\mathbf{q}_7$ is obtained by using $\mathbf{p}_5$, $\mathbf{p}_5$, and $\mathbf{p}_1$ in the manner.

[00236] 602: The second device receives the sounding frame.

10 **[00237]** Correspondingly, the first device sends the sounding frame.

[00238] For example, step 602 may include: The second device receives the sounding frame from the first device. Correspondingly, the first device sends the sounding frame to the second device.

[00239] 603: The second device performs channel measurement based on the first sequence.

15 **[00240]** It can be learned that, in the foregoing technical solution, the first device sends the sounding frame. The sounding frame includes the first field, the first field includes the predefined first sequence, the first sequence includes the sequence obtained after the second sequence is modulated by using at least one of the following modulation modes, and the modulation modes include: QPSK, 16-QAM, 64-QAM, 256-QAM, 1024-QAM, and 4096-QAM. Therefore, after
20 receiving the sounding frame, the second device may perform channel measurement based on the first sequence. Therefore, the second device may measure channel quality of a communication link in at least one of the modulation modes of QPSK, 16-QAM, 64-QAM, 256-QAM, 1024-QAM, and 4096-QAM when performing channel measurement by using the first sequence, thereby enriching application scenarios of the HE-LTF sequence or the EHT-LTF sequence. In addition,
25 because the PAPR of the first sequence is low, distortion of the first sequence is small, so that the second device can accurately measure the channel quality of the communication link in at least one of the modulation modes of QPSK, 16-QAM, 64-QAM, 256-QAM, 1024-QAM, and 4096-QAM when performing channel measurement by using the first sequence.

[00241] In addition, based on the 80 MHz tone design shown in FIG. 3, a corresponding
30 sounding frame format is defined in this application. FIG. 7 is a schematic diagram of a frame structure of a sounding frame according to an embodiment of this application. As shown in FIG. 7, the sounding frame includes an L-STF, an L-LTF, an L-SIG, a repeated legacy short training field (repeated legacy short training field, RL-STF), a (universal signal, U-SIG) field, an extremely high throughput signal (extremely high throughput signal, EHT-SIG) field, an extremely high

throughput short training field (extremely high throughput short training field, EHT-STF), a long training field (long training field, L-LTF), and a PE field. The LTF field includes binary phase shift keying long training fields (BPSK LTFs) and 4^q -QAM-LTFs fields. It may be understood that the BPSK LTFs may include at least one extremely high throughput long training field (extremely high throughput long training field, EHT-LTF). The 4^q -QAM-LTFs fields may include at least one 4^q -QAM-LTF field.

[00242] It should be noted that in this application, in a case in which the second sequence is the EHT-LTF sequence in the 4x mode at the 80 MHz bandwidth in 802.11be, and the first sequence may be included in the 4^q -QAM-LTFs fields. For example, a sequence obtained after the second sequence is modulated by using 16-QAM may be included in a 4^2 -QAM-LTF field, and a sequence obtained after the second sequence is modulated by using 64-QAM may be included in a 4^3 -QAM-LTF field.

[00243] It should be noted that in this application, a sum of differences between a peak average power ratio (peak to average power ratio, PAPR) of a first subsequence corresponding to each of at least one RU in any sequence included in the first sequence and a PAPR of a corresponding RU in the second sequence is less than or equal to a preset threshold. One RU may include one of the following: a 26-tone RU, a 52-tone RU, a 106-tone RU, a 242-tone RU, a 484-tone RU, and a 996-tone RU. The first subsequence is a subsequence with a maximum PAPR in subsequences corresponding to one RU. For example, in a case in which a transmission bandwidth is 80 MHz, 36 26-tone RUs are distributed on the transmission bandwidth, a subsequence corresponding to each 26-tone RU corresponds to one PAPR, and a first subsequence is a subsequence with a maximum PAPR in the 36 26-tone RUs. For example, in a case in which a transmission bandwidth is 80 MHz, 18 52-tone RUs are distributed on the transmission bandwidth, a subsequence corresponding to each 52-tone RU corresponds to one PAPR, and a first subsequence is a subsequence with a maximum PAPR in the 18 52-tone RUs. It may be understood that, in this embodiment of this application, an RU including K tones is referred to as a K-tone RU. For example, a 26-tone RU is an RU including 26 tones. That is, a concept of the K-tone RU is the same as that of a K-tone RU in the existing 802.11ax standard.

[00244] In addition, the preset threshold is a value predefined in a protocol. This is not limited in this application.

[00245] In this application, the sum of the differences between the PAPR of the first subsequence corresponding to each of at least one RU in any sequence included in the first sequence and the PAPR of the corresponding RU in the second sequence is less than or equal to the preset threshold. That is, it means that the PAPR of the first subsequence corresponding to each of at least one RU in any sequence included in the first sequence is close to the PAPR of the

corresponding RU in the second sequence. The second sequence can support an AP or a STA in performing channel measurement, and a transmit power of the second sequence has relatively high power efficiency. Therefore, a transmit power of a first sequence having a PAPR close to that of the second sequence also has relatively high power efficiency. That is, the first sequence whose PAPR is close to that of the second sequence can also relatively well support the AP or the STA in performing channel measurement.

[00246] For example, it is assumed that the sum of the differences between the PAPR of the first subsequence corresponding to each of at least one RU in any sequence included in the first sequence and the PAPR of the corresponding RU in the second sequence is δ . For Manner 1, it may be set that $\delta = \sum_{x=1}^6 |PAPR_s(x) - PAPR_{\hat{s}}(x)|$. $PAPR_s(x)$ is a PAPR corresponding to an RU in the second sequence, and $PAPR_{\hat{s}}(x)$ may be a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the RU in any sequence included in the first sequence. For example, $PAPR_s(1)$ may be a PAPR corresponding to a 26-tone RU in the second sequence, and $PAPR_{\hat{s}}(1)$ may be a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 26-tone RU in any sequence included in the first sequence. $PAPR_s(2)$ is a PAPR corresponding to a 52-tone RU in the second sequence, and $PAPR_{\hat{s}}(2)$ is a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 52-tone RU in any sequence included in the first sequence. $PAPR_s(3)$ is a PAPR corresponding to a 106-tone RU in the second sequence, and $PAPR_{\hat{s}}(3)$ is a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 106-tone RU in any sequence included in the first sequence. $PAPR_s(4)$ is a PAPR corresponding to a 242-tone RU in the second sequence, and $PAPR_{\hat{s}}(4)$ is a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 242-tone RU in any sequence included in the first sequence. $PAPR_s(5)$ is a PAPR corresponding to a 484-tone RU in the second sequence, and $PAPR_{\hat{s}}(5)$ is a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 484-tone RU in any sequence included in the first sequence. $PAPR_s(6)$ is a PAPR corresponding to a 996-tone RU in the second sequence, and $PAPR_{\hat{s}}(6)$ is a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 996-tone RU in any sequence included in the first sequence. It may be understood that the foregoing descriptions of $PAPR_s(1)$ to $PAPR_s(6)$ and $PAPR_{\hat{s}}(1)$ to $PAPR_{\hat{s}}(6)$ are merely examples, and there may be other cases. Details are not described herein again. It should be noted that, $PAPR_s(1)$ to $PAPR_s(6)$ should be PAPRs corresponding to different RUs in the second sequence, and $PAPR_{\hat{s}}(1)$ to $PAPR_{\hat{s}}(6)$ are also PAPRs of subsequences with maximum PAPRs in subsequences corresponding to different RUs in any sequence included in the first sequence. In addition, $PAPR_s(x)$ and $PAPR_{\hat{s}}(x)$ correspond to a same RU when a value of x is the same.

For Manner 7, it may be set that $\delta = \sum_{x=1}^6 |PAPR_p(x) - PAPR_{\hat{p}}(x)|$. $PAPR_p(x)$ is a PAPR

corresponding to an RU in the second sequence, and $PAPR_{\hat{p}}(x)$ may be a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the RU in any sequence included in the first sequence. In addition, when a value of x is different, for meanings represented by $PAPR_p(x)$ and $PAPR_{\hat{p}}(x)$, refer to $PAPR_s(x)$ and $PAPR_{\hat{s}}(x)$ respectively. Details are not described herein again. It should be noted that, in this application, δ in Table 1 to Table 12 is less than or equal to the preset threshold, and a PAPR of the first sequence in Table 1 to Table 12 is close to a PAPR of the second sequence. The second sequence can support an AP or a STA in performing channel measurement, and a transmit power of the second sequence has relatively high power efficiency. Therefore, in Table 1 to Table 12, a transmit power of a first sequence having a PAPR close to that of the second sequence also has relatively high power efficiency. That is, the first sequence whose PAPR is close to that of the second sequence can also relatively well support the AP or the STA in performing channel measurement.

[00247] In a case in which the second sequence is the HE-LTF sequence in the 4x mode at the 80 MHz bandwidth in 802.11ax, for PAPRs of the first sequence and the second sequence under different RUs in Manner 1, refer to Table 1. With reference to Table 1, it can be learned that, when $i = 1$ in Manner 1, a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 26-tone RU in s_1 is 7.0810 dB, a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 52-tone RU in s_1 is 7.6445 dB, a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 106-tone RU in s_1 is 6.6954 dB, a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 242-tone RU in s_1 is 6.9515 dB, a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 484-tone RU in s_1 is 6.5287 dB, and a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 996-tone RU in s_1 is 7.4502 dB. Therefore, δ corresponding to s_1 is 0.1551, and 0.1551 is less than the preset threshold. That is, it means that a PAPR of s_1 is close to that of the second sequence. Therefore, it indicates that a transmit power of s_1 also has relatively high power efficiency, and can well support the AP or the STA in performing channel measurement. Similarly, when $i = 2$ in Manner 1, for PAPRs of s_2 under different RUs, refer to Table 1, and δ corresponding to s_2 is 0.2086. When $i = 3$ in Manner 1, for PAPRs of s_3 under different RUs, refer to Table 1, and δ corresponding to s_3 is 0.1144. When $i = 4$ in Manner 1, for PAPRs of s_4 under different RUs, refer to Table 1, and δ corresponding to s_4 is 0.0507. When $i = 5$ in Manner 1, for PAPRs of s_5 under different RUs, refer to Table 1, and δ corresponding to s_5 is 0.1046. When $i = 6$ in Manner 1, for PAPRs of s_6 under different RUs, refer to Table 1, and δ corresponding to s_6 is 0.1519. When $i = 7$ in Manner 1, for PAPRs of s_7 under different RUs, refer to Table 1, and δ corresponding to s_7 is

0.0669. That is, 0.2086, 0.1144, 0.0507, and the like are all less than the preset threshold. That is, it means that PAPRs of s_2 , s_3 , s_4 , and the like are close to that of the second sequence, thereby indicating that transmit powers of s_2 , s_3 , s_4 , and the like also have relatively high power efficiency, and can well support the AP or the STA in performing channel measurement. In addition, in Table 1 to Table 6, a PAPR corresponding to the 26-tone RU in the second sequence is 7.0810 dB, a PAPR corresponding to the 52-tone RU in the second sequence is 7.6445 dB, a PAPR corresponding to the 106-tone RU in the second sequence is 6.6954 dB, a PAPR corresponding to the 242-tone RU in the second sequence is 6.9515 dB, a PAPR corresponding to the 484-tone RU in the second sequence is 6.5287 dB, and a PAPR corresponding to the 996-tone RU in the second sequence is 7.2951 dB. Details are not described subsequently.

Table 1: PAPRs of the first sequence and the second sequence under different RUs in Manner 1

	26-tone RU	52-tone RU	106-tone RU	242-tone RU	484-tone RU	996-tone RU
PAPRs of s_1 under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.4502 dB
PAPRs of s_2 under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.5037 dB
PAPRs of s_3 under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.4095 dB
PAPRs of s_4 under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.3458 dB
PAPRs of s_5 under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.1905 dB
PAPRs of s_6 under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.1432 dB
PAPRs of s_7 under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2282 dB
PAPRs of the second sequence under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2951 dB

[00248] In a case in which the second sequence is the HE-LTF sequence in the 4x mode at the 80 MHz bandwidth in 802.11ax, for PAPRs of the first sequence and the second sequence under

different RUs in Manner 2, refer to Table 2. It may be understood that, in this application, $\mathbf{q}_1(1,7)$ may be understood as that $\mathbf{q}_1 = \frac{2}{\sqrt{5}}e^{\frac{j\pi}{4}}\mathbf{s}_1 + \frac{1}{\sqrt{5}}e^{\frac{j\pi}{4}}\mathbf{s}_7$. That is, k_1 is 1, and k_2 is 7. Similarly, $\mathbf{q}_1(4,5)$ may be understood as that $\mathbf{q}_1 = \frac{2}{\sqrt{5}}e^{\frac{j\pi}{4}}\mathbf{s}_4 + \frac{1}{\sqrt{5}}e^{\frac{j\pi}{4}}\mathbf{s}_5$. That is, k_1 is 4, and k_2 is 5. For others such as $\mathbf{q}_1(4,6)$ in Table 2, refer to an understanding manner of $\mathbf{q}_1(1,7)$, and details are not described herein again. In addition, with reference to Table 2, when $\mathbf{q}_1 = \frac{2}{\sqrt{5}}e^{\frac{j\pi}{4}}\mathbf{s}_1 + \frac{1}{\sqrt{5}}e^{\frac{j\pi}{4}}\mathbf{s}_7$, a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 26-tone RU in $\mathbf{q}_1$ is 7.0810 dB, a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 52-tone RU in $\mathbf{q}_1$ is 7.6445 dB, a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 106-tone RU in $\mathbf{q}_1$ is 6.6954 dB, a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 242-tone RU in $\mathbf{q}_1$ is 6.9515 dB, a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 484-tone RU in $\mathbf{q}_1$ is 6.5287 dB, and a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 996-tone RU in $\mathbf{q}_1$ is 7.3083 dB. Therefore, when $\mathbf{q}_1 = \frac{2}{\sqrt{5}}e^{\frac{j\pi}{4}}\mathbf{s}_1 + \frac{1}{\sqrt{5}}e^{\frac{j\pi}{4}}\mathbf{s}_7$, δ is 0.0132. Similarly, when $\mathbf{q}_1 = \frac{2}{\sqrt{5}}e^{\frac{j\pi}{4}}\mathbf{s}_4 + \frac{1}{\sqrt{5}}e^{\frac{j\pi}{4}}\mathbf{s}_5$, for PAPRs of $\mathbf{q}_1$ under different RUs, refer to Table 2, and δ is 0.0011. When $\mathbf{q}_1 = \frac{2}{\sqrt{5}}e^{\frac{j\pi}{4}}\mathbf{s}_4 + \frac{1}{\sqrt{5}}e^{\frac{j\pi}{4}}\mathbf{s}_6$, for PAPRs of $\mathbf{q}_1$ under different RUs, refer to Table 2, and δ is 0.0191. When $\mathbf{q}_1 = \frac{2}{\sqrt{5}}e^{\frac{j\pi}{4}}\mathbf{s}_5 + \frac{1}{\sqrt{5}}e^{\frac{j\pi}{4}}\mathbf{s}_1$, for PAPRs of $\mathbf{q}_1$ under different RUs, refer to Table 2, and δ is 0.0047. When $\mathbf{q}_1 = \frac{2}{\sqrt{5}}e^{\frac{j\pi}{4}}\mathbf{s}_5 + \frac{1}{\sqrt{5}}e^{\frac{j\pi}{4}}\mathbf{s}_2$, for PAPRs of $\mathbf{q}_1$ under different RUs, refer to Table 2, and δ is 0.0086.

Table 2: PAPRs of the first sequence and the second sequence under different RUs in Manner 2

	26-tone RU	52-tone RU	106-tone RU	242-tone RU	484-tone RU	996-tone RU
PAPRs of $\mathbf{q}_1(1,7)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.3083 dB
PAPRs of $\mathbf{q}_1(4,5)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2962 dB
PAPRs of $\mathbf{q}_1(4,6)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2761 dB
PAPRs of $\mathbf{q}_1(5,1)$	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2905 dB

under different RUs						
PAPRs of $\mathbf{q}_1(5,2)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.6037 dB
PAPRs of the second sequence under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2951 dB

[00249] In a case in which the second sequence is the HE-LTF sequence in the 4x mode at the 80 MHz bandwidth in 802.11ax, for PAPRs of the first sequence and the second sequence under different RUs in Manner 3, refer to Table 3. It may be understood that, in this application,

5 $\mathbf{q}_2(1,6,7)$ may be understood as that $\mathbf{q}_2 = \frac{4}{\sqrt{21}}e^{\frac{j\pi}{4}}\mathbf{s}_1 + \frac{2}{\sqrt{21}}e^{\frac{j\pi}{4}}\mathbf{s}_6 + \frac{1}{\sqrt{21}}e^{\frac{j\pi}{4}}\mathbf{s}_7$. That is, k_3 is 1, k_4 is 6, and k_5 is 7. Similarly, $\mathbf{q}_2(1,7,5)$ may be understood as that $\mathbf{q}_2 = \frac{4}{\sqrt{21}}e^{\frac{j\pi}{4}}\mathbf{s}_1 + \frac{2}{\sqrt{21}}e^{\frac{j\pi}{4}}\mathbf{s}_7 + \frac{1}{\sqrt{21}}e^{\frac{j\pi}{4}}\mathbf{s}_5$. That is, k_3 is 1, k_4 is 7, and k_5 is 5. For others such as $\mathbf{q}_2(1,7,6)$ in Table 3, refer to an understanding manner of $\mathbf{q}_2(1,6,7)$, and details are not described herein again.

In addition, with reference to Table 3, when $\mathbf{q}_2 = \frac{4}{\sqrt{21}}e^{\frac{j\pi}{4}}\mathbf{s}_1 + \frac{2}{\sqrt{21}}e^{\frac{j\pi}{4}}\mathbf{s}_6 + \frac{1}{\sqrt{21}}e^{\frac{j\pi}{4}}\mathbf{s}_7$, a PAPR of a
10 subsequence with a maximum PAPR in subsequences corresponding to the 26-tone RU in $\mathbf{q}_2$ is 7.0810 dB, a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 52-tone RU in $\mathbf{q}_2$ is 7.6445 dB, a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 106-tone RU in $\mathbf{q}_2$ is 6.6954 dB, a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 242-tone RU in $\mathbf{q}_2$ is 6.9515 dB, a
15 PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 484-tone RU in $\mathbf{q}_2$ is 6.5287 dB, and a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 996-tone RU in $\mathbf{q}_2$ is 7.3074 dB. Therefore, when $\mathbf{q}_2 = \frac{4}{\sqrt{21}}e^{\frac{j\pi}{4}}\mathbf{s}_1 + \frac{2}{\sqrt{21}}e^{\frac{j\pi}{4}}\mathbf{s}_6 + \frac{1}{\sqrt{21}}e^{\frac{j\pi}{4}}\mathbf{s}_7$, δ is 0.0123. Similarly, when $\mathbf{q}_2 = \frac{4}{\sqrt{21}}e^{\frac{j\pi}{4}}\mathbf{s}_1 + \frac{2}{\sqrt{21}}e^{\frac{j\pi}{4}}\mathbf{s}_7 + \frac{1}{\sqrt{21}}e^{\frac{j\pi}{4}}\mathbf{s}_5$, for PAPRs of $\mathbf{q}_2$ under different RUs, refer to Table 3, and δ is 0.0003. In addition, for remaining
20 cases in Table 3, δ is successively 0.0091, 0.0161, 0.0056, 0.0167, 0.0041, 0.0077, 0.0015, 0.0069, 0.0121, 0.0036, 0.0125, 0.0005, 0.0185, 0.0083, 0.0135, 0.0124, 0.0173, 0.0012, 0.0088, 0.0138, 0.0044, 0.0181, 0.0154, 0.0071, 0.0156, 0.0046, 0.0098, 0.0059, 0.0155, 0.0146, 0.0096, 0.0133, 0.0066, 0.0008, 0.0039, and 0.0109 from top to bottom.

**Table 3: PAPRs of the first sequence and the second sequence under different RUs in
Manner 3**

	26-tone RU	52-tone RU	106-tone RU	242-tone RU	484-tone RU	996-tone RU
PAPRs of $\mathbf{q}_2(1,6,7)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.3074 dB
PAPRs of $\mathbf{q}_2(1,7,5)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2948 dB
PAPRs of $\mathbf{q}_2(1,7,6)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2860 dB
PAPRs of $\mathbf{q}_2(2,7,6)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.3112 dB
PAPRs of $\mathbf{q}_2(2,7,7)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2896 dB
PAPRs of $\mathbf{q}_2(3,5,6)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.3118 dB
PAPRs of $\mathbf{q}_2(3,5,7)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2911 dB
PAPRs of $\mathbf{q}_2(3,6,5)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.6029 dB
PAPRs of $\mathbf{q}_2(3,6,6)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2936 dB
PAPRs of $\mathbf{q}_2(3,7,1)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.6021 dB
PAPRs of $\mathbf{q}_2(3,7,2)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.3072 dB
PAPRs of $\mathbf{q}_2(3,7,3)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2915 dB
PAPRs of $\mathbf{q}_2(3,7,4)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2826 dB
PAPRs of $\mathbf{q}_2(4,4,7)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2956 dB
PAPRs of $\mathbf{q}_2(4,5,3)$	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.3136 dB

under different RUs						
PAPRs of $\mathbf{q}_2(4,5,4)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.6035 dB
PAPRs of $\mathbf{q}_2(4,5,5)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2817 dB
PAPRs of $\mathbf{q}_2(4,6,1)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.3076 dB
PAPRs of $\mathbf{q}_2(4,6,2)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.3124 dB
PAPRs of $\mathbf{q}_2(4,6,3)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2963 dB
PAPRs of $\mathbf{q}_2(4,6,4)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2863 dB
PAPRs of $\mathbf{q}_2(5,1,3)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.3089 dB
PAPRs of $\mathbf{q}_2(5,1,4)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2996 dB
PAPRs of $\mathbf{q}_2(5,1,5)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2770 dB
PAPRs of $\mathbf{q}_2(5,2,4)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.3106 dB
PAPRs of $\mathbf{q}_2(5,2,5)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2881 dB
PAPRs of $\mathbf{q}_2(5,2,6)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2796 dB
PAPRs of $\mathbf{q}_2(5,3,1)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2998 dB
PAPRs of $\mathbf{q}_2(5,3,2)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.3049 dB
PAPRs of $\mathbf{q}_2(5,3,3)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2892 dB
PAPRs of $\mathbf{q}_2(5,3,4)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2796 dB
PAPRs of $\mathbf{q}_2(5,4,1)$	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2805 dB

under different RUs						
PAPRs of $\mathbf{q}_2(5,4,2)$	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2856 dB
under different RUs						
PAPRs of $\mathbf{q}_2(6,1,1)$	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2818 dB
under different RUs						
PAPRs of $\mathbf{q}_2(6,1,2)$	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2886 dB
under different RUs						
PAPRs of $\mathbf{q}_2(6,2,1)$	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2943 dB
under different RUs						
PAPRs of $\mathbf{q}_2(6,2,2)$	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2990 dB
under different RUs						
PAPRs of $\mathbf{q}_2(6,2,3)$	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2842 dB
under different RUs						
PAPRs of the second sequence under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2951 dB

[00250] In a case in which the second sequence is the HE-LTF sequence in the 4x mode at the 80 MHz bandwidth in 802.11ax, for PAPRs of the first sequence and the second sequence under different RUs in Manner 4, refer to Table 4. It may be understood that, in this application,

- 5 $\mathbf{q}_3(1,7,4,7)$ may be understood as that $\mathbf{q}_3 = \frac{8}{\sqrt{85}}e^{\frac{j\pi}{4}}\mathbf{s}_1 + \frac{4}{\sqrt{85}}e^{\frac{j\pi}{4}}\mathbf{s}_7 + \frac{2}{\sqrt{85}}e^{\frac{j\pi}{4}}\mathbf{s}_4 + \frac{1}{\sqrt{85}}e^{\frac{j\pi}{4}}\mathbf{s}_7$. That is, k_6 is 1, k_7 is 7, k_8 is 4, and k_9 is 7. Similarly, $\mathbf{q}_3(1,7,6,3)$ may be understood as that $\mathbf{q}_3 = \frac{8}{\sqrt{85}}e^{\frac{j\pi}{4}}\mathbf{s}_1 + \frac{4}{\sqrt{85}}e^{\frac{j\pi}{4}}\mathbf{s}_7 + \frac{2}{\sqrt{85}}e^{\frac{j\pi}{4}}\mathbf{s}_6 + \frac{1}{\sqrt{85}}e^{\frac{j\pi}{4}}\mathbf{s}_3$. That is, k_6 is 1, k_7 is 7, k_8 is 6, and k_9 is 3. For others such as $\mathbf{q}_3(2,7,7,4)$ in Table 4, refer to an understanding manner of $\mathbf{q}_3(1,7,4,7)$, and details are not described herein again. In addition, with reference to Table 4, when $\mathbf{q}_3 =$
- 10 $\frac{8}{\sqrt{85}}e^{\frac{j\pi}{4}}\mathbf{s}_1 + \frac{4}{\sqrt{85}}e^{\frac{j\pi}{4}}\mathbf{s}_7 + \frac{2}{\sqrt{85}}e^{\frac{j\pi}{4}}\mathbf{s}_4 + \frac{1}{\sqrt{85}}e^{\frac{j\pi}{4}}\mathbf{s}_7$, a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 26-tone RU in $\mathbf{q}_3$ is 7.0810 dB, a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 52-tone RU in $\mathbf{q}_3$ is 7.6445 dB, a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 106-tone RU in $\mathbf{q}_3$ is 6.6954 dB, a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 242-tone RU in $\mathbf{q}_3$ is 6.9515 dB, a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 484-tone RU in $\mathbf{q}_3$ is 6.5287 dB, and a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 996-tone RU in $\mathbf{q}_3$ is
- 15

7.2955 dB. Therefore, when $\mathbf{q}_3 = \frac{8}{\sqrt{85}}e^{\frac{j\pi}{4}}\mathbf{s}_1 + \frac{4}{\sqrt{85}}e^{\frac{j\pi}{4}}\mathbf{s}_7 + \frac{2}{\sqrt{85}}e^{\frac{j\pi}{4}}\mathbf{s}_4 + \frac{1}{\sqrt{85}}e^{\frac{j\pi}{4}}\mathbf{s}_7$, δ is 0.0004.

Similarly, when $\mathbf{q}_3 = \frac{8}{\sqrt{85}}e^{\frac{j\pi}{4}}\mathbf{s}_1 + \frac{4}{\sqrt{85}}e^{\frac{j\pi}{4}}\mathbf{s}_7 + \frac{2}{\sqrt{85}}e^{\frac{j\pi}{4}}\mathbf{s}_6 + \frac{1}{\sqrt{85}}e^{\frac{j\pi}{4}}\mathbf{s}_3$, for PAPRs of $\mathbf{q}_3$ under different RUs, refer to Table 4, and δ is 0.0001. In addition, for remaining cases in Table 4, δ is successively 0.0010, 0.0001, 0.0007, 0.0002, 0.0007, 0.0004, 0.0003, 0.0009, 0.0000, 0.0002,

5 0.0007, 0.0008, 0.0007, and 0.0006 from top to bottom.

Table 4: PAPRs of the first sequence and the second sequence under different RUs in Manner 4

	26-tone RU	52-tone RU	106-tone RU	242-tone RU	484-tone RU	996-tone RU
PAPRs of $\mathbf{q}_3(1,7,4,7)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2955 dB
PAPRs of $\mathbf{q}_3(1,7,6,3)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2952 dB
PAPRs of $\mathbf{q}_3(2,7,7,4)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2942 dB
PAPRs of $\mathbf{q}_3(3,5,7,4)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2950 dB
PAPRs of $\mathbf{q}_3(3,6,5,5)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2958 dB
PAPRs of $\mathbf{q}_3(3,7,1,5)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2954 dB
PAPRs of $\mathbf{q}_3(3,7,2,6)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2958 dB
PAPRs of $\mathbf{q}_3(3,7,3,4)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2955 dB
PAPRs of $\mathbf{q}_3(4,4,6,7)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2948 dB
PAPRs of $\mathbf{q}_3(4,6,1,6)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2960 dB
PAPRs of $\mathbf{q}_3(4,6,4,3)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2951 dB
PAPRs of $\mathbf{q}_3(5,1,1,7)$	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2953 dB

under different RUs						
PAPRs of $\mathbf{q}_3(5,2,6,2)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2958 dB
PAPRs of $\mathbf{q}_3(5,4,1,1)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2944 dB
PAPRs of $\mathbf{q}_3(5,4,2,3)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2944 dB
PAPRs of $\mathbf{q}_3(6,1,1,1)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2945 dB
PAPRs of the second sequence under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2951 dB

[00251] In a case in which the second sequence is the HE-LTF sequence in the 4x mode at the 80 MHz bandwidth in 802.11ax, for PAPRs of the first sequence and the second sequence under different RUs in Manner 5, refer to Table 5. It may be understood that, in this application,

5 $\mathbf{q}_4(1,7,6,1,5)$ may be understood as that $\mathbf{q}_4 = \frac{16}{\sqrt{341}}e^{\frac{j\pi}{4}}\mathbf{s}_1 + \frac{8}{\sqrt{341}}e^{\frac{j\pi}{4}}\mathbf{s}_7 + \frac{4}{\sqrt{341}}e^{\frac{j\pi}{4}}\mathbf{s}_6 + \frac{2}{\sqrt{341}}e^{\frac{j\pi}{4}}\mathbf{s}_1 + \frac{1}{\sqrt{345}}e^{\frac{j\pi}{4}}\mathbf{s}_5$. That is, k_{10} is 1, k_{11} is 7, k_{12} is 6, k_{13} is 1, and k_{14} is 5.

Similarly, $\mathbf{q}_4(2,7,5,7,5)$ may be understood as that $\mathbf{q}_4 = \frac{16}{\sqrt{341}}e^{\frac{j\pi}{4}}\mathbf{s}_2 + \frac{8}{\sqrt{341}}e^{\frac{j\pi}{4}}\mathbf{s}_7 + \frac{4}{\sqrt{341}}e^{\frac{j\pi}{4}}\mathbf{s}_5 + \frac{2}{\sqrt{341}}e^{\frac{j\pi}{4}}\mathbf{s}_7 + \frac{1}{\sqrt{345}}e^{\frac{j\pi}{4}}\mathbf{s}_5$. That is, k_{10} is 2, k_{11} is 7, k_{12} is 5, k_{13} is 7, and k_{14} is 5. For others such as $\mathbf{q}_4(6,1,2,4,4)$ in Table 5, refer to an understanding manner of

10 $\mathbf{q}_4(1,7,6,1,5)$, and details are not described herein again. In addition, with reference to Table 5,

when $\mathbf{q}_4 = \frac{16}{\sqrt{341}}e^{\frac{j\pi}{4}}\mathbf{s}_1 + \frac{8}{\sqrt{341}}e^{\frac{j\pi}{4}}\mathbf{s}_7 + \frac{4}{\sqrt{341}}e^{\frac{j\pi}{4}}\mathbf{s}_6 + \frac{2}{\sqrt{341}}e^{\frac{j\pi}{4}}\mathbf{s}_1 + \frac{1}{\sqrt{345}}e^{\frac{j\pi}{4}}\mathbf{s}_5$, a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 26-tone RU in $\mathbf{q}_4$ is 7.0810 dB, a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 52-tone RU in $\mathbf{q}_4$ is 7.6445 dB, a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 106-tone RU in $\mathbf{q}_4$ is 6.6954 dB, a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 242-tone RU in $\mathbf{q}_4$ is 6.9515 dB, a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 484-tone RU in $\mathbf{q}_4$ is 6.5287 dB, and a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 996-tone RU in $\mathbf{q}_4$ is 7.2951 dB. Therefore, when $\mathbf{q}_4 = \frac{16}{\sqrt{341}}e^{\frac{j\pi}{4}}\mathbf{s}_1 +$

$\frac{8}{\sqrt{341}}e^{\frac{j\pi}{4}}\mathbf{s}_7 + \frac{4}{\sqrt{341}}e^{\frac{j\pi}{4}}\mathbf{s}_6 + \frac{2}{\sqrt{341}}e^{\frac{j\pi}{4}}\mathbf{s}_1 + \frac{1}{\sqrt{345}}e^{\frac{j\pi}{4}}\mathbf{s}_5$, δ is 2.16×10^{-5} . Similarly, when $\mathbf{q}_4 = \frac{16}{\sqrt{341}}e^{\frac{j\pi}{4}}\mathbf{s}_2 + \frac{8}{\sqrt{341}}e^{\frac{j\pi}{4}}\mathbf{s}_7 + \frac{4}{\sqrt{341}}e^{\frac{j\pi}{4}}\mathbf{s}_5 + \frac{2}{\sqrt{341}}e^{\frac{j\pi}{4}}\mathbf{s}_7 + \frac{1}{\sqrt{345}}e^{\frac{j\pi}{4}}\mathbf{s}_5$, for PAPRs of $\mathbf{q}_4$ under different RUs, refer to Table 5, and δ is 2.45×10^{-5} . In addition, for remaining cases in Table 5, δ is successively 2.51×10^{-5} , 4.06×10^{-5} , 4.58×10^{-5} , 5.26×10^{-5} , 5.43×10^{-5} , and 5.71×10^{-5} from top to bottom.

Table 5: PAPRs of the first sequence and the second sequence under different RUs in Manner 5

	26-tone RU	52-tone RU	106-tone RU	242-tone RU	484-tone RU	996-tone RU
PAPRs of $\mathbf{q}_4(1,7,6,1,5)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2951 dB
PAPRs of $\mathbf{q}_4(2,7,5,7,5)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2951 dB
PAPRs of $\mathbf{q}_4(6,1,2,4,4)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2952 dB
PAPRs of $\mathbf{q}_4(4,6,4,1,6)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2952 dB
PAPRs of $\mathbf{q}_4(6,2,1,4,5)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2952 dB
PAPRs of $\mathbf{q}_4(3,6,7,1,2)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2951 dB
PAPRs of $\mathbf{q}_4(5,3,1,6,1)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2952 dB
PAPRs of $\mathbf{q}_4(4,6,2,6,6)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2951 dB
PAPRs of the second sequence under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2951 dB

[00252] In a case in which the second sequence is the HE-LTF sequence in the 4x mode at the 80 MHz bandwidth in 802.11ax, for PAPRs of the first sequence and the second sequence under different RUs in Manner 6, refer to Table 6. It may be understood that, in this application,

$\mathbf{q}_5(5,2,4,7,2,5)$ may be understood as that $\mathbf{q}_5 = \frac{16}{\sqrt{1365}}e^{\frac{j\pi}{4}}\mathbf{s}_5 + \frac{16}{\sqrt{1365}}e^{\frac{j\pi}{4}}\mathbf{s}_2 + \frac{8}{\sqrt{1365}}e^{\frac{j\pi}{4}}\mathbf{s}_4 + \frac{4}{\sqrt{1365}}e^{\frac{j\pi}{4}}\mathbf{s}_7 + \frac{2}{\sqrt{1365}}e^{\frac{j\pi}{4}}\mathbf{s}_2 + \frac{1}{\sqrt{1365}}e^{\frac{j\pi}{4}}\mathbf{s}_5$. That is, k_{15} is 5, k_{16} is 2, k_{17} is 4, k_{18} is 7, k_{19} is 2, and k_{20} is 5. Similarly, $\mathbf{q}_5(5,2,5,1,7,2)$ may be understood as that $\mathbf{q}_5 = \frac{16}{\sqrt{1365}}e^{\frac{j\pi}{4}}\mathbf{s}_5 + \frac{16}{\sqrt{1365}}e^{\frac{j\pi}{4}}\mathbf{s}_2 + \frac{8}{\sqrt{1365}}e^{\frac{j\pi}{4}}\mathbf{s}_5 + \frac{4}{\sqrt{1365}}e^{\frac{j\pi}{4}}\mathbf{s}_1 + \frac{2}{\sqrt{1365}}e^{\frac{j\pi}{4}}\mathbf{s}_7 + \frac{1}{\sqrt{1365}}e^{\frac{j\pi}{4}}\mathbf{s}_2$. That is, k_{15} is 5, k_{16} is 2, k_{17} is 5, k_{18} is 1, k_{19} is 7, and k_{20} is 2. For others such as $\mathbf{q}_5(6,2,2,3,7,5)$ in Table 6, refer to an understanding manner of $\mathbf{q}_5(5,2,4,7,2,5)$, and details are not described herein again. In addition, with reference to Table 6, when $\mathbf{q}_5 = \frac{16}{\sqrt{1365}}e^{\frac{j\pi}{4}}\mathbf{s}_5 + \frac{16}{\sqrt{1365}}e^{\frac{j\pi}{4}}\mathbf{s}_2 + \frac{8}{\sqrt{1365}}e^{\frac{j\pi}{4}}\mathbf{s}_4 + \frac{4}{\sqrt{1365}}e^{\frac{j\pi}{4}}\mathbf{s}_7 + \frac{2}{\sqrt{1365}}e^{\frac{j\pi}{4}}\mathbf{s}_2 + \frac{1}{\sqrt{1365}}e^{\frac{j\pi}{4}}\mathbf{s}_5$, a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 26-tone RU in $\mathbf{q}_5$ is 7.0810 dB, a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 52-tone RU in $\mathbf{q}_5$ is 7.6445 dB, a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 106-tone RU in $\mathbf{q}_5$ is 6.6954 dB, a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 242-tone RU in $\mathbf{q}_5$ is 6.9515 dB, a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 484-tone RU in $\mathbf{q}_5$ is 6.5287 dB, and a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 996-tone RU in $\mathbf{q}_5$ is 7.2951 dB. Therefore, when $\mathbf{q}_5 = \frac{16}{\sqrt{1365}}e^{\frac{j\pi}{4}}\mathbf{s}_5 + \frac{16}{\sqrt{1365}}e^{\frac{j\pi}{4}}\mathbf{s}_2 + \frac{8}{\sqrt{1365}}e^{\frac{j\pi}{4}}\mathbf{s}_4 + \frac{4}{\sqrt{1365}}e^{\frac{j\pi}{4}}\mathbf{s}_7 + \frac{2}{\sqrt{1365}}e^{\frac{j\pi}{4}}\mathbf{s}_2 + \frac{1}{\sqrt{1365}}e^{\frac{j\pi}{4}}\mathbf{s}_5$, δ is 1.09×10^{-6} . Similarly, when $\mathbf{q}_5 = \frac{16}{\sqrt{1365}}e^{\frac{j\pi}{4}}\mathbf{s}_5 + \frac{16}{\sqrt{1365}}e^{\frac{j\pi}{4}}\mathbf{s}_2 + \frac{8}{\sqrt{1365}}e^{\frac{j\pi}{4}}\mathbf{s}_5 + \frac{4}{\sqrt{1365}}e^{\frac{j\pi}{4}}\mathbf{s}_1 + \frac{2}{\sqrt{1365}}e^{\frac{j\pi}{4}}\mathbf{s}_7 + \frac{1}{\sqrt{1365}}e^{\frac{j\pi}{4}}\mathbf{s}_2$, for PAPRs of $\mathbf{q}_5$ under different RUs, refer to Table 6, and δ is 4.07×10^{-6} . In addition, for remaining cases in Table 6, δ is successively 5.02×10^{-6} , 5.45×10^{-6} , 7.14×10^{-6} , 8.36×10^{-6} , 8.95×10^{-6} , and 9.02×10^{-6} from top to bottom.

Table 6: PAPRs of the first sequence and the second sequence under different RUs in Manner 6

	26-tone RU	52-tone RU	106-tone RU	242-tone RU	484-tone RU	996-tone RU
PAPRs of $\mathbf{q}_5(5,2,4,7,2,5)$ under different	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2951 dB

RUs						
PAPRs of $\mathbf{q}_5(5,2,5,1,7,2)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2951 dB
PAPRs of $\mathbf{q}_5(6,2,2,3,7,5)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2951 dB
PAPRs of $\mathbf{q}_5(3,6,6,4,5,4)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2951 dB
PAPRs of $\mathbf{q}_5(4,7,2,2,3,2)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2951 dB
PAPRs of $\mathbf{q}_5(6,1,2,3,5,4)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2951 dB
PAPRs of $\mathbf{q}_5(2,7,7,3,6,3)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2951 dB
PAPRs of $\mathbf{q}_5(1,7,5,5,4,2)$ under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2951 dB
PAPRs of the second sequence under different RUs	7.0810 dB	7.6445 dB	6.6954 dB	6.9515 dB	6.5287 dB	7.2951 dB

[00253] In a case in which the second sequence is the EHT-LTF sequence in the 4x mode at the

80 MHz bandwidth in 802.11be, for PAPRs of the first sequence and the second sequence under different RUs in Manner 7, refer to Table 7. With reference to Table 7, it can be learned that, when $u = 1$ in Manner 7, a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 26-tone RU in $\mathbf{p}_1$ is 4.1824 dB, a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 52-tone RU in $\mathbf{p}_1$ is 4.1720 dB, a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 106-tone RU in $\mathbf{p}_1$ is 4.7226 dB, a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 242-tone RU in $\mathbf{p}_1$ is 5.2664 dB, a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 484-tone RU in $\mathbf{p}_1$ is 5.6165 dB, and a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 996-tone RU in $\mathbf{p}_1$ is 6.0614 dB. Therefore, δ corresponding to $\mathbf{p}_1$ is 0.2422. Similarly, when $u = 2$ in Manner 7, for PAPRs of $\mathbf{p}_2$ under different RUs, refer to Table 7, and δ corresponding to $\mathbf{p}_2$ is 0.1989. When $u = 3$ in Manner 7, for PAPRs of $\mathbf{p}_3$ under different RUs, refer to Table 7, and δ corresponding to $\mathbf{p}_3$ is 0.2461. When $u = 4$ in Manner 7, for PAPRs of $\mathbf{p}_4$ under different RUs, refer to Table 7, and δ corresponding to $\mathbf{p}_4$ is 0.1821. When $u = 5$ in Manner 7, for PAPRs of $\mathbf{p}_5$ under different RUs, refer to Table 7, and δ corresponding to $\mathbf{p}_5$ is 0.014. In addition, in Table 7 to Table 12, a PAPR corresponding to the 26-tone RU in the second sequence is 4.1824 dB, a PAPR corresponding to the 52-tone RU in the second sequence is 4.1720 dB, a PAPR corresponding to the 106-tone RU in the second sequence is 4.7226 dB, a PAPR corresponding to the 242-tone RU in the second sequence is 5.2664 dB, a PAPR corresponding to the 484-tone RU in the second sequence is 5.6165 dB, and a PAPR corresponding to the 996-tone RU in the second sequence is 5.8192 dB. Details are not described subsequently.

Table 7: PAPRs of the first sequence and the second sequence under different RUs in Manner 7

	26-tone RU	52-tone RU	106-tone RU	242-tone RU	484-tone RU	996-tone RU
PAPRs of $\mathbf{p}_1$ under different RUs	4.1824 dB	4.1720 dB	4.7226 dB	5.2664 dB	5.6165 dB	6.0614 dB
PAPRs of $\mathbf{p}_2$ under different RUs	4.1824 dB	4.1720 dB	4.7226 dB	5.2664 dB	5.6165 dB	6.0181 dB
PAPRs of $\mathbf{p}_3$	4.1824 dB	4.1720 dB	4.7226 dB	5.2664 dB	5.6165 dB	6.0653 dB

under different RUs						
PAPRs of $\mathbf{p}_4$ under different RUs	4.1824 dB	4.1720 dB	4.7226 dB	5.2664 dB	5.6165 dB	6.0013 dB
PAPRs of $\mathbf{p}_5$ under different RUs	4.1824 dB	4.1720 dB	4.7226 dB	5.2664 dB	5.6165 dB	5.8052 dB
PAPRs of the second sequence under different RUs	4.1824 dB	4.1720 dB	4.7226 dB	5.2664 dB	5.6165 dB	5.8192 dB

[00254] In a case in which the second sequence is the EHT-LTF sequence in the 4x mode at the 80 MHz bandwidth in 802.11be, for PAPRs of the first sequence and the second sequence under different RUs in Manner 8, refer to Table 8. It may be understood that, in this application, $\mathbf{q}_6(5,5)$

5 may be understood as that $\mathbf{q}_6 = \frac{2}{\sqrt{5}}e^{\frac{j\pi}{4}}\mathbf{p}_5 + \frac{1}{\sqrt{5}}e^{\frac{j\pi}{4}}\mathbf{p}_5$. That is, t_1 is 5, and t_2 is 5. Similarly, $\mathbf{q}_6(5,1)$ may be understood as that $\mathbf{q}_6 = \frac{2}{\sqrt{5}}e^{\frac{j\pi}{4}}\mathbf{p}_5 + \frac{1}{\sqrt{5}}e^{\frac{j\pi}{4}}\mathbf{p}_1$. That is, t_1 is 5, and t_2 is 1. For others such as $\mathbf{q}_6(5,4)$ in Table 8, refer to an understanding manner of $\mathbf{q}_6(5,5)$, and details are not described herein again. In addition, with reference to Table 8, when $\mathbf{q}_6 = \frac{2}{\sqrt{5}}e^{\frac{j\pi}{4}}\mathbf{p}_5 + \frac{1}{\sqrt{5}}e^{\frac{j\pi}{4}}\mathbf{p}_5$, a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 26-tone

10 RU in $\mathbf{q}_6$ is 4.1824 dB, a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 52-tone RU in $\mathbf{q}_6$ is 4.1720 dB, a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 106-tone RU in $\mathbf{q}_6$ is 4.7226 dB, a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 242-tone RU in $\mathbf{q}_6$ is 5.2664 dB, a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 484-tone RU in $\mathbf{q}_6$ is 5.6165 dB, and a PAPR of a subsequence with a maximum PAPR in

15 subsequences corresponding to the 996-tone RU in $\mathbf{q}_6$ is 5.8052 dB. Therefore, when $\mathbf{q}_6 = \frac{2}{\sqrt{5}}e^{\frac{j\pi}{4}}\mathbf{p}_5 + \frac{1}{\sqrt{5}}e^{\frac{j\pi}{4}}\mathbf{p}_5$, δ is 0.0140. Similarly, when $\mathbf{q}_6 = \frac{2}{\sqrt{5}}e^{\frac{j\pi}{4}}\mathbf{p}_5 + \frac{1}{\sqrt{5}}e^{\frac{j\pi}{4}}\mathbf{p}_1$, for PAPRs of $\mathbf{q}_6$ under different RUs, refer to Table 8, and δ is 0.0170. In addition, for remaining cases in Table 8, δ is successively 0.0538, 0.064, 0.0783, 0.0794, and 0.1191 from top to bottom.

Table 8: PAPRs of the first sequence and the second sequence under different RUs in Manner 8

	26-tone RU	52-tone RU	106-tone RU	242-tone RU	484-tone RU	996-tone RU
PAPRs of $\mathbf{q}_6(5,5)$ under different RUs	4.1824 dB	4.1720 dB	4.7226 dB	5.2664 dB	5.6165 dB	5.8052 dB
PAPRs of $\mathbf{q}_6(5,1)$ under different RUs	4.1824 dB	4.1720 dB	4.7226 dB	5.2664 dB	5.6165 dB	5.8362 dB
PAPRs of $\mathbf{q}_6(5,4)$ under different RUs	4.1824 dB	4.1720 dB	4.7226 dB	5.2664 dB	5.6165 dB	5.8730 dB
PAPRs of $\mathbf{q}_6(5,2)$ under different RUs	4.1824 dB	4.1720 dB	4.7226 dB	5.2664 dB	5.6165 dB	5.8832 dB
PAPRs of $\mathbf{q}_6(1,5)$ under different RUs	4.1824 dB	4.1720 dB	4.7226 dB	5.2664 dB	5.6165 dB	5.8975 dB
PAPRs of $\mathbf{q}_6(5,3)$ under different RUs	4.1824 dB	4.1720 dB	4.7226 dB	5.2664 dB	5.6165 dB	5.8986 dB
PAPRs of $\mathbf{q}_6(4,5)$ under different RUs	4.1824 dB	4.1720 dB	4.7226 dB	5.2664 dB	5.6165 dB	5.9383 dB
PAPRs of the second sequence under different RUs	4.1824 dB	4.1720 dB	4.7226 dB	5.2664 dB	5.6165 dB	5.8192 dB

[00255] In a case in which the second sequence is the EHT-LTF sequence in the 4x mode at the 80 MHz bandwidth in 802.11be, for PAPRs of the first sequence and the second sequence under different RUs in Manner 9, refer to Table 9. It may be understood that, in this application, $\mathbf{q}_7(5,5,1)$ may be understood as that $\mathbf{q}_7 = \frac{4}{\sqrt{21}}e^{\frac{j\pi}{4}}\mathbf{p}_5 + \frac{2}{\sqrt{21}}e^{\frac{j\pi}{4}}\mathbf{p}_5 + \frac{1}{\sqrt{21}}e^{\frac{j\pi}{4}}\mathbf{p}_1$. That is, t_3 is 5,

t_4 is 5, and t_5 is 1. Similarly, $\mathbf{q}_7(5,1,5)$ may be understood as that $\mathbf{q}_7 = \frac{4}{\sqrt{21}}e^{\frac{j\pi}{4}}\mathbf{p}_5 + \frac{2}{\sqrt{21}}e^{\frac{j\pi}{4}}\mathbf{p}_1 + \frac{1}{\sqrt{21}}e^{\frac{j\pi}{4}}\mathbf{p}_5$. That is, t_3 is 5, t_4 is 1, and t_5 is 5. For others such as $\mathbf{q}_7(1,7,6)$ in Table 9, refer to an understanding manner of $\mathbf{q}_7(1,6,7)$, and details are not described herein again.

In addition, with reference to Table 9, when $\mathbf{q}_7 = \frac{4}{\sqrt{21}}e^{\frac{j\pi}{4}}\mathbf{p}_5 + \frac{2}{\sqrt{21}}e^{\frac{j\pi}{4}}\mathbf{p}_5 + \frac{1}{\sqrt{21}}e^{\frac{j\pi}{4}}\mathbf{p}_1$, a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 26-tone RU in $\mathbf{q}_7$ is 4.1824 dB, a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 52-tone RU in $\mathbf{q}_7$ is 4.1720 dB, a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 106-tone RU in $\mathbf{q}_7$ is 4.7226 dB, a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 242-tone RU in $\mathbf{q}_7$ is 5.2664 dB, a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 484-tone RU in $\mathbf{q}_7$ is 5.6165 dB, and a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 996-tone RU in $\mathbf{q}_7$ is 5.8195 dB. Therefore, when $\mathbf{q}_7 = \frac{4}{\sqrt{21}}e^{\frac{j\pi}{4}}\mathbf{p}_5 + \frac{2}{\sqrt{21}}e^{\frac{j\pi}{4}}\mathbf{p}_5 + \frac{1}{\sqrt{21}}e^{\frac{j\pi}{4}}\mathbf{p}_1$, δ is 0.0003. Similarly, when $\mathbf{q}_7 = \frac{4}{\sqrt{21}}e^{\frac{j\pi}{4}}\mathbf{p}_5 + \frac{2}{\sqrt{21}}e^{\frac{j\pi}{4}}\mathbf{p}_1 + \frac{1}{\sqrt{21}}e^{\frac{j\pi}{4}}\mathbf{p}_5$, for PAPRs of $\mathbf{q}_7$ under different RUs, refer to Table 9, and δ is 0.0131. In addition, for remaining cases in Table 9, δ is successively 0.0140, 0.0153, 0.6005, 0.0243, and 0.0268 from top to bottom.

Table 9: PAPRs of the first sequence and the second sequence under different RUs in Manner 9

	26-tone RU	52-tone RU	106-tone RU	242-tone RU	484-tone RU	996-tone RU
PAPRs of $\mathbf{q}_7(5,5,1)$ under different RUs	4.1824 dB	4.1720 dB	4.7226 dB	5.2664 dB	5.6165 dB	5.8195 dB
PAPRs of $\mathbf{q}_7(5,1,5)$ under different RUs	4.1824 dB	4.1720 dB	4.7226 dB	5.2664 dB	5.6165 dB	5.8323 dB
PAPRs of $\mathbf{q}_7(5,5,5)$ under different RUs	4.1824 dB	4.1720 dB	4.7226 dB	5.2664 dB	5.6165 dB	5.8052 dB
PAPRs of $\mathbf{q}_7(5,5,4)$ under different RUs	4.1824 dB	4.1720 dB	4.7226 dB	5.2664 dB	5.6165 dB	5.8345 dB
PAPRs of $\mathbf{q}_7(5,5,2)$ under different RUs	4.1824 dB	4.1720 dB	4.7226 dB	5.2664 dB	5.6165 dB	5.8397 dB

PAPRs of $\mathbf{q}_7(5,1,1)$ under different RUs	4.1824 dB	4.1720 dB	4.7226 dB	5.2664 dB	5.6165 dB	5.8435 dB
PAPRs of $\mathbf{q}_7(5,5,3)$ under different RUs	4.1824 dB	4.1720 dB	4.7226 dB	5.2664 dB	5.6165 dB	5.8460 dB
PAPRs of the second sequence under different RUs	4.1824 dB	4.1720 dB	4.7226 dB	5.2664 dB	5.6165 dB	5.8192 dB

[00256] In a case in which the second sequence is the EHT-LTF sequence in the 4x mode at the 80 MHz bandwidth in 802.11be, for PAPRs of the first sequence and the second sequence under different RUs in Manner 10, refer to Table 10. It may be understood that, in this application,

5 $\mathbf{q}_8(5,5,5,4)$ may be understood as that $\mathbf{q}_8 = \frac{8}{\sqrt{85}}e^{\frac{j\pi}{4}}\mathbf{p}_5 + \frac{4}{\sqrt{85}}e^{\frac{j\pi}{4}}\mathbf{p}_5 + \frac{2}{\sqrt{85}}e^{\frac{j\pi}{4}}\mathbf{p}_5 + \frac{1}{\sqrt{85}}e^{\frac{j\pi}{4}}\mathbf{p}_4$. That is, t_6 is 5, t_7 is 5, t_8 is 5, and t_9 is 4. Similarly, $\mathbf{q}_8(5,5,1,5)$ may be understood as that $\mathbf{q}_8 = \frac{8}{\sqrt{85}}e^{\frac{j\pi}{4}}\mathbf{p}_5 + \frac{4}{\sqrt{85}}e^{\frac{j\pi}{4}}\mathbf{p}_5 + \frac{2}{\sqrt{85}}e^{\frac{j\pi}{4}}\mathbf{p}_1 + \frac{1}{\sqrt{85}}e^{\frac{j\pi}{4}}\mathbf{p}_5$. That is, t_6 is 5, t_7 is 5, t_8 is 1, and t_9 is 5. For others such as $\mathbf{q}_8(5,5,5,2)$ in Table 10, refer to an understanding manner of $\mathbf{q}_8(5,5,5,4)$, and details are not described herein again. In addition, with reference to Table 10, when $\mathbf{q}_8 =$

10 $\frac{8}{\sqrt{85}}e^{\frac{j\pi}{4}}\mathbf{p}_5 + \frac{4}{\sqrt{85}}e^{\frac{j\pi}{4}}\mathbf{p}_5 + \frac{2}{\sqrt{85}}e^{\frac{j\pi}{4}}\mathbf{p}_5 + \frac{1}{\sqrt{85}}e^{\frac{j\pi}{4}}\mathbf{p}_4$, a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 26-tone RU in $\mathbf{q}_8$ is 4.1824 dB, a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 52-tone RU in $\mathbf{q}_8$ is 4.1720 dB, a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 106-tone RU in $\mathbf{q}_8$ is 4.7226 dB, a PAPR of a subsequence with a maximum PAPR in subsequences

15 corresponding to the 242-tone RU in $\mathbf{q}_8$ is 5.2664 dB, a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 484-tone RU in $\mathbf{q}_8$ is 5.6165 dB, and a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 996-tone RU in $\mathbf{q}_8$ is 5.8189 dB. Therefore, when $\mathbf{q}_8 = \frac{8}{\sqrt{85}}e^{\frac{j\pi}{4}}\mathbf{p}_5 + \frac{4}{\sqrt{85}}e^{\frac{j\pi}{4}}\mathbf{p}_5 + \frac{2}{\sqrt{85}}e^{\frac{j\pi}{4}}\mathbf{p}_5 + \frac{1}{\sqrt{85}}e^{\frac{j\pi}{4}}\mathbf{p}_4$, δ is 0.0003. Similarly, when $\mathbf{q}_8 = \frac{8}{\sqrt{85}}e^{\frac{j\pi}{4}}\mathbf{p}_5 + \frac{4}{\sqrt{85}}e^{\frac{j\pi}{4}}\mathbf{p}_5 + \frac{2}{\sqrt{85}}e^{\frac{j\pi}{4}}\mathbf{p}_1 + \frac{1}{\sqrt{85}}e^{\frac{j\pi}{4}}\mathbf{p}_5$, for PAPRs of $\mathbf{q}_8$ under

20 different RUs, refer to Table 10, and δ is 0.0006. In addition, for remaining cases in Table 10, δ is successively 0.0023, 0.0052, 0.0057, 0.0071, 0.0115, and 0.0130 from top to bottom.

**Table 10: PAPRs of the first sequence and the second sequence under different RUs in
Manner 10**

	26-tone RU	52-tone RU	106-tone RU	242-tone RU	484-tone RU	996-tone RU
PAPRs of $\mathbf{q}_8(5,5,5,4)$ under different RUs	4.1824 dB	4.1720 dB	4.7226 dB	5.2664 dB	5.6165 dB	5.8189 dB
PAPRs of $\mathbf{q}_8(5,5,1,5)$ under different RUs	4.1824 dB	4.1720 dB	4.7226 dB	5.2664 dB	5.6165 dB	5.8186 dB
PAPRs of $\mathbf{q}_8(5,5,5,2)$ under different RUs	4.1824 dB	4.1720 dB	4.7226 dB	5.2664 dB	5.6165 dB	5.8215 dB
PAPRs of $\mathbf{q}_8(5,5,5,3)$ under different RUs	4.1824 dB	4.1720 dB	4.7226 dB	5.2664 dB	5.6165 dB	5.8244 dB
PAPRs of $\mathbf{q}_8(5,5,1,1)$ under different RUs	4.1824 dB	4.1720 dB	4.7226 dB	5.2664 dB	5.6165 dB	5.8249 dB
PAPRs of $\mathbf{q}_8(5,5,5,1)$ under different RUs	4.1824 dB	4.1720 dB	4.7226 dB	5.2664 dB	5.6165 dB	5.8121 dB
PAPRs of $\mathbf{q}_8(5,1,5,5)$ under different RUs	4.1824 dB	4.1720 dB	4.7226 dB	5.2664 dB	5.6165 dB	5.8307 dB
PAPRs of $\mathbf{q}_8(5,5,1,4)$ under different RUs	4.1824 dB	4.1720 dB	4.7226 dB	5.2664 dB	5.6165 dB	5.8322 dB
PAPRs of the second sequence under different RUs	4.1824 dB	4.1720 dB	4.7226 dB	5.2664 dB	5.6165 dB	5.8192 dB

[00257] In a case in which the second sequence is the EHT-LTF sequence in the 4x mode at the

80 MHz bandwidth in 802.11be, for PAPRs of the first sequence and the second sequence under different RUs in Manner 11, refer to Table 11. It may be understood that, in this application,

$\mathbf{q}_9(5,5,5,1,2)$ may be understood as that $\mathbf{q}_9 = \frac{16}{\sqrt{341}}e^{\frac{j\pi}{4}}\mathbf{p}_5 + \frac{8}{\sqrt{341}}e^{\frac{j\pi}{4}}\mathbf{p}_5 + \frac{4}{\sqrt{341}}e^{\frac{j\pi}{4}}\mathbf{p}_5 + \frac{2}{\sqrt{341}}e^{\frac{j\pi}{4}}\mathbf{p}_1 + \frac{1}{\sqrt{345}}e^{\frac{j\pi}{4}}\mathbf{p}_2$. That is, t_{10} is 5, t_{11} is 5, t_{12} is 5, t_{13} is 1, and t_{14} is 2.

5 Similarly, $\mathbf{q}_9(5,5,5,1,4)$ may be understood as that $\mathbf{q}_9 = \frac{16}{\sqrt{341}}e^{\frac{j\pi}{4}}\mathbf{p}_5 + \frac{8}{\sqrt{341}}e^{\frac{j\pi}{4}}\mathbf{p}_5 + \frac{4}{\sqrt{341}}e^{\frac{j\pi}{4}}\mathbf{p}_5 + \frac{2}{\sqrt{341}}e^{\frac{j\pi}{4}}\mathbf{p}_1 + \frac{1}{\sqrt{345}}e^{\frac{j\pi}{4}}\mathbf{p}_4$. That is, t_{10} is 5, t_{11} is 5, t_{12} is 5, t_{13} is 1, and t_{14}

is 4. For others such as $\mathbf{q}_9(5,5,5,4,5)$ in Table 11, refer to an understanding manner of $\mathbf{q}_9(5,5,5,1,2)$, and details are not described herein again. In addition, with reference to Table 11,

when $\mathbf{q}_9 = \frac{16}{\sqrt{341}}e^{\frac{j\pi}{4}}\mathbf{p}_5 + \frac{8}{\sqrt{341}}e^{\frac{j\pi}{4}}\mathbf{p}_5 + \frac{4}{\sqrt{341}}e^{\frac{j\pi}{4}}\mathbf{p}_5 + \frac{2}{\sqrt{341}}e^{\frac{j\pi}{4}}\mathbf{p}_1 + \frac{1}{\sqrt{345}}e^{\frac{j\pi}{4}}\mathbf{p}_2$, a PAPR of a

10 subsequence with a maximum PAPR in subsequences corresponding to the 26-tone RU in $\mathbf{q}_9$ is 4.1824 dB, a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 52-tone RU in $\mathbf{q}_9$ is 4.1720 dB, a PAPR of a subsequence with a maximum PAPR in

subsequences corresponding to the 106-tone RU in $\mathbf{q}_9$ is 4.7226 dB, a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 242-tone RU in $\mathbf{q}_9$ is 5.2664 dB, a

15 PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 484-tone RU in $\mathbf{q}_9$ is 5.6165 dB, and a PAPR of a subsequence with a maximum PAPR in subsequences

corresponding to the 996-tone RU in $\mathbf{q}_9$ is 5.8197 dB. Therefore, when $\mathbf{q}_9 = \frac{16}{\sqrt{341}}e^{\frac{j\pi}{4}}\mathbf{p}_5 +$

$\frac{8}{\sqrt{341}}e^{\frac{j\pi}{4}}\mathbf{p}_5 + \frac{4}{\sqrt{341}}e^{\frac{j\pi}{4}}\mathbf{p}_5 + \frac{2}{\sqrt{341}}e^{\frac{j\pi}{4}}\mathbf{p}_1 + \frac{1}{\sqrt{345}}e^{\frac{j\pi}{4}}\mathbf{p}_2$, δ is 0.0002. Similarly, when $\mathbf{q}_9 =$

$\frac{16}{\sqrt{341}}e^{\frac{j\pi}{4}}\mathbf{p}_5 + \frac{8}{\sqrt{341}}e^{\frac{j\pi}{4}}\mathbf{p}_5 + \frac{4}{\sqrt{341}}e^{\frac{j\pi}{4}}\mathbf{p}_5 + \frac{2}{\sqrt{341}}e^{\frac{j\pi}{4}}\mathbf{p}_1 + \frac{1}{\sqrt{345}}e^{\frac{j\pi}{4}}\mathbf{p}_4$, for PAPRs of $\mathbf{q}_9$ under

20 different RUs, refer to Table 11, and δ is 0.0007. In addition, for remaining cases in Table 11, δ is successively 0.0008, 0.0010, 0.0017, 0.0018, 0.0020, and 0.0026 from top to bottom.

Table 11: PAPRs of the first sequence and the second sequence under different RUs in Manner 11

	26-tone RU	52-tone RU	106-tone RU	242-tone RU	484-tone RU	996-tone RU
PAPRs of $\mathbf{q}_9(5,5,5,1,2)$ under different RUs	4.1824 dB	4.1720 dB	4.7226 dB	5.2664 dB	5.6165 dB	5.8197 dB
PAPRs of	4.1824 dB	4.1720 dB	4.7226 dB	5.2664 dB	5.6165 dB	5.8185 dB

$\mathbf{q}_9(5,5,5,1,4)$ under different RUs						
PAPRs of $\mathbf{q}_9(5,5,5,4,5)$ under different RUs	4.1824 dB	4.1720 dB	4.7226 dB	5.2664 dB	5.6165 dB	5.8185 dB
PAPRs of $\mathbf{q}_9(5,5,1,5,5)$ under different RUs	4.1824 dB	4.1720 dB	4.7226 dB	5.2664 dB	5.6165 dB	5.8182 dB
PAPRs of $\mathbf{q}_9(5,5,5,2,5)$ under different RUs	4.1824 dB	4.1720 dB	4.7226 dB	5.2664 dB	5.6165 dB	5.8210 dB
PAPRs of $\mathbf{q}_9(5,5,5,1,3)$ under different RUs	4.1824 dB	4.1720 dB	4.7226 dB	5.2664 dB	5.6165 dB	5.8211 dB
PAPRs of $\mathbf{q}_9(5,5,1,5,1)$ under different RUs	4.1824 dB	4.1720 dB	4.7226 dB	5.2664 dB	5.6165 dB	5.8213 dB
PAPRs of $\mathbf{q}_9(5,5,5,4,1)$ under different RUs	4.1824 dB	4.1720 dB	4.7226 dB	5.2664 dB	5.6165 dB	5.8218 dB
PAPRs of the second sequence under different RUs	4.1824 dB	4.1720 dB	4.7226 dB	5.2664 dB	5.6165 dB	5.8192 dB

[00258] In a case in which the second sequence is the EHT-LTF sequence in the 4x mode at the 80 MHz bandwidth in 802.11be, for PAPRs of the first sequence and the second sequence under different RUs in Manner 12, refer to Table 12. It may be understood that, in this application,

5 $\mathbf{q}_{10}(5,5,5,1,2,5)$ may be understood as that $\mathbf{q}_{10} = \frac{16}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{p}_5 + \frac{16}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{p}_5 + \frac{8}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{p}_5 + \frac{4}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{p}_1 + \frac{2}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{p}_2 + \frac{1}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{p}_5$. That is, t_{15} is 5, t_{16} is 5, t_{17} is 5, t_{18} is 1, t_{19} is 2, and t_{20} is 5. Similarly, $\mathbf{q}_{10}(5,5,5,1,1,3)$ may be understood as that $\mathbf{q}_{10} = \frac{16}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{p}_5 + \frac{16}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{p}_5 + \frac{8}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{p}_5 + \frac{4}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{p}_1 + \frac{2}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{p}_1 + \frac{1}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{p}_3$. That is, t_{15} is 5, t_{16} is 5, t_{17} is 5, t_{18} is 1, t_{19} is 1, and t_{20} is 3. For others such as $\mathbf{q}_{10}(5,5,1,5,5,1)$ in Table 12,

10 refer to an understanding manner of $\mathbf{q}_{10}(5,5,5,1,2,5)$, and details are not described herein again.

In addition, with reference to Table 12, it can be learned that, when $\mathbf{q}_{10} = \frac{16}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{p}_5 + \frac{16}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{p}_5 + \frac{8}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{p}_5 + \frac{4}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{p}_1 + \frac{2}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{p}_2 + \frac{1}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{p}_5$, a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 26-tone RU in $\mathbf{q}_{10}$ is 4.1824 dB, a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 52-tone RU in $\mathbf{q}_{10}$ is 4.1720 dB, a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 106-tone RU in $\mathbf{q}_{10}$ is 4.7226 dB, a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 242-tone RU in $\mathbf{q}_{10}$ is 5.2664 dB, a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 484-tone RU in $\mathbf{q}_{10}$ is 5.6165 dB, and a PAPR of a subsequence with a maximum PAPR in subsequences corresponding to the 996-tone RU in $\mathbf{q}_{10}$ is 5.8194 dB. Therefore, when $\mathbf{q}_{10} = \frac{16}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{p}_5 + \frac{16}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{p}_5 + \frac{8}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{p}_5 + \frac{4}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{p}_1 + \frac{2}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{p}_2 + \frac{1}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{p}_5$, δ is 0.0002. Similarly, when $\mathbf{q}_{10} = \frac{16}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{p}_5 + \frac{16}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{p}_5 + \frac{8}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{p}_5 + \frac{4}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{p}_1 + \frac{2}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{p}_1 + \frac{1}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{p}_3$, for PAPRs of $\mathbf{q}_{10}$ under different RUs, refer to Table 12, and δ is 0.0002. In addition, for remaining cases in Table 12, δ is successively 0.0003, 0.0003, 0.0005, 0.0006, 0.0007, and 0.0010 from top to bottom.

Table 12: PAPRs of the first sequence and the second sequence under different RUs in Manner 12

	26-tone RU	52-tone RU	106-tone RU	242-tone RU	484-tone RU	996-tone RU
PAPRs of $\mathbf{q}_{10}(5,2,4,7,2,5)$ under different RUs	4.1824 dB	4.1720 dB	4.7226 dB	5.2664 dB	5.6165 dB	5.8194 dB
PAPRs of $\mathbf{q}_{10}(5,2,5,1,7,2)$ under different RUs	4.1824 dB	4.1720 dB	4.7226 dB	5.2664 dB	5.6165 dB	5.8194 dB
PAPRs of $\mathbf{q}_{10}(6,2,2,3,7,5)$ under different RUs	4.1824 dB	4.1720 dB	4.7226 dB	5.2664 dB	5.6165 dB	5.8195 dB

RUs						
PAPRs of $q_{10}(3,6,6,4,5,4)$ under different RUs	4.1824 dB	4.1720 dB	4.7226 dB	5.2664 dB	5.6165 dB	5.8189 dB
PAPRs of $q_{10}(4,7,2,2,3,2)$ under different RUs	4.1824 dB	4.1720 dB	4.7226 dB	5.2664 dB	5.6165 dB	5.8187 dB
PAPRs of $q_{10}(6,1,2,3,5,4)$ under different RUs	4.1824 dB	4.1720 dB	4.7226 dB	5.2664 dB	5.6165 dB	5.8199 dB
PAPRs of $q_{10}(2,7,7,3,6,3)$ under different RUs	4.1824 dB	4.1720 dB	4.7226 dB	5.2664 dB	5.6165 dB	5.8199 dB
PAPRs of $q_{10}(1,7,5,5,4,2)$ under different RUs	4.1824 dB	4.1720 dB	4.7226 dB	5.2664 dB	5.6165 dB	5.8183 dB
PAPRs of the second sequence under different RUs	4.1824 dB	4.1720 dB	4.7226 dB	5.2664 dB	5.6165 dB	5.8192 dB

[00259] The foregoing mainly describes the solutions provided in this application from the perspective of interaction between devices. It may be understood that, to implement the foregoing functions, each device includes a corresponding hardware structure and/or software module for performing each function. A person skilled in the art should be easily aware that units and algorithm steps in the examples described with reference to embodiments disclosed in this specification may be implemented in a form of hardware or in a form of a combination of hardware and computer software in this application. Whether a function is performed by hardware or hardware driven by computer software depends on a particular application and a design constraint of technical solutions. A person skilled in the art may use different methods to implement the

described functions for each particular application, but it should not be considered that the implementation goes beyond the scope of this application.

[00260] In embodiments of this application, the AP or the STA may be divided into functional modules based on the foregoing method examples. For example, each functional module may be obtained through division based on a corresponding function, or two or more functions may be integrated into one processing module. The integrated module may be implemented in a form of hardware, or may be implemented in a form of a software functional module. It should be noted that, in embodiments of this application, division into the modules is an example and is merely logical function division. In actual implementation, another division manner may be used.

[00261] When an integrated module is used, FIG. 8 is a schematic diagram of a structure of a communication apparatus according to an embodiment of this application. A communication apparatus 800 may be applied to the method shown in FIG. 6. As shown in FIG. 8, the communication apparatus 800 includes a processing module 801 and a transceiver module 802. The processing module 801 may be one or more processors, and the transceiver module 802 may be a transceiver or a communication interface. The communication apparatus may be configured to implement the AP or the STA in any one of the foregoing method embodiments, or configured to implement functions of the network element in any one of the foregoing method embodiments. The network element or network function may be a network element in a hardware device, a software function running on dedicated hardware, or a virtualization function instantiated on a platform (for example, a cloud platform). Optionally, the communication apparatus 800 may further include a storage module 803, configured to store program code and data that are of the communication apparatus 800.

[00262] In an instance, when the communication apparatus is used as a STA or a chip applied to a STA, and performs the steps performed by the STA in the foregoing method embodiments, the transceiver module 802 is configured to support communication with an AP and the like, and the transceiver module specifically performs a sending and/or receiving action performed by the STA in FIG. 6. For example, the transceiver module supports the STA in performing step 602, and/or is configured to perform another process of the technology described in this specification. The processing module 801 may be configured to support the communication apparatus 800 in performing the processing actions in the foregoing method embodiments. For example, the processing module supports the STA in performing step 603, and/or performs another process of the technology described in this specification.

[00263] For example, the processing module 801 is configured to generate a sounding frame. The sounding frame includes a first field, the first field includes a predefined first sequence, the first sequence includes a sequence obtained after a second sequence is modulated by using at least

one of the following modulation modes, and the modulation modes include: quadrature phase shift keying QPSK, 16-quadrature amplitude modulation 16-QAM, 64-QAM, 256-QAM, 1024-QAM, and 4096-QAM. The transceiver module 802 is configured to send the sounding frame. For the first sequence, refer to related descriptions in FIG. 7. Details are not described herein again.

5 **[00264]** In an instance, when the communication apparatus is used as an AP or a chip applied to an AP, and performs the steps performed by the AP in the foregoing method embodiments, the transceiver module 802 is configured to support communication with a STA and the like, and the transceiver module specifically performs a sending and/or receiving action performed by the AP in FIG. 6. For example, the transceiver module supports the AP in performing step 601, and/or is
10 configured to perform another process of the technology described in this specification. The processing module 801 may be configured to support the communication apparatus 800 in performing the processing actions in the foregoing method embodiments. For example, the processing module supports the AP in performing another process of the technology described in this specification.

15 **[00265]** For example, the transceiver module 802 is configured to receive a sounding frame. The sounding frame includes a first field, the first field includes a predefined first sequence, the first sequence includes a sequence obtained after a second sequence is modulated by using at least one of the following modulation modes, and the modulation modes include: quadrature phase shift keying QPSK, 16-quadrature amplitude modulation 16-QAM, 64-QAM, 256-QAM, 1024-QAM,
20 and 4096-QAM. The processing module 801 is configured to perform channel measurement based on the first sequence. For the first sequence, refer to related descriptions in FIG. 7. Details are not described herein again.

[00266] In a possible implementation, when the STA or the AP is a chip, the transceiver module 802 may be an input/output interface, a pin, a circuit, or the like. For example, the input/output
25 interface may be configured to input to-be-processed data to a logic circuit, and may output a processing result of the logic circuit to the outside. During specific implementation, the input/output interface may be a general purpose input output (general purpose input output, GPIO) interface, and may be connected to a plurality of peripheral devices (for example, a display (LCD), a camera (camera), a radio frequency (radio frequency, RF) module, and an antenna). The
30 input/output interface is connected to the processor by using a bus.

[00267] The processing module 801 may be a logic circuit, and the logic circuit may execute stored instructions, so that the chip performs the method according to the embodiment shown in FIG. 6. It may be understood that the instructions may be stored in the storage module.

[00268] The storage module may be a storage module inside the chip, for example, a register or
35 a cache. Alternatively, the storage module may be a storage module located outside the chip, for

example, a read-only memory (Read-Only Memory, ROM), another type of static storage device that can store static information and instructions, or a random access memory (Random Access Memory, RAM).

[00269] It should be noted that a function corresponding to each of the logic circuit and the input/output interface may be implemented by using a hardware design, may be implemented by using a software design, or may be implemented by a combination of software and hardware. This is not limited herein.

[00270] An embodiment of this application further provides a communication apparatus, including a processor and a transceiver. The processor is configured to support the communication apparatus in performing the embodiment shown in FIG. 6. The transceiver is configured to support communication between the communication apparatus and another communication apparatus other than the communication apparatus. The communication apparatus may further include a memory. The memory is configured to be coupled to the processor, and the memory stores program instructions and data that are necessary for the communication apparatus. The transceiver may be integrated into the communication apparatus or independent of the communication apparatus. This is not limited herein. For example, in a distributed scenario, the transceiver may be disposed remotely independent of the communication apparatus.

[00271] An embodiment of this application further provides a chip. The chip includes at least one logic circuit and an input/output interface. The logic circuit is configured to read and execute stored instructions. When the instructions are run, the chip is enabled to perform the embodiment shown in FIG. 6.

[00272] An embodiment of this application further provides a computer-readable storage medium. The computer-readable storage medium stores a computer program, the computer program includes program instructions, and when the program instructions are executed by a computer, the computer is enabled to perform the embodiment shown in FIG. 6.

[00273] An embodiment of this application further provides a computer program product including instructions. When the computer program product is run on a computer, the computer is enabled to implement the embodiment shown in FIG. 6.

[00274] The foregoing units described as separate parts may or may not be physically separate, and parts displayed as units may or may not be physical units, may be located in one position, or may be distributed on a plurality of network units. Some or all of the units may be selected based on an actual requirement, to achieve the objectives of the solutions in embodiments of this application. In addition, the network element units in embodiments of this application may be integrated into one processing unit, or each of the units may exist alone physically, or two or more units are integrated into one unit. The integrated unit may be implemented in a form of hardware,

or may be implemented in a form of a software network element unit.

[00275] When the integrated unit is implemented in the form of a software network element unit and sold or used as an independent product, the integrated unit may be stored in a computer-readable storage medium. Based on such an understanding, a part essentially contributing to the technical solutions of this application, or all or some of the technical solutions may be embodied in a form of a software product. The computer software product is stored in a storage medium, and includes several instructions for instructing a computer device (which may be a personal computer, a server, a network device, or the like) to perform all or some of the steps of the methods described in embodiments of this application. The foregoing storage medium includes any medium that can store program code, such as a USB flash drive, a removable hard disk, a read-only memory (ROM, Read-Only Memory), a random access memory (RAM, Random Access Memory), a magnetic disk, or an optical disc. The foregoing descriptions are merely specific implementations of this application, but are not intended to limit the protection scope of this application. Any equivalent modification or replacement readily figured out by a person skilled in the art within the technical scope disclosed in this application shall fall within the protection scope of this application. Therefore, the protection scope of this application shall be subject to the protection scope of the claims.

CLAIMS

What is claimed is:

1. A sounding frame transmission method, wherein the method is applied to a first device, and the method comprises:

5 generating a sounding frame, wherein the sounding frame comprises a first field, the first field comprises a predefined first sequence, the first sequence comprises a sequence obtained after a second sequence is modulated by using at least one of the following modulation modes, and the modulation modes comprise: quadrature phase shift keying QPSK, 16-quadrature amplitude modulation 16-QAM, 64-QAM, 256-QAM, 1024-QAM, and 4096-QAM; and
10 sending the sounding frame.

2. A sounding frame transmission method, wherein the method is applied to a second device, and the method comprises:

 receiving a sounding frame, wherein the sounding frame comprises a first field, the first field comprises a predefined first sequence, the first sequence comprises a sequence obtained after a
15 second sequence is modulated by using at least one of the following modulation modes, and the modulation modes comprise: quadrature phase shift keying QPSK, 16-quadrature amplitude modulation 16-QAM, 64-QAM, 256-QAM, 1024-QAM, and 4096-QAM; and
 performing channel measurement based on the first sequence.

3. The method according to claim 1 or 2, wherein the second sequence is a high efficiency
20 long training field HE-LTF sequence or an extremely high throughput long training field EHT-LTF sequence in a 4x mode at an 80 MHz bandwidth;

 the HE-LTF sequence is:

 HE – LTF_{4x}(–500:500) =

 [1, –1, –1, –1, –1, 1, –1, –1, 1, –1, –1, –1, 1, 1, –1, –1, –1, 1, –1, –1, 1, –1, 1, 1, –1, 1, –1,
25 1, –1, –1, –1, –1, 1, 1, 1, 1, 1, –1, –1, 1, –1, 1, –1, –1, 1, 1, –1, –1, 1, –1, –1, 1, 1, 1, –1, –
1, 1, 1, –1, –1, 1, –1, 1, 1, –1, 1, –1, 1, 1, –1, 1, –1, 1, 1, 1, 1, –1, –1, 1, –1, 1, –1, –1, –
1, 1, –1, –1, 1, 1, 1, 1, 1, 1, –1, 1, –1, 1, 1, –1, 1, –1, 1, –1, 1, –1, –1, 1, 1, 1, –1, –1, –
1, –1, –1, –1, –1, 1, –1, –1, 1, –1, –1, 1, 1, 1, –1, 1, –1, –1, 1, 1, 1, –1, 1, –1, –1, 1, –1, –1, –
1, 1, 1, 1, 1, –1, 1, 1, 1, 1, 1, –1, 1, –1, –1, 1, –1, 1, –1, 1, 1, 1, 1, –1, 1, 1, –1, 1, –1, –1, –
30 –1, 1, 1, –1, 1, 1, –1, –1, 1, 1, –1, –1, –1, 1, 1, 1, 1, 1, –1, 1, 1, 1, 1, –1, 1, –1, 1, –1, –1, 1, –
1, –1, –1, –1, –1, 1, –1, –1, –1, 1, 1, –1, 1, –1, 1, –1, –1, –1, 1, 1, 1, 1, –1, 1, –1, –1, 1, 1, –
1, –1, –1, 1, 1, 1, 1, 1, –1, 1, –1, 1, –1, –1, 1, 1, 1, 1, 1, 1, –1, 1, 1, –1, 1, –1, 1, –1, –1, –
1, –1, –1, 1, –1, –1, –1, –1, 1, 1, 1, 1, –1, –1, 1, 1, –1, –1, 1, –1, –1, 1, 1, –1, 1, –1, –1, –
1, –1, –1, –1, –1, 1, 1, –1, 1, –1, 1, 1, –1, 1, –1, –1, –1, –1, 1, 1, 1, 1, –1, 1, –1, –1, 1, 1, –

1, 1, 1, -1, -1, 1, -1, -1, -1, 1, 1, 1, -1, 1, -1, 1, -1, -1, -1, 1, -1, 1, -1, 1, -1, -1, -1, 1, -1, -1, 1,
-1, 1, 1, -1, -1, -1, 1, 1, -1, -1, -1, -1, 1, -1, 1, 1, -1, 1, -1, 1, 1, 1, 1, 1, -1, -1, 1, -1, -1, -1,
1, -1, 1, -1, -1, -1, 1, 1, 1, 1, 1, 1, -1, 1, -1, 1, 1, 1, -1, 1, -1, -1, 1, 1, -1, -1, 1, 1,
1, -1, -1, -1, 1, -1, -1, 1, 1, -1, -1, -1, 1, -1, 1, -1, -1, 1, 1, 1, 1, 1, -1, -1, -1, -1, 1, -1, 1, -1, 1,
5 1, 1, -1, 1, -1, -1, 1, -1, -1, -1, 1, 1, -1, -1, -1, 1, -1, -1, -1, -1, 1, -1, 1, 1, -1, -1, -
1, 1, -1, -1, 0, 0, 0, 0, 0, -1, -1, 1, -1, 1, 1, 1, 1, 1, -1, -1, -1, -1, 1, -1, -1, 1, -1, -1, -1, 1, 1,
-1, -1, -1, 1, -1, -1, 1, -1, 1, 1, 1, -1, 1, -1, 1, -1, -1, -1, 1, 1, 1, 1, 1, -1, -1, 1, -1, 1, -1, -
1, -1, 1, 1, -1, -1, 1, -1, -1, -1, 1, 1, 1, -1, -1, 1, 1, -1, -1, 1, -1, 1, 1, -1, 1, 1, -1, 1, -
1, 1, 1, 1, 1, 1, 1, -1, -1, -1, 1, -1, 1, -1, -1, -1, 1, -1, -1, 1, 1, 1, 1, 1, -1, 1, -1, 1, -1, 1, -
10 1, -1, -1, -1, 1, 1, -1, -1, -1, 1, 1, -1, 1, -1, -1, 1, -1, -1, -1, 1, -1, 1, -1, -1, -1, 1, -1, 1,
-1, 1, 1, 1, -1, -1, -1, 1, -1, -1, 1, 1, -1, 1, 1, 1, -1, -1, -1, -1, 1, -1, -1, -1, -1, 1, -1, 1,
1, -1, 1, -1, 1, 1, -1, -1, -1, -1, -1, 1, -1, -1, 1, 1, -1, -1, -1, 1, -1, -1, 1, 1, -1, -1, 1,
1, 1, 1, -1, -1, -1, -1, -1, 1, -1, -1, -1, -1, -1, 1, -1, 1, -1, 1, 1, 1, 1, 1, 1, -1, 1, 1, 1, -1, -
1, 1, -1, 1, -1, 1, 1, 1, 1, 1, -1, -1, -1, 1, 1, -1, -1, -1, -1, -1, 1, 1, 1, 1, 1, -1, 1, -1, 1,
15 -1, -1, 1, 1, 1, -1, 1, 1, 1, 1, 1, -1, 1, 1, -1, 1, -1, -1, -1, -1, 1, -1, -1, -1, -1, 1, -1, 1,
1, 1, -1, -1, 1, 1, -1, -1, 1, -1, -1, 1, -1, -1, -1, 1, 1, -1, -1, -1, -1, -1, 1, 1, -1, 1, -1,
1, 1, -1, 1, -1, -1, -1, -1, -1, 1, -1, -1, -1, -1, 1, 1, 1, -1, 1, 1, -1, -1, 1, -1, -1, 1, 1, -
1, 1, -1, -1, -1, 1, 1, -1, 1, 1, -1, 1, 1, 1, 1, 1, 1, 1, -1, -1, -1, -1, 1, 1, -1, 1, -1, 1,
-1, -1, 1, -1, 1, -1, -1, -1, -1, -1, 1, 1, -1, 1, 1, 1, -1, 1, -1, 1, 1, 1, -1, -1, -1, -1, -1, 1,
20 -1, 1, -1, -1, -1, 1, -1, 1, -1, -1, 1, -1, 1, 1, -1, -1, 1, 1, -1, -1, 1, 1, 1, -1, 1, 1, -1, -1, 1, 1,
1, -1, 1, -1, 1, 1, -1, -1, -1, -1, -1, 1, 1, 1, 1, -1, 1, -1, 1, -1, -1, -1, 1, -1, 1, 1, 1, -1, -
1, 1, 1, 1, -1, 1, 1, -1, 1, 1, 1, 1, 1, 1, 1, 1, -1, -1, -1, -1, 1, 1, -1, 1, -1, 1, -1, 1,
-1, -1, 1, -1, 1, -1, -1, -1, -1, -1, 1, 1, -1, 1, 1, 1, -1, 1, -1, 1, 1, 1, -1, -1, -1, -1, -1, 1,
-1, 1, -1, -1, -1, 1, -1, 1, -1, -1, 1, -1, 1, 1, -1, -1, 1, 1, 1, -1, 1, 1, -1, -1, 1, 1,
1, -1, 1, -1, 1, 1, -1, -1, -1, -1, -1, 1, 1, 1, 1, -1, 1, -1, 1, -1, -1, -1, 1, -1, 1, 1, 1, -1, -
1, 1, 1, 1, -1, 1, 1, -1, 1, 1, 1, 1, 1, 1, -1]; and

the EHT-LTF sequence is:

EHT - LTF_{4x}(-500:500) =
[1, -1, -1, -1, -1, 1, -1, -1, 1, -1, -1, -1, 1, 1, -1, -1, -1, 1, -1, -1, 1, -1, 1, 1, 1, -1, 1, -1,
1, -1, -1, -1, -1, 1, 1, 1, 1, 1, -1, -1, 1, -1, 1, -1, -1, -1, 1, 1, -1, -1, -1, 1, 1, 1, -1, -
1, 1, 1, -1, -1, 1, -1, 1, 1, -1, 1, -1, 1, 1, 1, -1, 1, -1, 1, 1, 1, 1, 1, 1, -1, -1, -1, 1, -1, 1, -1, -
1, 1, -1, -1, 1, 1, 1, 1, 1, 1, -1, 1, -1, 1, 1, -1, 1, -1, 1, -1, 1, -1, 1, 1, 1, -1, -1, -1, -
1, -1, -1, -1, -1, 1, -1, -1, 1, -1, -1, 1, 1, 1, -1, 1, -1, -1, -1, 1, 1, 1, -1, 1, 1, -1, -1, 1, -1, -
30 1, 1, 1, 1, 1, -1, 1, 1, 1, 1, 1, 1, -1, 1, -1, -1, 1, -1, -1, 1, 1, 1, 1, 1, -1, 1, 1, -1, -1, 1, 1,
-1, 1, 1, -1, 1, 1, -1, -1, 1, 1, -1, -1, -1, -1, 1, 1, 1, 1, 1, -1, 1, 1, 1, 1, 1, -1, 1, -1, -1, 1, -
1, -1, -1, -1, -1, 1, -1, -1, -1, 1, 1, -1, 1, -1, 1, -1, -1, -1, -1, 1, 1, 1, 1, -1, 1, -1, -1, 1, 1, -
1, -1, -1, 1, 1, 1, 1, 1, -1, 1, -1, 1, -1, -1, 1, 1, 1, -1, 1, 1, 1, 1, 1, -1, 1, 1, -1, 1, -1, -1, -
1, -1, -1, 1, -1, -1, -1, -1, -1, 1, 1, 1, 1, -1, -1, 1, 1, -1, -1, 1, -1, -1, 1, 1, -1, -1, 1, 1, -1, -1,
35 1, -1, -1, -1, -1, -1, 1, 1, -1, 1, -1, 1, 1, -1, 1, -1, -1, -1, -1, -1, 1, -1, -1, -1, -1, 1, 1, 1, -

1, 1, 1, -1, -1, 1, -1, -1, -1, 1, 1, 1, -1, 1, -1, 1, -1, -1, -1, 1, -1, 1, -1, 1, -1, -1, -1, 1, -1, -1, 1,
-1, 1, 1, -1, -1, -1, 1, 1, -1, -1, -1, -1, 1, -1, 1, 1, -1, 1, -1, 1, 1, 1, 1, 1, -1, -1, 1, -1, -1, -1,
1, -1, 1, -1, -1, -1, 1, 1, 1, 1, 1, 1, -1, 1, -1, 1, 1, 1, -1, 1, -1, -1, 1, 1, -1, -1, 1, 1,
1, -1, -1, -1, 1, -1, -1, 1, 1, -1, -1, -1, 1, -1, 1, -1, -1, 1, 1, 1, 1, 1, -1, -1, -1, -1, 1, -1, 1, -1, 1,
5 1, 1, -1, 1, -1, -1, 1, -1, -1, -1, 1, 1, -1, -1, -1, 1, -1, -1, -1, -1, 1, -1, 1, 1, -1, -1, -
1, 1, -1, -1, 0, 0, 0, 0, 0, -1, -1, 1, -1, 1, 1, 1, 1, 1, -1, -1, -1, -1, 1, -1, -1, 1, -1, -1, -1, 1, 1,
-1, -1, -1, 1, -1, -1, 1, -1, 1, 1, 1, -1, 1, -1, 1, -1, -1, -1, 1, 1, 1, 1, 1, -1, -1, 1, -1, 1, -1, -
1, -1, 1, 1, -1, -1, 1, -1, -1, -1, 1, 1, 1, -1, -1, 1, 1, -1, -1, 1, -1, 1, 1, -1, 1, 1, -1, 1, -
1, 1, 1, 1, 1, 1, 1, -1, -1, -1, 1, -1, 1, -1, -1, -1, 1, -1, -1, 1, 1, 1, 1, 1, -1, 1, -1, 1, 1, -
10 1, -1, -1, -1, 1, 1, -1, -1, -1, 1, 1, -1, 1, -1, -1, 1, -1, -1, -1, 1, -1, 1, -1, -1, -1, 1, -1, 1,
-1, 1, 1, 1, -1, -1, -1, 1, -1, -1, 1, 1, -1, 1, 1, 1, -1, -1, -1, -1, 1, -1, -1, -1, -1, 1, -1, 1,
1, -1, 1, -1, 1, 1, -1, -1, -1, -1, -1, 1, -1, -1, 1, 1, -1, -1, -1, 1, -1, -1, 1, 1, -1, -1, 1,
1, 1, 1, -1, -1, -1, -1, -1, 1, -1, -1, -1, -1, -1, 1, -1, 1, -1, 1, 1, 1, 1, 1, 1, -1, 1, 1, 1, -1, -
1, 1, -1, 1, -1, 1, 1, 1, 1, 1, -1, -1, -1, 1, 1, -1, -1, -1, -1, -1, 1, 1, 1, 1, 1, -1, 1, -1, 1,
15 -1, -1, 1, 1, 1, -1, 1, 1, 1, 1, 1, -1, 1, 1, -1, 1, -1, -1, -1, -1, 1, -1, -1, -1, -1, 1, -1, 1,
1, 1, -1, -1, 1, 1, -1, -1, 1, -1, -1, 1, -1, -1, -1, 1, 1, -1, -1, -1, -1, -1, 1, 1, -1, 1, -1,
1, 1, -1, 1, -1, -1, -1, -1, -1, -1, 1, -1, -1, -1, -1, 1, 1, 1, -1, -1, 1, -1, -1, -1, 1, 1, 1, -
1, 1, -1, -1, -1, 1, 1, -1, 1, 1, -1, 1, 1, 1, 1, 1, 1, 1, -1, -1, -1, -1, 1, 1, -1, 1, -1, 1,
-1, -1, 1, -1, 1, -1, -1, -1, -1, -1, 1, 1, -1, 1, 1, 1, -1, 1, -1, 1, 1, 1, -1, -1, -1, -1, -1, 1,
20 -1, 1, -1, -1, -1, 1, -1, 1, -1, -1, 1, -1, 1, 1, -1, -1, 1, 1, -1, -1, 1, 1, 1, -1, 1, 1, -1, -1, 1, 1,
1, -1, 1, -1, 1, 1, -1, -1, -1, -1, -1, 1, 1, 1, 1, -1, 1, -1, 1, -1, -1, -1, 1, -1, 1, 1, 1, -1, -
1, 1, 1, 1, -1, 1, 1, -1, 1, 1, 1, 1, -1], wherein

the expression $\text{HE} - \text{LTF}_{4x}(-500:500)$ means that values on tones whose sequence numbers are -500 to 500 are values in the HE-LTF sequence successively; and the expression
25 $\text{EHT} - \text{LTF}_{4x}(-500:500)$ means that values on tones whose sequence numbers are -500 to 500 are values in the EHT-LTF sequence successively.

4. The method according to any one of claims 1 to 3, wherein the first sequence meets the following formula:

$$s_i = [\mathbf{a}_0, \mathbf{c}_i, 0, 0, 0, 0, 0, (-1j) * \mathbf{a}_1], \text{ wherein}$$

30 the second sequence is the HE-LTF sequence, $\mathbf{a}_0$ and $\mathbf{a}_1$ are subsequences in the HE-LTF sequence, j is an imaginary unit, and i is an integer greater than or equal to 1 and less than or equal to 7;

$$\mathbf{c}_1 = [1j, 1j, 1j, -1j, -1j, -1j, 1j, 1j, -1j];$$

$$\mathbf{c}_2 = [-1, -1, -1, -1j, -1j, -1j, 1j, 1j, -1j];$$

35 $\mathbf{c}_3 = [-1, -1, -1, 1, 1, -1j, 1j, 1j, -1j];$

$$\begin{aligned} \mathbf{c}_4 &= [-1, -1, -1, 1, 1, 1, 1j, 1j, -1j]; \\ \mathbf{c}_5 &= [-1, -1, -1, 1, 1, 1, -1, 1j, -1j]; \\ \mathbf{c}_6 &= [-1, -1, -1, 1, 1, 1, -1, -1, -1j]; \text{ and} \\ \mathbf{c}_7 &= [-1, -1, -1, 1, 1, 1, -1, -1, 1]. \end{aligned}$$

5 5. The method according to any one of claims 1 to 3, wherein the first sequence meets the following formula:

$$\mathbf{q}_1 = \frac{2}{\sqrt{5}} e^{\frac{j\pi}{4}} \mathbf{s}_{k1} + \frac{1}{\sqrt{5}} e^{\frac{j\pi}{4}} \mathbf{s}_{k2}, \text{ wherein}$$

$\mathbf{s}_{k1} = [\mathbf{a}_0, \mathbf{c}_{k1}, 0, 0, 0, 0, 0, (-1j) * \mathbf{a}_1] ; \quad \mathbf{s}_{k2} = [\mathbf{a}_0, \mathbf{c}_{k2}, 0, 0, 0, 0, 0, (-1j) * \mathbf{a}_1] ;$ and the second sequence is the HE-LTF sequence, $\mathbf{a}_0$ and $\mathbf{a}_1$ are subsequences in the HE-LTF sequence,
10 and j is an imaginary unit, wherein

$k1$ is 1, and $k2$ is 7; or

$k1$ is 4, and $k2$ is 5 or 6; or

$k1$ is 5, and $k2$ is 1 or 2;

$$\mathbf{c}_1 = [1j, 1j, 1j, -1j, -1j, -1j, 1j, 1j, -1j];$$

$$15 \quad \mathbf{c}_2 = [-1, -1, -1, -1j, -1j, -1j, 1j, 1j, -1j];$$

$$\mathbf{c}_4 = [-1, -1, -1, 1, 1, 1, 1j, 1j, -1j];$$

$$\mathbf{c}_5 = [-1, -1, -1, 1, 1, 1, -1, 1j, -1j];$$

$$\mathbf{c}_6 = [-1, -1, -1, 1, 1, 1, -1, -1, -1j]; \text{ and}$$

$$\mathbf{c}_7 = [-1, -1, -1, 1, 1, 1, -1, -1, 1].$$

20 6. The method according to any one of claims 1 to 3, wherein the first sequence meets the following formula:

$$\mathbf{q}_2 = \frac{4}{\sqrt{21}} e^{\frac{j\pi}{4}} \mathbf{s}_{k3} + \frac{2}{\sqrt{21}} e^{\frac{j\pi}{4}} \mathbf{s}_{k4} + \frac{1}{\sqrt{21}} e^{\frac{j\pi}{4}} \mathbf{s}_{k5}, \text{ wherein}$$

$\mathbf{s}_{k3} = [\mathbf{a}_0, \mathbf{c}_{k3}, 0, 0, 0, 0, 0, (-1j) * \mathbf{a}_1] ; \quad \mathbf{s}_{k4} = [\mathbf{a}_0, \mathbf{c}_{k4}, 0, 0, 0, 0, 0, (-1j) * \mathbf{a}_1] ; \quad \mathbf{s}_{k5} =$
25 $[\mathbf{a}_0, \mathbf{c}_{k5}, 0, 0, 0, 0, 0, (-1j) * \mathbf{a}_1];$ and the second sequence is the HE-LTF sequence, $\mathbf{a}_0$ and $\mathbf{a}_1$ are subsequences in the HE-LTF sequence, and j is an imaginary unit, wherein

$k3$ is 1, $k4$ is 6, and $k5$ is 7; or

$k3$ is 1, $k4$ is 7, and $k5$ is 5 or 6; or

$k3$ is 2, $k4$ is 7, and $k5$ is 6 or 7; or

$k3$ is 3, $k4$ is 5, and $k5$ is 6; or

30 $k3$ is 3, $k4$ is 5, and $k5$ is 7; or

$k3$ is 3, $k4$ is 6, and $k5$ is 5 or 6; or

$k3$ is 3, $k4$ is 7, and $k5$ is 1, 2, 3, or 4; or

$k3$ is 4, $k4$ is 4, and $k5$ is 7; or

$k3$ is 4, $k4$ is 5, and $k5$ is 3, 4, or 5; or
 $k3$ is 4, $k4$ is 6, and $k5$ is 1, 2, 3, or 4; or
 $k3$ is 5, $k4$ is 1, and $k5$ is 3 or 4; or
 $k3$ is 5, $k4$ is 1, and $k5$ is 5; or
 $k3$ is 5, $k4$ is 2, and $k5$ is 4, 5, or 6; or
 $k3$ is 5, $k4$ is 3, and $k5$ is 1, 2, 3, or 4; or
 $k3$ is 5, $k4$ is 4, and $k5$ is 1 or 2; or
 $k3$ is 6, $k4$ is 1, and $k5$ is 1 or 2; or
 $k3$ is 6, $k4$ is 2, and $k5$ is 1, 2, or 3;

$\mathbf{c}_1 = [1j, 1j, 1j, -1j, -1j, -1j, 1j, 1j, -1j];$
 $\mathbf{c}_2 = [-1, -1, -1, -1j, -1j, -1j, 1j, 1j, -1j];$
 $\mathbf{c}_3 = [-1, -1, -1, 1, 1, -1j, 1j, 1j, -1j];$
 $\mathbf{c}_4 = [-1, -1, -1, 1, 1, 1, 1j, 1j, -1j];$
 $\mathbf{c}_5 = [-1, -1, -1, 1, 1, 1, -1, 1j, -1j];$
 $\mathbf{c}_6 = [-1, -1, -1, 1, 1, 1, -1, -1, -1j];$ and
 $\mathbf{c}_7 = [-1, -1, -1, 1, 1, 1, -1, -1, 1].$

7. The method according to any one of claims 1 to 3, wherein the first sequence meets the following formula:

$$\mathbf{q}_3 = \frac{8}{\sqrt{85}} e^{\frac{j\pi}{4}} \mathbf{s}_{k6} + \frac{4}{\sqrt{85}} e^{\frac{j\pi}{4}} \mathbf{s}_{k7} + \frac{2}{\sqrt{85}} e^{\frac{j\pi}{4}} \mathbf{s}_{k8} + \frac{1}{\sqrt{85}} e^{\frac{j\pi}{4}} \mathbf{s}_{k9}, \text{ wherein}$$

$\mathbf{s}_{k6} = [\mathbf{a}_0, \mathbf{c}_{k6}, 0, 0, 0, 0, 0, (-1j) * \mathbf{a}_1] ; \quad \mathbf{s}_{k7} = [\mathbf{a}_0, \mathbf{c}_{k7}, 0, 0, 0, 0, 0, (-1j) * \mathbf{a}_1] ; \quad \mathbf{s}_{k8} = [\mathbf{a}_0, \mathbf{c}_{k8}, 0, 0, 0, 0, 0, (-1j) * \mathbf{a}_1]; \quad \mathbf{s}_{k9} = [\mathbf{a}_0, \mathbf{c}_{k9}, 0, 0, 0, 0, 0, (-1j) * \mathbf{a}_1];$ and the second sequence is the HE-LTF sequence, $\mathbf{a}_0$ and $\mathbf{a}_1$ are subsequences in the HE-LTF sequence, and j is an imaginary unit, wherein

$k6$ is 1, $k7$ is 7, $k8$ is 4, and $k9$ is 7; or
 $k6$ is 1, $k7$ is 7, $k8$ is 6, and $k9$ is 3; or
 $k6$ is 2, $k7$ is 7, $k8$ is 7, and $k9$ is 4; or
 $k6$ is 3, $k7$ is 5, $k8$ is 7, and $k9$ is 4; or
 $k6$ is 3, $k7$ is 6, $k8$ is 5, and $k9$ is 5; or
 $k6$ is 3, $k7$ is 7, $k8$ is 1, and $k9$ is 5; or
 $k6$ is 3, $k7$ is 7, $k8$ is 2, and $k9$ is 6; or
 $k6$ is 3, $k7$ is 7, $k8$ is 3, and $k9$ is 4; or
 $k6$ is 4, $k7$ is 4, $k8$ is 6, and $k9$ is 7; or
 $k6$ is 4, $k7$ is 6, $k8$ is 1, and $k9$ is 6; or
 $k6$ is 4, $k7$ is 6, $k8$ is 4, and $k9$ is 3; or

k_6 is 5, k_7 is 1, k_8 is 1, and k_9 is 7; or
 k_6 is 5, k_7 is 2, k_8 is 6, and k_9 is 2; or
 k_6 is 5, k_7 is 4, k_8 is 1, and k_9 is 1; or
 k_6 is 5, k_7 is 4, k_8 is 2, and k_9 is 3; or

5 k_6 is 6, k_7 is 1, k_8 is 1, and k_9 is 1;

$$\mathbf{c}_1 = [1j, 1j, 1j, -1j, -1j, -1j, 1j, 1j, -1j];$$

$$\mathbf{c}_2 = [-1, -1, -1, -1j, -1j, -1j, 1j, 1j, -1j];$$

$$\mathbf{c}_3 = [-1, -1, -1, 1, 1, -1j, 1j, 1j, -1j];$$

$$\mathbf{c}_4 = [-1, -1, -1, 1, 1, 1, 1j, 1j, -1j];$$

10 $\mathbf{c}_5 = [-1, -1, -1, 1, 1, 1, -1, 1j, -1j];$

$$\mathbf{c}_6 = [-1, -1, -1, 1, 1, 1, -1, -1, -1j]; \text{ and}$$

$$\mathbf{c}_7 = [-1, -1, -1, 1, 1, 1, -1, -1, 1].$$

8. The method according to any one of claims 1 to 3, wherein the first sequence meets the following formula:

15 $\mathbf{q}_4 = \frac{16}{\sqrt{341}} e^{\frac{j\pi}{4}} \mathbf{s}_{k_{10}} + \frac{8}{\sqrt{341}} e^{\frac{j\pi}{4}} \mathbf{s}_{k_{11}} + \frac{4}{\sqrt{341}} e^{\frac{j\pi}{4}} \mathbf{s}_{k_{12}} + \frac{2}{\sqrt{341}} e^{\frac{j\pi}{4}} \mathbf{s}_{k_{13}} + \frac{1}{\sqrt{345}} e^{\frac{j\pi}{4}} \mathbf{s}_{k_{14}},$ wherein

$\mathbf{s}_{k_{10}} = [\mathbf{a}_0, \mathbf{c}_{k_{10}}, 0, 0, 0, 0, 0, (-1j) * \mathbf{a}_1];$ $\mathbf{s}_{k_{11}} = [\mathbf{a}_0, \mathbf{c}_{k_{11}}, 0, 0, 0, 0, 0, (-1j) * \mathbf{a}_1];$ $\mathbf{s}_{k_{12}} = [\mathbf{a}_0, \mathbf{c}_{k_{12}}, 0, 0, 0, 0, 0, (-1j) * \mathbf{a}_1];$ $\mathbf{s}_{k_{13}} = [\mathbf{a}_0, \mathbf{c}_{k_{13}}, 0, 0, 0, 0, 0, (-1j) * \mathbf{a}_1];$ $\mathbf{s}_{k_{14}} = [\mathbf{a}_0, \mathbf{c}_{k_{14}}, 0, 0, 0, 0, 0, (-1j) * \mathbf{a}_1];$ and the second sequence is the HE-LTF sequence, $\mathbf{a}_0$ and $\mathbf{a}_1$ are subsequences in the HE-LTF sequence, and j is an imaginary unit, wherein

20 k_{10} is 1, k_{11} is 7, k_{12} is 6, k_{13} is 1, and k_{14} is 5; or

k_{10} is 2, k_{11} is 7, k_{12} is 5, k_{13} is 7, and k_{14} is 5; or

k_{10} is 6, k_{11} is 1, k_{12} is 2, k_{13} is 4, and k_{14} is 4; or

k_{10} is 4, k_{11} is 6, k_{12} is 4, k_{13} is 1, and k_{14} is 6; or

k_{10} is 6, k_{11} is 2, k_{12} is 1, k_{13} is 4, and k_{14} is 5; or

25 k_{10} is 3, k_{11} is 6, k_{12} is 7, k_{13} is 1, and k_{14} is 2; or

k_{10} is 5, k_{11} is 3, k_{12} is 1, k_{13} is 6, and k_{14} is 1; or

k_{10} is 4, k_{11} is 6, k_{12} is 2, k_{13} is 6, and k_{14} is 6;

$$\mathbf{c}_1 = [1j, 1j, 1j, -1j, -1j, -1j, 1j, 1j, -1j];$$

$$\mathbf{c}_2 = [-1, -1, -1, -1j, -1j, -1j, 1j, 1j, -1j];$$

30 $\mathbf{c}_3 = [-1, -1, -1, 1, 1, -1j, 1j, 1j, -1j];$

$$\mathbf{c}_4 = [-1, -1, -1, 1, 1, 1, 1j, 1j, -1j];$$

$$\mathbf{c}_5 = [-1, -1, -1, 1, 1, 1, -1, 1j, -1j];$$

$$\mathbf{c}_6 = [-1, -1, -1, 1, 1, 1, -1, -1, -1j]; \text{ and}$$

$$\mathbf{c}_7 = [-1, -1, -1, 1, 1, 1, -1, -1, 1].$$

9. The method according to any one of claims 1 to 3, wherein the first sequence meets the following formula:

$$\mathbf{q}_5 = \frac{16}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{s}_{k15} + \frac{16}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{s}_{k16} + \frac{8}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{s}_{k17} + \frac{4}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{s}_{k18} + \frac{2}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{s}_{k19} + \frac{1}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{s}_{k20}, \text{ wherein}$$

5 $\mathbf{s}_{k15} = [\mathbf{a}_0, \mathbf{c}_{k15}, 0,0,0,0,0, (-1j) * \mathbf{a}_1]$; $\mathbf{s}_{k16} = [\mathbf{a}_0, \mathbf{c}_{k16}, 0,0,0,0,0, (-1j) * \mathbf{a}_1]$; $\mathbf{s}_{k17} = [\mathbf{a}_0, \mathbf{c}_{k17}, 0,0,0,0,0, (-1j) * \mathbf{a}_1]$; $\mathbf{s}_{k18} = [\mathbf{a}_0, \mathbf{c}_{k18}, 0,0,0,0,0, (-1j) * \mathbf{a}_1]$; $\mathbf{s}_{k19} = [\mathbf{a}_0, \mathbf{c}_{k19}, 0,0,0,0,0, (-1j) * \mathbf{a}_1]$; $\mathbf{s}_{k20} = [\mathbf{a}_0, \mathbf{c}_{k20}, 0,0,0,0,0, (-1j) * \mathbf{a}_1]$; and the second sequence is the HE-LTF sequence, $\mathbf{a}_0$ and $\mathbf{a}_1$ are subsequences in the HE-LTF sequence, and j is an imaginary unit, wherein

10 $k15$ is 5, $k16$ is 2, $k17$ is 4, $k18$ is 7, $k19$ is 2, and $k20$ is 5; or
 $k15$ is 5, $k16$ is 2, $k17$ is 5, $k18$ is 1, $k19$ is 7, and $k20$ is 2; or
 $k15$ is 6, $k16$ is 2, $k17$ is 2, $k18$ is 3, $k19$ is 7, and $k20$ is 5; or
 $k15$ is 3, $k16$ is 6, $k17$ is 6, $k18$ is 4, $k19$ is 5, and $k20$ is 4; or
 $k15$ is 4, $k16$ is 7, $k17$ is 2, $k18$ is 2, $k19$ is 3, and $k20$ is 2; or
15 $k15$ is 6, $k16$ is 1, $k17$ is 2, $k18$ is 3, $k19$ is 5, and $k20$ is 4; or
 $k15$ is 2, $k16$ is 7, $k17$ is 7, $k18$ is 3, $k19$ is 6, and $k20$ is 3; or
 $k15$ is 1, $k16$ is 7, $k17$ is 5, $k18$ is 5, $k19$ is 4, and $k20$ is 2;

$\mathbf{c}_1 = [1j, 1j, 1j, -1j, -1j, -1j, 1j, 1j, -1j]$;
 $\mathbf{c}_2 = [-1, -1, -1, -1j, -1j, -1j, 1j, 1j, -1j]$;
20 $\mathbf{c}_3 = [-1, -1, -1, 1, 1, -1j, 1j, 1j, -1j]$;
 $\mathbf{c}_4 = [-1, -1, -1, 1, 1, 1, 1j, 1j, -1j]$;
 $\mathbf{c}_5 = [-1, -1, -1, 1, 1, 1, -1, 1j, -1j]$;
 $\mathbf{c}_6 = [-1, -1, -1, 1, 1, 1, -1, -1, -1j]$; and
 $\mathbf{c}_7 = [-1, -1, -1, 1, 1, 1, -1, -1, 1]$.

25 10. The method according to any one of claims 4 to 9, wherein $\mathbf{a}_0$ is one of first to 489th elements in the HE-LTF sequence, and $\mathbf{a}_1$ is one of 504th to 1001st elements in the HE-LTF sequence.

11. The method according to any one of claims 1 to 3, wherein the first sequence meets the following formula:

30 $\mathbf{p}_u = [\mathbf{b}_0, \mathbf{d}_u, 0,0,0,0,0, (-1j) * \mathbf{b}_1]$, wherein

the second sequence is the EHT-LTF sequence, $\mathbf{b}_0$ and $\mathbf{b}_1$ are subsequences in the EHT-LTF sequence, j is an imaginary unit, and u is an integer greater than or equal to 1 and less than or equal to 5;

$$\mathbf{d}_1 = [1j, 1j, 1j, -1j, 1j, 1j];$$

$$\begin{aligned} \mathbf{d}_2 &= [-1, 1j, 1j, -1j, 1j, 1j]; \\ \mathbf{d}_3 &= [-1, -1, -1, -1j, 1j, 1j]; \\ \mathbf{d}_4 &= [-1, -1, -1, 1, -1, 1j]; \text{ and} \\ \mathbf{d}_5 &= [-1, -1, -1, 1, -1, -1]. \end{aligned}$$

5 12. The method according to any one of claims 1 to 3, wherein the first sequence meets the following formula:

$$\mathbf{q}_6 = \frac{2}{\sqrt{5}} e^{\frac{j\pi}{4}} \mathbf{p}_{t1} + \frac{1}{\sqrt{5}} e^{\frac{j\pi}{4}} \mathbf{p}_{t2}, \text{ wherein}$$

10 $\mathbf{p}_{t1} = [\mathbf{b}_0, \mathbf{d}_{t1}, 0, 0, 0, 0, 0, (-1j) * \mathbf{b}_1]$; $\mathbf{p}_{t2} = [\mathbf{b}_0, \mathbf{d}_{t2}, 0, 0, 0, 0, 0, (-1j) * \mathbf{b}_1]$; and the second sequence is the EHT-LTF sequence, $\mathbf{b}_0$ and $\mathbf{b}_1$ are subsequences in the EHT-LTF sequence, and j is an imaginary unit, wherein

$t1$ is 5, and $t2$ is 1, 2, 3, 4, or 5; or

$t1$ is 1, and $t2$ is 5; or

$t1$ is 4, and $t2$ is 5;

$$\begin{aligned} \mathbf{d}_1 &= [1j, 1j, 1j, -1j, 1j, 1j]; \\ 15 \quad \mathbf{d}_2 &= [-1, 1j, 1j, -1j, 1j, 1j]; \\ \mathbf{d}_3 &= [-1, -1, -1, -1j, 1j, 1j]; \\ \mathbf{d}_4 &= [-1, -1, -1, 1, -1, 1j]; \text{ and} \\ \mathbf{d}_5 &= [-1, -1, -1, 1, -1, -1]. \end{aligned}$$

20 13. The method according to any one of claims 1 to 3, wherein the first sequence meets the following formula:

$$\mathbf{q}_7 = \frac{4}{\sqrt{21}} e^{\frac{j\pi}{4}} \mathbf{p}_{t3} + \frac{2}{\sqrt{21}} e^{\frac{j\pi}{4}} \mathbf{p}_{t4} + \frac{1}{\sqrt{21}} e^{\frac{j\pi}{4}} \mathbf{p}_{t5}, \text{ wherein}$$

25 $\mathbf{p}_{t3} = [\mathbf{b}_0, \mathbf{d}_{t3}, 0, 0, 0, 0, 0, (-1j) * \mathbf{b}_1]$; $\mathbf{p}_{t4} = [\mathbf{b}_0, \mathbf{d}_{t4}, 0, 0, 0, 0, 0, (-1j) * \mathbf{b}_1]$; $\mathbf{p}_{t5} = [\mathbf{b}_0, \mathbf{d}_{t5}, 0, 0, 0, 0, 0, (-1j) * \mathbf{b}_1]$; and the second sequence is the EHT-LTF sequence, $\mathbf{b}_0$ and $\mathbf{b}_1$ are subsequences in the EHT-LTF sequence, and j is an imaginary unit, wherein

30 $t3$ is 5, $t4$ is 5, and $t5$ is 1, 2, 3, 4, or 5; or

$t3$ is 5, $t4$ is 1, and $t5$ is 5; or

$t3$ is 5, $t4$ is 1, and $t5$ is 1;

$$\begin{aligned} \mathbf{d}_1 &= [1j, 1j, 1j, -1j, 1j, 1j]; \\ \mathbf{d}_2 &= [-1, 1j, 1j, -1j, 1j, 1j]; \\ 30 \quad \mathbf{d}_3 &= [-1, -1, -1, -1j, 1j, 1j]; \\ \mathbf{d}_4 &= [-1, -1, -1, 1, -1, 1j]; \text{ and} \\ \mathbf{d}_5 &= [-1, -1, -1, 1, -1, -1]. \end{aligned}$$

14. The method according to any one of claims 1 to 3, wherein the first sequence meets the

following formula:

$$\mathbf{q}_8 = \frac{8}{\sqrt{85}} e^{\frac{j\pi}{4}} \mathbf{p}_{t6} + \frac{4}{\sqrt{85}} e^{\frac{j\pi}{4}} \mathbf{p}_{t7} + \frac{2}{\sqrt{85}} e^{\frac{j\pi}{4}} \mathbf{p}_{t8} + \frac{1}{\sqrt{85}} e^{\frac{j\pi}{4}} \mathbf{p}_{t9}, \text{ wherein}$$

$\mathbf{p}_{t6} = [\mathbf{b}_0, \mathbf{d}_{t6}, 0, 0, 0, 0, 0, (-1j) * \mathbf{b}_1]$; $\mathbf{p}_{t7} = [\mathbf{b}_0, \mathbf{d}_{t7}, 0, 0, 0, 0, 0, (-1j) * \mathbf{b}_1]$; $\mathbf{p}_{t8} = [\mathbf{b}_0, \mathbf{d}_{t8}, 0, 0, 0, 0, 0, (-1j) * \mathbf{b}_1]$; $\mathbf{p}_{t9} = [\mathbf{b}_0, \mathbf{d}_{t9}, 0, 0, 0, 0, 0, (-1j) * \mathbf{b}_1]$; and the second sequence is the EHT-LTF sequence, $\mathbf{b}_0$ and $\mathbf{b}_1$ are subsequences in the EHT-LTF sequence, and j is an imaginary unit, wherein

$t6$ is 5, $t7$ is 5, and $t8$ is 5, and $t9$ is 1, 2, 3, or 4; or

$t6$ is 5, $t7$ is 5, $t8$ is 1, and $t9$ is 1, 4 or 5; or

$t6$ is 5, $t7$ is 1, $t8$ is 5, and $t9$ is 5;

$$\mathbf{d}_1 = [1j, 1j, 1j, -1j, 1j, 1j];$$

$$\mathbf{d}_2 = [-1, 1j, 1j, -1j, 1j, 1j];$$

$$\mathbf{d}_3 = [-1, -1, -1, -1j, 1j, 1j];$$

$$\mathbf{d}_4 = [-1, -1, -1, 1, -1, 1j]; \text{ and}$$

$$\mathbf{d}_5 = [-1, -1, -1, 1, -1, -1].$$

15. The method according to any one of claims 1 to 3, wherein the first sequence meets the following formula:

$$\mathbf{q}_9 = \frac{16}{\sqrt{341}} e^{\frac{j\pi}{4}} \mathbf{p}_{t10} + \frac{8}{\sqrt{341}} e^{\frac{j\pi}{4}} \mathbf{p}_{t11} + \frac{4}{\sqrt{341}} e^{\frac{j\pi}{4}} \mathbf{p}_{t12} + \frac{2}{\sqrt{341}} e^{\frac{j\pi}{4}} \mathbf{p}_{t13} + \frac{1}{\sqrt{341}} e^{\frac{j\pi}{4}} \mathbf{p}_{t14}, \text{ wherein}$$

$\mathbf{p}_{t10} = [\mathbf{b}_0, \mathbf{d}_{t10}, 0, 0, 0, 0, 0, (-1j) * \mathbf{b}_1]$; $\mathbf{p}_{t11} = [\mathbf{b}_0, \mathbf{d}_{t11}, 0, 0, 0, 0, 0, (-1j) * \mathbf{b}_1]$; $\mathbf{p}_{t12} = [\mathbf{b}_0, \mathbf{d}_{t12}, 0, 0, 0, 0, 0, (-1j) * \mathbf{b}_1]$; $\mathbf{p}_{t13} = [\mathbf{b}_0, \mathbf{d}_{t13}, 0, 0, 0, 0, 0, (-1j) * \mathbf{b}_1]$; $\mathbf{p}_{t14} = [\mathbf{b}_0, \mathbf{d}_{t14}, 0, 0, 0, 0, 0, (-1j) * \mathbf{b}_1]$; and the second sequence is the EHT-LTF sequence, $\mathbf{b}_0$ and $\mathbf{b}_1$ are subsequences in the EHT-LTF sequence, and j is an imaginary unit, wherein

$t10$ is 5, $t11$ is 5, $t12$ is 5, $t13$ is 1, and $t14$ is 2 or 4; or

$t10$ is 5, $t11$ is 5, $t12$ is 5, $t13$ is 4, and $t14$ is 1 or 5; or

$t10$ is 5, $t11$ is 5, $t12$ is 1, $t13$ is 5, and $t14$ is 1 or 5; or

$t10$ is 5, $t11$ is 5, $t12$ is 1, $t13$ is 5, and $t14$ is 5; or

$t10$ is 5, $t11$ is 5, $t12$ is 5, $t13$ is 2, and $t14$ is 5; or

$t10$ is 5, $t11$ is 5, $t12$ is 5, $t13$ is 1, and $t14$ is 3;

$$\mathbf{d}_1 = [1j, 1j, 1j, -1j, 1j, 1j];$$

$$\mathbf{d}_2 = [-1, 1j, 1j, -1j, 1j, 1j];$$

$$\mathbf{d}_3 = [-1, -1, -1, -1j, 1j, 1j];$$

$$\mathbf{d}_4 = [-1, -1, -1, 1, -1, 1j]; \text{ and}$$

$$\mathbf{d}_5 = [-1, -1, -1, 1, -1, -1].$$

16. The method according to any one of claims 1 to 3, wherein the first sequence meets the

following formula:

$$\mathbf{q}_{10} = \frac{16}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{p}_{t15} + \frac{16}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{p}_{t16} + \frac{8}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{p}_{t17} + \frac{4}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{p}_{t18} + \frac{2}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{p}_{t19} + \frac{1}{\sqrt{1365}} e^{\frac{j\pi}{4}} \mathbf{p}_{t20}, \text{ wherein}$$

5 $\mathbf{p}_{t15} = [\mathbf{b}_0, \mathbf{d}_{t15}, 0,0,0,0,0, (-1j) * \mathbf{b}_1]; \mathbf{p}_{t16} = [\mathbf{b}_0, \mathbf{d}_{t16}, 0,0,0,0,0, (-1j) * \mathbf{b}_1]; \mathbf{p}_{t17} = [\mathbf{b}_0, \mathbf{d}_{t17}, 0,0,0,0,0, (-1j) * \mathbf{b}_1]; \mathbf{p}_{t18} = [\mathbf{b}_0, \mathbf{d}_{t18}, 0,0,0,0,0, (-1j) * \mathbf{b}_1]; \mathbf{p}_{t19} = [\mathbf{b}_0, \mathbf{d}_{t19}, 0,0,0,0,0, (-1j) * \mathbf{b}_1]; \mathbf{p}_{t20} = [\mathbf{b}_0, \mathbf{d}_{t20}, 0,0,0,0,0, (-1j) * \mathbf{b}_1];$ and the second sequence is the EHT-LTF sequence, $\mathbf{b}_0$ and $\mathbf{b}_1$ are subsequences in the EHT-LTF sequence, and j is an imaginary unit, wherein

10 t_{15} is 5, t_{16} is 5, t_{17} is 5, t_{18} is 1, t_{19} is 2, and t_{20} is 5; or
 t_{15} is 5, t_{16} is 5, t_{17} is 5, t_{18} is 1, t_{19} is 1, and t_{20} is 3; or
 t_{15} is 5, t_{16} is 5, t_{17} is 1, t_{18} is 5, t_{19} is 5, and t_{20} is 1; or
 t_{15} is 5, t_{16} is 5, t_{17} is 5, t_{18} is 5, t_{19} is 3, and t_{20} is 3; or
 t_{15} is 5, t_{16} is 5, t_{17} is 5, t_{18} is 1, t_{19} is 1, and t_{20} is 2; or
 t_{15} is 5, t_{16} is 5, t_{17} is 5, t_{18} is 1, t_{19} is 4, and t_{20} is 1; or
15 t_{15} is 5, t_{16} is 5, t_{17} is 5, t_{18} is 4, t_{19} is 5, and t_{20} is 1; or
 t_{15} is 5, t_{16} is 5, t_{17} is 5, t_{18} is 1, t_{19} is 4, and t_{20} is 5;

$\mathbf{d}_1 = [1j, 1j, 1j, -1j, 1j, 1j];$
 $\mathbf{d}_2 = [-1, 1j, 1j, -1j, 1j, 1j];$
 $\mathbf{d}_3 = [-1, -1, -1, -1j, 1j, 1j];$
20 $\mathbf{d}_4 = [-1, -1, -1, 1, -1, 1j];$ and
 $\mathbf{d}_5 = [-1, -1, -1, 1, -1, -1].$

17. The method according to any one of claims 11 to 16, wherein $\mathbf{b}_0$ is one of first to 492nd elements in the EHT-LTF sequence, and $\mathbf{b}_1$ is one of 504th to 1001st elements in the EHT-LTF sequence.

25 18. A communication apparatus, comprising a processing module and a transceiver module, wherein

the processing module is configured to generate a sounding frame, wherein the sounding frame comprises a first field, the first field comprises a predefined first sequence, the first sequence comprises a sequence obtained after a second sequence is modulated by using at least one of the
30 following modulation modes, and the modulation modes comprise: quadrature phase shift keying QPSK, 16-quadrature amplitude modulation 16-QAM, 64-QAM, 256-QAM, 1024-QAM, and 4096-QAM; and

the transceiver module is configured to send the sounding frame.

19. A communication apparatus, comprising a processing module and a transceiver module,

wherein

the transceiver module is configured to receive a sounding frame, wherein the sounding frame comprises a first field, the first field comprises a predefined first sequence, the first sequence comprises a sequence obtained after a second sequence is modulated by using at least one of the following modulation modes, and the modulation modes comprise: quadrature phase shift keying QPSK, 16-quadrature amplitude modulation 16-QAM, 64-QAM, 256-QAM, 1024-QAM, and 4096-QAM; and

the processing module is configured to perform channel measurement based on the first sequence.

20. A chip, wherein the chip comprises at least one logic circuit and an input/output interface, the logic circuit is configured to read and execute stored instructions, and when the instructions are run, the chip is enabled to perform the method according to any one of claims 1 to 17.

21. A computer-readable storage medium, wherein the computer-readable storage medium stores a computer program, the computer program comprises program instructions, and when the program instructions are executed by a computer, the computer is enabled to perform the method according to any one of claims 1 to 17.